ACOS 6.0.7

SNMP MIB Reference

March, 2025

© 2025 A10 Networks, Inc.CONFIDENTIAL AND PROPRIETARY- ALL RIGHTS RESERVED.

Information in this document is subject to change without notice.

PATENT PROTECTION

A10 Networks, Inc. products are protected by patents in the U.S. and elsewhere. The following website is provided to satisfy the virtual patent marking provisions of various jurisdictions including the virtual patent marking provisions of the America Invents Act. A10 Networks, Inc. products, including all Thunder Series products, are protected by one or more of U.S. patents and patents pending listed at:

a10-virtual-patent-marking.

TRADEMARKS

A10 Networks, Inc. trademarks are listed at: a10-trademarks

CONFIDENTIALITY

This document contains confidential materials proprietary to A10 Networks, Inc.. This document and information and ideas herein may not be disclosed, copied, reproduced or distributed to anyone outside A10 Networks, Inc. without prior written consent of A10 Networks, Inc..

DISCLAIMER

This document does not create any express or implied warranty about A10 Networks, Inc. or about its products or services, including but not limited to fitness for a particular use and non-infringement. A10 Networks, Inc. has made reasonable efforts to verify that the information contained herein is accurate, but A10 Networks, Inc. assumes no responsibility for its use. All information is provided "as-is." The product specifications and features described in this publication are based on the latest information available; however, specifications are subject to change without notice, and certain features may not be available upon initial product release. Contact A10 Networks, Inc. for current information regarding its products or services. A10 Networks, Inc. products and services are subject to A10 Networks, Inc. standard terms and conditions.

ENVIRONMENTAL CONSIDERATIONS

Some electronic components may possibly contain dangerous substances. For information on specific component types, please contact the manufacturer of that component. Always consult local authorities for regulations regarding proper disposal of electronic components in your area.

FURTHER INFORMATION

For additional information about A10 products, terms and conditions of delivery, and pricing, contact your nearest A10 Networks, Inc. location, which can be found by visiting www.a10networks.com.

Table of Contents

Introduction **5**

SNMP Versions 6

SNMP MIB Information **7**

Downloading the MIBs 7

AX MIB Groups 7

MIB Access 8

SNMP RFCs Support 8

ifIndex Table Support 12

Partition-aware SNMP Configuration **13**

Prerequisites 13

Limitations 13

Multi-PU Platform Support **15**

CLI Configuration 15

Limitation 15

SNMP Views and Community Strings **16**

SNMP Views 16

GUI Configuration 16

CLI Configuration 17

SNMP Community Strings 17

GUI Configuration 17

CLI Configuration 18

SNMP Groups **21**

GUI Configuration 21

CLI Configuration 21

Authentication and Encryption for SNMPv3 Users **22**

GUI Configuration 22

CLI Configuration 23

SNMP Traps **24**
GUI Configuration for Enabling SNMP Traps 24
CLI Configuration for Enabling SNMP Traps 25
CLI Configuration for Disabling the SNMP Traps for L3V Partitions 27
SNMP Configuration **28**
GUI Configuration 28
CLI Configuration 29
Source Interface for SNMP Notifications **31**
GUI Configuration 31
CLI Configuration 32
List of MIB Objects **33**

Introduction

Simple Network Management Protocol or SNMP is a commonly used protocol for managing and monitoring network devices. It provides a standard way to collect network information, set configurations, and receive alerts about network devices. Thus, SNMP helps to maintain network reliability and performance.

SNMP has multiple versions such as SNMPv1, SNMPv2c, and SNMPv3. SNMPv3 is a more preferred protocol as it offers improved security features compared to earlier versions.

SNMP supports single as well as multi-PU platforms.

The main components of SNMP are as follows:

- Managed devices
  These are the network nodes such as routers, switches, servers, printers, and so on that are to be monitored.
- SNMP Agents
  SNMP agent is a process that runs on a managed device to collect, store, and make the managed device's configuration available to the SNMP Manager.
  - SNMP Subagent extends the functionality of SNMP agent. It allows to define custom MIB variables and register them with the SNMP agent.
  - SNMP Schema agent provides the SNMP manager with data from individual PU or aggregated data from multiple PU. Multiple SNMP MIB tables are generated for stats data and oper data of a configuration management object. Each SNMP table contains a default index, `slotId`, for identifying blades in a multi-PU platform:
    - slotId 0: Aggregation of all blades
    - slotId 1: Data from PU1/Standalone platform
    - slotId 2: Data from PU2
- SNMP Manager
  SNMP manager makes a request to the SNMP agent to receive data and configure the managed devices.

- Management Information Base (MIB)
  MIB defines the structure and organization of data that can be accessed using SNMP. It acts as a database of available information for SNMP managers.

SNMP Versions

ACOS Devices support the following SNMP versions: v1, v2c, v3. SNMP is disabled by default.

You can configure an ACOS Device to send the SNMP traps to the Syslog and to the external trap receivers. You also can configure read (GET) access to SNMP Management Information Base (MIB) objects on the ACOS Device by external SNMP managers. .

NOTE: SNMP access to the ACOS Device is read-only. SET operations (write access) are not supported.

The following list of items clarifies the current implementation of SNMP:

- Limit the number of SNMP polling requests to two or three instances. Several concurrent “snmpwalk” requests, will result in delays, unfinished requests, time out, or error messages.
- Certain SNMP objects, such as the “CPU Per Partition” value, might not work in the current release.
- As the ACOS Device generates the SNMP community string for private partitions, you are not allowed to configure or change the community string.
- The SNMP process may consume 100% of the Control CPU cycles.

SNMP MIB Information

The following topics are covered:

Downloading the MIBs 7

AX MIB Groups 7

MIB Access 8

SNMP RFCs Support 8

ifIndex Table Support 12

Downloading the MIBs

The MIB files are available for download through the ACOS GUI:

1. Hover over **System** on the menu bar and select **Monitoring**.
2. Click on the **SNMP** tab and select **SNMP MIB Download** from the drop-down menu.
3. Select a target location for the MIB archive file and click **Save**.

AX MIB Groups

The AX MIB Groups classify the MIB structure and provide a way to organize or manage related information for network devices. The AX MIB consists of the following groups:

Table 1 : AX MIB Groups

Group	Description
axSystem	Provides system-level information about the ACOS Device, such as the installed software versions, the serial number, and current CPU utilization.
axLogging	Provides configuration information about system logging.
axApp	Provides configuration and operational information for ACOS

Table 1 : AX MIB Groups

Group	Description
	Device features.
`axChassis`	Provides configuration information about multiple processing units (PUs).
`acosSchema`	Provides stats and oper tables of configuration management objects.
`acosRootStats`	Deprecated.
`acosRootOper`	Deprecated.

MIB Access

SNMP access to the ACOS Device is read-only. SNMP managers can retrieve information using GET or GET NEXT requests. SET requests are not supported.

SNMP RFCs Support

ACOS Device supports the SNMP-related RFCs described as follows:

Table 2 : Supported SNMP-related RFCs

RFC	Description and Notes
RFC 1155	Structure and Identification of Management Information for TCP/IP-based Networks.
RFC 1157	A Simple Network Management Protocol (SNMP).
RFC 1212	Concise MIB Definitions: the MIB SET operation is not supported.
RFC 1213	Management Information Base for Network Management of TCP/IP-based Networks: MIB-II. The following system objects are supported: • sysDescr • sysObjectID

Table 2 : Supported SNMP-related RFCs

RFC	Description and Notes
	• sysUpTime • sysContact • sysName • sysLocation • sysServices The sysService object returns a value that indicates the set of services the ACOS Device offers. For the ACOS Device, the sysService object always returns the value 76. This value indicates that the ACOS Device offers the following services (for information about how this value is calculated, refer to the RFC): • datalink/subnetwork – 0x2 • internet – 0x4 • end-to-end – 0x8 • applications – 0x40 The following interfaces on MIB-II are supported: • ifNumber • ifTable The ipAddrTable on MIB-II are also supported.
RFC 1215	A convention for defining traps for use with the SNMP.
RFC 1850	OSPF Version 2 Management Information Base.
RFC 1901	Introduction to Community-based SNMPv2.
RFC 2233	The Interfaces Group MIB using SMIv2. The ifXTable table is supported.
RFC 2465	Management Information Base for IP Version 6: Textual Conventions and General Group. The ipv6AddrTable on MIB-II is supported.

Table 2 : Supported SNMP-related RFCs

RFC	Description and Notes
RFC 2576	Coexistence between Version 1, Version 2, and Version 3 of the Internet-standard Network Management Framework.
RFC 2578	Structure of Management Information Version 2 (SMIv2).
RFC 2790	Host Resources MIB. The following subtrees are supported: • hrSystem: .1.3.6.1.2.1.25.1 • hrStorage: .1.3.6.1.2.1.25.2 • hrDeviceTable: .1.3.6.1.2.1.25.3.2 • hrProcessorTable: .1.3.6.1.2.1.25.3.3
RFC 2863	The Interfaces Group MIB. The following table is supported: • ifXTable: .1.3.6.1.2.1.31.1.1
RFC 3418	Physical Topology MIB. The following objects are supported: • lldpV2PortConfigTable • lldpV2DestAddrTable • lldpV2LocPortTable • lldpV2LocManAddrTable • lldpV2RemTable • lldpV2RemManAddrTable • lldpV2LocChassisIdSubtype • lldpV2LocChassisId • lldpV2LocSysName • lldpV2LocSysDesc • lldpV2LocSysCapSupported • lldpV2LocSysCapEnabled
RFC 3410	Introduction and Applicability Statements for Internet Standard Management Framework.
RFC 3411	An Architecture for Describing Simple Network Management

Table 2 : Supported SNMP-related RFCs

RFC	Description and Notes
	Protocol (SNMP) Management Frameworks.
RFC 3412	Message Processing and Dispatching for the Simple Network Management Protocol (SNMP).
RFC 3413	Simple Network Management Protocol (SNMP) Applications.
RFC 3414	User-based Security Model (USM) for version 3 of the Simple Network Management Protocol (SNMPv3).
RFC 3415	View-based Access Control Model (VACM) for the Simple Network Management Protocol (SNMP).
RFC 3416	Version 2 of Protocol Operations for the SNMP.
RFC 3418	MIB for the SNMP.
RFC 3635	Definitions of Managed Objects for the Ethernet-like Interface Types.
RFC 4001	Textual Conventions for Internet Network Addresses. The following values for IP address types are supported: • 0 - Unknown • 1 - IPv4 • 2 - IPv6
RFC 4273	Definitions of Managed Objects for BGP-4. The following traps are supported: • bgpEstablishedNotification • bgpBackwardTransNotification
RFC 4293	Management Information Base for the Internet Protocol. The following tables are supported: • Ipv4InterfaceTable • Ipv6InterfaceTable • IpAddrTable • Ipv6AddrTable

ifIndex Table Support

The `ifInUnknownProtos` and `ifOutLen` objects in the `ifIndex` table are not implemented on AX interfaces and always return value 0. Likewise, the `ifSpecific` object is not present and always returns “0.0”.

Partition-aware SNMP Configuration

SNMP can be configured on private partitions. The SNMP configurations only apply to the partition being configured and these configuration are partition-aware.

When SNMP is disabled in the shared partition, no configuration change is required in any L3V partition. From the shared partition, the ACOS Device will not get SNMP responses nor see any L3V traps.

You can get SNMP response and traps of a L3V partition through shared VLAN interfaces. Traps in the L3V partition uses different community strings.

To enable L3V partition traps, SNMP service and community string on L3V partition must be configured. The enabling/disabling of traps in L3V partition can only be done on the group level, and not on individual trap level.

Since the community string on the L3V partition is configured and encrypted, there is no auto-generated community string on the L3V partition.

The following topics are covered:

Prerequisites 13

Limitations 13

Prerequisites

- SNMP must be enabled in the L3V partition.
- SNMP service and community string on the L3V partition must be configured.

Limitations

- SNMP traps will be only snmp-v2 traps.
- SNMP configuration of GSLB group traps is not supported on L3V partitions.

- The SNMPv2 and SNMPv3 get requests with or without communityString@partition_name are supported on L3V partitions. However, if the partition name is not provided, the snmpget request returns:
  - Data from the shared partition only for OIDs under axChassis
  - Data from all partitions for all other OIDs.

Multi-PU Platform Support

SNMP supports MIB OIDs and tables for multi-PU platforms. A schema agent is used to provide the SNMP manager with data from individual PU or aggregated data from multiple PUs. For multi-PU platform support, enable the schema agent on ACOS.

The following topics are covered:

CLI Configuration 15

Limitation 15

CLI Configuration

To allow SNMP monitoring for multi-PU platform, enable the new CM subagent:

```
ACOS(config)#snmp-server enable schema-agent
```

Limitation

- The SNMP tables do not include an index for L3V partitions. To request data for an L3V partition, attach the partition name to the community string (e.g., public@p1) in the SNMP request. The response for the request will contain data specific to the requested L3V partition.

SNMP Views and Community Strings

You can allow external SNMP managers to access the values of MIB objects from the ACOS Device. To allow remote read-only access to the ACOS MIB objects, configure one or both of the following types of access:

- SNMP Views
- SNMP Community Strings

SNMP Views

An SNMP view is like a filter that permits or denies access to a specific OID or portions of an OID. You can configure SNMP user groups and individual SNMP users, and allow or disallow them to read specific portions of the ACOS MIBs using different views.

When you configure an SNMP user group or user, you specify the SNMP version. SNMP v1 and SNMP v2c do not support authentication or encryption of the SNMP packets, while SNMPv3 does. You can enable authentication, encryption, or both, on an individual SNMP user-group when you configure the groups. You can specify the authentication method and the password for individual SNMP users when you configure the users.

The following topics are covered:

GUI Configuration 16
CLI Configuration 17

GUI Configuration

To configure an SNMP view using the GUI:

1. Hover over **System** in the menu bar and select **Monitoring**.
2. Select **SNMP** and select **SNMP Views** from the drop-down menu.

3. Click **Create**.
4. Enter a name for the view in the Viewname field.
5. Enter the MIB view family name or OID in the Oid field and then specify whether this OID should be included or excluded in the view.
6. Click **Create**.

CLI Configuration

Use the **snmp-server view** command to configure an SNMP view from the CLI. The following example creates a view called “exampleview” that includes OID 1.2.3:

```
ACOS(config)# snmp-server view exampleview 1.2.3 included
```

SNMP Community Strings

An SNMP community string is a string that an SNMP manager can present to the ACOS Device when requesting MIB values.

Community strings are similar like passwords. You can minimize security risk by applying the same principles for selecting a community name as you would do for selecting a password. Use a hard-to-guess string and avoid use of commonly used community names such as “public” or “private”.

You also can restrict access to specific Object IDs (OIDs) within the MIB, on an individual community basis. OIDs indicate the position of a set of MIB objects in the global MIB tree. The OID for A10 Networks, Inc. Thunder Series objects is 1.3.6.1.4.1.22610.

The following topics are covered:

GUI Configuration 17
CLI Configuration 18

GUI Configuration

To configure an SNMP community string using the GUI:

1. Hover over **System** and select **Monitoring**.
2. Select the **SNMP** tab and then select **SNMP** from the drop-down menu.
3. Enter the community string in the Community Read field and click **Add**.
4. Click **Configure SNMP**.

CLI Configuration

This section contains the following examples:

- CLI Example—Configuring a Community String for SNMPv1 or SNMPv2c Users
- CLI Example—Configuring a Community String for SNMPv3 Users
- CLI Example—Restricting Access to Specific Remote Hosts
- CLI Example—Restricting Access to Specific OIDs

CLI Example—Configuring a Community String for SNMPv1 or SNMPv2c Users

The following example shows how to configure an SNMP community string using the CLI for SNMPv1 or SNMPv2c users:

```
ACOS(config)# snmp-server SNMPv1-v2c user u1
ACOS(config-user:u1)# community read examplestring
ACOS(config-user:u1)# show running-config | sec snmp
snmp-server enable service
snmp-server enable traps all
snmp-server SNMPv1-v2c user u1
  community read encrypted
mGXzd9xrcGiMBaDQuY/jnDwQjLjV2wDnPBCMuNXbAOc8EIy41dsA5zwQjLjV2wDn
snmp-server host 10.6.7.22 version v2c public
```

NOTE: The community string is encrypted in the **`show running-config`** output for security purposes. Each SNMP v1-v2c user has a community string. You can change the value of this string by using the **`community read`** command and enterg a new community string.

The username **`u1`** is a system-specific name and cannot be used to retrieve any SNMP data. Instead, the encrypted community string configured under this user should be

used to retrieve data. This community string can also be used by any remote host to access the ACOS Device, assuming there are no access restrictions configured.

CLI Example—Configuring a Community String for SNMPv3 Users

The following example shows how to configure an SNMP community string for SNMPv3 users. An SNMP view and group must be configured prior to configuring the SNMPv3 user.

```
ACOS(config)# snmp-server view exampleview 1.2.3 included
ACOS(config)# snmp-server group examplegroup v3 auth read exampleview
ACOS(config)# snmp-server SNMPv3 user exampleuser group examplegroup v3
auth md5 examplepassword1 priv aes examplepassword2
ACOS(config)# show running-config | sec snmp
snmp-server enable service
snmp-server enable traps all
snmp-server view exampleview 1.2.3 included
snmp-server group examplegroup v3 auth read exampleview
snmp-server SNMPv3 user exampleuser group examplegroup v3 auth md5
encrypted IrrqRoL9DI2HGP3wipS0lDwQjLjV2wDnPBCMuNXbAOc8EIy41dsA5zwQjLjV2wDn
priv aes encrypted
6D2AC0vBjbGHGP3wipS0lLD/mjXR6wFMPBCMuNXbAOc8EIy41dsA5zwQjLjV2wDn
snmp-server host 10.6.7.22 version v2c public
```

CLI Example—Restricting Access to Specific Remote Hosts

The following example shows how to restrict access to allow only specific remote hosts to access SNMP data. From the SNMP v1-v2c user configuration level, specify which remote hosts are allowed to access the ACOS Device using the community string:

```
ACOS(config-user:u1)# remote 192.168.20.1 /24
ACOS(config-user:u1)# remote 192.168.30.1 /24
```

CLI Example—Restricting Access to Specific OIDs

The following example shows how to restrict access so that only a specific OID (1.2.3) can be accessed by the specified hosts (subnets 192.168.30.x and 192.168.40.x). From the SNMPv1-v2c user configuration level:

```
ACOS(config-user:u1)# oid 1.2.3
```

```
ACOS(config-user:u1-oid:1.2.3)# remote 192.168.40.1 255.255.255.0
ACOS(config-user:u1-oid:1.2.3)# remote 192.168.50.1 255.255.255.0
```

SNMP Groups

SNMP users can be organized into groups, which can be configured to allow or disallow users access to read specific SNMP views.

The following topics are covered:

GUI Configuration 21

CLI Configuration 21

GUI Configuration

To configure an SNMP group using the GUI:

1. Hover over **System** in the menu bar and select **Monitoring**.
2. Select **SNMP** and select **SNMP Groups** from the drop-down menu.
3. Click **Create**.
4. Enter a name for the group in the Groupname field.
5. Select the desired SNMPv3 packet authentication level.
6. Select a read-only view for accessing MIB objects.
7. Click **Create**.

CLI Configuration

Use the **`snmp-server group`** command to configure an SNMP group from the CLI. The following example creates a group called “examplegroup”:

```
ACOS(config)# snmp-server group examplegroup v3 priv read exampleview
```

Authentication and Encryption for SNMPv3 Users

Advanced Encryption Standard (AES) or Data Encryption Standard (DES) encryption can be added at the SNMP “user” level. This feature extends overall security with support for SNMPv3 notifications (traps). SNMPv3 traps are authenticated and encrypted, using the same options already supported for SNMPv3 in previous releases.

- Authentication is performed by using authentication key of a user to sign the message being sent. This can be done using either MD5 or SHA authentication. The authentication key is generated using the specified authentication method and the specified password. The key size for SHA is typically 512, 384, 256, or 224 bits.
- Encryption is performed by using the privacy key of a user to encrypt the data portion of the message being sent. This can be done using either AES or DES encryption. The privacy key is generated using the specified encryption method and the specified password. The AES method uses a fixed block size of 128 bits and a key size of 128, 192, or 256 bits.

NOTE: After changing the encryption for an SNMP user, SNMP must be restarted to reload the configuration. This process takes some time before the SNMP service becomes available.

The following topics are covered:

GUI Configuration 22
CLI Configuration 23

GUI Configuration

To configure authentication and encryption for SNMPv3 users from the GUI:

1. Go to **System > Monitoring**, under **SNMP** tab, select **SNMP Users**.
2. Click **Create** to create a new user and enter the appropriate information.

3. Click **Create** to save the configuration.

CLI Configuration

To configure the SNMPv3 user authentication and encryption, use the following command:

```
ACOS(config)# snmp-server enable service
ACOS(config)# snmp-server view exampleview 1.2.3 included
ACOS(config)# snmp-server group examplegroup v3 auth read exampleview
ACOS(config)# snmp-server SNMPv3 user exampleuser group examplegroup v3
auth sha-512
ACOS(config)# snmp-server SNMPv3 user exampleuser group examplegroup v3
auth sha-512 examplepassword1 priv aes-192 examplepassword2
```

In this example, **exampleuser** is an SNMPv3 user, who is a member in **examplegroup**, which is part of **exampleview**. The `auth sha-512 examplepassword1` portion of the command generates a user key using SHA-512 authentications and an **examplepassword1** string. The `priv aes-192 examplepassword2` portion of the command encrypts the message using a key with AES-192 encryption and an **examplepassword2** string.

SNMP Traps

To start receiving SNMP traps, you must enable the SNMP traps on a configured SNMP server. You can enable any of the individual traps, or a category of new SNMP traps. Follow the steps below to enable the SNMP traps. All traps are disabled by default.

For more information about the SNMP CLI commands used for enabling SNMP traps, along with a list of available traps, see the *Command Line Interface Reference*.

For information about configuring the SNMP traps on L3V partitions, see the *Configuring Application Delivery Partitions* guide.

Take note of the following:

- To begin receiving the **`ssl-cert-expire`** SNMP traps, you must enable email notification of SSL certificate expiration. To do so, use the **`logging email-address`** command from the global configuration level in the CLI. For more information, refer to the *Command Line Interface Reference*.
- To begin receiving the **`resource-usage-warning`** SNMP traps, you must set resource utilization thresholds for partitions.
- If you have a DNS anycast configuration, all ports of a given virtual server must to be down before an SNMP trap is sent.

NOTE: Enabling/disabling of traps in the L3V partition can only be done on the group level, and not on an individual trap level.

The following topics are covered:

GUI Configuration for Enabling SNMP Traps 24

CLI Configuration for Enabling SNMP Traps 25

CLI Configuration for Disabling the SNMP Traps for L3V Partitions 27

GUI Configuration for Enabling SNMP Traps

To enable the SNMP traps:

1. Hover over **System** in the navigation bar and select **Monitoring**.
2. Click **SNMP** on the menu bar and select **SNMP** from the drop-down menu that appears.
3. Click **Trap List** to display the traps you can add, sorted by category.
4. Select the checkbox next to any SNMP traps you want to enable.
5. Click **Configure SNMP** to save your changes.

CLI Configuration for Enabling SNMP Traps

The **`snmp-server enable traps`** command allows you to enable the SNMP traps. The following traps are available on the shared partition:

- all
- gslb
- lldp
- lsn
- network
- routing
- scaleout
- slb
- slb-change
- snmp
- system
- vcs
- vrrp-a

NOTE: On the L3V partition, only the all, snmp, gslb, slb, slb-change, and vrrp-a traps are available. For details on these traps, see the *Command Line Interface Reference*.

The following CLI command enables the SNMP traps for all SLB events. Note that using the ? allows you to see all the SNMP traps within the category before activating that category.

```
ACOS(config)# snmp-server enable traps slb ?
  all                          Enable all SLB traps
  application-buffer-limit     Enable application buffer reach limit trap
  bw-rate-limit-exceed         Enable SLB server/port bandwidth rate limit
exceed
                               trap
  bw-rate-limit-resume         Enable SLB server/port bandwidth rate limit
resume
                               trap
  server-conn-limit            Enable SLB server connection limit trap
  server-conn-resume           Enable SLB server connection resume trap
  server-disabled              Enable SLB server-disabled trap
  server-down                  Enable SLB server-down trap
  server-selection-failure     Enable SLB server selection failure trap
  server-up                    Enable slb server up trap
  service-conn-limit           Enable SLB service connection limit trap
  service-conn-resume          Enable SLB service connection resume trap
  service-down                 Enable SLB service-down trap
  service-group-down           Enable SLB service-group-down trap
  service-group-member-down    Enable SLB service-group-member-down trap
  service-group-member-up      Enable SLB service-group-member-up trap
  service-group-up             Enable SLB service-group-up trap
  service-up                   Enable SLB service-up trap
  vip-connlimit                Enable the virtual server reach conn-limit
trap
  vip-connratelimit            Enable the virtual server reach conn-rate-
limit
                               trap
  vip-down                     Enable SLB virtual server down trap
  vip-port-connlimit           Enable the virtual port reach conn-limit trap
  vip-port-connratelimit       Enable the virtual port reach conn-rate-limit
trap
  vip-port-down                Enable SLB virtual port down trap
  vip-port-up                  Enable SLB virtual port up trap
  vip-up                       Enable SLB virtual server up trap
```

The following CLI command enables the SNMP traps for all SLB changes. An SNMP trap will be sent whenever a change has been made to the SLB configuration. This includes the creation or deletion of virtual or real servers or ports, and changes to or near expiration of SSL certificates.

```
ACOS(config)# snmp-server enable traps slb-change
```

The following CLI commands enable the SNMP traps for the creation or removal of virtual and real servers and ports.

```
ACOS(config)# snmp-server enable traps slb-change server
ACOS(config)# snmp-server enable traps slb-change server-port
ACOS(config)# snmp-server enable traps slb-change vip
ACOS(config)# snmp-server enable traps slb-change vip-port
```

CLI Configuration for Disabling the SNMP Traps for L3V Partitions

ACOS allows you to enable the SNMP traps on shared partitions. The ACOS Device can disable traps on L3V partitions while the SNMP traps are still enabled on shared partitions. The default behavior is for both shared and L3V partition traps to be sent out when the SNMP traps are enabled on shared partitions.

When SNMP is disabled in the shared partition, no configuration change is required in any L3V partition. From the shared partition, the ACOS Device will not send any SNMP responses nor traps once SNMP is disabled.

NOTE: GSLB group traps are not partition-aware, so they cannot be controlled using the **snmp-server disable traps gslb** command.

To disable the SNMP traps on L3V partitions, use the CLI and make sure that you are in the configuration level for an L3V partition.

The following command helps to switch to the private partition named “pl3v,” and then disables the network and LLDP traps on this partition:

```
ACOS(config)# active-partition pl3v
ACOS[pl3v](config)# snmp-server disable traps network
ACOS[pl3v](config)# snmp-server disable traps LLDP
```

SNMP Configuration

By default, SNMP service is disabled for all data interfaces. See “Default Management Access Settings” in the *Management Access and Security Guide* for more information.

To configure SNMP:

1. If desired, configure location and contact information.
2. If desired, configure external SNMP trap receivers.
3. If desired, configure SNMPv1/v2c.
4. If desired, configure views, groups, and users.
5. Enable the SNMP agent and the SNMP traps.
6. Save the configuration changes.

You are not required to perform these configuration tasks in this order precisely. The workflow in the GUI may be slightly different from the workflow shown here.

The following topics are covered:

GUI Configuration 28
CLI Configuration 29

GUI Configuration

To configure the basic SNMP parameters:

1. Hover over **System** in the navigation bar, and select **Monitoring**.
2. Click **SNMP** on the menu bar and, then select **SNMP** from the drop-down list.
3. Configure general SNMP settings, including the system information, Engine ID, and trap host, in the General Fields section. Refer to the GUI online help for detailed information about each field.

4. Configure the SNMP trap settings by clicking and expanding the Trap List section and then select the traps that you want to monitor.
5. Click **Create SNMP Server**.

CLI Configuration

All SNMP configuration commands are available at the global configuration level of the CLI.

1. To configure SNMPv1/v2c, use the following command:

```
ACOS(config)# snmp-server snmpv1-v2c
```

2. To configure an SNMPv3 user, specify the username, group name, and authentication method. For example:

```
ACOS(config)# snmp-server snmpv3 user example-user group example-group
v3 auth md5 example-password
```

3. To configure contact information, use the **snmp-server contact** command:

```
ACOS(config)# snmp-server contact example-contact
```

4. To enable the SNMP agent and SNMP traps, use the **snmp-server enable traps** command. For example, to enable all SNMP traps:

```
ACOS(config)# snmp-server enable traps all
```

5. To enable the SNMP schema agent for IP Anomaly Drop Statistics, and multi-PU platform, use the following command:

```
ACOS(config)# snmp-server enable schema-agent
```

6. To configure an SNMP group, specify the group name and security level. For example:

```
ACOS(config)# snmp-server group example-grou-name v3 auth read example-
read-view-name
```

7. To configure the external SNMP trap receivers, use the **snmp-server host** command:

```
ACOS(config)# snmp-server host 10.10.10.10 version v3 user WDCS
```

8. To configure the location information, use the **snmp-server location** command:

```
ACOS(config)# snmp-server location example-location
```

9. To configure an SNMP view, use the following command:

```
ACOS(config)# snmp-server view example-view-name example-oid included
```

NOTE: For more information about these commands and other SNMP-related commands, refer to the *Command Line Interface Reference*.

Make sure that you run the **write memory** command to save the changes.

Source Interface for SNMP Notifications

You can specify a data interface to use as the source interface for the SNMP traps. By default, the management interface is the source interface for the SNMP traps.

- This feature does not support IPv6.
- This feature supports SNMPv1 but not SNMPv2c or SNMPv3.

The interface can be any of the following types:

- Ethernet
- VLAN / VE
- Loopback

When the ACOS Device sends an SNMP trap from the data interface you specify, the “agent-address” in the SNMP trap is the IP address for data interface.

The following topics are covered:

GUI Configuration 31
CLI Configuration 32

GUI Configuration

To configure an Ethernet interface as the source for the SNMP traps:

1. Hover over **Network** in the navigation bar and select **Interface**.
2. On the menu bar, click **LAN**.
3. Click **Edit** in the Actions column for the Ethernet interface.
4. Select the checkbox next to Trap Source in the General Fields section.
5. Click **Update**.

CLI Configuration

The following command attempts to set a loopback interface as the SNMP trap source. However, the feature has already been enabled on Ethernet port 1, and only one interface can be enabled for the SNMP traps, so this example shows that the existing trap source will be overwritten with the new one:

```
ACOS(config)# interface loopback 1
ACOS(config-if:loopback:1)# snmp-server trap-source
The trap source already exists for interface eth1. Do you want to
overwrite? [yes/no]:yes
ACOS(config-if:loopback:1)#
```

List of MIB Objects

Field Name : axFPGADropCounterTable
Field Type : TABLE
Field Status : current
Description : A table has information of FPGA drop-counter
: it will contain the result as the CLI command,
: 'show system platform drop-counter'
OID : 1.3.6.1.4.1.22610.2.4.3.25.2

Field Name : axFPGACount
Field Type : INTEGER
Field Status : current
Description : The number of FPGA in the platform.
OID : 1.3.6.1.4.1.22610.2.4.3.25.1

Field Name : axFPGADropCounterEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axAppGlobalSystemResourceUsage Table
OID : 1.3.6.1.4.1.22610.2.4.3.25.2.1

Field Name : axFPGADropCounterValue
Field Type : String
Field Status : current
Description : The value of the counter.
OID : 1.3.6.1.4.1.22610.2.4.3.25.2.1.4

Field Name : axFPGADropCounterName
Field Type : String
Field Status : current
Description : The counter name.
OID : 1.3.6.1.4.1.22610.2.4.3.25.2.1.3

Field Name : axFPGADropCounterFPGANum
Field Type : INTEGER
Field Status : current
Description : The FPGA number.
OID : 1.3.6.1.4.1.22610.2.4.3.25.2.1.2

Field Name : axFPGADropCounterIndex
Field Type : INTEGER
Field Status : current
Description : The index of the table.
OID : 1.3.6.1.4.1.22610.2.4.3.25.2.1.1

Field Name : axDDosStatsHWL4EntryMatchDrop
Field Type : Counter64
Field Status : current
Description : The number of HW L4 entry match drops.
OID : 1.3.6.1.4.1.22610.2.4.3.24.1.16

Field Name : axDDosStatsL4EntryMatchDrop
Field Type : Counter64
Field Status : current
Description : The number of L4 entry match drops.
OID : 1.3.6.1.4.1.22610.2.4.3.24.1.15

Field Name : axDDosStatsHWOutOfL4Entries
Field Type : Counter64
Field Status : current
Description : The number of times HW is out of L4 entries.
OID : 1.3.6.1.4.1.22610.2.4.3.24.1.14

Field Name : axDDosStatsL4EntryRemovedFromHW
Field Type : Counter64
Field Status : current
Description : The number of L4 entries removed from HW.
OID : 1.3.6.1.4.1.22610.2.4.3.24.1.13

Field Name : axDDosStatsL4EntryAddedToHW
Field Type : Counter64
Field Status : current
Description : The number of L4 entries added to HW.
OID : 1.3.6.1.4.1.22610.2.4.3.24.1.12

Field Name : axDDosStatsL4EntryDeleted
Field Type : Counter64
Field Status : current
Description : The number of L4 entries deleted.
OID : 1.3.6.1.4.1.22610.2.4.3.24.1.11

Field Name : axDDosStatsL4EntryAdded
Field Type : Counter64
Field Status : current
Description : The number of L4 entries added.
OID : 1.3.6.1.4.1.22610.2.4.3.24.1.10

Field Name : axDDosStatsHWL3EntryMatchDrop
Field Type : Counter64
Field Status : current
Description : The number of HW L3 entry match drops.
OID : 1.3.6.1.4.1.22610.2.4.3.24.1.9

Field Name : axDDosStatsL3EntryMatchDrop
Field Type : Counter64
Field Status : current
Description : The number of L3 entry match drops.
OID : 1.3.6.1.4.1.22610.2.4.3.24.1.8

Field Name : axDDosStatsTooManyL3Entries
Field Type : Counter64
Field Status : current
Description : The number of times L3 entries are exceeded.
OID : 1.3.6.1.4.1.22610.2.4.3.24.1.7

Field Name : axDDosStatsL3EntryRemovedFromHW
Field Type : Counter64
Field Status : current
Description : The number of L3 entries removed from HW.
OID : 1.3.6.1.4.1.22610.2.4.3.24.1.6

Field Name : axDDosStatsL3EntryAddedToHW
Field Type : Counter64
Field Status : current

Description : The number of L3 entries added to HW.
OID : 1.3.6.1.4.1.22610.2.4.3.24.1.5

Field Name : axDDosStatsL3EntryRemovedFromBGP
Field Type : Counter64
Field Status : current
Description : The number of L3 entries removed from BGP.
OID : 1.3.6.1.4.1.22610.2.4.3.24.1.4

Field Name : axDDosStatsL3EntryAddedToBGP
Field Type : Counter64
Field Status : current
Description : The number of L3 entries added to BGP.
OID : 1.3.6.1.4.1.22610.2.4.3.24.1.3

Field Name : axDDosStatsL3EntryDeleted
Field Type : Counter64
Field Status : current
Description : The number of L3 entries deleted.
OID : 1.3.6.1.4.1.22610.2.4.3.24.1.2

Field Name : axDDosStatsL3EntryAdded
Field Type : Counter64
Field Status : current
Description : The number of L3 entries added.
OID : 1.3.6.1.4.1.22610.2.4.3.24.1.1

Field Name : axVrrpGroupStatusTable
Field Type : TABLE
Field Status : current
Description : A table contains the Vrrp group status information.
OID : 1.3.6.1.4.1.22610.2.4.3.23.1.1

Field Name : axVrrpGroupStatusEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axVrrpGroupStatus Table
OID : 1.3.6.1.4.1.22610.2.4.3.23.1.1.1

Field Name : axVrrpGroupForcedStandBy
Field Type : EnumVal
Field Status : current
Description : It is forcedStandBy or not.
OID : 1.3.6.1.4.1.22610.2.4.3.23.1.1.1.6

Field Name : axVrrpGroupPriority
Field Type : Integer32
Field Status : current
Description : The priority of this vrrp group.
OID : 1.3.6.1.4.1.22610.2.4.3.23.1.1.1.5

Field Name : axVrrpGroupWeight
Field Type : Integer32
Field Status : current
Description : The Weight of this vrrp group.
OID : 1.3.6.1.4.1.22610.2.4.3.23.1.1.1.4

Field Name : axVrrpGroupStatus

Field Type : EnumVal
Field Status : current
Description : The status of this vrrp group.
OID : 1.3.6.1.4.1.22610.2.4.3.23.1.1.1.3

Field Name : axVrrpUnit
Field Type : INTEGER
Field Status : current
Description : The devive id.
OID : 1.3.6.1.4.1.22610.2.4.3.23.1.1.1.2

Field Name : axVrid
Field Type : INTEGER
Field Status : current
Description : The vrid. Zero(0) is default.
OID : 1.3.6.1.4.1.22610.2.4.3.23.1.1.1.1

Field Name : axIpv4InIpv6SessionMaxPacketsExceed
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 fragment Session max packets exceed.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.39

Field Name : axIpv4InIpv6TooManyPacketsPerReassemblyDrop
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 fragment too many packets per reassembly drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.38

Field Name : axIpv4InIpv6FragmentProcessingDrop
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 fragment processing drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.37

Field Name : axIpv4InIpv6MtuExceedPolicyDrop
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 MTU exceed policy drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.36

Field Name : axIpv4InIpv6FragmentReassemblyFailure
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 fragment reassembly failure.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.35

Field Name : axIpv4InIpv6FragmentMaxDataLengthExceed
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 fragment max data length exceed.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.34

Field Name : axIpv4InIpv6FragmentReassemblySuccess
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 fragment reassembly success.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.33

Field Name : axIpv4InIpv6FragmentQueueFailure
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 fragment queue failure.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.32

Field Name : axIpv4InIpv6TotalQueuedFragmentsExceed
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 total queued fragments exceed.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.31

Field Name : axIpv4InIpv6DuplicateLastFragment
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 duplicate last fragment.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.30

Field Name : axIpv4InIpv6DuplicateFirstFragment
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 duplicate first fragment.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.29

Field Name : axIpv4InIpv6PayloadLengthOutOfBounds
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 payload length out of bounds.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.28

Field Name : axIpv4InIpv6PayloadLengthUnaligned
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 payload length unaligned.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.27

Field Name : axIpv4InIpv6FragmentQueueSuccess
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 fragment queue success.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.26

Field Name : axIpv4InIpv6FragmentationFastAgingUnset
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 fragmentation fast aging unset.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.25

Field Name : axIpv4InIpv6FragmentationFastAgingSet
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 fragmentation fast aging set.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.24

Field Name : axIpv4InIpv6OutOfSessionMemory
Field Type : Counter64
Field Status : current

Description : The count of l3 ipv4 in ipv6 out of session memory.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.23

Field Name : axIpv4InIpv6TotalSessionsExceedDrop
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 total sessions exceed drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.22

Field Name : axIpv4InIpv6FirstL4FragmentTooSmallDrop
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 first L4 fragment too small drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.21

Field Name : axIpv4InIpv6FirstTcpFragmentTooSmallDrop
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 first TCP fragment too small drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.20

Field Name : axIpv4InIpv6FragmentTooSmallDrop
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 fragment too small drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.19

Field Name : axIpv4InIpv6BadIpLength
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 bad ip length.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.18

Field Name : axIpv4InIpv6OverlappingFragmentDropped
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 overlapping fragment dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.17

Field Name : axIpv4InIpv6OtherDropped
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 Other dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.16

Field Name : axIpv4InIpv6Ipv6InIpDropped
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 Ipv6-In-Ip dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.15

Field Name : axIpv4InIpv6IpInIpDropped
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 Ip-In-Ip dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.14

Field Name : axIpv4InIpv6TcpDropped

Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 TCP dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.13

Field Name : axIpv4InIpv6UdpDropped
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 UDP dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.12

Field Name : axIpv4InIpv6Icmpv6Dropped
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 ICMPv6 dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.11

Field Name : axIpv4InIpv6IcmpDropped
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 ICMP dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.10

Field Name : axIpv4InIpv6OtherReceived
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 other Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.9

Field Name : axIpv4InIpv6Ipv6InIpReceived
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 Ipv6-In-Ip Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.8

Field Name : axIpv4InIpv6IpInIpReceived
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 Ip-In-Ip Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.7

Field Name : axIpv4InIpv6TcpReceived
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 Tcp Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.6

Field Name : axIpv4InIpv6UdpReceived
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 UDP Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.5

Field Name : axIpv4InIpv6Icmpv6Received
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 ICMPv6 Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.4

Field Name : axIpv4InIpv6IcmpReceived
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 ICMP Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.3

Field Name : axIpv4InIpv6SessionExpired
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 session expired.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.2

Field Name : axIpv4InIpv6SessionInsert
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 session inserts.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.1

Field Name : axIpv6SessionMaxPacketsExceed
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 fragment Session max packets exceed.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.39

Field Name : axIpv6TooManyPacketsPerReassemblyDrop
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 fragment too many packets per reassembly drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.38

Field Name : axIpv6FragmentProcessingDrop
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 fragment processing drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.37

Field Name : axIpv6MtuExceedPolicyDrop
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 MTU exceed policy drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.36

Field Name : axIpv6FragmentReassemblyFailure
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 fragment reassembly failure.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.35

Field Name : axIpv6FragmentMaxDataLengthExceed
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 fragment max data length exceed.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.34

Field Name : axIpv6FragmentReassemblySuccess
Field Type : Counter64
Field Status : current

Description : The count of l3 ipv6 fragment reassembly success.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.33

Field Name : axIpv6FragmentQueueFailure
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 fragment queue failure.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.32

Field Name : axIpv6TotalQueuedFragmentsExceed
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 total queued fragments exceed.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.31

Field Name : axIpv6DuplicateLastFragment
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 duplicate last fragment.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.30

Field Name : axIpv6DuplicateFirstFragment
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 duplicate first fragment.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.29

Field Name : axIpv6PayloadLengthOutOfBounds
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 payload length out of bounds.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.28

Field Name : axIpv6PayloadLengthUnaligned
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 payload length unaligned.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.27

Field Name : axIpv6FragmentQueueSuccess
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 fragment queue success.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.26

Field Name : axIpv6FragmentationFastAgingUnset
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 fragmentation fast aging unset.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.25

Field Name : axIpv6FragmentationFastAgingSet
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 fragmentation fast aging set.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.24

Field Name : axIpv6OutOfSessionMemory

Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 out of session memory.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.23

Field Name : axIpv6TotalSessionsExceedDrop
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 total sessions exceed drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.22

Field Name : axIpv6FirstL4FragmentTooSmallDrop
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 first L4 fragment too small drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.21

Field Name : axIpv6FirstTcpFragmentTooSmallDrop
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 first TCP fragment too small drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.20

Field Name : axIpv6FragmentTooSmallDrop
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 fragment too small drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.19

Field Name : axIpv6BadIpLength
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 bad ip length.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.18

Field Name : axIpv6OverlappingFragmentDropped
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 overlapping fragment dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.17

Field Name : axIpv6OtherDropped
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 Other dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.16

Field Name : axIpv6Ipv6InIpDropped
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 Ipv6-In-Ip dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.15

Field Name : axIpv6IpInIpDropped
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 Ip-In-Ip dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.14

Field Name : axIpv6TcpDropped
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 TCP dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.13

Field Name : axIpv6UdpDropped
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 UDP dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.12

Field Name : axIpv6Icmpv6Dropped
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 ICMPv6 dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.11

Field Name : axIpv6IcmpDropped
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 ICMP dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.10

Field Name : axIpv6OtherReceived
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 other Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.9

Field Name : axIpv6Ipv6InIpReceived
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 Ipv6-In-Ip Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.8

Field Name : axIpv6IpInIpReceived
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 Ip-In-Ip Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.7

Field Name : axIpv6TcpReceived
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 Tcp Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.6

Field Name : axIpv6UdpReceived
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 UDP Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.5

Field Name : axIpv6Icmpv6Received
Field Type : Counter64
Field Status : current

Description : The count of l3 ipv6 ICMPv6 Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.4

Field Name : axIpv6IcmpReceived
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 ICMP Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.3

Field Name : axIpv6SessionExpired
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 session expired.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.2

Field Name : axIpv6SessionInsert
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 session inserts.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.1

Field Name : axIpv4DDoSProtectionDrop
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 fragment DDoS protection drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.43

Field Name : axIpv4HighCpuDrop
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 fragment high cpu drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.42

Field Name : axIpv4LowCpuThresholdReached
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 fragment low cpu threshold.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.41

Field Name : axIpv4HighCpuThresholdReached
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 fragment high cpu threshold.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.40

Field Name : axIpv4SessionMaxPacketsExceed
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 fragment Session max packets exceed.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.39

Field Name : axIpv4TooManyPacketsPerReassemblyDrop
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 fragment too many packets per reassembly drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.38

Field Name : axIpv4FragmentProcessingDrop

Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 fragment processing drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.37

Field Name : axIpv4MtuExceedPolicyDrop
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 MTU exceed policy drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.36

Field Name : axIpv4FragmentReassemblyFailure
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 fragment reassembly failure.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.35

Field Name : axIpv4FragmentMaxDataLengthExceed
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 fragment max data length exceed.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.34

Field Name : axIpv4FragmentReassemblySuccess
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 fragment reassembly success.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.33

Field Name : axIpv4FragmentQueueFailure
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 fragment queue failure.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.32

Field Name : axIpv4TotalQueuedFragmentsExceed
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 total queued fragments exceed.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.31

Field Name : axIpv4DuplicateLastFragment
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 duplicate last fragment.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.30

Field Name : axIpv4DuplicateFirstFragment
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 duplicate first fragment.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.29

Field Name : axIpv4PayloadLengthOutOfBounds
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 payload length out of bounds.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.28

Field Name : axIpv4PayloadLengthUnaligned
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 payload length unaligned.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.27

Field Name : axIpv4FragmentQueueSuccess
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 fragment queue success.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.26

Field Name : axIpv4FragmentationFastAgingUnset
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 fragmentation fast aging unset.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.25

Field Name : axIpv4FragmentationFastAgingSet
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 fragmentation fast aging set.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.24

Field Name : axIpv4OutOfSessionMemory
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 out of session memory.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.23

Field Name : axIpv4TotalSessionsExceedDrop
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 total sessions exceed drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.22

Field Name : axIpv4FirstL4FragmentTooSmallDrop
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 first L4 fragment too small drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.21

Field Name : axIpv4FirstTcpFragmentTooSmallDrop
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 first TCP fragment too small drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.20

Field Name : axIpv4FragmentTooSmallDrop
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 fragment too small drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.19

Field Name : axIpv4BadIpLength
Field Type : Counter64
Field Status : current

Description : The count of l3 ipv4 bad ip length.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.18

Field Name : axIpv4OverlappingFragmentDropped
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 overlapping fragment dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.17

Field Name : axIpv4OtherDropped
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 Other dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.16

Field Name : axIpv4Ipv6InIpDropped
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 Ipv6-In-Ip dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.15

Field Name : axIpv4IpInIpDropped
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 Ip-In-Ip dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.14

Field Name : axIpv4TcpDropped
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 TCP dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.13

Field Name : axIpv4UdpDropped
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 UDP dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.12

Field Name : axIpv4Icmpv6Dropped
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 ICMPv6 dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.11

Field Name : axIpv4IcmpDropped
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 ICMP dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.10

Field Name : axIpv4OtherReceived
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 other Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.9

Field Name : axIpv4Ipv6InIpReceived

Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 Ipv6-In-Ip Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.8

Field Name : axIpv4IpInIpReceived
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 Ip-In-Ip Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.7

Field Name : axIpv4TcpReceived
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 Tcp Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.6

Field Name : axIpv4UdpReceived
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 UDP Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.5

Field Name : axIpv4Icmpv6Received
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 ICMPv6 Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.4

Field Name : axIpv4IcmpReceived
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 ICMP Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.3

Field Name : axIpv4SessionExpired
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 session expired.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.2

Field Name : axIpv4SessionInsert
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 session inserts.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.1

Field Name : axIpv6InIpv4SessionMaxPacketsExceed
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 fragment Session max packets exceed.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.39

Field Name : axIpv6InIpv4TooManyPacketsPerReassemblyDrop
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 fragment too many packets per reassembly drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.38

Field Name : axIpv6InIpv4FragmentProcessingDrop
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 fragment processing drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.37

Field Name : axIpv6InIpv4MtuExceedPolicyDrop
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 MTU exceed policy drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.36

Field Name : axIpv6InIpv4FragmentReassemblyFailure
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 fragment reassembly failure.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.35

Field Name : axIpv6InIpv4FragmentMaxDataLengthExceed
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 fragment max data length exceed.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.34

Field Name : axIpv6InIpv4FragmentReassemblySuccess
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 fragment reassembly success.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.33

Field Name : axIpv6InIpv4FragmentQueueFailure
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 fragment queue failure.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.32

Field Name : axIpv6InIpv4TotalQueuedFragmentsExceed
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 total queued fragments exceed.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.31

Field Name : axIpv6InIpv4DuplicateLastFragment
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 duplicate last fragment.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.30

Field Name : axIpv6InIpv4DuplicateFirstFragment
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 duplicate first fragment.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.29

Field Name : axIpv6InIpv4PayloadLengthOutOfBounds
Field Type : Counter64
Field Status : current

Description : The count of l3 ipv6 in ipv4 payload length out of bounds.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.28

Field Name : axIpv6InIpv4PayloadLengthUnaligned
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 payload length unaligned.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.27

Field Name : axIpv6InIpv4FragmentQueueSuccess
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 fragment queue success.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.26

Field Name : axIpv6InIpv4FragmentationFastAgingUnset
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 fragmentation fast aging unset.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.25

Field Name : axIpv6InIpv4FragmentationFastAgingSet
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 fragmentation fast aging set.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.24

Field Name : axIpv6InIpv4OutOfSessionMemory
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 out of session memory.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.23

Field Name : axIpv6InIpv4TotalSessionsExceedDrop
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 total sessions exceed drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.22

Field Name : axIpv6InIpv4FirstL4FragmentTooSmallDrop
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 first L4 fragment too small drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.21

Field Name : axIpv6InIpv4FirstTcpFragmentTooSmallDrop
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 first TCP fragment too small drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.20

Field Name : axIpv6InIpv4FragmentTooSmallDrop
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 fragment too small drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.19

Field Name : axIpv6InIpv4BadIpLength

Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 bad ip length.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.18

Field Name : axIpv6InIpv4OverlappingFragmentDropped
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 overlapping fragment dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.17

Field Name : axIpv6InIpv4OtherDropped
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 Other dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.16

Field Name : axIpv6InIpv4Ipv6InIpDropped
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 Ipv6-In-Ip dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.15

Field Name : axIpv6InIpv4IpInIpDropped
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 Ip-In-Ip dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.14

Field Name : axIpv6InIpv4TcpDropped
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 TCP dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.13

Field Name : axIpv6InIpv4UdpDropped
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 UDP dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.12

Field Name : axIpv6InIpv4Icmpv6Dropped
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 ICMPv6 dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.11

Field Name : axIpv6InIpv4IcmpDropped
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 ICMP dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.10

Field Name : axIpv6InIpv4OtherReceived
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 other Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.9

Field Name : axIpv6InIpv4Ipv6InIpReceived
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 Ipv6-In-Ip Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.8

Field Name : axIpv6InIpv4IpInIpReceived
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 Ip-In-Ip Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.7

Field Name : axIpv6InIpv4TcpReceived
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 Tcp Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.6

Field Name : axIpv6InIpv4UdpReceived
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 UDP Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.5

Field Name : axIpv6InIpv4Icmpv6Received
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 ICMPv6 Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.4

Field Name : axIpv6InIpv4IcmpReceived
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 ICMP Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.3

Field Name : axIpv6InIpv4SessionExpired
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 session expired.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.2

Field Name : axIpv6InIpv4SessionInsert
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv6 in ipv4 session inserts.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.1

Field Name : axGslbSiteSlbDeviceTable
Field Type : TABLE
Field Status : current
Description : A table has information of GSLB service ports
OID : 1.3.6.1.4.1.22610.2.4.3.20.5.1

Field Name : axGslbSiteSlbDeviceEntry
Field Type : CounterBasedGauge64
Field Status : current

Description : Columns in the axGslbSiteSlbDevices Table
OID : 1.3.6.1.4.1.22610.2.4.3.20.5.1.1

Field Name : axGslbSiteSlbDeviceServicIpCount
Field Type : Counter
Field Status : current
Description : The number of the service-ip entries.
OID : 1.3.6.1.4.1.22610.2.4.3.20.5.1.1.8

Field Name : axGslbSiteSlbDeviceAvailSessionCount
Field Type : Counter
Field Status : current
Description : The number of the available sessions in the SLB device entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.5.1.1.7

Field Name : axGslbSiteSlbDeviceSessionUtilization
Field Type : INTEGER
Field Status : current
Description : The session utilization of the SLB device entry in percentage.
OID : 1.3.6.1.4.1.22610.2.4.3.20.5.1.1.6

Field Name : axGslbSiteSlbDeviceAdminPreference
Field Type : INTEGER
Field Status : current
Description : The administrative preference of the SLB device entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.5.1.1.5

Field Name : axGslbSiteSlbDeviceProtocolFlag
Field Type : EnumVal
Field Status : current
Description : The SLB device with the GSLB protocol or local protocol.
OID : 1.3.6.1.4.1.22610.2.4.3.20.5.1.1.4

Field Name : axGslbSiteForSlbDeviceName
Field Type : String
Field Status : current
Description : The name of the slb-device entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.5.1.1.3

Field Name : axGslbSiteSlbForDeviceIpAddr
Field Type : String
Field Status : current
Description : The IP address of the slb-device entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.5.1.1.2

Field Name : axGslbSiteSlbDeviceSiteName
Field Type : String
Field Status : current
Description : The site name of the slb-device entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.5.1.1.1

Field Name : axGslbServiceIpPortTable
Field Type : TABLE
Field Status : current
Description : A table has information of GSLB service ports
OID : 1.3.6.1.4.1.22610.2.4.3.20.4.1

Field Name : axGslbServiceIpPortEntry

Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axGslbServicePorts Table
OID : 1.3.6.1.4.1.22610.2.4.3.20.4.1.1

Field Name : axGslbServiceIpPortCurrConns
Field Type : Counter64
Field Status : current
Description : The number of the current connections.
OID : 1.3.6.1.4.1.22610.2.4.3.20.4.1.1.6

Field Name : axGslbServiceIpPortActiveServerCount
Field Type : Counter
Field Status : current
Description : The number of the active real servers.
OID : 1.3.6.1.4.1.22610.2.4.3.20.4.1.1.5

Field Name : axGslbServiceIpPortProtocolFlag
Field Type : EnumVal
Field Status : current
Description : The service-ip port with the GSLB protocol or local protocol.
OID : 1.3.6.1.4.1.22610.2.4.3.20.4.1.1.4

Field Name : axGslbServiceIpPortOperState
Field Type : EnumVal
Field Status : current
Description : The service-ip port operational state.
OID : 1.3.6.1.4.1.22610.2.4.3.20.4.1.1.3

Field Name : axGslbServiceIpPortNum
Field Type : INTEGER
Field Status : current
Description : The port number of the service-ip port entry
OID : 1.3.6.1.4.1.22610.2.4.3.20.4.1.1.2

Field Name : axGslbServiceIpPortAddr
Field Type : String
Field Status : current
Description : The IP address of the service-ip entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.4.1.1.1

Field Name : axGslbServiceIPTable
Field Type : TABLE
Field Status : current
Description : A table has information of GSLB service IPs
OID : 1.3.6.1.4.1.22610.2.4.3.20.3.2

Field Name : axGslbServiceIPCount
Field Type : INTEGER
Field Status : current
Description : The number of axGslbServiceIPTable entries in the table.
OID : 1.3.6.1.4.1.22610.2.4.3.20.3.1

Field Name : axGslbServiceIPEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axGslbServiceIPs Table
OID : 1.3.6.1.4.1.22610.2.4.3.20.3.2.1

Field Name : axGslbServiceIpHitCount
Field Type : Counter64
Field Status : current
Description : The hit count of the service-ip entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.3.2.1.9

Field Name : axGslbServiceIpServicePortCount
Field Type : Counter
Field Status : current
Description : The number of ports for the service-ip entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.3.2.1.8

Field Name : axGslbServiceIpProtocolFlag
Field Type : EnumVal
Field Status : current
Description : The service-ip with the GSLB protocol or local protocol.
OID : 1.3.6.1.4.1.22610.2.4.3.20.3.2.1.7

Field Name : axGslbServiceIpIsVirtualServerFlag
Field Type : EnumVal
Field Status : current
Description : The flag of virtual server.
OID : 1.3.6.1.4.1.22610.2.4.3.20.3.2.1.6

Field Name : axGslbServiceIpOperState
Field Type : EnumVal
Field Status : current
Description : The service-ip operational state.
OID : 1.3.6.1.4.1.22610.2.4.3.20.3.2.1.5

Field Name : axGslbServiceIpAdminState
Field Type : EnumVal
Field Status : current
Description : The service-ip administrative state.
OID : 1.3.6.1.4.1.22610.2.4.3.20.3.2.1.4

Field Name : axGslbServiceIpSiteName
Field Type : String
Field Status : current
Description : The site name has the service-ip entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.3.2.1.3

Field Name : axGslbServiceIpName
Field Type : String
Field Status : current
Description : The name of the service-ip entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.3.2.1.2

Field Name : axGslbServiceIpAddr
Field Type : String
Field Status : current
Description : The IP address of the service-ip entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.3.2.1.1

Field Name : axGslbSiteDeviceStatsTable
Field Type : TABLE
Field Status : current

Description : A table has information of GSLB site devices
OID : 1.3.6.1.4.1.22610.2.4.3.20.2.3

Field Name : axGslbSiteStatsTable
Field Type : TABLE
Field Status : current
Description : A table has information of GSLB sites
OID : 1.3.6.1.4.1.22610.2.4.3.20.2.2

Field Name : axGslbSiteStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axGslbSiteStats Table
OID : 1.3.6.1.4.1.22610.2.4.3.20.2.2.1

Field Name : axGslbSiteHitCount
Field Type : Counter64
Field Status : current
Description : The hit count of the site.
OID : 1.3.6.1.4.1.22610.2.4.3.20.2.2.1.4

Field Name : axGslbSiteOperState
Field Type : EnumVal
Field Status : current
Description : The site operational state.
OID : 1.3.6.1.4.1.22610.2.4.3.20.2.2.1.3

Field Name : axGslbSiteAdminState
Field Type : EnumVal
Field Status : current
Description : The site administrative state.
OID : 1.3.6.1.4.1.22610.2.4.3.20.2.2.1.2

Field Name : axGslbSiteName
Field Type : String
Field Status : current
Description : The name of the site entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.2.2.1.1

Field Name : axGslbSiteCount
Field Type : INTEGER
Field Status : current
Description : The total number of sites.
OID : 1.3.6.1.4.1.22610.2.4.3.20.2.1

Field Name : axGslbSiteDeviceStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axGslbSiteDevicesStats Table
OID : 1.3.6.1.4.1.22610.2.4.3.20.2.3.1

Field Name : axGslbSiteServiceIpHitCount
Field Type : Counter64
Field Status : current
Description : The hit count of the service-ip name in the site device entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.2.3.1.9

Field Name : axGslbSiteServiceIpOperState

Field Type : EnumVal
Field Status : current
Description : The service-ip operational state.
OID : 1.3.6.1.4.1.22610.2.4.3.20.2.3.1.8

Field Name : axGslbSiteServiceIpAdminState
Field Type : EnumVal
Field Status : current
Description : The service-ip administrative state.
OID : 1.3.6.1.4.1.22610.2.4.3.20.2.3.1.7

Field Name : axGslbSiteServiceIpName
Field Type : String
Field Status : current
Description : The service-ip name in the site device entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.2.3.1.6

Field Name : axGslbSiteSlbDeviceName
Field Type : String
Field Status : current
Description : The SLB device name in the site device entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.2.3.1.5

Field Name : axGslbSiteServiceIpPortNum
Field Type : INTEGER
Field Status : current
Description : The port number of the service-ip in the site device entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.2.3.1.4

Field Name : axGslbSiteServiceIpAddr
Field Type : String
Field Status : current
Description : The IP address of the service-ip in the site device entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.2.3.1.3

Field Name : axGslbSiteSlbDeviceIpAddr
Field Type : String
Field Status : current
Description : The IP address of the SLB device in the site entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.2.3.1.2

Field Name : axGslbSiteNameInDeviceEntry
Field Type : String
Field Status : current
Description : The name of the site.
OID : 1.3.6.1.4.1.22610.2.4.3.20.2.3.1.1

Field Name : axGslbZoneServiceStatsTable
Field Type : TABLE
Field Status : current
Description : A table has information of GSLB zone services
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.3

Field Name : axGslbZoneStatsTable
Field Type : TABLE
Field Status : current
Description : A table has information of GSLB zones
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.2

Field Name : axGslbZoneStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axGslbStatsZones Table
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.2.1

Field Name : axGslbZoneBackupModeCount
Field Type : Counter64
Field Status : current
Description : The count in backup mode.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.2.1.10

Field Name : axGslbZoneStickyModeCount
Field Type : Counter64
Field Status : current
Description : The count in sticky mode.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.2.1.9

Field Name : axGslbZoneServerModeCount
Field Type : Counter64
Field Status : current
Description : The count in server mode.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.2.1.8

Field Name : axGslbZoneCacheModeCount
Field Type : Counter64
Field Status : current
Description : The count in cache mode.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.2.1.7

Field Name : axGslbZoneProxyModeCount
Field Type : Counter64
Field Status : current
Description : The count in proxy mode.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.2.1.6

Field Name : axGslbZoneSentResponses
Field Type : Counter64
Field Status : current
Description : The number of sent response on the zone entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.2.1.5

Field Name : axGslbZoneReceivedQueries
Field Type : Counter64
Field Status : current
Description : The number of received queries on the zone entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.2.1.4

Field Name : axGslbZoneOperState
Field Type : EnumVal
Field Status : current
Description : The Zone operational state.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.2.1.3

Field Name : axGslbZoneAdminState
Field Type : EnumVal
Field Status : current

Description : The Zone administrative state.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.2.1.2

Field Name : axGslbZoneName
Field Type : String
Field Status : current
Description : The name of the zone entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.2.1.1

Field Name : axGslbZoneCount
Field Type : INTEGER
Field Status : current
Description : The number of axGslbZoneStatsTable entries in the table.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.1

Field Name : axGslbZoneServiceStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axGslbZoneServiceStats Table
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.3.1

Field Name : axGslbZoneServiceBackupModeCount
Field Type : Counter64
Field Status : current
Description : The count in backup mode.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.3.1.13

Field Name : axGslbZoneServiceStickyModeCount
Field Type : Counter64
Field Status : current
Description : The count in sticky mode.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.3.1.12

Field Name : axGslbZoneServiceServerModeCount
Field Type : Counter64
Field Status : current
Description : The count in server mode.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.3.1.11

Field Name : axGslbZoneServiceCacheModeCount
Field Type : Counter64
Field Status : current
Description : The count in cache mode.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.3.1.10

Field Name : axGslbZoneServiceProxyModeCount
Field Type : Counter64
Field Status : current
Description : The count in proxy mode.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.3.1.9

Field Name : axGslbZoneServiceSentResponses
Field Type : Counter64
Field Status : current
Description : The number of sent response on the zone service entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.3.1.8

Field Name : axGslbZoneServiceReceivedQueries

Field Type : Counter64
Field Status : current
Description : The number of received queries on the zone service entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.3.1.7

Field Name : axGslbZoneServiceOperState
Field Type : EnumVal
Field Status : current
Description : The Zone Service operational state.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.3.1.6

Field Name : axGslbZoneServiceAdminState
Field Type : EnumVal
Field Status : current
Description : The Zone Service administrative state.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.3.1.5

Field Name : axGslbZoneServicePortNum
Field Type : INTEGER
Field Status : current
Description : The port number of the zone service entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.3.1.4

Field Name : axGslbZoneServiceName
Field Type : String
Field Status : current
Description : The service name of the zone service entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.3.1.3

Field Name : axGslbZoneNameInServiceEntry
Field Type : String
Field Status : current
Description : The name of the zone in service entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.3.1.2

Field Name : axGslbZoneServiceFqdn
Field Type : String
Field Status : current
Description : The Fqdn of Zone Service Entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.3.1.1

Field Name : axGslbGroupTable
Field Type : TABLE
Field Status : current
Description : A table has information on GSLB groups.
OID : 1.3.6.1.4.1.22610.2.4.3.20.6.1

Field Name : axGslbGroupEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axGslbGroup Table
OID : 1.3.6.1.4.1.22610.2.4.3.20.6.1.1

Field Name : axGslbGroupAddress
Field Type : String
Field Status : current
Description : The ip address of the member in the axGslbGroupTable entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.6.1.1.7

Field Name : axGslbGroupStatus
Field Type : EnumVal
Field Status : current
Description : The status of the member in the axGslbGroupTable entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.6.1.1.6

Field Name : axGslbGroupAttribute
Field Type : BitString
Field Status : current
Description : The attribute of the member in the axGslbGroupTable entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.6.1.1.5

Field Name : axGslbGroupPriority
Field Type : INTEGER
Field Status : current
Description : The priority of the member in the axGslbGroupTable entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.6.1.1.4

Field Name : axGslbGroupSysID
Field Type : String
Field Status : current
Description : The sys id of the member in the axGslbGroupTable entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.6.1.1.3

Field Name : axGslbGroupMember
Field Type : String
Field Status : current
Description : The member of the group in the axGslbGroupTable entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.6.1.1.2

Field Name : axGslbGroupName
Field Type : String
Field Status : current
Description : The name of the axGslbGroupTable entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.6.1.1.1

Field Name : axSessionGlobalStatConnSMPFree
Field Type : Gauge
Field Status : current
Description : The count of free SMP connections.
OID : 1.3.6.1.4.1.22610.2.4.3.19.1.14

Field Name : axSessionGlobalStatConnSMPAllocated
Field Type : Gauge
Field Status : current
Description : The count of allocated SMP connections.
OID : 1.3.6.1.4.1.22610.2.4.3.19.1.13

Field Name : axSessionGlobalStatTCPSynHalfOpen
Field Type : Gauge
Field Status : current
Description : The count of TCP SYN half open.
OID : 1.3.6.1.4.1.22610.2.4.3.19.1.12

Field Name : axSessionGlobalStatConnFree
Field Type : Gauge
Field Status : current

Description : The count of freed connections.
OID : 1.3.6.1.4.1.22610.2.4.3.19.1.11

Field Name : axSessionGlobalStatConnCount
Field Type : Gauge
Field Status : current
Description : The count of current connections.
OID : 1.3.6.1.4.1.22610.2.4.3.19.1.10

Field Name : axSessionGlobalStatFreeCurrentConns
Field Type : Gauge
Field Status : current
Description : The count of free current connections.
OID : 1.3.6.1.4.1.22610.2.4.3.19.1.9

Field Name : axSessionGlobalStatReverseNATUDP
Field Type : Gauge
Field Status : current
Description : The count of reverse NAT UDP.
OID : 1.3.6.1.4.1.22610.2.4.3.19.1.7

Field Name : axSessionGlobalStatReverseNATTCP
Field Type : Gauge
Field Status : current
Description : The count of reverse NAT TCP.
OID : 1.3.6.1.4.1.22610.2.4.3.19.1.6

Field Name : axSessionGlobalStatOther
Field Type : Gauge
Field Status : current
Description : The count of others.
OID : 1.3.6.1.4.1.22610.2.4.3.19.1.5

Field Name : axSessionGlobalStatNonTcpUdpIPSession
Field Type : Gauge
Field Status : current
Description : The count of non TCP/UDP IP sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.19.1.4

Field Name : axSessionGlobalStatUDP
Field Type : Gauge
Field Status : current
Description : The count of UDP connections.
OID : 1.3.6.1.4.1.22610.2.4.3.19.1.3

Field Name : axSessionGlobalStatTCPHalfOpen
Field Type : Gauge
Field Status : current
Description : The count of TCP half open.
OID : 1.3.6.1.4.1.22610.2.4.3.19.1.2

Field Name : axSessionGlobalStatTCPEstablished
Field Type : Gauge
Field Status : current
Description : The count of TCP established.
OID : 1.3.6.1.4.1.22610.2.4.3.19.1.1

Field Name : axIpNatStatsDynamicMappingAclNameTable

Field Type : TABLE
Field Status : current
Description : A table has information of IP NAT interface inside/outside
OID : 1.3.6.1.4.1.22610.2.4.3.18.19.1

Field Name : axIpNatStatsDynamicMappingAclNameEndAddressType
Field Type : EnumVal
Field Status : current
Description : The type of axIpNatStatsDynamicMappingEndAddress:
: unknown(0), ipv4(1), ipv6(2)...
OID : 1.3.6.1.4.1.22610.2.4.3.18.19.1.1.10

Field Name : axIpNatStatsDynamicMappingAclNameStartAddressType
Field Type : EnumVal
Field Status : current
Description : The type of axIpNatStatsDynamicMappingStartAddress:
: unknown(0), ipv4(1), ipv6(2)...
OID : 1.3.6.1.4.1.22610.2.4.3.18.19.1.1.9

Field Name : axIpNatStatsDynamicMappingAclNameMissAddresses
Field Type : INTEGER
Field Status : current
Description : The total misses in the pool
OID : 1.3.6.1.4.1.22610.2.4.3.18.19.1.1.8

Field Name : axIpNatStatsDynamicMappingAclNameAllocAddresses
Field Type : INTEGER
Field Status : current
Description : The total allocated addresses in the pool
OID : 1.3.6.1.4.1.22610.2.4.3.18.19.1.1.7

Field Name : axIpNatStatsDynamicMappingAclNameTotalAddresses
Field Type : INTEGER
Field Status : current
Description : The total addresses in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.19.1.1.6

Field Name : axIpNatStatsDynamicMappingAclNameEndAddress
Field Type : String
Field Status : current
Description : The end address of the pool
OID : 1.3.6.1.4.1.22610.2.4.3.18.19.1.1.5

Field Name : axIpNatStatsDynamicMappingAclNameStartAddress
Field Type : String
Field Status : current
Description : The start adddress of the pool
OID : 1.3.6.1.4.1.22610.2.4.3.18.19.1.1.4

Field Name : axIpNatStatsDynamicMappingAclNamePoolName
Field Type : String
Field Status : current
Description : The IP source NAT pool name
OID : 1.3.6.1.4.1.22610.2.4.3.18.19.1.1.3

Field Name : axIpNatStatsDynamicMappingAclNameAccessListID
Field Type : INTEGER
Field Status : current

Description : The access list id.
OID : 1.3.6.1.4.1.22610.2.4.3.18.19.1.1.2

Field Name : axIpNatStatsDynamicMappingAclNameAccessListName
Field Type : String
Field Status : current
Description : The access list acl name.
OID : 1.3.6.1.4.1.22610.2.4.3.18.19.1.1.1

Field Name : axIpNatDsliteStatNoRadiusProfileMatch
Field Type : Counter64
Field Status : current
Description : The number of no radius profile match for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.48

Field Name : axIpNatDsliteStatNatHANatPoolUnusable
Field Type : Counter64
Field Status : current
Description : The number of HA nat pool unusable for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.47

Field Name : axIpNatDsliteStatNatPoolUnusable
Field Type : Counter64
Field Status : current
Description : The number of nat pool unusable for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.46

Field Name : axIpNatDsliteStatUdpPortOverloadingSessionFreed
Field Type : Counter64
Field Status : current
Description : The number of UDP port overloading session freed for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.45

Field Name : axIpNatDsliteStatTcpPortOverloadingSessionFreed
Field Type : Counter64
Field Status : current
Description : The number of TCP port overloading session Freed for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.44

Field Name : axIpNatDsliteStatUdpPortOverloadingSessionCreated
Field Type : Counter64
Field Status : current
Description : The number of UDP port overloading session created for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.43

Field Name : axIpNatDsliteStatTcpPortOverloadingSessionCreated
Field Type : Counter64
Field Status : current
Description : The number of TCP port overloading session created for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.42

Field Name : axIpNatDsliteStatUdpPortOverloaded
Field Type : Counter64
Field Status : current
Description : The number of UDP port overloaded for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.41

Field Name : axIpNatDsliteStatTcpPortOverloaded

Field Type : Counter64
Field Status : current
Description : The number of TCP port overloaded for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.40

Field Name : axIpNatDsliteStatNatPoolMismatchDrop
Field Type : Counter64
Field Status : current
Description : The number of nat pool mismatch drop for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.39

Field Name : axIpNatDsliteStatEndpointIndependentFilterInboundLimitExceeded
Field Type : Counter64
Field Status : current
Description : The number of endpoint independent filter inbound limit exceeded for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.38

Field Name : axIpNatDsliteStatConnRateUserQuotaExceeded
Field Type : Counter64
Field Status : current
Description : The number of connect rate user quota exceeded for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.37

Field Name : axIpNatDsliteStatDataSessionUserQuotaExceeded
Field Type : Counter64
Field Status : current
Description : The number of data session user quota exceeded for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.36

Field Name : axIpNatDsliteStatPermitClassListDrop
Field Type : Counter64
Field Status : current
Description : The number of drop of permit class list for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.35

Field Name : axIpNatDsliteStatNoClassListMatch
Field Type : Counter64
Field Status : current
Description : The number of no class list match for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.34

Field Name : axIpNatDsliteStatLsnLidPassThrough
Field Type : Counter64
Field Status : current
Description : The number of pass through of lsn lid for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.33

Field Name : axIpNatDsliteStatLsnLidDrop
Field Type : Counter64
Field Status : current
Description : The number of drop of lsn lid for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.32

Field Name : axIpNatDsliteStatTruncatedPacket
Field Type : Counter64
Field Status : current
Description : The number of truncated packets for the DsLite.

OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.31

Field Name : axIpNatDsliteStatEndpointDependentFilterDrop
Field Type : Counter64
Field Status : current
Description : The number of endpoint independent filtering drop for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.30

Field Name : axIpNatDsliteStatEndpointIndependentFilterMatched
Field Type : Counter64
Field Status : current
Description : The number of endpoint indenpendent filtering matched for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.29

Field Name : axIpNatDsliteStatEndpointIndependentMapMatched
Field Type : Counter64
Field Status : current
Description : The number of endpoint independent mapping for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.28

Field Name : axIpNatDsliteStatSelfHairpinDrop
Field Type : Counter64
Field Status : current
Description : The number of self hairpin drop for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.27

Field Name : axIpNatDsliteStatHairpinSessionCreated
Field Type : Counter64
Field Status : current
Description : The number of created hairpin session for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.26

Field Name : axIpNatDsLiteStatFullConeSessionFailed
Field Type : Counter64
Field Status : current
Description : The number of failed full cone session for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.25

Field Name : axIpNatDsLiteStatUdpFullConeSessionFreed
Field Type : Counter64
Field Status : current
Description : The total ICMP ports allocted for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.24

Field Name : axIpNatDsliteStatUdpFullConeSessionCreated
Field Type : Counter64
Field Status : current
Description : The number of created UDP full cone session for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.23

Field Name : axIpNatDsliteStatTcpFullConeSessionFreed
Field Type : Counter64
Field Status : current
Description : The number of freed TCP full cone session for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.22

Field Name : axIpNatDsliteStatTcpFullConeSessionCreated
Field Type : Counter64

Field Status : current
Description : The number of created TCP full cone session for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.21

Field Name : axIpNatDsliteStatExtendedUserQuotaExceeded
Field Type : Counter64
Field Status : current
Description : The number of exceeded extend user quota for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.20

Field Name : axIpNatDsliteStatExtendedUserQuotaMatched
Field Type : Counter64
Field Status : current
Description : The number of Extended user quota matched for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.19

Field Name : axIpNatDsliteStatIcmpUserQuotaExceed
Field Type : Counter64
Field Status : current
Description : The total ICMP ports allocted for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.18

Field Name : axIpNatDsliteStatUdpUserQuotaExceed
Field Type : Counter64
Field Status : current
Description : The number of exceeding UDP user quota for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.17

Field Name : axIpNatDsliteStatTcpUserQuotaExceed
Field Type : Counter64
Field Status : current
Description : The number of exceeding TCP user quota for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.16

Field Name : axIpNatDsliteStatNewUserResourceUnAvail
Field Type : Counter64
Field Status : current
Description : The number of unavailable new user resource for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.15

Field Name : axIpNatDsliteStatIcmpNatPortUnavail
Field Type : Counter64
Field Status : current
Description : The number of unavailable ICM NAT ports for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.14

Field Name : axIpNatDsliteStatUdpNatPortUnAvail
Field Type : Counter64
Field Status : current
Description : The number of unavailable UDP NAT ports for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.13

Field Name : axIpNatDsliteStatTcpNatPortUnAvail
Field Type : Counter64
Field Status : current
Description : The number of unavailable TCP NAT ports DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.12

Field Name : axIpNatDsliteUserQuotaCreateFailed
Field Type : Counter64
Field Status : current
Description : The number of user quota creation failed for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.11

Field Name : axIpNatDsliteUserQuotaFreed
Field Type : Counter64
Field Status : current
Description : The number of user quota freed for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.10

Field Name : axIpNatDsliteUserQuotaCreated
Field Type : Counter64
Field Status : current
Description : The number of user quota created for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.9

Field Name : axIpNatDsliteStatDataSessionFreed
Field Type : Counter64
Field Status : current
Description : The number of session freed for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.8

Field Name : axIpNatDsliteStatDataSessionCreated
Field Type : Counter64
Field Status : current
Description : The number of session created for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.7

Field Name : axIpNatDsliteStatTotalIcmpPortFreed
Field Type : Counter64
Field Status : current
Description : The total ICMP ports freed for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.6

Field Name : axIpNatDsliteStatTotalIcmpPortAlloc
Field Type : Counter64
Field Status : current
Description : The total ICMP ports allocted for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.5

Field Name : axIpNatDsliteStatTotalUdpPortFreed
Field Type : Counter64
Field Status : current
Description : The total UDP ports allocted for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.4

Field Name : axIpNatDsliteStatTotalUdpPortAlloc
Field Type : Counter64
Field Status : current
Description : The total UDP ports allocted for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.3

Field Name : axIpNatDsliteStatTotalTcpPortFreed
Field Type : Counter64
Field Status : current
Description : The total TCP ports freed for the DsLite.

OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.2

Field Name : axIpNatDsliteStatTotalTcpPortAlloc
Field Type : Counter64
Field Status : current
Description : The total TCP ports allocted for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.1

Field Name : axIpNatNat64StatNoRadiusProfileMatch
Field Type : Counter64
Field Status : current
Description : The number of no radius profile match.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.48

Field Name : axIpNatNat64StatHANatPoolUnusable
Field Type : Counter64
Field Status : current
Description : The number of HA nat pool unusable.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.47

Field Name : axIpNatNat64StatNatPoolUnusable
Field Type : Counter64
Field Status : current
Description : The number of nat pool unusable.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.46

Field Name : axIpNatNat64StatUdpPortOverloadingSessionFreed
Field Type : Counter64
Field Status : current
Description : The number of UDP port overloading session Freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.45

Field Name : axIpNatNat64StatTcpPortOverloadingSessionFreed
Field Type : Counter64
Field Status : current
Description : The number of TCP port overloading session Freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.44

Field Name : axIpNatNat64StatUdpPortOverloadingSessionCreated
Field Type : Counter64
Field Status : current
Description : The number of UDP port overloading session created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.43

Field Name : axIpNatNat64StatTcpPortOverloadingSessionCreated
Field Type : Counter64
Field Status : current
Description : The number of TCP port overloading session created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.42

Field Name : axIpNatNat64StatUdpPortOverloaded
Field Type : Counter64
Field Status : current
Description : The number of UDP port overloaded.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.41

Field Name : axIpNatNat64StatTcpPortOverloaded
Field Type : Counter64

Field Status : current
Description : The number of TCP port overloaded.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.40

Field Name : axIpNatNat64StatEndPointIndependentFilteringInboundLimitExceeded
Field Type : Counter64
Field Status : current
Description : The number of endpoint independent filtering inbound limit exceeded.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.39

Field Name : axIpNatNat64StatConnRateUserQuotaExceeded
Field Type : Counter64
Field Status : current
Description : The number of connection rate user-quota exceeded.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.38

Field Name : axIpNatNat64StatDataSessionUserQuotaExceeded
Field Type : Counter64
Field Status : current
Description : The number of data session user-quota exceeded.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.37

Field Name : axIpNatNat64StatNatPoolMismatchDrop
Field Type : Counter64
Field Status : current
Description : The number of nat pool mismatch drop for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.36

Field Name : axIpNatNat64StatNoClassListMatch
Field Type : Counter64
Field Status : current
Description : The number of no class list match for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.35

Field Name : axIpNatNat64StatLsnLidPassThrough
Field Type : Counter64
Field Status : current
Description : The number of pass through of lsn lid for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.34

Field Name : axIpNatNat64StatLsnLidDrop
Field Type : Counter64
Field Status : current
Description : The number of drop of lsn lid for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.33

Field Name : axIpNatNat64StatSourceAddrPrefixMatchDrop
Field Type : Counter64
Field Status : current
Description : The number of drop of source address prefix match for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.32

Field Name : axIpNatNat64StatLayer3ForwardPackets
Field Type : Counter64
Field Status : current
Description : The number of packets NAT64 layer 3 forwarded.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.31

Field Name : axIpNatNat64StatEndpointDependentFilterDrop
Field Type : Counter64
Field Status : current
Description : The number of endpoint independent filtering drop for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.30

Field Name : axIpNatNat64StatEndpointIndependentFilterMatched
Field Type : Counter64
Field Status : current
Description : The number of endpoint indenpendent filtering matched for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.29

Field Name : axIpNatNat64StatEndpointIndependentMapMatched
Field Type : Counter64
Field Status : current
Description : The number of endpoint independent mapping for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.28

Field Name : axIpNatNat64StatSelfHairpinDrop
Field Type : Counter64
Field Status : current
Description : The number of self hairpin drop for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.27

Field Name : axIpNatNat64StatHairpinSessionCreated
Field Type : Counter64
Field Status : current
Description : The number of created hairpin session for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.26

Field Name : axIpNatNat64StatFullConeSessionFailed
Field Type : Counter64
Field Status : current
Description : The number of failed full cone session for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.25

Field Name : axIpNatNat64StatUdpFullConeSessionFreed
Field Type : Counter64
Field Status : current
Description : The total ICMP ports allocted for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.24

Field Name : axIpNatNat64StatUdpFullConeSessionCreated
Field Type : Counter64
Field Status : current
Description : The number of created UDP full cone session for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.23

Field Name : axIpNatNat64StatTcpFullConeSessionFreed
Field Type : Counter64
Field Status : current
Description : The number of freed TCP full cone session for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.22

Field Name : axIpNatNat64StatTcpFullConeSessionCreated
Field Type : Counter64
Field Status : current
Description : The number of created TCP full cone session for the NAT64.

OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.21

Field Name : axIpNatNat64StatExtendedUserQuotaExceeded
Field Type : Counter64
Field Status : current
Description : The number of exceeded extend user quota for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.20

Field Name : axIpNatNat64StatExtendedUserQuotaMatched
Field Type : Counter64
Field Status : current
Description : The number of Extended user quota matched for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.19

Field Name : axIpNatNat64StatIcmpUserQuotaExceed
Field Type : Counter64
Field Status : current
Description : The total ICMP ports allocted for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.18

Field Name : axIpNatNat64StatUdpUserQuotaExceed
Field Type : Counter64
Field Status : current
Description : The number of exceeding UDP user quota for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.17

Field Name : axIpNatNat64StatTcpUserQuotaExceed
Field Type : Counter64
Field Status : current
Description : The number of exceeding TCP user quota for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.16

Field Name : axIpNatNat64StatNewUserResourceUnAvail
Field Type : Counter64
Field Status : current
Description : The number of unavailable new user resource for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.15

Field Name : axIpNatNat64StatIcmpNatPortUnavail
Field Type : Counter64
Field Status : current
Description : The number of unavailable ICM NAT ports for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.14

Field Name : axIpNatNat64StatUdpNatPortUnAvail
Field Type : Counter64
Field Status : current
Description : The number of unavailable UDP NAT ports for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.13

Field Name : axIpNatNat64StatTcpNatPortUnAvail
Field Type : Counter64
Field Status : current
Description : The number of unavailable TCP NAT ports NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.12

Field Name : axIpNatNat64UserQuotaCreateFailed
Field Type : Counter64

Field Status : current
Description : The number of user quota creation failed for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.11

Field Name : axIpNatNat64UserQuotaFreed
Field Type : Counter64
Field Status : current
Description : The number of user quota freed for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.10

Field Name : axIpNatNat64UserQuotaCreated
Field Type : Counter64
Field Status : current
Description : The number of user quota created for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.9

Field Name : axIpNatNat64StatDataSessionFreed
Field Type : Counter64
Field Status : current
Description : The number of session freed for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.8

Field Name : axIpNatNat64StatDataSessionCreated
Field Type : Counter64
Field Status : current
Description : The number of session created for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.7

Field Name : axIpNatNat64StatTotalIcmpPortFreed
Field Type : Counter64
Field Status : current
Description : The total ICMP ports allocted for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.6

Field Name : axIpNatNat64StatTotalIcmpPortAlloc
Field Type : Counter64
Field Status : current
Description : The total ICMP ports allocted for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.5

Field Name : axIpNatNat64StatTotalUdpPortFreed
Field Type : Counter64
Field Status : current
Description : The total UDP ports allocted for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.4

Field Name : axIpNatNat64StatTotalUdpPortAlloc
Field Type : Counter64
Field Status : current
Description : The total UDP ports allocted for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.3

Field Name : axIpNatNat64StatTotalTcpPortFreed
Field Type : Counter64
Field Status : current
Description : The total TCP ports freed for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.2

Field Name : axIpNatNat64StatTotalTcpPortAlloc
Field Type : Counter64
Field Status : current
Description : The total TCP ports allocted for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.1

Field Name : axIpNatLsnPoolNameStatTable
Field Type : TABLE
Field Status : current
Description : A table has information of IP NAT Lsn Pool Statistics group by the pool name.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12

Field Name : axIpNatLsnPoolNameStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axIpNatLsnPoolNameStats Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1

Field Name : axIpNatLsnPoolNameStatTotalUsedIps
Field Type : Counter64
Field Status : current
Description : The number of ips used in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.25

Field Name : axIpNatLsnPoolNameStatTotalFreeIps
Field Type : Counter64
Field Status : current
Description : The number of free ips in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.24

Field Name : axIpNatLsnPoolNameStatTotalIps
Field Type : Counter64
Field Status : current
Description : The total number of ips in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.23

Field Name : axIpNatLsnPoolNameStatUdpHitFull
Field Type : Counter64
Field Status : current
Description : The number of times port limit reached for UDP port allocation in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.22

Field Name : axIpNatLsnPoolNameStatUdpPeak
Field Type : Counter64
Field Status : current
Description : The number of udp ports in the peak for the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.21

Field Name : axIpNatLsnPoolNameStatUdpReserved
Field Type : Counter64
Field Status : current
Description : The number reserved icmp ports in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.20

Field Name : axIpNatLsnPoolNameStatUdpTotal
Field Type : Counter64
Field Status : current

Description : The total number of icmp ports in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.19

Field Name : axIpNatLsnPoolNameStatUdpFreed
Field Type : Counter64
Field Status : current
Description : The number of port Udpicmp freed in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.18

Field Name : axIpNatLsnPoolNameStatUdpUsed
Field Type : Counter64
Field Status : current
Description : The number of port udp used in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.17

Field Name : axIpNatLsnPoolNameStatTcpHitFull
Field Type : Counter64
Field Status : current
Description : The number of times port limit reached for TCP port allocation in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.16

Field Name : axIpNatLsnPoolNameStatTcpPeak
Field Type : Counter64
Field Status : current
Description : The number of tcp ports in the peak for the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.15

Field Name : axIpNatLsnPoolNameStatTcpReserved
Field Type : Counter64
Field Status : current
Description : The number reserved tcp ports in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.14

Field Name : axIpNatLsnPoolNameStatTcpTotal
Field Type : Counter64
Field Status : current
Description : The total number of tcp ports in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.13

Field Name : axIpNatLsnPoolNameStatTcpFreed
Field Type : Counter64
Field Status : current
Description : The number of port tcp freed in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.12

Field Name : axIpNatLsnPoolNameStatTcpUsed
Field Type : Counter64
Field Status : current
Description : The number of port tcp used in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.11

Field Name : axIpNatLsnPoolNameStatIcmpHitFull
Field Type : Counter64
Field Status : current
Description : The number of times port limit reached for ICMP port allocation in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.10

Field Name : axIpNatLsnPoolNameStatIcmpPeak
Field Type : Counter64
Field Status : current
Description : The number of icmp ports in the peak for the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.9

Field Name : axIpNatLsnPoolNameStatIcmpTotal
Field Type : Counter64
Field Status : current
Description : The total number of icmp ports in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.7

Field Name : axIpNatLsnPoolNameStatIcmpFreed
Field Type : Counter64
Field Status : current
Description : The number of port icmp freed in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.6

Field Name : axIpNatLsnPoolNameStatIcmpUsed
Field Type : Counter64
Field Status : current
Description : The number of port icmp used in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.5

Field Name : axIpNatLsnPoolNameStatUsers
Field Type : Counter64
Field Status : current
Description : The number of users in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.4

Field Name : axIpNatLsnPoolNameEndAddress
Field Type : String
Field Status : current
Description : The pool end IP address.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.3

Field Name : axIpNatLsnPoolNameStatAddress
Field Type : String
Field Status : current
Description : The pool start IP address.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.2

Field Name : axIpNatLsnPoolNameStatPoolName
Field Type : String
Field Status : current
Description : The name of the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.1

Field Name : axIpNatLsnPoolStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axIpNatLsnPoolStats Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1

Field Name : axIpNatLsnPoolStatUdpHitFull
Field Type : Counter64
Field Status : current
Description : The number of times port limit reached for UDP port allocation in the pool.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.21

Field Name : axIpNatLsnPoolStatUdpPeak
Field Type : Counter64
Field Status : current
Description : The number of udp ports in the peak for the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.20

Field Name : axIpNatLsnPoolStatUdpReserved
Field Type : Counter64
Field Status : current
Description : The number reserved icmp ports in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.19

Field Name : axIpNatLsnPoolStatUdpTotal
Field Type : Counter64
Field Status : current
Description : The total number of icmp ports in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.18

Field Name : axIpNatLsnPoolStatUdpFreed
Field Type : Counter64
Field Status : current
Description : The number of port Udpicmp freed in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.17

Field Name : axIpNatLsnPoolStatUdpUsed
Field Type : Counter64
Field Status : current
Description : The number of port udp used in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.16

Field Name : axIpNatLsnPoolStatTcpHitFull
Field Type : Counter64
Field Status : current
Description : The number of times port limit reached for TCP port allocation in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.15

Field Name : axIpNatLsnPoolStatTcpPeak
Field Type : Counter64
Field Status : current
Description : The number of tcp ports in the peak for the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.14

Field Name : axIpNatLsnPoolStatTcpReserved
Field Type : Counter64
Field Status : current
Description : The number reserved tcp ports in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.13

Field Name : axIpNatLsnPoolStatTcpTotal
Field Type : Counter64
Field Status : current
Description : The total number of tcp ports in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.12

Field Name : axIpNatLsnPoolStatTcpFreed
Field Type : Counter64

Field Status : current
Description : The number of port tcp freed in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.11

Field Name : axIpNatLsnPoolStatTcpUsed
Field Type : Counter64
Field Status : current
Description : The number of port tcp used in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.10

Field Name : axIpNatLsnPoolStatIcmpHitFull
Field Type : Counter64
Field Status : current
Description : The number of times port limit reached for ICMP port allocation in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.9

Field Name : axIpNatLsnPoolStatIcmpPeak
Field Type : Counter64
Field Status : current
Description : The number of icmp ports in the peak for the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.8

Field Name : axIpNatLsnPoolStatIcmpReserved
Field Type : Counter64
Field Status : current
Description : The number reserved icmp ports in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.7

Field Name : axIpNatLsnPoolStatIcmpTotal
Field Type : Counter64
Field Status : current
Description : The total number of icmp ports in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.6

Field Name : axIpNatLsnPoolStatIcmpFreed
Field Type : Counter64
Field Status : current
Description : The number of port icmp freed in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.5

Field Name : axIpNatLsnPoolStatIcmpUsed
Field Type : Counter64
Field Status : current
Description : The number of port icmp used in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.4

Field Name : axIpNatLsnPoolStatUsers
Field Type : Counter64
Field Status : current
Description : The number of users in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.3

Field Name : axIpNatLsnPoolStatAddress
Field Type : String
Field Status : current
Description : The IP address of the server.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.2

Field Name : axIpNatLsnPoolStatPoolName
Field Type : String
Field Status : current
Description : The name of the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.1

Field Name : axIpNatLsnPoolGroupTable
Field Type : TABLE
Field Status : current
Description : Table has information of IP NAT Lsn Pool group statistics indexed by the pool group name.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2

Field Name : axIpNatLsnPoolGroupCount
Field Type : INTEGER
Field Status : current
Description : The number of pool group in the system.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.1

Field Name : axIpNatLsnPoolGroupEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axIpNatLsnPoolGroup Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1

Field Name : axIpNatLsnPoolGroupFreedIp
Field Type : Counter64
Field Status : current
Description : The number of ip freed in the pool group.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.23

Field Name : axIpNatLsnPoolGroupUsedIp
Field Type : Counter64
Field Status : current
Description : The number of IP addressed used in the pool group.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.22

Field Name : axIpNatLsnPoolGroupTotalIp
Field Type : Counter64
Field Status : current
Description : Total number of IP addressed in the pool group.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.21

Field Name : axIpNatLsnPoolGroupUdpHitFull
Field Type : Counter64
Field Status : current
Description : The number of times port limit reached for UDP port allocation in the pool group.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.20

Field Name : axIpNatLsnPoolGroupUdpPeak
Field Type : Counter64
Field Status : current
Description : The peak number of UDP ports for the pool group.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.19

Field Name : axIpNatLsnPoolGroupUdpReserved

Field Type : Counter64
Field Status : current
Description : The number of reserved UDP ports in the pool group.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.18

Field Name : axIpNatLsnPoolGroupUdpTotal
Field Type : Counter64
Field Status : current
Description : The total number of UDP ports in the pool group.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.17

Field Name : axIpNatLsnPoolGroupUdpFreed
Field Type : Counter64
Field Status : current
Description : The number of UDP ports freed in the pool group.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.16

Field Name : axIpNatLsnPoolGroupUdpUsed
Field Type : Counter64
Field Status : current
Description : The number of UDP ports used in the pool group.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.15

Field Name : axIpNatLsnPoolGroupTcpHitFull
Field Type : Counter64
Field Status : current
Description : The number of times port limit reached for TCP port allocation in the pool group.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.14

Field Name : axIpNatLsnPoolGroupTcpPeak
Field Type : Counter64
Field Status : current
Description : The peak number of TCP ports for the pool group.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.13

Field Name : axIpNatLsnPoolGroupTcpReserved
Field Type : Counter64
Field Status : current
Description : The number of reserved TCP ports in the pool group.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.12

Field Name : axIpNatLsnPoolGroupTcpTotal
Field Type : Counter64
Field Status : current
Description : The total number of tcp ports in the pool group.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.11

Field Name : axIpNatLsnPoolGroupTcpFreed
Field Type : Counter64
Field Status : current
Description : The number of TCP ports freed in the pool group.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.10

Field Name : axIpNatLsnPoolGroupTcpUsed
Field Type : Counter64
Field Status : current
Description : The number of TCP ports used in the pool group.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.9

Field Name : axIpNatLsnPoolGroupIcmpHitFull
Field Type : Counter64
Field Status : current
Description : The number of times port limit reached for ICMP port allocation in the pool group.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.8

Field Name : axIpNatLsnPoolGroupIcmpPeak
Field Type : Counter64
Field Status : current
Description : The peak number of ICMP ports for the pool group.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.7

Field Name : axIpNatLsnPoolGroupIcmpReserved
Field Type : Counter64
Field Status : current
Description : The number reserved ICMP ports in the pool group.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.6

Field Name : axIpNatLsnPoolGroupIcmpTotal
Field Type : Counter64
Field Status : current
Description : The total number of ICMP ports in the pool group.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.5

Field Name : axIpNatLsnPoolGroupIcmpFreed
Field Type : Counter64
Field Status : current
Description : The number of ICMP ports freed in the pool group.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.4

Field Name : axIpNatLsnPoolGroupIcmpUsed
Field Type : Counter64
Field Status : current
Description : The number of port icmp used in the pool group.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.3

Field Name : axIpNatLsnPoolGroupUsers
Field Type : Counter64
Field Status : current
Description : The number of users in the pool group.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.2

Field Name : axIpNatLsnPoolGroupName
Field Type : String
Field Status : current
Description : The name of the pool group.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.1

Field Name : axIpNatLsnAlgSipStatMethodUnknown
Field Type : Counter64
Field Status : current
Description : The number of Sip method unknown on Ip Nat Lsn.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.13.15

Field Name : axIpNatLsnAlgSipStatMethodUpdate

Field Type : Counter64
Field Status : current
Description : The number of Sip method update on Ip Nat Lsn.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.13.14

Field Name : axIpNatLsnAlgSipStatMethodMessage
Field Type : Counter64
Field Status : current
Description : The number of Sip method message on Ip Nat Lsn.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.13.13

Field Name : axIpNatLsnAlgSipStatMethodRefer
Field Type : Counter64
Field Status : current
Description : The number of Sip method refer on Ip Nat Lsn.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.13.12

Field Name : axIpNatLsnAlgSipStatMethodInfo
Field Type : Counter64
Field Status : current
Description : The number of Sip method info on Ip Nat Lsn.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.13.11

Field Name : axIpNatLsnAlgSipStatMethodPublish
Field Type : Counter64
Field Status : current
Description : The number of Sip method publish on Ip Nat Lsn.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.13.10

Field Name : axIpNatLsnAlgSipStatMethodNotify
Field Type : Counter64
Field Status : current
Description : The number of Sip method notify on Ip Nat Lsn.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.13.9

Field Name : axIpNatLsnAlgSipStatMethodSubscribe
Field Type : Counter64
Field Status : current
Description : The number of Sip method subscribte on Ip Nat Lsn.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.13.8

Field Name : axIpNatLsnAlgSipStatMethodPrack
Field Type : Counter64
Field Status : current
Description : The number of Sip method Prack on Ip Nat Lsn.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.13.7

Field Name : axIpNatLsnAlgSipStatMethodOptions
Field Type : Counter64
Field Status : current
Description : The number of Sip method options on Ip Nat Lsn.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.13.6

Field Name : axIpNatLsnAlgSipStatMethodBye
Field Type : Counter64
Field Status : current
Description : The number of Sip method bye on Ip Nat Lsn.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.13.5

Field Name : axIpNatLsnAlgSipStatMethodCancel
Field Type : Counter64
Field Status : current
Description : The number of Sip method cancel on Ip Nat Lsn.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.13.4

Field Name : axIpNatLsnAlgSipStatMethodAck
Field Type : Counter64
Field Status : current
Description : The number of Sip method Ack on Ip Nat Lsn.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.13.3

Field Name : axIpNatLsnAlgSipStatMethodInvite
Field Type : Counter64
Field Status : current
Description : The number of Sip method invite on Ip Nat Lsn.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.13.2

Field Name : axIpNatLsnAlgSipStatMethodRegister
Field Type : Counter64
Field Status : current
Description : The number of Sip method register on Ip Nat Lsn.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.13.1

Field Name : axIpNatLsnTop5GlobalPoolIpAddrTotUdpPortTable
Field Type : TABLE
Field Status : current
Description : A table containing Top 5 global pool IPs and total number of UDP ports.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.12.1

Field Name : axIpNatLsnTop5GlobalPoolIpAddrTotUdpPortEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axIpNatLsnTop5GlobalPoolIpAddrTotUdpPorts Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.12.1.1

Field Name : axIpNatLsnTop5GlobalPoolIpAddrTotNumUdpPorts
Field Type : Integer32
Field Status : current
Description : The total number of UDP ports in the Top 5 global pool IPs entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.12.1.1.2

Field Name : axIpNatLsnTop5GlobalPoolIpAddrInUdp
Field Type : String
Field Status : current
Description : The global pool IP address in the Top 5 global pool IPs entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.12.1.1.1

Field Name : axIpNatLsnTop5GlobalPoolIpAddrTotTcpPortTable
Field Type : TABLE
Field Status : current
Description : A table containing Top 5 global pool IPs and total number of TCP ports.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.11.1

Field Name : axIpNatLsnTop5GlobalPoolIpAddrTotTcpPortEntry
Field Type : CounterBasedGauge64
Field Status : current

Description : Columns in the axIpNatLsnTop5GlobalPoolIpAddrTotTcpPorts Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.11.1.1

Field Name : axIpNatLsnTop5GlobalPoolIpAddrTotNumTcpPorts
Field Type : Integer32
Field Status : current
Description : The total number of TCP ports in the Top 5 global pool IPs entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.11.1.1.2

Field Name : axIpNatLsnTop5GlobalPoolIpAddrInTcp
Field Type : String
Field Status : current
Description : The global pool IP address in the Top 5 global pool IPs entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.11.1.1.1

Field Name : axIpNatLsnTop5GlobalPoolIpAddrTotUserTable
Field Type : TABLE
Field Status : current
Description : A table containing Top 5 global pool IPs and total number of users.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.10.1

Field Name : axIpNatLsnTop5GlobalPoolIpAddrTotUserEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axIpNatLsnTop5GlobalPoolIpAddrTotUsers Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.10.1.1

Field Name : axIpNatLsnTop5GlobalPoolIpAddrTotNumUsers
Field Type : Integer32
Field Status : current
Description : The total number of users in the Top 5 global pool IPs entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.10.1.1.2

Field Name : axIpNatLsnTop5GlobalPoolIpAddr
Field Type : String
Field Status : current
Description : The global pool IP address in the Top 5 global pool IPs entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.10.1.1.1

Field Name : axIpNatLsnTop5UserPrivateIpAddrTotIcmpSessionTable
Field Type : TABLE
Field Status : current
Description : A table containing Top 5 users private IPs and total number of sessions.
: To monitor users who use most of resources: pick up global pool IP which
: ports are most used total of TCP/UDP/ICMP sessions;
: then, find out the top 5 users who use the global pool most used total of ICMP sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.9.1

Field Name : axIpNatLsnTop5UserPrivateIpAddrTotIcmpSessionEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axIpNatLsnTop5UserPrivateIpAddrTotIcmpSessions Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.9.1.1

Field Name : axIpNatLsnTop5UserPrivateIpAddrGlobalIpAddrInIcmp
Field Type : String
Field Status : current
Description : The global IP address in the Top 5 user entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.9.1.1.3

Field Name : axIpNatLsnTop5UserPrivateIpAddrTotNumIcmpSessions
Field Type : Integer32
Field Status : current
Description : The total number of ICMP sessions in the Top 5 user entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.9.1.1.2

Field Name : axIpNatLsnTop5UserPrivateIpAddrInIcmp
Field Type : String
Field Status : current
Description : The private IP address in the Top 5 user entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.9.1.1.1

Field Name : axIpNatLsnTop5UserPrivateIpAddrTotUdpSessionTable
Field Type : TABLE
Field Status : current
Description : A table containing Top 5 users private IPs and total number of sessions.
: To monitor users who use most of resources: pick up global pool IP which
: ports are most used total of TCP/UDP/ICMP sessions;
: then, find out the top 5 users who use the global pool most used total of UDP sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.8.1

Field Name : axIpNatLsnTop5UserPrivateIpAddrTotUdpSessionEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axIpNatLsnTop5UserPrivateIpAddrTotUdpSessions Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.8.1.1

Field Name : axIpNatLsnTop5UserPrivateIpAddrGlobalIpAddrInUdp
Field Type : String
Field Status : current
Description : The global IP address in the Top 5 user entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.8.1.1.3

Field Name : axIpNatLsnTop5UserPrivateIpAddrTotNumUdpSessions
Field Type : Integer32
Field Status : current
Description : The total number of UDP sessions in the Top 5 user entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.8.1.1.2

Field Name : axIpNatLsnTop5UserPrivateIpAddrInUdp
Field Type : String
Field Status : current
Description : The private IP address in the Top 5 user entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.8.1.1.1

Field Name : axIpNatLsnTop5UserPrivateIpAddrTotTcpSessionTable
Field Type : TABLE
Field Status : current
Description : A table containing Top 5 users private IPs and total number of sessions.
: To monitor users who use most of resources: pick up global pool IP which
: ports are most used total of TCP/UDP/ICMP sessions;
: then, find out the top 5 users who use the global pool most used total of TCP sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.7.1

Field Name : axIpNatLsnTop5UserPrivateIpAddrTotTcpSessionEntry
Field Type : CounterBasedGauge64

Field Status : current
Description : Columns in the axIpNatLsnTop5UserPrivateIpAddrTotTcpSessions Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.7.1.1

Field Name : axIpNatLsnTop5UserPrivateIpAddrGlobalIpAddrInTcp
Field Type : String
Field Status : current
Description : The global IP address in the Top 5 user entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.7.1.1.3

Field Name : axIpNatLsnTop5UserPrivateIpAddrTotNumTcpSessions
Field Type : Integer32
Field Status : current
Description : The total number of TCP sessions in the Top 5 user entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.7.1.1.2

Field Name : axIpNatLsnTop5UserPrivateIpAddrInTcp
Field Type : String
Field Status : current
Description : The private IP address in the Top 5 user entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.7.1.1.1

Field Name : axIpNatLsnTop5UserPrivateIpAddrTotSessionTable
Field Type : TABLE
Field Status : current
Description : A table containing Top 5 users private IPs and total number of sessions.
: To monitor users who use most of resources: pick up global pool IP which
: ports are most used total of TCP/UDP/ICMP sessions;
: then, find out the top 5 users who use the global pool most used total of TCP/UDP/ICMP sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.6.1

Field Name : axIpNatLsnTop5UserPrivateIpAddrTotSessionEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axIpNatLsnTop5UserPrivateIpAddrTotSessions Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.6.1.1

Field Name : axIpNatLsnTop5UserPrivateIpAddrGlobalIpAddr
Field Type : String
Field Status : current
Description : The global IP address in the Top 5 user entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.6.1.1.3

Field Name : axIpNatLsnTop5UserPrivateIpAddrTotNumSessions
Field Type : Integer32
Field Status : current
Description : The total number of TCP/UDP/ICMP sessions in the Top 5 user entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.6.1.1.2

Field Name : axIpNatLsnTop5UserPrivateIpAddr
Field Type : String
Field Status : current
Description : The private IP address in the Top 5 user entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.6.1.1.1

Field Name : axIpNatLsnTop5PrivateIpAddrTotIcmpPortTable
Field Type : TABLE
Field Status : current

Description : A table containing Top 5 private IPs and total number of ICMP ports.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.5.1

Field Name : axIpNatLsnTop5PrivateIpAddrTotIcmpPortEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axIpNatLsnTop5PrivateIpAddrTotIcmpPorts Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.5.1.1

Field Name : axIpNatLsnTop5PrivateIpAddrGlobalIpAddrInIcmpPort
Field Type : String
Field Status : current
Description : The global IP address in the Top 5 private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.5.1.1.3

Field Name : axIpNatLsnTop5PrivateIpAddrTotNumIcmpPorts
Field Type : Integer32
Field Status : current
Description : The total number of ICMP sessions in the Top 5 private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.5.1.1.2

Field Name : axIpNatLsnTop5PrivateIpAddrInIcmpPort
Field Type : String
Field Status : current
Description : The private IP address in the Top 5 private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.5.1.1.1

Field Name : axIpNatLsnTop5PrivateIpAddrTotUdpPortTable
Field Type : TABLE
Field Status : current
Description : A table containing Top 5 private IPs and total number of UDP ports.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.4.1

Field Name : axIpNatLsnTop5PrivateIpAddrTotUdpPortEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axIpNatLsnTop5PrivateIpAddrTotUdpPorts Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.4.1.1

Field Name : axIpNatLsnTop5PrivateIpAddrGlobalIpAddrInUdpPort
Field Type : String
Field Status : current
Description : The global IP address in the Top 5 private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.4.1.1.3

Field Name : axIpNatLsnTop5PrivateIpAddrTotNumUdpPorts
Field Type : Integer32
Field Status : current
Description : The total number of UDP sessions in the Top 5 private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.4.1.1.2

Field Name : axIpNatLsnTop5PrivateIpAddrInUdpPort
Field Type : String
Field Status : current
Description : The private IP address in the Top 5 private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.4.1.1.1

Field Name : axIpNatLsnTop5PrivateIpAddrTotTcpPortTable

Field Type : TABLE
Field Status : current
Description : A table containing Top 5 private IPs and total number of TCP ports.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.3.1

Field Name : axIpNatLsnTop5PrivateIpAddrTotTcpPortEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axIpNatLsnTop5PrivateIpAddrTotTcpPorts Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.3.1.1

Field Name : axIpNatLsnTop5PrivateIpAddrGlobalIpAddrInTcpPort
Field Type : String
Field Status : current
Description : The global IP address in the Top 5 private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.3.1.1.3

Field Name : axIpNatLsnTop5PrivateIpAddrTotNumTcpPorts
Field Type : Integer32
Field Status : current
Description : The total number of TCP sessions in the Top 5 private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.3.1.1.2

Field Name : axIpNatLsnTop5PrivateIpAddrInTcpPort
Field Type : String
Field Status : current
Description : The private IP address in the Top 5 private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.3.1.1.1

Field Name : axIpNatLsnTop5PrivateIpAddrTotSessionTable
Field Type : TABLE
Field Status : current
Description : A table containing Top 5 private IPs and total number of sessions(ports).
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.2.1

Field Name : axIpNatLsnTop5PrivateIpAddrTotSessionEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axIpNatLsnTop5PrivateIpAddrTotSessions Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.2.1.1

Field Name : axIpNatLsnTop5PrivateIpAddrGlobalIpAddr
Field Type : String
Field Status : current
Description : The global IP address in the Top 5 private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.2.1.1.3

Field Name : axIpNatLsnTop5PrivateIpAddrTotNumSessions
Field Type : Integer32
Field Status : current
Description : The total number of sessions in the Top 5 private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.2.1.1.2

Field Name : axIpNatLsnTop5PrivateIpAddr
Field Type : String
Field Status : current
Description : The private IP address in the Top 5 private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.2.1.1.1

Field Name : axIpNatLsnSessionLsnCps
Field Type : Counter64
Field Status : current
Description : The LSN CPS.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.5.5

Field Name : axIpNatLsnSessionSmpSessionsFree
Field Type : Counter64
Field Status : current
Description : The number of SMP sessions free.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.5.4

Field Name : axIpNatLsnSessionSmpSessionsUsed
Field Type : Counter64
Field Status : current
Description : The number of SMP sessions used.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.5.3

Field Name : axIpNatLsnSessionDataSessionsFree
Field Type : Counter64
Field Status : current
Description : The number of data sessions free.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.5.2

Field Name : axIpNatLsnSessionDataSessionsUsed
Field Type : Counter64
Field Status : current
Description : The number of data sessions used.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.5.1

Field Name : axIpNatLsnTrafficNewUserResourceUnavailable64Gauge
Field Type : Counter64
Field Status : current
Description : The total number of NAT resource unavailable for new users.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.32

Field Name : axIpNatLsnTrafficNatPortUnavailable64Gauge
Field Type : Counter64
Field Status : current
Description : The total number of NAT port unavailable.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.31

Field Name : axIpNatLsnTrafficExtendedUserQuotasExceeded64Gauge
Field Type : Counter64
Field Status : current
Description : The total number of extended user-quotas exceeded.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.30

Field Name : axIpNatLsnTrafficExtendedUserQuotasMatch64Gauge
Field Type : Counter64
Field Status : current
Description : The total number of extended user-quotas matches.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.29

Field Name : axIpNatLsnTrafficTcpUserQuotasExceeded64Gauge
Field Type : Counter64
Field Status : current

Description : The total number of TCP user-quotas exceeded.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.28

Field Name : axIpNatLsnTrafficUdpUserQuotasExceeded64Gauge
Field Type : Counter64
Field Status : current
Description : The total number of UDP user-quotas exceeded.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.27

Field Name : axIpNatLsnTrafficIcmpUserQuotasExceeded64Gauge
Field Type : Counter64
Field Status : current
Description : The total number of ICMP user-quotas exceeded.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.26

Field Name : axIpNatLsnTrafficFailsInUserQuotasCreation64Gauge
Field Type : Counter64
Field Status : current
Description : The total number of user-quotas creation failure.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.25

Field Name : axIpNatLsnTrafficUserQuotasFreed64Gauge
Field Type : Counter64
Field Status : current
Description : The total number of user-quotas freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.24

Field Name : axIpNatLsnTrafficUserQuotasCreated64Gauge
Field Type : Counter64
Field Status : current
Description : The total number of user-quotas created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.23

Field Name : axIpNatLsnTrafficEndpointIndepFilterMatch64Gauge
Field Type : Counter64
Field Status : current
Description : The total number of endpoint independent filtering match.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.22

Field Name : axIpNatLsnTrafficEndpointIndepMapMatch64Gauge
Field Type : Counter64
Field Status : current
Description : The total number of endpoint independent mapping match.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.21

Field Name : axIpNatLsnTrafficHairpinSessionCreated64Gauge
Field Type : Counter64
Field Status : current
Description : The total number of hairpin session created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.20

Field Name : axIpNatLsnTrafficFailsInFullConeSessionCreation64Gauge
Field Type : Counter64
Field Status : current
Description : The total number of full-cone session creation failure.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.19

Field Name : axIpNatLsnTrafficFullConeSessionFreed64Gauge

Field Type : Counter64
Field Status : current
Description : The total number of full-cone session freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.18

Field Name : axIpNatLsnTrafficFullConeSessionCreated64Gauge
Field Type : Counter64
Field Status : current
Description : The total number of full-cone session created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.17

Field Name : axIpNatLsnTrafficNewUserResourceUnavailable
Field Type : Integer32
Field Status : current
Description : The total number of NAT resource unavailable for new users.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.16

Field Name : axIpNatLsnTrafficNatPortUnavailable
Field Type : Integer32
Field Status : current
Description : The total number of NAT port unavailable.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.15

Field Name : axIpNatLsnTrafficExtendedUserQuotasExceeded
Field Type : Integer32
Field Status : current
Description : The total number of extended user-quotas exceeded.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.14

Field Name : axIpNatLsnTrafficExtendedUserQuotasMatch
Field Type : Integer32
Field Status : current
Description : The total number of extended user-quotas matches.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.13

Field Name : axIpNatLsnTrafficTcpUserQuotasExceeded
Field Type : Integer32
Field Status : current
Description : The total number of TCP user-quotas exceeded.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.12

Field Name : axIpNatLsnTrafficUdpUserQuotasExceeded
Field Type : Integer32
Field Status : current
Description : The total number of UDP user-quotas exceeded.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.11

Field Name : axIpNatLsnTrafficIcmpUserQuotasExceeded
Field Type : Integer32
Field Status : current
Description : The total number of ICMP user-quotas exceeded.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.10

Field Name : axIpNatLsnTrafficFailsInUserQuotasCreation
Field Type : Integer32
Field Status : current
Description : The total number of user-quotas creation failure.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.9

Field Name : axIpNatLsnTrafficUserQuotasFreed
Field Type : Integer32
Field Status : current
Description : The total number of user-quotas freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.8

Field Name : axIpNatLsnTrafficUserQuotasCreated
Field Type : Integer32
Field Status : current
Description : The total number of user-quotas created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.7

Field Name : axIpNatLsnTrafficEndpointIndepFilterMatch
Field Type : Integer32
Field Status : current
Description : The total number of endpoint independent filtering match.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.6

Field Name : axIpNatLsnTrafficEndpointIndepMapMatch
Field Type : Integer32
Field Status : current
Description : The total number of endpoint independent mapping match.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.5

Field Name : axIpNatLsnTrafficHairpinSessionCreated
Field Type : Integer32
Field Status : current
Description : The total number of hairpin session created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.4

Field Name : axIpNatLsnTrafficFailsInFullConeSessionCreation
Field Type : Integer32
Field Status : current
Description : The total number of full-cone session creation failure.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.3

Field Name : axIpNatLsnTrafficFullConeSessionFreed
Field Type : Integer32
Field Status : current
Description : The total number of full-cone session freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.2

Field Name : axIpNatLsnTrafficFullConeSessionCreated
Field Type : Integer32
Field Status : current
Description : The total number of full-cone session created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.1

Field Name : axIpNatLsnTotalFullConeSessions
Field Type : Integer32
Field Status : current
Description : The total number of full cone sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.3

Field Name : axIpNatLsnTotalIpAddrTranslated
Field Type : Integer32
Field Status : current

Description : The total number of global (translated) Ip addresses which has at least 1 users.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.2

Field Name : axIpNatLsnTotalUserQuotaSessions
Field Type : Integer32
Field Status : current
Description : The total number of user-quota sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.1

Field Name : axIpNatLsnNatPortUdpNatPortFree
Field Type : Counter64
Field Status : current
Description : The number of UDP NAT ports free.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.6.4

Field Name : axIpNatLsnNatPortUdpNatPortUsed
Field Type : Counter64
Field Status : current
Description : The number of UDP NAT ports used.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.6.3

Field Name : axIpNatLsnNatPortTcpNatPortFree
Field Type : Counter64
Field Status : current
Description : The number of TCP NAT ports free.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.6.2

Field Name : axIpNatLsnNatPortTcpNatPortUsed
Field Type : Counter64
Field Status : current
Description : The number of TCP NAT ports used.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.6.1

Field Name : axIpNatLsnRadiusSecretNotConfigDropped
Field Type : Counter64
Field Status : current
Description : The non-configured secret dropped on lsn radius server.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.15.12

Field Name : axIpNatLsnHAStandbyDropped
Field Type : Counter64
Field Status : current
Description : The HA standby dropped on lsn radius server.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.15.11

Field Name : axIpNatLsnRadiusRequestTableFullDropped
Field Type : TABLE
Field Status : current
Description : The radius request table full dropped on lsn radius server.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.15.10

Field Name : axIpNatLsnRadiusRequestIgnored
Field Type : Counter64
Field Status : current
Description : The radius request ignored on lsn radius server.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.15.9

Field Name : axIpNatLsnRadiusRequestMalFormedDropped
Field Type : Counter64
Field Status : current
Description : The malformed radius request dropped on lsn radius server.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.15.8

Field Name : axIpNatLsnRadiusRequestNoKeyAttrDropped
Field Type : Counter64
Field Status : current
Description : The radius request no key attribute dropped on lsn radius server.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.15.7

Field Name : axIpNatLsnRadiusRequestBadSecretDropped
Field Type : Counter64
Field Status : current
Description : The radius request bad secret dropped on lsn radius server.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.15.6

Field Name : axIpNatLsnRadiusRequestReceived
Field Type : Counter64
Field Status : current
Description : The radius request received on lsn radius server.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.15.5

Field Name : axIpNatLsnCustAttrReceived
Field Type : Counter64
Field Status : current
Description : The custom attribute received on lsn radius server.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.15.4

Field Name : axIpNatLsnRadiusIMSIReceived
Field Type : Counter64
Field Status : current
Description : The IMSI received on lsn radius server.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.15.3

Field Name : axIpNatLsnRadiusIMEIReceived
Field Type : Counter64
Field Status : current
Description : The IMEI received on lsn radius server.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.15.2

Field Name : axIpNatLsnMSISDNReceived
Field Type : Counter64
Field Status : current
Description : The MSISDN received on lsn radius server.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.15.1

Field Name : axIpNatHttpRequestLogged
Field Type : Counter64
Field Status : current
Description : Total number of HTTP request logged.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.42

Field Name : axIpNatUdpPortOverloadingFreed
Field Type : Counter64
Field Status : current
Description : Total number of TCP port overloading freed.

OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.41

Field Name : axIpNatUdpPortOverloadingAllocated
Field Type : Counter64
Field Status : current
Description : Total number of UDP port overloading allocated.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.40

Field Name : axIpNatTcpPortOverloadingFreed
Field Type : Counter64
Field Status : current
Description : Total number of TCP port overloading freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.39

Field Name : axIpNatTcpPortOverloadingAllocated
Field Type : Counter64
Field Status : current
Description : Total number of TCP port overloading allocated.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.38

Field Name : axIpNatTcpConnectionLost
Field Type : Counter64
Field Status : current
Description : Total number of TCP connection lost.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.37

Field Name : axIpNatTcpConnectionEstablished
Field Type : Counter64
Field Status : current
Description : Total number of TCP connection established.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.36

Field Name : axIpNatLoggingLogPacketsDrop
Field Type : Counter64
Field Status : current
Description : Total number of log packets drop.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.35

Field Name : axIpNatLoggingFixedNatPeriodicConfigLogged
Field Type : Counter64
Field Status : current
Description : Total number of Fixed NAT periodic config logged.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.34

Field Name : axIpNatLoggingFixedNatPeriodicConfigLogsSent
Field Type : Counter64
Field Status : current
Description : Total number of Fixed NAT periodic config logs sent.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.33

Field Name : axIpNatLoggingFixedNatDisabledConfigLogsSent
Field Type : Counter64
Field Status : current
Description : Total number of Fixed NAT disabled config logs sent out.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.32

Field Name : axIpNatLoggingFixedNatDisabledConfigLogged
Field Type : Counter64

Field Status : current
Description : Total number of Fixed NAT disabled configs logged.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.31

Field Name : axIpNatLoggingFixedNatInsideUserPortMapping
Field Type : Counter64
Field Status : current
Description : Total number of Fixed NAT inside user port mappings.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.30

Field Name : axIpNatLoggingEspResourcetFreed
Field Type : Counter64
Field Status : current
Description : Total number of ESP resource freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.29

Field Name : axIpNatLoggingEspResourceAllocated
Field Type : Counter64
Field Status : current
Description : Total number of ESP resource allocated.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.28

Field Name : axIpNatLoggingEspSessDeleted
Field Type : Counter64
Field Status : current
Description : Total number of ESP sessions deleted.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.27

Field Name : axIpNatLoggingEspSessCreated
Field Type : Counter64
Field Status : current
Description : Total number of ESP sessions created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.26

Field Name : axIpNatLoggingGreResourcetFreed
Field Type : Counter64
Field Status : current
Description : Total number of GRE resource freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.25

Field Name : axIpNatLoggingGreResourceAllocated
Field Type : Counter64
Field Status : current
Description : Total number of GRE resource allocated.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.24

Field Name : axIpNatLoggingGreSessDeleted
Field Type : Counter64
Field Status : current
Description : Total number of GRE sessions deleted.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.23

Field Name : axIpNatLoggingGreSessCreated
Field Type : Counter64
Field Status : current
Description : Total number of GRE sessions created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.22

Field Name : axIpNatLoggingIcmpV6ResourcetFreed
Field Type : Counter64
Field Status : current
Description : Total number of ICMPv6 resource freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.21

Field Name : axIpNatLoggingIcmpV6ResourceAllocated
Field Type : Counter64
Field Status : current
Description : Total number of ICMPv6 resource allocated.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.20

Field Name : axIpNatLoggingIcmpV6SessDeleted
Field Type : Counter64
Field Status : current
Description : Total number of ICMPv6 sessions deleted.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.19

Field Name : axIpNatLoggingIcmpV6SessCreated
Field Type : Counter64
Field Status : current
Description : Total number of ICMPv6 sessions created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.18

Field Name : axIpNatLoggingIcmpResourcetFreed
Field Type : Counter64
Field Status : current
Description : Total number of ICMP resource freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.17

Field Name : axIpNatLoggingIcmpResourceAllocated
Field Type : Counter64
Field Status : current
Description : Total number of ICMP resource allocated.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.16

Field Name : axIpNatLoggingIcmpSessDeleted
Field Type : Counter64
Field Status : current
Description : Total number of ICMP sessions deleted.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.15

Field Name : axIpNatLoggingIcmpSessCreated
Field Type : Counter64
Field Status : current
Description : Total number of ICMP sessions created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.14

Field Name : axIpNatLoggingUdpPortBatchFreed
Field Type : Counter64
Field Status : current
Description : Total number of UDP ports batch-freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.13

Field Name : axIpNatLoggingUdpPortBatchAllocated
Field Type : Counter64
Field Status : current
Description : Total number of UDP ports batch-allocated.

OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.12

Field Name : axIpNatLoggingUdpPortFreed
Field Type : Counter64
Field Status : current
Description : Total number of UDP ports freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.11

Field Name : axIpNatLoggingUdpPortAllocated
Field Type : Counter64
Field Status : current
Description : Total number of UDP ports allocated.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.10

Field Name : axIpNatLoggingUdpSessDeleted
Field Type : Counter64
Field Status : current
Description : Total number of UDP sessions deleted.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.9

Field Name : axIpNatLoggingUdpSessCreated
Field Type : Counter64
Field Status : current
Description : Total number of UDP sessions created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.8

Field Name : axIpNatLoggingTcpPortBatchFreed
Field Type : Counter64
Field Status : current
Description : Total number of TCP ports batch-freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.7

Field Name : axIpNatLoggingTcpPortBatchAllocated
Field Type : Counter64
Field Status : current
Description : Total number of TCP ports batch-allocated.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.6

Field Name : axIpNatLoggingTcpPortFreed
Field Type : Counter64
Field Status : current
Description : Total number of TCP ports freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.5

Field Name : axIpNatLoggingTcpPortAllocated
Field Type : Counter64
Field Status : current
Description : Total number of TCP ports allocated.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.4

Field Name : axIpNatLoggingTcpSessDeleted
Field Type : Counter64
Field Status : current
Description : Total number of TCP sessions deleted.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.3

Field Name : axIpNatLoggingTcpSessCreated
Field Type : Counter64

Field Status : current
Description : Total number of TCP sessions created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.2

Field Name : axIpNatLoggingLogPktSent
Field Type : Counter64
Field Status : current
Description : Total number of logging packets sent out.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.1

Field Name : axIpNatPoolStatsTable
Field Type : TABLE
Field Status : current
Description : A table has information of IP NAT pool statistics.
OID : 1.3.6.1.4.1.22610.2.4.3.18.100.1

Field Name : axIpNatPoolStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axIpNatPoolStats Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.100.1.1

Field Name : axIpNatPoolFailed
Field Type : INTEGER
Field Status : current
Description : The total misses in the pool
OID : 1.3.6.1.4.1.22610.2.4.3.18.100.1.1.7

Field Name : axIpNatPoolTotalFree
Field Type : INTEGER
Field Status : current
Description : The total of free addresses in the pool
OID : 1.3.6.1.4.1.22610.2.4.3.18.100.1.1.6

Field Name : axIpNatPoolTotalUsed
Field Type : INTEGER
Field Status : current
Description : The total of used addresses in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.100.1.1.5

Field Name : axIpNatPoolPortUsage
Field Type : INTEGER
Field Status : current
Description : The total port usage in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.100.1.1.4

Field Name : axIpNatPoolEndAddress
Field Type : String
Field Status : current
Description : The IP NAT pool end address (IPv4 or IPv6)
OID : 1.3.6.1.4.1.22610.2.4.3.18.100.1.1.3

Field Name : axIpNatPoolStartAddress
Field Type : String
Field Status : current
Description : The IP NAT pool start address (IPv4 or IPv6)
OID : 1.3.6.1.4.1.22610.2.4.3.18.100.1.1.2

Field Name : axIpNatPoolName
Field Type : String
Field Status : current
Description : The IP NAT pool name
OID : 1.3.6.1.4.1.22610.2.4.3.18.100.1.1.1

Field Name : axIpNatStatsDynamicMappingEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axIpNatStatsDynamicMapping Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.3.1.1

Field Name : axIpNatStatsDynamicMappingEndAddressType
Field Type : EnumVal
Field Status : current
Description : The type of axIpNatStatsDynamicMappingEndAddress:
: unknown(0), ipv4(1), ipv6(2)...
OID : 1.3.6.1.4.1.22610.2.4.3.18.3.1.1.9

Field Name : axIpNatStatsDynamicMappingStartAddressType
Field Type : EnumVal
Field Status : current
Description : The type of axIpNatStatsDynamicMappingStartAddress:
: unknown(0), ipv4(1), ipv6(2)...
OID : 1.3.6.1.4.1.22610.2.4.3.18.3.1.1.8

Field Name : axIpNatStatsDynamicMappingMissAddresses
Field Type : INTEGER
Field Status : current
Description : The total misses in the pool
OID : 1.3.6.1.4.1.22610.2.4.3.18.3.1.1.7

Field Name : axIpNatStatsDynamicMappingAllocAddresses
Field Type : INTEGER
Field Status : current
Description : The total allocated addresses in the pool
OID : 1.3.6.1.4.1.22610.2.4.3.18.3.1.1.6

Field Name : axIpNatStatsDynamicMappingTotalAddresses
Field Type : INTEGER
Field Status : current
Description : The total addresses in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.3.1.1.5

Field Name : axIpNatStatsDynamicMappingEndAddress
Field Type : String
Field Status : current
Description : The end address of the pool
OID : 1.3.6.1.4.1.22610.2.4.3.18.3.1.1.4

Field Name : axIpNatStatsDynamicMappingStartAddress
Field Type : String
Field Status : current
Description : The start adddress of the pool
OID : 1.3.6.1.4.1.22610.2.4.3.18.3.1.1.3

Field Name : axIpNatStatsDynamicMappingPoolName
Field Type : String

Field Status : current
Description : The IP source NAT pool name
OID : 1.3.6.1.4.1.22610.2.4.3.18.3.1.1.2

Field Name : axIpNatStatsDynamicMappingAccessListID
Field Type : INTEGER
Field Status : current
Description : The access list id.
OID : 1.3.6.1.4.1.22610.2.4.3.18.3.1.1.1

Field Name : axIpNatStatsIntfInsideOutsideTable
Field Type : TABLE
Field Status : current
Description : A table has information of IP NAT interface inside/outside
OID : 1.3.6.1.4.1.22610.2.4.3.18.2.1

Field Name : axIpNatStatsIntfInsideOutsideEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axIpNatStatsIntfInsideOutside Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.2.1.1

Field Name : axIpNatStatsInsideOutsideIntfDirection
Field Type : EnumVal
Field Status : current
Description : The interface bind direction, inside or outside.
OID : 1.3.6.1.4.1.22610.2.4.3.18.2.1.1.3

Field Name : axIpNatStatsInsideOutsideIntfName
Field Type : String
Field Status : current
Description : The interface name, such as ethernet1, ethernet2, ve3, ...
OID : 1.3.6.1.4.1.22610.2.4.3.18.2.1.1.2

Field Name : axIpNatStatsInsideOutsideIntfIndex
Field Type : INTEGER
Field Status : current
Description : The index of the AxIpNatStatsIntfInsideOutside table.
OID : 1.3.6.1.4.1.22610.2.4.3.18.2.1.1.1

Field Name : axIpNatStatsGlobalMisses
Field Type : Counter64
Field Status : current
Description : Total misses in the IP source NAT
OID : 1.3.6.1.4.1.22610.2.4.3.18.1.2

Field Name : axIpNatStatsGlobalHits
Field Type : Counter64
Field Status : current
Description : Total hits in the IP source NAT.
OID : 1.3.6.1.4.1.22610.2.4.3.18.1.1

Field Name : axFixedNatTop5GlobalIpAddrTotUdpPortTable
Field Type : TABLE
Field Status : current
Description : A table containing Top 5 fixed nat private IPs and total number of udp(ports).
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.15.1

Field Name : axFixedNatTop5GlobalIpAddrTotUdpPortEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axFixedNatTop5GlobalIpAddrTotUdpPort Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.15.1.1

Field Name : axFixedNatTop5GlobalIpAddrTotNumInUdp
Field Type : Integer32
Field Status : current
Description : The total number of tcp ports in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.15.1.1.2

Field Name : axFixedNatTop5GlobalIpAddrInUdp
Field Type : String
Field Status : current
Description : The private IP address in the Top 5 fixed nat global IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.15.1.1.1

Field Name : axFixedNatTop5GlobalIpAddrTotTcpPortTable
Field Type : TABLE
Field Status : current
Description : A table containing Top 5 fixed nat private IPs and total number of tcp(ports).
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.14.1

Field Name : axFixedNatTop5GlobalIpAddrTotTcpPortEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axFixedNatTop5GlobalIpAddrTotTcpPort Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.14.1.1

Field Name : axFixedNatTop5GlobalIpAddrTotNumInTcp
Field Type : Integer32
Field Status : current
Description : The total number of tcp ports in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.14.1.1.2

Field Name : axFixedNatTop5GlobalIpAddrInTcp
Field Type : String
Field Status : current
Description : The private IP address in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.14.1.1.1

Field Name : axFixedNatTop5GlobalIpAddrTotUserTable
Field Type : TABLE
Field Status : current
Description : A table containing Top 5 fixed nat private IPs and total number of udp(ports).
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.13.1

Field Name : axFixedNatTop5GlobalIpAddrTotUserEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axFixedNatTop5GlobalIpAddrTotUser Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.13.1.1

Field Name : axFixedNatTop5GlobalIpAddrTotNum
Field Type : Integer32

Field Status : current
Description : The total number of tcp ports in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.13.1.1.2

Field Name : axFixedNatTop5GlobalIpAddrUser
Field Type : String
Field Status : current
Description : The private IP address in the Top 5 fixed nat global IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.13.1.1.1

Field Name : axFixedNatTop5UserPrivateIpAddrTotIcmpPortTable
Field Type : TABLE
Field Status : current
Description : A table containing Top 5 fixed nat user private IPs and total number of icmp(ports).
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.12.1

Field Name : axFixedNatTop5UserPrivateIpAddrTotIcmpPortEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axFixedNatTop5UserPrivateIpAddrTotIcmpPort Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.12.1.1

Field Name : axFixedNatTop5UserPrivateIpAddrGlobalIpAddrInIcmp
Field Type : String
Field Status : current
Description : The global IP address in the Top 5 fixed nat user private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.12.1.1.3

Field Name : axFixedNatTop5UserPrivateIpAddrTotNumInIcmp
Field Type : Integer32
Field Status : current
Description : The total number of icmp ports in the Top 5 fixed nat user private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.12.1.1.2

Field Name : axFixedNatTop5UserPrivateIpAddrInIcmp
Field Type : String
Field Status : current
Description : The private IP address in the Top 5 fixed nat user private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.12.1.1.1

Field Name : axFixedNatTop5UserPrivateIpAddrTotUdpPortTable
Field Type : TABLE
Field Status : current
Description : A table containing Top 5 fixed nat private IPs and total number of ucp(ports).
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.11.1

Field Name : axFixedNatTop5UserPrivateIpAddrTotUdpPortEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axFixedNatTop5UserPrivateIpAddrTotUdpPort Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.11.1.1

Field Name : axFixedNatTop5UserPrivateIpAddrGlobalIpAddrInUdp
Field Type : String
Field Status : current

Description : The global IP address in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.11.1.1.3

Field Name : axFixedNatTop5UserPrivateIpAddrTotNumInUdp
Field Type : Integer32
Field Status : current
Description : The total number of tcp ports in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.11.1.1.2

Field Name : axFixedNatTop5UserPrivateIpAddrInUdp
Field Type : String
Field Status : current
Description : The private IP address in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.11.1.1.1

Field Name : axFixedNatTop5UserPrivateIpAddrTotTcpPortTable
Field Type : TABLE
Field Status : current
Description : A table containing Top 5 fixed nat private IPs and total number of tcp(ports).
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.10.1

Field Name : axFixedNatTop5UserPrivateIpAddrTotTcpPortEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axFixedNatTop5UserPrivateIpAddrTotTcpPort Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.10.1.1

Field Name : axFixedNatTop5UserPrivateIpAddrGlobalIpAddrInTcp
Field Type : String
Field Status : current
Description : The global IP address in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.10.1.1.3

Field Name : axFixedNatTop5UserPrivateIpAddrTotNumInTcp
Field Type : Integer32
Field Status : current
Description : The total number of tcp ports in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.10.1.1.2

Field Name : axFixedNatTop5UserPrivateIpAddrInTcp
Field Type : String
Field Status : current
Description : The private IP address in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.10.1.1.1

Field Name : axFixedNatTop5UserPrivateIpAddrTotSessionTable
Field Type : TABLE
Field Status : current
Description : A table containing Top 5 fixed nat private IPs and total number of tcp(ports).
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.9.1

Field Name : axFixedNatTop5UserPrivateIpAddrTotSessionEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axFixedNatTop5UserPrivateIpAddrSession Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.9.1.1

Field Name : axFixedNatTop5UserPrivateIpAddrGlobalIpAddr
Field Type : String
Field Status : current
Description : The global IP address in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.9.1.1.3

Field Name : axFixedNatTop5UserPrivateIpAddrTotNumSession
Field Type : Integer32
Field Status : current
Description : The total number of tcp ports in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.9.1.1.2

Field Name : axFixedNatTop5UserPrivateIpAddr
Field Type : String
Field Status : current
Description : The private IP address in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.9.1.1.1

Field Name : axFixedNatTop5PrivateIpAddrTotIcmpPortTable
Field Type : TABLE
Field Status : current
Description : A table containing Top 5 fixed nat private IPs and total number of icmp(ports).
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.8.1

Field Name : axFixedNatTop5PrivateIpAddrTotIcmpPortEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axFixedNatTop5PrivateIpAddrTotIcmpPorts Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.8.1.1

Field Name : axFixedNatTop5PrivateIpAddrGlobalIpAddrInIcmpPort
Field Type : String
Field Status : current
Description : The global IP address in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.8.1.1.3

Field Name : axFixedNatTop5PrivateIpAddrTotNumInIcmpPort
Field Type : Integer32
Field Status : current
Description : The total number of tcp ports in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.8.1.1.2

Field Name : axFixedNatTop5PrivateIpAddrInIcmpPort
Field Type : String
Field Status : current
Description : The private IP address in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.8.1.1.1

Field Name : axFixedNatTop5PrivateIpAddrTotUdpPortTable
Field Type : TABLE
Field Status : current
Description : A table containing Top 5 fixed nat private IPs and total number of udp(ports).
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.7.1

Field Name : axFixedNatTop5PrivateIpAddrTotUdpPortEntry

Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axFixedNatTop5PrivateIpAddrTotUdpPorts Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.7.1.1

Field Name : axFixedNatTop5PrivateIpAddrGlobalIpAddrInUdpPort
Field Type : String
Field Status : current
Description : The global IP address in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.7.1.1.3

Field Name : axFixedNatTop5PrivateIpAddrTotNumInUdpPort
Field Type : Integer32
Field Status : current
Description : The total number of tcp ports in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.7.1.1.2

Field Name : axFixedNatTop5PrivateIpAddrInUdpPort
Field Type : String
Field Status : current
Description : The private IP address in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.7.1.1.1

Field Name : axFixedNatTop5PrivateIpAddrTotTcpPortTable
Field Type : TABLE
Field Status : current
Description : A table containing Top 5 fixed nat private IPs and total number of tcp(ports).
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.6.1

Field Name : axFixedNatTop5PrivateIpAddrTotTcpPortEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axFixedNatTop5PrivateIpAddrTotTcpPorts Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.6.1.1

Field Name : axFixedNatTop5PrivateIpAddrGlobalIpAddrInTcpPort
Field Type : String
Field Status : current
Description : The global IP address in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.6.1.1.3

Field Name : axFixedNatTop5PrivateIpAddrTotNumInTcpPort
Field Type : Integer32
Field Status : current
Description : The total number of tcp ports in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.6.1.1.2

Field Name : axFixedNatTop5PrivateIpAddrInTcpPort
Field Type : String
Field Status : current
Description : The private IP address in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.6.1.1.1

Field Name : axFixedNatTop5PrivateIpAddrTotSessionTable
Field Type : TABLE
Field Status : current

Description : A table containing Top 5 fixed nat private IPs and total number of sessions(ports).
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.5.1

Field Name : axFixedNatTop5PrivateIpAddrTotSessionEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axFixedNatTop5PrivateIpAddrTotSessions Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.5.1.1

Field Name : axFixedNatTop5PrivateIpAddrGlobalIpAddr
Field Type : String
Field Status : current
Description : The global IP address in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.5.1.1.3

Field Name : axFixedNatTop5PrivateIpAddrTotNumSessions
Field Type : Integer32
Field Status : current
Description : The total number of sessions in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.5.1.1.2

Field Name : axFixedNatTop5PrivateIpAddr
Field Type : String
Field Status : current
Description : The private IP address in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.5.1.1.1

Field Name : axFixedNatFullConeSessNat64Table
Field Type : TABLE
Field Status : current
Description : A table has information of fixed nat full-cone-session NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.3

Field Name : axFixedNatFullConeSessNat44Table
Field Type : TABLE
Field Status : current
Description : A table has information of fixed nat full-cone-session NAT44.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.2

Field Name : axFixedNatFullConeSessNat44Entry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axFixedNatFullConeSessNat44Table Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.2.1

Field Name : axFixedNatFullConeSessNat44PcpFlags
Field Type : EnumVal
Field Status : current
Description : The flag of pcp.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.2.1.8

Field Name : axFixedNatFullConeSessNat44Age
Field Type : INTEGER
Field Status : current
Description : The ages of the full cone session fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.2.1.7

Field Name : axFixedNatFullConeSessNat44CPU
Field Type : INTEGER
Field Status : current
Description : The CPU of the full cone session fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.2.1.6

Field Name : axFixedNatFullConeSessNat44EIF
Field Type : INTEGER
Field Status : current
Description : The EIF value of the full cone session fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.2.1.5

Field Name : axFixedNatFullConeSessNat44EIM
Field Type : INTEGER
Field Status : current
Description : The EIM value of the full cone session fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.2.1.4

Field Name : axFixedNatFullConeSessNat44ProtType
Field Type : EnumVal
Field Status : current
Description : The protocol type of fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.2.1.3

Field Name : axFixedNatFullConeSessNat44InsideUser
Field Type : String
Field Status : current
Description : The inside user address and port of the fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.2.1.2

Field Name : axFixedNatFullConeSessNat44NatIpAddress
Field Type : String
Field Status : current
Description : The nat ip address and port of the fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.2.1.1

Field Name : axFixedNatFullConeSessDsliteTable
Field Type : TABLE
Field Status : current
Description : A table has information of fixed nat full-cone-session ds-lite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.1

Field Name : axFixedNatFullConeSessDsliteEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axFixedNatFullConeSessDsliteTable Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.1.1

Field Name : axFixedNatFullConeSessDslitePcpFlags
Field Type : EnumVal
Field Status : current
Description : The flag of pcp.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.1.1.8

Field Name : axFixedNatFullConeSessDsliteAge
Field Type : INTEGER
Field Status : current
Description : The ages of the full cone session fixed nat.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.1.1.7

Field Name : axFixedNatFullConeSessDsliteCPU
Field Type : INTEGER
Field Status : current
Description : The CPU of the full cone session fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.1.1.6

Field Name : axFixedNatFullConeSessDsliteEIF
Field Type : INTEGER
Field Status : current
Description : The EIF value of the full cone session fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.1.1.5

Field Name : axFixedNatFullConeSessDsliteEIM
Field Type : INTEGER
Field Status : current
Description : The EIM value of the full cone session fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.1.1.4

Field Name : axFixedNatFullConeSessDsliteProtType
Field Type : EnumVal
Field Status : current
Description : The protocol type of fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.1.1.3

Field Name : axFixedNatFullConeSessDsliteInsideUser
Field Type : String
Field Status : current
Description : The inside user address and port of the fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.1.1.2

Field Name : axFixedNatFullConeSessDsliteNatIpAddress
Field Type : String
Field Status : current
Description : The nat ip address and port of the fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.1.1.1

Field Name : axFixedNatFullConeSessNat64Entry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axFixedNatFullConeSessNat64Table Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.3.1

Field Name : axFixedNatFullConeSessNat64PcpFlags
Field Type : EnumVal
Field Status : current
Description : The flag of pcp.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.3.1.8

Field Name : axFixedNatFullConeSessNat64Age
Field Type : INTEGER
Field Status : current
Description : The ages of the full cone session fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.3.1.7

Field Name : axFixedNatFullConeSessNat64CPU
Field Type : INTEGER

Field Status : current
Description : The CPU of the full cone session fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.3.1.6

Field Name : axFixedNatFullConeSessNat64EIF
Field Type : INTEGER
Field Status : current
Description : The EIF value of the full cone session fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.3.1.5

Field Name : axFixedNatFullConeSessNat64EIM
Field Type : INTEGER
Field Status : current
Description : The EIM value of the full cone session fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.3.1.4

Field Name : axFixedNatFullConeSessNat64ProtType
Field Type : EnumVal
Field Status : current
Description : The protocol type of fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.3.1.3

Field Name : axFixedNatFullConeSessNat64InsideUser
Field Type : String
Field Status : current
Description : The inside user address and port of the fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.3.1.2

Field Name : axFixedNatFullConeSessNat64NatIpAddress
Field Type : String
Field Status : current
Description : The nat ip address and port of the fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.3.1.1

Field Name : axFixedNatPortMappingPortTable
Field Type : TABLE
Field Status : current
Description : A table has information of the servers.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.3.1

Field Name : axFixedNatPortMappingPortEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axFixedNatPortMappingPortTable Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.3.1.1

Field Name : axFixedNatPortMappingPortIcmpEndPort
Field Type : INTEGER
Field Status : current
Description : The ICMP end port of the fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.3.1.1.9

Field Name : axFixedNatPortMappingPortIcmpBeginPort
Field Type : INTEGER
Field Status : current
Description : The ICMP end port of the fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.3.1.1.8

Field Name : axFixedNatPortMappingPortUdpEndPort
Field Type : INTEGER
Field Status : current
Description : The UDP end port of the fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.3.1.1.7

Field Name : axFixedNatPortMappingPortUdpBeginPort
Field Type : INTEGER
Field Status : current
Description : The UDP end port of the fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.3.1.1.6

Field Name : axFixedNatPortMappingPortTcpEndPort
Field Type : INTEGER
Field Status : current
Description : The TCP end port of the fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.3.1.1.5

Field Name : axFixedNatPortMappingPortTcpBeginPort
Field Type : INTEGER
Field Status : current
Description : The TCP begin port of the fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.3.1.1.4

Field Name : axFixedNatPortMappingPortInsideUserIpType
Field Type : EnumVal
Field Status : current
Description : The inside user address type of the fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.3.1.1.3

Field Name : axFixedNatPortMappingPortInsideUser
Field Type : String
Field Status : current
Description : The inside user address of the fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.3.1.1.2

Field Name : axFixedNatPortMappingPortNatIpAddress
Field Type : String
Field Status : current
Description : The nat ip address of the fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.3.1.1.1

Field Name : axFixedNatAlgSipMethodUnknown
Field Type : Counter64
Field Status : current
Description : The fixed nat alg sip method unknown.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.6.15

Field Name : axFixedNatAlgSipMethodUpdate
Field Type : Counter64
Field Status : current
Description : The fixed nat alg sip method update.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.6.14

Field Name : axFixedNatAlgSipMethodMessage
Field Type : Counter64
Field Status : current
Description : The fixed nat alg sip method message.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.6.13

Field Name : axFixedNatAlgSipMethodRefer
Field Type : Counter64
Field Status : current
Description : The fixed nat alg sip method Refer.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.6.12

Field Name : axFixedNatAlgSipMethodInfo
Field Type : Counter64
Field Status : current
Description : The fixed nat alg sip method information.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.6.11

Field Name : axFixedNatAlgSipMethodPublish
Field Type : Counter64
Field Status : current
Description : The fixed nat alg sip method publish.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.6.10

Field Name : axFixedNatAlgSipMethodNotify
Field Type : Counter64
Field Status : current
Description : The fixed nat alg sip method notify.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.6.9

Field Name : axFixedNatAlgSipMethodSubscribe
Field Type : Counter64
Field Status : current
Description : The fixed nat alg sip method subscribe.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.6.8

Field Name : axFixedNatAlgSipMethodPrack
Field Type : Counter64
Field Status : current
Description : The fixed nat alg sip method prack.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.6.7

Field Name : axFixedNatAlgSipMethodOptions
Field Type : Counter64
Field Status : current
Description : The fixed nat alg sip method options.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.6.6

Field Name : axFixedNatAlgSipMethodBye
Field Type : Counter64
Field Status : current
Description : The fixed nat alg sip method bye.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.6.5

Field Name : axFixedNatAlgSipMethodCancel
Field Type : Counter64
Field Status : current
Description : The fixed nat alg sip method cancel.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.6.4

Field Name : axFixedNatAlgSipMethodAck
Field Type : Counter64

Field Status : current
Description : The fixed nat alg sip method ack.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.6.3

Field Name : axFixedNatAlgSipMethodInvite
Field Type : Counter64
Field Status : current
Description : The fixed nat alg sip method invite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.6.2

Field Name : axFixedNatAlgSipMethodReg
Field Type : Counter64
Field Status : current
Description : The fixed nat alg sip method register.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.6.1

Field Name : axFixedNatAlgRtspDataSessionCreationFailed
Field Type : Counter64
Field Status : current
Description : The fixed nat alg rtsp data session creation failures.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.5.10

Field Name : axFixedNatAlgRtspDataSessionFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat alg rtsp data session freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.5.9

Field Name : axFixedNatAlgRtspDataSessionCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat alg rtsp data session created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.5.8

Field Name : axFixedNatAlgRtspSrvRepWithUnknownClientPorts
Field Type : Counter64
Field Status : current
Description : The fixed nat alg rtsp server replies with unknown client ports.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.5.7

Field Name : axFixedNatAlgRtspStreamClientPortAllocationFailed
Field Type : Counter64
Field Status : current
Description : The fixed nat alg rtsp stream client port allocation failures.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.5.6

Field Name : axFixedNatAlgRtspStreamClientPortFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat alg rtsp stream client ports freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.5.5

Field Name : axFixedNatAlgRtspStreamClientPortAllocated
Field Type : Counter64
Field Status : current
Description : The fixed nat alg rtsp stream client ports allocated.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.5.4

Field Name : axFixedNatAlgRtspStreamCreationFailed
Field Type : Counter64
Field Status : current
Description : The fixed nat alg rtsp stream creation failures.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.5.3

Field Name : axFixedNatAlgRtspStreamFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat alg rtsp stream freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.5.2

Field Name : axFixedNatAlgRtspStreamCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat alg rtsp stream created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.5.1

Field Name : axFixedNatAlgPptpGreNoMatchGreSession
Field Type : Counter64
Field Status : current
Description : The fixed nat alg pptp no matching gre sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.4.5

Field Name : axFixedNatAlgPptpGreSessionFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat alg pptp gre sessions freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.4.4

Field Name : axFixedNatAlgPptpGreSessionCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat alg pptp gre sessions created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.4.3

Field Name : axFixedNatAlgPptpMismatchedPnsCallId
Field Type : Counter64
Field Status : current
Description : The fixed nat alg pptp mismatched pns call id.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.4.2

Field Name : axFixedNatAlgPptpCallEsp
Field Type : Counter64
Field Status : current
Description : The fixed nat alg pptp calls established.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.4.1

Field Name : axFixedNatAlgH323FastStart
Field Type : Counter64
Field Status : current
Description : The fixed nat alg H323 fast start.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.3.5

Field Name : axFixedNatAlgH323H245TunnelMsg
Field Type : Counter64
Field Status : current
Description : The fixed nat alg H323 H245 Tunnelled message.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.3.4

Field Name : axFixedNatAlgH323H245MedCtrMsg
Field Type : Counter64
Field Status : current
Description : The fixed nat alg H323 H245 media control message.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.3.3

Field Name : axFixedNatAlgH323H225CallSigMsg
Field Type : Counter64
Field Status : current
Description : The fixed nat alg H323 H225 Call Signaling Message.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.3.2

Field Name : axFixedNatAlgH323H225RasMsg
Field Type : Counter64
Field Status : current
Description : The fixed nat alg H323 H225 Ras message.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.3.1

Field Name : axFixedNatAlgFtpLpsvRepFromServer
Field Type : Counter64
Field Status : current
Description : The fixed nat alg ftp lpsv replies from server.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.2.6

Field Name : axFixedNatAlgFtpEpsvRepFromServer
Field Type : Counter64
Field Status : current
Description : The fixed nat alg ftp epsv replies from server.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.2.5

Field Name : axFixedNatAlgFtpPasvRepFromServer
Field Type : Counter64
Field Status : current
Description : The fixed nat alg ftp pasv replies from server.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.2.4

Field Name : axFixedNatAlgFtpLprtReqFromClient
Field Type : Counter64
Field Status : current
Description : The fixed nat alg ftp lprt requests from client.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.2.3

Field Name : axFixedNatAlgFtpEprtReqFromClient
Field Type : Counter64
Field Status : current
Description : The fixed nat alg ftp eprt requests from client.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.2.2

Field Name : axFixedNatAlgFtpPortReqFromClient
Field Type : Counter64
Field Status : current
Description : The fixed nat alg ftp port requests from client.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.2.1

Field Name : axFixedNatAlgEspSessionCreated
Field Type : Counter64

Field Status : current
Description : The fixed nat alg esp session created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.1.1

Field Name : axFixedNatAlgTftpClientSessionCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat alg tftp client sessions created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.7.1

Field Name : axFixedNatNat64HairpinSessionCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat nat64 hairpin session created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.19.13

Field Name : axFixedNatNat64EndpointIndependentFilteringLimitExceed
Field Type : Counter64
Field Status : current
Description : The fixed nat nat64 endpoint independent filtering matched.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.19.12

Field Name : axFixedNatNat64EndpointIndependentFilteringDrop
Field Type : Counter64
Field Status : current
Description : The fixed nat nat64 endpoint independent filtering matched.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.19.11

Field Name : axFixedNatNat64EndpointIndependentFilteringMatched
Field Type : Counter64
Field Status : current
Description : The fixed nat nat64 endpoint independent filtering matched.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.19.10

Field Name : axFixedNatNat64EndpointIndependentMappingMatched
Field Type : Counter64
Field Status : current
Description : The fixed nat nat64 endpoint independent mapping matched.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.19.9

Field Name : axFixedNatNat64UdpAlgFullConeFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat nat64 udp alg full cone freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.19.8

Field Name : axFixedNatNat64UdpAlgFullConeCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat nat64 udp alg full cone created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.19.7

Field Name : axFixedNatNat64UdpFullConeFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat nat64 udp full cone freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.19.6

Field Name : axFixedNatNat64UdpFullConeCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat nat64 udp full cone created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.19.5

Field Name : axFixedNatNat64TcpFullConeFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat nat64 tcp full cone freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.19.4

Field Name : axFixedNatNat64TcpFullConeCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat nat64 tcp full cone created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.19.3

Field Name : axFixedNatNat64DataSessionsFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat nat64 data session freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.19.2

Field Name : axFixedNatNat64DataSessionsCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat nat64 data session created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.19.1

Field Name : axFixedNatNat44HairpinSessionCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat nat44 hairpin session created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.18.13

Field Name : axFixedNatNat44EndpointIndependentFilteringLimitExceed
Field Type : Counter64
Field Status : current
Description : The fixed nat nat44 endpoint independent filtering matched.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.18.12

Field Name : axFixedNatNat44EndpointIndependentFilteringDrop
Field Type : Counter64
Field Status : current
Description : The fixed nat nat44 endpoint independent filtering matched.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.18.11

Field Name : axFixedNatNat44EndpointIndependentFilteringMatched
Field Type : Counter64
Field Status : current
Description : The fixed nat nat44 endpoint independent filtering matched.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.18.10

Field Name : axFixedNatNat44EndpointIndependentMappingMatched
Field Type : Counter64
Field Status : current
Description : The fixed nat nat44 endpoint independent mapping matched.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.18.9

Field Name : axFixedNatNat44UdpAlgFullConeFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat nat44 udp alg full cone freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.18.8

Field Name : axFixedNatNat44UdpAlgFullConeCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat nat44 udp alg full cone created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.18.7

Field Name : axFixedNatNat44UdpFullConeFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat nat44 udp full cone freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.18.6

Field Name : axFixedNatNat44UdpFullConeCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat nat44 udp full cone created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.18.5

Field Name : axFixedNatNat44TcpFullConeFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat nat44 tcp full cone freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.18.4

Field Name : axFixedNatNat44TcpFullConeCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat nat44 tcp full cone created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.18.3

Field Name : axFixedNatNat44DataSessionsFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat nat44 data session freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.18.2

Field Name : axFixedNatNat44DataSessionsCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat nat44 data session created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.18.1

Field Name : axFixedNatDestRuleListPassThrough
Field Type : Counter64
Field Status : current
Description : The fixed nat destination rule list pass through.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.17

Field Name : axFixedNatDestRuleListDrop
Field Type : Counter64

Field Status : current
Description : The fixed nat destination rule list drop.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.16

Field Name : axFixedNatIpv6InIpv4PacketDrop
Field Type : Counter64
Field Status : current
Description : The fixed nat ipv6 in ipv4 packet drop.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.15

Field Name : axFixedNatSelfHairpinningDrop
Field Type : Counter64
Field Status : current
Description : The fixed nat self hairpining drop.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.14

Field Name : axFixedNatLidStandbyDrop
Field Type : Counter64
Field Status : current
Description : The fixed nat lid standby drop.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.13

Field Name : axFixedNatFullConeSessionCreationFailed
Field Type : Counter64
Field Status : current
Description : The fixed nat full cone session creation failed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.12

Field Name : axFixedNatSessionUserQuotaExceed
Field Type : Counter64
Field Status : current
Description : The fixed nat session user quota exceed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.11

Field Name : axFixedNatIcmpNatPortUnavailable
Field Type : Counter64
Field Status : current
Description : The fixed nat icmp nat port unavailable.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.10

Field Name : axFixedNatUdpNatPortUnavailable
Field Type : Counter64
Field Status : current
Description : The fixed nat udp nat port unavailable.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.9

Field Name : axFixedNatTcpNatPortUnavailable
Field Type : Counter64
Field Status : current
Description : The fixed nat tcp nat port unavailable.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.8

Field Name : axFixedNatTotalIcmpPortsFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat total icmp ports freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.7

Field Name : axFixedNatTotalIcmpPortsAllocated
Field Type : Counter64
Field Status : current
Description : The fixed nat total icmp ports allocated.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.6

Field Name : axFixedNatTotalUdpPortsFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat total udp ports freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.5

Field Name : axFixedNatTotalUdpPortsAllocated
Field Type : Counter64
Field Status : current
Description : The fixed nat total udp ports allocated.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.4

Field Name : axFixedNatTotalTcpPortsFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat total tcp ports freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.3

Field Name : axFixedNatTotalTcpPortsAllocated
Field Type : Counter64
Field Status : current
Description : The fixed nat total tcp ports allocated.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.2

Field Name : axFixedNatTotalNatAddressInUse
Field Type : Counter64
Field Status : current
Description : The fixed nat total nat address in use.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.1

Field Name : axFixedNatDsliteHairpinSessionCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat dslite hairpin session created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.20.13

Field Name : axFixedNatDsliteEndpointIndependentFilteringLimitExceed
Field Type : Counter64
Field Status : current
Description : The fixed nat dslite endpoint independent filtering matched.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.20.12

Field Name : axFixedNatDsliteEndpointIndependentFilteringDrop
Field Type : Counter64
Field Status : current
Description : The fixed nat dslite endpoint independent filtering matched.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.20.11

Field Name : axFixedNatDsliteEndpointIndependentFilteringMatched
Field Type : Counter64
Field Status : current
Description : The fixed nat dslite endpoint independent filtering matched.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.20.10

Field Name : axFixedNatDsliteEndpointIndependentMappingMatched
Field Type : Counter64
Field Status : current
Description : The fixed nat dslite endpoint independent mapping matched.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.20.9

Field Name : axFixedNatDsliteUdpAlgFullConeFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat dslite udp alg full cone freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.20.8

Field Name : axFixedNatDsliteUdpAlgFullConeCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat dslite udp alg full cone created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.20.7

Field Name : axFixedNatDsliteUdpFullConeFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat dslite udp full cone freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.20.6

Field Name : axFixedNatDsliteUdpFullConeCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat dslite udp full cone created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.20.5

Field Name : axFixedNatDsliteTcpFullConeFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat dslite tcp full cone freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.20.4

Field Name : axFixedNatDsliteTcpFullConeCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat dslite tcp full cone created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.20.3

Field Name : axFixedNatDsliteDataSessionsFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat dslite data session freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.20.2

Field Name : axFixedNatDsliteDataSessionsCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat dslite data session created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.20.1

Field Name : axFixedNatFileTable
Field Type : TABLE

Field Status : current
Description : A table containing fixed nat files.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.16.1

Field Name : axFixedNatFileEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axFixedNatFile Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.16.1.1

Field Name : axFixedNatFileTimeStamp
Field Type : String
Field Status : current
Description : The time stamp of fixed nat files.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.16.1.1.2

Field Name : axFixedNatFileName
Field Type : String
Field Status : current
Description : The file name in fixed nat file table entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.16.1.1.1

Field Name : axHAGroupStatusTable
Field Type : TABLE
Field Status : current
Description : A table contains the HA group status information.
OID : 1.3.6.1.4.1.22610.2.4.3.17.2.2

Field Name : axHAGroupCount
Field Type : INTEGER
Field Status : current
Description : The number of valid HA groups.
OID : 1.3.6.1.4.1.22610.2.4.3.17.2.1

Field Name : axHAGroupStatusEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axHAGroupStatus Table
OID : 1.3.6.1.4.1.22610.2.4.3.17.2.2.1

Field Name : axHAGroupPeerPriority
Field Type : Integer32
Field Status : current
Description : The peer priority of this HA group.
OID : 1.3.6.1.4.1.22610.2.4.3.17.2.2.1.5

Field Name : axHAGroupPeerStatus
Field Type : EnumVal
Field Status : current
Description : The peer status of this HA group.
OID : 1.3.6.1.4.1.22610.2.4.3.17.2.2.1.4

Field Name : axHAGroupLocalPriority
Field Type : Integer32
Field Status : current
Description : The local priority of this HA group.
OID : 1.3.6.1.4.1.22610.2.4.3.17.2.2.1.3

Field Name : axHAGroupLocalStatus
Field Type : EnumVal
Field Status : current
Description : The local status of this HA group.
OID : 1.3.6.1.4.1.22610.2.4.3.17.2.2.1.2

Field Name : axHAGroupID
Field Type : Integer32
Field Status : current
Description : The HA group ID.
OID : 1.3.6.1.4.1.22610.2.4.3.17.2.2.1.1

Field Name : axHAARPRetry
Field Type : INTEGER
Field Status : current
Description : The ARP retries.
OID : 1.3.6.1.4.1.22610.2.4.3.17.1.7

Field Name : axHATimeoutRetry
Field Type : INTEGER
Field Status : current
Description : The HA retries when time out.
OID : 1.3.6.1.4.1.22610.2.4.3.17.1.6

Field Name : axHATimeoutInterval
Field Type : INTEGER
Field Status : current
Description : The HA time interval.
OID : 1.3.6.1.4.1.22610.2.4.3.17.1.5

Field Name : axHAPreemptStatusEnabled
Field Type : EnumVal
Field Status : current
Description : The HA preempt enabled flag
OID : 1.3.6.1.4.1.22610.2.4.3.17.1.4

Field Name : axHASetID
Field Type : INTEGER
Field Status : current
Description : Local configured HA group set-id
OID : 1.3.6.1.4.1.22610.2.4.3.17.1.3

Field Name : axHAID
Field Type : INTEGER
Field Status : current
Description : Local configured HA group ID.
OID : 1.3.6.1.4.1.22610.2.4.3.17.1.2

Field Name : axHAConfigEnabled
Field Type : EnumVal
Field Status : current
Description : The HA configuration enabled flag.
OID : 1.3.6.1.4.1.22610.2.4.3.17.1.1

Field Name : axHAFloatingIPTable
Field Type : TABLE
Field Status : current
Description : A table contains the HA floating-IP information.

OID : 1.3.6.1.4.1.22610.2.4.3.17.3.2

Field Name : axHAFloatingIPCount
Field Type : INTEGER
Field Status : current
Description : The number of HA floating-IP entries.
OID : 1.3.6.1.4.1.22610.2.4.3.17.3.1

Field Name : axHAFloatingIPEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The index column in the axHAFloatingIP Table
OID : 1.3.6.1.4.1.22610.2.4.3.17.3.2.1

Field Name : axHAFloatingIPHaGroupID
Field Type : INTEGER
Field Status : current
Description : The HA group ID for the HA floating-IP entry.
OID : 1.3.6.1.4.1.22610.2.4.3.17.3.2.1.3

Field Name : axHAFloatingIPAddress
Field Type : String
Field Status : current
Description : HA floating-IP address (either IPv4 or IPv6).
OID : 1.3.6.1.4.1.22610.2.4.3.17.3.2.1.2

Field Name : axHAFloatingIPIndex
Field Type : INTEGER
Field Status : current
Description : The index column.
OID : 1.3.6.1.4.1.22610.2.4.3.17.3.2.1.1

Field Name : axSwitchStatTable
Field Type : TABLE
Field Status : current
Description : The switch status table.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31

Field Name : axSwitchStatsAnomAnyDrop
Field Type : INTEGER
Field Status : current
Description : Number of packets dropped by any type of hardware-based DDoS protection filter.
OID : 1.3.6.1.4.1.22610.2.4.3.16.30

Field Name : axSwitchStatsAnomTCPSynFinDrop
Field Type : INTEGER
Field Status : current
Description : Number of packets dropped by a tcp-syn-fin filter.
OID : 1.3.6.1.4.1.22610.2.4.3.16.29

Field Name : axSwitchStatsAnomSYNFragDrop
Field Type : INTEGER
Field Status : current
Description : Number of packets dropped by a tcp-syn-frag filter.
OID : 1.3.6.1.4.1.22610.2.4.3.16.28

Field Name : axSwitchStatsAnomTCPNoFragDrop

Field Type : INTEGER
Field Status : current
Description : Number of packets dropped by a tcp-no-flag filter.
OID : 1.3.6.1.4.1.22610.2.4.3.16.27

Field Name : axSwitchStatsAnomAllFragDrop
Field Type : INTEGER
Field Status : current
Description : Number of packets dropped by a frag filter.
OID : 1.3.6.1.4.1.22610.2.4.3.16.26

Field Name : axSwitchStatsAnomPingDeathDrop
Field Type : INTEGER
Field Status : current
Description : Number of packets dropped by a ping-of-death filter.
OID : 1.3.6.1.4.1.22610.2.4.3.16.25

Field Name : axSwitchStatsAnomIPOptionDrop
Field Type : INTEGER
Field Status : current
Description : Number of packets dropped by an IP option filter.
OID : 1.3.6.1.4.1.22610.2.4.3.16.24

Field Name : axSwitchStatsAnomLanAttackDrop
Field Type : INTEGER
Field Status : current
Description : Number of packets dropped by an IP land attack filter.This statistic and
the other Anomaly statistics show how many packets were dropped by DDoS
protection filters. For the AX device to drop these packets, the corresponding
DDoS protection options must be enabled.
OID : 1.3.6.1.4.1.22610.2.4.3.16.23

Field Name : axSwitchStatsIPFragReasmFail
Field Type : INTEGER
Field Status : current
Description : Number of fragment reassembly failures.
OID : 1.3.6.1.4.1.22610.2.4.3.16.22

Field Name : axSwitchStatsIPFragReasmOk
Field Type : INTEGER
Field Status : current
Description : Number of successfully reassembled IP fragments.
OID : 1.3.6.1.4.1.22610.2.4.3.16.21

Field Name : axSwitchStatsIPFragOverlapDrop
Field Type : INTEGER
Field Status : current
Description : Number of fragments dropped due to overload.
OID : 1.3.6.1.4.1.22610.2.4.3.16.20

Field Name : axSwitchStatsIPFragOverlap
Field Type : INTEGER
Field Status : current
Description : Number of overlapping fragments received.
OID : 1.3.6.1.4.1.22610.2.4.3.16.19

Field Name : axSwitchStatsIPTCPFragRcv
Field Type : INTEGER

Field Status : current
Description : Number of IP TCP fragments received.
OID : 1.3.6.1.4.1.22610.2.4.3.16.18

Field Name : axSwitchStatsFwdKernel
Field Type : INTEGER
Field Status : current
Description : Number of packets received by the kernel from data interfaces.
OID : 1.3.6.1.4.1.22610.2.4.3.16.17

Field Name : axSwitchStatsARPRespRcv
Field Type : INTEGER
Field Status : current
Description : Number of ARP responses that have been received.
OID : 1.3.6.1.4.1.22610.2.4.3.16.16

Field Name : axSwitchStatsARPReqRcv
Field Type : INTEGER
Field Status : current
Description : Number of ARP requests that have been received.
OID : 1.3.6.1.4.1.22610.2.4.3.16.15

Field Name : axSwitchStatsIPFragRcv
Field Type : INTEGER
Field Status : current
Description : Number of IPv4 fragments that have been received.
OID : 1.3.6.1.4.1.22610.2.4.3.16.14

Field Name : axSwitchStatsVLANFlood
Field Type : INTEGER
Field Status : current
Description : Number of packets that have been broadcast to a VLAN.
OID : 1.3.6.1.4.1.22610.2.4.3.16.13

Field Name : axSwitchStatsSRCPortSuppress
Field Type : INTEGER
Field Status : current
Description : Packet drops because of source port suppression.
OID : 1.3.6.1.4.1.22610.2.4.3.16.12

Field Name : axSwitchStatsLinkdownDrop
Field Type : INTEGER
Field Status : current
Description : Number of packets dropped because the outgoing link was down.
OID : 1.3.6.1.4.1.22610.2.4.3.16.11

Field Name : axSwitchStatsTTLExceedDrop
Field Type : INTEGER
Field Status : current
Description : Number of packets dropped due to TTL expiration.
OID : 1.3.6.1.4.1.22610.2.4.3.16.10

Field Name : axSwitchStatsUnknownProtoDrop
Field Type : INTEGER
Field Status : current
Description : Number of packets dropped because the protocol was unknown.
OID : 1.3.6.1.4.1.22610.2.4.3.16.9

Field Name : axSwitchStatsProtoDownDrop
Field Type : INTEGER
Field Status : current
Description : Number of packets dropped because the corresponding protocol was disabled.
OID : 1.3.6.1.4.1.22610.2.4.3.16.8

Field Name : axSwitchStatsIncorrectLenDrop
Field Type : INTEGER
Field Status : current
Description : Number of packets dropped due to incorrect protocol length.A high value
for this counter can indicate a packet length attack.
OID : 1.3.6.1.4.1.22610.2.4.3.16.7

Field Name : axSwitchStatsL4Process
Field Type : INTEGER
Field Status : current
Description : Number of packets that went to a VIP or NAT for processing.
OID : 1.3.6.1.4.1.22610.2.4.3.16.6

Field Name : axSwitchStatsIPv6NoRouteDrop
Field Type : INTEGER
Field Status : current
Description : Number of IPv6 packets that were dropped due to routing failures.
OID : 1.3.6.1.4.1.22610.2.4.3.16.5

Field Name : axSwitchStatsL3IPv6Forward
Field Type : INTEGER
Field Status : current
Description : Number of IPv6 packets that have been Layer 3 routed.
OID : 1.3.6.1.4.1.22610.2.4.3.16.4

Field Name : axSwitchStatsIPv4NoRouteDrop
Field Type : INTEGER
Field Status : current
Description : Number of IPv4 packets that were dropped due to routing failures.
OID : 1.3.6.1.4.1.22610.2.4.3.16.3

Field Name : axSwitchStatsL3IPForward
Field Type : INTEGER
Field Status : current
Description : Number of packets that have been Layer 3 routed.
OID : 1.3.6.1.4.1.22610.2.4.3.16.2

Field Name : axSwitchStatsL2Forward
Field Type : INTEGER
Field Status : current
Description : Number of packets that have been Layer 2 switched.
OID : 1.3.6.1.4.1.22610.2.4.3.16.1

Field Name : axSwitchStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The Switch status entry.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1

Field Name : axSwitchStatAnomAnyDrop
Field Type : Counter
Field Status : current

Description : Number of packets dropped by any type of hardware-based DDoS protection filter.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.31

Field Name : axSwitchStatAnomTCPSynFinDrop
Field Type : Counter
Field Status : current
Description : Number of packets dropped by a tcp-syn-fin filter.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.30

Field Name : axSwitchStatAnomSYNFragDrop
Field Type : Counter
Field Status : current
Description : Number of packets dropped by a tcp-syn-frag filter.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.29

Field Name : axSwitchStatAnomTCPNoFragDrop
Field Type : Counter
Field Status : current
Description : Number of packets dropped by a tcp-no-flag filter.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.28

Field Name : axSwitchStatAnomAllFragDrop
Field Type : Counter
Field Status : current
Description : Number of packets dropped by a frag filter.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.27

Field Name : axSwitchStatAnomPingDeathDrop
Field Type : Counter
Field Status : current
Description : Number of packets dropped by a ping-of-death filter.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.26

Field Name : axSwitchStatAnomIPOptionDrop
Field Type : Counter
Field Status : current
Description : Number of packets dropped by an IP option filter.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.25

Field Name : axSwitchStatAnomLanAttackDrop
Field Type : Counter
Field Status : current
Description : Number of packets dropped by an IP land attack filter.This statistic and the other Anomaly statistics show how many packets were dropped by DDoS protection filters. For the AX device to drop these packets, the corresponding DDoS protection options must be enabled.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.24

Field Name : axSwitchStatIPFragReasmFail
Field Type : Counter
Field Status : current
Description : Number of fragment reassembly failures.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.23

Field Name : axSwitchStatIPFragReasmOk
Field Type : Counter
Field Status : current

Description : Number of successfully reassembled IP fragments.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.22

Field Name : axSwitchStatIPFragOverlapDrop
Field Type : Counter
Field Status : current
Description : Number of fragments dropped due to overload.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.21

Field Name : axSwitchStatIPFragOverlap
Field Type : Counter
Field Status : current
Description : Number of overlapping fragments received.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.20

Field Name : axSwitchStatIPTCPFragRcv
Field Type : Counter
Field Status : current
Description : Number of IP TCP fragments received.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.19

Field Name : axSwitchStatFwdKernel
Field Type : Counter
Field Status : current
Description : Number of packets received by the kernel from data interfaces.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.18

Field Name : axSwitchStatARPRespRcv
Field Type : Counter
Field Status : current
Description : Number of ARP responses that have been received.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.17

Field Name : axSwitchStatARPReqRcv
Field Type : Counter
Field Status : current
Description : Number of ARP requests that have been received.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.16

Field Name : axSwitchStatIPFragRcv
Field Type : Counter
Field Status : current
Description : Number of IPv4 fragments that have been received.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.15

Field Name : axSwitchStatVLANFlood
Field Type : Counter
Field Status : current
Description : Number of packets that have been broadcast to a VLAN.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.14

Field Name : axSwitchStatSRCPortSuppress
Field Type : Counter
Field Status : current
Description : Packet drops because of source port suppression.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.13

Field Name : axSwitchStatLinkdownDrop

Field Type : Counter
Field Status : current
Description : Number of packets dropped because the outgoing link was down.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.12

Field Name : axSwitchStatTTLExceedDrop
Field Type : Counter
Field Status : current
Description : Number of packets dropped due to TTL expiration.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.11

Field Name : axSwitchStatUnknownProtoDrop
Field Type : Counter
Field Status : current
Description : Number of packets dropped because the protocol was unknown.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.10

Field Name : axSwitchStatProtoDownDrop
Field Type : Counter
Field Status : current
Description : Number of packets dropped because the corresponding protocol was disabled.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.9

Field Name : axSwitchStatIncorrectLenDrop
Field Type : Counter
Field Status : current
Description : Number of packets dropped due to incorrect protocol length.A high value
for this counter can indicate a packet length attack.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.8

Field Name : axSwitchStatL4Process
Field Type : Counter
Field Status : current
Description : Number of packets that went to a VIP or NAT for processing.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.7

Field Name : axSwitchStatIPv6NoRouteDrop
Field Type : Counter
Field Status : current
Description : Number of IPv6 packets that were dropped due to routing failures.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.6

Field Name : axSwitchStatL3IPv6Forward
Field Type : Counter
Field Status : current
Description : Number of IPv6 packets that have been Layer 3 routed.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.5

Field Name : axSwitchStatIPv4NoRouteDrop
Field Type : Counter
Field Status : current
Description : Number of IPv4 packets that were dropped due to routing failures.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.4

Field Name : axSwitchStatL3IPForward
Field Type : Counter
Field Status : current
Description : Number of packets that have been Layer 3 routed.

OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.3

Field Name : axSwitchStatL2Forward
Field Type : Counter
Field Status : current
Description : Number of packets that have been Layer 2 switched.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.2

Field Name : axSwitchStatCpuIndex
Field Type : Integer32
Field Status : current
Description : The cpu index of Switch STAT table
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.1

Field Name : axPersistentStatTable
Field Type : TABLE
Field Status : current
Description : The Persistent STAT table.
OID : 1.3.6.1.4.1.22610.2.4.3.15.11

Field Name : axPersistentStatsPersistCookieNotFound
Field Type : INTEGER
Field Status : current
Description : Total number of cookie persistent failure in not-found cases.
OID : 1.3.6.1.4.1.22610.2.4.3.15.10

Field Name : axPersistentStatsCookiePersistFail
Field Type : INTEGER
Field Status : current
Description : Total number of cookie persistent failure.
OID : 1.3.6.1.4.1.22610.2.4.3.15.9

Field Name : axPersistentStatsCookiePersistOK
Field Type : INTEGER
Field Status : current
Description : Total number of cookie persistent success.
OID : 1.3.6.1.4.1.22610.2.4.3.15.8

Field Name : axPersistentStatsSSLSIDPersistFail
Field Type : INTEGER
Field Status : current
Description : Total number of SSL session ID persistent failure.
OID : 1.3.6.1.4.1.22610.2.4.3.15.7

Field Name : axPersistentStatsSSLSIDPersistOK
Field Type : INTEGER
Field Status : current
Description : Total number of SSL session ID persistent success.
OID : 1.3.6.1.4.1.22610.2.4.3.15.6

Field Name : axPersistentStatsSIPPersistFail
Field Type : INTEGER
Field Status : current
Description : Number of requests that could not be fulfilled by the same server as previous requests from the same client, based on source-IP persistence.
OID : 1.3.6.1.4.1.22610.2.4.3.15.5

Field Name : axPersistentStatsSIPPersistOK

Field Type : INTEGER
Field Status : current
Description : Number of requests successfully sent to the same server as previous requests from the same client, based on source-IP persistence.
OID : 1.3.6.1.4.1.22610.2.4.3.15.4

Field Name : axPersistentStatsUrlHashPersistFail
Field Type : INTEGER
Field Status : current
Description : Number of requests that could not be fulfilled using URL hashing.
OID : 1.3.6.1.4.1.22610.2.4.3.15.3

Field Name : axPersistentStatsUrlHashPersistOKSec
Field Type : INTEGER
Field Status : current
Description : Number of requests that were sent to another server (a secondary server) because the primary server selected by URL hashing was unavailable.
OID : 1.3.6.1.4.1.22610.2.4.3.15.2

Field Name : axPersistentStatsUrlHashPersistOKPri
Field Type : INTEGER
Field Status : current
Description : Number of requests successfully sent to the primary server selected by URL hashing. The primary server is the one that was initially selected and then re-used based on the hash value.
OID : 1.3.6.1.4.1.22610.2.4.3.15.1

Field Name : axPersistentStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The Persistent STAT entry.
OID : 1.3.6.1.4.1.22610.2.4.3.15.11.1

Field Name : axPersistentStatPersistCookieNotFound
Field Type : Counter
Field Status : current
Description : Number of cookie persistent failure in not-found cases.
OID : 1.3.6.1.4.1.22610.2.4.3.15.11.1.11

Field Name : axPersistentStatCookiePersistFail
Field Type : Counter
Field Status : current
Description : Number of cookie persistent failure.
OID : 1.3.6.1.4.1.22610.2.4.3.15.11.1.10

Field Name : axPersistentStatCookiePersistOK
Field Type : Counter
Field Status : current
Description : Number of cookie persistent success.
OID : 1.3.6.1.4.1.22610.2.4.3.15.11.1.9

Field Name : axPersistentStatSSLSIDPersistFail
Field Type : Counter
Field Status : current
Description : Number of SSL session ID persistent failure.
OID : 1.3.6.1.4.1.22610.2.4.3.15.11.1.8

Field Name : axPersistentStatSSLSIDPersistOK

Field Type : Counter
Field Status : current
Description : Number of SSL session ID persistent success.
OID : 1.3.6.1.4.1.22610.2.4.3.15.11.1.7

Field Name : axPersistentStatSIPPersistFail
Field Type : Counter
Field Status : current
Description : Number of requests that could not be fulfilled by the same server as previous requests from the same client, based on source-IP persistence.
OID : 1.3.6.1.4.1.22610.2.4.3.15.11.1.6

Field Name : axPersistentStatSIPPersistOK
Field Type : Counter
Field Status : current
Description : Number of requests successfully sent to the same server as previous requests from the same client, based on source-IP persistence.
OID : 1.3.6.1.4.1.22610.2.4.3.15.11.1.5

Field Name : axPersistentStatUrlHashPersistFail
Field Type : Counter
Field Status : current
Description : Number of requests that could not be fulfilled using URL hashing.
OID : 1.3.6.1.4.1.22610.2.4.3.15.11.1.4

Field Name : axPersistentStatUrlHashPersistOKSec
Field Type : Counter
Field Status : current
Description : Number of requests that were sent to another server (a secondary server) because the primary server selected by URL hashing was unavailable.
OID : 1.3.6.1.4.1.22610.2.4.3.15.11.1.3

Field Name : axPersistentStatUrlHashPersistOKPri
Field Type : Counter
Field Status : current
Description : Number of requests successfully sent to the primary server selected by URL hashing. The primary server is the one that was initially selected and then re-used based on the hash value.
OID : 1.3.6.1.4.1.22610.2.4.3.15.11.1.2

Field Name : axPersistentStatCpuIndex
Field Type : Integer32
Field Status : current
Description : The cpu index of Persistent STAT table
OID : 1.3.6.1.4.1.22610.2.4.3.15.11.1.1

Field Name : axSslProxyStatsSNATFail
Field Type : INTEGER
Field Status : current
Description : Number of occurrences of source NAT failure.
OID : 1.3.6.1.4.1.22610.2.4.3.14.8

Field Name : axSslProxyStatsSvrSelFail
Field Type : INTEGER
Field Status : current
Description : Number of times selection or a real server failed.
OID : 1.3.6.1.4.1.22610.2.4.3.14.7

Field Name : axSslProxyStatsNoRoute
Field Type : INTEGER
Field Status : current
Description : Number of times no route was available.
OID : 1.3.6.1.4.1.22610.2.4.3.14.6

Field Name : axSslProxyStatsSessNotFound
Field Type : INTEGER
Field Status : current
Description : Number of times a session was not found.
OID : 1.3.6.1.4.1.22610.2.4.3.14.5

Field Name : axSslProxyStatsServerErr
Field Type : INTEGER
Field Status : current
Description : Number of server errors.
OID : 1.3.6.1.4.1.22610.2.4.3.14.4

Field Name : axSslProxyStatsClientErr
Field Type : INTEGER
Field Status : current
Description : Number of client errors.
OID : 1.3.6.1.4.1.22610.2.4.3.14.3

Field Name : axSslProxyStatsTotalProxyConns
Field Type : INTEGER
Field Status : current
Description : Total number of connections using the AX device as an SSL proxy.
OID : 1.3.6.1.4.1.22610.2.4.3.14.2

Field Name : axSslProxyStatsCurrProxyConns
Field Type : INTEGER
Field Status : current
Description : Number of currently active connections using the AX device as an SSL proxy.
OID : 1.3.6.1.4.1.22610.2.4.3.14.1

Field Name : axSmtpProxyStatTable
Field Type : TABLE
Field Status : current
Description : The Smtp proxy STAT table.
OID : 1.3.6.1.4.1.22610.2.4.3.13.19

Field Name : axSmtpProxyStatsSNATFail
Field Type : INTEGER
Field Status : current
Description : Number of source NAT failures.
OID : 1.3.6.1.4.1.22610.2.4.3.13.18

Field Name : axSmtpProxyStatsSvrConnMade
Field Type : INTEGER
Field Status : current
Description : Number of connections made with servers.
OID : 1.3.6.1.4.1.22610.2.4.3.13.17

Field Name : axSmtpProxyStatsSvrPrematureClose
Field Type : INTEGER
Field Status : current
Description : Number of times the connection with a server closed prematurely.

OID : 1.3.6.1.4.1.22610.2.4.3.13.16

Field Name : axSmtpProxyStatsServerResel
Field Type : INTEGER
Field Status : current
Description : Number of times a request was forwarded to another server because the current server was failing.
OID : 1.3.6.1.4.1.22610.2.4.3.13.15

Field Name : axSmtpProxyStatsReqPktOutOrder
Field Type : INTEGER
Field Status : current
Description : Number of request packets received from clients out of sequence.
OID : 1.3.6.1.4.1.22610.2.4.3.13.14

Field Name : axSmtpProxyStatsReqRetrans
Field Type : INTEGER
Field Status : current
Description : Number of retransmitted requests.
OID : 1.3.6.1.4.1.22610.2.4.3.13.13

Field Name : axSmtpProxyStatsFwdReqDataFail
Field Type : INTEGER
Field Status : current
Description : Number of forward request data failures.
OID : 1.3.6.1.4.1.22610.2.4.3.13.12

Field Name : axSmtpProxyStatsFwdReqFail
Field Type : INTEGER
Field Status : current
Description : Number of forward request failures.
OID : 1.3.6.1.4.1.22610.2.4.3.13.11

Field Name : axSmtpProxyStatsServerSelFail
Field Type : INTEGER
Field Status : current
Description : Number of times selection of a real server failed.
OID : 1.3.6.1.4.1.22610.2.4.3.13.10

Field Name : axSmtpProxyStatsParseReqFail
Field Type : INTEGER
Field Status : current
Description : Number of times parsing of an SMTP request failed.
OID : 1.3.6.1.4.1.22610.2.4.3.13.9

Field Name : axSmtpProxyStatsNoTupleError
Field Type : INTEGER
Field Status : current
Description : Number of tuple errors.
OID : 1.3.6.1.4.1.22610.2.4.3.13.8

Field Name : axSmtpProxyStatsServerRST
Field Type : INTEGER
Field Status : current
Description : Number of times TCP connections with servers were reset.
OID : 1.3.6.1.4.1.22610.2.4.3.13.7

Field Name : axSmtpProxyStatsClientRST

Field Type : INTEGER
Field Status : current
Description : Number of times TCP connections with clients were reset.
OID : 1.3.6.1.4.1.22610.2.4.3.13.6

Field Name : axSmtpProxyStatsNoProxyError
Field Type : INTEGER
Field Status : current
Description : Number of proxy errors.
OID : 1.3.6.1.4.1.22610.2.4.3.13.5

Field Name : axSmtpProxyStatsSmtpReqSuccs
Field Type : INTEGER
Field Status : current
Description : Number of SMTP requests received by the AX Series device that were successfully fulfilled (by connection to a real server).
OID : 1.3.6.1.4.1.22610.2.4.3.13.4

Field Name : axSmtpProxyStatsSmtpRequests
Field Type : INTEGER
Field Status : current
Description : Total number of SMTP requests received by the SMTP proxy.
OID : 1.3.6.1.4.1.22610.2.4.3.13.3

Field Name : axSmtpProxyStatsTotalProxyConns
Field Type : INTEGER
Field Status : current
Description : Total number of SMTP connections that have used the AX Series device as an SMTP proxy.
OID : 1.3.6.1.4.1.22610.2.4.3.13.2

Field Name : axSmtpProxyStatsCurrProxyConns
Field Type : INTEGER
Field Status : current
Description : Number of currently active SMTP connections using the AX Series device as an SMTP proxy.
OID : 1.3.6.1.4.1.22610.2.4.3.13.1

Field Name : axSmtpProxyStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The Smtp proxy STAT entry.
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1

Field Name : axSmtpProxyStatSNATFail
Field Type : Counter
Field Status : current
Description : Number of source NAT failures.
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.19

Field Name : axSmtpProxyStatSvrConnMade
Field Type : Counter
Field Status : current
Description : Number of connections made with servers.
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.18

Field Name : axSmtpProxyStatSvrPrematureClose
Field Type : Counter

Field Status : current
Description : TNumber of times the connection with a server closed prematurely.
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.17

Field Name : axSmtpProxyStatServerResel
Field Type : Counter
Field Status : current
Description : Number of times a request was forwarded to another server because the current server was failing.
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.16

Field Name : axSmtpProxyStatReqPktOutOrder
Field Type : Counter
Field Status : current
Description : Number of request packets received from clients out of sequence.
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.15

Field Name : axSmtpProxyStatReqRetrans
Field Type : Counter
Field Status : current
Description : Number of retransmitted requests.
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.14

Field Name : axSmtpProxyStatFwdReqDataFail
Field Type : Counter
Field Status : current
Description : Number of forward request data failures.
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.13

Field Name : axSmtpProxyStatFwdReqFail
Field Type : Counter
Field Status : current
Description : Number of forward request failures.
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.12

Field Name : axSmtpProxyStatServerSelFail
Field Type : Counter
Field Status : current
Description : Number of times selection of a real server failed.
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.11

Field Name : axSmtpProxyStatParseReqFail
Field Type : Counter
Field Status : current
Description : Number of times parsing of an SMTP request failed.
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.10

Field Name : axSmtpProxyStatNoTupleError
Field Type : Counter
Field Status : current
Description : Number of tuple errors.
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.9

Field Name : axSmtpProxyStatServerRST
Field Type : Counter
Field Status : current
Description : Number of times TCP connections with servers were reset.
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.8

Field Name : axSmtpProxyStatClientRST
Field Type : Counter
Field Status : current
Description : Number of times TCP connections with clients were reset.
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.7

Field Name : axSmtpProxyStatNoProxyError
Field Type : Counter
Field Status : current
Description : Number of proxy errors.
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.6

Field Name : axSmtpProxyStatSmtpReqSucc
Field Type : Counter
Field Status : current
Description : Number of SMTP requests received by the AX Series device that were successfully fulfilled (by connection to a real server).
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.5

Field Name : axSmtpProxyStatSmtpReq
Field Type : Counter
Field Status : current
Description : Total number of SMTP requests received by the SMTP proxy.
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.4

Field Name : axSmtpProxyStatTotalProxyConn
Field Type : Counter
Field Status : current
Description : Total number of SMTP connections that have used the AX Series device as an SMTP proxy.
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.3

Field Name : axSmtpProxyStatCurrProxyConn
Field Type : Counter
Field Status : current
Description : Number of currently active SMTP connections using the AX Series device as an SMTP proxy.
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.2

Field Name : axSmtpProxyStatCpuIndex
Field Type : Integer32
Field Status : current
Description : The Module Index of Smtp Proxy STAT table
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.1

Field Name : axNetStatTable
Field Type : TABLE
Field Status : current
Description : The Net STAT table.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100

Field Name : axNetStatExtPSBLBEntryLimitExceed
Field Type : Counter
Field Status : current
Description : Number of L4 skip insert client ip
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.70

Field Name : axNetStatExtL4ServerDownDel
Field Type : Counter
Field Status : current
Description : Number of L4 skip insert client ip
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.69

Field Name : axNetStatExtL4SkipInsertClientIp
Field Type : Counter
Field Status : current
Description : Number of L4 skip insert client ip
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.68

Field Name : axNetStatExtL4TcpEst
Field Type : Counter
Field Status : current
Description : Number of L4 TCP Established
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.67

Field Name : axNetStatExtL4UdpRsps
Field Type : Counter
Field Status : current
Description : Number of L4 UDP rsps
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.66

Field Name : axNetStatExtL4UdpReqs
Field Type : Counter
Field Status : current
Description : Number of L4 UDP reqs
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.65

Field Name : axNetStatExtL4UdpRspsGreaterReqs
Field Type : Counter
Field Status : current
Description : Number of L4 UDP rsps > reqs
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.64

Field Name : axNetStatExtL4UdpReqGreaterRsps
Field Type : Counter
Field Status : current
Description : Number of L4 UDP req > rsps
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.63

Field Name : axNetStatExtL4UdpReqRspNotMatch
Field Type : Counter
Field Status : current
Description : Number of L4 UDP req/rsp not match
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.62

Field Name : axNetStatExtL4UdpReqRsps
Field Type : Counter
Field Status : current
Description : Number of L4 UDP req rsps
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.61

Field Name : axNetStatExtL4UdpReqsNoRsp
Field Type : Counter
Field Status : current
Description : Number of L4 UDP reqs no rsp

OID : 1.3.6.1.4.1.22610.2.4.3.11.90.60

Field Name : axNetStatExtL4RcfRevRst
Field Type : Counter
Field Status : current
Description : Number of L4 rcv rev RST
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.59

Field Name : axNetStatExtL4RcvFwdRst
Field Type : Counter
Field Status : current
Description : Number of L4 rcv fwd RST
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.58

Field Name : axNetStatExtL4RcvFevFinAck
Field Type : Counter
Field Status : current
Description : Number of L4 rcv rev FIN|ACK
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.57

Field Name : axNetStatExtL4RcvRevFinDup
Field Type : Counter
Field Status : current
Description : Number of L4 rcv rev FIN dup
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.56

Field Name : axNetStatExtL4RcvRevFin
Field Type : Counter
Field Status : current
Description : Number of L4 rcv rev FIN
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.55

Field Name : axNetStatExtL4RcvFwdFinAck
Field Type : Counter
Field Status : current
Description : Number of L4 rcv fwd FIN|ACK
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.54

Field Name : axNetStatExtL4RcvFwdFinDrop
Field Type : Counter
Field Status : current
Description : Number of L4 rcv fwd FIN dup
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.53

Field Name : axNetStatExtL4RcvFwdFin
Field Type : Counter
Field Status : current
Description : Number of L4 rcv fwd FIN
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.52

Field Name : axNetStatExtL4RcvRevLastAck
Field Type : Counter
Field Status : current
Description : Number of L4 rcv rev last ACK
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.51

Field Name : axNetStatExtL4RcvFwdLastAck
Field Type : Counter

Field Status : current
Description : Number of L4 rcv fwd last ACK
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.50

Field Name : axNetStatExtL4RcvReXmitSynAckDq
Field Type : Counter
Field Status : current
Description : Number of L4 rcv rexmit SYN|ACK DQ
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.49

Field Name : axNetStatExtL4RcvReXmitSynAck
Field Type : Counter
Field Status : current
Description : Number of L4 rcv rexmit SYN|ACK
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.48

Field Name : axNetStatExtL4RcvReXmitSynDelq
Field Type : Counter
Field Status : current
Description : Number of L4 rcv rexmit SYN (delq)
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.47

Field Name : axNetStatExtL4RcvReXmitSyn
Field Type : Counter
Field Status : current
Description : Number of L4 rcv rexmit SYN
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.46

Field Name : axNetStatExtNoEstSsynSntAgedOut
Field Type : Counter
Field Status : current
Description : Number of no-Est SSYN snt aged out
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.45

Field Name : axNetStatExtNoEstCsynRcvAgedOut
Field Type : Counter
Field Status : current
Description : Number of no-Est CSYN rcv aged out
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.44

Field Name : axNetStatExtTcpNoEstSessionAgedOut
Field Type : Counter
Field Status : current
Description : Number of TCP no-Est Sess aged out
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.43

Field Name : axNetStatExtL4RcvRstOnSyn
Field Type : Counter
Field Status : current
Description : Number of L4 rcv RST on SYN
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.42

Field Name : axNetStatExtL4RcvAckOnSyn
Field Type : Counter
Field Status : current
Description : Number of L4 rcv ACK on SYN
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.41

Field Name : axNetStatExtL4AxReXmitSyn
Field Type : Counter
Field Status : current
Description : Number of L4 AX re-xmit SYN
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.40

Field Name : axNetStatExtL4ServerHandshakeFail
Field Type : Counter
Field Status : current
Description : Number of L4 server handshake fail
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.39

Field Name : axNetStatExtL3vConnLimitDrop
Field Type : Counter
Field Status : current
Description : Number of L3V Conn Limit Drop
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.38

Field Name : axNetStatExtSslTptWaterMarkDrop
Field Type : Counter
Field Status : current
Description : Number of SSL TPT-Watermark drop
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.37

Field Name : axNetStatExtSslTptExceedDrop
Field Type : Counter
Field Status : current
Description : Number of SSL TPT exceed drop
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.36

Field Name : axNetStatExtSslCpsExceedDrop
Field Type : Counter
Field Status : current
Description : Number of SSL CPS exceed drop
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.35

Field Name : axNetStatExtL7CpsExceedDrop
Field Type : Counter
Field Status : current
Description : Number of L7 CPS exceed drop
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.34

Field Name : axNetStatExtNatCpsExceedDrop
Field Type : Counter
Field Status : current
Description : Number of NAT CPS exceed drop
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.33

Field Name : axNetStatExtL4CpsExceedDrop
Field Type : Counter
Field Status : current
Description : Number of L4 CPS exceed drop
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.32

Field Name : axNetStatExtBwWaterMarkDrop
Field Type : Counter
Field Status : current
Description : Number of BW-Watermark drop

OID : 1.3.6.1.4.1.22610.2.4.3.11.90.31

Field Name : axNetStatExtBwLimitExceedDrop
Field Type : Counter
Field Status : current
Description : Number of BW-Limit Exceed drop
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.30

Field Name : axNetStatExtNatPortPreserveSucc
Field Type : Counter
Field Status : current
Description : Number of NAT Port Preserve Succ
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.29

Field Name : axNetStatExtNatPortPreserveTry
Field Type : Counter
Field Status : current
Description : Number of NAT Port Preserve Try
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.28

Field Name : axNetStatExtIgnoreMsl
Field Type : Counter
Field Status : current
Description : Number of ignore msl
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.27

Field Name : axNetStatExtTcpSynWithDataDrop
Field Type : Counter
Field Status : current
Description : Number of TCP SYN With Data Drop
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.26

Field Name : axNetStatExtTcpSynOtherFlagsDrop
Field Type : Counter
Field Status : current
Description : Number of TCP SYN Other Flags Drop
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.25

Field Name : axNetStatExtRstL7OnFailover
Field Type : Counter
Field Status : current
Description : Number of RST L7 on failover
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.24

Field Name : axNetStatExtResetUnknownConns
Field Type : Counter
Field Status : current
Description : Number of Reset unknown conn
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.23

Field Name : axNetStatExtNoResourceDrop
Field Type : Counter
Field Status : current
Description : Number of No resource drop
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.22

Field Name : axNetStatExtAnomalyPbslbDrop
Field Type : Counter

Field Status : current
Description : Number of Anomaly pbslb drop
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.21

Field Name : axNetStatExtAnomalyBadContent
Field Type : Counter
Field Status : current
Description : Number of Anomaly bad content
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.20

Field Name : axNetStatExtAnomalyZeroWindow
Field Type : Counter
Field Status : current
Description : Number of Anomaly zero window
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.19

Field Name : axNetStatExtAnomalyOutOfSeq
Field Type : Counter
Field Status : current
Description : Number of Anomaly out of sequence
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.18

Field Name : axNetStatExtTcpSynStaleSessionDrop
Field Type : Counter
Field Status : current
Description : Number of SYN stale sess drop
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.17

Field Name : axNetStatExtOutOfSeqAckDrop
Field Type : Counter
Field Status : current
Description : Number of Out of sequence ACK drop
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.16

Field Name : axNetStatExtTcpInvalidDrop
Field Type : Counter
Field Status : current
Description : Number of TCP invalid drop
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.15

Field Name : axNetStatExtFastAgingReset
Field Type : Counter
Field Status : current
Description : Number of Fast aging reset
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.14

Field Name : axNetStatExtFastAgingSet
Field Type : Counter
Field Status : current
Description : Number of Fast aging set
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.13

Field Name : axNetStatExtAutoReselectServer
Field Type : Counter
Field Status : current
Description : Number of Auto-reselect server
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.12

Field Name : axNetStatExtOtherSessionAgedOut
Field Type : Counter
Field Status : current
Description : Number of Other Session aged out
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.11

Field Name : axNetStatExtUdpSessionAgedOut
Field Type : Counter
Field Status : current
Description : Number of UDP Session aged out
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.10

Field Name : axNetStatExtTcpSessionAgedOut
Field Type : Counter
Field Status : current
Description : Number of TCP Session aged out
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.9

Field Name : axNetStatExtNoVportDrop
Field Type : Counter
Field Status : current
Description : Number of vport not matching drops
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.8

Field Name : axNetStatExtAutoNatIdMismatch
Field Type : Counter
Field Status : current
Description : Number of Auto NAT id mismatch
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.7

Field Name : axNetStatExtNatIcmpNoMatch
Field Type : Counter
Field Status : current
Description : Number of Source NAT ICMP no match
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.6

Field Name : axNetStatExtNatIcmpProcess
Field Type : Counter
Field Status : current
Description : Number of Source NAT ICMP process
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.5

Field Name : axNetStatExtNatNoRevRoute
Field Type : Counter
Field Status : current
Description : Number of Source NAT no rev route
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.4

Field Name : axNetStatExtNatNoFwdRoute
Field Type : Counter
Field Status : current
Description : Number of Source NAT no fwd route
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.3

Field Name : axNetStatExtL3Dsr
Field Type : Counter
Field Status : current
Description : Number of L3 DSR

OID : 1.3.6.1.4.1.22610.2.4.3.11.90.2

Field Name : axNetStatExtL2Dsr
Field Type : Counter
Field Status : current
Description : Number of L2 DSR
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.1

Field Name : axNetStatL4SynAttack
Field Type : Counter
Field Status : current
Description : Number of L4 SYN attacks
OID : 1.3.6.1.4.1.22610.2.4.3.11.47

Field Name : axNetStat2UDPReceive
Field Type : Counter64
Field Status : current
Description : Number of UDP packets received in the 64-bit counter.
OID : 1.3.6.1.4.1.22610.2.4.3.11.46

Field Name : axNetStat2TCPReceive
Field Type : Counter64
Field Status : current
Description : Number of TCP packets received in the 64-bit counter.
OID : 1.3.6.1.4.1.22610.2.4.3.11.45

Field Name : axNetStatInbandHMReassign
Field Type : Counter
Field Status : current
Description : Total number of Inband HM reassign.
OID : 1.3.6.1.4.1.22610.2.4.3.11.44

Field Name : axNetStatInbandHMRetry
Field Type : Counter
Field Status : current
Description : Total number of Inband HM retry.
OID : 1.3.6.1.4.1.22610.2.4.3.11.43

Field Name : axNetStatConnRateLimitResets
Field Type : Counter
Field Status : current
Description : Total number of Conn rate limit resets.
OID : 1.3.6.1.4.1.22610.2.4.3.11.42

Field Name : axNetStatConnRateLimitDrops
Field Type : Counter
Field Status : current
Description : Total number of Conn rate limit drops.
OID : 1.3.6.1.4.1.22610.2.4.3.11.41

Field Name : axNetStatCreateSSLSIDFail
Field Type : Counter
Field Status : current
Description : Total number of Create SSL SID failed.
OID : 1.3.6.1.4.1.22610.2.4.3.11.40

Field Name : axNetStatCreateSSLSIDSucc
Field Type : Counter

Field Status : current
Description : Total number of Create SSL SID successfully.
OID : 1.3.6.1.4.1.22610.2.4.3.11.39

Field Name : axNetStatServerSSLSIDNotMatch
Field Type : Counter
Field Status : current
Description : Total number of Server SSL SID not match.
OID : 1.3.6.1.4.1.22610.2.4.3.11.38

Field Name : axNetStatServerSSLSIDMatch
Field Type : Counter
Field Status : current
Description : Total number of Server SSL SID match.
OID : 1.3.6.1.4.1.22610.2.4.3.11.37

Field Name : axNetStatServerSSLSIDReset
Field Type : Counter
Field Status : current
Description : Total number of Server SSL SID reset.
OID : 1.3.6.1.4.1.22610.2.4.3.11.36

Field Name : axNetStatServerSSLSIDNotFound
Field Type : Counter
Field Status : current
Description : Total number of Server SSL SID not found.
OID : 1.3.6.1.4.1.22610.2.4.3.11.35

Field Name : axNetStatClientSSLSIDNotMatch
Field Type : Counter
Field Status : current
Description : Total number of Client SSL SID not match.
OID : 1.3.6.1.4.1.22610.2.4.3.11.34

Field Name : axNetStatClientSSLSIDMatch
Field Type : Counter
Field Status : current
Description : Total number of Client SSL SID match
OID : 1.3.6.1.4.1.22610.2.4.3.11.33

Field Name : axNetStatClientSSLSIDNotFound
Field Type : Counter
Field Status : current
Description : Total number of Client SSL SID not found.
OID : 1.3.6.1.4.1.22610.2.4.3.11.32

Field Name : axNetStatSSLSIDPersistFail
Field Type : Counter
Field Status : current
Description : Total number of SSL SID persist failed.
OID : 1.3.6.1.4.1.22610.2.4.3.11.31

Field Name : axNetStatSSLSIDPersistSucc
Field Type : Counter
Field Status : current
Description : Total number of SSL SID persist successful.
OID : 1.3.6.1.4.1.22610.2.4.3.11.30

Field Name : axNetStatSYNThrotte
Field Type : Counter
Field Status : current
Description : Total number of SYN Throttle.
OID : 1.3.6.1.4.1.22610.2.4.3.11.29

Field Name : axNetStatNoSYNPktDropACK
Field Type : Counter
Field Status : current
Description : Total number of No SYN pkt drops - ACK.
OID : 1.3.6.1.4.1.22610.2.4.3.11.28

Field Name : axNetStatNoSYNPktDropRST
Field Type : Counter
Field Status : current
Description : Total number of No SYN pkt drops - RST.
OID : 1.3.6.1.4.1.22610.2.4.3.11.27

Field Name : axNetStatNoSYNPktDropFIN
Field Type : Counter
Field Status : current
Description : Total number of No SYN pkt drops - FIN.
OID : 1.3.6.1.4.1.22610.2.4.3.11.26

Field Name : axNetStatTCPOutRSTProxy
Field Type : Counter
Field Status : current
Description : Total number of TCP out RST TCP proxy.
OID : 1.3.6.1.4.1.22610.2.4.3.11.25

Field Name : axNetStatTCPOutRSTStaleSess
Field Type : Counter
Field Status : current
Description : Total number of TCP out RST stale session.
OID : 1.3.6.1.4.1.22610.2.4.3.11.24

Field Name : axNetStatTCPOutRSTAFleX
Field Type : Counter
Field Status : current
Description : Total number of TCP out RST aFlex.
OID : 1.3.6.1.4.1.22610.2.4.3.11.23

Field Name : axNetStatTCPOutRSTACKattack
Field Type : Counter
Field Status : current
Description : Total number of TCP out RST ACK attack.
OID : 1.3.6.1.4.1.22610.2.4.3.11.22

Field Name : axNetStatTCPOutRSTL4Proxy
Field Type : Counter
Field Status : current
Description : Total number of TCP out RST L4 proxy.
OID : 1.3.6.1.4.1.22610.2.4.3.11.21

Field Name : axNetStatTCPOutRSTNoSYN
Field Type : Counter
Field Status : current
Description : Total number of TCP out RST no SYN.

OID : 1.3.6.1.4.1.22610.2.4.3.11.20

Field Name : axNetStatUDPNoSLB
Field Type : Counter
Field Status : current
Description : Total number of UDP packets in non SLB processing.
OID : 1.3.6.1.4.1.22610.2.4.3.11.19

Field Name : axNetStatTCPNoSLB
Field Type : Counter
Field Status : current
Description : Total number of TCP packets in non SLB processing.
OID : 1.3.6.1.4.1.22610.2.4.3.11.18

Field Name : axNetStatSessionAgingOut
Field Type : Counter
Field Status : current
Description : Number of sessions that have aged out.
OID : 1.3.6.1.4.1.22610.2.4.3.11.17

Field Name : axNetStataFlexDrop
Field Type : Counter
Field Status : current
Description : Number of packets dropped due to an aFlex.
OID : 1.3.6.1.4.1.22610.2.4.3.11.16

Field Name : axNetStatProxyNoSockDrop
Field Type : Counter
Field Status : current
Description : Number of packets dropped because the proxy did not have an available socket.
OID : 1.3.6.1.4.1.22610.2.4.3.11.15

Field Name : axNetStatConnLimitReset
Field Type : Counter
Field Status : current
Description : Number of connections reset because the server connection limit had been reached.
OID : 1.3.6.1.4.1.22610.2.4.3.11.14

Field Name : axNetStatConnLimitDrop
Field Type : Counter
Field Status : current
Description : Number of packets dropped because the server connection limit had been reached.
OID : 1.3.6.1.4.1.22610.2.4.3.11.13

Field Name : axNetStatNoSynPktDrop
Field Type : Counter
Field Status : current
Description : Number of SYN packets dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.11.12

Field Name : axNetStatNoVportDrop
Field Type : Counter
Field Status : current
Description : Number of times traffic was dropped because the requested virtual port was not available.
OID : 1.3.6.1.4.1.22610.2.4.3.11.11

Field Name : axNetStatTCPSynCookieFail
Field Type : Counter
Field Status : current
Description : Number of times a TCP SYN cookie failure occurred.
OID : 1.3.6.1.4.1.22610.2.4.3.11.10

Field Name : axNetStatSourceNATFail
Field Type : Counter
Field Status : current
Description : Number of times a source NAT failure occurred.
OID : 1.3.6.1.4.1.22610.2.4.3.11.9

Field Name : axNetStatServerSelFail
Field Type : Counter
Field Status : current
Description : Number of times selection of a real server failed.
OID : 1.3.6.1.4.1.22610.2.4.3.11.8

Field Name : axNetStatUDPReceive
Field Type : Counter
Field Status : current
Description : Number of UDP packets received.
OID : 1.3.6.1.4.1.22610.2.4.3.11.7

Field Name : axNetStatTCPReceive
Field Type : Counter
Field Status : current
Description : Number of TCP packets received.
OID : 1.3.6.1.4.1.22610.2.4.3.11.6

Field Name : axNetStatTCPSYNCookieSentFail
Field Type : Counter
Field Status : current
Description : The count of TCP SYN cookie sent fail.
OID : 1.3.6.1.4.1.22610.2.4.3.11.5

Field Name : axNetStatTCPSYNCookieSent
Field Type : Counter
Field Status : current
Description : The count of TCP SYN cookie sent.
OID : 1.3.6.1.4.1.22610.2.4.3.11.4

Field Name : axNetStatTCPSynRcv
Field Type : Counter
Field Status : current
Description : The count of TCP SYN packets received.
OID : 1.3.6.1.4.1.22610.2.4.3.11.3

Field Name : axNetStatTCPOutRst
Field Type : Counter
Field Status : current
Description : The count of TCP out Reset.
OID : 1.3.6.1.4.1.22610.2.4.3.11.2

Field Name : axNetStatIPOutNoRoute
Field Type : Counter
Field Status : current

Description : The count of IP out no route.
OID : 1.3.6.1.4.1.22610.2.4.3.11.1

Field Name : axNetStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The Net STAT entry.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1

Field Name : axNetStatEntryInbandHMReassign
Field Type : Counter
Field Status : current
Description : Number of Inband HM reassign.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.45

Field Name : axNetStatEntryInbandHMRetry
Field Type : Counter
Field Status : current
Description : Number of Inband HM retry.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.44

Field Name : axNetStatEntryConnRateLimitResets
Field Type : Counter
Field Status : current
Description : Number of Conn rate limit resets.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.43

Field Name : axNetStatEntryConnRateLimitDrops
Field Type : Counter
Field Status : current
Description : Number of Conn rate limit drops.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.42

Field Name : axNetStatEntryCreateSSLSIDFail
Field Type : Counter
Field Status : current
Description : Total number of Create SSL SID failed.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.41

Field Name : axNetStatEntryCreateSSLSIDSucc
Field Type : Counter
Field Status : current
Description : Total number of Create SSL SID successfully.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.40

Field Name : axNetStatEntryServerSSLSIDNotMatch
Field Type : Counter
Field Status : current
Description : Total number of Server SSL SID not match.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.39

Field Name : axNetStatEntryServerSSLSIDMatch
Field Type : Counter
Field Status : current
Description : Total number of Server SSL SID match.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.38

Field Name : axNetStatEntryServerSSLSIDReset

Field Type : Counter
Field Status : current
Description : Total number of Server SSL SID reset.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.37

Field Name : axNetStatEntryServerSSLSIDNotFound
Field Type : Counter
Field Status : current
Description : Total number of Server SSL SID not found.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.36

Field Name : axNetStatEntryClientSSLSIDNotMatch
Field Type : Counter
Field Status : current
Description : Total number of Client SSL SID not match.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.35

Field Name : axNetStatEntryClientSSLSIDMatch
Field Type : Counter
Field Status : current
Description : Total number of Client SSL SID match
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.34

Field Name : axNetStatEntryClientSSLSIDNotFound
Field Type : Counter
Field Status : current
Description : Total number of Client SSL SID not found.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.33

Field Name : axNetStatEntrySSLSIDPersistFail
Field Type : Counter
Field Status : current
Description : Total number of SSL SID persist failed.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.32

Field Name : axNetStatEntrySSLSIDPersistSucc
Field Type : Counter
Field Status : current
Description : Total number of SSL SID persist successful.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.31

Field Name : axNetStatEntrySYNThrotte
Field Type : Counter
Field Status : current
Description : Number of SYN Throttle.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.30

Field Name : axNetStatEntryNoSYNPktDropACK
Field Type : Counter
Field Status : current
Description : Number of No SYN pkt drops - ACK.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.29

Field Name : axNetStatEntryNoSYNPktDropRST
Field Type : Counter
Field Status : current
Description : Number of No SYN pkt drops - RST.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.28

Field Name : axNetStatEntryNoSYNPktDropFIN
Field Type : Counter
Field Status : current
Description : Number of No SYN pkt drops - FIN.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.27

Field Name : axNetStatEntryTCPOutRSTProxy
Field Type : Counter
Field Status : current
Description : Number of TCP out RST TCP proxy.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.26

Field Name : axNetStatEntryTCPOutRSTStaleSess
Field Type : Counter
Field Status : current
Description : Number of TCP out RST stale session.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.25

Field Name : axNetStatEntryTCPOutRSTAFleX
Field Type : Counter
Field Status : current
Description : Number of TCP out RST aFlex.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.24

Field Name : axNetStatEntryTCPOutRSTACKattack
Field Type : Counter
Field Status : current
Description : Number of TCP out RST ACK attack.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.23

Field Name : axNetStatEntryTCPOutRSTL4Proxy
Field Type : Counter
Field Status : current
Description : Number of TCP out RST L4 proxy.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.22

Field Name : axNetStatEntryTCPOutRSTNoSYN
Field Type : Counter
Field Status : current
Description : Number of TCP out RST no SYN.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.21

Field Name : axNetStatUDPsNoSLB
Field Type : Counter
Field Status : current
Description : Number of UDP packets in non SLB processing.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.20

Field Name : axNetStatTCPsNoSLB
Field Type : Counter
Field Status : current
Description : Number of TCP packets in non SLB processing.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.19

Field Name : axNetStatSessionsAgingOut
Field Type : Counter
Field Status : current

Description : Number of sessions that have aged out.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.18

Field Name : axNetStataFlexDrops
Field Type : Counter
Field Status : current
Description : Number of packets dropped due to an aFlex.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.17

Field Name : axNetStatProxyNoSockDrops
Field Type : Counter
Field Status : current
Description : Number of packets dropped because the proxy did not have an available socket.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.16

Field Name : axNetStatConnLimitResets
Field Type : Counter
Field Status : current
Description : Number of connections reset because the server connection limit had been reached.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.15

Field Name : axNetStatConnLimitDrops
Field Type : Counter
Field Status : current
Description : Number of packets dropped because the server connection limit had been reached.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.14

Field Name : axNetStatNoSynPktDrops
Field Type : Counter
Field Status : current
Description : Number of SYN packets dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.13

Field Name : axNetStatNoVportDrops
Field Type : Counter
Field Status : current
Description : Number of times traffic was dropped because the requested virtual port was not available.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.12

Field Name : axNetStatTCPSynCookieFails
Field Type : Counter
Field Status : current
Description : Number of times a TCP SYN cookie failure occurred.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.11

Field Name : axNetStatSourceNATFails
Field Type : Counter
Field Status : current
Description : Number of times a source NAT failure occurred.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.10

Field Name : axNetStatServerSelFails
Field Type : Counter
Field Status : current
Description : Number of times selection of a real server failed.

OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.9

Field Name : axNetStatUDPRcv
Field Type : Counter
Field Status : current
Description : Number of UDP packets received.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.8

Field Name : axNetStatTCPRcv
Field Type : Counter
Field Status : current
Description : Number of TCP packets received.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.7

Field Name : axNetStatTCPSYNCookieSntFail
Field Type : Counter
Field Status : current
Description : Number of TCP SYN cookie send attempts that failed.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.6

Field Name : axNetStatTCPSYNCookieSnt
Field Type : Counter
Field Status : current
Description : Number of TCP SYN cookies sent.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.5

Field Name : axNetStatTCPSynRecv
Field Type : Counter
Field Status : current
Description : Number of TCP SYN packets received.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.4

Field Name : axNetStatTCPOutReset
Field Type : Counter
Field Status : current
Description : Number of TCP Resets sent.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.3

Field Name : axNetStatIPOutNoRt
Field Type : Counter
Field Status : current
Description : Number of IP packets that could not be routed.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.2

Field Name : axNetStatCpuIndex
Field Type : Gauge
Field Status : current
Description : The Module Index of Net STAT table
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.1

Field Name : axFtpStatOutConnData
Field Type : Integer32
Field Status : current
Description : The total count of out of data connections.
OID : 1.3.6.1.4.1.22610.2.4.3.10.6

Field Name : axFtpStatTotalDataSession
Field Type : INTEGER

Field Status : current
Description : The total count of data sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.10.5

Field Name : axFtpStatOutConnCtrl
Field Type : INTEGER
Field Status : current
Description : The count of out of control connections.
OID : 1.3.6.1.4.1.22610.2.4.3.10.4

Field Name : axFtpStatALGPktReXmit
Field Type : INTEGER
Field Status : current
Description : The count of ALG packets rexmitted.
OID : 1.3.6.1.4.1.22610.2.4.3.10.3

Field Name : axFtpStatTotalALGPkt
Field Type : INTEGER
Field Status : current
Description : The total count of ALG packets.
OID : 1.3.6.1.4.1.22610.2.4.3.10.2

Field Name : axFtpStatTotalCtrlSession
Field Type : INTEGER
Field Status : current
Description : The total count of control sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.10.1

Field Name : axSslStatSSLFailedCryptoOperation
Field Type : INTEGER
Field Status : current
Description : Number of times when the crypto opertion fails.
OID : 1.3.6.1.4.1.22610.2.4.3.9.10

Field Name : axSslStatSSLHWRingFull
Field Type : INTEGER
Field Status : current
Description : Number of times the AX software was unable to enqueue an SSL record to the SSL processor for encryption/decryption.(Number of times the processor reached its performance limit.)
OID : 1.3.6.1.4.1.22610.2.4.3.9.9

Field Name : axSslStatSSLNoHWContextMem
Field Type : INTEGER
Field Status : current
Description : Number of times the encryption processor was unable to allocate memory.
OID : 1.3.6.1.4.1.22610.2.4.3.9.8

Field Name : axSslStatSSLFailedCAVfy
Field Type : INTEGER
Field Status : current
Description : Number of times an SSL session was terminated due to a certificate verification failure.
OID : 1.3.6.1.4.1.22610.2.4.3.9.7

Field Name : axSslStatTable
Field Type : TABLE
Field Status : current

Description : The SSL STAT table.
OID : 1.3.6.1.4.1.22610.2.4.3.9.6

Field Name : axSslStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The SSL STAT entry.
OID : 1.3.6.1.4.1.22610.2.4.3.9.6.1

Field Name : axSslStatAvailCryptoEngine
Field Type : Counter
Field Status : current
Description : The number of available crypto engines.
OID : 1.3.6.1.4.1.22610.2.4.3.9.6.1.3

Field Name : axSslStatEnableCryptoEngine
Field Type : Counter
Field Status : current
Description : The number of enabled crypto engines.
OID : 1.3.6.1.4.1.22610.2.4.3.9.6.1.2

Field Name : axSslStatModuleIndex
Field Type : Integer32
Field Status : current
Description : The Module Index of SSL STAT table
OID : 1.3.6.1.4.1.22610.2.4.3.9.6.1.1

Field Name : axSslStatSSLMemUsage
Field Type : INTEGER
Field Status : current
Description : The SSL Memory usage(Byte).
OID : 1.3.6.1.4.1.22610.2.4.3.9.5

Field Name : axSslStatFailSSLHandshake
Field Type : Counter64
Field Status : current
Description : Failed SSL handshake.
OID : 1.3.6.1.4.1.22610.2.4.3.9.4

Field Name : axSslStatTotalSSLConn
Field Type : Counter64
Field Status : current
Description : Total SSL connections.
OID : 1.3.6.1.4.1.22610.2.4.3.9.3

Field Name : axSslStatCurrSSLConn
Field Type : Counter64
Field Status : current
Description : Current SSL Connections.
OID : 1.3.6.1.4.1.22610.2.4.3.9.2

Field Name : axSslStatSSLModNum
Field Type : INTEGER
Field Status : current
Description : The number of SSL modules.
OID : 1.3.6.1.4.1.22610.2.4.3.9.1

Field Name : axTCPProxyStatTable

Field Type : TABLE
Field Status : current
Description : The TCP proxy STAT table.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10

Field Name : axTcpProxyStatTotalRstSent
Field Type : INTEGER
Field Status : current
Description : The total count of reset sent.
OID : 1.3.6.1.4.1.22610.2.4.3.8.9

Field Name : axTcpProxyStatTotalRstRcvOnEstConn
Field Type : INTEGER
Field Status : current
Description : The total count of reset received on established connection.
OID : 1.3.6.1.4.1.22610.2.4.3.8.8

Field Name : axTcpProxyStatTotalReXmitPkt
Field Type : INTEGER
Field Status : current
Description : The total count of re-transmitted packets.
OID : 1.3.6.1.4.1.22610.2.4.3.8.7

Field Name : axTcpProxyStatTotalOutTCPPkt
Field Type : INTEGER
Field Status : current
Description : The total count of sent tcp packets.
OID : 1.3.6.1.4.1.22610.2.4.3.8.6

Field Name : axTcpProxyStatTotalInTCPPacket
Field Type : INTEGER
Field Status : current
Description : The total count of received tcp packets.
OID : 1.3.6.1.4.1.22610.2.4.3.8.5

Field Name : axTcpProxyStatTotalConnAttemptFail
Field Type : INTEGER
Field Status : current
Description : The total count of connectting attempt fails.
OID : 1.3.6.1.4.1.22610.2.4.3.8.4

Field Name : axTcpProxyStatTotalPassiveOpenConn
Field Type : INTEGER
Field Status : current
Description : The total count of passively opened tcp connections.
OID : 1.3.6.1.4.1.22610.2.4.3.8.3

Field Name : axTcpProxyStatTotalActiveOpenConn
Field Type : INTEGER
Field Status : current
Description : The total count of actively opened tcp Connections.
OID : 1.3.6.1.4.1.22610.2.4.3.8.2

Field Name : axTcpProxyStatTotalCurrEstConn
Field Type : INTEGER
Field Status : current
Description : The total count of currently established tcp Connections.
OID : 1.3.6.1.4.1.22610.2.4.3.8.1

Field Name : axTCPProxyStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The TCP proxy STAT entry.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1

Field Name : axTcpProxyStatTCPClosingState
Field Type : Counter
Field Status : current
Description : The count of TCP connections in closing state.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.26

Field Name : axTcpProxyStatTCPListenState
Field Type : Counter
Field Status : current
Description : The count of TCP connections in listen state.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.25

Field Name : axTcpProxyStatTCPLastACKState
Field Type : Counter
Field Status : current
Description : The count of TCP connections in lastACK state.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.24

Field Name : axTcpProxyStatTCPCloseWState
Field Type : Counter
Field Status : current
Description : The count of TCP connections in closeW state.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.23

Field Name : axTcpProxyStatTCPCloseState
Field Type : Counter
Field Status : current
Description : The count of TCP connections in close state.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.22

Field Name : axTcpProxyStatTimeWstate
Field Type : Counter
Field Status : current
Description : The count of TCP connections in TCP TimeW state.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.21

Field Name : axTcpProxyStatTCPFINW2State
Field Type : Counter
Field Status : current
Description : The count of TCP connections in FIN-W2 state.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.20

Field Name : axTcpProxyStatTCPFINW1State
Field Type : Counter
Field Status : current
Description : The count of TCP connections in FIN-W1 state.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.19

Field Name : axTcpProxyStatTCPSYNRCVState
Field Type : Counter
Field Status : current

Description : The count of TCP connections in SYN-RCV state.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.18

Field Name : axTcpProxyStatTCPSYNSNTState
Field Type : Counter
Field Status : current
Description : The count of TCP connections in SYN-SNT state.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.17

Field Name : axTcpProxyStatTotalTxBuf
Field Type : Counter
Field Status : current
Description : The size of TX buffer.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.16

Field Name : axTcpProxyStatTotalRxBuf
Field Type : Counter
Field Status : current
Description : The size of Rx buffer.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.15

Field Name : axTcpProxyStatMemAlloc
Field Type : Counter
Field Status : current
Description : The size of allocated memory used by tcp proxy.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.14

Field Name : axTcpProxyStatOrphanSocket
Field Type : Counter
Field Status : current
Description : The count of orphan sockets.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.13

Field Name : axTcpProxyStatSocketAlloc
Field Type : Counter
Field Status : current
Description : The count of socket allocated.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.12

Field Name : axTcpProxyStatInputErr
Field Type : Counter
Field Status : current
Description : The count of Input Error.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.11

Field Name : axTcpProxyStatRstSent
Field Type : Counter
Field Status : current
Description : The count of Reset Sent.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.10

Field Name : axTcpProxyStatRstRvdEstConn
Field Type : Counter
Field Status : current
Description : The count of reset received on established connections.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.9

Field Name : axTcpProxyStatReTranPkt

Field Type : Counter
Field Status : current
Description : The count of re-transmit packets.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.8

Field Name : axTcpProxyStatTotalOutPkt
Field Type : Counter
Field Status : current
Description : The total count of packets sent.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.7

Field Name : axTcpProxyStatTotalInTCPPkt
Field Type : Counter
Field Status : current
Description : The total count of packet received.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.6

Field Name : axTcpProxyStatConnAttempFail
Field Type : Counter
Field Status : current
Description : The count of connecting attempt fail.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.5

Field Name : axTcpProxyStatPassiveOpenConns
Field Type : Counter
Field Status : current
Description : The count of passive open connections.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.4

Field Name : axTcpProxyStatActiveOpenConns
Field Type : Counter
Field Status : current
Description : The count of active open connections.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.3

Field Name : axTcpProxyStatCurrEstConns
Field Type : Counter
Field Status : current
Description : The count of currently established connections.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.2

Field Name : axTcpProxyStatCpuIndex
Field Type : Integer32
Field Status : current
Description : The cpu index of TCP proxy STAT table.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.1

Field Name : axHttpProxyStatTable
Field Type : TABLE
Field Status : current
Description : The http proxy STAT table.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18

Field Name : axHttpProxyStatTotalSNATErr
Field Type : INTEGER
Field Status : current
Description : The total count of Source NAT failed.
OID : 1.3.6.1.4.1.22610.2.4.3.7.17

Field Name : axHttpProxyStatTotalSvrConn
Field Type : INTEGER
Field Status : current
Description : The total count of server connections made.
OID : 1.3.6.1.4.1.22610.2.4.3.7.16

Field Name : axHttpProxyStatTotalPreMatureClose
Field Type : INTEGER
Field Status : current
Description : The total count of server premature closed connections.
OID : 1.3.6.1.4.1.22610.2.4.3.7.15

Field Name : axHttpProxyStatTotalSvrReSel
Field Type : INTEGER
Field Status : current
Description : The total count of server reselect.
OID : 1.3.6.1.4.1.22610.2.4.3.7.14

Field Name : axHttpProxyStatTotalReqPktOutOrder
Field Type : INTEGER
Field Status : current
Description : The total count of request packet out of order.
OID : 1.3.6.1.4.1.22610.2.4.3.7.13

Field Name : axHttpProxyStatTotalReqReXmit
Field Type : INTEGER
Field Status : current
Description : The total count of retransmitted http request.
OID : 1.3.6.1.4.1.22610.2.4.3.7.12

Field Name : axHttpProxyStatTotalFwdDataReqErr
Field Type : INTEGER
Field Status : current
Description : The total count of firewall data request failed.
OID : 1.3.6.1.4.1.22610.2.4.3.7.11

Field Name : axHttpProxyStatTotalFwdReqErr
Field Type : INTEGER
Field Status : current
Description : The total count of firewall request fail.
OID : 1.3.6.1.4.1.22610.2.4.3.7.10

Field Name : axHttpProxyStatTotalSvrSelErr
Field Type : INTEGER
Field Status : current
Description : The total count of server select failed.
OID : 1.3.6.1.4.1.22610.2.4.3.7.9

Field Name : axHttpProxyStatTotalReqErr
Field Type : INTEGER
Field Status : current
Description : The total count of request parse failed.
OID : 1.3.6.1.4.1.22610.2.4.3.7.8

Field Name : axHttpProxyStatTotalNoTuple
Field Type : INTEGER
Field Status : current

Description : The total count of no tuple fail.
OID : 1.3.6.1.4.1.22610.2.4.3.7.7

Field Name : axHttpProxyStatTotalSRst
Field Type : INTEGER
Field Status : current
Description : The total count of http connections reset by server.
OID : 1.3.6.1.4.1.22610.2.4.3.7.6

Field Name : axHttpProxyStatTotalCRst
Field Type : INTEGER
Field Status : current
Description : The total count of http connections reset by client.
OID : 1.3.6.1.4.1.22610.2.4.3.7.5

Field Name : axHttpProxyStatTotalNoProxy
Field Type : INTEGER
Field Status : current
Description : The total count of no proxy fail.
OID : 1.3.6.1.4.1.22610.2.4.3.7.4

Field Name : axHttpProxyStatTotalSuccReq
Field Type : INTEGER
Field Status : current
Description : The total count of http requests which connected
: successful.
OID : 1.3.6.1.4.1.22610.2.4.3.7.3

Field Name : axHttpProxyStatTotalReq
Field Type : INTEGER
Field Status : current
Description : The total count of http requests.
OID : 1.3.6.1.4.1.22610.2.4.3.7.2

Field Name : axHttpProxyStatTotalConn
Field Type : INTEGER
Field Status : current
Description : The total count of proxy connections.
OID : 1.3.6.1.4.1.22610.2.4.3.7.1

Field Name : axHttpProxyStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The http proxy STAT entry.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1

Field Name : axHttpProxyStatServerConnMade
Field Type : Counter
Field Status : current
Description : The count of server connections made.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.18

Field Name : axHttpProxyStatServerPreMatureClose
Field Type : Counter
Field Status : current
Description : The count of server premature closed connections.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.17

Field Name : axHttpProxyStatServerReSel
Field Type : Counter
Field Status : current
Description : The count of server reselect.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.16

Field Name : axHttpProxyStatReqPktOutOrder
Field Type : Counter
Field Status : current
Description : The count of request packet out of order.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.15

Field Name : axHttpProxyStatReqReTran
Field Type : Counter
Field Status : current
Description : The count of retransmitted http request.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.14

Field Name : axHttpProxyStatFwdReqDataFail
Field Type : Counter
Field Status : current
Description : The count of firewall data request failed.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.13

Field Name : axHttpProxyStatFwdReqFail
Field Type : Counter
Field Status : current
Description : The count of firewall request fail.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.12

Field Name : axHttpProxyStatServerSelFail
Field Type : Counter
Field Status : current
Description : he count of server select failed.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.11

Field Name : axHttpProxyStatParseReqFail
Field Type : Counter
Field Status : current
Description : The count of request parse failed.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.10

Field Name : axHttpProxyStatNoTupleErr
Field Type : Counter
Field Status : current
Description : The count of no tuple fail.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.9

Field Name : axHttpProxyStatServerRst
Field Type : Counter
Field Status : current
Description : The count of http connections reset by server.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.8

Field Name : axHttpProxyStatClientRst
Field Type : Counter
Field Status : current
Description : The count of http connections reset by client.

OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.7

Field Name : axHttpProxyStatNoProxyErr
Field Type : Counter
Field Status : current
Description : The count of no proxy error.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.6

Field Name : axHttpProxyStatHttpReqSucc
Field Type : Counter
Field Status : current
Description : The count of http reqests which connected successfully.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.5

Field Name : axHttpProxyStatHttpReq
Field Type : Counter
Field Status : current
Description : The count of http requests.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.4

Field Name : axHttpProxyStatTotalProxyConns
Field Type : Counter
Field Status : current
Description : The total count of http proxy connections of current cpu.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.3

Field Name : axHttpProxyStatCurrProxyConns
Field Type : Counter
Field Status : current
Description : The count of current http proxy connections
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.2

Field Name : axHttpProxyStatCpuIndex
Field Type : Integer32
Field Status : current
Description : The cpu Index of http proxy STAT table.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.1

Field Name : axFastHttpProxyStatTable
Field Type : TABLE
Field Status : current
Description : The fast http proxy status table.
OID : 1.3.6.1.4.1.22610.2.4.3.6.18

Field Name : axFastHttpProxyStatTotalSNATErr
Field Type : INTEGER
Field Status : current
Description : The total count of Source NAT failed.
OID : 1.3.6.1.4.1.22610.2.4.3.6.17

Field Name : axFastHttpProxyStatTotalSvrConn
Field Type : INTEGER
Field Status : current
Description : The total count of server connections made.
OID : 1.3.6.1.4.1.22610.2.4.3.6.16

Field Name : axFastHttpProxyStatTotalPreMatureClose
Field Type : INTEGER

Field Status : current
Description : The total count of server premature closed connections.
OID : 1.3.6.1.4.1.22610.2.4.3.6.15

Field Name : axFastHttpProxyStatTotalSvrReSel
Field Type : INTEGER
Field Status : current
Description : The total count of server reselect.
OID : 1.3.6.1.4.1.22610.2.4.3.6.14

Field Name : axFastHttpProxyStatTotalReqPktOutOrder
Field Type : INTEGER
Field Status : current
Description : The total count of request packet out of order.
OID : 1.3.6.1.4.1.22610.2.4.3.6.13

Field Name : axFastHttpProxyStatTotalReqReXmit
Field Type : INTEGER
Field Status : current
Description : The total count of retransmitted http request.
OID : 1.3.6.1.4.1.22610.2.4.3.6.12

Field Name : axFastHttpProxyStatTotalFwdDataReqErr
Field Type : INTEGER
Field Status : current
Description : The total count of firewall data request failed.
OID : 1.3.6.1.4.1.22610.2.4.3.6.11

Field Name : axFastHttpProxyStatTotalFwdReqErr
Field Type : INTEGER
Field Status : current
Description : The total count of firewall request fail.
OID : 1.3.6.1.4.1.22610.2.4.3.6.10

Field Name : axFastHttpProxyStatTotalSvrSelErr
Field Type : INTEGER
Field Status : current
Description : The total count of server select failed.
OID : 1.3.6.1.4.1.22610.2.4.3.6.9

Field Name : axFastHttpProxyStatTotalReqErr
Field Type : INTEGER
Field Status : current
Description : The total count of request parse failed.
OID : 1.3.6.1.4.1.22610.2.4.3.6.8

Field Name : axFastHttpProxyStatTotalNoTuple
Field Type : INTEGER
Field Status : current
Description : The total count of no tuple fail.
OID : 1.3.6.1.4.1.22610.2.4.3.6.7

Field Name : axFastHttpProxyStatTotalSRst
Field Type : INTEGER
Field Status : current
Description : The total count of http connections reset by server.
OID : 1.3.6.1.4.1.22610.2.4.3.6.6

Field Name : axFastHttpProxyStatTotalCRst
Field Type : INTEGER
Field Status : current
Description : The total count of http connections reset by client.
OID : 1.3.6.1.4.1.22610.2.4.3.6.5

Field Name : axFastHttpProxyStatTotalNoProxy
Field Type : INTEGER
Field Status : current
Description : The total count of no proxy fail.
OID : 1.3.6.1.4.1.22610.2.4.3.6.4

Field Name : axFastHttpProxyStatTotalSuccReq
Field Type : INTEGER
Field Status : current
Description : The total count of http requests which connected successful.
OID : 1.3.6.1.4.1.22610.2.4.3.6.3

Field Name : axFastHttpProxyStatTotalReq
Field Type : INTEGER
Field Status : current
Description : The total count of http requests.
OID : 1.3.6.1.4.1.22610.2.4.3.6.2

Field Name : axFastHttpProxyStatTotalConn
Field Type : INTEGER
Field Status : current
Description : The total count of proxy connections.
OID : 1.3.6.1.4.1.22610.2.4.3.6.1

Field Name : axFastHttpProxyStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The fast http proxy status entry.
OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1

Field Name : axFastHttpProxyStatServerConnMade
Field Type : Counter
Field Status : current
Description : The count of server connections made.
OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.18

Field Name : axFastHttpProxyStatServerPreMatureClose
Field Type : Counter
Field Status : current
Description : The count of server premature closed connections.
OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.17

Field Name : axFastHttpProxyStatServerReSel
Field Type : Counter
Field Status : current
Description : The count of server reselect.
OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.16

Field Name : axFastHttpProxyStatReqPktOutOrder
Field Type : Counter
Field Status : current
Description : The count of request packet out of order.

OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.15

Field Name : axFastHttpProxyStatReqReTran
Field Type : Counter
Field Status : current
Description : The count of retransmitted http request.
OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.14

Field Name : axFastHttpProxyStatFwdReqDataFail
Field Type : Counter
Field Status : current
Description : The count of firewall data request failed.
OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.13

Field Name : axFastHttpProxyStatFwdReqFail
Field Type : Counter
Field Status : current
Description : The count of firewall request fail.
OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.12

Field Name : axFastHttpProxyStatServerSelFail
Field Type : Counter
Field Status : current
Description : The count of server select failed.
OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.11

Field Name : axFastHttpProxyStatParseReqFail
Field Type : Counter
Field Status : current
Description : The count of request parse failed.
OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.10

Field Name : axFastHttpProxyStatNoTupleErr
Field Type : Counter
Field Status : current
Description : The count of no tuple fail.
OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.9

Field Name : axFastHttpProxyStatServerRst
Field Type : Counter
Field Status : current
Description : The count of http connections reset by server.
OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.8

Field Name : axFastHttpProxyStatClientRst
Field Type : Counter
Field Status : current
Description : The count of http connections reset by client.
OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.7

Field Name : axFastHttpProxyStatNoProxyErr
Field Type : Counter
Field Status : current
Description : The count of no proxy error.
OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.6

Field Name : axFastHttpProxyStatHttpReqSucc
Field Type : Counter

Field Status : current
Description : The count of http reqests which connected successfully.
OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.5

Field Name : axFastHttpProxyStatHttpReq
Field Type : Counter
Field Status : current
Description : The count of http requests.
OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.4

Field Name : axFastHttpProxyStatTotalProxyConns
Field Type : Counter
Field Status : current
Description : The total count of fast http proxy connections of current cpu.
OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.3

Field Name : axFastHttpProxyStatCurrProxyConns
Field Type : Counter
Field Status : current
Description : The count of current fast http proxy connections
OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.2

Field Name : axFastHttpProxyStatCpuIndex
Field Type : Integer32
Field Status : current
Description : The cpu index of fast http proxy STAT table
OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.1

Field Name : axConnReuseStatTotalMissedResponse
Field Type : INTEGER
Field Status : current
Description : Number of missed responses to HTTP requests.
OID : 1.3.6.1.4.1.22610.2.4.3.5.10

Field Name : axConnReuseStatTotalLongResponse
Field Type : INTEGER
Field Status : current
Description : Number of responses that took too long.
OID : 1.3.6.1.4.1.22610.2.4.3.5.9

Field Name : axConnReuseStatTotalDelayedUNBound
Field Type : INTEGER
Field Status : current
Description : Number of connections whose unbinding was delayed.
OID : 1.3.6.1.4.1.22610.2.4.3.5.8

Field Name : axConnReuseStatTable
Field Type : TABLE
Field Status : current
Description : The connection-reuse status table.
OID : 1.3.6.1.4.1.22610.2.4.3.5.7

Field Name : axConnReuseStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The connection-reuse entry.
OID : 1.3.6.1.4.1.22610.2.4.3.5.7.1

Field Name : axConnReuseStatTotalMissedRes
Field Type : Counter
Field Status : current
Description : Number of missed responses to HTTP requests.
OID : 1.3.6.1.4.1.22610.2.4.3.5.7.1.10

Field Name : axConnReuseStatTotalLongRes
Field Type : Counter
Field Status : current
Description : Number of responses that took too long.
OID : 1.3.6.1.4.1.22610.2.4.3.5.7.1.9

Field Name : axConnReuseStatTotalDelayedUNBind
Field Type : Counter
Field Status : current
Description : Number of connections whose unbinding was delayed.
OID : 1.3.6.1.4.1.22610.2.4.3.5.7.1.8

Field Name : axConnReuseStatTotalUNBind
Field Type : Counter
Field Status : current
Description : The count of unbound connection-reuse sessions
OID : 1.3.6.1.4.1.22610.2.4.3.5.7.1.7

Field Name : axConnReuseStatTotalBind
Field Type : Counter
Field Status : current
Description : The count of bound connection-reuse sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.5.7.1.6

Field Name : axConnReuseStatTotalTerm
Field Type : Counter
Field Status : current
Description : The count of terminated connection-reuse sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.5.7.1.5

Field Name : axConnReuseStatTotalEst
Field Type : Counter
Field Status : current
Description : The count of established connection-reuse sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.5.7.1.4

Field Name : axConnReuseStatActivePersist
Field Type : Counter
Field Status : current
Description : The count of active persistent connection-reuse sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.5.7.1.3

Field Name : axConnReuseStatOpenPersist
Field Type : Counter
Field Status : current
Description : The count of open persistent connection-reuse sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.5.7.1.2

Field Name : axConnReuseStatCpuIndex
Field Type : Integer32
Field Status : current
Description : Cpu Index to the connection-reuse STAT.

OID : 1.3.6.1.4.1.22610.2.4.3.5.7.1.1

Field Name : axConnReuseStatTotalUNBound
Field Type : INTEGER
Field Status : current
Description : The total count of unbound connection-reuse sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.5.6

Field Name : axConnReuseStatTotalBound
Field Type : INTEGER
Field Status : current
Description : The total count of bound connection-reuse sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.5.5

Field Name : axConnReuseStatTotalTerminated
Field Type : INTEGER
Field Status : current
Description : The total count of terminated connection-reuse sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.5.4

Field Name : axConnReuseStatTotalEstablished
Field Type : INTEGER
Field Status : current
Description : The total count of established connection-reuse sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.5.3

Field Name : axConnReuseStatTotalActivePersist
Field Type : INTEGER
Field Status : current
Description : The total count of active persistent connection-reuse sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.5.2

Field Name : axConnReuseStatTotalOpenPersist
Field Type : INTEGER
Field Status : current
Description : The total count of open persistent connection-reuse sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.5.1

Field Name : axVirtualServerNameStatTable
Field Type : TABLE
Field Status : current
Description : A table containing statistic information of virtual servers.
OID : 1.3.6.1.4.1.22610.2.4.3.4.5.1

Field Name : axVirtualServerNameStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axVirtualServerNameStat Table
OID : 1.3.6.1.4.1.22610.2.4.3.4.5.1.1

Field Name : axVirtualServerNameStatPeakConns
Field Type : Counter
Field Status : current
Description : The number of peak connections
OID : 1.3.6.1.4.1.22610.2.4.3.4.5.1.1.14

Field Name : axVirtualServerNameStatTotalSuccL7Reqs
Field Type : Counter64

Field Status : current
Description : The number of successful L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.4.5.1.1.13

Field Name : axVirtualServerNameStatTotalCurrL7Reqs
Field Type : Counter64
Field Status : current
Description : The number of current L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.4.5.1.1.12

Field Name : axVirtualServerNameStatTotalL7Reqs
Field Type : Counter64
Field Status : current
Description : The total number of L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.4.5.1.1.11

Field Name : axVirtualServerNameStatDisplayStatus
Field Type : EnumVal
Field Status : current
Description : The display status of this virtual server:
: Disabled(0), AllUp(1), FunctionalUp(2), PartialUp(3), Stopped(4).
OID : 1.3.6.1.4.1.22610.2.4.3.4.5.1.1.10

Field Name : axVirtualServerNameStatStatus
Field Type : EnumVal
Field Status : current
Description : The current virtual server status.
OID : 1.3.6.1.4.1.22610.2.4.3.4.5.1.1.9

Field Name : axVirtualServerNameStatCurConns
Field Type : Integer32
Field Status : current
Description : The current connections from client side.
OID : 1.3.6.1.4.1.22610.2.4.3.4.5.1.1.8

Field Name : axVirtualServerNameStatTotConns
Field Type : Counter64
Field Status : current
Description : The total connections from client side.
OID : 1.3.6.1.4.1.22610.2.4.3.4.5.1.1.7

Field Name : axVirtualServerNameStatBytesOut
Field Type : Counter64
Field Status : current
Description : The number of bytes sent from server to client.
OID : 1.3.6.1.4.1.22610.2.4.3.4.5.1.1.5

Field Name : axVirtualServerNameStatPktsOut
Field Type : Counter64
Field Status : current
Description : The number of packets sent from server to client.
OID : 1.3.6.1.4.1.22610.2.4.3.4.5.1.1.4

Field Name : axVirtualServerNameStatBytesIn
Field Type : Counter64
Field Status : current
Description : The number of bytes received from client to server.
OID : 1.3.6.1.4.1.22610.2.4.3.4.5.1.1.3

Field Name : axVirtualServerNameStatPktsIn
Field Type : Counter64
Field Status : current
Description : The number of packets received from client to server.
OID : 1.3.6.1.4.1.22610.2.4.3.4.5.1.1.2

Field Name : axVirtualServerStatDisplayName
Field Type : String
Field Status : current
Description : The name of this virtual server.
OID : 1.3.6.1.4.1.22610.2.4.3.4.5.1.1.1

Field Name : axVirtualServerPortStatTable
Field Type : TABLE
Field Status : current
Description : A table containing statistic information of virtual server service ports.
OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1

Field Name : axVirtualServerPortStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axVirtualServerPortStat Table
OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1

Field Name : axVirtualServerPortStatAddressType
Field Type : EnumVal
Field Status : current
Description : The type of axVirtualServerPortStatAddress:
: unknown(0), ipv4(1), ipv6(2)...
OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.18

Field Name : axVirtualServerPortStatPeakConns
Field Type : Counter
Field Status : current
Description : The number of peak connections
OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.17

Field Name : axVirtualServerPortStatTotalSuccL7Reqs
Field Type : Counter64
Field Status : current
Description : The number of successful L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.16

Field Name : axVirtualServerPortStatTotalCurrL7Reqs
Field Type : Counter64
Field Status : current
Description : The number of current L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.15

Field Name : axVirtualServerPortStatTotalL7Reqs
Field Type : Counter64
Field Status : current
Description : The total number of L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.14

Field Name : axVirtualServerStatPortDisplayStatus
Field Type : EnumVal

Field Status : current
Description : The display status of this virtual server port:
: Disabled(0), AllUp(1), FunctionalUp(2), Stopped(4).
OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.13

Field Name : axVirtualServerPortStatCurConns
Field Type : Integer32
Field Status : current
Description : Current connections from client side.
OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.12

Field Name : axVirtualServerPortStatTotConns
Field Type : Counter64
Field Status : current
Description : Total connections from client side.
OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.11

Field Name : axVirtualServerPortStatBytesOut
Field Type : Counter64
Field Status : current
Description : The number of bytes sent from server to client.
OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.9

Field Name : axVirtualServerPortStatPktsOut
Field Type : Counter64
Field Status : current
Description : The number of packets sent from server to client.
OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.8

Field Name : axVirtualServerPortStatBytesIn
Field Type : Counter64
Field Status : current
Description : The number of bytes received from client to server.
OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.7

Field Name : axVirtualServerPortStatPktsIn
Field Type : Counter64
Field Status : current
Description : The number of packets received from client to server.
OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.6

Field Name : axVirtualServerStatPortStatus
Field Type : EnumVal
Field Status : current
Description : The status of this virtual server port.
OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.5

Field Name : axVirtualServerPortStatName
Field Type : String
Field Status : current
Description : The name of the virtual server
OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.4

Field Name : axVirtualServerStatPortNum
Field Type : Integer32
Field Status : current
Description : The service port number.
OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.3

Field Name : axVirtualServerStatPortType
Field Type : EnumVal
Field Status : current
Description : The port type of a virtual server port
OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.2

Field Name : axVirtualServerPortStatAddress
Field Type : String
Field Status : current
Description : The ip address of this virtual address.
OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.1

Field Name : axVirtualServerPortTable
Field Type : TABLE
Field Status : current
Description : A table containing information of virtual server port configuration.
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1

Field Name : axVirtualServerPortEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axVirtualServerPort Table
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1

Field Name : axVirtualServerPortDiameterTemplate
Field Type : String
Field Status : current
Description : The Diameter template for diameter type only.
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.25

Field Name : axVirtualServerPortAddressType
Field Type : EnumVal
Field Status : current
Description : The type of axVirtualServerPortAddress:
: unknown(0), ipv4(1), ipv6(2)...
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.24

Field Name : axVirtualServerPortDisplayStatus
Field Type : EnumVal
Field Status : current
Description : The display status of this virtual server port:
: Disabled(0), AllUp(1), FunctionalUp(2), Stopped(4).
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.23

Field Name : axVirtualServerPortUDPTemplate
Field Type : String
Field Status : current
Description : The UDP template for UDP port type only.
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.22

Field Name : axVirtualServerPortSIPTemplate
Field Type : String
Field Status : current
Description : The SIP template for SIP port type only.
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.21

Field Name : axVirtualServerPortSMTPTemplate

Field Type : String
Field Status : current
Description : The SMTP template for SMTP port type only.
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.20

Field Name : axVirtualServerPortRTSPTemplate
Field Type : String
Field Status : current
Description : The RTSP template for RTSP port type only.
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.19

Field Name : axVirtualServerPortServerSSLTemplate
Field Type : String
Field Status : current
Description : The Server-SSL template for HTTPS port type only.
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.18

Field Name : axVirtualServerPortClientSSLTemplate
Field Type : String
Field Status : current
Description : The Client-SSL template for HTTPS/SSLProxy/SMTP port types.
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.17

Field Name : axVirtualServerPortTCPProxyTemplate
Field Type : String
Field Status : current
Description : The TCP proxy template for HTTP/HTTPS/SSLProxy/SMTP port types.
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.16

Field Name : axVirtualServerPortConnReuseTemplate
Field Type : String
Field Status : current
Description : The connection reuse template for HTTP/HTTPS/FastHTTP port types.
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.15

Field Name : axVirtualServerPortRamCacheTemplate
Field Type : String
Field Status : current
Description : The RAM cache template for HTTP/HTTPS port types.
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.14

Field Name : axVirtualServerPortHTTPTemplate
Field Type : String
Field Status : current
Description : The HTTP template for HTTP/HTTPS/FastHTTP port types.
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.13

Field Name : axVirtualServerPortTCPTemplate
Field Type : String
Field Status : current
Description : The TCP template for TPC/FastHTTP/RTSP/FTP/MMS/Others port types.
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.12

Field Name : axVirtualServerPortPolicyTemplate
Field Type : String
Field Status : current
Description : The policy template for all port types except for Firewall.
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.11

Field Name : axVirtualServerPortTemplate
Field Type : String
Field Status : current
Description : The virtual server port template for all port types except for Firewall.
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.10

Field Name : axVirtualServerPortPersistTemplate
Field Type : String
Field Status : current
Description : The persistent template dependent on the axVirtualServerPortPersistTemplateType value.
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.9

Field Name : axVirtualServerPortPersistTemplateType
Field Type : EnumVal
Field Status : current
Description : The persistent template type if applicable.
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.8

Field Name : axVirtualServerPortHaGroupID
Field Type : INTEGER
Field Status : current
Description : The HA group ID assigned to the virtual service port.
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.7

Field Name : axVirtualServerPortServiceGroup
Field Type : String
Field Status : current
Description : The service group is assigned to the virtual server port.
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.6

Field Name : axVirtualServerPortEnabled
Field Type : EnumVal
Field Status : current
Description : The status of this virtual server port is enabled.
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.5

Field Name : axVirtualServerPortAddress
Field Type : String
Field Status : current
Description : The ip address of this virtual server.
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.4

Field Name : axVirtualServerPortNum
Field Type : Integer32
Field Status : current
Description : The virtual server port number.
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.3

Field Name : axVirtualServerPortType
Field Type : EnumVal
Field Status : current
Description : The port type of a virtual server port.
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.2

Field Name : axVirtualServerPortName
Field Type : String

Field Status : current
Description : The name of the virtual server.
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.1

Field Name : axVirtualServerStatTable
Field Type : TABLE
Field Status : current
Description : A table containing statistic information of virtual servers.
OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1

Field Name : axVirtualServerStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axVirtualServerStat Table
OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1.1

Field Name : axVirtualServerStatAddressType
Field Type : EnumVal
Field Status : current
Description : The type of axVirtualServerStatAddress:
: unknown(0), ipv4(1), ipv6(2)...
OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1.1.16

Field Name : axVirtualServerStatPeakConns
Field Type : Counter
Field Status : current
Description : The number of peak connections
OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1.1.15

Field Name : axVirtualServerStatTotalSuccL7Reqs
Field Type : Counter64
Field Status : current
Description : The number of successful L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1.1.14

Field Name : axVirtualServerStatTotalCurrL7Reqs
Field Type : Counter64
Field Status : current
Description : The number of current L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1.1.13

Field Name : axVirtualServerStatTotalL7Reqs
Field Type : Counter64
Field Status : current
Description : The total number of L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1.1.12

Field Name : axVirtualServerStatDisplayStatus
Field Type : EnumVal
Field Status : current
Description : The display status of this virtual server:
: Disabled(0), AllUp(1), FunctionalUp(2), PartialUp(3), Stopped(4).
OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1.1.11

Field Name : axVirtualServerStatStatus
Field Type : EnumVal
Field Status : current
Description : The current virtual server status.

OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1.1.10

Field Name : axVirtualServerStatCurConns
Field Type : Integer32
Field Status : current
Description : The current connections from client side.
OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1.1.9

Field Name : axVirtualServerStatTotConns
Field Type : Counter64
Field Status : current
Description : The total connections from client side.
OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1.1.8

Field Name : axVirtualServerStatBytesOut
Field Type : Counter64
Field Status : current
Description : The number of bytes sent from server to client.
OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1.1.6

Field Name : axVirtualServerStatPktsOut
Field Type : Counter64
Field Status : current
Description : The number of packets sent from server to client.
OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1.1.5

Field Name : axVirtualServerStatBytesIn
Field Type : Counter64
Field Status : current
Description : The number of bytes received from client to server.
OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1.1.4

Field Name : axVirtualServerStatPktsIn
Field Type : Counter64
Field Status : current
Description : The number of packets received from client to server.
OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1.1.3

Field Name : axVirtualServerStatName
Field Type : String
Field Status : current
Description : The name of this virtual server.
OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1.1.2

Field Name : axVirtualServerStatAddress
Field Type : String
Field Status : current
Description : The address of this virtual server.
OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1.1.1

Field Name : axVirtualServerTable
Field Type : TABLE
Field Status : current
Description : A table containing information of virtual servers.
OID : 1.3.6.1.4.1.22610.2.4.3.4.1.2

Field Name : axVirtualServerCount
Field Type : INTEGER

Field Status : current
Description : The number of axVirtualServer entries in the table.
OID : 1.3.6.1.4.1.22610.2.4.3.4.1.1

Field Name : axVirtualServerEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axVirtualServer Table
OID : 1.3.6.1.4.1.22610.2.4.3.4.1.2.1

Field Name : axVirtualServerVrid
Field Type : INTEGER
Field Status : current
Description : The assigned vrid for the virtual server
OID : 1.3.6.1.4.1.22610.2.4.3.4.1.2.1.7

Field Name : axVirtualServerAddressType
Field Type : EnumVal
Field Status : current
Description : The type of axVirtualServerAddress:
: unknown(0), ipv4(1), ipv6(2)...
OID : 1.3.6.1.4.1.22610.2.4.3.4.1.2.1.6

Field Name : axVirtualServerDisplayStatus
Field Type : EnumVal
Field Status : current
Description : The display status of this virtual server port:
: Disabled(0), AllUp(1), FunctionalUp(2), PartialUp(3), Stopped(4).
OID : 1.3.6.1.4.1.22610.2.4.3.4.1.2.1.5

Field Name : axVirtualServerHAGroup
Field Type : String
Field Status : current
Description : HA group name configured for the virtual server.
OID : 1.3.6.1.4.1.22610.2.4.3.4.1.2.1.4

Field Name : axVirtualServerEnabled
Field Type : EnumVal
Field Status : current
Description : Whether this virtual server is enabled.
OID : 1.3.6.1.4.1.22610.2.4.3.4.1.2.1.3

Field Name : axVirtualServerAddress
Field Type : String
Field Status : current
Description : The ip address of this virtual server.
OID : 1.3.6.1.4.1.22610.2.4.3.4.1.2.1.2

Field Name : axVirtualServerName
Field Type : String
Field Status : current
Description : The name of this virtual server.
OID : 1.3.6.1.4.1.22610.2.4.3.4.1.2.1.1

Field Name : axVirtualServerNamePortStatTable
Field Type : TABLE
Field Status : current
Description : A table containing statistic information of virtual server service ports.

OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1

Field Name : axVirtualServerNamePortStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axVirtualServerNamePortStat Table
OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1.1

Field Name : axVirtualServerNamePortStatPeakConns
Field Type : Counter
Field Status : current
Description : The number of peak connections
OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1.1.16

Field Name : axVirtualServerNamePortStatTotalSuccL7Reqs
Field Type : Counter64
Field Status : current
Description : The number of successful L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1.1.15

Field Name : axVirtualServerNamePortStatTotalCurrL7Reqs
Field Type : Counter64
Field Status : current
Description : The number of current L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1.1.14

Field Name : axVirtualServerNamePortStatTotalL7Reqs
Field Type : Counter64
Field Status : current
Description : The total number of L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1.1.13

Field Name : axVirtualServerNameStatPortDisplayStatus
Field Type : EnumVal
Field Status : current
Description : The display status of this virtual server port:
: Disabled(0), AllUp(1), FunctionalUp(2), Stopped(4).
OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1.1.12

Field Name : axVirtualServerNamePortStatCurConns
Field Type : Integer32
Field Status : current
Description : Current connections from client side.
OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1.1.11

Field Name : axVirtualServerNamePortStatTotConns
Field Type : Counter64
Field Status : current
Description : Total connections from client side.
OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1.1.10

Field Name : axVirtualServerNamePortStatBytesOut
Field Type : Counter64
Field Status : current
Description : The number of bytes sent from server to client.
OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1.1.8

Field Name : axVirtualServerNamePortStatPktsOut

Field Type : Counter64
Field Status : current
Description : The number of packets sent from server to client.
OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1.1.7

Field Name : axVirtualServerNamePortStatBytesIn
Field Type : Counter64
Field Status : current
Description : The number of bytes received from client to server.
OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1.1.6

Field Name : axVirtualServerNamePortStatPktsIn
Field Type : Counter64
Field Status : current
Description : The number of packets received from client to server.
OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1.1.5

Field Name : axVirtualServerNameStatPortStatus
Field Type : EnumVal
Field Status : current
Description : The status of this virtual server port.
OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1.1.4

Field Name : axVirtualServerNameStatPortNum
Field Type : Integer32
Field Status : current
Description : The service port number.
OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1.1.3

Field Name : axVirtualServerNameStatPortType
Field Type : EnumVal
Field Status : current
Description : The port type of a virtual server port
OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1.1.2

Field Name : axVirtualServerNamePortStatName
Field Type : String
Field Status : current
Description : The name of the virtual server
OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1.1.1

Field Name : axServiceGroupMemberTable
Field Type : TABLE
Field Status : current
Description : A table containing information of service group members.
OID : 1.3.6.1.4.1.22610.2.4.3.3.3.1

Field Name : axServiceGroupMemberEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axServiceGroupMember Table
OID : 1.3.6.1.4.1.22610.2.4.3.3.3.1.1

Field Name : axServerPortStatusInServiceGroupMember
Field Type : EnumVal
Field Status : current
Description : The server port status of the service group member:
: Disabled(0), Up(1), Down(2).

OID : 1.3.6.1.4.1.22610.2.4.3.3.3.1.1.6

Field Name : axServerPortPriorityInServiceGroupMember
Field Type : Integer32
Field Status : current
Description : The priority value of a service group member.
OID : 1.3.6.1.4.1.22610.2.4.3.3.3.1.1.5

Field Name : axServerPortNumInServiceGroupMember
Field Type : Integer32
Field Status : current
Description : The port number of this member.
OID : 1.3.6.1.4.1.22610.2.4.3.3.3.1.1.4

Field Name : axServerNameInServiceGroupMember
Field Type : String
Field Status : current
Description : The server name in the service group member.
OID : 1.3.6.1.4.1.22610.2.4.3.3.3.1.1.3

Field Name : axServiceGroupMemberAddrType
Field Type : EnumVal
Field Status : current
Description : The type of service group
OID : 1.3.6.1.4.1.22610.2.4.3.3.3.1.1.2

Field Name : axServiceGroupNameInMember
Field Type : String
Field Status : current
Description : The name of axServiceGroup.
OID : 1.3.6.1.4.1.22610.2.4.3.3.3.1.1.1

Field Name : axServiceGroupStatTable
Field Type : TABLE
Field Status : current
Description : A table containing statistic information of service groups.
OID : 1.3.6.1.4.1.22610.2.4.3.3.2.1

Field Name : axServiceGroupStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axServiceGroupStat Table
OID : 1.3.6.1.4.1.22610.2.4.3.3.2.1.1

Field Name : axServiceGroupStatPeakConns
Field Type : Counter
Field Status : current
Description : The number of peak connections
OID : 1.3.6.1.4.1.22610.2.4.3.3.2.1.1.13

Field Name : axServiceGroupStatTotalSuccL7Reqs
Field Type : Counter64
Field Status : current
Description : The number of successful L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.3.2.1.1.12

Field Name : axServiceGroupStatTotalCurrL7Reqs
Field Type : Counter64

Field Status : current
Description : The number of current L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.3.2.1.1.11

Field Name : axServiceGroupStatTotalL7Reqs
Field Type : Counter64
Field Status : current
Description : The total number of L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.3.2.1.1.10

Field Name : axServiceGroupStatDisplayStatus
Field Type : EnumVal
Field Status : current
Description : The display status of the service group:
: AllUp(1), FunctionalUp(2), PartialUp(3), Stopped(4).
OID : 1.3.6.1.4.1.22610.2.4.3.3.2.1.1.9

Field Name : axServiceGroupStatCurConns
Field Type : Integer32
Field Status : current
Description : The current connections from server side.
OID : 1.3.6.1.4.1.22610.2.4.3.3.2.1.1.7

Field Name : axServiceGroupStatTotConns
Field Type : Counter64
Field Status : current
Description : The total connections from server side.
OID : 1.3.6.1.4.1.22610.2.4.3.3.2.1.1.6

Field Name : axServiceGroupStatBytesOut
Field Type : Counter64
Field Status : current
Description : The number of bytes sent from server to client.
OID : 1.3.6.1.4.1.22610.2.4.3.3.2.1.1.5

Field Name : axServiceGroupStatPktsOut
Field Type : Counter64
Field Status : current
Description : The number of packets sent from server to client.
OID : 1.3.6.1.4.1.22610.2.4.3.3.2.1.1.4

Field Name : axServiceGroupStatBytesIn
Field Type : Counter64
Field Status : current
Description : The number of bytes received from client to server.
OID : 1.3.6.1.4.1.22610.2.4.3.3.2.1.1.3

Field Name : axServiceGroupStatPktsIn
Field Type : Counter64
Field Status : current
Description : The number of packets received from client to server.
OID : 1.3.6.1.4.1.22610.2.4.3.3.2.1.1.2

Field Name : axServiceGroupStatName
Field Type : String
Field Status : current
Description : The service group name.
OID : 1.3.6.1.4.1.22610.2.4.3.3.2.1.1.1

Field Name : axServiceGroupTable
Field Type : TABLE
Field Status : current
Description : A table containing information of service groups.
OID : 1.3.6.1.4.1.22610.2.4.3.3.1.2

Field Name : axServiceGroupCount
Field Type : Integer32
Field Status : current
Description : The number of axServiceGroup entries in the table.
OID : 1.3.6.1.4.1.22610.2.4.3.3.1.1

Field Name : axServiceGroupEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axServiceGroup Table
OID : 1.3.6.1.4.1.22610.2.4.3.3.1.2.1

Field Name : axServiceGroupDisplayStatus
Field Type : EnumVal
Field Status : current
Description : The display status of the service group:
: AllUp(1), FunctionalUp(2), PartialUp(3), Stopped(4).
OID : 1.3.6.1.4.1.22610.2.4.3.3.1.2.1.4

Field Name : axServiceGroupLbAlgorithm
Field Type : EnumVal
Field Status : current
Description : The load balance method for the service group
OID : 1.3.6.1.4.1.22610.2.4.3.3.1.2.1.3

Field Name : axServiceGroupType
Field Type : EnumVal
Field Status : current
Description : The type of the service group.
OID : 1.3.6.1.4.1.22610.2.4.3.3.1.2.1.2

Field Name : axServiceGroupName
Field Type : String
Field Status : current
Description : The service group name.
OID : 1.3.6.1.4.1.22610.2.4.3.3.1.2.1.1

Field Name : axServiceGroupMemberStatTable
Field Type : TABLE
Field Status : current
Description : A table containing statistic information of service group members.
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1

Field Name : axServiceGroupMemberStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axServiceGroupMemberStat Table
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1

Field Name : axServiceGroupMemberStatPeakConns
Field Type : Counter

Field Status : current
Description : The service group member peak connections.
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1.17

Field Name : axServiceGroupMemberStatResponseTime
Field Type : Integer32
Field Status : current
Description : The service group member response time in millisecond.
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1.16

Field Name : axServiceGroupMemberStatTotalSuccL7Reqs
Field Type : Counter64
Field Status : current
Description : The number of successful L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1.15

Field Name : axServiceGroupMemberStatTotalCurrL7Reqs
Field Type : Counter64
Field Status : current
Description : The number of current L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1.14

Field Name : axServiceGroupMemberStatTotalL7Reqs
Field Type : Counter64
Field Status : current
Description : The total number of L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1.13

Field Name : axServerPortStatusInServiceGroupMemberStat
Field Type : EnumVal
Field Status : current
Description : The server port status of the service group member:
: Disabled(0), Up(1), Down(2)
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1.12

Field Name : axServiceGroupMemberStatCurConns
Field Type : Integer32
Field Status : current
Description : The current connections from server side.
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1.11

Field Name : axServiceGroupMemberStatTotConns
Field Type : Counter64
Field Status : current
Description : The total connections from server side.
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1.10

Field Name : axServiceGroupMemberStatBytesOut
Field Type : Counter64
Field Status : current
Description : The number of bytes sent from server to client.
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1.8

Field Name : axServiceGroupMemberStatPktsOut
Field Type : Counter64
Field Status : current
Description : The number of packets sent from server to client.
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1.7

Field Name : axServiceGroupMemberStatBytesIn
Field Type : Counter64
Field Status : current
Description : The number of bytes received from client to server.
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1.6

Field Name : axServiceGroupMemberStatPktsIn
Field Type : Counter64
Field Status : current
Description : The number of packets received from client to server.
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1.5

Field Name : axServerPortNumInServiceGroupMemberStat
Field Type : Integer32
Field Status : current
Description : The port number of this member.
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1.4

Field Name : axServerNameInServiceGroupMemberStat
Field Type : String
Field Status : current
Description : The ip address of this member in the service group.
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1.3

Field Name : axServiceGroupMemberStatAddrType
Field Type : EnumVal
Field Status : current
Description : The type of service group
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1.2

Field Name : axServiceGroupMemberStatName
Field Type : String
Field Status : current
Description : The service group name.
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1.1

Field Name : axServerPortTable
Field Type : TABLE
Field Status : current
Description : A table has information of real servers.
OID : 1.3.6.1.4.1.22610.2.4.3.2.3.1

Field Name : axServerPortEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axServer Port Table
OID : 1.3.6.1.4.1.22610.2.4.3.2.3.1.1

Field Name : axServerPortAddressType
Field Type : EnumVal
Field Status : current
Description : The type of axServerAddressInPort:
: unknown(0), ipv4(1), ipv6(2)...
OID : 1.3.6.1.4.1.22610.2.4.3.2.3.1.1.10

Field Name : axServerPortMonitorState
Field Type : EnumVal

Field Status : current
Description : The server port status is in
: 0: Disabled (administrative disabled)
: 1: Up (administrative enabled)
: 2: Down (administrative enabled)
OID : 1.3.6.1.4.1.22610.2.4.3.2.3.1.1.9

Field Name : axServerPortWeight
Field Type : Integer32
Field Status : current
Description : The weight of the server port.
OID : 1.3.6.1.4.1.22610.2.4.3.2.3.1.1.8

Field Name : axServerPortConnLimit
Field Type : Integer32
Field Status : current
Description : The connection limit of the server port.
OID : 1.3.6.1.4.1.22610.2.4.3.2.3.1.1.7

Field Name : axServerPortHealthMonitor
Field Type : String
Field Status : current
Description : The health monitor name assigned to the server
OID : 1.3.6.1.4.1.22610.2.4.3.2.3.1.1.6

Field Name : axServerPortEnabledState
Field Type : EnumVal
Field Status : current
Description : The monitor state for this node address.
OID : 1.3.6.1.4.1.22610.2.4.3.2.3.1.1.5

Field Name : axServerAddressInPort
Field Type : String
Field Status : current
Description : The IP address or host name of the server.
OID : 1.3.6.1.4.1.22610.2.4.3.2.3.1.1.4

Field Name : axServerPortNum
Field Type : Integer32
Field Status : current
Description : The port number of the server.
OID : 1.3.6.1.4.1.22610.2.4.3.2.3.1.1.3

Field Name : axServerPortType
Field Type : EnumVal
Field Status : current
Description : The port type of the server port.
OID : 1.3.6.1.4.1.22610.2.4.3.2.3.1.1.2

Field Name : axServerNameInPort
Field Type : String
Field Status : current
Description : The server name.
OID : 1.3.6.1.4.1.22610.2.4.3.2.3.1.1.1

Field Name : axServerStatTable
Field Type : TABLE
Field Status : current

Description : A table containing statistic information of node addresses.
OID : 1.3.6.1.4.1.22610.2.4.3.2.2.2

Field Name : axServerStatCount
Field Type : INTEGER
Field Status : current
Description : The total count of axServerStat entries in the table.
OID : 1.3.6.1.4.1.22610.2.4.3.2.2.1

Field Name : axServerStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axServerStat Table
OID : 1.3.6.1.4.1.22610.2.4.3.2.2.2.1

Field Name : axServerStatAddressType
Field Type : EnumVal
Field Status : current
Description : The type of axServerStatAddress:
: unknown(0), ipv4(1), ipv6(2)...
OID : 1.3.6.1.4.1.22610.2.4.3.2.2.2.1.15

Field Name : axServerStatServerPeakConns
Field Type : Counter
Field Status : current
Description : The number of the peak connections
OID : 1.3.6.1.4.1.22610.2.4.3.2.2.2.1.14

Field Name : axServerStatServerTotalSuccL7Reqs
Field Type : Counter64
Field Status : current
Description : The number of successful L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.2.2.2.1.13

Field Name : axServerStatServerTotalCurrL7Reqs
Field Type : Counter64
Field Status : current
Description : The number of current L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.2.2.2.1.12

Field Name : axServerStatServerTotalL7Reqs
Field Type : Counter64
Field Status : current
Description : The total number of L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.2.2.2.1.11

Field Name : axServerStatServerStatus
Field Type : EnumVal
Field Status : current
Description : The server status is in
: 0: Disabled (administrative disabled)
: 1: Up (administrative enabled)
: 2: Down (administrative enabled)
OID : 1.3.6.1.4.1.22610.2.4.3.2.2.2.1.10

Field Name : axServerStatServerCurConns
Field Type : Integer32
Field Status : current

Description : The current connections from server side.
OID : 1.3.6.1.4.1.22610.2.4.3.2.2.2.1.8

Field Name : axServerStatServerTotalConns
Field Type : Counter64
Field Status : current
Description : The total connections from server side.
OID : 1.3.6.1.4.1.22610.2.4.3.2.2.2.1.7

Field Name : axServerStatServerBytesOut
Field Type : Counter64
Field Status : current
Description : The number of bytes sent from server to client.
OID : 1.3.6.1.4.1.22610.2.4.3.2.2.2.1.6

Field Name : axServerStatServerPktsOut
Field Type : Counter64
Field Status : current
Description : The number of packets sent for server to client.
OID : 1.3.6.1.4.1.22610.2.4.3.2.2.2.1.5

Field Name : axServerStatServerBytesIn
Field Type : Counter64
Field Status : current
Description : The number of bytes received from client to server.
OID : 1.3.6.1.4.1.22610.2.4.3.2.2.2.1.4

Field Name : axServerStatServerPktsIn
Field Type : Counter64
Field Status : current
Description : The number of packets received from client to server.
OID : 1.3.6.1.4.1.22610.2.4.3.2.2.2.1.3

Field Name : axServerStatName
Field Type : String
Field Status : current
Description : The server name.
OID : 1.3.6.1.4.1.22610.2.4.3.2.2.2.1.2

Field Name : axServerStatAddress
Field Type : String
Field Status : current
Description : The ip address of this server.
OID : 1.3.6.1.4.1.22610.2.4.3.2.2.2.1.1

Field Name : axServerTable
Field Type : TABLE
Field Status : current
Description : A table has information of the servers.
OID : 1.3.6.1.4.1.22610.2.4.3.2.1.2

Field Name : axServerCount
Field Type : INTEGER
Field Status : current
Description : The total count of axServer entries in the table.
OID : 1.3.6.1.4.1.22610.2.4.3.2.1.1

Field Name : axServerEntry

Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axServer Table
OID : 1.3.6.1.4.1.22610.2.4.3.2.1.2.1

Field Name : axServerWeight
Field Type : INTEGER
Field Status : current
Description : The server weight
OID : 1.3.6.1.4.1.22610.2.4.3.2.1.2.1.7

Field Name : axServerAddressType
Field Type : EnumVal
Field Status : current
Description : The type of axServerAddress:
: unknown(0), ipv4(1), ipv6(2)...
OID : 1.3.6.1.4.1.22610.2.4.3.2.1.2.1.6

Field Name : axServerMonitorState
Field Type : EnumVal
Field Status : current
Description : The server monitor status is in
: 0: Disabled (administrative disabled)
: 1: Up (administrative enabled)
: 2: Down (administrative enabled)
OID : 1.3.6.1.4.1.22610.2.4.3.2.1.2.1.5

Field Name : axServerHealthMonitor
Field Type : String
Field Status : current
Description : The health monitor name assigned to the server
OID : 1.3.6.1.4.1.22610.2.4.3.2.1.2.1.4

Field Name : axServerEnabledState
Field Type : EnumVal
Field Status : current
Description : The monitor state for this node address.
OID : 1.3.6.1.4.1.22610.2.4.3.2.1.2.1.3

Field Name : axServerAddress
Field Type : String
Field Status : current
Description : The IP address or host name of the server.
OID : 1.3.6.1.4.1.22610.2.4.3.2.1.2.1.2

Field Name : axServerName
Field Type : String
Field Status : current
Description : The name of the server.
OID : 1.3.6.1.4.1.22610.2.4.3.2.1.2.1.1

Field Name : axServerPortStatTable
Field Type : TABLE
Field Status : current
Description : A table containing statistic information of node addresses.
OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1

Field Name : axServerPortStatEntry

Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axServerStat Table
OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1

Field Name : axServerPortStatAddressType
Field Type : EnumVal
Field Status : current
Description : The type of axServerStatAddrInPort:
: unknown(0), ipv4(1), ipv6(2)...
OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1.17

Field Name : axServerPortStatPeakConns
Field Type : Counter
Field Status : current
Description : The number of peak connections
OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1.16

Field Name : axServerPortStatTotalSuccL7Reqs
Field Type : Counter64
Field Status : current
Description : The number of successful L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1.15

Field Name : axServerPortStatTotalCurrL7Reqs
Field Type : Counter64
Field Status : current
Description : The number of current L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1.14

Field Name : axServerPortStatTotalL7Reqs
Field Type : Counter64
Field Status : current
Description : The total number of L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1.13

Field Name : axServerPortStatStatus
Field Type : EnumVal
Field Status : current
Description : The server port status is in
: 0: Disabled (administrative disabled)
: 1: Up (administrative enabled)
: 2: Down (administrative enabled)
OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1.12

Field Name : axServerPortStatCurConns
Field Type : Integer32
Field Status : current
Description : The current connections from server side.
OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1.10

Field Name : axServerPortStatTotalConns
Field Type : Counter64
Field Status : current
Description : The maximum connections from server side.
OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1.9

Field Name : axServerPortStatBytesOut

Field Type : Counter64
Field Status : current
Description : The number of bytes sent from server to client.
OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1.8

Field Name : axServerPortStatPktsOut
Field Type : Counter64
Field Status : current
Description : The number of packets sent from server to client.
OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1.7

Field Name : axServerPortStatBytesIn
Field Type : Counter64
Field Status : current
Description : The number of bytes received from client to server.
OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1.6

Field Name : axServerPortStatPktsIn
Field Type : Counter64
Field Status : current
Description : The number of packets received from client to server.
OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1.5

Field Name : axServerStatNameInPort
Field Type : String
Field Status : current
Description : The ip address of this server.
OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1.4

Field Name : axServerStatPortNum
Field Type : Integer32
Field Status : current
Description : The server port number.
OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1.3

Field Name : axServerStatPortType
Field Type : EnumVal
Field Status : current
Description : The server port type.
OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1.2

Field Name : axServerStatAddrInPort
Field Type : String
Field Status : current
Description : The ip address of this server.
OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1.1

Field Name : axAppGlobalBufferCurrentUsage
Field Type : INTEGER
Field Status : current
Description : Application buffer current usage.
OID : 1.3.6.1.4.1.22610.2.4.3.1.3.2

Field Name : axAppGlobalBufferConfigLimit
Field Type : INTEGER
Field Status : current
Description : Application buffer configured limit.
OID : 1.3.6.1.4.1.22610.2.4.3.1.3.1

Field Name : axGlobalAggregateCps
Field Type : Counter64
Field Status : current
Description : Global aggregate connection per second.
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.24

Field Name : axGlobalFWCps
Field Type : Counter64
Field Status : current
Description : Firewall connection per second.
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.23

Field Name : axGlobalL7ConnectionCps
Field Type : Counter64
Field Status : current
Description : Layer 7 connections per second.
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.22

Field Name : axGlobalL4ConnectionCps
Field Type : Counter64
Field Status : current
Description : Layer 4 connections per second.
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.21

Field Name : axGlobalConcurrentConnection
Field Type : Counter64
Field Status : current
Description : Total layer 4 and layer 7 established connections.
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.20

Field Name : axGlobalThroughputPerSecond
Field Type : Counter64
Field Status : current
Description : The per second throughput across all Ethernet ports.
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.19

Field Name : axGlobalTotalSslCps
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL CPS across all the partitions.
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.18

Field Name : axGlobalTotalL7Cps
Field Type : CounterBasedGauge64
Field Status : current
Description : Total L7 CPS across all the partitions.
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.17

Field Name : axGlobalTotalL4Cps
Field Type : CounterBasedGauge64
Field Status : current
Description : Total L4 CPS across all the partitions.
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.16

Field Name : axGlobalTotalSslThroughput
Field Type : Counter64
Field Status : current

Description : Total SSL throughput across all the partitions.
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.15

Field Name : axGlobalTotalBandWidth
Field Type : CounterBasedGauge64
Field Status : current
Description : Total bandwidth across all the partitions.
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.14

Field Name : axGlobalTotalThroughput
Field Type : Counter64
Field Status : current
Description : Total throughput of all the interfaces.
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.13

Field Name : axGlobalTotalL4SessionInteger
Field Type : INTEGER
Field Status : current
Description : Total number of L4 sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.12

Field Name : axAppGlobalTotalCurrentConnectionsInteger
Field Type : INTEGER
Field Status : current
Description : Total current connections
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.11

Field Name : axGlobalTotalL4Session
Field Type : CounterBasedGauge64
Field Status : current
Description : Total number of L4 sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.10

Field Name : axGlobalTotalAppPacketDrop
Field Type : Counter64
Field Status : current
Description : Total number of accumulative buffer drops.
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.9

Field Name : axGlobalAppPacketDrop
Field Type : INTEGER
Field Status : current
Description : Total number of buffer drops in the last 10 seconds.
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.8

Field Name : axAppGlobalTotalL7Requests
Field Type : Counter64
Field Status : current
Description : Total L7 requests
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.7

Field Name : axAppGlobalTotalSSLConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL connections
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.6

Field Name : axAppGlobalTotalNewIPNatConnections

Field Type : CounterBasedGauge64
Field Status : current
Description : Total new IP-NAT connections
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.5

Field Name : axAppGlobalTotalNewL7Connections
Field Type : Counter64
Field Status : current
Description : Total new L7 connections
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.4

Field Name : axAppGlobalTotalNewL4Connections
Field Type : CounterBasedGauge64
Field Status : current
Description : Total new L4 connections
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.3

Field Name : axAppGlobalTotalNewConnections
Field Type : Counter64
Field Status : current
Description : Total new connections
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.2

Field Name : axAppGlobalTotalCurrentConnections
Field Type : Counter64
Field Status : current
Description : Total current connections
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.1

Field Name : axAppGlobalResourceUsageTable
Field Type : TABLE
Field Status : current
Description : A table has information of the resource usages,
: it should contains the results as the CLI command,
: 'show resouce-usage'
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.2

Field Name : axAppGlobalSystemResourceUsageTable
Field Type : TABLE
Field Status : current
Description : A table has information of the system resource usages,
: it should contains the results as the CLI command,
: 'show slb resource-usage'
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.1

Field Name : axAppGlobalSystemResourceUsageEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axAppGlobalSystemResourceUsage Table
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.1.1

Field Name : axAppGlobalAllowedMaxValue
Field Type : INTEGER
Field Status : current
Description : The maximum value for the allowed system resource.
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.1.1.6

Field Name : axAppGlobalAllowedMinValue

Field Type : INTEGER
Field Status : current
Description : The minimum value for the allowed system resource.
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.1.1.5

Field Name : axAppGlobalAllowedDefaultValue
Field Type : INTEGER
Field Status : current
Description : The default value for the allowed system resource.
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.1.1.4

Field Name : axAppGlobalAllowedCurrentValue
Field Type : INTEGER
Field Status : current
Description : The current value for the allowed system resource.
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.1.1.3

Field Name : axAppGlobalSystemResourceName
Field Type : String
Field Status : current
Description : The system resource name.
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.1.1.2

Field Name : axAppGlobalSystemResourceIndex
Field Type : INTEGER
Field Status : current
Description : The system resource usage table index.
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.1.1.1

Field Name : axAppGlobalResourceUsageEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axAppGlobalResourceUsage Table
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.2.1

Field Name : axAppGlobalResourcePeak
Field Type : INTEGER
Field Status : current
Description : The peak utilization of the resource.
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.2.1.11

Field Name : axAppGlobalResourceAverage
Field Type : INTEGER
Field Status : current
Description : The average of the resource usage.
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.2.1.10

Field Name : axAppGlobalResourceThresholdExceeded
Field Type : INTEGER
Field Status : current
Description : The number of threshold exceeded for the resource.
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.2.1.9

Field Name : axAppGlobalResourceMaxExceeded
Field Type : INTEGER
Field Status : current
Description : The number of maximum exceeded for the resource.
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.2.1.8

Field Name : axAppGlobalResourceUtilization
Field Type : INTEGER
Field Status : current
Description : The utilization percentage of the resource usage.
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.2.1.7

Field Name : axAppGlobalResourceAllowedMaxValue
Field Type : INTEGER
Field Status : current
Description : The maximum value for the allowed system resource.
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.2.1.6

Field Name : axAppGlobalResourceAllowedMinValue
Field Type : INTEGER
Field Status : current
Description : The minimum value for the allowed system resource.
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.2.1.5

Field Name : axAppGlobalResourceAllowedCurrentValue
Field Type : INTEGER
Field Status : current
Description : The current value for the allowed system resource.
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.2.1.3

Field Name : axAppGlobalResourceName
Field Type : String
Field Status : current
Description : The resource name.
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.2.1.2

Field Name : axAppGlobalResourceIndex
Field Type : INTEGER
Field Status : current
Description : The resource usage table index.
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.2.1.1

Field Name : axL3vGlobalStatsTable
Field Type : TABLE
Field Status : current
Description : The global statitics on a l3v partition.
OID : 1.3.6.1.4.1.22610.2.4.3.1.4.1

Field Name : axL3vGlobalStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axL3vGlobalStatsTable
OID : 1.3.6.1.4.1.22610.2.4.3.1.4.1.1

Field Name : axL3vGlobalStatsL7ConnectionCps
Field Type : Counter64
Field Status : current
Description : Layer 7 connection per second in a L3V partition.
OID : 1.3.6.1.4.1.22610.2.4.3.1.4.1.1.12

Field Name : axL3vGlobalStatsL4ConnectionCps
Field Type : Counter64
Field Status : current

Description : Layer 4 connection per second in a L3V partition.
OID : 1.3.6.1.4.1.22610.2.4.3.1.4.1.1.11

Field Name : axL3vGlobalStatsConcurrentConnections
Field Type : Counter64
Field Status : current
Description : Total layer 4 and layer 7 established connections in a L3V Partition.
OID : 1.3.6.1.4.1.22610.2.4.3.1.4.1.1.10

Field Name : axL3vGlobalStatsTotalL4Sessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Total layer 4 sessions in a L3V partition.
OID : 1.3.6.1.4.1.22610.2.4.3.1.4.1.1.9

Field Name : axL3vGlobalStatsTotalL7Requests
Field Type : Counter64
Field Status : current
Description : Total layer 7 requests in a L3V partition.
OID : 1.3.6.1.4.1.22610.2.4.3.1.4.1.1.8

Field Name : axL3vGlobalStatsTotalSslConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : The SSL connections per second in a L3V partition.
OID : 1.3.6.1.4.1.22610.2.4.3.1.4.1.1.7

Field Name : axL3vGlobalStatsTotalNewL7Connections
Field Type : Counter64
Field Status : current
Description : Total new layer 7 connections in a L3V partition.
OID : 1.3.6.1.4.1.22610.2.4.3.1.4.1.1.6

Field Name : axL3vGlobalStatsTotalNewL4Connections
Field Type : CounterBasedGauge64
Field Status : current
Description : Total new layer 4 connections in a L3V partition.
OID : 1.3.6.1.4.1.22610.2.4.3.1.4.1.1.5

Field Name : axL3vGlobalStatsTotalNewConnections
Field Type : Counter64
Field Status : current
Description : Total new connections in a L3V partition.
OID : 1.3.6.1.4.1.22610.2.4.3.1.4.1.1.4

Field Name : axL3vGlobalStatsTotalCurrentConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : Total current connections in a L3V partition.
OID : 1.3.6.1.4.1.22610.2.4.3.1.4.1.1.3

Field Name : axL3vGlobalStatsTotalThroughput
Field Type : CounterBasedGauge64
Field Status : current
Description : Total throughput of all the interfaces in a L3V partition.
OID : 1.3.6.1.4.1.22610.2.4.3.1.4.1.1.2

Field Name : axL3vGlobalStatsPartitionName

Field Type : String
Field Status : current
Description : The L3V partition name.
OID : 1.3.6.1.4.1.22610.2.4.3.1.4.1.1.1

Field Name : axFwDataSessionFree
Field Type : Counter64
Field Status : current
Description : The foward data session free.
OID : 1.3.6.1.4.1.22610.2.4.3.26.2

Field Name : axFwDataSessionUsed
Field Type : Counter64
Field Status : current
Description : The foward data session used.
OID : 1.3.6.1.4.1.22610.2.4.3.26.1

Field Name : axLogMonitorPri
Field Type : EnumVal
Field Status : current
Description : The logging monitor priority, logging messages which levels above
: that value must be output to snmp trap host.
OID : 1.3.6.1.4.1.22610.2.4.2.11

Field Name : axLogSyslogPort
Field Type : Integer32
Field Status : current
Description : The logging syslog host port.
OID : 1.3.6.1.4.1.22610.2.4.2.10

Field Name : axLogSyslogHostTable
Field Type : TABLE
Field Status : current
Description : The syslog host table.
OID : 1.3.6.1.4.1.22610.2.4.2.9

Field Name : axLogSyslogHostEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The syslog host entry
OID : 1.3.6.1.4.1.22610.2.4.2.9.1

Field Name : axLogSyslogHost
Field Type : String
Field Status : current
Description : The syslog host IP address or DNS name.
OID : 1.3.6.1.4.1.22610.2.4.2.9.1.2

Field Name : axLogSyslogHostIndex
Field Type : Integer32
Field Status : current
Description : The index of the syslog host list.
OID : 1.3.6.1.4.1.22610.2.4.2.9.1.1

Field Name : axLogSyslogPri
Field Type : EnumVal
Field Status : current
Description : The logging syslog priority, logging messages which levels above

: that value must be output to syslog host.
OID : 1.3.6.1.4.1.22610.2.4.2.8

Field Name : axLogEmailAddr
Field Type : String
Field Status : current
Description : The email address that receive the logging messages.
OID : 1.3.6.1.4.1.22610.2.4.2.5

Field Name : axLogEmailPri
Field Type : EnumVal
Field Status : current
Description : The logging email priority, logging messages which levels above
: that value must be output to email address.
OID : 1.3.6.1.4.1.22610.2.4.2.4

Field Name : axLogConsolePri
Field Type : EnumVal
Field Status : current
Description : The logging console priority, logging messages which levels above
: that value must be output to console.
OID : 1.3.6.1.4.1.22610.2.4.2.3

Field Name : axLogBufferPri
Field Type : EnumVal
Field Status : current
Description : The logging buffer priority, logging messages which levels above
: that value must be output to internal database.
OID : 1.3.6.1.4.1.22610.2.4.2.2

Field Name : axLogBufferSize
Field Type : Integer32
Field Status : current
Description : The logging database size.
OID : 1.3.6.1.4.1.22610.2.4.2.1

Field Name : axSysVendorModelVersion
Field Type : String
Field Status : current
Description : The system vendor, model and version.
OID : 1.3.6.1.4.1.22610.2.4.1.6.5

Field Name : axSysAFleXEngineVersion
Field Type : String
Field Status : current
Description : The system aFlex engine version.
OID : 1.3.6.1.4.1.22610.2.4.1.6.4

Field Name : axSysFirmwareVersion
Field Type : String
Field Status : current
Description : The system firmware version.
OID : 1.3.6.1.4.1.22610.2.4.1.6.3

Field Name : axSysSerialNumber
Field Type : String
Field Status : current
Description : The system serial number.

OID : 1.3.6.1.4.1.22610.2.4.1.6.2

Field Name : axSysStartupMode
Field Type : EnumVal
Field Status : current
Description : The startup mode.
OID : 1.3.6.1.4.1.22610.2.4.1.6.1

Field Name : axSysPowerSupplyStatusTable
Field Type : TABLE
Field Status : current
Description : The table contains power supply status.
OID : 1.3.6.1.4.1.22610.2.4.1.5.12

Field Name : axPowerSupplyVoltageTable
Field Type : TABLE
Field Status : current
Description : A table contains the system power supply voltage status.
OID : 1.3.6.1.4.1.22610.2.4.1.5.11

Field Name : axPowerSupplyVoltageEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axPowerSupplyVoltageTable
OID : 1.3.6.1.4.1.22610.2.4.1.5.11.1

Field Name : axPowerSupplyVoltageDescription
Field Type : String
Field Status : current
Description : The description of the system power supply voltage.
OID : 1.3.6.1.4.1.22610.2.4.1.5.11.1.3

Field Name : axPowerSupplyVoltageStatus
Field Type : EnumVal
Field Status : current
Description : The status of the indexed system power supply voltage.
: This is only supported for the platform where the sensor data is available.
OID : 1.3.6.1.4.1.22610.2.4.1.5.11.1.2

Field Name : axPowerSupplyVoltageIndex
Field Type : INTEGER
Field Status : current
Description : The table index.
OID : 1.3.6.1.4.1.22610.2.4.1.5.11.1.1

Field Name : axPowerSupplyVoltageTotal
Field Type : INTEGER
Field Status : current
Description : The total number of axPowerSupplyVoltage entries.
OID : 1.3.6.1.4.1.22610.2.4.1.5.10

Field Name : axSysFanStatusTable
Field Type : TABLE
Field Status : current
Description : The table contains system fan status
OID : 1.3.6.1.4.1.22610.2.4.1.5.9

Field Name : axSysFanStatusEntry

Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axSysFanStatusTable
OID : 1.3.6.1.4.1.22610.2.4.1.5.9.1

Field Name : axFanSpeed
Field Type : Integer32
Field Status : current
Description : The fan speed.
OID : 1.3.6.1.4.1.22610.2.4.1.5.9.1.4

Field Name : axFanStatus
Field Type : EnumVal
Field Status : current
Description : Fan status:
: 0: Failed, 4: OK-fixed/high, 5: OK-low/med, 6: OK-med/med, 7: OK-med/high,
: -2: not ready, -1: unknown.
OID : 1.3.6.1.4.1.22610.2.4.1.5.9.1.3

Field Name : axFanName
Field Type : String
Field Status : current
Description : The system fan name.
OID : 1.3.6.1.4.1.22610.2.4.1.5.9.1.2

Field Name : axFanIndex
Field Type : Integer32
Field Status : current
Description : The system fan index.
OID : 1.3.6.1.4.1.22610.2.4.1.5.9.1.1

Field Name : axSysHwPhySystemTempStatus
Field Type : EnumVal
Field Status : current
Description : The system temperature status range
OID : 1.3.6.1.4.1.22610.2.4.1.5.5

Field Name : axSysHwPhySystemTemp
Field Type : Integer32
Field Status : current
Description : The physical system temperature in Celsius.
OID : 1.3.6.1.4.1.22610.2.4.1.5.1

Field Name : axSysPowerSupplyStatusEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axSysPowerSupplyStatusTable
OID : 1.3.6.1.4.1.22610.2.4.1.5.12.1

Field Name : axPowerSupplyStatus
Field Type : EnumVal
Field Status : current
Description : The power supply status.
OID : 1.3.6.1.4.1.22610.2.4.1.5.12.1.3

Field Name : axPowerSupplyName
Field Type : String
Field Status : current

Description : The pwer supply name.
OID : 1.3.6.1.4.1.22610.2.4.1.5.12.1.2

Field Name : axPowerSupplyIndex
Field Type : Integer32
Field Status : current
Description : The system power suplly index.
OID : 1.3.6.1.4.1.22610.2.4.1.5.12.1.1

Field Name : axSysDiskFreeSpace
Field Type : Integer32
Field Status : current
Description : The free space of the disk in MB.
OID : 1.3.6.1.4.1.22610.2.4.1.4.2

Field Name : axSysDiskTotalSpace
Field Type : Integer32
Field Status : current
Description : The total space of the disk in MB.
OID : 1.3.6.1.4.1.22610.2.4.1.4.1

Field Name : axSysCpuUsagePerPartitionTable
Field Type : TABLE
Field Status : current
Description : The cpu usage per partition information table.
OID : 1.3.6.1.4.1.22610.2.4.1.3.7

Field Name : axSysCpuUsageTable
Field Type : TABLE
Field Status : current
Description : The cpu usage information table.
OID : 1.3.6.1.4.1.22610.2.4.1.3.6

Field Name : axSysCpuUsageEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The CPU Usage entry
OID : 1.3.6.1.4.1.22610.2.4.1.3.6.1

Field Name : axSysCpuUsageCtrlCpuFlag
Field Type : Integer32
Field Status : current
Description : The control CPU flag: 1 - control CPU, 0 - data CPU.
OID : 1.3.6.1.4.1.22610.2.4.1.3.6.1.4

Field Name : axSysCpuUsageValueAtPeriod
Field Type : Integer32
Field Status : current
Description : The CPU usage value at given period, 1-sec, 5-sec, 10-sec, 30-sec, and 60-sec.
OID : 1.3.6.1.4.1.22610.2.4.1.3.6.1.3

Field Name : axSysCpuUsagePeriodIndex
Field Type : Integer32
Field Status : current
Description : The CPU usage sampling period:
: 1: 1-second sampling,
: 2: 5-second sampling,

: 3: 10-second sampling,
: 4: 30-second sampling,
: 5: 60-second sampling.
OID : 1.3.6.1.4.1.22610.2.4.1.3.6.1.2

Field Name : axSysCpuIndexInUsage
Field Type : Integer32
Field Status : current
Description : The index of the CPU.
OID : 1.3.6.1.4.1.22610.2.4.1.3.6.1.1

Field Name : axSysAverageDataCpuUsage
Field Type : Integer32
Field Status : current
Description : The average data CPU usage in last 5 seconds.
OID : 1.3.6.1.4.1.22610.2.4.1.3.5

Field Name : axSysAverageControlCpuUsage
Field Type : Integer32
Field Status : current
Description : The average control CPU usage in last 5 seconds.
OID : 1.3.6.1.4.1.22610.2.4.1.3.4

Field Name : axSysAverageCpuUsage
Field Type : Integer32
Field Status : current
Description : The average CPU usage in last 5 seconds.
OID : 1.3.6.1.4.1.22610.2.4.1.3.3

Field Name : axSysCpuTable
Field Type : TABLE
Field Status : current
Description : The cpu information table.
OID : 1.3.6.1.4.1.22610.2.4.1.3.2

Field Name : axSysCpuEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The cpu entry
OID : 1.3.6.1.4.1.22610.2.4.1.3.2.1

Field Name : axSysCpuCtrlCpuFlag
Field Type : Integer32
Field Status : current
Description : The control CPU flag: 1 - control CPU, 0 - data CPU.
OID : 1.3.6.1.4.1.22610.2.4.1.3.2.1.4

Field Name : axSysCpuUsageValue
Field Type : Integer32
Field Status : current
Description : The CPU usage value.
OID : 1.3.6.1.4.1.22610.2.4.1.3.2.1.3

Field Name : axSysCpuUsage
Field Type : String
Field Status : current
Description : The CPU Usage.
OID : 1.3.6.1.4.1.22610.2.4.1.3.2.1.2

Field Name : axSysCpuIndex
Field Type : Integer32
Field Status : current
Description : The index of the CPU.
OID : 1.3.6.1.4.1.22610.2.4.1.3.2.1.1

Field Name : axSysCpuNumber
Field Type : Integer32
Field Status : current
Description : The cpu number in a10System
OID : 1.3.6.1.4.1.22610.2.4.1.3.1

Field Name : axSysCpuUsagePerPartitionEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The CPU Usage per partition entry
OID : 1.3.6.1.4.1.22610.2.4.1.3.7.1

Field Name : axSysCpuUsagePerPartitionCtrlCpuFlag
Field Type : Integer32
Field Status : current
Description : The control CPU flag: 1 - control CPU, 0 - data CPU.
OID : 1.3.6.1.4.1.22610.2.4.1.3.7.1.5

Field Name : axSysCpuUsagePerPartitionValueAtPeriod
Field Type : Integer32
Field Status : current
Description : The CPU usage per partition value at given period, 1-sec, 5-sec, 10-sec,
30-sec, and 60-sec.
OID : 1.3.6.1.4.1.22610.2.4.1.3.7.1.4

Field Name : axSysCpuUsagePartitionName
Field Type : String
Field Status : current
Description : The partition name in the CPU usage per partition table.
OID : 1.3.6.1.4.1.22610.2.4.1.3.7.1.3

Field Name : axSysCpuUsagePerPartitionPeriodIndex
Field Type : Integer32
Field Status : current
Description : The CPU usage per partition sampling period:
: 1: 1-second sampling,
: 2: 5-second sampling,
: 3: 10-second sampling,
: 4: 30-second sampling,
: 5: 60-second sampling.
OID : 1.3.6.1.4.1.22610.2.4.1.3.7.1.2

Field Name : axSysCpuIndexInUsagePerPartition
Field Type : Integer32
Field Status : current
Description : The index of the CPU. The value, 0, is for the control CPU.
OID : 1.3.6.1.4.1.22610.2.4.1.3.7.1.1

Field Name : axSysMemoryUsage
Field Type : Integer32
Field Status : current

Description : The usage memory(KB).
OID : 1.3.6.1.4.1.22610.2.4.1.2.2

Field Name : axSysMemoryTotal
Field Type : Integer32
Field Status : current
Description : The total memory(KB).
OID : 1.3.6.1.4.1.22610.2.4.1.2.1

Field Name : axSysSecondaryVersionOnCF
Field Type : String
Field Status : current
Description : The secondary system image version on Compact Flash.
OID : 1.3.6.1.4.1.22610.2.4.1.1.4

Field Name : axSysPrimaryVersionOnCF
Field Type : String
Field Status : current
Description : The primary system image version on Compact Flash.
OID : 1.3.6.1.4.1.22610.2.4.1.1.3

Field Name : axSysSecondaryVersionOnDisk
Field Type : String
Field Status : current
Description : The secondary system image version on hard disk.
OID : 1.3.6.1.4.1.22610.2.4.1.1.2

Field Name : axSysPrimaryVersionOnDisk
Field Type : String
Field Status : current
Description : The primary system image version on hard disk.
OID : 1.3.6.1.4.1.22610.2.4.1.1.1

Field Name : axTrunkStatTable
Field Type : TABLE
Field Status : current
Description : A table contains trunk statistic information.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.2.2

Field Name : axTrunkStatTotal
Field Type : INTEGER
Field Status : current
Description : The total number of axTrunkStat entries in the table.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.2.1

Field Name : axTrunkStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axTrunkStatTable
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.2.2.1

Field Name : axTrunkStatDropsOut
Field Type : Counter64
Field Status : current
Description : The total number of packets aged out or with excessive transmission
: delays due to multiple deferrals on the given trunk.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.2.2.1.11

Field Name : axTrunkStatDropsIn
Field Type : Counter64
Field Status : current
Description : The total number of dropped packets on the given trunk.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.2.2.1.10

Field Name : axTrunkStatErrorsOut
Field Type : Counter64
Field Status : current
Description : The total number of excessive collisions, incremented for each
: frame that experienced 16 collisions during transmission and
: was aborted on the given trunk.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.2.2.1.9

Field Name : axTrunkStatErrorsIn
Field Type : Counter64
Field Status : current
Description : The total number of received packets with errors by the given trunk.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.2.2.1.8

Field Name : axTrunkStatMcastOut
Field Type : Counter64
Field Status : current
Description : The total number of transmitted multicast packets out of the given trunk.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.2.2.1.7

Field Name : axTrunkStatMcastIn
Field Type : Counter64
Field Status : current
Description : The total number of received multicast packets on the given trunk.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.2.2.1.6

Field Name : axTrunkStatBytesOut
Field Type : Counter64
Field Status : current
Description : The total number of transmitted bytes on the given trunk.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.2.2.1.5

Field Name : axTrunkStatPktsOut
Field Type : Counter64
Field Status : current
Description : The total number of transmitted packets on the given trunk.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.2.2.1.4

Field Name : axTrunkStatBytesIn
Field Type : Counter64
Field Status : current
Description : The total number of received bytes on the given trunk.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.2.2.1.3

Field Name : axTrunkStatPktsIn
Field Type : Counter64
Field Status : current
Description : The total number of received packets on the given trunk.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.2.2.1.2

Field Name : axTrunkStatName
Field Type : String

Field Status : current
Description : The trunk name.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.2.2.1.1

Field Name : axTrunkTable
Field Type : TABLE
Field Status : current
Description : A table contains trunk information.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.1.2

Field Name : axTrunkTotal
Field Type : INTEGER
Field Status : current
Description : The total number of axTrunk entries in the table.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.1.1

Field Name : axTrunkEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axTrunkTable
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.1.2.1

Field Name : axTrunkAlias
Field Type : String
Field Status : current
Description : The trunk alias name.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.1.2.1.8

Field Name : axTrunkPortThresholdTimer
Field Type : INTEGER
Field Status : current
Description : Timer for port-threshold in second.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.1.2.1.7

Field Name : axTrunkPortThreshold
Field Type : INTEGER
Field Status : current
Description : Threshold for minimum number of ports that need to be up.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.1.2.1.6

Field Name : axTrunkCfgMemberCount
Field Type : INTEGER
Field Status : current
Description : The total number of configured trunk members.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.1.2.1.5

Field Name : axTrunkTypeLacpEnabled
Field Type : EnumVal
Field Status : current
Description : The trunk type is dynamic, LACP.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.1.2.1.4

Field Name : axTrunkDescription
Field Type : String
Field Status : current
Description : The trunk description.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.1.2.1.3

Field Name : axTrunkStatus
Field Type : EnumVal
Field Status : current
Description : The trunk status.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.1.2.1.2

Field Name : axTrunkName
Field Type : String
Field Status : current
Description : The trunk name.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.1.2.1.1

Field Name : axTrunkCfgMemberTable
Field Type : TABLE
Field Status : current
Description : A table contains configured trunk member information.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.3.2

Field Name : axTrunkCfgMemberTotal
Field Type : INTEGER
Field Status : current
Description : The total number of axTrunkCfgMember entries.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.3.1

Field Name : axTrunkCfgMemberEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the sysTrunkCfgMember Table
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.3.2.1

Field Name : axTrunkCfgMemberOperStatus
Field Type : EnumVal
Field Status : current
Description : The trunk port member operational status.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.3.2.1.4

Field Name : axTrunkCfgMemberAdminStatus
Field Type : EnumVal
Field Status : current
Description : The trunk port member administrative status.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.3.2.1.3

Field Name : axTrunkCfgMemberName
Field Type : String
Field Status : current
Description : The trunk member name: the physical port belongs to the trunk.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.3.2.1.2

Field Name : axTrunkCfgMemberTrunkName
Field Type : String
Field Status : current
Description : The trunk name.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.3.2.1.1

Field Name : axVlanCfgMemberTable
Field Type : TABLE
Field Status : current
Description : The table contains VLAN member configuration.

OID : 1.3.6.1.4.1.22610.2.4.1.7.2.1.2

Field Name : axVlanCfgTable
Field Type : TABLE
Field Status : current
Description : The table contains VLAN configuration.
OID : 1.3.6.1.4.1.22610.2.4.1.7.2.1.1

Field Name : axVlanCfgEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axVlanCfgTable
OID : 1.3.6.1.4.1.22610.2.4.1.7.2.1.1.1

Field Name : axVlanRouterInterface
Field Type : Integer32
Field Status : current
Description : VLAN router interface (ve) if configured. If a SNMP-Get value is zero,
that means this object is not configured.
OID : 1.3.6.1.4.1.22610.2.4.1.7.2.1.1.1.3

Field Name : axVlanName
Field Type : String
Field Status : current
Description : The VLAN name.
OID : 1.3.6.1.4.1.22610.2.4.1.7.2.1.1.1.2

Field Name : axVlanId
Field Type : Integer32
Field Status : current
Description : The VLAN id.
OID : 1.3.6.1.4.1.22610.2.4.1.7.2.1.1.1.1

Field Name : axVlanCfgMemberEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axVlanCfgMemberTable
OID : 1.3.6.1.4.1.22610.2.4.1.7.2.1.2.1

Field Name : axVlanMemberTagged
Field Type : EnumVal
Field Status : current
Description : The tagged/untagged state of the specific VLAN member.
OID : 1.3.6.1.4.1.22610.2.4.1.7.2.1.2.1.3

Field Name : axVlanMemberIntfId
Field Type : Integer32
Field Status : current
Description : The interface id configures as the VLAN member.
OID : 1.3.6.1.4.1.22610.2.4.1.7.2.1.2.1.2

Field Name : axVlanMemberVlanId
Field Type : Integer32
Field Status : current
Description : The VLAN id.
OID : 1.3.6.1.4.1.22610.2.4.1.7.2.1.2.1.1

Field Name : axInterfaceTable

Field Type : TABLE
Field Status : current
Description : A table containing information of the physical interfaces.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.1.2

Field Name : axInterfaceCount
Field Type : Integer32
Field Status : current
Description : The number of axInterface entries in the table.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.1.1

Field Name : axInterfaceEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axInterface Table
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.1.2.1

Field Name : axInterfaceFlowCtrlOperStatus
Field Type : EnumVal
Field Status : current
Description : The control flow state of this interface.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.1.2.1.13

Field Name : axInterfaceFlowCtrlAdminStatus
Field Type : EnumVal
Field Status : current
Description : The control flow of this interface is enabled or disabled.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.1.2.1.12

Field Name : axInterfaceAlias
Field Type : String
Field Status : current
Description : The alias name of the interface if defined.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.1.2.1.11

Field Name : axInterfaceStatus
Field Type : EnumVal
Field Status : current
Description : The current state of the interface.
: up - has link and is initialized;
: down - has no link and is initialized;
: disabled - has been forced down
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.1.2.1.10

Field Name : axInterfaceAdminStatus
Field Type : EnumVal
Field Status : current
Description : The state of this interface, whether it is enabled.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.1.2.1.9

Field Name : axInterfaceMtu
Field Type : Integer32
Field Status : current
Description : The maximum transmission unit size of datagram which can be
: sent/received on the specified interface.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.1.2.1.8

Field Name : axInterfaceMacAddr

Field Type : String
Field Status : current
Description : The MAC address of the specified interface.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.1.2.1.7

Field Name : axInterfaceMediaActiveDuplex
Field Type : EnumVal
Field Status : current
Description : The active media duplex mode for the specified interface.
: half - Half duplex;
: full - Full duplex;
: auto - Auto duplex;
: none - All media is disabled.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.1.2.1.6

Field Name : axInterfaceMediaActiveSpeed
Field Type : Integer32
Field Status : current
Description : The current active media speed for the interface.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.1.2.1.5

Field Name : axInterfaceMediaMaxDuplex
Field Type : EnumVal
Field Status : current
Description : The best possible media duplex mode for the interface.
: half - Force half duplex;
: full - Force full duplex;
: none - All media is deselected.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.1.2.1.4

Field Name : axInterfaceMediaMaxSpeed
Field Type : Integer32
Field Status : current
Description : The best possible media speed in MBPS for the interface.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.1.2.1.3

Field Name : axInterfaceName
Field Type : String
Field Status : current
Description : The name of the interface.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.1.2.1.2

Field Name : axInterfaceIndex
Field Type : Integer32
Field Status : current
Description : The index value of the interface.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.1.2.1.1

Field Name : axInterfaceStatTable
Field Type : TABLE
Field Status : current
Description : A table containing statistic information of the physical interfacess.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1

Field Name : axInterfaceStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axInterfaceStat Table

OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1

Field Name : axInterfaceStatUtilPercentOut
Field Type : Integer32
Field Status : current
Description : The output utilization in percentage. For the ve interface, it's 0.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.18

Field Name : axInterfaceStatPktsPerSecOut
Field Type : Counter64
Field Status : current
Description : The output rate in packets per second.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.17

Field Name : axInterfaceStatBitsPerSecOut
Field Type : Counter64
Field Status : current
Description : The output rate in bits per second.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.16

Field Name : axInterfaceStatUtilPercentIn
Field Type : Integer32
Field Status : current
Description : The input utilization in percentage. For the ve interface, it's 0.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.15

Field Name : axInterfaceStatPktsPerSecIn
Field Type : Counter64
Field Status : current
Description : The input rate in packets per second.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.14

Field Name : axInterfaceStatBitsPerSecIn
Field Type : Counter64
Field Status : current
Description : The input rate in bits per second.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.13

Field Name : axInterfaceStatCollisions
Field Type : Counter64
Field Status : current
Description : The number of collisions on this interface, incremented by the
: number of collisions experienced during transmissions of a frame
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.12

Field Name : axInterfaceStatDropsOut
Field Type : Counter64
Field Status : current
Description : The number of packets aged out or with excessive transmission
: delays due to multiple deferrals.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.11

Field Name : axInterfaceStatDropsIn
Field Type : Counter64
Field Status : current
Description : The number of packets dropped on ingress for various reasons.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.10

Field Name : axInterfaceStatErrorsOut
Field Type : Counter64
Field Status : current
Description : The number of excessive collisions, incremented for each
: frame that experienced 16 collisions during transmission and
: was aborted.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.9

Field Name : axInterfaceStatErrorsIn
Field Type : Counter64
Field Status : current
Description : The number of received packets that are either undersized,
: oversized, or have FCS errors.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.8

Field Name : axInterfaceStatMcastOut
Field Type : Counter64
Field Status : current
Description : The number of multicast packets transmitted out of this interface.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.7

Field Name : axInterfaceStatMcastIn
Field Type : Counter64
Field Status : current
Description : The number of multicast packets received on this interface.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.6

Field Name : axInterfaceStatBytesOut
Field Type : Counter64
Field Status : current
Description : The number of bytes transmitted out of this interface.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.5

Field Name : axInterfaceStatPktsOut
Field Type : Counter64
Field Status : current
Description : The number of packets transmitted out of this interface.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.4

Field Name : axInterfaceStatBytesIn
Field Type : Counter64
Field Status : current
Description : The number of bytes received on this interface.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.3

Field Name : axInterfaceStatPktsIn
Field Type : Counter64
Field Status : current
Description : The number of packets received on this interface.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.2

Field Name : axInterfaceStatIndex
Field Type : Integer32
Field Status : current
Description : The index value of the interface.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.1

Field Name : axArpInfoTable

Field Type : TABLE
Field Status : current
Description : A table contains opertional ARP information.
OID : 1.3.6.1.4.1.22610.2.4.1.7.100.1.2

Field Name : axArpEntryTotal
Field Type : INTEGER
Field Status : current
Description : The total number of ARP entries in the table.
OID : 1.3.6.1.4.1.22610.2.4.1.7.100.1.1

Field Name : axArpInfoEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axArpInfoTable
OID : 1.3.6.1.4.1.22610.2.4.1.7.100.1.2.1

Field Name : axArpEntryAging
Field Type : INTEGER
Field Status : current
Description : The aging time of the ARP entry in seconds.
OID : 1.3.6.1.4.1.22610.2.4.1.7.100.1.2.1.7

Field Name : axArpEntryType
Field Type : EnumVal
Field Status : current
Description : The type of the ARP entry.
OID : 1.3.6.1.4.1.22610.2.4.1.7.100.1.2.1.6

Field Name : axArpEntrySourceIntName
Field Type : String
Field Status : current
Description : The interface description name for axArpEntrySourceInterface.
OID : 1.3.6.1.4.1.22610.2.4.1.7.100.1.2.1.5

Field Name : axArpEntrySourceInterface
Field Type : INTEGER
Field Status : current
Description : The port number in ifIndex for the ARP entry taking effective.
OID : 1.3.6.1.4.1.22610.2.4.1.7.100.1.2.1.4

Field Name : axArpEntryVlan
Field Type : INTEGER
Field Status : current
Description : The VLAN identifier for the ARP entry.
OID : 1.3.6.1.4.1.22610.2.4.1.7.100.1.2.1.3

Field Name : axArpMacAddr
Field Type : String
Field Status : current
Description : The MAC address for the ARP entry.
OID : 1.3.6.1.4.1.22610.2.4.1.7.100.1.2.1.2

Field Name : axArpIpAddr
Field Type : String
Field Status : current
Description : The destination IP address of the ARP entry.
OID : 1.3.6.1.4.1.22610.2.4.1.7.100.1.2.1.1

Field Name : axCurrFiveSecCtrlCpuUsageTable
Field Type : TABLE
Field Status : current
Description : The table contains current 5 second control cpu usage
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.10

Field Name : axCurrFiveSecDataCpuUsageTable
Field Type : TABLE
Field Status : current
Description : The table contains current 5 second data cpu usage
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.9

Field Name : axCurrFiveSecDataCpuUsageEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axCurrFiveSecDataCpuUsageTable
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.9.1

Field Name : axCurrFiveSecDataCpuUsage
Field Type : Integer32
Field Status : current
Description : The five second data cpu usage in the slot.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.9.1.3

Field Name : axCurrFiveSecDataCpuId
Field Type : Integer32
Field Status : current
Description : The data cpu id.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.9.1.2

Field Name : axCurrFiveSecDataCpuUsageSlotId
Field Type : Integer32
Field Status : current
Description : The slot id of chassis.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.9.1.1

Field Name : axDiskTable
Field Type : TABLE
Field Status : current
Description : The table contains disk information
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.8

Field Name : axDiskEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axDiskTable
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.8.1

Field Name : axDiskFree
Field Type : Integer32
Field Status : current
Description : Free disk.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.8.1.4

Field Name : axDiskUsed
Field Type : Integer32
Field Status : current

Description : Used disk.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.8.1.3

Field Name : axDiskTotal
Field Type : Integer32
Field Status : current
Description : Total Disk Space.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.8.1.2

Field Name : axDiskSlotId
Field Type : Integer32
Field Status : current
Description : The slot id of chassis.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.8.1.1

Field Name : axPowerSupplyTable
Field Type : TABLE
Field Status : current
Description : The table contains power supply.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.7

Field Name : axPowerSupplyEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axPowerSupplyTable
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.7.1

Field Name : axPowerSupplyStatus
Field Type : EnumVal
Field Status : current
Description : System Voltage status:
: 0: off, 1: on, 2: absent, -1: unknown.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.7.1.4

Field Name : axPowerSupplyName
Field Type : String
Field Status : current
Description : Power supply name.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.7.1.3

Field Name : axPowerSupplyIndex
Field Type : Integer32
Field Status : current
Description : The power supply index.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.7.1.2

Field Name : axPowerSupplySlotId
Field Type : Integer32
Field Status : current
Description : The slot id of chassis.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.7.1.1

Field Name : axSystemVoltageTable
Field Type : TABLE
Field Status : current
Description : The table contains system voltage.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.6

Field Name : axSystemVoltageEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axSystemVoltageTable
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.6.1

Field Name : axSystemVoltageDesc
Field Type : String
Field Status : current
Description : System voltage description.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.6.1.4

Field Name : axSystemVoltageStatus
Field Type : EnumVal
Field Status : current
Description : System Voltage status:
: 0: invalid, 1: normal, 2: unknown.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.6.1.3

Field Name : axSystemVoltageIndex
Field Type : Integer32
Field Status : current
Description : The system voltage index.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.6.1.2

Field Name : axSystemVoltageSlotId
Field Type : Integer32
Field Status : current
Description : The slot id of chassis.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.6.1.1

Field Name : axMemoryTable
Field Type : TABLE
Field Status : current
Description : The table contains memory information
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.5

Field Name : axMemoryEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axMemoryTable
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.5.1

Field Name : axMemoryUsage
Field Type : Integer32
Field Status : current
Description : Memory Usage.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.5.1.3

Field Name : axMemoryTotal
Field Type : Integer32
Field Status : current
Description : Total Memory(KB).
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.5.1.2

Field Name : axMemorySlotId
Field Type : Integer32
Field Status : current

Description : The slot id of chassis.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.5.1.1

Field Name : axAverageDataCpuUsageTable
Field Type : TABLE
Field Status : current
Description : The table contains average data cpu usage
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.4

Field Name : axAverageDataCpuUsageEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axAverageDataCpuUsageTable
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.4.1

Field Name : axAverageDataCpuUsage
Field Type : Integer32
Field Status : current
Description : The average Data cpu usage in the slot.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.4.1.2

Field Name : axAverageDataCpuUsageSlotId
Field Type : Integer32
Field Status : current
Description : The slot id of chassis.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.4.1.1

Field Name : axAverageControlCpuUsageTable
Field Type : TABLE
Field Status : current
Description : The table contains average control cpu usage.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.3

Field Name : axAverageControlCpuUsageEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axAverageControlCpuUsageTable.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.3.1

Field Name : axAverageControlCpuUsage
Field Type : Integer32
Field Status : current
Description : The average control cpu usage in the slot.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.3.1.2

Field Name : axAverageControlCpuUsageSlotId
Field Type : Integer32
Field Status : current
Description : The slot id of chassis.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.3.1.1

Field Name : axTemperatureTable
Field Type : TABLE
Field Status : current
Description : The table contains system temperature.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.2

Field Name : axTemperatureEntry

Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axTemperatureTable
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.2.1

Field Name : axTemperature
Field Type : EnumVal
Field Status : current
Description : The physical temperature.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.2.1.3

Field Name : axTemperatureIndex
Field Type : Integer32
Field Status : current
Description : The index of axTermperature
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.2.1.2

Field Name : axTemperatureSlotId
Field Type : Integer32
Field Status : current
Description : The slot id in chassis, slot id start from 1 for master.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.2.1.1

Field Name : axFanTable
Field Type : TABLE
Field Status : current
Description : The table contains system fan status
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.1

Field Name : axFanEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axFanTable
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.1.1

Field Name : axFanSpeed
Field Type : Integer32
Field Status : current
Description : The fan speed.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.1.1.5

Field Name : axFanStatus
Field Type : EnumVal
Field Status : current
Description : Fan status:
: 0: Failed, 4: OK-fixed/high, 5: OK-low/med, 6: OK-med/med, 7:
: OK-med/high,
: -2: not ready, -1: unknown.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.1.1.4

Field Name : axFanName
Field Type : String
Field Status : current
Description : The system fan name.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.1.1.3

Field Name : axFanIndex
Field Type : Integer32

Field Status : current
Description : The system fan index, index start from 1 which is the first fan.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.1.2

Field Name : axFanSlotId
Field Type : Integer32
Field Status : current
Description : The slot id in chassis, slot id start from 1 for master.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.1.1

Field Name : axCurrFiveSecCtrlCpuUsageEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axCurrFiveSecCtrlCpuUsageTable
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.10.1

Field Name : axCurrFiveSecCtrlCpuUsage
Field Type : Integer32
Field Status : current
Description : The five second control cpu usage in the slot.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.10.1.3

Field Name : axCurrFiveSecCtrlCpuId
Field Type : Integer32
Field Status : current
Description : The data cpu id.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.10.1.2

Field Name : axCurrFiveSecCtrlCpuUsageSlotId
Field Type : Integer32
Field Status : current
Description : The slot id of chassis.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.10.1.1

Field Name : axSlbL4StatsTable
Field Type : TABLE
Field Status : current
Description : The table contains slb layer 4 statistics
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.5.1

Field Name : axSlbL4StatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axSlbL4Table
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.5.1.1

Field Name : axSlbL4StatsNatNoSessionDrops
Field Type : CounterBasedGauge64
Field Status : current
Description : SLB L4 NAT no session drops.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.5.1.1.2

Field Name : axSlbL4StatsSlotId
Field Type : Integer32
Field Status : current
Description : The slot-id of chassis .
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.5.1.1.1

Field Name : axFwGlobalStatsTable
Field Type : TABLE
Field Status : current
Description : The table contains fw global statistics.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.4.1

Field Name : axFwSystemStatusTable
Field Type : TABLE
Field Status : current
Description : The table contains fw system-status.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.4.4

Field Name : axFwSystemStatusEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axFwSystemStatusTable.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.4.4.1

Field Name : axFwSystemStatusDataSessionFree
Field Type : CounterBasedGauge64
Field Status : current
Description : The fw data session free.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.4.4.1.3

Field Name : axFwSystemStatusDataSessionUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : The fw data session used.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.4.4.1.2

Field Name : axFwSystemStatusSlotId
Field Type : Integer32
Field Status : current
Description : The slot-id of chassis .
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.4.4.1.1

Field Name : axFwGlobalStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axFwGlobalStatsTable.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.4.1.1

Field Name : axFwDataSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : The firewall data session freed.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.4.1.1.8

Field Name : axFwFullconeCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : The firewall full cone creation failure.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.4.1.1.7

Field Name : axFwActiveFullconeSession
Field Type : CounterBasedGauge64
Field Status : current
Description : The firewall active full cone session.

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.4.1.1.6

Field Name : axFwUdpFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : The firewall udp full cone freed.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.4.1.1.5

Field Name : axFwUdpFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : The firewall udp full cone created.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.4.1.1.4

Field Name : axFwTcpFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : The firewall tcp full cone freed.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.4.1.1.3

Field Name : axFwTcpFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : The firewall tcp full cone created.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.4.1.1.2

Field Name : axFwGlobalStatsSlotId
Field Type : Integer32
Field Status : current
Description : The slot-id of chassis .
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.4.1.1.1

Field Name : axLsnGlobalStatsTable
Field Type : TABLE
Field Status : current
Description : The table contains cgnv6 lsn global statistics.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.4

Field Name : axLsnGlobalStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axLsnGlobalStatsTable
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.4.1

Field Name : axLsnGlobalStatsIcmpUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : The lsn global icmp user quota exceeded
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.4.1.4

Field Name : axLsnGlobalStatsUdpUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : The lsn global udp user quota exceeded
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.4.1.3

Field Name : axLsnGlobalStatsTcpUserQuotaExceeded
Field Type : CounterBasedGauge64

Field Status : current
Description : The lsn global tcp user quota exceeded
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.4.1.2

Field Name : axLsnGlobalStatsSlotId
Field Type : Integer32
Field Status : current
Description : The slot-id of chassis .
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.4.1.1

Field Name : axLsnSystemStatusNatPortUsageTable
Field Type : TABLE
Field Status : current
Description : The table contains nat port usage of cgnv6 lsn system-status.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.3

Field Name : axLsnSystemStatusNatPortUsageEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axLsnSystemStatusNatPortUsageTable
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.3.1

Field Name : axLsnSystemStatusUdpNatPortFree
Field Type : CounterBasedGauge64
Field Status : current
Description : The udp nat port free on cgnv6 lsn system status
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.3.1.5

Field Name : axLsnSystemStatusUdpNatPortUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : The udp nat port used on cgnv6 lsn system status
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.3.1.4

Field Name : axLsnSystemStatusTcpNatPortFree
Field Type : CounterBasedGauge64
Field Status : current
Description : The tcp nat port free on cgnv6 lsn system status
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.3.1.3

Field Name : axLsnSystemStatusTcpNatPortUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : The tcp nat port used on cgnv6 lsn system status
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.3.1.2

Field Name : axLsnSystemStatusNatPortUsageSlotId
Field Type : Integer32
Field Status : current
Description : The slot-id of chassis .
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.3.1.1

Field Name : axLsnSystemStatusSessionTable
Field Type : TABLE
Field Status : current
Description : The table contains session of cgnv6 lsn system-status.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.2

Field Name : axLsnSystemStatusSessionEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axLsnSystemStatusSessionTable
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.2.1

Field Name : axLsnSystemStatusSMPSessionFree
Field Type : CounterBasedGauge64
Field Status : current
Description : The SMP session free on cgnv6 lsn system status
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.2.1.5

Field Name : axLsnSystemStatusSMPSessionUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : The SMP session used on cgnv6 lsn system status
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.2.1.4

Field Name : axLsnSystemStatusDataSessionFree
Field Type : CounterBasedGauge64
Field Status : current
Description : The data session free on cgnv6 lsn system status
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.2.1.3

Field Name : axLsnSystemStatusDataSessionUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : The data session used on cgnv6 lsn system status
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.2.1.2

Field Name : axLsnSystemStatusSessionSlotId
Field Type : Integer32
Field Status : current
Description : The slot-id of chassis .
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.2.1.1

Field Name : axLsnUserQuotaSessionTable
Field Type : TABLE
Field Status : current
Description : The table contains cgnv6 lsn user quota session count
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.1.1

Field Name : axLsnUserQuotaSessionEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axLsnUserQuotaSessionTable
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.1.1.1

Field Name : axLsnUserQuotaSessionCount
Field Type : CounterBasedGauge64
Field Status : current
Description : The total session of lsn user quota session.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.1.1.1.2

Field Name : axLsnUserQuotaSessionSlotId
Field Type : Integer32
Field Status : current
Description : The slot-id of chassis .

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.1.1.1.1

Field Name : axLsnFullConeSessionStatsTable
Field Type : TABLE
Field Status : current
Description : The table contains cgnv6 lsn full-cone-session statistics.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.5.1

Field Name : axLsnFullConeSessionStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axLsnFullConeSessionStatsTable
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.5.1.1

Field Name : axLsnFullConeSessionStatsTotalSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : The lsn total full cone sessions.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.5.1.1.2

Field Name : axLsnFullConeSessionStatsSlotId
Field Type : Integer32
Field Status : current
Description : The slot-id of chassis .
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.5.1.1.1

Field Name : axNatPoolStatTable
Field Type : TABLE
Field Status : current
Description : The table contains pool statistics of cgnv6 nat pool.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.2.1

Field Name : axNatPoolStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axNatPoolStatTable
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.2.1.1

Field Name : axNatPoolStatUsers
Field Type : CounterBasedGauge64
Field Status : current
Description : The number of users of cgnv6 lsn nat pool.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.2.1.1.3

Field Name : axNatPoolStatPoolName
Field Type : String
Field Status : current
Description : The pool name of cgnv6 lsn nat pool.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.2.1.1.2

Field Name : axNatPoolStatSlotId
Field Type : Integer32
Field Status : current
Description : The slot-id of chassis .
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.2.1.1.1

Field Name : axEthIntfStatsTable
Field Type : TABLE

Field Status : current
Description : The table contains ethernet interface statistics.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.3

Field Name : axLifIntfStatsTable
Field Type : TABLE
Field Status : current
Description : The table contains lif interface statistics.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.2

Field Name : axLifIntfStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axLifIntfStatsTable.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.2.1

Field Name : axLifIntfStatsRateBitsSend
Field Type : CounterBasedGauge64
Field Status : current
Description : The rate bites send out on the lif interface.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.2.1.4

Field Name : axLifIntfStatsRateBitsRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : The rate bites received on the lif interface.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.2.1.3

Field Name : axLifIntfStatsIntfName
Field Type : String
Field Status : current
Description : The lif interface name.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.2.1.2

Field Name : axLifIntfStatsSlotId
Field Type : Integer32
Field Status : current
Description : The slot-id of chassis .
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.2.1.1

Field Name : axVEIntfStatsTable
Field Type : TABLE
Field Status : current
Description : The table contains ve interface statistics.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.1

Field Name : axVEIntfStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axVEIntfStatsTable.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.1.1

Field Name : axVEIntfStatsRateBitsSend
Field Type : CounterBasedGauge64
Field Status : current
Description : The rate bites send out on the ve interface.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.1.1.4

Field Name : axVEIntfStatsRateBitsRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : The rate bites received on the ve interface.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.1.1.3

Field Name : axVEIntfStatsIntfNum
Field Type : Integer32
Field Status : current
Description : The ve interface number.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.1.1.2

Field Name : axVEIntfStatsSlotId
Field Type : Integer32
Field Status : current
Description : The slot-id of chassis.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.1.1.1

Field Name : axEthIntfStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axEthIntfStatsTable.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.3.1

Field Name : axEthIntfStatUtilPercentOut
Field Type : Integer32
Field Status : current
Description : The output utilization in percentage.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.3.1.11

Field Name : axEthIntfStatUtilPercentIn
Field Type : Integer32
Field Status : current
Description : The input utilization in percentage
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.3.1.10

Field Name : axEthIntfStatCollisions
Field Type : Counter64
Field Status : current
Description : The number of collisions on this interface, incremented by the
: number of collisions experienced during transmissions of a frame
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.3.1.9

Field Name : axEthIntfStatDropsOut
Field Type : Counter64
Field Status : current
Description : The number of packets aged out or with excessive transmission
: delays due to multiple deferrals.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.3.1.8

Field Name : axEthIntfStatDropsIn
Field Type : CounterBasedGauge64
Field Status : current
Description : The number of packets dropped on ingress for various reasons.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.3.1.7

Field Name : axEthIntfStatErrorsOut
Field Type : Counter64

Field Status : current
Description : The number of excessive collisions, incremented for each
: frame that experienced 16 collisions during transmission and
: was aborted.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.3.1.6

Field Name : axEthIntfStatErrorsIn
Field Type : Counter64
Field Status : current
Description : The number of received packets that are either undersized,
: oversized, or have FCS errors.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.3.1.5

Field Name : axEthIntfStatsRateBitsSend
Field Type : CounterBasedGauge64
Field Status : current
Description : The rate bites send out on the ethernet interface.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.3.1.4

Field Name : axEthIntfStatsRateBitsRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : The rate bites received on the ethernet interface.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.3.1.3

Field Name : axEthIntfStatsIfNum
Field Type : Integer32
Field Status : current
Description : The ethernet interface number.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.3.1.2

Field Name : axEthIntfStatsSlotId
Field Type : Integer32
Field Status : current
Description : The slot-id of chassis .
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.3.1.1

Field Name : axSystemAppBufferTable
Field Type : TABLE
Field Status : current
Description : The table contains system application buffer data.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.5

Field Name : axSystemRadiusServerStatTable
Field Type : TABLE
Field Status : current
Description : The table contains radius server statistics of system
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.4.1

Field Name : axSystemRadiusServerStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axSystemRadiusServerStatTable
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.4.1.1

Field Name : axSystemRadiusServerRequestTableFullDropped
Field Type : TABLE
Field Status : current

Description : The radius request table full dropped on system radius server statistics
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.4.1.1.5

Field Name : axSystemRadiusServerRequestMalformedDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : The radius request malformed dropped on system radius server statistics
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.4.1.1.4

Field Name : axSystemRadiusServerRequestBadSecretDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : The radius request bad secret dropped on system radius server statistics
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.4.1.1.3

Field Name : axSystemRadiusServerRequestReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : The radius request received on system radius server statistics
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.4.1.1.2

Field Name : axSystemRadiusServerStatSlotId
Field Type : Integer32
Field Status : current
Description : The slot-id of chassis .
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.4.1.1.1

Field Name : axSessionStatsTable
Field Type : TABLE
Field Status : current
Description : The table contains session stats.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.3

Field Name : axSessionStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axSessionStatsTable.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.3.1

Field Name : axSessionStatsTcpEstabRate
Field Type : INTEGER
Field Status : current
Description : The TCP Estab Rate.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.3.1.97

Field Name : axSessionStatsTcpHalfOpenCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : The TCP half open.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.3.1.14

Field Name : axSessionStatsTcpEstCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : The TCP established.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.3.1.13

Field Name : axSessionStatsConnCount

Field Type : CounterBasedGauge64
Field Status : current
Description : The global total connection count.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.3.1.5

Field Name : axSessionStatsTotalFwConn
Field Type : CounterBasedGauge64
Field Status : current
Description : The global total firewall connections.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.3.1.4

Field Name : axSessionStatsCurrFreeConn
Field Type : CounterBasedGauge64
Field Status : current
Description : The global current free connections.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.3.1.3

Field Name : axSessionStatsUDP
Field Type : CounterBasedGauge64
Field Status : current
Description : The global UDP connections.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.3.1.2

Field Name : axSessionStatsSlotId
Field Type : Integer32
Field Status : current
Description : The slot-id of chassis .
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.3.1.1

Field Name : axSystemAppPerformanceTable
Field Type : TABLE
Field Status : current
Description : The table contains system app-performance cpi.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.2

Field Name : axSystemAppPerformanceEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axSystemAppPerformanceTable.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.2.1

Field Name : axSystemAppPerformanceFwCpi
Field Type : CounterBasedGauge64
Field Status : current
Description : The FW cpi of global system app-performance.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.2.1.5

Field Name : axSystemAppPerformanceNatCpi
Field Type : CounterBasedGauge64
Field Status : current
Description : The NAT cpi of global system app-performance.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.2.1.4

Field Name : axSystemAppPerformanceNewConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : The total new connections of global system app-performance.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.2.1.3

Field Name : axSystemAppPerformanceCurrentConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : The total current connections of global system app-performance.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.2.1.2

Field Name : axSystemAppPerformanceSlotId
Field Type : Integer32
Field Status : current
Description : The slot-id of chassis .
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.2.1.1

Field Name : axGlobalThroughputTable
Field Type : TABLE
Field Status : current
Description : The table contains throughput.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.1

Field Name : axGlobalThroughputEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axGlobalThroughputTable.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.1.1

Field Name : axGlobalThroughput
Field Type : CounterBasedGauge64
Field Status : current
Description : The total throughput.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.1.1.2

Field Name : axGlobalThroughputSlotId
Field Type : Integer32
Field Status : current
Description : The slot-id of chassis .
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.1.1.1

Field Name : axSystemAppBufferEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axSystemAppBufferTable.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.5.1

Field Name : axSystemAppBufferTotalDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total number of accumulative buffer drop.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.5.1.3

Field Name : axSystemAppBufferDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total number of buffer drop in last 10 seconds.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.5.1.2

Field Name : axSystemAppBufferSlotId
Field Type : Integer32
Field Status : current

Description : The slot-id of chassis .
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.5.1.1

Field Name : axNetflowMonitorStatsTable
Field Type : TABLE
Field Status : current
Description : The table contains netflow monitor statistics
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.6.1

Field Name : axNetflowMonitorStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axNetflowMonitorTable
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.6.1.1

Field Name : axNetflowMonitorStatsCustSesEveNat44DelRecSentFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom sessoin event nat44 deletion records sent failure.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.6.1.1.4

Field Name : axNetflowMonitorStatsCustSesEveNat44CreatRecSentFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom sessoin event nat44 creation records sent failure.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.6.1.1.3

Field Name : axNetflowMonitorStatsName
Field Type : String
Field Status : current
Description : The netflow monitor name.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.6.1.1.2

Field Name : axNetflowMonitorStatsSlotId
Field Type : Integer32
Field Status : current
Description : The slot-id of chassis .
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.6.1.1.1

Field Name : partitionSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.6.1.1

Field Name : partitionSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.6.1.1.1

Field Name : countersCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : dummy counter for infra
OID : 1.3.6.1.4.1.22610.2.4.10.6.1.1.1.2

Field Name : partitionName

Field Type : String
Field Status : current
Description : Object partition name
OID : 1.3.6.1.4.1.22610.2.4.10.6.1.1.1.1

Field Name : vrrpCommonDummy
Field Type : CounterBasedGauge64
Field Status : current
Description : dummy counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.3.1.1

Field Name : queryPktRxError
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Query recv error
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.180

Field Name : syncTxUpdateMiscCounterAct
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Update misc Sent counter actual
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.179

Field Name : syncTxUpdateAgeCounterAct
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Update Age Sent counter actual
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.178

Field Name : syncTxDelCounterAct
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Del Session Sent counter actual
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.177

Field Name : syncTxCreateCounterAct
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Create Session Sent counter actual
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.176

Field Name : syncTxUpdateMiscBearer
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync update misc bearer sent
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.175

Field Name : syncPktRcvDcMsgDir
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync pkt recv with DCMSG dir
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.174

Field Name : syncRxDropSyncPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync drop all packets
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.173

Field Name : syncRxDcmsgCounterInterPu
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync forward CPU with inter-pu comm
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.172

Field Name : dnsCacheSyncRxErrorCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Cache Sync Error Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.171

Field Name : dnsCacheSyncTxErrorCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Cache Sync Error Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.170

Field Name : dnsCacheSyncRxFragCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Cache Sync Frag Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.169

Field Name : dnsCacheSyncTxFragCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Cache Sync Frag Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.168

Field Name : dnsCacheSyncRxDelCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Cache Sync Del Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.167

Field Name : dnsCacheSyncTxDelCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Cache Sync Del Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.166

Field Name : dnsCacheSyncRxCreateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Cache Sync Create Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.165

Field Name : dnsCacheSyncTxCreateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Cache Sync Create Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.164

Field Name : syncRxFwSetDscpCounter
Field Type : CounterBasedGauge64
Field Status : current

Description : Conn Sync receive fw set dscp counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.163

Field Name : syncTxFwSetDscpCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync send fw set dscp counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.162

Field Name : syncRxExtFwLimitEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync FW Limit Entry Info Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.161

Field Name : syncTxAflexTableEntryNotEligibleCounter
Field Type : TABLE
Field Status : current
Description : send of aflex table entry not eligible
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.160

Field Name : syncTxAflexTableEntryErrorCounter
Field Type : TABLE
Field Status : current
Description : Error on send packet with aflex table entry
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.159

Field Name : syncRxAflexTableEntryFastsyncCounter
Field Type : TABLE
Field Status : current
Description : Sync receive packet with aflex table entry fast sync
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.158

Field Name : syncTxAflexTableEntryFastsyncCounter
Field Type : TABLE
Field Status : current
Description : Sync send packet with aflex table entry fast sync
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.157

Field Name : syncRxAflexTableEntryTimeoutCounter
Field Type : TABLE
Field Status : current
Description : Sync receive packet with aflex table entry timeout
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.156

Field Name : syncTxAflexTableEntryTimeoutCounter
Field Type : TABLE
Field Status : current
Description : Sync send packet with aflex table entry timeout
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.155

Field Name : syncRxAflexTableEntrySetCounter
Field Type : TABLE
Field Status : current
Description : Sync receive packet with aflex table entry set
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.154

Field Name : syncTxAflexTableEntrySetCounter

Field Type : TABLE
Field Status : current
Description : Sync send packet with aflex table entry set
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.153

Field Name : syncRxAflexTableEntryReplaceCounter
Field Type : TABLE
Field Status : current
Description : Sync receive packet with aflex table entry replace
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.152

Field Name : syncTxAflexTableEntryReplaceCounter
Field Type : TABLE
Field Status : current
Description : Sync send packet with aflex table entry replace
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.151

Field Name : syncRxAflexTableEntryLifetimeCounter
Field Type : TABLE
Field Status : current
Description : Sync receive packet with aflex table entry lifetime
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.150

Field Name : syncTxAflexTableEntryLifetimeCounter
Field Type : TABLE
Field Status : current
Description : Sync send packet with aflex table entry lifetime
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.149

Field Name : syncRxAflexTableEntryLookupCounter
Field Type : TABLE
Field Status : current
Description : Sync receive packet with aflex table entry lookup
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.148

Field Name : syncTxAflexTableEntryLookupCounter
Field Type : TABLE
Field Status : current
Description : Sync send packet with aflex table entry lookup
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.147

Field Name : syncRxAflexTableEntryIncrCounter
Field Type : TABLE
Field Status : current
Description : Sync receive packet with aflex table entry incr
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.146

Field Name : syncTxAflexTableEntryIncrCounter
Field Type : TABLE
Field Status : current
Description : Sync send packet with aflex table entry incr
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.145

Field Name : syncRxAflexTableEntryDeleteCounter
Field Type : TABLE
Field Status : current
Description : Sync receive packet with aflex table entry delete
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.144

Field Name : syncTxAflexTableEntryDeleteCounter
Field Type : TABLE
Field Status : current
Description : Sync send packet with aflex table entry delete
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.143

Field Name : syncRxAflexTableEntryAppendCounter
Field Type : TABLE
Field Status : current
Description : Sync receive packet with aflex table entry append
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.142

Field Name : syncTxAflexTableEntryAppendCounter
Field Type : TABLE
Field Status : current
Description : Sync send packet with aflex table entry append
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.141

Field Name : syncRxAflexTableEntryAddCounter
Field Type : TABLE
Field Status : current
Description : Sync receive packet with aflex table entry add
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.140

Field Name : syncTxAflexTableEntryAddCounter
Field Type : TABLE
Field Status : current
Description : Sync send packet with aflex table entry add
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.139

Field Name : syncRxExtFwSoShadowExtInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : FW Scaleout Shadow Ext Info Received
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.138

Field Name : syncTxSmpClearCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Clear SMP Session Pkts Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.137

Field Name : syncRxSmpClearCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Clear SMP Session Pkts Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.136

Field Name : syncTxSmpUpdateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Update SMP Session Pkts Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.135

Field Name : syncTxSmpDeleteCounter
Field Type : CounterBasedGauge64
Field Status : current

Description : Sync Delete SMP Session Pkts Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.134

Field Name : syncTxSmpCreateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Create SMP Session Pkts Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.133

Field Name : syncRxSmpUpdateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Update SMP Session Pkts Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.132

Field Name : syncRxSmpDeleteCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Delete SMP Session Pkts Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.131

Field Name : syncRxSmpCreateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Create SMP Session Pkts Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.130

Field Name : syncRxExtFwGtpEchoExtInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : FW GTP Echo Ext Info Received
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.129

Field Name : syncRxUnreachedPktCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : total number of unreached packets
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.128

Field Name : syncRxOutOfOrderPktCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : total number of out of order packets received
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.127

Field Name : queryRxInvalidMsgDirCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync receive query packet with invalid message dir
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.126

Field Name : queryRxInvalidSyncVersionCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync receive query packet with invalid sync version
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.125

Field Name : queryRxInvalidHaGroupCounter

Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync receive query packet with invalid ha group
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.124

Field Name : queryRxInvalidPartitionCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync receive query packet with invalid partition
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.123

Field Name : syncRxAflexFragCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync receive packet with aflex fragment
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.122

Field Name : syncRxAflexDelCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync receive packet with aflex delete
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.121

Field Name : syncRxAflexCreateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync receive packet with aflex create
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.120

Field Name : syncRxAflexUpdateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync receive packet with aflex update
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.119

Field Name : syncRxTableEntryDelCounter
Field Type : TABLE
Field Status : current
Description : Conn Sync receive packet with table entry delete
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.118

Field Name : syncRxTableEntryCreateCounter
Field Type : TABLE
Field Status : current
Description : Conn Sync receive packet with table entry create
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.117

Field Name : syncRxTableEntryUpdateCounter
Field Type : TABLE
Field Status : current
Description : Conn Sync receive packet with table entry update
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.116

Field Name : syncRxByInactivePeerCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync receive packet by inactive peer
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.115

Field Name : syncRxNoVgrpCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync receive packet with no virtual group
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.114

Field Name : syncRxBadProtocolCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync receive packet with bad protocol
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.113

Field Name : syncPktFailedBuffCopyCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync drop sending packet for failure in sending buffer copy
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.112

Field Name : queryPktNoReceivingIpCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync drop sending packet for invalid receiving ip
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.111

Field Name : syncPktNoReceivingVgrpCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync drop sending packet for invalid receiving virtual group
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.110

Field Name : syncPktNoSendingVgrpCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync drop sending packet for invalid sending virtual group
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.109

Field Name : syncPktEmptyBuffCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync drop sending packet for empty buffer
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.108

Field Name : syncRxInvalidSyncPacketCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync receive invalid packet
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.106

Field Name : syncRxDdosDropCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync receive ddos protect packet
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.105

Field Name : syncRxExtFwGtpLogExtInfo
Field Type : CounterBasedGauge64
Field Status : current

Description : FW GTP Ext Log Info Received
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.104

Field Name : syncRxExtFwGtpExtInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : FW GTP Ext Info Received
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.103

Field Name : syncRxExtFwGtpUInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : FW GTP U Info Received
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.102

Field Name : syncRxExtFwGtpLogInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : FW GTP Log Info Received
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.101

Field Name : syncRxMonEntity
Field Type : CounterBasedGauge64
Field Status : current
Description : Acos monitoring Entities Sync Messages Received
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.100

Field Name : syncTxMonEntity
Field Type : CounterBasedGauge64
Field Status : current
Description : Acos Monitoring Entities Sync Messages Sent
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.99

Field Name : syncRxExtFwApps
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync FIREWALL application information Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.98

Field Name : syncRxNotExpectSyncPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : unexpected session sync packets
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.97

Field Name : syncRxExtFwGtpInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : FW GTP Info Received
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.96

Field Name : syncRxExtDcfwRuleIdleTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync FIREWALL session rule idle timeout information Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.95

Field Name : syncRxExtFwHttpLogging

Field Type : CounterBasedGauge64
Field Status : current
Description : FW HTTP Logging Sync Failures
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.94

Field Name : syncRxZoneFailureCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Zone Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.93

Field Name : syncTxEstabCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync send established state
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.92

Field Name : syncRxEstabCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync rcv established state
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.91

Field Name : syncRxExtDcfwLog
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync FIREWALL session logging information Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.90

Field Name : syncRxExtDcfwRuleId
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync FIREWALL session rule ID information Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.89

Field Name : syncRxExtNatAlgTcpInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync NAT ALG TCP Information
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.88

Field Name : syncRxUpdateSctpConnAddr
Field Type : CounterBasedGauge64
Field Status : current
Description : Update SCTP Addresses Received
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.87

Field Name : syncTxUpdateSctpConnAddr
Field Type : CounterBasedGauge64
Field Status : current
Description : Update SCTP Addresses Sent
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.86

Field Name : syncErrLsnFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync LSN Fullcone Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.85

Field Name : syncRxLsnFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Update LSN Fullcone Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.84

Field Name : syncTxLsnFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Update LSN Fullcone Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.83

Field Name : syncRxExtNatMac
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync NAT MAC Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.82

Field Name : syncRxExtH323Alg
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync H323 TCP ALG Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.81

Field Name : syncRxExtSipAlg
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync SIP TCP ALG Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.80

Field Name : syncRxExtLsnAcIdleTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync LSN ACL Idle Timeout Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.79

Field Name : syncRxExtLsnAcl
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync LSN ACL Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.78

Field Name : syncRxFtpControl
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync FTP Control Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.77

Field Name : syncRxSeqDeltas
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Seq Deltas Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.76

Field Name : syncRxReserveHa
Field Type : CounterBasedGauge64
Field Status : current

Description : Conn Sync Reserve HA Conn
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.75

Field Name : syncRxExtRtsp
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Ext RTSP
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.74

Field Name : syncRxExtPptp
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Ext PPTP
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.73

Field Name : syncRxCreateStaticSby
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Create Static Standby
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.72

Field Name : syncRxSfw
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync SFW
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.71

Field Name : syncRxInsertTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Insert Tuple
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.70

Field Name : syncRxNatAllocSby
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync NAT Alloc Standby
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.69

Field Name : syncRxNatCreateSby
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync NAT Create Standby
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.68

Field Name : syncRxLsnCreateSby
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync LSN Create Standby
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.67

Field Name : syncGetBuffFailedPort
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Get Buff Failure Wrong Port
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.66

Field Name : syncGetBuffFailedRt

Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Get Buff Failure No Route
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.65

Field Name : syncQueryDcmsgCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync query forward CPU
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.64

Field Name : syncRxApptypeNotSupported
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync App Type Invalid
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.63

Field Name : syncRxUnkCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Unknown Type
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.62

Field Name : syncRxUpdateSeqnosCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Update Seq Num Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.61

Field Name : syncRxTotalInfoCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Total Info Pkts Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.60

Field Name : syncRxDcmsgCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync forward CPU
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.59

Field Name : syncRxZeroInfoCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Packet Empty
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.58

Field Name : syncRxTypeInvalid
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Type Invalid
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.57

Field Name : syncRxDelNoSuchSession
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Del Conn not Found
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.56

Field Name : syncRxNoSuchSgNode
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync no SG node found
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.55

Field Name : syncRxNoSuchNatPool
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync NAT Pool Error
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.54

Field Name : syncRxNoDstForVportInline
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync 'dst' not found for vport inline
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.53

Field Name : syncRxProtoNotSupported
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Protocol Invalid
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.52

Field Name : syncRxConnGetFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Get Conn Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.51

Field Name : syncRxConnExists
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Create Conn Exists
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.50

Field Name : syncRxCreateExtBitCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Create with Ext Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.49

Field Name : syncRxExtBitProcessError
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Proc Ext Bit Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.48

Field Name : syncRxCannotProcessMandatory
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Process Mandatory Invalid
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.47

Field Name : syncRxNoSuchRport
Field Type : CounterBasedGauge64
Field Status : current

Description : Conn Sync Real Port Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.46

Field Name : syncRxNoSuchVport
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Virt Port Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.45

Field Name : syncPersistRxConnGetFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Persist Conn Sync Get Conn Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.44

Field Name : syncPersistRxNoSgGroupInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : Persist Conn Sync No Service Group Info Found
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.43

Field Name : syncPersistRxNoSuchSgGroup
Field Type : CounterBasedGauge64
Field Status : current
Description : Persist Conn Sync No Service Group Found
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.42

Field Name : syncPersistRxNoSuchRport
Field Type : CounterBasedGauge64
Field Status : current
Description : Persist Conn Sync Real Port Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.41

Field Name : syncPersistRxVporttypeNotSupported
Field Type : CounterBasedGauge64
Field Status : current
Description : Persist Conn Sync Virt Port Type Invalid
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.40

Field Name : syncPersistRxNoSuchVport
Field Type : CounterBasedGauge64
Field Status : current
Description : Persist Conn Sync Virt Port Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.39

Field Name : syncPersistRxExtBitProcessError
Field Type : CounterBasedGauge64
Field Status : current
Description : Persist Conn Sync Proc Ext Bit Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.38

Field Name : syncPersistRxCannotProcessMandatory
Field Type : CounterBasedGauge64
Field Status : current
Description : Persist Conn Sync Process Mandatory Invalid
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.37

Field Name : syncPersistRxTypeInvalid

Field Type : CounterBasedGauge64
Field Status : current
Description : Persist Conn Sync Type Invalid
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.36

Field Name : syncPersistRxProtoNotSupported
Field Type : CounterBasedGauge64
Field Status : current
Description : Persist Conn Sync Protocol Invalid
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.35

Field Name : syncPersistRxLenInvalid
Field Type : CounterBasedGauge64
Field Status : current
Description : Persist Conn Sync Length Invalid
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.34

Field Name : syncRxLenInvalid
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Length Invalid
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.33

Field Name : syncTxMaxPacked
Field Type : CounterBasedGauge64
Field Status : current
Description : Min Sync Msg Per Packet
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.32

Field Name : syncTxMinPacked
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Sync Msg Per Packet
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.31

Field Name : syncTxUpdateSeqnosCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Update Seq Num Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.30

Field Name : syncTxCreateExtBitCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Create with Ext Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.29

Field Name : syncTxTotalInfoCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Total Info Pkts Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.28

Field Name : syncTxGetBuffFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Get Buff Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.27

Field Name : syncPktInvalidIdxCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Invalid Interface
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.26

Field Name : queryRxUnkCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Query Unknown Type
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.25

Field Name : queryRxFullInfoCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Query Packet Full
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.24

Field Name : queryRxZeroInfoCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Query Packet Empty
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.23

Field Name : queryTxGetBuffFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Query Get Buff Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.22

Field Name : queryPktInvalidIdxCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Query Invalid Interface
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.21

Field Name : queryTxMinPacked
Field Type : CounterBasedGauge64
Field Status : current
Description : Min Query Msg Per Packet
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.20

Field Name : queryTxMaxPacked
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Query Msg Per Packet
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.19

Field Name : syncRxSmpRadiusTableCounter
Field Type : TABLE
Field Status : current
Description : Conn Sync Update LSN RADIUS Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.18

Field Name : syncTxSmpRadiusTableCounter
Field Type : TABLE
Field Status : current

Description : Conn Sync Update LSN RADIUS Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.17

Field Name : queryPktRcvCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Query Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.16

Field Name : queryPktTxCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Query sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.15

Field Name : syncTxPersistUpdateAgeCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Update Persist Age Pkts Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.14

Field Name : syncTxPersistDelCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Delete Persist Session Pkts Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.13

Field Name : syncTxPersistCreateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Create Persist Session Pkts Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.12

Field Name : syncRxPersistUpdateAgeCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Update Persist Age Pkts Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.11

Field Name : syncRxPersistDelCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Delete Persist Session Pkts Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.10

Field Name : syncRxPersistCreateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Create Persist Session Pkts Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.9

Field Name : syncTxUpdateAgeCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Update Age Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.8

Field Name : syncTxDelCounter

Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Del Session Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.7

Field Name : syncTxCreateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Create Session Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.6

Field Name : syncRxUpdateAgeCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Update Age Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.5

Field Name : syncRxDelCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Del Session Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.4

Field Name : syncRxCreateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Create Session Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.3

Field Name : syncPktRcvCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.2

Field Name : syncPktTxCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.1

Field Name : vrrpAVridSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.13.11.1.1

Field Name : vrrpAVridSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.13.11.1.1.1

Field Name : associatedNatpoolCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of nat pools associated to vrid
OID : 1.3.6.1.4.1.22610.2.4.10.13.11.1.1.1.4

Field Name : associatedVportCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of vports associated to vrid
OID : 1.3.6.1.4.1.22610.2.4.10.13.11.1.1.1.3

Field Name : associatedVipCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of vips associated to vrid
OID : 1.3.6.1.4.1.22610.2.4.10.13.11.1.1.1.2

Field Name : vridVal
Field Type : INTEGER
Field Status : current
Description : Specify ha VRRP-A vrid
OID : 1.3.6.1.4.1.22610.2.4.10.13.11.1.1.1.1

Field Name : templateGtpPolicySTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1

Field Name : templateGtpPolicySEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1

Field Name : rlMessageMonitor
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Message forwarded via monitor mode at rate-limit policy
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.124

Field Name : dropRlGtpUMaxConcurrentTunnels
Field Type : CounterBasedGauge64
Field Status : current
Description : Rate-limit Drop: GTP-U Concurrent Tunnels
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.95

Field Name : dropRlGtpUTotalPacket
Field Type : CounterBasedGauge64
Field Status : current
Description : Rate-limit Drop: GTP-U Total packet rate
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.94

Field Name : dropRlGtpUTotalByte
Field Type : CounterBasedGauge64
Field Status : current
Description : Rate-limit Drop: GTP-U Total byte rate
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.93

Field Name : dropRlGtpUDownlinkPacket
Field Type : CounterBasedGauge64
Field Status : current

Description : Rate-limit Drop: GTP-U Downlink packet rate
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.92

Field Name : dropRlGtpUDownlinkByte
Field Type : CounterBasedGauge64
Field Status : current
Description : Rate-limit Drop: GTP-U Downlink byte rate
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.91

Field Name : dropRlGtpUUplinkPacket
Field Type : CounterBasedGauge64
Field Status : current
Description : Rate-limit Drop: GTP-U Uplink packet rate
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.90

Field Name : dropRlGtpUUplinkByte
Field Type : CounterBasedGauge64
Field Status : current
Description : Rate-limit Drop: GTP-U Uplink byte rate
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.89

Field Name : dropRlGtpUTunnelCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : Rate-limit Drop: GTP-U Tunnel Creation rate
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.88

Field Name : dropRlGtpV2CModifyBearerRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Rate-limit Drop: GTPv2-C Modify Bearer Request rate
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.87

Field Name : dropRlGtpV1CUpdatePdpRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Rate-limit Drop: GTPv1-C Update PDP Request rate
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.86

Field Name : dropRlGtpV2CCreateSessionRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Rate-limit Drop: GTPv2-C Create Session Request rate
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.85

Field Name : dropRlGtpV1CCreatePdpRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Rate-limit Drop: GTPv1-C Create PDP Request rate
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.84

Field Name : dropRlGtpV2CAgg
Field Type : CounterBasedGauge64
Field Status : current
Description : Rate-limit Drop: Maximum GTPv2-C Message rate
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.83

Field Name : dropRlGtpV1CAgg

Field Type : CounterBasedGauge64
Field Status : current
Description : Rate-limit Drop: Maximum GTPv1-C Message rate
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.82

Field Name : dropRlGtpV0CAgg
Field Type : CounterBasedGauge64
Field Status : current
Description : Rate-limit Drop: Maximum GTPv0-C Message rate
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.81

Field Name : gtpInGtpFltMessageMonitor
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Message forwarded via monitor mode at GTP-IN_GTP filtering policy
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.123

Field Name : msisdnFltMessageMonitor
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Message forwarded via monitor mode at Msisdn filtering policy
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.122

Field Name : apnImsiFltMessageMonitor
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Message forwarded via monitor mode at APN-IMSI filtering policy
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.121

Field Name : ratFltMessageMonitor
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Message forwarded via monitor mode at rat filtering policy
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.120

Field Name : fltMessageMonitor
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Message forwarded via monitor mode at message filtering policy
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.119

Field Name : dropFltGtpInGtp
Field Type : CounterBasedGauge64
Field Status : current
Description : Filtering Drop: GTP in GTP Tunnel Present
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.80

Field Name : dropFltRatTypeFiltering
Field Type : CounterBasedGauge64
Field Status : current
Description : Filtering Drop: RAT Type Filtering
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.79

Field Name : dropFltMsisdnFiltering
Field Type : CounterBasedGauge64
Field Status : current
Description : Filtering Drop: MSISDN Filtering
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.78

Field Name : dropFltApnFiltering
Field Type : CounterBasedGauge64
Field Status : current
Description : Filtering Drop: APN IMSI Filtering
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.77

Field Name : dropFltMessageFiltering
Field Type : CounterBasedGauge64
Field Status : current
Description : Filtering Drop: Message Type Not Permitted on Interface
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.76

Field Name : dropVldGtpV2CMessageSkippedApnFilteringNoApn
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTPv2-C APN/IMSI Filtering Dropped (No APN)
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.107

Field Name : dropVldGtpV1CMessageSkippedApnFilteringNoApn
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTPv1-C APN/IMSI Filtering Dropped (No APN)
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.106

Field Name : dropVldGtpV0CMessageSkippedApnFilteringNoApn
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTPv0-C APN/IMSI Filtering Dropped (No APN)
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.105

Field Name : genMessageLengthMonitor
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Message forwarded via monitor mode at validation policy
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.118

Field Name : vldMessageMonitor
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Message forwarded via monitor mode at validation policy
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.117

Field Name : dropVldGtpV2CMessageLengthMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Message Length Mismatch Across Layers
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.101

Field Name : dropVldGtpV1CMessageLengthMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Message Length Mismatch Across Layers
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.100

Field Name : dropVldGtpV0CMessageLengthMismatch
Field Type : CounterBasedGauge64
Field Status : current

Description : GTPv0-C Message Length Mismatch Across Layers
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.99

Field Name : dropVldGtpV2CIeLenExceedMsgLen
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C IE Length Exceeds Message Length
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.98

Field Name : dropVldGtpV1CIeLenExceedMsgLen
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C IE Length Exceeds Message Length
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.97

Field Name : dropVldGtpV0CIeLenExceedMsgLen
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C IE Length Exceeds Message Length
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.96

Field Name : dropVldGtpv2SubscriberAttrMiss
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTPV2-c Subscriber Attributes Missing
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.104

Field Name : dropVldGtpv1SubscriberAttrMiss
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTPV1-c Subscriber Attributes Missing
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.103

Field Name : dropVldGtpv0SubscriberAttrMiss
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTPV0-c Subscriber Attributes Missing
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.102

Field Name : dropVldProtocolFlagUnset
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: Protocol flag in Header Field not Set
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.75

Field Name : dropVldGtpInvalidApnLenDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTP-C Invalid APN Length Drop
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.74

Field Name : dropVldGtpInvalidImsiLenDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTP-C Invalid IMSI Length Drop
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.73

Field Name : dropVldGtpv2SeqnumBufferFull

Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTPV2-C conn Sequence number Buffer Full
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.72

Field Name : dropVldGtpv1SeqnumBufferFull
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTPV1-C conn Sequence number Buffer Full
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.71

Field Name : dropVldGtpv0SeqnumBufferFull
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTPV0-C conn Sequence number Buffer Full
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.70

Field Name : dropVldSequenceNumCorrelation
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTP-C Sequence number Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.69

Field Name : dropVldSanityFailedPiggyback
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: piggyback message anomaly failed
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.68

Field Name : dropVldInvalidPktLenPiggyback
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: Piggyback message invalid packet length
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.67

Field Name : dropVldV2ReservedMessageDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTPv2-C Reserved Message Drop
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.66

Field Name : dropVldV1ReservedMessageDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTPv1-C Reserved Message Drop
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.65

Field Name : dropVldV0ReservedMessageDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTPv0-C Reserved Message Drop
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.64

Field Name : gtpCHandoverInProgressWithConn
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C matching a conn with Handover In Progress
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.62

Field Name : dropVldGtpV2WrongLbiCreateBearerReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTPV2-C Wrong LBI in Create Bearer Request
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.61

Field Name : dropVldGtpBearerCountExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTP Bearer count exceeded max (11)
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.60

Field Name : dropVldGtpUSpoofedSourceAddress
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTP-U IP Address Spoofed
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.59

Field Name : dropVldCountryCodeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: Country Code Mismatch in IMSI and MSISDN
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.58

Field Name : dropVldCrossLayerCorrelation
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: Cross Layer IP Address Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.57

Field Name : dropVldMessageLength
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: Message Length Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.56

Field Name : dropVldVersionNotSupported
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: Invalid GTP version
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.55

Field Name : dropVldReservedInformationElement
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: Reserved IE Field Present
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.54

Field Name : dropVldOutOfStateIe
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: Unexpected IE Present in Message
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.53

Field Name : dropVldOutOfOrderIe
Field Type : CounterBasedGauge64
Field Status : current

Description : Validation Drop: GTPv1-C Message Out of Order IE
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.52

Field Name : dropVldMandatoryIeInGroupedIe
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: Mandatory IE in Grouped IE Not Present
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.51

Field Name : dropVldMandatoryInformationElement
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: Mandatory IE Not Present
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.50

Field Name : dropVldOutOfState
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: Out Of State GTP Message
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.49

Field Name : dropVldInvalidTeid
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: Invalid TEID Value
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.48

Field Name : dropVldInvalidFlowLabelV0
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: Invalid Flow Label in GTPv0-C Header
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.47

Field Name : dropVldTunnelIdFlag
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: Tunnel Header Flag Not Set
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.46

Field Name : dropVldReservedFieldSet
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: Reserved Header Field Set
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.45

Field Name : dropVldGtpIeRepeatCountExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTP repeated IE count exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.44

Field Name : dropVldSanityGtpV0CMessageWithTeidZeroExpected
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTPv0-C PDU Notification Request with TEID
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.43

Field Name : dropVldSanityGtpV1CMessageWithTeidZeroExpected

Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTPv1-C PDU Notification Request with TEID
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.42

Field Name : dropVldSanityGtpV2CMessageWithTeidZeroExpected
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTPv2-C Create Session Request with TEID
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.41

Field Name : gtpV2CPacketDummyMsisdn
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Packet With Dummy MSISDN Forwarded
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.116

Field Name : gtpV1CPacketDummyMsisdn
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Packet With Dummy MSISDN Forwarded
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.115

Field Name : gtpV0CPacketDummyMsisdn
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Packet With Dummy MSISDN Forwarded
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.114

Field Name : gtpV2CMessageSkippedMsisdnFilteringNoImsi
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C MSISDN Filtering Skipped (No MSISDN)
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.113

Field Name : gtpV1CMessageSkippedMsisdnFilteringNoImsi
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C MSISDN Filtering Skipped (No MSISDN)
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.112

Field Name : gtpV0CMessageSkippedMsisdnFilteringNoImsi
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C MSISDN Filtering Skipped (No MSISDN)
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.111

Field Name : gtpV2CMessageSkippedApnFilteringNoImsi
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C APN/IMSI Filtering Skipped (No IMSI)
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.110

Field Name : gtpV1CMessageSkippedApnFilteringNoImsi
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C APN/IMSI Filtering Skipped (No IMSI)
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.109

Field Name : gtpV0CMessageSkippedApnFilteringNoImsi
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C APN/IMSI Filtering Skipped (No IMSI)
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.108

Field Name : gtpV0CPduNotificationRejectRequestForward
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C PDU Notification Reject Request Forward
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.40

Field Name : gtpV0CPduNotificationRequestForward
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C PDU Notification Request Forward
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.39

Field Name : gtpV1CPduNotificationRejectRequestForward
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C PDU Notification Reject Request Forward
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.38

Field Name : gtpV1CPduNotificationRequestForward
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C PDU Notification Request Forward
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.37

Field Name : gtpV2CLoadContrInfoExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Load Control Info IEs in message exceeded 2
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.36

Field Name : gtpV2CReservedMessageAllow
Field Type : CounterBasedGauge64
Field Status : current
Description : Permit GTPv2-C Reserved Messages
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.35

Field Name : gtpV1CReservedMessageAllow
Field Type : CounterBasedGauge64
Field Status : current
Description : Permit GTPv1-C Reserved Messages
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.34

Field Name : gtpV0CReservedMessageAllow
Field Type : CounterBasedGauge64
Field Status : current
Description : Permit GTPv0-C Reserved Messages
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.33

Field Name : gtpV2CTunnelDeletedRestart
Field Type : CounterBasedGauge64
Field Status : current

Description : GTPv2-C Tunnel Deleted with Restart/failure
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.32

Field Name : gtpV1CTunnelDeletedRestart
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Tunnel Deleted with Restart/failure
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.31

Field Name : gtpV0CTunnelDeletedRestart
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Tunnel Deleted with Restart/failure
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.30

Field Name : gtpPathManagementMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Path Management Messages Received
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.29

Field Name : gtpV2CPiggybackMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Piggyback Message
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.28

Field Name : gtpV2CCreateSessRespUnsuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Create Session Response Unsuccessful
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.27

Field Name : gtpV1CCreatePdpRespUnsuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Create PDP Context Response Unsuccessful
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.26

Field Name : gtpV0CCreatePdpRespUnsuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Create PDP Context Response Unsuccessful
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.25

Field Name : gtpV2CModBearerRespUnsuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Modify Bearer Response Unsuccessful
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.24

Field Name : gtpV1CUpdatePdpRespUnsuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Update PDP Context Response Unsuccessful
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.23

Field Name : gtpV0CUpdatePdpRespUnsuccess

Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Update PDP Context Response Unsuccessful
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.22

Field Name : gtpUTunnelDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Tunnel Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.21

Field Name : gtpUTunnelCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Tunnel Created
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.20

Field Name : gtpV2CHalfOpenTunnelClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Half open tunnel closed
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.19

Field Name : gtpV2CTunnelDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Tunnel Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.18

Field Name : gtpV2CTunnelClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Tunnel Marked Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.17

Field Name : gtpV2CTunnelHalfClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Tunnel Delete Request
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.16

Field Name : gtpV2CTunnelHalfOpen
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Half open tunnel created
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.15

Field Name : gtpV2CTunnelCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Tunnel Created
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.14

Field Name : gtpV1CHalfOpenTunnelClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Half open tunnel closed
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.13

Field Name : gtpV1CTunnelDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Tunnel Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.12

Field Name : gtpV1CTunnelClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Tunnel Marked Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.11

Field Name : gtpV1CTunnelHalfClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Tunnel Delete Request
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.10

Field Name : gtpV1CTunnelHalfOpen
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Half open tunnel created
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.9

Field Name : gtpV1CTunnelCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Tunnel Created
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.8

Field Name : gtpV0CHalfOpenTunnelClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Half open tunnel closed
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.7

Field Name : gtpV0CTunnelDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Tunnel Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.6

Field Name : gtpV0CTunnelClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Tunnel Marked Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.5

Field Name : gtpV0CTunnelHalfClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Tunnel Delete Request
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.4

Field Name : gtpV0CTunnelHalfOpen
Field Type : CounterBasedGauge64
Field Status : current

Description : GTPv0-C Half open tunnel created
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.3

Field Name : gtpV0CTunnelCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Tunnel Created
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Configure the GTP Policy Name
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.1

Field Name : usagePercentage
Field Type : CounterBasedGauge64
Field Status : current
Description : Usage percentage
OID : 1.3.6.1.4.1.22610.2.4.10.38.1.1.1

Field Name : proxyheaderv2
Field Type : CounterBasedGauge64
Field Status : current
Description : Proxy header v2
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.97

Field Name : proxyheaderv1
Field Type : CounterBasedGauge64
Field Status : current
Description : Proxy header v1
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.96

Field Name : a2bsndwnd
Field Type : CounterBasedGauge64
Field Status : current
Description : ATCP to BTCP send window
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.95

Field Name : mburstlim
Field Type : CounterBasedGauge64
Field Status : current
Description : Maxburst limited tx
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.94

Field Name : earlyrexmit
Field Type : CounterBasedGauge64
Field Status : current
Description : Early Retransmission sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.93

Field Name : atcpsendfail
Field Type : CounterBasedGauge64
Field Status : current
Description : Adaptive TCP sent fails
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.91

Field Name : a2bappbuffering

Field Type : CounterBasedGauge64
Field Status : current
Description : Transition to full stack on when application buffers too much data
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.90

Field Name : atcpbuffallocfail
Field Type : CounterBasedGauge64
Field Status : current
Description : Adaptive TCP buffer allocation fails
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.89

Field Name : atcprexmit
Field Type : CounterBasedGauge64
Field Status : current
Description : Adaptive TCP retransmits
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.88

Field Name : atcpsendbackack
Field Type : CounterBasedGauge64
Field Status : current
Description : Adaptive TCP sendback ACK
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.87

Field Name : atcprexmitsadrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Adaptive TCP transmit SA drops
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.86

Field Name : atcpsent
Field Type : CounterBasedGauge64
Field Status : current
Description : Adaptive TCP sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.85

Field Name : atcpforward
Field Type : CounterBasedGauge64
Field Status : current
Description : Adaptive TCP forward
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.84

Field Name : badIochan
Field Type : CounterBasedGauge64
Field Status : current
Description : IO Channel Modified
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.83

Field Name : b2atransitionnum
Field Type : CounterBasedGauge64
Field Status : current
Description : ATCP to BTCP total transitions
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.82

Field Name : a2btransitionnum
Field Type : CounterBasedGauge64
Field Status : current
Description : ATCP to BTCP total transitions
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.81

Field Name : a2bfsmtransition
Field Type : CounterBasedGauge64
Field Status : current
Description : ATCP to BTCP state machine transition
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.76

Field Name : a2bpartialack
Field Type : CounterBasedGauge64
Field Status : current
Description : ATCP to BTCP partial ack received
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.75

Field Name : a2boodata
Field Type : CounterBasedGauge64
Field Status : current
Description : ATCP to BTCP oo data received
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.74

Field Name : a2btcpoptions
Field Type : CounterBasedGauge64
Field Status : current
Description : ATCP to BTCP unsupported TCP options
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.73

Field Name : a2brxdata
Field Type : CounterBasedGauge64
Field Status : current
Description : ATCP to BTCP Rxmitted data
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.72

Field Name : a2bdupack
Field Type : CounterBasedGauge64
Field Status : current
Description : ATCP to BTCP Dup/OO ACK
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.71

Field Name : a2bsackpresent
Field Type : CounterBasedGauge64
Field Status : current
Description : ATCP to BTCP SACK options present
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.70

Field Name : a2brcvwnd
Field Type : CounterBasedGauge64
Field Status : current
Description : ATCP to BTCP receive window
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.69

Field Name : rcvdsack
Field Type : CounterBasedGauge64
Field Status : current
Description : Rcvd DSACK packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.68

Field Name : ccReduce
Field Type : CounterBasedGauge64
Field Status : current

Description : Congestion control window reduced by event
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.67

Field Name : ccIdle
Field Type : CounterBasedGauge64
Field Status : current
Description : Congestion control window set do to idle
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.66

Field Name : reasstimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : Reassembly Time Out
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.92

Field Name : reassmemdrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet dropped during reassembly
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.65

Field Name : cacklim
Field Type : CounterBasedGauge64
Field Status : current
Description : Challenge ACK limited
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.64

Field Name : sndcack
Field Type : CounterBasedGauge64
Field Status : current
Description : Challenge ACK sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.63

Field Name : sackSendBlocks
Field Type : CounterBasedGauge64
Field Status : current
Description : SACK sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.60

Field Name : sackRcvBlocks
Field Type : CounterBasedGauge64
Field Status : current
Description : SACK received
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.59

Field Name : sackRexmitBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : SACK rexmit bytes
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.58

Field Name : sackRexmits
Field Type : CounterBasedGauge64
Field Status : current
Description : SACK rexmit segments
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.57

Field Name : sackRecoveryEpisode

Field Type : CounterBasedGauge64
Field Status : current
Description : SACK recovery episodes
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.56

Field Name : finwait2Drops
Field Type : CounterBasedGauge64
Field Status : current
Description : Drop FIN_WAIT_2 connection after time limit
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.55

Field Name : badrst
Field Type : CounterBasedGauge64
Field Status : current
Description : Ignored RST
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.54

Field Name : persistdrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Timeout in persist state
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.52

Field Name : preddat
Field Type : CounterBasedGauge64
Field Status : current
Description : Hdr predict for data pkts
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.51

Field Name : predack
Field Type : CounterBasedGauge64
Field Status : current
Description : Hdr predict for acks
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.50

Field Name : pawsdrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Segments dropped due to PAWS
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.49

Field Name : rcvwinupd
Field Type : CounterBasedGauge64
Field Status : current
Description : Rcvd window update packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.48

Field Name : rcvackbyte
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes acked by rcvd acks
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.47

Field Name : rcvackpack
Field Type : CounterBasedGauge64
Field Status : current
Description : Rcvd ack packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.46

Field Name : rcvacktoomuch
Field Type : CounterBasedGauge64
Field Status : current
Description : Rcvd acks for unsent data
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.45

Field Name : rcvdupack
Field Type : CounterBasedGauge64
Field Status : current
Description : Rcvd duplicate acks
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.44

Field Name : rcvwinprobe
Field Type : CounterBasedGauge64
Field Status : current
Description : Rcvd window probe packet
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.43

Field Name : rcvbyteafterwin
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes rcvd after window
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.42

Field Name : rcvpackafterwin
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets with data after window
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.41

Field Name : rcvoobyte
Field Type : CounterBasedGauge64
Field Status : current
Description : Out-of-order bytes received
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.40

Field Name : rcvoopack
Field Type : CounterBasedGauge64
Field Status : current
Description : Out-of-order packet received
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.39

Field Name : rcvpartdupbyte
Field Type : CounterBasedGauge64
Field Status : current
Description : Dup. bytes in part-dup. packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.38

Field Name : rcvpartduppack
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet with some duplicate data
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.37

Field Name : rcvdupbyte
Field Type : CounterBasedGauge64
Field Status : current

Description : Duplicate bytes received
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.36

Field Name : rcvduppack
Field Type : CounterBasedGauge64
Field Status : current
Description : Duplicate packet received
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.35

Field Name : rcvmemdrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet dropped for lack of memory
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.33

Field Name : rcvbadoff
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet received with bad offset
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.32

Field Name : rcvbyte
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes received
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.31

Field Name : rcvpack
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet received
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.30

Field Name : rcvtotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total packet received
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.29

Field Name : sndsyn
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN packet sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.28

Field Name : sndfin
Field Type : CounterBasedGauge64
Field Status : current
Description : FIN packet sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.27

Field Name : sndrst
Field Type : CounterBasedGauge64
Field Status : current
Description : RST packet sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.26

Field Name : sndctrl

Field Type : CounterBasedGauge64
Field Status : current
Description : SYN|FIN|RST packet sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.25

Field Name : sndwinup
Field Type : CounterBasedGauge64
Field Status : current
Description : Window update packet sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.24

Field Name : sndurg
Field Type : CounterBasedGauge64
Field Status : current
Description : URG packet sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.23

Field Name : sndprobe
Field Type : CounterBasedGauge64
Field Status : current
Description : Window probe sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.22

Field Name : sndacks
Field Type : CounterBasedGauge64
Field Status : current
Description : Ack packet sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.21

Field Name : sndrexmitbad
Field Type : CounterBasedGauge64
Field Status : current
Description : Unnecessary packet retransmit
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.20

Field Name : sndrexmitbyte
Field Type : CounterBasedGauge64
Field Status : current
Description : Data byte retransmit
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.19

Field Name : sndrexmitpack
Field Type : CounterBasedGauge64
Field Status : current
Description : Data packet retransmit
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.18

Field Name : sndbyte
Field Type : CounterBasedGauge64
Field Status : current
Description : Data bytes sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.17

Field Name : sndpack
Field Type : CounterBasedGauge64
Field Status : current
Description : Data packet sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.16

Field Name : sndtotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total packet sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.15

Field Name : keepdrops
Field Type : CounterBasedGauge64
Field Status : current
Description : Connect dropped in keepalive
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.14

Field Name : keepprobe
Field Type : CounterBasedGauge64
Field Status : current
Description : Keepalive probe sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.13

Field Name : keeptimeo
Field Type : CounterBasedGauge64
Field Status : current
Description : Keepalive timeout
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.12

Field Name : persisttimeo
Field Type : CounterBasedGauge64
Field Status : current
Description : Persist timeout
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.11

Field Name : rexmttimeo
Field Type : CounterBasedGauge64
Field Status : current
Description : Retransmit timeout
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.10

Field Name : timeoutdrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn dropped in rxmt timeout
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.9

Field Name : delack
Field Type : CounterBasedGauge64
Field Status : current
Description : Delayed acks sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.8

Field Name : rttupdated
Field Type : CounterBasedGauge64
Field Status : current
Description : Update RTT
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.7

Field Name : segstimed
Field Type : CounterBasedGauge64
Field Status : current

Description : Segs to get RTT
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.6

Field Name : closed
Field Type : CounterBasedGauge64
Field Status : current
Description : Connect closed
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.5

Field Name : conndrops
Field Type : CounterBasedGauge64
Field Status : current
Description : Embryonic connect dropped
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.4

Field Name : drops
Field Type : CounterBasedGauge64
Field Status : current
Description : Connect dropped
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.3

Field Name : connects
Field Type : CounterBasedGauge64
Field Status : current
Description : Connect established
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.2

Field Name : connattempt
Field Type : CounterBasedGauge64
Field Status : current
Description : Connect initiated
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.1

Field Name : noFreeBuffers
Field Type : CounterBasedGauge64
Field Status : current
Description : No Free Buffers to send R.A.
OID : 1.3.6.1.4.1.22610.2.4.10.39.56.1.10

Field Name : l2AddrAndUnspec
Field Type : CounterBasedGauge64
Field Status : current
Description : R.S. Src Link-Layer Option and Unspecified Address
OID : 1.3.6.1.4.1.22610.2.4.10.39.56.1.9

Field Name : badIcmpv6Option
Field Type : CounterBasedGauge64
Field Status : current
Description : R.S. Bad ICMPv6 Option
OID : 1.3.6.1.4.1.22610.2.4.10.39.56.1.8

Field Name : badIcmpv6Code
Field Type : CounterBasedGauge64
Field Status : current
Description : R.S. Unknown ICMPv6 Code
OID : 1.3.6.1.4.1.22610.2.4.10.39.56.1.7

Field Name : badIcmpv6Csum

Field Type : CounterBasedGauge64
Field Status : current
Description : R.S. Bad ICMPv6 Checksum
OID : 1.3.6.1.4.1.22610.2.4.10.39.56.1.6

Field Name : truncated
Field Type : CounterBasedGauge64
Field Status : current
Description : R.S. Truncated
OID : 1.3.6.1.4.1.22610.2.4.10.39.56.1.5

Field Name : badHopLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : R.S. Bad Hop Limit
OID : 1.3.6.1.4.1.22610.2.4.10.39.56.1.4

Field Name : rateLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : R.S. Rate Limited
OID : 1.3.6.1.4.1.22610.2.4.10.39.56.1.3

Field Name : periodicSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Periodic Router Advertisements (R.A.) Sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.56.1.2

Field Name : goodRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : Good Router Solicitations (R.S.) Received
OID : 1.3.6.1.4.1.22610.2.4.10.39.56.1.1

Field Name : totalSystemSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Total system-wide sessions
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.110

Field Name : freeConnNotInSp
Field Type : CounterBasedGauge64
Field Status : current
Description : Attempt to Free a Conn Whoes Address Not in Session Pool
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.109

Field Name : schedConnWithWrongNextIdxToRml
Field Type : CounterBasedGauge64
Field Status : current
Description : Attempt to Put a Conn to RML Whose next_idx is NOT Invalid
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.108

Field Name : serverTcpHalfOpenCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Server TCP Half Open
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.107

Field Name : serverTcpEstCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Server TCP Established
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.106

Field Name : fwBlacklistSessFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Blacklist Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.105

Field Name : fwBlacklistSessCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Blacklist Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.104

Field Name : fwBlacklistSess
Field Type : CounterBasedGauge64
Field Status : current
Description : Blacklist Sessions
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.103

Field Name : gtpCumConnFreedCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP cumulative Conn Freed
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.102

Field Name : gtpCumConnCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP cumulative Conn Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.101

Field Name : gtpCurrFreeConn
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Current Available Conn
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.100

Field Name : gtpUEchoCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Echo Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.99

Field Name : gtpCEchoCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Echo Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.98

Field Name : gtpUCounter
Field Type : CounterBasedGauge64
Field Status : current

Description : GTP-U Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.97

Field Name : gtpCHalfOpenCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Half Open
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.96

Field Name : gtpCEstCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Established
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.95

Field Name : totalLoggingConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Logging Conn
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.94

Field Name : sslForwardProxyEsniResetTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy ESNI Drop Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.93

Field Name : sslForwardProxyEsniBypassTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy ESNI Bypass Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.92

Field Name : totalServersideFailedEarlyDataConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : Total serverside failed early data connections
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.91

Field Name : totalClientsideFailedEarlyDataConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : Total clientside failed early data connections
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.90

Field Name : totalServersideEarlyDataConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : Total serverside early data connections
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.89

Field Name : totalClientsideEarlyDataConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : Total clientside early data connections
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.88

Field Name : serverSslSessionTicketReuseTotal

Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Server Session Ticket Reuse
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.87

Field Name : clientSslSessionTicketReuseTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Client Session Ticket Reuse
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.86

Field Name : diameterConcurrentUserSessionsCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Diameter Concurrent User-Sessions
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.85

Field Name : sslForwardProxyAdGrpupBypassTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy AD-Group Bypass Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.84

Field Name : sslForwardProxyUsernameBypassTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy Username Bypass Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.83

Field Name : sslForwardProxyNoSniResetTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy No SNI reset Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.82

Field Name : sslForwardProxyNoSniBypassTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy No SNI Bypass Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.81

Field Name : sslForwardProxyCertSanBypassTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy Certificate SAN Bypass Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.80

Field Name : sslForwardProxyCertIssuerBypassTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy Certificate Issuer Bypass Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.79

Field Name : sslForwardProxyCertSubjectBypassTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy Certificate Subject Bypass Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.78

Field Name : sslForwardProxyFailedAflexTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy AFLEX Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.77

Field Name : totalDebugConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Debug Conn
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.76

Field Name : serverTemplateUnknownErr
Field Type : CounterBasedGauge64
Field Status : current
Description : server template unknown error
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.75

Field Name : serverTemplateIntErr
Field Type : CounterBasedGauge64
Field Status : current
Description : server template int error
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.74

Field Name : clientTemplateUnknownErr
Field Type : CounterBasedGauge64
Field Status : current
Description : client template unknown error
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.73

Field Name : clientTemplateIntErr
Field Type : CounterBasedGauge64
Field Status : current
Description : client template internal error
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.72

Field Name : serverSslFinRst
Field Type : CounterBasedGauge64
Field Status : current
Description : server ssl fin rst
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.71

Field Name : serverSslFatalAlert
Field Type : CounterBasedGauge64
Field Status : current
Description : server ssl fatal alert
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.70

Field Name : fpSessionFinRst
Field Type : CounterBasedGauge64
Field Status : current
Description : FP Session FIN/RST
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.69

Field Name : clientSslFinRst
Field Type : CounterBasedGauge64
Field Status : current

Description : client ssl fin rst
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.68

Field Name : clientSslFatalAlert
Field Type : CounterBasedGauge64
Field Status : current
Description : client ssl fatal alert
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.67

Field Name : totalCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Curr Conn
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.66

Field Name : totalLocalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Local Conn
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.65

Field Name : totalFwConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Firewall Conn
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.64

Field Name : debugUdpCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Hidden UDP sessions for CGNv6 Stateless Technologies
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.63

Field Name : debugTcpCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Hidden TCP sessions for CGNv6 Stateless Technologies
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.62

Field Name : diameterConnFreedCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Diameter Conn Freed
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.61

Field Name : diameterConnCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Diameter Conn Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.60

Field Name : connAppSmpAllocCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn APP SMP Alloc
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.59

Field Name : sslForwardProxyClientAuthBypassTotal

Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy Client Auth Bypass Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.58

Field Name : sslForwardProxySniBypassTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy SNI Bypass Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.57

Field Name : sslForwardProxyFailedSslVersionTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy Unsupported version Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.56

Field Name : sslForwardProxyFailedCertSigningTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy Failed Certificate Signing Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.55

Field Name : sslForwardProxyRevokedOcspTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy Revoked OCSP Response Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.54

Field Name : sslForwardProxyInvalidOcspStaplingTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy Invalid OCSP Stapling Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.53

Field Name : sslForwardProxyFailedCertVerifyTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy Failed Certificate Verification Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.52

Field Name : sslForwardProxyFailedCryptoTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy Failed Crypto Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.51

Field Name : sslForwardProxyFailedTcpTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy Failed TCP Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.50

Field Name : sslForwardProxyFailedHandshakeTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy Failed Handshake Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.49

Field Name : sslFailsafeTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Failsafe Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.48

Field Name : nonsslBypass
Field Type : CounterBasedGauge64
Field Status : current
Description : NON SSL Bypass Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.47

Field Name : sctpEstCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Established
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.46

Field Name : sctpHalfOpenCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Half Open
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.45

Field Name : connSmpType4Available
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn SMP Type 4 Available
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.44

Field Name : connSmpType3Available
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn SMP Type 3 Available
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.43

Field Name : connSmpType2Available
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn SMP Type 2 Available
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.42

Field Name : connSmpType1Available
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn SMP Type 1 Available
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.41

Field Name : connSmpType0Available
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn SMP Type 0 Available
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.40

Field Name : connType4Available
Field Type : CounterBasedGauge64
Field Status : current

Description : Conn Type 4 Available
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.39

Field Name : connType3Available
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Type 3 Available
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.38

Field Name : connType2Available
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Type 2 Available
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.37

Field Name : connType1Available
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Type 1 Available
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.36

Field Name : connType0Available
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Type 0 Available
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.35

Field Name : clientSslCtxMallocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Client SSL Ctx malloc Failures
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.34

Field Name : totalL2l3Conn
Field Type : CounterBasedGauge64
Field Status : current
Description : Totl L2/L3 Connections
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.33

Field Name : totalIpNatConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total IP Nat Conn
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.32

Field Name : sslClientCertAuthFail
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL Client Cert Auth Failures
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.31

Field Name : sslServerCertError
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL Server Cert Errors
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.30

Field Name : sslFailedCaVerification

Field Type : CounterBasedGauge64
Field Status : current
Description : SSL Cert Auth Verification Errors
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.29

Field Name : sslFailedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Failures
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.28

Field Name : serverSslReuseTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Server Reuse
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.27

Field Name : clientSslReuseTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Client Reuse
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.26

Field Name : serverSslCountTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Server Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.25

Field Name : serverSslCountCurr
Field Type : CounterBasedGauge64
Field Status : current
Description : Current SSL Server Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.24

Field Name : sslCountTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.23

Field Name : sslCountCurr
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr SSL Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.22

Field Name : connSmpAgedCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn SMP Aged
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.21

Field Name : connSmpFreeCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn SMP Free
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.20

Field Name : connSmpAllocCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn SMP Alloc
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.19

Field Name : tcpSynHalfOpenCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Half Open
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.18

Field Name : reverseNatUdpCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse NAT UDP
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.17

Field Name : reverseNatTcpCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse NAT TCP
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.16

Field Name : otherCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Non TCP/UDP IP sessions
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.15

Field Name : ipCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.14

Field Name : udpCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.13

Field Name : tcpHalfCloseCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Half Closed
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.12

Field Name : tcpHalfOpenCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Half Open
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.11

Field Name : tcpEstCounter
Field Type : CounterBasedGauge64
Field Status : current

Description : TCP Established
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.10

Field Name : currFreeConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr Free Conn
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.9

Field Name : systemSessionTotalTcpConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Conn
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.8

Field Name : systemSessionTotalL7Conn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total L7 Conn
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.7

Field Name : totalL4ConnProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Total L4 Conn Proxy Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.6

Field Name : totalL7PacketCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Total L7 Packet Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.5

Field Name : totalL4PacketCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Total L4 Packet Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.4

Field Name : connFreedCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Freed
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.3

Field Name : connCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.2

Field Name : systemSessionTotalL4Conn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total L4 Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.1

Field Name : hitRatePerSec

Field Type : CounterBasedGauge64
Field Status : current
Description : Cache hit rate per second
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.25

Field Name : qps
Field Type : CounterBasedGauge64
Field Status : current
Description : Cache Queries-per-second
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.24

Field Name : truncatedR
Field Type : CounterBasedGauge64
Field Status : current
Description : Response with Truncation bit set
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.23

Field Name : resolverQueueFull
Field Type : CounterBasedGauge64
Field Status : current
Description : Resolver task queue full
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.22

Field Name : currentDataAllocate
Field Type : CounterBasedGauge64
Field Status : current
Description : Current data allocate
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.21

Field Name : currentAllocate
Field Type : CounterBasedGauge64
Field Status : current
Description : Current allocate
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.20

Field Name : dnsTotalFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total freed
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.19

Field Name : totalAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Total allocated
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.18

Field Name : totalLog
Field Type : CounterBasedGauge64
Field Status : current
Description : Total stats log sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.17

Field Name : ageoutWeight
Field Type : CounterBasedGauge64
Field Status : current
Description : Total aged for lower weight
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.16

Field Name : badAnswer
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Answer
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.15

Field Name : ageout
Field Type : CounterBasedGauge64
Field Status : current
Description : Total aged out
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.14

Field Name : ttlR
Field Type : CounterBasedGauge64
Field Status : current
Description : Response with short TTL
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.13

Field Name : answerR
Field Type : CounterBasedGauge64
Field Status : current
Description : Response with multiple answers
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.12

Field Name : multipleR
Field Type : CounterBasedGauge64
Field Status : current
Description : Response with multiple questions
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.11

Field Name : encodeR
Field Type : CounterBasedGauge64
Field Status : current
Description : Response encoded
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.10

Field Name : oversizeR
Field Type : CounterBasedGauge64
Field Status : current
Description : Response exceed cache size
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.9

Field Name : badR
Field Type : CounterBasedGauge64
Field Status : current
Description : Response not passed
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.8

Field Name : oversizeQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Query exceed cache size
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.7

Field Name : multipleQ
Field Type : CounterBasedGauge64
Field Status : current

Description : Query with multiple questions
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.6

Field Name : encodeQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Query encoded
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.5

Field Name : badQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Query not passed
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.4

Field Name : hit
Field Type : CounterBasedGauge64
Field Status : current
Description : Total cache hit
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.3

Field Name : totalR
Field Type : CounterBasedGauge64
Field Status : current
Description : Total server response
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.2

Field Name : totalQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Total query
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.1

Field Name : slbDnsEdnsEcsInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of ecs inserted
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.36

Field Name : slbDnsEdnsEcsReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of ecs from client received
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.35

Field Name : invalidQLenToUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid query length to conver to UDP
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.34

Field Name : natSlbDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : (NAT)DNS requests drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.33

Field Name : slbDrop

Field Type : CounterBasedGauge64
Field Status : current
Description : DNS requests drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.32

Field Name : rpzActionLocalData
Field Type : CounterBasedGauge64
Field Status : current
Description : RPZ Action Local Data
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.31

Field Name : rpzActionNodata
Field Type : CounterBasedGauge64
Field Status : current
Description : RPZ Action NODATA
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.30

Field Name : rpzActionNxdomain
Field Type : CounterBasedGauge64
Field Status : current
Description : RPZ Action NXDOMAIN
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.29

Field Name : rpzActionTcpOnly
Field Type : CounterBasedGauge64
Field Status : current
Description : RPZ Action TCP Only
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.28

Field Name : rpzActionPassThru
Field Type : CounterBasedGauge64
Field Status : current
Description : RPZ Action Pass Through
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.27

Field Name : rpzActionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : RPZ Action Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.26

Field Name : slbDnsUdpRetransmitFail
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.25

Field Name : slbDnsUdpRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.24

Field Name : slbDnsEdnsSubnetToServerRemoved
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.23

Field Name : slbDnsPaddingToClientAdded
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.22

Field Name : slbDnsPaddingToServerRemoved
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.21

Field Name : slbDnsUdpConnSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : No. of backend udp conn established
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.20

Field Name : slbDnsUdpConn
Field Type : CounterBasedGauge64
Field Status : current
Description : No. of backend udp connections
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.19

Field Name : slbDnsServerSslSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : No. of server ssl success
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.18

Field Name : slbDnsClientSslSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : No. of client ssl success
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.17

Field Name : filterTypeAnyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Query ANY Type Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.16

Field Name : filterClassDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Query Class Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.15

Field Name : filterTypeDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Query Type Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.14

Field Name : natXidReused
Field Type : CounterBasedGauge64
Field Status : current

Description : (NAT) No. of requests reusing a transaction id
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.13

Field Name : natNoResource
Field Type : CounterBasedGauge64
Field Status : current
Description : (NAT) No. of resource failures
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.12

Field Name : natRespNoMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : (NAT) No. of requests with no response
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.11

Field Name : natReqRexmit
Field Type : CounterBasedGauge64
Field Status : current
Description : (NAT) No. of request retransmits
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.10

Field Name : natNoResp
Field Type : CounterBasedGauge64
Field Status : current
Description : (NAT) No. of resource failures
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.9

Field Name : natResp
Field Type : CounterBasedGauge64
Field Status : current
Description : (NAT) No. of responses
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.8

Field Name : natReq
Field Type : CounterBasedGauge64
Field Status : current
Description : (NAT) No. of requests
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.7

Field Name : slbNoResource
Field Type : CounterBasedGauge64
Field Status : current
Description : No. of resource failures
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.6

Field Name : slbRespNoMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : No. of requests and responses with no match
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.5

Field Name : slbReqRexmit
Field Type : CounterBasedGauge64
Field Status : current
Description : No. of requests retransmit
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.4

Field Name : slbNoResp

Field Type : CounterBasedGauge64
Field Status : current
Description : No. of requests with no response
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.3

Field Name : slbResp
Field Type : CounterBasedGauge64
Field Status : current
Description : No. of responses
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.2

Field Name : slbReq
Field Type : CounterBasedGauge64
Field Status : current
Description : No. of requests
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.1

Field Name : failComplete
Field Type : CounterBasedGauge64
Field Status : current
Description : Failed to Complete Job
OID : 1.3.6.1.4.1.22610.2.4.10.39.131.1.11

Field Name : failExecute
Field Type : CounterBasedGauge64
Field Status : current
Description : Failed to Execute Job
OID : 1.3.6.1.4.1.22610.2.4.10.39.131.1.10

Field Name : qNoSpace
Field Type : CounterBasedGauge64
Field Status : current
Description : No More Space in Q
OID : 1.3.6.1.4.1.22610.2.4.10.39.131.1.9

Field Name : failSubmit
Field Type : CounterBasedGauge64
Field Status : current
Description : Jobs Failed to Submit
OID : 1.3.6.1.4.1.22610.2.4.10.39.131.1.8

Field Name : complete
Field Type : CounterBasedGauge64
Field Status : current
Description : Jobs Completed
OID : 1.3.6.1.4.1.22610.2.4.10.39.131.1.7

Field Name : rcvHome
Field Type : CounterBasedGauge64
Field Status : current
Description : Jobs Received Home
OID : 1.3.6.1.4.1.22610.2.4.10.39.131.1.6

Field Name : sntHome
Field Type : CounterBasedGauge64
Field Status : current
Description : Jobs Sent Back Home
OID : 1.3.6.1.4.1.22610.2.4.10.39.131.1.5

Field Name : execute
Field Type : CounterBasedGauge64
Field Status : current
Description : Jobs Executed
OID : 1.3.6.1.4.1.22610.2.4.10.39.131.1.4

Field Name : receive
Field Type : CounterBasedGauge64
Field Status : current
Description : Jobs Received
OID : 1.3.6.1.4.1.22610.2.4.10.39.131.1.3

Field Name : submit
Field Type : CounterBasedGauge64
Field Status : current
Description : Jobs Submitted
OID : 1.3.6.1.4.1.22610.2.4.10.39.131.1.2

Field Name : jobs
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Jobs
OID : 1.3.6.1.4.1.22610.2.4.10.39.131.1.1

Field Name : v6CurrRate
Field Type : CounterBasedGauge64
Field Status : current
Description : Current rate (v6)
OID : 1.3.6.1.4.1.22610.2.4.10.39.54.1.12

Field Name : v6LockupTimeLeft
Field Type : CounterBasedGauge64
Field Status : current
Description : Lockup time left (v6)
OID : 1.3.6.1.4.1.22610.2.4.10.39.54.1.11

Field Name : v6LimitTotalDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total rate limit drops (v6)
OID : 1.3.6.1.4.1.22610.2.4.10.39.54.1.10

Field Name : v6LimitVserverDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Virtual Server rate limit drops (v6)
OID : 1.3.6.1.4.1.22610.2.4.10.39.54.1.9

Field Name : v6LimitIntfDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Interfaces rate limit drops (v6)
OID : 1.3.6.1.4.1.22610.2.4.10.39.54.1.8

Field Name : v6OverLimitDrop
Field Type : CounterBasedGauge64
Field Status : current

Description : Over limit drops (v6)
OID : 1.3.6.1.4.1.22610.2.4.10.39.54.1.7

Field Name : currRate
Field Type : CounterBasedGauge64
Field Status : current
Description : Current rate
OID : 1.3.6.1.4.1.22610.2.4.10.39.54.1.6

Field Name : lockupTimeLeft
Field Type : CounterBasedGauge64
Field Status : current
Description : Lockup time left
OID : 1.3.6.1.4.1.22610.2.4.10.39.54.1.5

Field Name : limitTotalDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total rate limit drops
OID : 1.3.6.1.4.1.22610.2.4.10.39.54.1.4

Field Name : limitVserverDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Virtual Server rate limit drops
OID : 1.3.6.1.4.1.22610.2.4.10.39.54.1.3

Field Name : limitIntfDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Interfaces rate limit drops
OID : 1.3.6.1.4.1.22610.2.4.10.39.54.1.2

Field Name : overLimitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Over limit drops
OID : 1.3.6.1.4.1.22610.2.4.10.39.54.1.1

Field Name : systemBfdOtherError
Field Type : CounterBasedGauge64
Field Status : current
Description : Other errors
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.22

Field Name : noIpv6Enable
Field Type : CounterBasedGauge64
Field Status : current
Description : No IPv6 enable
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.21

Field Name : destUnreachable
Field Type : CounterBasedGauge64
Field Status : current
Description : Destination unreachable
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.20

Field Name : localStateAdminDown

Field Type : CounterBasedGauge64
Field Status : current
Description : Local admin down session state
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.19

Field Name : authFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Authentication failures
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.18

Field Name : authSeqnumInvalid
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid authentication sequence number
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.17

Field Name : authKeyMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Authentication key mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.16

Field Name : authKeyIdMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Authentication key-id mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.15

Field Name : authTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Authentication type mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.14

Field Name : authMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Authentication mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.13

Field Name : authLengthInvalid
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid authentication length
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.12

Field Name : invalidTtl
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid TTL
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.11

Field Name : invalidMyDisc
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid my descriptor
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.10

Field Name : invalidMultipoint
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid multipoint setting
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.9

Field Name : invalidDetectMult
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid detect multiplier
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.8

Field Name : dataIsShort
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet data length too short
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.7

Field Name : lengthTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets too small
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.6

Field Name : versionMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : BFD version mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.5

Field Name : multihopMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Multihop session or packet mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.4

Field Name : sessionNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Session not found
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.3

Field Name : udpChecksumError
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP packet checksum errors
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.2

Field Name : ipChecksumError
Field Type : CounterBasedGauge64
Field Status : current
Description : IP packet checksum errors
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.1

Field Name : outmcastpkts
Field Type : CounterBasedGauge64
Field Status : current

Description : Outgoing multicast packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.22

Field Name : inmcastpkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming multicast packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.21

Field Name : fragcreates
Field Type : CounterBasedGauge64
Field Status : current
Description : Outgoing fragmented packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.20

Field Name : fragfails
Field Type : CounterBasedGauge64
Field Status : current
Description : Outgoing packets fragmentation failed
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.19

Field Name : fragoks
Field Type : CounterBasedGauge64
Field Status : current
Description : Outgoing packets fragmented
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.18

Field Name : reasmfails
Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming reassembly requests failed
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.17

Field Name : reasmoks
Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming reassembled packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.16

Field Name : reasmreqds
Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming reassembly requests
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.15

Field Name : reasmtimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : Reassembly timed out packet drops
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.14

Field Name : outnoroutes
Field Type : CounterBasedGauge64
Field Status : current
Description : Outgoing no route packet drops
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.13

Field Name : outdiscards

Field Type : CounterBasedGauge64
Field Status : current
Description : Outgoing packets discarded
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.12

Field Name : outrequests
Field Type : CounterBasedGauge64
Field Status : current
Description : Outgoing packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.11

Field Name : outforwdatagrams
Field Type : CounterBasedGauge64
Field Status : current
Description : Outgoing forwarded datagrams
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.10

Field Name : indelivers
Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming packets delivered
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.9

Field Name : indiscards
Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming packets discarded
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.8

Field Name : intruncatedpkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming truncated packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.7

Field Name : inunknownprotos
Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming unkown protocol packet drops
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.6

Field Name : inaddrerrors
Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming packet address errors
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.5

Field Name : innoroutes
Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming no route packet drops
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.4

Field Name : intoobigerrors
Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming packet too big errors
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.3

Field Name : inhdrerrors
Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming packet header errors
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.2

Field Name : inreceives
Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming packets received
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.1

Field Name : systemIpStatsOutmcastpkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Outgoing multicast packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.22

Field Name : systemIpStatsInmcastpkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming multicast packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.21

Field Name : systemIpStatsFragcreate
Field Type : CounterBasedGauge64
Field Status : current
Description : Outgoing fragmented packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.20

Field Name : systemIpStatsFragfails
Field Type : CounterBasedGauge64
Field Status : current
Description : Outgoing packets fragmentation failed
OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.19

Field Name : systemIpStatsFragoks
Field Type : CounterBasedGauge64
Field Status : current
Description : Outgoing packets fragmented
OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.18

Field Name : systemIpStatsReasmfails
Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming reassembly requests failed
OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.17

Field Name : systemIpStatsReasmoks
Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming reassembled packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.16

Field Name : systemIpStatsReasmreqds
Field Type : CounterBasedGauge64
Field Status : current

Description : Incoming reassembly requests
OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.15

Field Name : systemIpStatsReasmtimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : Reassembly timed out packet drops
OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.14

Field Name : systemIpStatsOutnoroutes
Field Type : CounterBasedGauge64
Field Status : current
Description : Outgoing no route packet drops
OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.13

Field Name : systemIpStatsOutdiscards
Field Type : CounterBasedGauge64
Field Status : current
Description : Outgoing packets discarded
OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.12

Field Name : systemIpStatsOutrequests
Field Type : CounterBasedGauge64
Field Status : current
Description : Outgoing packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.11

Field Name : systemIpStatsOutforwdatagrams
Field Type : CounterBasedGauge64
Field Status : current
Description : Outgoing forwarded datagrams
OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.10

Field Name : systemIpStatsIndelivers
Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming packets delivered
OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.9

Field Name : systemIpStatsIndiscards
Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming packets discarded
OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.8

Field Name : systemIpStatsIntruncatedpkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming truncated packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.7

Field Name : systemIpStatsInunknownprotos
Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming unkown protocol packet drops
OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.6

Field Name : systemIpStatsInhdrerrors

Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming packet address errors
OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.5

Field Name : systemIpStatsInnoroutes
Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming no route packet drops
OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.4

Field Name : systemIpStatsIntoobigerrors
Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming packet too big errors
OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.3

Field Name : systemIpStatsInhdrerrors
Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming packet header errors
OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.2

Field Name : systemIpStatsInreceives
Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming packets received
OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.1

Field Name : errEchoReplies
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Echo replies
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.37

Field Name : errEchoes
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Echo requests
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.36

Field Name : errRedirects
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Redirects
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.35

Field Name : errNa
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Neighbor advertisement
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.34

Field Name : errNs
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Neighbor solicitation
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.33

Field Name : errRa
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Router advertisement
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.32

Field Name : errRs
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Router solicitation
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.31

Field Name : outMemReductions
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Group member reduction
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.30

Field Name : outMemResp
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Group member reply
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.29

Field Name : outRedirects
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Redirects
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.28

Field Name : outNa
Field Type : CounterBasedGauge64
Field Status : current
Description : Out neighbor advertisement
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.27

Field Name : outNs
Field Type : CounterBasedGauge64
Field Status : current
Description : Out neighbor solicitation
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.26

Field Name : outRa
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Router advertisement
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.25

Field Name : outRs
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Router solicitation
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.24

Field Name : outEchoReplies
Field Type : CounterBasedGauge64
Field Status : current

Description : Out Echo replies
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.23

Field Name : outEchoReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Echo requests
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.22

Field Name : outParamProb
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Parameter Problem
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.21

Field Name : outTimeExceeds
Field Type : CounterBasedGauge64
Field Status : current
Description : Out TTL Exceeds
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.20

Field Name : outPktTooBig
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Packet too big
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.19

Field Name : outDstUnReach
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Destination Unreachable
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.18

Field Name : outMsg
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Messages
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.17

Field Name : inRedirect
Field Type : CounterBasedGauge64
Field Status : current
Description : In Redirects
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.16

Field Name : inNa
Field Type : CounterBasedGauge64
Field Status : current
Description : In neighbor advertisement
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.15

Field Name : inNs
Field Type : CounterBasedGauge64
Field Status : current
Description : In neighbor solicitation
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.14

Field Name : inRa

Field Type : CounterBasedGauge64
Field Status : current
Description : In Router advertisement
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.13

Field Name : inRouterSol
Field Type : CounterBasedGauge64
Field Status : current
Description : In Router solicitation
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.12

Field Name : inGrpMemReduction
Field Type : CounterBasedGauge64
Field Status : current
Description : In Group member reduction
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.11

Field Name : inGrpMemResp
Field Type : CounterBasedGauge64
Field Status : current
Description : In Group member reply
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.10

Field Name : inGrpMemQuery
Field Type : CounterBasedGauge64
Field Status : current
Description : In Group member query
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.9

Field Name : inExhoReply
Field Type : CounterBasedGauge64
Field Status : current
Description : In Echo replies
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.8

Field Name : inEchoes
Field Type : CounterBasedGauge64
Field Status : current
Description : In Echo requests
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.7

Field Name : inParamProb
Field Type : CounterBasedGauge64
Field Status : current
Description : In Parameter Problem
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.6

Field Name : inTimeExceeds
Field Type : CounterBasedGauge64
Field Status : current
Description : In TTL Exceeds
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.5

Field Name : inPktTooBig
Field Type : CounterBasedGauge64
Field Status : current
Description : In Packet too big
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.4

Field Name : inDestUnReach
Field Type : CounterBasedGauge64
Field Status : current
Description : In Destunation Unreachable
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.3

Field Name : inErrors
Field Type : CounterBasedGauge64
Field Status : current
Description : In Errors
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.2

Field Name : inMsgs
Field Type : CounterBasedGauge64
Field Status : current
Description : In messages
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.1

Field Name : outaddrmaskreps
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Address Mask Rep
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.27

Field Name : outaddrmasks
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Address Mask
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.26

Field Name : outtimestampreps
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Time Stamp Rep
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.25

Field Name : outtimestamps
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Time Stamp
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.24

Field Name : outechoreps
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Echo Replies
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.23

Field Name : outechos
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Echo Requests
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.22

Field Name : outredirects
Field Type : CounterBasedGauge64
Field Status : current

Description : Out Redirects
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.21

Field Name : outsrcquenchs
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Source Quench Error
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.20

Field Name : outparmprobs
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Parameter Problem
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.19

Field Name : outtimeexcds
Field Type : CounterBasedGauge64
Field Status : current
Description : Out TTL Exceeds
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.18

Field Name : outdestunreachs
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Destination Unreachable
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.17

Field Name : outerrors
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Errors
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.16

Field Name : outmsgs
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Message
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.15

Field Name : inaddrmaskreps
Field Type : CounterBasedGauge64
Field Status : current
Description : In Address Mask Rep
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.14

Field Name : inaddrmasks
Field Type : CounterBasedGauge64
Field Status : current
Description : In Address Masks
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.13

Field Name : intimestampreps
Field Type : CounterBasedGauge64
Field Status : current
Description : In Timestamp Rep
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.12

Field Name : intimestamps

Field Type : CounterBasedGauge64
Field Status : current
Description : In Timestamp
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.11

Field Name : inechoreps
Field Type : CounterBasedGauge64
Field Status : current
Description : In Echo replies
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.10

Field Name : inechos
Field Type : CounterBasedGauge64
Field Status : current
Description : In Echo requests
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.9

Field Name : inredirects
Field Type : CounterBasedGauge64
Field Status : current
Description : In Redirects
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.8

Field Name : insrcquenchs
Field Type : CounterBasedGauge64
Field Status : current
Description : In Source Quench Error
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.7

Field Name : inparmprobs
Field Type : CounterBasedGauge64
Field Status : current
Description : In Parameter Problem
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.6

Field Name : intimeexcds
Field Type : CounterBasedGauge64
Field Status : current
Description : In TTL Exceeds
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.5

Field Name : indestunreachs
Field Type : CounterBasedGauge64
Field Status : current
Description : In Destination Unreachable
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.4

Field Name : inerrors
Field Type : CounterBasedGauge64
Field Status : current
Description : In Errors
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.3

Field Name : inmsgs
Field Type : CounterBasedGauge64
Field Status : current
Description : In Messages
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.2

Field Name : systemIcmpNum
Field Type : CounterBasedGauge64
Field Status : current
Description : Total number
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.1

Field Name : delayedFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Delayed free return
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.40

Field Name : invalidDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid packet drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.39

Field Name : sockInit
Field Type : CounterBasedGauge64
Field Status : current
Description : Socket init
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.38

Field Name : synRcvRexmit
Field Type : CounterBasedGauge64
Field Status : current
Description : Rcv SYN rexmit
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.37

Field Name : tfoDenied
Field Type : CounterBasedGauge64
Field Status : current
Description : TFO Denied
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.36

Field Name : tfoActives
Field Type : CounterBasedGauge64
Field Status : current
Description : TFO Current Actives
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.35

Field Name : tfoConns
Field Type : CounterBasedGauge64
Field Status : current
Description : TFO Total Connections
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.34

Field Name : exceedmss
Field Type : CounterBasedGauge64
Field Status : current
Description : MSS exceeded pkt dropped
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.33

Field Name : noroute
Field Type : CounterBasedGauge64
Field Status : current

Description : TCPIP out noroute
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.32

Field Name : tcpabortontimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP abort on timeout
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.31

Field Name : axRexmitSyn
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP rexmit SYN
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.30

Field Name : synRcvAck
Field Type : CounterBasedGauge64
Field Status : current
Description : Rcv ACK on SYN
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.29

Field Name : synRcvRst
Field Type : CounterBasedGauge64
Field Status : current
Description : Rcv RST on SYN
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.28

Field Name : synRcvRstack
Field Type : CounterBasedGauge64
Field Status : current
Description : Rcv RST|ACK on SYN
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.27

Field Name : pawsactiverejected
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP paw active rej
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.26

Field Name : currclsg
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP in Closing state
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.25

Field Name : currlstn
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP in Listen state
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.24

Field Name : currlack
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP in LastACK state
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.23

Field Name : currclsw

Field Type : CounterBasedGauge64
Field Status : current
Description : TCP in CloseW state
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.22

Field Name : currclose
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP in Close state
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.21

Field Name : currtimew
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP TimeW state
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.20

Field Name : currfinw2
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP FIN-W2 state
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.19

Field Name : currfinw1
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP in FIN-W1 state
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.18

Field Name : currsynrcv
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP in SYN-RCV state
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.17

Field Name : currsyssnt
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP in SYN-SNT state
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.16

Field Name : currestab
Field Type : CounterBasedGauge64
Field Status : current
Description : Currently EST conns
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.15

Field Name : sendMem
Field Type : CounterBasedGauge64
Field Status : current
Description : Total tx buffer
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.14

Field Name : recvMem
Field Type : CounterBasedGauge64
Field Status : current
Description : Total rx buffer
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.13

Field Name : memAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Memory alloc
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.12

Field Name : orphanCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Orphan sockets
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.11

Field Name : sockAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Sockets allocated
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.10

Field Name : outrsts
Field Type : CounterBasedGauge64
Field Status : current
Description : Reset Sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.9

Field Name : inerrs
Field Type : CounterBasedGauge64
Field Status : current
Description : Input errors
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.8

Field Name : retranssegs
Field Type : CounterBasedGauge64
Field Status : current
Description : Retransmited packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.7

Field Name : outsegs
Field Type : CounterBasedGauge64
Field Status : current
Description : Total out TCP packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.6

Field Name : insegs
Field Type : CounterBasedGauge64
Field Status : current
Description : Total in TCP packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.5

Field Name : estabresets
Field Type : CounterBasedGauge64
Field Status : current
Description : Resets rcvd on EST conn
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.4

Field Name : attemptfails
Field Type : CounterBasedGauge64
Field Status : current

Description : Connect attemp failures
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.3

Field Name : passiveopens
Field Type : CounterBasedGauge64
Field Status : current
Description : Passive open conns
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.2

Field Name : activeopens
Field Type : CounterBasedGauge64
Field Status : current
Description : Active open conns
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.1

Field Name : sslHwQInuseTot
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.39.94.1.5

Field Name : sslHwQDepthTot
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.39.94.1.4

Field Name : sslReqQInuseTot
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.39.94.1.3

Field Name : sslReqQDepthTot
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.39.94.1.2

Field Name : numSslQueues
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.39.94.1.1

Field Name : gifwConnsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : GiFW Connections/sec
OID : 1.3.6.1.4.1.22610.2.4.10.39.71.1.13

Field Name : fwConnsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : FW Connections/sec
OID : 1.3.6.1.4.1.22610.2.4.10.39.71.1.12

Field Name : servSslConnsPerSec

Field Type : CounterBasedGauge64
Field Status : current
Description : Server SSL Connections/sec
OID : 1.3.6.1.4.1.22610.2.4.10.39.71.1.11

Field Name : l7Bandwidth
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 Bandwidth in bits/sec
OID : 1.3.6.1.4.1.22610.2.4.10.39.71.1.10

Field Name : l4Bandwidth
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 Bandwidth in bits/sec
OID : 1.3.6.1.4.1.22610.2.4.10.39.71.1.9

Field Name : totalCurrConns
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Current Established Connections
OID : 1.3.6.1.4.1.22610.2.4.10.39.71.1.8

Field Name : totalNewConnsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : Total New Connections Established/sec
OID : 1.3.6.1.4.1.22610.2.4.10.39.71.1.7

Field Name : ipNatConnsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : IP NAT Connections/sec
OID : 1.3.6.1.4.1.22610.2.4.10.39.71.1.6

Field Name : sslConnsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL Connections/sec
OID : 1.3.6.1.4.1.22610.2.4.10.39.71.1.5

Field Name : l7TransPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 Transactions/sec
OID : 1.3.6.1.4.1.22610.2.4.10.39.71.1.4

Field Name : l7ConnsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 Connections/sec
OID : 1.3.6.1.4.1.22610.2.4.10.39.71.1.3

Field Name : l4ConnsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 Connections/sec
OID : 1.3.6.1.4.1.22610.2.4.10.39.71.1.2

Field Name : totalThroughputBitsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Throughput in bits/sec
OID : 1.3.6.1.4.1.22610.2.4.10.39.71.1.1

Field Name : wRingDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total worker core ring drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.27

Field Name : wLinkDownDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total worker core link down drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.26

Field Name : wTxQueDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total worker core queue drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.25

Field Name : ioRingDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total IO core ring drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.24

Field Name : ioTxQueDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total IO core TX queue drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.23

Field Name : ioRxQueDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total IO core Rx queue drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.22

Field Name : rxCsumOffloadErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Rx packet check-sum offload error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.21

Field Name : rxAlignErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total RX packet align error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.20

Field Name : rxShortLenErr
Field Type : CounterBasedGauge64
Field Status : current

Description : Total RX packet short length error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.19

Field Name : rxLongLenErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total RX packet long length error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.18

Field Name : txWindowsErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TX windows error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.17

Field Name : txHbeatErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TX packet HBEAT error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.16

Field Name : txFifoErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TX packet fifo error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.15

Field Name : txCarrierErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TX packert carrier error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.14

Field Name : txAbortErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TX packet abort error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.13

Field Name : rxMissErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total RX packet miss error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.12

Field Name : rxNoBuffErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total RX packet no buffer error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.11

Field Name : rxFrameErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total RX packet frame error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.10

Field Name : rxCrcErr

Field Type : CounterBasedGauge64
Field Status : current
Description : Total RX packet CRC error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.9

Field Name : rxOverErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total RX packet over error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.8

Field Name : rxLenErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total RX packet length error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.7

Field Name : txDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TX packet drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.6

Field Name : txErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TX packet error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.5

Field Name : rxErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total RX packet error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.4

Field Name : errPktDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total error packet drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.3

Field Name : pktLnkDownDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total packets link down drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.2

Field Name : pktDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total packet drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.1

Field Name : qdrDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total QDR Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.38

Field Name : tunMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Tun mismatch Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.37

Field Name : runtTcpudpHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Runt TCPUDP hdr Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.36

Field Name : runtIpHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Runt IP hdr Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.35

Field Name : udpBadChksum
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP bad csum Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.34

Field Name : udpPortLb
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP port LB Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.33

Field Name : udpKbFrags
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP KB frag Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.32

Field Name : udpBadIpLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP bad leng Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.31

Field Name : udpShortHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP short hdr Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.30

Field Name : tcpBadChksum
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP bad csum Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.29

Field Name : tcpFragHdr
Field Type : CounterBasedGauge64
Field Status : current

Description : Total TCP frag header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.28

Field Name : tcpSynFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP SYN frag Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.27

Field Name : tcpXmasScan
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP XMAS scan Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.26

Field Name : tcpXmasFlags
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP XMAS FLAGS Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.25

Field Name : tcpFinSin
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP SYN&FIN Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.24

Field Name : tcpNullScan
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP null scan Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.23

Field Name : tcpNullFlags
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP null flags Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.22

Field Name : tcpBadIpLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Bad IP Len Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.21

Field Name : tcpShortHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP short hdr Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.20

Field Name : tcpBadUrgOffet
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP bad urg off Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.19

Field Name : icmpPodDrop

Field Type : CounterBasedGauge64
Field Status : current
Description : Total ICMP POD Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.18

Field Name : badIpChksumDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Bad IP csum Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.17

Field Name : badIpFragOffset
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Bad IP frag off Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.16

Field Name : badIpPayloadLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Bad IP PL len Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.15

Field Name : oversizeIpPayload
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Oversize IP PL Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.14

Field Name : noIpPayloadDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total No IP Payload Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.13

Field Name : badIpTtlDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Bad IP TTL Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.12

Field Name : badIpFlagsDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Bad IP Flags Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.11

Field Name : badIpHdrLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Bad IP hdr len Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.10

Field Name : ipv4Frag
Field Type : CounterBasedGauge64
Field Status : current
Description : Total IP frag Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.9

Field Name : ipv4OptDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total IPv4 opt Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.8

Field Name : micFragDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Micro frag Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.7

Field Name : emptyFragDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Empty frag Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.6

Field Name : landDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total LAND Attack Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.5

Field Name : fcsDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total FCS Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.4

Field Name : sizDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Size Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.3

Field Name : hrxDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total HRX Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.2

Field Name : mrxDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total MRX Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.1

Field Name : errorOutOfSpeEntries
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of SPE Entries Error
OID : 1.3.6.1.4.1.22610.2.4.10.39.103.1.8

Field Name : errorOutOfMemory
Field Type : CounterBasedGauge64
Field Status : current

Description : Out of memory Error
OID : 1.3.6.1.4.1.22610.2.4.10.39.103.1.7

Field Name : entriesRemovedFromSpe
Field Type : CounterBasedGauge64
Field Status : current
Description : Entries Removed from SPE
OID : 1.3.6.1.4.1.22610.2.4.10.39.103.1.6

Field Name : entriesAddedInSpe
Field Type : CounterBasedGauge64
Field Status : current
Description : Entries Added in SPE
OID : 1.3.6.1.4.1.22610.2.4.10.39.103.1.5

Field Name : entriesRemovedFromSw
Field Type : CounterBasedGauge64
Field Status : current
Description : Entries Removed from SW
OID : 1.3.6.1.4.1.22610.2.4.10.39.103.1.4

Field Name : entriesAddedInSw
Field Type : CounterBasedGauge64
Field Status : current
Description : Entries Added in SW
OID : 1.3.6.1.4.1.22610.2.4.10.39.103.1.3

Field Name : packetHitCountInSpe
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet Hit Count in SPE
OID : 1.3.6.1.4.1.22610.2.4.10.39.103.1.2

Field Name : packetHitCountInSw
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet Hit Count in SW
OID : 1.3.6.1.4.1.22610.2.4.10.39.103.1.1

Field Name : placeHolder
Field Type : CounterBasedGauge64
Field Status : current
Description : place-holder
OID : 1.3.6.1.4.1.22610.2.4.10.39.87.1.1

Field Name : placeHolder
Field Type : CounterBasedGauge64
Field Status : current
Description : place-holder
OID : 1.3.6.1.4.1.22610.2.4.10.39.85.1.1

Field Name : systemGeolocListSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.39.84.1.1

Field Name : systemGeolocListSEntry

Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.39.84.1.1.1

Field Name : totalActive
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.39.84.1.1.1.4

Field Name : totalGeoloc
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.39.84.1.1.1.3

Field Name : hitCount
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.39.84.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Specify name of Geolocation list
OID : 1.3.6.1.4.1.22610.2.4.10.39.84.1.1.1.1

Field Name : radiusInterCardDupRedir
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS packet dropped as redirected by other blade (SO)
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.39

Field Name : radiusPacketsDroppedNotLo
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS packets dropped dest not loopback (SO)
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.38

Field Name : radiusPacketsProcessLocal
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS packets processed locally without redirection (SO)
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.37

Field Name : radiusPacketsRedirectFailDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS packets dropped due to redirect failure (SO)
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.36

Field Name : radiusPacketsRedirected
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS packets redirected (SO)
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.35

Field Name : interCardMsgFailDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Inter-Card Message Fail Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.34

Field Name : haSyncNoKeyVapDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Record Sync No key dropped
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.33

Field Name : ipAddRaceDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Radius Entry IP Add Race Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.32

Field Name : ipMismatchDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : Radius Entry IP Mismatch Delete
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.31

Field Name : acctOnDupRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Duplicate RADIUS Acct On Request
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.30

Field Name : acctOnFiltersFull
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Acct On Request Ignored(Filters Full)
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.29

Field Name : haSyncDeleteRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Record Sync Delete Received
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.28

Field Name : haSyncCreateRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Record Sync Create Received
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.27

Field Name : haSyncDeleteSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Record Sync Delete Sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.26

Field Name : haSyncCreateSent
Field Type : CounterBasedGauge64
Field Status : current

Description : HA Record Sync Create Sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.25

Field Name : memFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Memory Freed
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.24

Field Name : memAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Memory Allocation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.23

Field Name : memAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Memory Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.22

Field Name : smpInRml
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS SMP in RML
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.21

Field Name : smpMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS SMP Memory Freed
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.20

Field Name : smpMemAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS SMP Memory Allocation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.19

Field Name : smpMemAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS SMP Memory Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.18

Field Name : smpDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS SMP Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.17

Field Name : smpCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS SMP Created
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.16

Field Name : invalidKey

Field Type : CounterBasedGauge64
Field Status : current
Description : Radius Request has Invalid Key Field
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.15

Field Name : ipv6PrefixLengthMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Framed IPV6 Prefix Length Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.14

Field Name : haStandbyDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Standby Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.13

Field Name : secretNotConfiguredDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Secret Not Configured Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.12

Field Name : radiusTableFull
Field Type : TABLE
Field Status : current
Description : RADIUS Request Dropped (Table Full)
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.11

Field Name : requestIgnored
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request Ignored
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.10

Field Name : requestMalformedDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request Malformed Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.9

Field Name : requestNoKeyVapDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request No Key Attribute Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.8

Field Name : requestBadSecretDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request Bad Secret Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.7

Field Name : radiusRequestDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request Dropped (Malformed Packet)
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.6

Field Name : radiusRequestReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request Received
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.5

Field Name : customReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom attribute Received
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.4

Field Name : imsiReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : IMSI Received
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.3

Field Name : imeiReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : IMEI Received
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.2

Field Name : msisdnReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : MSISDN Received
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.1

Field Name : perPartThroughputBitsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : Partition throughput in bits/sec
OID : 1.3.6.1.4.1.22610.2.4.10.39.38.1.2

Field Name : globalSystemThroughputBitsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : Global System throughput in bits/sec
OID : 1.3.6.1.4.1.22610.2.4.10.39.38.1.1

Field Name : hwFwdFlowSflowCount
Field Type : CounterBasedGauge64
Field Status : current
Description : hardware forward rate drop count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.33

Field Name : hwFwdStatsUpdateRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward entry stats update count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.32

Field Name : hwFwdLookupFailRcvd
Field Type : CounterBasedGauge64
Field Status : current

Description : Hardware forward entry lookup fail count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.31

Field Name : hwFwdTcpRstAgeoutRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward tcp RST ageout received count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.30

Field Name : hwFwdTcpFinAgeoutRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward tcp FIN ageout received count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.29

Field Name : hwFwdNormalAgeoutRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward normal ageout received count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.28

Field Name : hwFwdRateDropCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward rate drop count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.27

Field Name : hwFwdAvailIpv6Entry
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward available ipv6 entries count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.26

Field Name : hwFwdAvailIpv4Entry
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward available ipv4 entries count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.25

Field Name : hwFwdProtocolMismatchDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward protocol mismatch count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.24

Field Name : hwFwdVmidDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward vmid mismatch count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.23

Field Name : hwFwdVlanidMismatchDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward vlanid mismatch count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.22

Field Name : hwFwdPhyportMismatchDrop

Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward phyport mismatch count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.21

Field Name : hwFwdFlowQdrFullDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward flow qdr full drop count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.20

Field Name : hwFwdFlowTxFullDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward flow tx full drop count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.19

Field Name : hwFwdFlowUnderflowCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward flow underflow count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.18

Field Name : hwFwdFlowUnalignCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward flow unalign count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.17

Field Name : hwFwdFlowErrorCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward flow error count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.16

Field Name : hwFwdFlowDropCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward flow drop count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.15

Field Name : hwFwdFlowReasonFlags
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward flow reason flags
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.14

Field Name : hwFwdFlowHitIndex
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward flow hit index
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.13

Field Name : hwFwdInvalidationDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward invalid drop count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.12

Field Name : hwFwdAgeoutDropCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward ageout drop count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.11

Field Name : hwFwdFlowSeqMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward sequence mismatch errors
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.10

Field Name : hwFwdFlowTagMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward tag mismatch errors
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.9

Field Name : hwFwdFlowSinglebitErrors
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward singlebit Errors
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.8

Field Name : hwFwdProgErrors
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward programming Errors
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.7

Field Name : hwFwdProgReqs
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward programming requests
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.6

Field Name : hwFwdModuleStatus
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forwarder status flags
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.5

Field Name : ipv6ForwardCounts
Field Type : CounterBasedGauge64
Field Status : current
Description : Total IPv6 hardware forwarded packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.4

Field Name : ipv4ForwardCounts
Field Type : CounterBasedGauge64
Field Status : current
Description : Total IPv4 hardware forwarded packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.3

Field Name : hitIndex
Field Type : CounterBasedGauge64
Field Status : current

Description : HW Fwd hit index
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.2

Field Name : hitCounts
Field Type : CounterBasedGauge64
Field Status : current
Description : Total packets hit counts
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.1

Field Name : tcamCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : TCAM Entry Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.20

Field Name : tcamFree
Field Type : CounterBasedGauge64
Field Status : current
Description : TCAM Entries Freed
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.19

Field Name : tcamCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : TCAM Entries Created
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.18

Field Name : entryInvalidateServerDown
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware Entries Invalidate due to server down
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.17

Field Name : entryForceHwInvalidate
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware Entries Force HW Invalidate
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.16

Field Name : entryAgeOutInvalidDst
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware Entries Aged Out invalid dst
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.15

Field Name : entryAgeOutTcpRst
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware Entries Aged Out TCP RST
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.14

Field Name : entryAgeOutTcpFin
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware Entries Aged Out TCP FIN
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.13

Field Name : entryAgeOutIdle

Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware Entries Aged Out Idle
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.12

Field Name : entryAgeOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware Entries Aged Out
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.11

Field Name : entryCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware Entry Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.10

Field Name : entryFreeNoSwEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware Entry Free no software entry
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.9

Field Name : entryFreeNoConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware Entry Free no matched conn
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.8

Field Name : entryFreeNoHwProg
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware Entry Free no hw prog
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.7

Field Name : entryFreeOppEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware Entries Free due to opposite tuple entry ageout event
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.6

Field Name : entryFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware Entries Freed
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.5

Field Name : entryCreateFailMaxEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware Entries Created
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.4

Field Name : entryCreateFailServerDown
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware Entries Created
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.3

Field Name : entryCreateFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware Entries Created
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.2

Field Name : entryCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware Entries Created
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.1

Field Name : acosSystemTableIntegrity
Field Type : TABLE
Field Status : none
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.39.129

Field Name : acosSystemTableIntegrityS
Field Type : TABLE
Field Status : none
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1

Field Name : macTblCksumCancelM
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table checksum cancelled count in master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.230

Field Name : ipv6FibTblCksumCancelM
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table checksum cancelled count in master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.229

Field Name : ipv4FibTblCksumCancelM
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table checksum cancelled count in master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.228

Field Name : nd6TblCksumCancelM
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table checksum cancelled count in master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.227

Field Name : arpTblCksumCancelM
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table checksum cancelled count in master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.226

Field Name : macTblCksumMismatchB
Field Type : CounterBasedGauge64
Field Status : current

Description : mac table checksum mismatch count in blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.225

Field Name : ipv6FibTblCksumMismatchB
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table checksum mismatch count in blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.224

Field Name : ipv4FibTblCksumMismatchB
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table checksum mismatch count in blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.223

Field Name : nd6TblCksumMismatchB
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table checksum mismatch count in blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.222

Field Name : arpTblCksumMismatchB
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table checksum mismatch count in blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.221

Field Name : macTblCksumB
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table checksum count in blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.220

Field Name : ipv6FibTblCksumB
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table checksum count in blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.219

Field Name : ipv4FibTblCksumB
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table checksum count in blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.218

Field Name : nd6TblCksumB
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table checksum count in blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.217

Field Name : arpTblCksumB
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table checksum count in blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.216

Field Name : macTblCksumM

Field Type : CounterBasedGauge64
Field Status : current
Description : mac table checksum count in master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.215

Field Name : ipv6FibTblCksumM
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table checksum count in master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.214

Field Name : ipv4FibTblCksumM
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table checksum count in master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.213

Field Name : nd6TblCksumM
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table checksum count in master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.212

Field Name : arpTblCksumM
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table checksum count in master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.211

Field Name : macTblSyncB
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync count in blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.210

Field Name : ipv6FibTblSyncB
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync count in blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.209

Field Name : ipv4FibTblSyncB
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync count in blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.208

Field Name : nd6TblSyncB
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync count in blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.207

Field Name : arpTblSyncB
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync count in blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.206

Field Name : macTblSyncM
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync count in master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.205

Field Name : ipv6FibTblSyncM
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync count in master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.204

Field Name : ipv4FibTblSyncM
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync count in master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.203

Field Name : nd6TblSyncM
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync count in master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.202

Field Name : arpTblSyncM
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync count in master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.201

Field Name : macTblSyncEndTsB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync end time stamp blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.200

Field Name : ipv6FibTblSyncEndTsB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync end time stamp blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.199

Field Name : ipv4FibTblSyncEndTsB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync end time stamp blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.198

Field Name : nd6TblSyncEndTsB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync end time stamp blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.197

Field Name : arpTblSyncEndTsB5th
Field Type : CounterBasedGauge64
Field Status : current

Description : arp table sync end time stamp blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.196

Field Name : macTblSyncEndTsM5th
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync end time stamp master for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.195

Field Name : ipv6FibTblSyncEndTsM5th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync end time stamp master for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.194

Field Name : ipv4FibTblSyncEndTsM5th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync end time stamp master for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.193

Field Name : nd6TblSyncEndTsM5th
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync end time stamp master for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.192

Field Name : arpTblSyncEndTsM5th
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync end time stamp master for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.191

Field Name : macTblSyncEntriesRemovedB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries removed in blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.190

Field Name : ipv6FibTblSyncEntriesRemovedB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries removed in blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.189

Field Name : ipv4FibTblSyncEntriesRemovedB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries removed in blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.188

Field Name : nd6TblSyncEntriesRemovedB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table entries removed in blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.187

Field Name : arpTblSyncEntriesRemovedB5th

Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries removed in blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.186

Field Name : macTblSyncEntriesAddedB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries added in blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.185

Field Name : ipv6FibTblSyncEntriesAddedB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries added in blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.184

Field Name : ipv4FibTblSyncEntriesAddedB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries added in blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.183

Field Name : nd6TblSyncEntriesAddedB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table entries added in blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.182

Field Name : arpTblSyncEntriesAddedB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries added in blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.181

Field Name : macTblSyncEntriesRcvdB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries received in blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.180

Field Name : ipv6FibTblSyncEntriesRcvdB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries received in blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.179

Field Name : ipv4FibTblSyncEntriesRcvdB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries received in blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.178

Field Name : nd6TblSyncEntriesRcvdB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table entries received in blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.177

Field Name : arpTblSyncEntriesRcvdB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries received in blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.176

Field Name : macTblSyncEntriesSentM5th
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync start time stamp blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.175

Field Name : ipv6FibTblSyncEntriesSentM5th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync start time stamp blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.174

Field Name : ipv4FibTblSyncEntriesSentM5th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync start time stamp blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.173

Field Name : nd6TblSyncEntriesSentM5th
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync start time stamp blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.172

Field Name : arpTblSyncEntriesSentM5th
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync start time stamp blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.171

Field Name : macTblSyncStartTsB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync start time stamp blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.170

Field Name : ipv6FibTblSyncStartTsB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync start time stamp blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.169

Field Name : ipv4FibTblSyncStartTsB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync start time stamp blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.168

Field Name : nd6TblSyncStartTsB5th
Field Type : CounterBasedGauge64
Field Status : current

Description : nd6 table sync start time stamp blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.167

Field Name : arpTblSyncStartTsB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync start time stamp blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.166

Field Name : macTblSyncStartTsM5th
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync start time stamp master for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.165

Field Name : ipv6FibTblSyncStartTsM5th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync start time stamp master for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.164

Field Name : ipv4FibTblSyncStartTsM5th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync start time stamp master for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.163

Field Name : nd6TblSyncStartTsM5th
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync start time stamp master for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.162

Field Name : arpTblSyncStartTsM5th
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync start time stamp master for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.161

Field Name : macTblSyncEndTsB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync end time stamp blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.160

Field Name : ipv6FibTblSyncEndTsB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync end time stamp blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.159

Field Name : ipv4FibTblSyncEndTsB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync end time stamp blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.158

Field Name : nd6TblSyncEndTsB4th

Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync end time stamp blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.157

Field Name : arpTblSyncEndTsB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync end time stamp blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.156

Field Name : macTblSyncEndTsM4th
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync end time stamp master for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.155

Field Name : ipv6FibTblSyncEndTsM4th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync end time stamp master for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.154

Field Name : ipv4FibTblSyncEndTsM4th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync end time stamp master for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.153

Field Name : nd6TblSyncEndTsM4th
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync end time stamp master for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.152

Field Name : arpTblSyncEndTsM4th
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync end time stamp master for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.151

Field Name : macTblSyncEntriesRemovedB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries removed in blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.150

Field Name : ipv6FibTblSyncEntriesRemovedB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries removed in blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.149

Field Name : ipv4FibTblSyncEntriesRemovedB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries removed in blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.148

Field Name : nd6TblSyncEntriesRemovedB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table entries removed in blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.147

Field Name : arpTblSyncEntriesRemovedB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries removed in blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.146

Field Name : macTblSyncEntriesAddedB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries added in blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.145

Field Name : ipv6FibTblSyncEntriesAddedB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries added in blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.144

Field Name : ipv4FibTblSyncEntriesAddedB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries added in blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.143

Field Name : nd6TblSyncEntriesAddedB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table entries added in blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.142

Field Name : arpTblSyncEntriesAddedB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries added in blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.141

Field Name : macTblSyncEntriesRcvdB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries received in blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.140

Field Name : ipv6FibTblSyncEntriesRcvdB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries received in blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.139

Field Name : ipv4FibTblSyncEntriesRcvdB4th
Field Type : CounterBasedGauge64
Field Status : current

Description : ipv4-fib table entries received in blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.138

Field Name : nd6TblSyncEntriesRcvdB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table entries received in blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.137

Field Name : arpTblSyncEntriesRcvdB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries received in blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.136

Field Name : macTblSyncEntriesSentM4th
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries sent from master for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.135

Field Name : ipv6FibTblSyncEntriesSentM4th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries sent from master for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.134

Field Name : ipv4FibTblSyncEntriesSentM4th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries sent from master for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.133

Field Name : nd6TblSyncEntriesSentM4th
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table entries sent from master for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.132

Field Name : arpTblSyncEntriesSentM4th
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries sent from master for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.131

Field Name : macTblSyncStartTsB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync start time stamp blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.130

Field Name : ipv6FibTblSyncStartTsB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync start time stamp blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.129

Field Name : ipv4FibTblSyncStartTsB4th

Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync start time stamp blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.128

Field Name : nd6TblSyncStartTsB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync start time stamp blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.127

Field Name : arpTblSyncStartTsB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync start time stamp blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.126

Field Name : macTblSyncStartTsM4th
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync start time stamp master for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.125

Field Name : ipv6FibTblSyncStartTsM4th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync start time stamp master for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.124

Field Name : ipv4FibTblSyncStartTsM4th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync start time stamp master for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.123

Field Name : nd6TblSyncStartTsM4th
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync start time stamp master for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.122

Field Name : arpTblSyncStartTsM4th
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync start time stamp master for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.121

Field Name : macTblSyncEndTsB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync end time stamp blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.120

Field Name : ipv6FibTblSyncEndTsB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync end time stamp blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.119

Field Name : ipv4FibTblSyncEndTsB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync end time stamp blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.118

Field Name : nd6TblSyncEndTsB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync end time stamp blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.117

Field Name : arpTblSyncEndTsB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync end time stamp blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.116

Field Name : macTblSyncEndTsM3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync end time stamp master for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.115

Field Name : ipv6FibTblSyncEndTsM3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync end time stamp master for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.114

Field Name : ipv4FibTblSyncEndTsM3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync end time stamp master for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.113

Field Name : nd6TblSyncEndTsM3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync end time stamp master for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.112

Field Name : arpTblSyncEndTsM3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync end time stamp master for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.111

Field Name : macTblSyncEntriesRemovedB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries removed in blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.110

Field Name : ipv6FibTblSyncEntriesRemovedB3rd
Field Type : CounterBasedGauge64
Field Status : current

Description : ipv6-fib table entries removed in blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.109

Field Name : ipv4FibTblSyncEntriesRemovedB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries removed in blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.108

Field Name : nd6TblSyncEntriesRemovedB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table entries removed in blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.107

Field Name : arpTblSyncEntriesRemovedB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries removed in blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.106

Field Name : macTblSyncEntriesAddedB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries added in blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.105

Field Name : ipv6FibTblSyncEntriesAddedB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries added in blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.104

Field Name : ipv4FibTblSyncEntriesAddedB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries added in blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.103

Field Name : nd6TblSyncEntriesAddedB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table entries added in blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.102

Field Name : arpTblSyncEntriesAddedB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries added in blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.101

Field Name : macTblSyncEntriesRcvdB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries received in blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.100

Field Name : ipv6FibTblSyncEntriesRcvdB3rd

Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries received in blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.99

Field Name : ipv4FibTblSyncEntriesRcvdB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries received in blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.98

Field Name : nd6TblSyncEntriesRcvdB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table entries received in blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.97

Field Name : arpTblSyncEntriesRcvdB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries received in blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.96

Field Name : macTblSyncEntriesSentM3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries sent from master for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.95

Field Name : ipv6FibTblSyncEntriesSentM3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries sent from master for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.94

Field Name : ipv4FibTblSyncEntriesSentM3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries sent from master for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.93

Field Name : nd6TblSyncEntriesSentM3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table entries sent from master for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.92

Field Name : arpTblSyncEntriesSentM3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries sent from master for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.91

Field Name : macTblSyncStartTsB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync start time stamp blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.90

Field Name : ipv6FibTblSyncStartTsB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync start time stamp blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.89

Field Name : ipv4FibTblSyncStartTsB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync start time stamp blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.88

Field Name : nd6TblSyncStartTsB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync start time stamp blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.87

Field Name : arpTblSyncStartTsB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync start time stamp blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.86

Field Name : macTblSyncStartTsM3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync start time stamp master for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.85

Field Name : ipv6FibTblSyncStartTsM3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync start time stamp master for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.84

Field Name : ipv4FibTblSyncStartTsM3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync start time stamp master for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.83

Field Name : nd6TblSyncStartTsM3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync start time stamp master for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.82

Field Name : arpTblSyncStartTsM3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync start time stamp master for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.81

Field Name : macTblSyncEndTsB2nd
Field Type : CounterBasedGauge64
Field Status : current

Description : mac table sync end time stamp blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.80

Field Name : ipv6FibTblSyncEndTsB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync end time stamp blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.79

Field Name : ipv4FibTblSyncEndTsB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync end time stamp blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.78

Field Name : nd6TblSyncEndTsB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync end time stamp blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.77

Field Name : arpTblSyncEndTsB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync end time stamp blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.76

Field Name : macTblSyncEndTsM2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync end time stamp master for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.75

Field Name : ipv6FibTblSyncEndTsM2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync end time stamp master for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.74

Field Name : ipv4FibTblSyncEndTsM2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync end time stamp master for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.73

Field Name : nd6TblSyncEndTsM2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync end time stamp master for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.72

Field Name : arpTblSyncEndTsM2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync end time stamp master for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.71

Field Name : macTblSyncEntriesRemovedB2nd

Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries removed in blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.70

Field Name : ipv6FibTblSyncEntriesRemovedB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries removed in blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.69

Field Name : ipv4FibTblSyncEntriesRemovedB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries removed in blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.68

Field Name : nd6TblSyncEntriesRemovedB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table entries removed in blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.67

Field Name : arpTblSyncEntriesRemovedB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries removed in blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.66

Field Name : macTblSyncEntriesAddedB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries added in blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.65

Field Name : ipv6FibTblSyncEntriesAddedB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries added in blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.64

Field Name : ipv4FibTblSyncEntriesAddedB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries added in blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.63

Field Name : nd6TblSyncEntriesAddedB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table entries added in blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.62

Field Name : arpTblSyncEntriesAddedB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries added in blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.61

Field Name : macTblSyncEntriesRcvdB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries received in blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.60

Field Name : ipv6FibTblSyncEntriesRcvdB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries received in blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.59

Field Name : ipv4FibTblSyncEntriesRcvdB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries received in blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.58

Field Name : nd6TblSyncEntriesRcvdB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table entries received in blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.57

Field Name : arpTblSyncEntriesRcvdB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries received in blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.56

Field Name : macTblSyncEntriesSentM2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries sent from master for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.55

Field Name : ipv6FibTblSyncEntriesSentM2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries sent from master for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.54

Field Name : ipv4FibTblSyncEntriesSentM2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries sent from master for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.53

Field Name : nd6TblSyncEntriesSentM2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table entries sent from master for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.52

Field Name : arpTblSyncEntriesSentM2nd
Field Type : CounterBasedGauge64
Field Status : current

Description : arp table entries sent from master for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.51

Field Name : macTblSyncStartTsB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync start time stamp blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.50

Field Name : ipv6FibTblSyncStartTsB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync start time stamp blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.49

Field Name : ipv4FibTblSyncStartTsB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync start time stamp blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.48

Field Name : nd6TblSyncStartTsB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync start time stamp blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.47

Field Name : arpTblSyncStartTsB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync start time stamp blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.46

Field Name : macTblSyncStartTsM2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync start time stamp master for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.45

Field Name : ipv6FibTblSyncStartTsM2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync start time stamp master for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.44

Field Name : ipv4FibTblSyncStartTsM2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync start time stamp master for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.43

Field Name : nd6TblSyncStartTsM2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync start time stamp master for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.42

Field Name : arpTblSyncStartTsM2nd

Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync start time stamp master for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.41

Field Name : macTblSyncEndTsB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync end time stamp blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.40

Field Name : ipv6FibTblSyncEndTsB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync end time stamp blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.39

Field Name : ipv4FibTblSyncEndTsB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync end time stamp blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.38

Field Name : nd6TblSyncEndTsB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync end time stamp blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.37

Field Name : arpTblSyncEndTsB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync end time stamp blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.36

Field Name : macTblSyncEndTsM1st
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync end time stamp master for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.35

Field Name : ipv6FibTblSyncEndTsM1st
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync end time stamp master for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.34

Field Name : ipv4FibTblSyncEndTsM1st
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync end time stamp master for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.33

Field Name : nd6TblSyncEndTsM1st
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync end time stamp master for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.32

Field Name : arpTblSyncEndTsM1st
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync end time stamp master for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.31

Field Name : macTblSyncEntriesRemovedB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries removed on blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.30

Field Name : ipv6FibTblSyncEntriesRemovedB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries removed on blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.29

Field Name : ipv4FibTblSyncEntriesRemovedB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries removed on blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.28

Field Name : nd6TblSyncEntriesRemovedB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries removed on blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.27

Field Name : arpTblSyncEntriesRemovedB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries removed on blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.26

Field Name : macTblSyncEntriesAddedB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries added on blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.25

Field Name : ipv6FibTblSyncEntriesAddedB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries added on blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.24

Field Name : ipv4FibTblSyncEntriesAddedB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries added on blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.23

Field Name : nd6TblSyncEntriesAddedB1st
Field Type : CounterBasedGauge64
Field Status : current

Description : nd6 table entries added on blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.22

Field Name : arpTblSyncEntriesAddedB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries added on blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.21

Field Name : macTblSyncEntriesRcvdB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries received on blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.20

Field Name : ipv6FibTblSyncEntriesRcvdB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries received on blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.19

Field Name : ipv4FibTblSyncEntriesRcvdB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries received on blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.18

Field Name : nd6TblSyncEntriesRcvdB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table entries received on blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.17

Field Name : arpTblSyncEntriesRcvdB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries received on blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.16

Field Name : macTblSyncEntriesSentM1st
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries sent from master for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.15

Field Name : ipv6FibTblSyncEntriesSentM1st
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries sent from master for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.14

Field Name : ipv4FibTblSyncEntriesSentM1st
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries sent from master for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.13

Field Name : nd6TblSyncEntriesSentM1st

Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table entries sent from master for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.12

Field Name : arpTblSyncEntriesSentM1st
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries sent from master for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.11

Field Name : macTblSyncStartTsB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync start time stamp blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.10

Field Name : ipv6FibTblSyncStartTsB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync start time stamp blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.9

Field Name : ipv4FibTblSyncStartTsB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync start time stamp blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.8

Field Name : nd6TblSyncStartTsB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync start time stamp blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.7

Field Name : arpTblSyncStartTsB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync start time stamp blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.6

Field Name : macTblSyncStartTsM1st
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync start time stamp master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.5

Field Name : ipv6FibTblSyncStartTsM1st
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync start time stamp master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.4

Field Name : ipv4FibTblSyncStartTsM1st
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync start time stamp master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.3

Field Name : nd6TblSyncStartTsM1st
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync start time stamp master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.2

Field Name : arpTblSyncStartTsM1st
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync start time stamp master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.1

Field Name : usagePercentage
Field Type : CounterBasedGauge64
Field Status : current
Description : Memory Usage percentage
OID : 1.3.6.1.4.1.22610.2.4.10.39.23.1.1

Field Name : cpu100
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-100
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.101

Field Name : cpu99
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-99
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.100

Field Name : cpu98
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-98
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.99

Field Name : cpu97
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-97
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.98

Field Name : cpu96
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-96
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.97

Field Name : cpu95
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-95
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.96

Field Name : cpu94
Field Type : CounterBasedGauge64
Field Status : current

Description : Data CPU-94
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.95

Field Name : cpu93
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-93
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.94

Field Name : cpu92
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-92
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.93

Field Name : cpu91
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-91
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.92

Field Name : cpu90
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-90
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.91

Field Name : cpu89
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-89
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.90

Field Name : cpu88
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-88
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.89

Field Name : cpu87
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-87
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.88

Field Name : cpu86
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-86
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.87

Field Name : cpu85
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-85
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.86

Field Name : cpu84

Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-84
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.85

Field Name : cpu83
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-83
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.84

Field Name : cpu82
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-82
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.83

Field Name : cpu81
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-81
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.82

Field Name : cpu80
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-80
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.81

Field Name : cpu79
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-79
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.80

Field Name : cpu78
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-78
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.79

Field Name : cpu77
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-77
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.78

Field Name : cpu76
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-76
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.77

Field Name : cpu75
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-75
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.76

Field Name : cpu74
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-74
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.75

Field Name : cpu73
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-73
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.74

Field Name : cpu72
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-72
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.73

Field Name : cpu71
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-71
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.72

Field Name : cpu70
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-70
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.71

Field Name : cpu69
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-69
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.70

Field Name : cpu68
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-68
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.69

Field Name : cpu67
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-67
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.68

Field Name : cpu66
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-66
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.67

Field Name : cpu65
Field Type : CounterBasedGauge64
Field Status : current

Description : Data CPU-65
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.66

Field Name : cpu64
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-64
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.65

Field Name : cpu63
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-63
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.64

Field Name : cpu62
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-62
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.63

Field Name : cpu61
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-61
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.62

Field Name : cpu60
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-60
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.61

Field Name : cpu59
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-59
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.60

Field Name : cpu58
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-58
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.59

Field Name : cpu57
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-57
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.58

Field Name : cpu56
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-56
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.57

Field Name : cpu55

Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-55
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.56

Field Name : cpu54
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-54
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.55

Field Name : cpu53
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-53
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.54

Field Name : cpu52
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-52
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.53

Field Name : cpu51
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-51
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.52

Field Name : cpu50
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-50
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.51

Field Name : cpu49
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-49
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.50

Field Name : cpu48
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-48
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.49

Field Name : cpu47
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-47
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.48

Field Name : cpu46
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-46
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.47

Field Name : cpu45
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-45
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.46

Field Name : cpu44
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-44
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.45

Field Name : cpu43
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-43
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.44

Field Name : cpu42
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-42
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.43

Field Name : cpu41
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-41
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.42

Field Name : cpu40
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-40
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.41

Field Name : cpu39
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-39
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.40

Field Name : cpu38
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-38
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.39

Field Name : cpu37
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-37
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.38

Field Name : cpu36
Field Type : CounterBasedGauge64
Field Status : current

Description : Data CPU-36
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.37

Field Name : cpu35
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-35
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.36

Field Name : cpu34
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-34
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.35

Field Name : cpu33
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-33
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.34

Field Name : cpu32
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-32
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.33

Field Name : cpu31
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-31
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.32

Field Name : cpu30
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-30
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.31

Field Name : cpu29
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-29
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.30

Field Name : cpu28
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-28
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.29

Field Name : cpu27
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-27
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.28

Field Name : cpu26

Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-26
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.27

Field Name : cpu25
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-25
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.26

Field Name : cpu24
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-24
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.25

Field Name : cpu23
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-23
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.24

Field Name : cpu22
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-22
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.23

Field Name : cpu21
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-21
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.22

Field Name : cpu20
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-20
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.21

Field Name : cpu19
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-19
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.20

Field Name : cpu18
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-18
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.19

Field Name : cpu17
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-17
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.18

Field Name : cpu16
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-16
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.17

Field Name : cpu15
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-15
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.16

Field Name : cpu14
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-14
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.15

Field Name : cpu13
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-13
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.14

Field Name : cpu12
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-12
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.13

Field Name : cpu11
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-11
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.12

Field Name : cpu10
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-10
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.11

Field Name : cpu9
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-9
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.10

Field Name : cpu8
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-8
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.9

Field Name : cpu7
Field Type : CounterBasedGauge64
Field Status : current

Description : Data CPU-7
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.8

Field Name : cpu6
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-6
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.7

Field Name : cpu5
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-5
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.6

Field Name : cpu4
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-4
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.5

Field Name : cpu3
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-3
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.4

Field Name : cpu2
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-2
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.3

Field Name : cpu1
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-1
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.2

Field Name : dataCpuNumber
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of data cpus
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.1

Field Name : cpu64
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-64
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.65

Field Name : cpu63
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-63
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.64

Field Name : cpu62

Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-62
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.63

Field Name : cpu61
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-61
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.62

Field Name : cpu60
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-60
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.61

Field Name : cpu59
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-59
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.60

Field Name : cpu58
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-58
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.59

Field Name : cpu57
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-57
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.58

Field Name : cpu56
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-56
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.57

Field Name : cpu55
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-55
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.56

Field Name : cpu54
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-54
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.55

Field Name : cpu53
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-53
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.54

Field Name : cpu52
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-52
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.53

Field Name : cpu51
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-51
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.52

Field Name : cpu50
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-50
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.51

Field Name : cpu49
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-49
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.50

Field Name : cpu48
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-48
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.49

Field Name : cpu47
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-47
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.48

Field Name : cpu46
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-46
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.47

Field Name : cpu45
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-45
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.46

Field Name : cpu44
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-44
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.45

Field Name : cpu43
Field Type : CounterBasedGauge64
Field Status : current

Description : Control CPU-43
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.44

Field Name : cpu42
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-42
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.43

Field Name : cpu41
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-41
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.42

Field Name : cpu40
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-40
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.41

Field Name : cpu39
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-39
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.40

Field Name : cpu38
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-38
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.39

Field Name : cpu37
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-37
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.38

Field Name : cpu36
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-36
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.37

Field Name : cpu35
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-35
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.36

Field Name : cpu34
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-34
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.35

Field Name : cpu33

Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-33
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.34

Field Name : cpu32
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-32
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.33

Field Name : cpu31
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-31
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.32

Field Name : cpu30
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-30
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.31

Field Name : cpu29
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-29
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.30

Field Name : cpu28
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-28
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.29

Field Name : cpu27
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-27
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.28

Field Name : cpu26
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-26
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.27

Field Name : cpu25
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-25
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.26

Field Name : cpu24
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-24
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.25

Field Name : cpu23
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-23
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.24

Field Name : cpu22
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-22
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.23

Field Name : cpu21
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-21
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.22

Field Name : cpu20
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-20
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.21

Field Name : cpu19
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-19
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.20

Field Name : cpu18
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-18
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.19

Field Name : cpu17
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-17
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.18

Field Name : cpu16
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-16
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.17

Field Name : cpu15
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-15
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.16

Field Name : cpu14
Field Type : CounterBasedGauge64
Field Status : current

Description : Control CPU-14
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.15

Field Name : cpu13
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-13
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.14

Field Name : cpu12
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-12
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.13

Field Name : cpu11
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-11
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.12

Field Name : cpu10
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-10
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.11

Field Name : cpu9
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-9
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.10

Field Name : cpu8
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-8
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.9

Field Name : cpu7
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-7
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.8

Field Name : cpu6
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-6
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.7

Field Name : cpu5
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-5
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.6

Field Name : cpu4

Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-4
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.5

Field Name : cpu3
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-3
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.4

Field Name : cpu2
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-2
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.3

Field Name : cpu1
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-1
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.2

Field Name : ctrlCpuNumber
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of ctrl cpus
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.1

Field Name : totalMemblocksReallocAvro
Field Type : CounterBasedGauge64
Field Status : current
Description : Total memory blocks realloc by avro lib
OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.17

Field Name : totalMemblocksFreeAvro
Field Type : CounterBasedGauge64
Field Status : current
Description : Total memory blocks freed by avro lib
OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.16

Field Name : totalMemblocksAllocAvro
Field Type : CounterBasedGauge64
Field Status : current
Description : Total memory blocks allocated by avro lib
OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.15

Field Name : totalNodesInSystem
Field Type : CounterBasedGauge64
Field Status : current
Description : Total nodes currently allocated in system
OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.14

Field Name : totalNodesUnlinkFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total nodes unlink failed
OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.13

Field Name : totalNodesFreeFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total nodes free failed
OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.12

Field Name : totalNodesFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Total nodes freed(sflow/history/telemetry/cpu-compute)
OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.11

Field Name : totalNodesInRml
Field Type : CounterBasedGauge64
Field Status : current
Description : Total nodes put in rml queue
OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.10

Field Name : totalNodesAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Total nodes allocated(sflow/history/telemetry/cpu-compute)
OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.9

Field Name : totalBlocksInRmlHash
Field Type : CounterBasedGauge64
Field Status : current
Description : Total blocks in rml in hash table
OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.8

Field Name : totalBlocksInHash
Field Type : CounterBasedGauge64
Field Status : current
Description : Total blocks in hash table
OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.7

Field Name : totalOperFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Total oper blocks freed
OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.6

Field Name : totalOperAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Total oper blocks allocated
OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.5

Field Name : totalCtrInSystem
Field Type : CounterBasedGauge64
Field Status : current
Description : Total counters currently allocated in system
OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.4

Field Name : totalCtrFreed
Field Type : CounterBasedGauge64
Field Status : current

Description : Total counters actually freed
OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.3

Field Name : totalCtrInRml
Field Type : CounterBasedGauge64
Field Status : current
Description : Total counters put in rml queue
OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.2

Field Name : totalCtrAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Total counters allocated
OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.1

Field Name : bwlDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : BW Limit Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.4.1.7

Field Name : licexpireDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : License Expire Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.4.1.6

Field Name : ppslIgnoreLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet-Per-Sec Limit ignored packets count
OID : 1.3.6.1.4.1.22610.2.4.10.39.4.1.5

Field Name : ppslDropIng
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet-Per-Sec Limit Drop at ingress
OID : 1.3.6.1.4.1.22610.2.4.10.39.4.1.4

Field Name : ppslDropEgr
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet-Per-Sec Limit Drop at egress
OID : 1.3.6.1.4.1.22610.2.4.10.39.4.1.3

Field Name : outputBytesPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Bytes per second
OID : 1.3.6.1.4.1.22610.2.4.10.39.4.1.2

Field Name : inputBytesPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : In Bytes per second
OID : 1.3.6.1.4.1.22610.2.4.10.39.4.1.1

Field Name : currEntriesTargetGlobalDnsCache

Field Type : CounterBasedGauge64
Field Status : current
Description : Current Entry Target Global DNS Cache
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.18

Field Name : currEntriesStats
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Entry Stats Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.17

Field Name : currEntriesTargetService
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Entry Target Service
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.16

Field Name : currEntriesTargetRport
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Entry Target Rport
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.15

Field Name : currEntriesTargetRserver
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Entry Target Rserver
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.14

Field Name : currEntriesTargetLOC
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Entry Target LOC
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.13

Field Name : currEntriesTargetVport
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Entry Target Vport
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.12

Field Name : currEntriesTargetVserver
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Entry Target Vserver
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.11

Field Name : currEntriesTargetGlobal
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Entry Target Global
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.10

Field Name : totalDirectActionEntriesFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Direct Action Entry Count Freed
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.9

Field Name : totalDirectActionEntriesCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Direct Action Entry Count Created
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.8

Field Name : totalDomainEntriesFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Domain Entry Count Freed
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.7

Field Name : totalDomainEntriesCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Domain Entry Count Created
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.6

Field Name : totalV6EntriesFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total V6 Entry Count Freed
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.5

Field Name : totalV6EntriesCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total V6 Entry Count Created
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.4

Field Name : totalV4EntriesFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total V4 Entry Count Freed
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.3

Field Name : totalV4EntriesCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total V4 Entry Count Created
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.2

Field Name : currEntries
Field Type : CounterBasedGauge64
Field Status : current
Description : Current PBSLB Entry Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.1

Field Name : ngwafHcMetricsTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : NGWAF HC metrics export failed
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.86

Field Name : ngwafHcMetricsTopic
Field Type : CounterBasedGauge64
Field Status : current

Description : NGWAF HC metrics export
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.85

Field Name : ngwafHcEpTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : NGWAF HC PE export failed
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.84

Field Name : ngwafHcEpTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : NGWAF HC PE export
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.83

Field Name : certPinningListTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Cert-pinning candidate list dropped,enq error analytics queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.82

Field Name : certPinningListTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : Cert-pinning candidate list sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.81

Field Name : avroSystemEnvDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : System Environmet dropped,enq error analytics queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.80

Field Name : avroSystemEnvTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : System environment sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.79

Field Name : cgnPortUsageHstgrmAcosHarmonyTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : CGN Port Usage Histogram HC Export Failed
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.78

Field Name : cgnPortUsageHstgrmAcosHarmonyTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : CGN Port Usage Histogram HC Export
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.77

Field Name : vpnStatsMetricsTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : VPN STATS metrics dropped,enq error analytics qs
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.76

Field Name : vpnStatsMetricsTopic

Field Type : CounterBasedGauge64
Field Status : current
Description : VPN STATS metrics sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.75

Field Name : vpnIkeGatewayMetricsTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : IKE gateway metrics dropped,enq error analytics qs
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.74

Field Name : vpnIkeGatewayMetricsTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : IKE gateway metrics sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.73

Field Name : vpnIpsecSaMetricsTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : IPSec SA metrics dropped,enq error analytics qs
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.72

Field Name : vpnIpsecSaMetricsTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : IPSec SA metrics sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.71

Field Name : peAcosHarmonyTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 PE dropped,enq error analytics queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.70

Field Name : peAcosHarmonyTopicEnqueueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 PE dropped,enq error on acos queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.69

Field Name : peAcosHarmonyTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 PE logs sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.68

Field Name : hcCountersDroppedFromBlade
Field Type : CounterBasedGauge64
Field Status : current
Description : HC counters dropped from blade (uuid or size mismatch)
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.67

Field Name : hcCountersReceivedFromBlade
Field Type : CounterBasedGauge64
Field Status : current
Description : HC counters received from blade
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.66

Field Name : hcCountersSentToMaster
Field Type : CounterBasedGauge64
Field Status : current
Description : HC counters sent to master
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.65

Field Name : hcOperReceivedFromBlade
Field Type : CounterBasedGauge64
Field Status : current
Description : HC oper received from blade
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.64

Field Name : hcOperSentToMaster
Field Type : CounterBasedGauge64
Field Status : current
Description : HC oper to master
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.63

Field Name : hcLogsReceivedFromBlade
Field Type : CounterBasedGauge64
Field Status : current
Description : HC logs received from blade
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.62

Field Name : hcLogsSentToMaster
Field Type : CounterBasedGauge64
Field Status : current
Description : HC logs sent to master
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.61

Field Name : visibilityTopnHarmonyTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Visibility TopN metrics dropped,enq error analytics qs
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.60

Field Name : visibilityTopnHarmonyTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : Visibility TopN sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.59

Field Name : wafEventsTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF events metrics dropped,enq error analytics qs
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.58

Field Name : wafEventsTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF events topic counter
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.57

Field Name : wafLearnPrTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current

Description : WAF learn metrics dropped,enq error analytics qs
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.56

Field Name : wafLearnPrTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF learn topic counter
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.55

Field Name : analyticsBusRestart
Field Type : CounterBasedGauge64
Field Status : current
Description : Analytics bus restart count
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.54

Field Name : ssliPeAcosHarmonyTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : SSLi PE topic to harmony dequeue error
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.53

Field Name : ssliPeAcosHarmonyTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : SSLi PE topic counter from acos to harmony
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.52

Field Name : ssliPcAcosHarmonyTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : SSLi PC topic to harmony dequeue error
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.51

Field Name : ssliPcAcosHarmonyTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : SSLi PC topic counter from acos to harmony
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.50

Field Name : metricsDroppedPtMissing
Field Type : CounterBasedGauge64
Field Status : current
Description : Metrics dropped,missing partition tenant mapping
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.49

Field Name : pcThrottleDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 PC logs dropped,throttling
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.48

Field Name : slbServerSslCountersMetricsTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Server SSL metrics dropped,enq error analytics qs
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.47

Field Name : slbServerSslCountersMetricsTopic

Field Type : CounterBasedGauge64
Field Status : current
Description : Server SSL metrics sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.46

Field Name : slbClientSslCountersMetricsTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Cilent SSL metrics dropped,enq error analytics qs
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.45

Field Name : slbClientSslCountersMetricsTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : Client SSL metrics sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.44

Field Name : slbSslStatsMetricsTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL metrics dropped,enq error analytics queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.43

Field Name : slbSslStatsMetricsTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL metrics sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.42

Field Name : ruleSetApplicationMetricsTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : AppFW metrics dropped,enq error analytics queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.41

Field Name : ruleSetApplicationMetricsTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : AppFW metrics sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.40

Field Name : cgnSummaryErrorAcosHarmonyTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : CGN PE logs dropped,enq error analytics queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.39

Field Name : cgnSummaryErrorAcosHarmonyTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : CGN PE logs sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.38

Field Name : fwRstPcAcosHarmonyTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : FW RST PC logs dropped,enq error analytics queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.37

Field Name : fwRstPcAcosHarmonyTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : FW RST PC logs sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.36

Field Name : fwDenyPcAcosHarmonyTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : FW DENY PC logs dropped,enq error analytics queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.35

Field Name : fwDenyPcAcosHarmonyTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : FW DENY PC logs sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.34

Field Name : fwPcAcosHarmonyTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : FW PC logs dropped,enq error analytics queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.33

Field Name : fwPcAcosHarmonyTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : FW PC logs sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.32

Field Name : cgnPeAcosHarmonyTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : CGN PE logs dropped,enq error analytics queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.31

Field Name : cgnPeAcosHarmonyTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : CGN PE logs sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.30

Field Name : cgnPcAcosHarmonyTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : CGN PC logs dropped,enq error analytics queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.29

Field Name : cgnPcAcosHarmonyTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : CGN PC logs sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.28

Field Name : pcAcosHarmonyTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current

Description : L4 PC logs dropped,enq error analytics queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.27

Field Name : pcAcosHarmonyTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 PC logs sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.26

Field Name : pcEncodingFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 PC logs dropped,encoding error
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.25

Field Name : kafkaTopicError
Field Type : CounterBasedGauge64
Field Status : current
Description : Module not supported by analytics
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.24

Field Name : prInLatencyAnomaly
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 PR on latency negative
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.23

Field Name : prOutLatencyAnomaly
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 PR out latency negative
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.22

Field Name : prOutLatencyThresholdExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 PR out latency threshold exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.21

Field Name : prInLatencyThresholdExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 PR on latency threshold exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.20

Field Name : prBeTtlbAnomaly
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 PR back-end ttlb is negative
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.19

Field Name : prBeTtfbAnomaly
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 PR back-end ttfb is negative
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.18

Field Name : prNotAllowedDrop

Field Type : CounterBasedGauge64
Field Status : current
Description : L7 PR dropped, not allowed to be sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.17

Field Name : prThrottleDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 PR dropped,log throttling
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.16

Field Name : kafkaQueueFullErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages dropped,acos analytics queue full
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.15

Field Name : kafkaBrokerDown
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages dropped,analytics down
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.14

Field Name : kafkaUnknownTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Unknown type dropped,enq error analytics queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.13

Field Name : avroPartitionMetricsTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Part metrics dropped,enq error analytics queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.12

Field Name : avroPartitionMetricsTopicEnqueueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Part metrics dropped,enq error on acos queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.11

Field Name : avroDeviceStatusTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Device Status dropped,enq error analytics queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.10

Field Name : avroDeviceStatusTopicEnqueueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Device Status dropped,enq error on acos queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.9

Field Name : avroGenericFailedSending
Field Type : CounterBasedGauge64
Field Status : current
Description : Generic Metrics dropped,sending failure
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.8

Field Name : avroGenericFailedEncoding
Field Type : CounterBasedGauge64
Field Status : current
Description : Generic Metrics dropped,encoding error
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.7

Field Name : prAcosHarmonyTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 PR dropped,enq error analytics queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.6

Field Name : prAcosHarmonyTopicEnqueueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 PR dropped,enq error on acos queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.5

Field Name : avroGenericSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Generic Metrics sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.4

Field Name : avroPartitionMetricsTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : Partition Metrics sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.3

Field Name : avroDeviceStatusTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : Device Status Metrics sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.2

Field Name : prAcosHarmonyTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 PR logs sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.1

Field Name : ipFragFirstGTPPacketTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : First GTP Fragment Too Small Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.47

Field Name : ipFragSctpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.46

Field Name : ipFragSctpRcv
Field Type : CounterBasedGauge64
Field Status : current

Description : SCTP Received
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.45

Field Name : fragSessionCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragmentation Session Count
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.44

Field Name : ipFragSessionPacketsExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Max Packets Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.43

Field Name : ipFragMaxPacketsExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Too Many Packets Per Reassembly Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.42

Field Name : ipdEntryDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DDoS Protection Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.41

Field Name : cpuThresholdDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : High CPU Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.40

Field Name : lowCpuThreshold
Field Type : CounterBasedGauge64
Field Status : current
Description : Low CPU Threshold Reached
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.39

Field Name : highCpuThreshold
Field Type : CounterBasedGauge64
Field Status : current
Description : High CPU Threshold Reached
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.38

Field Name : ipFragErrorDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Processing Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.37

Field Name : ipFragPolicyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : MTU Exceeded Policy Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.36

Field Name : ipFragReassemblyFailure

Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Reassembly Failure
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.35

Field Name : ipFragMaxLenExeeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Max Data Length Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.34

Field Name : ipFragReassemblySucess
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Reassembly Success
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.33

Field Name : ipFragFramentQueueFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Queue Failure
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.32

Field Name : ipFragTotalFragmentsExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Queued Fragments Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.31

Field Name : ipFragDuplicateLastFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : Duplicate Last Fragment
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.30

Field Name : ipFragDuplicateFirstFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : Duplicate First Fragment
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.29

Field Name : ipFragExceededLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Payload Length Out of Bounds
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.28

Field Name : ipFragUnalignedLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Payload Length Unaligned
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.27

Field Name : ipFragFramentQueueSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Queue Success
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.26

Field Name : ipFragFastAgingUnset
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragmentation Fast Aging Unset
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.25

Field Name : ipFragFastAgingSet
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragmentation Fast Aging Set
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.24

Field Name : ipFragNoSessionMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of Session Memory
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.23

Field Name : ipFragTotalSessionsExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Sessions Exceeded Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.22

Field Name : ipFragFirstL4TooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : First L4 Fragment Too Small Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.21

Field Name : ipFragFirstTcpTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : First TCP Fragment Too Small Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.20

Field Name : ipFragTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Too Small Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.19

Field Name : iipFragBadIpLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad IP Length
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.18

Field Name : ipFragOverlapError
Field Type : CounterBasedGauge64
Field Status : current
Description : Overlapping Fragment Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.17

Field Name : ipFragOtherDropped
Field Type : CounterBasedGauge64
Field Status : current

Description : Other Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.16

Field Name : ipFragIpv6ipDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6-in-IP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.15

Field Name : ipFragIpipDroped
Field Type : CounterBasedGauge64
Field Status : current
Description : IP-in-IP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.14

Field Name : ipFragTcpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.13

Field Name : ipFragUdpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.12

Field Name : ipFragIcmpv6Dropped
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.11

Field Name : ipFragIcmpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.10

Field Name : ipFragOtherRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : Other Received
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.9

Field Name : ipFragIpv6ipRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6-in-IP Received
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.8

Field Name : ipFragIpipRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : IP-in-IP Received
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.7

Field Name : ipFragTcpRcv

Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Received
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.6

Field Name : ipFragUdpRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Received
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.5

Field Name : ipFragIcmpv6Rcv
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 Received
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.4

Field Name : ipFragIcmpRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Received
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.3

Field Name : ipFragSessionExpired
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Expired
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.2

Field Name : ipFragSessionInsert
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.1

Field Name : ipv6EhMalformed
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Malformed Extension Header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.48

Field Name : ipv6EhOther
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Unknown Extension Header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.47

Field Name : ipv6EhNone
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 No Next Header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.46

Field Name : ipv6EhMobility
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Mobility Header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.45

Field Name : ipv6EhEsp
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 ESP Header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.44

Field Name : ipv6EhAh
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Authentication Header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.43

Field Name : ipv6EhFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Fragmentation Header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.42

Field Name : ipv6EhRouting
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Routing Header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.41

Field Name : ipv6EhDest
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Destination Header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.40

Field Name : ipv6EhHbh
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Hop by Hop Header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.39

Field Name : grePptpErr
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE PPTP Error Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.38

Field Name : nvgreErr
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Tunnel Error Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.37

Field Name : vxlanErr
Field Type : CounterBasedGauge64
Field Status : current
Description : VXLAN Tunnel Error Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.36

Field Name : ipipTnlErr
Field Type : CounterBasedGauge64
Field Status : current

Description : IP-over-IP Tunnel Error Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.35

Field Name : tcpOptErr
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Option Error Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.34

Field Name : ipipTnlMsmtch
Field Type : CounterBasedGauge64
Field Status : current
Description : IP-over-IP Tunnel Mismatch Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.33

Field Name : runtTcpUdpHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : Runt TCP/UDP Header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.32

Field Name : runtIpHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : Runt IP Header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.31

Field Name : udpBadCsum
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Bad Checksum Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.30

Field Name : udpPortLb
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Loopback Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.29

Field Name : udpKerbFrg
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Kerberos Fragment Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.28

Field Name : udpBadLen
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Bad Length Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.27

Field Name : udpSrtHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Short Header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.26

Field Name : tcpBadCsum

Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Bad Checksum Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.25

Field Name : tcpFrgHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Fragmented Header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.24

Field Name : tcpSynFrg
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Syn Fragment Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.23

Field Name : tcpXmasScan
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP XMAS Scan Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.22

Field Name : tcpXmas
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP XMAS Flags Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.21

Field Name : tcpSynFin
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Syn and Fin Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.20

Field Name : tcpNullScan
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Null Scan Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.19

Field Name : tcpNullFrg
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Null Flags Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.18

Field Name : tcpBadIplen
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Bad IP Length Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.17

Field Name : tcpShtHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Short Header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.16

Field Name : badTcpUrgOffset
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Bad Urgent Offset Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.15

Field Name : pod
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Ping of Death Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.14

Field Name : csum
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad IP Checksum Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.13

Field Name : badIpFrgOffset
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad IP Fragment Offset Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.12

Field Name : badIpPayloadLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad IP Payload Len Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.11

Field Name : overIpPayload
Field Type : CounterBasedGauge64
Field Status : current
Description : Oversize IP Payload Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.10

Field Name : noIpPayload
Field Type : CounterBasedGauge64
Field Status : current
Description : No IP Payload drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.9

Field Name : badIpTtl
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad IP TTL Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.8

Field Name : badIpFlg
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad IP Flags Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.7

Field Name : badIpHdrlen
Field Type : CounterBasedGauge64
Field Status : current

Description : Bad IP Header Len Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.6

Field Name : frg
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Fragment Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.5

Field Name : opt
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Options Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.4

Field Name : empMicFrg
Field Type : CounterBasedGauge64
Field Status : current
Description : Micro Fragment Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.3

Field Name : empFrg
Field Type : CounterBasedGauge64
Field Status : current
Description : Empty Fragment Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.2

Field Name : land
Field Type : CounterBasedGauge64
Field Status : current
Description : Land Attack Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.1

Field Name : ipNatPoolGroupSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.3.1.1

Field Name : ipNatPoolGroupSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.3.1.1.1

Field Name : Failed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.3.1.1.1.2

Field Name : poolGroupName
Field Type : String
Field Status : current
Description : Specify pool group name
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.3.1.1.1.1

Field Name : ipNatPoolSTable

Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.2.1.1

Field Name : ipNatPoolSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.2.1.1.1

Field Name : ipNatPoolFailed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.2.1.1.1.5

Field Name : ipNatPoolTotalFreed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.2.1.1.1.4

Field Name : ipNatPoolTotalUsed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.2.1.1.1.3

Field Name : ipNatPoolPortUsage
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.2.1.1.1.2

Field Name : ipNatPoolName
Field Type : String
Field Status : current
Description : Specify pool name or pool group
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.2.1.1.1.1

Field Name : crossCpuHelperFreeNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Free Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.1.1.12

Field Name : crossCpuHelperFreeRetryLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Free Retry Lookup
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.1.1.11

Field Name : crossCpuHelperDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.1.1.10

Field Name : crossCpuNoSession
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU No Session Found
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.1.1.9

Field Name : crossCpuBadL4
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Unsupported L4
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.1.1.8

Field Name : crossCpuBadL3
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Unsupported L3
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.1.1.7

Field Name : crossCpuHelperCpuMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper CPU Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.1.1.6

Field Name : crossCpuHelperNatPoolStandby
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Standby
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.1.1.5

Field Name : crossCpuRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Packets Received
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.1.1.4

Field Name : crossCpuSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Packets Sent
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.1.1.3

Field Name : crossCpuHelperFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Free
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.1.1.2

Field Name : crossCpuHelperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Created
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.1.1.1

Field Name : noMatchingGreSession
Field Type : CounterBasedGauge64
Field Status : current

Description :
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.9.1.1.12

Field Name : unknownGreVersion
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.9.1.1.11

Field Name : truncatedGrePacket
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.9.1.1.10

Field Name : retransmittedPacMessage
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.9.1.1.9

Field Name : retransmittedPnsMessage
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.9.1.1.8

Field Name : mismatchedPacCallId
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.9.1.1.7

Field Name : mismatchedPnsCallId
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.9.1.1.6

Field Name : truncatedPacMessage
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.9.1.1.5

Field Name : truncatedPnsMessage
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.9.1.1.4

Field Name : smpSessionCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.9.1.1.3

Field Name : currentGreSessions

Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.9.1.1.2

Field Name : currentSmpSessions
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.9.1.1.1

Field Name : hcPktDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet drop due to health check
OID : 1.3.6.1.4.1.22610.2.4.10.56.24.1.4

Field Name : vlanPairUpdate
Field Type : CounterBasedGauge64
Field Status : current
Description : VLAN pair update
OID : 1.3.6.1.4.1.22610.2.4.10.56.24.1.3

Field Name : macUpdate
Field Type : CounterBasedGauge64
Field Status : current
Description : MAC update
OID : 1.3.6.1.4.1.22610.2.4.10.56.24.1.2

Field Name : vlanUpdate
Field Type : CounterBasedGauge64
Field Status : current
Description : VLAN update
OID : 1.3.6.1.4.1.22610.2.4.10.56.24.1.1

Field Name : networkVirtualWireHealthCheckSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.56.28.1.1

Field Name : networkVirtualWireHealthCheckSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.56.28.1.1.1

Field Name : packetCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet Count
OID : 1.3.6.1.4.1.22610.2.4.10.56.28.1.1.1.4

Field Name : sbyEvent
Field Type : CounterBasedGauge64
Field Status : current
Description : Standby Event Count
OID : 1.3.6.1.4.1.22610.2.4.10.56.28.1.1.1.3

Field Name : actEvent
Field Type : CounterBasedGauge64
Field Status : current
Description : Active Event Count
OID : 1.3.6.1.4.1.22610.2.4.10.56.28.1.1.1.2

Field Name : vlan
Field Type : INTEGER
Field Status : current
Description : VLAN ID, specify 1 for untagged traffic
OID : 1.3.6.1.4.1.22610.2.4.10.56.28.1.1.1.1

Field Name : asymmetricRouteDropErr
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.56.9.1.2

Field Name : xparentVlanListErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Transparent Mode VLAN List Errors
OID : 1.3.6.1.4.1.22610.2.4.10.56.9.1.1

Field Name : networkVlanSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.56.4.1.1

Field Name : networkVlanSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.56.4.1.1.1

Field Name : sharedVlanPartitionSwitchedCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : SVLAN Partition switched counter
OID : 1.3.6.1.4.1.22610.2.4.10.56.4.1.1.1.7

Field Name : macMovementCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Mac Movement counter
OID : 1.3.6.1.4.1.22610.2.4.10.56.4.1.1.1.6

Field Name : unknownUnicastCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Unknown Unicast counter
OID : 1.3.6.1.4.1.22610.2.4.10.56.4.1.1.1.5

Field Name : ipMulticastCount
Field Type : CounterBasedGauge64
Field Status : current

Description : IP Multicast counter
OID : 1.3.6.1.4.1.22610.2.4.10.56.4.1.1.1.4

Field Name : multicastCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Multicast counter
OID : 1.3.6.1.4.1.22610.2.4.10.56.4.1.1.1.3

Field Name : broadcastCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Broadcast counter
OID : 1.3.6.1.4.1.22610.2.4.10.56.4.1.1.1.2

Field Name : vlanNum
Field Type : INTEGER
Field Status : current
Description : VLAN number
OID : 1.3.6.1.4.1.22610.2.4.10.56.4.1.1.1.1

Field Name : otherErr
Field Type : CounterBasedGauge64
Field Status : current
Description : IP other error drop
OID : 1.3.6.1.4.1.22610.2.4.10.56.20.1.2.1.7

Field Name : noRouteErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Tx IP no route error drop
OID : 1.3.6.1.4.1.22610.2.4.10.56.20.1.2.1.6

Field Name : twampHdrLenErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Rx TWAMP hdr length error drop
OID : 1.3.6.1.4.1.22610.2.4.10.56.20.1.2.1.5

Field Name : rxAclDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Rx IP client-list drop
OID : 1.3.6.1.4.1.22610.2.4.10.56.20.1.2.1.4

Field Name : rxDropNotEnabledV4
Field Type : CounterBasedGauge64
Field Status : current
Description : Rx IP disabled drop
OID : 1.3.6.1.4.1.22610.2.4.10.56.20.1.2.1.3

Field Name : txPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Tx IP TWAMP test packets
OID : 1.3.6.1.4.1.22610.2.4.10.56.20.1.2.1.2

Field Name : rxPkts

Field Type : CounterBasedGauge64
Field Status : current
Description : Rx IP TWAMP test packets
OID : 1.3.6.1.4.1.22610.2.4.10.56.20.1.2.1.1

Field Name : otherErrV6
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Other error drop
OID : 1.3.6.1.4.1.22610.2.4.10.56.20.1.3.1.14

Field Name : noRouteErrV6
Field Type : CounterBasedGauge64
Field Status : current
Description : Tx IPv6 no route error drop
OID : 1.3.6.1.4.1.22610.2.4.10.56.20.1.3.1.13

Field Name : twampHdrLenErrV6
Field Type : CounterBasedGauge64
Field Status : current
Description : Rx IPv6 TWAMP hdr length error drop
OID : 1.3.6.1.4.1.22610.2.4.10.56.20.1.3.1.12

Field Name : rxAclDropV6
Field Type : CounterBasedGauge64
Field Status : current
Description : Rx IPv6 client-list drop
OID : 1.3.6.1.4.1.22610.2.4.10.56.20.1.3.1.11

Field Name : rxDropNotEnabledV6
Field Type : CounterBasedGauge64
Field Status : current
Description : Rx IPv6 disabled drop
OID : 1.3.6.1.4.1.22610.2.4.10.56.20.1.3.1.10

Field Name : txPktsV6
Field Type : CounterBasedGauge64
Field Status : current
Description : Tx IPv6 TWAMP test packets
OID : 1.3.6.1.4.1.22610.2.4.10.56.20.1.3.1.9

Field Name : rxPktsV6
Field Type : CounterBasedGauge64
Field Status : current
Description : Rx IPv6 TWAMP test packets
OID : 1.3.6.1.4.1.22610.2.4.10.56.20.1.3.1.8

Field Name : ipFragFirstGTPPacketTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : First GTP Fragment Too Small Drop
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.47

Field Name : ipv6FragSctpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.46

Field Name : ipv6FragSctpRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Received
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.45

Field Name : fragSessionCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragmentation Session Count
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.44

Field Name : ipv6FragSessionPacketsExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Max Packets Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.43

Field Name : ipv6FragMaxPacketsExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Too Many Packets Per Reassembly Drop
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.42

Field Name : ipdEntryDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DDoS Protection Drop
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.41

Field Name : cpuThresholdDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : High CPU Drop
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.40

Field Name : lowCpuThreshold
Field Type : CounterBasedGauge64
Field Status : current
Description : Low CPU Threshold Reached
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.39

Field Name : highCpuThreshold
Field Type : CounterBasedGauge64
Field Status : current
Description : High CPU Threshold Reached
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.38

Field Name : ipv6FragErrorDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Processing Drop
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.37

Field Name : ipv6FragPolicyDrop
Field Type : CounterBasedGauge64
Field Status : current

Description : MTU Exceeded Policy Drop
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.36

Field Name : ipv6FragReassemblyFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Reassembly Failure
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.35

Field Name : ipv6FragMaxLenExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Max Data Length Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.34

Field Name : ipv6FragReassemblySuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Reassembly Success
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.33

Field Name : ipv6FragFragmentQueueFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Queue Failure
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.32

Field Name : ipv6FragTotalFragmentsExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Queued Fragments Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.31

Field Name : ipv6FragDuplicateLastFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : Duplicate Last Fragment
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.30

Field Name : ipv6FragDuplicateFirstFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : Duplicate First Fragment
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.29

Field Name : ipv6FragExceededLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Payload Length Out of Bounds
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.28

Field Name : ipv6FragUnalignedLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Payload Length Unaligned
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.27

Field Name : ipv6FragFragmentQueueSuccess

Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Queue Success
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.26

Field Name : ipv6FragFastAgingUnset
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragmentation Fast Aging Unset
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.25

Field Name : ipv6FragFastAgingSet
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragmentation Fast Aging Set
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.24

Field Name : ipv6FragNoSessionMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of Session Memory
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.23

Field Name : ipv6FragTotalSessionsExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Sessions Exceeded Drop
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.22

Field Name : ipv6FragFirstL4TooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : First L4 Fragment Too Small Drop
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.21

Field Name : ipv6FragFirstTcpTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : First TCP Fragment Too Small Drop
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.20

Field Name : ipv6FragTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Too Small Drop
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.19

Field Name : ipv6FragBadIpLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad IP Length
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.18

Field Name : ipv6FragOverlapError
Field Type : CounterBasedGauge64
Field Status : current
Description : Overlapping Fragment Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.17

Field Name : ipv6FragOtherDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Other Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.16

Field Name : ipv6FragIpv6ipDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6-in-IP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.15

Field Name : ipv6FragIpipDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : IP-in-IP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.14

Field Name : ipv6FragTcpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.13

Field Name : ipv6FragUdpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.12

Field Name : ipv6FragIcmpv6Dropped
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.11

Field Name : ipv6FragIcmpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.10

Field Name : ipv6FragOtherRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : Other Received
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.9

Field Name : ipv6FragIpv6ipRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6-in-IP Received
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.8

Field Name : ipv6FragIpipRcv
Field Type : CounterBasedGauge64
Field Status : current

Description : IP-in-IP Received
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.7

Field Name : ipv6FragTcpRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Received
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.6

Field Name : ipv6FragUdpRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Received
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.5

Field Name : ipv6FragIcmpv6Rcv
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 Received
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.4

Field Name : ipv6FragIcmpRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Received
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.3

Field Name : ipv6FragSessionExpired
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Expired
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.2

Field Name : ipv6FragSessionInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.1

Field Name : ipv6NatPoolSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.57.9.1.1.1

Field Name : ipv6NatPoolSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.57.9.1.1.1.1

Field Name : failed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.57.9.1.1.1.1.5

Field Name : totalFreed

Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.57.9.1.1.1.1.4

Field Name : totalUsed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.57.9.1.1.1.1.3

Field Name : portUsage
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.57.9.1.1.1.1.2

Field Name : poolName
Field Type : String
Field Status : current
Description : Specify pool name
OID : 1.3.6.1.4.1.22610.2.4.10.57.9.1.1.1.1.1

Field Name : ipv6NatPoolGroupSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.57.9.2.1.1

Field Name : ipv6NatPoolGroupSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.57.9.2.1.1.1

Field Name : Failed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.57.9.2.1.1.1.2

Field Name : poolGroupName
Field Type : String
Field Status : current
Description : Specify pool group name
OID : 1.3.6.1.4.1.22610.2.4.10.57.9.2.1.1.1.1

Field Name : hcObjAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Send failed to HC, Out of Memory
OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.17

Field Name : objMetricDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Object metric node deleted
OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.16

Field Name : objMoveToDelq
Field Type : CounterBasedGauge64
Field Status : current
Description : Total object node moved to delq
OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.15

Field Name : objMetricRegOom
Field Type : CounterBasedGauge64
Field Status : current
Description : Total object Metric node alloc failed Out of Memory
OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.14

Field Name : objMetricRegSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total object Metric node allocated
OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.13

Field Name : heapMetricDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Heap metric node deleted
OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.12

Field Name : heapMoveToDelq
Field Type : CounterBasedGauge64
Field Status : current
Description : Total heap node moved to delq
OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.11

Field Name : heapMetricAllocOom
Field Type : CounterBasedGauge64
Field Status : current
Description : Total heap metric node alloc failed Out of Memory
OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.10

Field Name : heapMetricAllocSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total heap metric node allocated
OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.9

Field Name : objDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Object node deleted
OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.8

Field Name : heapDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Heap node deleted
OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.7

Field Name : objRegOom
Field Type : CounterBasedGauge64
Field Status : current

Description : Total object node alloc failed Out of Memory
OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.6

Field Name : objRegFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total object node alloc failed
OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.5

Field Name : objRegSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total object node allocated
OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.4

Field Name : heapAllocOom
Field Type : CounterBasedGauge64
Field Status : current
Description : Total heap node alloc failed Out of Memory
OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.3

Field Name : heapAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total heap node alloc failed
OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.2

Field Name : heapAllocSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total heap node allocated
OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.1

Field Name : unknownDir
Field Type : CounterBasedGauge64
Field Status : current
Description : sflow sample direction is unknown
OID : 1.3.6.1.4.1.22610.2.4.10.169.6.1.1.5

Field Name : versionNotSupported
Field Type : CounterBasedGauge64
Field Status : current
Description : sflow version not supported
OID : 1.3.6.1.4.1.22610.2.4.10.169.6.1.1.4

Field Name : agentNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : sflow pkts from not configured agents
OID : 1.3.6.1.4.1.22610.2.4.10.169.6.1.1.3

Field Name : fragDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Total sflow fragment packets droppped
OID : 1.3.6.1.4.1.22610.2.4.10.169.6.1.1.2

Field Name : pktsReceived

Field Type : CounterBasedGauge64
Field Status : current
Description : Total sflow pkts received
OID : 1.3.6.1.4.1.22610.2.4.10.169.6.1.1.1

Field Name : unknownDir
Field Type : CounterBasedGauge64
Field Status : current
Description : nflow sample direction is unknown
OID : 1.3.6.1.4.1.22610.2.4.10.169.6.2.1.11

Field Name : versionNotSupported
Field Type : CounterBasedGauge64
Field Status : current
Description : nflow version not supported
OID : 1.3.6.1.4.1.22610.2.4.10.169.6.2.1.10

Field Name : agentNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : nflow pkts from not configured agents
OID : 1.3.6.1.4.1.22610.2.4.10.169.6.2.1.9

Field Name : fragDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Total nflow fragment packets dropped
OID : 1.3.6.1.4.1.22610.2.4.10.169.6.2.1.8

Field Name : templateDropOutOfMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : Total templates dropped becuase of out of memory
OID : 1.3.6.1.4.1.22610.2.4.10.169.6.2.1.7

Field Name : templateDropExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Total templates dropped because of maximum limit
OID : 1.3.6.1.4.1.22610.2.4.10.169.6.2.1.6

Field Name : v10TemplatesDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Total v10(IPFIX) templates deleted
OID : 1.3.6.1.4.1.22610.2.4.10.169.6.2.1.5

Field Name : v10TemplatesCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total v10(IPFIX) templates created
OID : 1.3.6.1.4.1.22610.2.4.10.169.6.2.1.4

Field Name : v9TemplatesDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Total v9 templates deleted
OID : 1.3.6.1.4.1.22610.2.4.10.169.6.2.1.3

Field Name : v9TemplatesCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total v9 templates created
OID : 1.3.6.1.4.1.22610.2.4.10.169.6.2.1.2

Field Name : pktsRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Total nflow packets received
OID : 1.3.6.1.4.1.22610.2.4.10.169.6.2.1.1

Field Name : dequeued
Field Type : CounterBasedGauge64
Field Status : current
Description : Total jobs dequeued
OID : 1.3.6.1.4.1.22610.2.4.10.169.4.1.6

Field Name : enqueuePass
Field Type : CounterBasedGauge64
Field Status : current
Description : Total enqueue jobs passed
OID : 1.3.6.1.4.1.22610.2.4.10.169.4.1.5

Field Name : enqueueFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Total enqueue jobs failed
OID : 1.3.6.1.4.1.22610.2.4.10.169.4.1.4

Field Name : notifJobsInQueue
Field Type : CounterBasedGauge64
Field Status : current
Description : Total notification jobs in queue
OID : 1.3.6.1.4.1.22610.2.4.10.169.4.1.3

Field Name : bufferAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total reporting buffer allocation failures
OID : 1.3.6.1.4.1.22610.2.4.10.169.4.1.2

Field Name : logTransmitFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total log transmit failures
OID : 1.3.6.1.4.1.22610.2.4.10.169.4.1.1

Field Name : monEntityRrdFileCreateErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total monitor entity rrd file create error
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.17

Field Name : monEntityRrdOutOfMemoryErr
Field Type : CounterBasedGauge64
Field Status : current

Description : Total monitor entity rrd load failed, out of memory error
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.16

Field Name : monEntityRrdTuneErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total monitor entity rrd tune error
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.15

Field Name : monEntityRrdLastUpdateFetchFailedErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total monitor entity rrd last update fetch failed error
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.14

Field Name : monEntityRrdUpdateErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total monitor entity rrd update error
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.13

Field Name : monEntityRrdFileTimestampErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total monitor entity rrd file timestamp errors
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.12

Field Name : lwOutOfMemoryAllocFailures
Field Type : CounterBasedGauge64
Field Status : current
Description : Light Weight Out-of-memory allocation failures
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.11

Field Name : lwMonEntityLimitExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Light weight limit exceeded errors
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.10

Field Name : lwMonEntityDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Light-weight entities deleted
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.9

Field Name : lwMonEntityCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Light-weight entities created
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.8

Field Name : outOfMemoryAllocFailures
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of memory allocation failures
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.7

Field Name : haEntityPeriodicSyncSent

Field Type : CounterBasedGauge64
Field Status : current
Description : Total monitor entity periodic sync messages sent
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.6

Field Name : haEntityAnomalyOffSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total anomaly off HA messages sent
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.5

Field Name : haEntityAnomalyOnSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total anomaly on HA messages sent
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.4

Field Name : haEntityDeleteSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total montior entity HA delete messages sent
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.3

Field Name : haEntityCreateSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total montior entity HA create messages sent
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.2

Field Name : monEntityLimitExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total monitor entity limit exceed failures
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.1

Field Name : failureMisc
Field Type : CounterBasedGauge64
Field Status : current
Description : Failed, other
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.81

Field Name : smpExists
Field Type : CounterBasedGauge64
Field Status : current
Description : Dynamic Capture(3 tuple based/SMP) already exists
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.80

Field Name : numPerObjectCountersDeregistered
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of per instance objects deregistered
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.79

Field Name : numPerObjectCountersRegistered
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of per instance objects registered
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.78

Field Name : numGlobalCountersDeregistered
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of global objects deregistered
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.77

Field Name : numGlobalCountersRegistered
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of global objects registered
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.76

Field Name : numDynamicCaptureConfigUnlinked
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of times dynamic capture-config unlinked from template
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.75

Field Name : numCaptureConfigUnlinked
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of times capture-config unlinked from template
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.74

Field Name : numDynamicCaptureConfigLinked
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of times dynamic capture-config linked to template
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.73

Field Name : numCaptureConfigLinked
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of times capture-config linked to template
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.72

Field Name : numDynamicCaptureConfigDeleteQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of dynamic capture-config set for deletion
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.71

Field Name : numCaptureConfigDeleteQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of capture-config set for deletion
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.70

Field Name : numDynamicCaptureConfigDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of dynamic capture-config deleted
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.69

Field Name : numCaptureConfigDeleted
Field Type : CounterBasedGauge64
Field Status : current

Description : Number of capture-config deleted
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.68

Field Name : numDynamicCaptureConfigCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of dynamic capture-config created
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.67

Field Name : numCaptureConfigCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of capture-config created
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.66

Field Name : numObjectTmplDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of object templates deleted
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.65

Field Name : numGlobalTmplDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of global templates deleted
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.64

Field Name : numObjectTmplCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of object templates created
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.63

Field Name : numGlobalTmplCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of global templates created
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.62

Field Name : autoPcapFileMergedFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Auto pcapng files merged failed
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.61

Field Name : autoPcapFileMerged
Field Type : CounterBasedGauge64
Field Status : current
Description : Auto pcapng files merged
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.60

Field Name : wrongCtrIncremented
Field Type : CounterBasedGauge64
Field Status : current
Description : Counter increment issue
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.59

Field Name : pktAlreadyCaptured

Field Type : CounterBasedGauge64
Field Status : current
Description : Skip capturing, packet already captured
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.58

Field Name : nonPktPath
Field Type : CounterBasedGauge64
Field Status : current
Description : Skip capturing, not packet processing path
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.57

Field Name : failedAsReturnCompletedSet
Field Type : CounterBasedGauge64
Field Status : current
Description : Skip capturing, capture-config marked completed
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.56

Field Name : skipCaptureAsConnCreatedBeforeSmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Skip capturing, conn was created before the capture started
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.55

Field Name : skipAsConnAlreadyRecapture
Field Type : CounterBasedGauge64
Field Status : current
Description : Skip creating capture, conn was already captured
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.54

Field Name : connExtFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Error, Conn extension creation fail
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.53

Field Name : failedDiskFull
Field Type : CounterBasedGauge64
Field Status : current
Description : Error, Capture fail, Disk limit reached
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.52

Field Name : pktcapOom
Field Type : CounterBasedGauge64
Field Status : current
Description : Error, Automated Packet capture infra OOM
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.51

Field Name : numPcapsCreateFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Error, Number of pcapng files creation failed
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.50

Field Name : numTmpPcapsCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of temporary pcapng files created
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.49

Field Name : numPcapsCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of pcapng files created
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.48

Field Name : numOfAnomaliesCleared
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of times ctr Anomaly cleared
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.47

Field Name : numOfAnomaliesDetected
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of times ctr Anomaly detected
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.46

Field Name : pktcaptureTriggeredByOtherFeature
Field Type : CounterBasedGauge64
Field Status : current
Description : Capture triggered by Other feature
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.45

Field Name : pktcaptureTriggeredByAnomaly
Field Type : CounterBasedGauge64
Field Status : current
Description : Capture triggered by counter anomaly
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.44

Field Name : pktcaptureTriggeredByIncrement
Field Type : CounterBasedGauge64
Field Status : current
Description : Capture triggered by counter increment
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.43

Field Name : numConnsUntagged
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of conns untagged (done with conn limit or capture)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.42

Field Name : numConnsTaggedOtherFeatureMaxed
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn tag fail, reached limit (based on Other feature, dynamic)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.41

Field Name : numConnsTaggedAnomalyMaxed
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn tag fail, reached limit (based on ctr anomaly, dynamic)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.40

Field Name : numConnsTaggedIncrementMaxed
Field Type : CounterBasedGauge64
Field Status : current

Description : Conn tag fail, reached limit (based on ctr increment, dynamic)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.39

Field Name : numConnsTaggedOtherFeatureFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn tag fail (based on Other feature, dynamic)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.38

Field Name : numConnsTaggedAnomalyFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn tag fail (based on ctr anomaly, dynamic)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.37

Field Name : numConnsTaggedIncrementFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn tag fail (based on ctr increment, dynamic)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.36

Field Name : numConnsTaggedOtherFeature
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn tag success (based on Other feature, dynamic)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.35

Field Name : numConnsTaggedAnomaly
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn tag success (based on ctr anomaly, dynamic)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.34

Field Name : numConnsTaggedIncrement
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn tag success (based on ctr increment, dynamic)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.33

Field Name : numConnsTaggedGlobalOtherFeatureMaxed
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn tag fail, reached limit (based on Other feature, Global)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.32

Field Name : numConnsTaggedGlobalAnomalyMaxed
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn tag fail, reached limit (based on ctr anomaly, Global)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.31

Field Name : numConnsTaggedGlobalIncrementMaxed
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn tag fail, reached limit (based on ctr increment, Global)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.30

Field Name : numConnsTaggedGlobalOtherFeatureFail

Field Type : CounterBasedGauge64
Field Status : current
Description : Conn tag fail (based on Other feature, Global)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.29

Field Name : numConnsTaggedGlobalAnomalyFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn tag fail (based on ctr anomaly, Global)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.28

Field Name : numConnsTaggedGlobalIncrementFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn tag fail (based on ctr increment, Global)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.27

Field Name : numConnsTaggedGlobalOtherFeature
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn tag success (based on Other feature, Global)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.26

Field Name : numConnsTaggedGlobalAnomaly
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn tag success (based on ctr anomaly, Global)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.25

Field Name : numConnsTaggedGlobalIncrement
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn tag success (based on ctr increment, Global)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.24

Field Name : pktcaptureFailureFileSizeRchd
Field Type : CounterBasedGauge64
Field Status : current
Description : Capture fail, file size reached
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.23

Field Name : pktcaptureFailureWaitForBlock
Field Type : CounterBasedGauge64
Field Status : current
Description : Capture fail, waiting to get free buffer
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.22

Field Name : pktcaptureWithConnFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Capture fail, Packets with tagged conn (dynamic capture)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.21

Field Name : pktcaptureWithConnFailureGlobal
Field Type : CounterBasedGauge64
Field Status : current
Description : Capture fail, Packets with tagged conn (global capture)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.20

Field Name : pktcaptureWithConnSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Capture success, Packets with tagged conn (dynamic capture)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.19

Field Name : pktcaptureWithConnSuccessGlobal
Field Type : CounterBasedGauge64
Field Status : current
Description : Capture success, Packets with tagged conn (global capture)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.18

Field Name : pktcaptureWithConnButNotTaggedFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Capture fail, Packets with untagged conn
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.17

Field Name : pktcaptureWithConnButNotTaggedSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Capture success, Packets with untagged conn
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.16

Field Name : pktcaptureWithNoConnFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Capture fail, Packets without conn
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.15

Field Name : pktcaptureWithNoConnSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Capture success, Packets without conn
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.14

Field Name : concurrentCaptureFinished
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Dynamic captures(3 tuple based) finished capturing
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.13

Field Name : globalCaptureFinished
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of times global capture finished capturing
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.12

Field Name : concurrentCaptureByCtrOtherFeatureFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dynamic Capture(Other feature based) freed
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.11

Field Name : concurrentCaptureByCtrAnomalyFreed
Field Type : CounterBasedGauge64
Field Status : current

Description : Dynamic Capture(ctr anomaly based) freed
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.10

Field Name : concurrentCaptureByCtrIncrementFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dynamic Capture(ctr increment based) freed
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.9

Field Name : concurrentCaptureLimitReached
Field Type : CounterBasedGauge64
Field Status : current
Description : Dynamic Capture configured concurrent limit reached
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.8

Field Name : concurrentCaptureCreateFailedOom
Field Type : CounterBasedGauge64
Field Status : current
Description : Error, Dynamic Capture create failed, OOM
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.7

Field Name : concurrentCaptureCreateFailedByOtherFeature
Field Type : CounterBasedGauge64
Field Status : current
Description : Error, Dynamic Capture(Other feature based) create failed
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.6

Field Name : concurrentCaptureCreateFailedByCtrAnomaly
Field Type : CounterBasedGauge64
Field Status : current
Description : Error, Dynamic Capture(ctr anomaly based) create failed
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.5

Field Name : concurrentCaptureCreateFailedByCtrIncrement
Field Type : CounterBasedGauge64
Field Status : current
Description : Error, Dynamic Capture(ctr increment based) create failed
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.4

Field Name : concurrentCaptureCreatedByOtherFeature
Field Type : CounterBasedGauge64
Field Status : current
Description : Dynamic 3 tuple based capture created (Other feature based)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.3

Field Name : concurrentCaptureCreatedByCtrAnomaly
Field Type : CounterBasedGauge64
Field Status : current
Description : Dynamic 3 tuple based capture created (ctr anomaly based)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.2

Field Name : concurrentCaptureCreatedByCtrIncrement
Field Type : CounterBasedGauge64
Field Status : current
Description : Dynamic 3 tuple based capture created (ctr increment based)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.1

Field Name : interfaceLifSTable

Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1

Field Name : interfaceLifSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1

Field Name : droppedRxPktsGreKey
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1.16

Field Name : droppedTxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1.15

Field Name : droppedDisTxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1.14

Field Name : droppedRxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1.13

Field Name : droppedDisRxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1.12

Field Name : lifNumMulticastTxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1.11

Field Name : lifNumBroadcastTxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1.10

Field Name : lifNumUnicastTxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1.9

Field Name : lifNumTotalTxBytes
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1.8

Field Name : lifNumTxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1.7

Field Name : lifNumMulticastPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1.6

Field Name : lifNumBroadcastPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1.5

Field Name : lifNumUnicastPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1.4

Field Name : lifNumTotalBytes
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1.3

Field Name : lifNumPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1.2

Field Name : lifIfName
Field Type : String
Field Status : current
Description : Lif interface name
OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1.1

Field Name : interfaceVeSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1

Field Name : interfaceVeSEntry
Field Type : CounterBasedGauge64
Field Status : current

Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1

Field Name : loadInterval
Field Type : CounterBasedGauge64
Field Status : current
Description : Load Interval
OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1.16

Field Name : rateByteRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Byte received rate bits/sec
OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1.15

Field Name : ratePktRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet received rate packets/sec
OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1.14

Field Name : rateByteSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Byte sent rate bits/sec
OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1.13

Field Name : ratePktSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet sent rate packets/sec
OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1.12

Field Name : numMulticastTxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Transmitted multicasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1.11

Field Name : numBroadcastTxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Transmitted broadcasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1.10

Field Name : numUnicastTxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Transmitted unicasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1.9

Field Name : numTotalTxBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : Transmitted bytes
OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1.8

Field Name : numTxPkts

Field Type : CounterBasedGauge64
Field Status : current
Description : Transmitted packets
OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1.7

Field Name : numMulticastPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Received multicasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1.6

Field Name : numBroadcastPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Received broadcasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1.5

Field Name : numUnicastPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Received unicasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1.4

Field Name : numTotalBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : Input bytes
OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1.3

Field Name : numPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Input packets
OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1.2

Field Name : veIfNum
Field Type : INTEGER
Field Status : current
Description : Virtual ethernet interface number
OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1.1

Field Name : interfaceTrunkSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1

Field Name : interfaceTrunkSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1.1

Field Name : droppedTxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1.1.15

Field Name : droppedDisTxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1.1.14

Field Name : droppedRxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1.1.13

Field Name : droppedDisRxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1.1.12

Field Name : numMulticastTxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1.1.11

Field Name : numBroadcastTxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1.1.10

Field Name : numUnicastTxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1.1.9

Field Name : numTotalTxBytes
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1.1.8

Field Name : numTxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1.1.7

Field Name : numMulticastPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1.1.6

Field Name : numBroadcastPkts
Field Type : CounterBasedGauge64
Field Status : current

Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1.1.5

Field Name : numUnicastPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1.1.4

Field Name : numTotalBytes
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1.1.3

Field Name : numPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1.1.2

Field Name : ifnum
Field Type : INTEGER
Field Status : current
Description : Trunk interface number
OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1.1.1

Field Name : interfaceEthernetSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1

Field Name : interfaceEthernetSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1

Field Name : outputUtilization
Field Type : CounterBasedGauge64
Field Status : current
Description : Output Utilization
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.28

Field Name : inputUtilization
Field Type : CounterBasedGauge64
Field Status : current
Description : Input Utilization
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.27

Field Name : receiveDrops
Field Type : CounterBasedGauge64
Field Status : current
Description : Receive Drops
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.26

Field Name : transmitDrops

Field Type : CounterBasedGauge64
Field Status : current
Description : Transmit Drops
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.25

Field Name : loadInterval
Field Type : CounterBasedGauge64
Field Status : current
Description : Load Interval
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.24

Field Name : rateByteRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Byte received rate bits/sec
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.23

Field Name : ratePktRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet received rate packets/sec
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.22

Field Name : rateByteSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Byte sent rate bits/sec
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.21

Field Name : ratePktSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet sent rate packets/sec
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.20

Field Name : giantsOutput
Field Type : CounterBasedGauge64
Field Status : current
Description : Output Giants
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.19

Field Name : collisions
Field Type : CounterBasedGauge64
Field Status : current
Description : Collisions
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.18

Field Name : outputErrors
Field Type : CounterBasedGauge64
Field Status : current
Description : Output errors
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.17

Field Name : transmittedUnicasts
Field Type : CounterBasedGauge64
Field Status : current
Description : Transmitted unicasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.16

Field Name : transmittedMulticasts
Field Type : CounterBasedGauge64
Field Status : current
Description : Transmitted multicasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.15

Field Name : transmittedBroadcasts
Field Type : CounterBasedGauge64
Field Status : current
Description : Transmitted broadcasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.14

Field Name : bytesOutput
Field Type : CounterBasedGauge64
Field Status : current
Description : Output bytes
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.13

Field Name : packetsOutput
Field Type : CounterBasedGauge64
Field Status : current
Description : Output packets
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.12

Field Name : giants
Field Type : CounterBasedGauge64
Field Status : current
Description : Giants
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.11

Field Name : runts
Field Type : CounterBasedGauge64
Field Status : current
Description : Runts
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.10

Field Name : frame
Field Type : CounterBasedGauge64
Field Status : current
Description : Frames
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.9

Field Name : crc
Field Type : CounterBasedGauge64
Field Status : current
Description : CRC
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.8

Field Name : inputErrors
Field Type : CounterBasedGauge64
Field Status : current
Description : Input errors
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.7

Field Name : receivedUnicasts
Field Type : CounterBasedGauge64
Field Status : current

Description : Received unicasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.6

Field Name : receivedMulticasts
Field Type : CounterBasedGauge64
Field Status : current
Description : Received multicasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.5

Field Name : receivedBroadcasts
Field Type : CounterBasedGauge64
Field Status : current
Description : Received broadcasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.4

Field Name : bytesInput
Field Type : CounterBasedGauge64
Field Status : current
Description : Input bytes
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.3

Field Name : packetsInput
Field Type : CounterBasedGauge64
Field Status : current
Description : Input packets
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.2

Field Name : ifnum
Field Type : String
Field Status : current
Description : Ethernet interface number
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.1

Field Name : collisions
Field Type : CounterBasedGauge64
Field Status : current
Description : Collisions
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.17

Field Name : outputErrors
Field Type : CounterBasedGauge64
Field Status : current
Description : Output errors
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.16

Field Name : transmittedUnicasts
Field Type : CounterBasedGauge64
Field Status : current
Description : Transmitted unicasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.15

Field Name : transmittedMulticasts
Field Type : CounterBasedGauge64
Field Status : current
Description : Transmitted multicasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.14

Field Name : transmittedBroadcasts

Field Type : CounterBasedGauge64
Field Status : current
Description : Transmitted broadcasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.13

Field Name : bytesOutput
Field Type : CounterBasedGauge64
Field Status : current
Description : Output bytes
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.12

Field Name : packetsOutput
Field Type : CounterBasedGauge64
Field Status : current
Description : Output packets
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.11

Field Name : inputErrLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Giants
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.10

Field Name : inputErrShort
Field Type : CounterBasedGauge64
Field Status : current
Description : Runts
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.9

Field Name : frame
Field Type : CounterBasedGauge64
Field Status : current
Description : Frames
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.8

Field Name : crc
Field Type : CounterBasedGauge64
Field Status : current
Description : CRC
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.7

Field Name : inputErrors
Field Type : CounterBasedGauge64
Field Status : current
Description : Input errors
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.6

Field Name : receivedUnicasts
Field Type : CounterBasedGauge64
Field Status : current
Description : Received unicasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.5

Field Name : receivedMulticasts
Field Type : CounterBasedGauge64
Field Status : current
Description : Received multicasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.4

Field Name : receivedBroadcasts
Field Type : CounterBasedGauge64
Field Status : current
Description : Received broadcasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.3

Field Name : bytesInput
Field Type : CounterBasedGauge64
Field Status : current
Description : Input bytes
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.2

Field Name : packetsInput
Field Type : CounterBasedGauge64
Field Status : current
Description : Input packets
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.1

Field Name : collisions
Field Type : CounterBasedGauge64
Field Status : current
Description : Collisions
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.17

Field Name : outputErrors
Field Type : CounterBasedGauge64
Field Status : current
Description : Output errors
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.16

Field Name : transmittedUnicasts
Field Type : CounterBasedGauge64
Field Status : current
Description : Transmitted unicasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.15

Field Name : transmittedMulticasts
Field Type : CounterBasedGauge64
Field Status : current
Description : Transmitted multicasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.14

Field Name : transmittedBroadcasts
Field Type : CounterBasedGauge64
Field Status : current
Description : Transmitted broadcasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.13

Field Name : bytesOutput
Field Type : CounterBasedGauge64
Field Status : current
Description : Output bytes
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.12

Field Name : packetsOutput
Field Type : CounterBasedGauge64
Field Status : current

Description : Output packets
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.11

Field Name : inputErrLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Giants
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.10

Field Name : inputErrShort
Field Type : CounterBasedGauge64
Field Status : current
Description : Runts
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.9

Field Name : frame
Field Type : CounterBasedGauge64
Field Status : current
Description : Frames
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.8

Field Name : crc
Field Type : CounterBasedGauge64
Field Status : current
Description : CRC
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.7

Field Name : inputErrors
Field Type : CounterBasedGauge64
Field Status : current
Description : Input errors
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.6

Field Name : receivedUnicasts
Field Type : CounterBasedGauge64
Field Status : current
Description : Received unicasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.5

Field Name : receivedMulticasts
Field Type : CounterBasedGauge64
Field Status : current
Description : Received multicasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.4

Field Name : receivedBroadcasts
Field Type : CounterBasedGauge64
Field Status : current
Description : Received broadcasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.3

Field Name : bytesInput
Field Type : CounterBasedGauge64
Field Status : current
Description : Input bytes
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.2

Field Name : packetsInput

Field Type : CounterBasedGauge64
Field Status : current
Description : Input packets
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.1

Field Name : interfaceTunnelSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.8.1.1

Field Name : interfaceTunnelSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.8.1.1.1

Field Name : rateByteRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Byte received rate bits/sec
OID : 1.3.6.1.4.1.22610.2.4.10.95.8.1.1.1.11

Field Name : ratePktRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet received rate packets/sec
OID : 1.3.6.1.4.1.22610.2.4.10.95.8.1.1.1.10

Field Name : rateByteSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Byte sent rate bits/sec
OID : 1.3.6.1.4.1.22610.2.4.10.95.8.1.1.1.9

Field Name : ratePktSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet sent rate packets/sec
OID : 1.3.6.1.4.1.22610.2.4.10.95.8.1.1.1.8

Field Name : numTxErrPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : sent error packets
OID : 1.3.6.1.4.1.22610.2.4.10.95.8.1.1.1.7

Field Name : numRxErrPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : received error packets
OID : 1.3.6.1.4.1.22610.2.4.10.95.8.1.1.1.6

Field Name : numTotalTxBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : sent bytes
OID : 1.3.6.1.4.1.22610.2.4.10.95.8.1.1.1.5

Field Name : numTxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : sent packets
OID : 1.3.6.1.4.1.22610.2.4.10.95.8.1.1.1.4

Field Name : numTotalRxBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : received bytes
OID : 1.3.6.1.4.1.22610.2.4.10.95.8.1.1.1.3

Field Name : numRxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : received packets
OID : 1.3.6.1.4.1.22610.2.4.10.95.8.1.1.1.2

Field Name : ifnum
Field Type : INTEGER
Field Status : current
Description : Tunnel interface number
OID : 1.3.6.1.4.1.22610.2.4.10.95.8.1.1.1.1

Field Name : ipFragFirstGTPPacketTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : First GTP Fragment Too Small Drop
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.47

Field Name : ipv4InIpv6SctpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.46

Field Name : ipv4InIpv6SctpRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Received
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.45

Field Name : fragSessionCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragmentation Session Count
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.44

Field Name : ipv4InIpv6SessionPacketsExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Max Packets Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.43

Field Name : ipv4InIpv6MaxPackets
Field Type : CounterBasedGauge64
Field Status : current

Description : Too Many Packets Per Reassembly Drop
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.42

Field Name : ipdEntryDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DDoS Protection Drop
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.41

Field Name : cpuThresholdDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : High CPU Drop
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.40

Field Name : lowCpuThreshold
Field Type : CounterBasedGauge64
Field Status : current
Description : Low CPU Threshold Reached
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.39

Field Name : highCpuThreshold
Field Type : CounterBasedGauge64
Field Status : current
Description : High CPU Threshold Reached
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.38

Field Name : ipv4InIpv6ErrorDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Processing Drop
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.37

Field Name : ipv4InIpv6PolicyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : MTU Exceeded Policy Drop
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.36

Field Name : ipv4InIpv6ReassemblyFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Reassembly Failure
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.35

Field Name : ipv4InIpv6MaxLenExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Max Data Length Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.34

Field Name : ipv4InIpv6ReassemblySuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Reassembly Success
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.33

Field Name : ipv4InIpv6FragmentQueueFailure

Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Queue Failure
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.32

Field Name : ipv4InIpv6TotalFragmentsExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Queued Fragments Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.31

Field Name : ipv4InIpv6DuplicateLastFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : Duplicate Last Fragment
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.30

Field Name : ipv4InIpv6DuplicateFirstFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : Duplicate First Fragment
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.29

Field Name : ipv4InIpv6ExceededLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Payload Length Out of Bounds
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.28

Field Name : ipv4InIpv6Unaligned
Field Type : CounterBasedGauge64
Field Status : current
Description : Payload Length Unaligned
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.27

Field Name : ipv4InIpv6FragmentQueueSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Queue Success
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.26

Field Name : ipv4InIpv6FastAgingUnset
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragmentation Fast Aging Unset
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.25

Field Name : ipv4InIpv6FastAgingSet
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragmentation Fast Aging Set
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.24

Field Name : ipv4InIpv6NoSessionMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of Session Memory
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.23

Field Name : ipv4InIpv6TotalSessionsExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Sessions Exceeded Drop
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.22

Field Name : ipv4InIpv6FirstL4TooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : First L4 Fragment Too Small Drop
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.21

Field Name : ipv4InIpv6FirstTcpTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : First TCP Fragment Too Small Drop
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.20

Field Name : ipv4InIpv6TooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Too Small Drop
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.19

Field Name : ipv4InIpv6BadIpLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad IP Length
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.18

Field Name : ipv4InIpv6OverlapError
Field Type : CounterBasedGauge64
Field Status : current
Description : Overlapping Fragment Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.17

Field Name : ipv4InIpv6OtherDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Other Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.16

Field Name : ipv4InIpv6Ipv6ipDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6-in-IP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.15

Field Name : ipv4InIpv6IpipDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : IP-in-IP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.14

Field Name : ipv4InIpv6TcpDropped
Field Type : CounterBasedGauge64
Field Status : current

Description : TCP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.13

Field Name : ipv4InIpv6UdpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.12

Field Name : ipv4InIpv6Icmpv6Dropped
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.11

Field Name : ipv4InIpv6IcmpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.10

Field Name : ipv4InIpv6OtherRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : Other Received
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.9

Field Name : ipv4InIpv6Ipv6ipRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6-in-IP Received
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.8

Field Name : ipv4InIpv6IpipRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : IP-in-IP Received
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.7

Field Name : ipv4InIpv6TcpRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Received
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.6

Field Name : ipv4InIpv6UdpRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Received
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.5

Field Name : ipv4InIpv6Icmpv6Rcv
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 Received
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.4

Field Name : ipv4InIpv6IcmpRcv

Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Received
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.3

Field Name : ipv4InIpv6SessionExpired
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Expired
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.2

Field Name : ipv4InIpv6SessionInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.98.1.1.1

Field Name : ipFragFirstGTPPacketTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : First GTP Fragment Too Small Drop
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.47

Field Name : sctpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.46

Field Name : sctpRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Received
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.45

Field Name : fragSessionCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragmentation Session Count
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.44

Field Name : sessionPacketsExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Max Packets Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.43

Field Name : maxPacketsExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Too Many Packets Per Reassembly Drop
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.42

Field Name : ipdEntryDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DDoS Protection Drop
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.41

Field Name : cpuThresholdDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : High CPU Drop
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.40

Field Name : lowCpuThreshold
Field Type : CounterBasedGauge64
Field Status : current
Description : Low CPU Threshold Reached
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.39

Field Name : highCpuThreshold
Field Type : CounterBasedGauge64
Field Status : current
Description : High CPU Threshold Reached
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.38

Field Name : errorDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Processing Drop
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.37

Field Name : policyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : MTU Exceeded Policy Drop
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.36

Field Name : reassemblyFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Reassembly Failure
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.35

Field Name : maxLenExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Max Data Length Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.34

Field Name : reassemblySuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Reassembly Success
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.33

Field Name : fragmentQueueFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Queue Failure
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.32

Field Name : totalFragmentsExceeded
Field Type : CounterBasedGauge64
Field Status : current

Description : Total Queued Fragments Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.31

Field Name : duplicateLastFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : Duplicate Last Fragment
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.30

Field Name : duplicateFirstFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : Duplicate First Fragment
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.29

Field Name : exceededLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Payload Length Out of Bounds
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.28

Field Name : unalignedLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Payload Length Unaligned
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.27

Field Name : fragmentQueueSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Queue Success
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.26

Field Name : fastAgingUnset
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragmentation Fast Aging Unset
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.25

Field Name : ipv6InIpv4FastAgingSet
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragmentation Fast Aging Set
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.24

Field Name : noSessionMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of Session Memory
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.23

Field Name : totalSessionsExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Sessions Exceeded Drop
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.22

Field Name : firstL4TooSmall

Field Type : CounterBasedGauge64
Field Status : current
Description : First L4 Fragment Too Small Drop
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.21

Field Name : firstTcpTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : First TCP Fragment Too Small Drop
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.20

Field Name : tooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Too Small Drop
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.19

Field Name : badIpLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad IP Length
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.18

Field Name : overlapError
Field Type : CounterBasedGauge64
Field Status : current
Description : Overlapping Fragment Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.17

Field Name : otherDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Other Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.16

Field Name : ipv6ipDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6-in-IP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.15

Field Name : ipipDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : IP-in-IP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.14

Field Name : tcpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.13

Field Name : udpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.12

Field Name : icmpv6Dropped
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.11

Field Name : icmpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.10

Field Name : otherRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : Other Received
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.9

Field Name : ipv6ipRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6-in-IP Received
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.8

Field Name : ipipRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : IP-in-IP Received
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.7

Field Name : tcpRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Received
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.6

Field Name : udpRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Received
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.5

Field Name : icmpv6Rcv
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 Received
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.4

Field Name : icmpRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Received
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.3

Field Name : sessionExpired
Field Type : CounterBasedGauge64
Field Status : current

Description : Session Expired
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.2

Field Name : sessionInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.1

Field Name : fragErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragmentation error
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.17

Field Name : natResourceErr
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT resource error
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.16

Field Name : smartNatRserverIpErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Smart NAT rserver ip update error
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.15

Field Name : smartNatRserverRouteErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Smart NAT rserver route update error
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.14

Field Name : smartNatInitInstErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Smart NAT instance initialization error
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.13

Field Name : smartNatInitPortErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Smart NAT port initialization error
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.12

Field Name : noSlbObject
Field Type : CounterBasedGauge64
Field Status : current
Description : SLB object not found
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.11

Field Name : dcmsgErr
Field Type : CounterBasedGauge64
Field Status : current
Description : DCMSG error
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.10

Field Name : sbyNoPeer

Field Type : CounterBasedGauge64
Field Status : current
Description : Peer not found on standby
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.9

Field Name : sendToKernelErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets sent to kernel error
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.8

Field Name : sendToKernel
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets sent to kernel
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.7

Field Name : recvFromKernel
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets received from kernel
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.6

Field Name : sbyRecvFromActErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets received from active error
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.5

Field Name : sbySendToAct
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets sent to active
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.4

Field Name : sbyRecvFromAct
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets received from active
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.3

Field Name : actSendToSby
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets sent to standby
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.2

Field Name : actRecvFromSby
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets received from standby
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.1

Field Name : tokenAuthenticationInvalid
Field Type : CounterBasedGauge64
Field Status : current
Description : Token Authentication Invalid Packets
OID : 1.3.6.1.4.1.22610.2.4.10.102.83.1.3

Field Name : tokenAuthenticationMismatched
Field Type : CounterBasedGauge64
Field Status : current
Description : Token Authentication Mismatched Packets
OID : 1.3.6.1.4.1.22610.2.4.10.102.83.1.2

Field Name : tokenAuthenticationMatched
Field Type : CounterBasedGauge64
Field Status : current
Description : Token Authentication Matched Packets
OID : 1.3.6.1.4.1.22610.2.4.10.102.83.1.1

Field Name : logMsgSendErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Message Send Error
OID : 1.3.6.1.4.1.22610.2.4.10.102.67.1.9

Field Name : logMsgSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Message Sent
OID : 1.3.6.1.4.1.22610.2.4.10.102.67.1.8

Field Name : logMsgDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Message Dequeue Error
OID : 1.3.6.1.4.1.22610.2.4.10.102.67.1.7

Field Name : logMsgDequeue
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Message Dequeue
OID : 1.3.6.1.4.1.22610.2.4.10.102.67.1.6

Field Name : logMsgEnqueueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Message Enqueue Error
OID : 1.3.6.1.4.1.22610.2.4.10.102.67.1.5

Field Name : logMsgEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Message Enqueue
OID : 1.3.6.1.4.1.22610.2.4.10.102.67.1.4

Field Name : logQueueFull
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Message Queue Full
OID : 1.3.6.1.4.1.22610.2.4.10.102.67.1.3

Field Name : logMsgOom
Field Type : CounterBasedGauge64
Field Status : current

Description : Log Message Out of Memory Error
OID : 1.3.6.1.4.1.22610.2.4.10.102.67.1.2

Field Name : logMsgQuotaExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Message Per CPU Quota Exceed
OID : 1.3.6.1.4.1.22610.2.4.10.102.67.1.1

Field Name : syncSzpBlRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received SrcZoneService Blacklist
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.64

Field Name : syncSzpDnsTcpAuthRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received SrcZoneService DNS Force-TCP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.63

Field Name : syncSzpDnsUdpAuthRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received SrcZoneService DNS UDP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.62

Field Name : syncSzpOtherAuthRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received SrcZoneService OTHER Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.61

Field Name : syncSzpIcmpAuthRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received SrcZoneService ICMP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.60

Field Name : syncSzpUdpAuthRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received SrcZoneService UDP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.59

Field Name : syncSzpTcpAuthRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received SrcZoneService TCP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.58

Field Name : syncSrcDstBlRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received SrcDst Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.57

Field Name : syncSrcDstDnsTcpAuthRcvd

Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received SrcDst DNS Force-TCP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.56

Field Name : syncSrcDstDnsUdpAuthRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received SrcDst DNS UDP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.55

Field Name : syncSrcDstOtherWlRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received SrcDst OTHER Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.54

Field Name : syncSrcDstIcmpWlRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received SrcDst ICMP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.53

Field Name : syncSrcDstTcpWlRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received SrcDst TCP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.52

Field Name : syncSrcDstUdpWlRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received SrcDst UDP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.51

Field Name : syncSrcBlRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received Src Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.50

Field Name : syncSrcDnsTcpAuthRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received Src DNS Force-TCP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.49

Field Name : syncSrcDnsUdpAuthRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received Src DNS UDP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.48

Field Name : syncSrcOtherWlRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received Src OTHER Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.47

Field Name : syncSrcIcmpWlRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received Src ICMP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.46

Field Name : syncSrcTcpWlRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received Src TCP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.45

Field Name : syncSrcUdpWlRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received Src UDP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.44

Field Name : syncSzpBlSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent SrcZoneService Blacklist
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.43

Field Name : syncSzpDnsTcpAuthSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent SrcZoneService DNS Force-TCP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.42

Field Name : syncSzpDnsUdpAuthSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent SrcZoneService DNS UDP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.41

Field Name : syncSzpOtherAuthSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent SrcZoneService OTHER Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.40

Field Name : syncSzpIcmpAuthSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent SrcZoneService ICMP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.39

Field Name : syncSzpUdpAuthSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent SrcZoneService UDP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.38

Field Name : syncSzpTcpAuthSent
Field Type : CounterBasedGauge64
Field Status : current

Description : Sync Sent SrcZoneService TCP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.37

Field Name : syncSrcDstBlSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent SrcDst Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.36

Field Name : syncSrcDstDnsTcpAuthSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent SrcDst DNS Force-TCP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.35

Field Name : syncSrcDstDnsUdpAuthSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent SrcDst DNS UDP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.34

Field Name : syncSrcDstOtherWlSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent SrcDst OTHER Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.33

Field Name : syncSrcDstIcmpWlSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent SrcDst ICMP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.32

Field Name : syncSrcDstTcpWlSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent SrcDst TCP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.31

Field Name : syncSrcDstUdpWlSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent SrcDst UDP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.30

Field Name : syncSrcBlSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent Src Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.29

Field Name : syncSrcDnsTcpAuthSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent Src DNS Force-TCP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.28

Field Name : syncSrcDnsUdpAuthSent

Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent Src DNS UDP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.27

Field Name : syncSrcOtherWlSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent Src OTHER Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.26

Field Name : syncSrcIcmpWlSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent Src ICMP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.25

Field Name : syncSrcTcpWlSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent Src TCP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.24

Field Name : syncSrcUdpWlSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent Src UDP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.23

Field Name : syncRcvEntryUnk
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received Unknown Entry
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.22

Field Name : syncRcvEntryUnkSubtype
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received Entry Unknown Subtype
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.21

Field Name : syncRcvHelloUnkSubtype
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received Hello Unknown Subtype
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.20

Field Name : syncRcvFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.19

Field Name : syncRcvUnkMsg
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received Unknown Msg
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.18

Field Name : syncRcvEntryConflictStatic
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received Entry Conflict Static
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.17

Field Name : syncRcvEntryCreateFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received Entry Create Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.16

Field Name : syncSzpNoDstDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync SrcZoneService No-Dst
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.15

Field Name : syncSrcDstNoDstDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync SrcDst No-Dst
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.14

Field Name : syncRcvHelloUnkPeer
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received Hello Unknown Peer
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.13

Field Name : syncSentFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.12

Field Name : syncSentNoPeer
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent No Peer
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.11

Field Name : syncSzpRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync SrcZoneService Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.10

Field Name : syncSzpSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync SrcZoneService Sent
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.9

Field Name : syncSrcDstRcv
Field Type : CounterBasedGauge64
Field Status : current

Description : Sync SrcDst Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.8

Field Name : syncSrcDstSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync SrcDst Sent
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.7

Field Name : syncSrcRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Src Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.6

Field Name : syncSrcSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Src Sent
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.5

Field Name : syncDstRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Dst Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.4

Field Name : syncDstSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Dst Sent
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.3

Field Name : syncHelloSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Hello Sent
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.2

Field Name : syncHelloRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Hello Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.1

Field Name : undersizeIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Undersize
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.36

Field Name : undersizeIpPl
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Payload Too Small
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.35

Field Name : tcpOptOverflow

Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Option Error
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.34

Field Name : tunMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Tunnel Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.33

Field Name : runtTcpudpHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : TCPUDP Runt Header
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.32

Field Name : runtIpHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Runt Header
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.31

Field Name : udpBadCsum
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Invalid Checksum
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.30

Field Name : udpPortLb
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port LB
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.29

Field Name : udpKbFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP KB Fragment
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.28

Field Name : udpShortLeng
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Invalid Length
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.27

Field Name : udpShortHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Short Header
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.26

Field Name : tcpBadCsum
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Invalid Checksum
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.25

Field Name : tcpFragHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Fragment Header
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.24

Field Name : tcpSynFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Fragment
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.23

Field Name : tcpXmasScan
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP XMAS Scan
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.22

Field Name : tcpXmasFlags
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP XMAS Flags
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.21

Field Name : tcpSynFin
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN&FIN
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.20

Field Name : tcpNullScan
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Null Scan
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.19

Field Name : tcpNullFlags
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Null Flags
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.18

Field Name : tcpBadIpLen
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Invalid IPv4 Length
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.17

Field Name : tcpShortHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Short Header
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.16

Field Name : tcpBadUrgOff
Field Type : CounterBasedGauge64
Field Status : current

Description : TCP Invalid Urgent Offset
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.15

Field Name : icmpPod
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Ping Of Death
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.14

Field Name : badIpCsum
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Invalid Checksum
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.13

Field Name : badIpFragOff
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Invalid Fragment Offset
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.12

Field Name : badIpPlLen
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Invalid Payload Length
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.11

Field Name : oversizeIpPl
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Payload Too Large
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.10

Field Name : noIpPayload
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Payload None
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.9

Field Name : badIpTtl
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Invalid TTL
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.8

Field Name : badIpFlags
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Invalid Flags
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.7

Field Name : badIpHdrLen
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Invalid Header Length
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.6

Field Name : ipFrag

Field Type : CounterBasedGauge64
Field Status : current
Description : IP Fragment
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.5

Field Name : ipv4Opt
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Option
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.4

Field Name : microFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Micro Fragment
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.3

Field Name : emptyFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Empty Fragment
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.2

Field Name : landAttack
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Land Attack
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.1

Field Name : jumboInTunnelDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Jumbo Packet in Tunnel Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.42

Field Name : ipGreTunnelKeepaliveRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Tunnel Keep-Alive Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.41

Field Name : ipVxlanTunnelDecapErr
Field Type : CounterBasedGauge64
Field Status : current
Description : IP VxLAN Decap Error
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.40

Field Name : ipVxlanTunnelDecap
Field Type : CounterBasedGauge64
Field Status : current
Description : IP VxLAN Decap
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.39

Field Name : ipVxlanTunnelInvalidVni
Field Type : CounterBasedGauge64
Field Status : current
Description : IP VxLAN Invalid VNI
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.38

Field Name : ipVxlanTunnelRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : IP VxLAN Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.37

Field Name : ip6EspTunnelInspectFail
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP V6 Tunnel Inspect Fail
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.36

Field Name : ip6EspTunnelInspect
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP V6 Tunnel Inspect
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.35

Field Name : ip6EspTunnelRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP V6 Tunnel Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.34

Field Name : ipEspTunnelInspectFail
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP Tunnel Inspect Fail
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.33

Field Name : ipEspTunnelInspect
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP Tunnel Inspect
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.32

Field Name : ipEspTunnelRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP Tunnel Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.31

Field Name : ip6GreTunnelDecapDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE V6 Tunnel Decap No Key Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.30

Field Name : ip6GreTunnelDecapKey
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE V6 Tunnel Decap W/ Key
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.29

Field Name : ip6GreTunnelEncapKey
Field Type : CounterBasedGauge64
Field Status : current

Description : GRE V6 Tunnel Encap W/ Key
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.28

Field Name : ip6GreTunnelDecapFail
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE V6 Tunnel Decap Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.27

Field Name : ip6GreTunnelDecap
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE V6 Tunnel Decap
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.26

Field Name : ip6GreTunnelEncapFail
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE V6 Tunnel Encap Received Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.25

Field Name : ip6GreTunnelEncap
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE V6 Tunnel Encap
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.24

Field Name : ip6GreTunnelRateLimitInner
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE V6 Tunnel Rate Limit Inner Pkts
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.23

Field Name : ip6GreTunnelRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE V6 Tunnel Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.22

Field Name : ipGreTunnelDecapDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Tunnel Decap Key Mismatch Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.21

Field Name : ipGreTunnelDecapKey
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Tunnel Decap W/ Key
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.20

Field Name : ipGreTunnelEncapKey
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Tunnel Encap W/ Key
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.19

Field Name : ipGreTunnelDecapFail

Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Tunnel Decap Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.18

Field Name : ipGreTunnelDecap
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Tunnel Decap
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.17

Field Name : ipGreTunnelEncapFail
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Tunnel Encap Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.16

Field Name : ipGreTunnelEncap
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Tunnel Encap
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.15

Field Name : ipGreTunnelRateLimitInner
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Tunnel Rate Limit Inner Pkts
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.14

Field Name : ipGreTunnelRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Tunnel Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.13

Field Name : ip6TunnelDecapFail
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Tunnel Decap Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.12

Field Name : ip6TunnelDecap
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Tunnel Decap
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.11

Field Name : ip6TunnelEncapFail
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Tunnel Encap Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.10

Field Name : ip6TunnelEncap
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Tunnel Encap
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.9

Field Name : ip6TunnelRateLimitInner
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Tunnel Rate Limit Inner Pkts
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.8

Field Name : ip6TunnelRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Tunnel Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.7

Field Name : ipTunnelDecapFail
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Tunnel Decap Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.6

Field Name : ipTunnelDecap
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Tunnel Decap
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.5

Field Name : ipTunnelEncapFail
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Tunnel Encap Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.4

Field Name : ipTunnelEncap
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Tunnel Encap
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.3

Field Name : ipTunnelRateLimitInner
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Tunnel Rate Limit Inner Pkts
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.2

Field Name : ipTunnelRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Tunnel Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.1

Field Name : dstIpprotoFragRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst IP-Proto Frag Pkt Rate Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.61.1.7

Field Name : dstIpprotoKbitRateExceed
Field Type : CounterBasedGauge64
Field Status : current

Description : Dst IP-Proto KiBit Rate Exceeded (KiBit)
OID : 1.3.6.1.4.1.22610.2.4.10.102.61.1.6

Field Name : dstIpprotoPktRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst IP-Proto Pkt Rate Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.61.1.5

Field Name : dstIpprotoExceedDropAny
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst IP-Proto Exceed Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.61.1.4

Field Name : dstIpprotoBl
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst IP-Proto Blacklist Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.61.1.3

Field Name : dstIpprotoDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst IP-Proto Total Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.61.1.2

Field Name : dstIpprotoRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst IP-Proto Total Packets Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.61.1.1

Field Name : dstPortSameSportDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Port Same Src Port Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.60.1.16

Field Name : dstSportConnRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst SrcPort Conn Rate Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.60.1.15

Field Name : dstSportConnLimitExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst SrcPort Conn Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.60.1.14

Field Name : dstSportFragRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst SrcPort Frag Pkt Rate Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.60.1.13

Field Name : dstSportKbitRateExceed

Field Type : CounterBasedGauge64
Field Status : current
Description : Dst SrcPort KiBit Rate Exceeded (KiBit)
OID : 1.3.6.1.4.1.22610.2.4.10.102.60.1.12

Field Name : dstSportPktRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst SrcPort Pkt Rate Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.60.1.11

Field Name : dstSportExceedDropAny
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst SrcPort Exceed Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.60.1.10

Field Name : dstSportBl
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst SrcPort Blacklist Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.60.1.9

Field Name : dstPortConnRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Port Conn Rate Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.60.1.8

Field Name : dstPortConnLimitExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Port Conn Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.60.1.7

Field Name : dstPortFragRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Port Frag Pkt Rate Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.60.1.6

Field Name : dstPortKbitRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Port KiBit Rate Exceeded (KiBit)
OID : 1.3.6.1.4.1.22610.2.4.10.102.60.1.5

Field Name : dstPortPktRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Port Pkt Rate Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.60.1.4

Field Name : dstPortExceedDropAny
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Port Exceed Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.60.1.3

Field Name : dstPortBl
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Port Blacklist Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.60.1.2

Field Name : dstPortUndefDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Port Undefined Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.60.1.1

Field Name : runtimeDisable
Field Type : CounterBasedGauge64
Field Status : current
Description : DDOS Runtime Disable
OID : 1.3.6.1.4.1.22610.2.4.10.102.59.1.4

Field Name : runtimeEnable
Field Type : CounterBasedGauge64
Field Status : current
Description : DDOS Runtime Enable
OID : 1.3.6.1.4.1.22610.2.4.10.102.59.1.3

Field Name : dcmsgPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : DDOS DCMSG Pkt
OID : 1.3.6.1.4.1.22610.2.4.10.102.59.1.2

Field Name : rrSessLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : DDOS RR Session Lookup
OID : 1.3.6.1.4.1.22610.2.4.10.102.59.1.1

Field Name : acosDdosTable
Field Type : TABLE
Field Status : none
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.102.58

Field Name : acosDdosTableS
Field Type : TABLE
Field Status : none
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1

Field Name : srcZoneServiceClasslistOverflowPolicyAtLearning
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcZoneService Class-List Overflow Policy Hit
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.72

Field Name : srcDstClasslistOverflowPolicyAtLearning
Field Type : CounterBasedGauge64
Field Status : current

Description : SrcDst Class-List Overflow Policy Hit
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.71

Field Name : entryExtOom
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of Entry Extension Memory
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.70

Field Name : entryOom
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of Entry Memory
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.69

Field Name : srcZoneServiceOverThrePolicyAtLearning
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcZoneService Overflow Policy Learning Hit
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.68

Field Name : srcZoneServiceOverThrePolicyAtLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcZoneService Overflow Policy Lookup Hit
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.67

Field Name : srcZoneServiceLearningThreExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcZoneService Dynamic Entry Count Overflow
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.66

Field Name : srcDstOverThrePolicyAtLearning
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Overflow Policy Hit At Learning Stage
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.65

Field Name : srcDstOverThrePolicyAtLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Overflow Policy Hit At Lookup Stage
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.64

Field Name : srcDstLearningThreExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Dynamic Entry Count Overflow
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.63

Field Name : srcOverThrePolicyAtLearning
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Overflow Policy Hit At Learning Stage
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.62

Field Name : srcOverThrePolicyAtLookup

Field Type : CounterBasedGauge64
Field Status : current
Description : Src Overflow Policy Hit At Lookup Stage
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.61

Field Name : srcLearningThreExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Dynamic Entry Count Overflow
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.60

Field Name : dstOverThrePolicyAtLearning
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Overflow Policy Hit At Learning Stage
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.59

Field Name : dstLearningThreExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Dynamic Entry Count Overflow
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.58

Field Name : srcZoneServiceBlackList
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcZoneService Entry Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.57

Field Name : srcDstBlackList
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Entry Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.56

Field Name : srcBlackList
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Entry Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.55

Field Name : dstBlackList
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Entry Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.54

Field Name : srcZoneServiceWhiteList
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcZoneService Entry Whitelisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.53

Field Name : srcDstWhiteList
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Entry Whitelisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.52

Field Name : srcWhiteList
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Entry Whitelisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.51

Field Name : dstWhiteList
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Entry Whitelisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.50

Field Name : srcZoneServiceEntryAged
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcZoneService Entry Aged
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.49

Field Name : srcZoneServiceMiss
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcZoneService Entry Missed
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.48

Field Name : srcZoneServiceHit
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcZoneService Entry Hit
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.47

Field Name : srcZoneServiceLearn
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcZoneService Entry Learned
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.46

Field Name : telemErrFailToDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : From-l3-peer: Zone Entry Delete Fail
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.45

Field Name : telemErrFailToCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : From-l3-peer: Zone Entry Create Fail
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.44

Field Name : telemErrConflictWithStatic
Field Type : CounterBasedGauge64
Field Status : current
Description : From-l3-peer: Conflict with Static Entry
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.43

Field Name : telemErrTelemEntryPreExist
Field Type : CounterBasedGauge64
Field Status : current

Description : From-l3-peer: Zone Entry Pre-exist
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.42

Field Name : telemEntryCleared
Field Type : CounterBasedGauge64
Field Status : current
Description : From-l3-peer: Zone Entry Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.41

Field Name : telemEntryCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : From-l3-peer: Zone Entry Created
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.40

Field Name : telemRouteDelRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : From-l3-peer: Route-del Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.39

Field Name : telemRouteAddRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : From-l3-peer: Route-add Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.38

Field Name : telemErrMisc
Field Type : CounterBasedGauge64
Field Status : current
Description : From-l3-peer: Misc Error
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.37

Field Name : srcDstOverLimitOff
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Over Limit Trigger OFF (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.36

Field Name : srcOverLimitOff
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Over Limit Trigger OFF (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.35

Field Name : dstPortOverLimitOff
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Port Over Limit Trigger OFF (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.34

Field Name : dstOverLimitOff
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Over Limit Trigger OFF (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.33

Field Name : srcDstOverLimitOn

Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Over Limit Trigger ON (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.32

Field Name : srcOverLimitOn
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Over Limit Trigger ON (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.31

Field Name : dstPortOverLimitOn
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Port Over Limit Trigger ON (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.30

Field Name : dstOverLimitOn
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Over Limit Trigger ON (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.29

Field Name : srcDstOtherBlackList
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER SrcDst Blacklist (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.28

Field Name : srcDstIcmpBlackList
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP SrcDst Blacklist (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.27

Field Name : srcDstTcpBlackList
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SrcDst Blacklist (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.26

Field Name : srcDstUdpBlackList
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP SrcDst Blacklist (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.25

Field Name : srcDstOtherWhiteList
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER SrcDst Whitelist (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.24

Field Name : srcDstIcmpWhiteList
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP SrcDst Whitelist (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.23

Field Name : srcDstTcpWhiteList
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SrcDst Whitelist (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.22

Field Name : srcDstUdpWhiteList
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP SrcDst Whitelist (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.21

Field Name : srcOtherBlackList
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Src Blacklist (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.20

Field Name : srcIcmpBlackList
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Src Blacklist (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.19

Field Name : srcTcpBlackList
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Src Blacklist (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.18

Field Name : srcUdpBlackList
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Src Blacklist (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.17

Field Name : srcOtherWhiteList
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Src Whitelist (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.16

Field Name : srcIcmpWhiteList
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Src Whitelist (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.15

Field Name : srcTcpWhiteList
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Src Whitelist (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.14

Field Name : srcUdpWhiteList
Field Type : CounterBasedGauge64
Field Status : current

Description : UDP Src Whitelist (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.13

Field Name : srcDstEntryAged
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Entry Aged
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.12

Field Name : srcDstMiss
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Entry Missed
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.11

Field Name : srcDstHit
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Entry Hit
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.10

Field Name : srcDstLearn
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Entry Learned
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.9

Field Name : srcEntryAged
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Entry Aged
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.8

Field Name : srcMiss
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Entry Missed
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.7

Field Name : srcHit
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Entry Hit
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.6

Field Name : srcLearn
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Entry Learned
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.5

Field Name : dstEntryAged
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Entry Aged
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.4

Field Name : dstMiss

Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Entry Missed
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.3

Field Name : dstHit
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Entry Hit
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.2

Field Name : dstLearn
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Entry Learned
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.1

Field Name : jumboOutgoingMtuExceedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Jumbo Outgoing MTU Exceed Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.23

Field Name : jumboFragDropBeforeSlb
Field Type : CounterBasedGauge64
Field Status : current
Description : Jumbo Fragment Non Data Plane Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.22

Field Name : jumboFragDropByFilter
Field Type : CounterBasedGauge64
Field Status : current
Description : Jumbo Fragment Filter Miss Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.21

Field Name : fragDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.20

Field Name : fragRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Received (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.19

Field Name : mplsMalformed
Field Type : CounterBasedGauge64
Field Status : current
Description : MPLS Malformed
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.18

Field Name : mplsDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : MPLS Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.17

Field Name : mplsRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : MPLS Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.16

Field Name : dstBlackholeWithdraw
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Blackhole Withdrawn
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.15

Field Name : dstBlackholeInject
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Blackhole Injected
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.14

Field Name : dstIpBypass
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst IP Bypass
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.13

Field Name : srcIpBypass
Field Type : CounterBasedGauge64
Field Status : current
Description : Src IP Bypass
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.12

Field Name : egressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound Packets Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.11

Field Name : ingressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound Packets Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.10

Field Name : egressBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound Bytes Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.9

Field Name : ingressBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound Bytes Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.8

Field Name : pktNotForDdos
Field Type : CounterBasedGauge64
Field Status : current

Description : Not For DDOS
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.7

Field Name : noroute
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4/v6 Out No Route
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.6

Field Name : inStatelessPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : Stateless Packets Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.5

Field Name : ipv6Sent
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Sent
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.4

Field Name : ipv6Rcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.3

Field Name : ipSent
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Sent
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.2

Field Name : ipRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.1

Field Name : sessSnatFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Source NAT Failure
OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.22

Field Name : sessAgedUdpAuth
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Helper Auth Sessions Aged Out
OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.21

Field Name : sessCreateUdpAuth
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Helper Auth Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.20

Field Name : sessOom

Field Type : CounterBasedGauge64
Field Status : current
Description : Out of Session Memory
OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.19

Field Name : connTcpCreateFromAck
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Conn Created From ACK
OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.18

Field Name : connTcpCreateFromSyn
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Conn Created From SYN
OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.17

Field Name : connEntryMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Entry Mismatch Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.16

Field Name : sessAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Aged Out
OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.15

Field Name : connUdpClose
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Conn Closed
OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.14

Field Name : connUdpEst
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Conn Established
OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.13

Field Name : sessCreateUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.12

Field Name : connTcpClose
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Conn Closed
OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.11

Field Name : connTcpCloseWHalfOpen
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Conn Closed With Half Open
OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.10

Field Name : connTcpCloseWIdle
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Conn Closed With Idle
OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.9

Field Name : connTcpCloseWFin
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Conn Closed With FIN
OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.8

Field Name : connTcpCloseWRst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Conn Closed With RST
OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.7

Field Name : connTcpEst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Conn Established
OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.6

Field Name : connTcpEstWAck
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Conn Established With ACK
OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.5

Field Name : connTcpEstWSyn
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Conn Established With SYN
OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.4

Field Name : sessCreateTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.3

Field Name : sessCreateIp6
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.2

Field Name : sessCreateIp
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.1

Field Name : sslBadHeaderDrop
Field Type : CounterBasedGauge64
Field Status : current

Description : SSL Traffic Check Bad Header Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.29

Field Name : sslBadHeaderForw
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL Traffic Check Bad Header Forwarded
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.28

Field Name : sslHeaderBadLen
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL Header Bad Length
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.27

Field Name : sslHeaderBadVer
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL Header Bad Version
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.26

Field Name : sslHeaderInvalidType
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL Header Invalid Type
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.25

Field Name : sslNonTls
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL Non-TLS Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.24

Field Name : sslL4AuthResp
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL Auth Responded
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.23

Field Name : sslL4AuthDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL Auth Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.22

Field Name : sslL4RenegotiationIncomplete
Field Type : CounterBasedGauge64
Field Status : current
Description : Renegotiation Incomplete
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.21

Field Name : sslL4AuthHandshakeFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Auth Handshake Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.20

Field Name : sslL4AuthHandshakeBl

Field Type : CounterBasedGauge64
Field Status : current
Description : Auth Handshake Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.19

Field Name : sslL4AuthHandshakeOk
Field Type : CounterBasedGauge64
Field Status : current
Description : Auth Handshake Success
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.18

Field Name : sslL4HandshakeTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : Auth Handshake Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.17

Field Name : sslL4ResetForHandshake
Field Type : CounterBasedGauge64
Field Status : current
Description : Reset While Others in Handshake
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.16

Field Name : sslL4DoAuthHandshake
Field Type : CounterBasedGauge64
Field Status : current
Description : Do Auth Handshake
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.15

Field Name : sslL4IsSrcReqRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Request Rate Exceed Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.14

Field Name : sslL4IsDstReqRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Request Rate Exceed Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.13

Field Name : sslL4RenegotiationExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Renegotiation Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.12

Field Name : sslL4IsRenegotiation
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL Renegotiation
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.11

Field Name : sslL4IsTls13
Field Type : CounterBasedGauge64
Field Status : current
Description : TLS v1.2 or higher version
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.10

Field Name : sslL4IsTls12
Field Type : CounterBasedGauge64
Field Status : current
Description : TLS v1.1
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.9

Field Name : sslL4IsTls11
Field Type : CounterBasedGauge64
Field Status : current
Description : TLS v1.0
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.8

Field Name : sslL4IsSsl3
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL v3
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.7

Field Name : sslL4NewSyn
Field Type : CounterBasedGauge64
Field Status : current
Description : New TCP SYN
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.6

Field Name : sslL4Processed
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets Processed
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.5

Field Name : sslL4ErCondition
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Condition
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.4

Field Name : sslL4DropPacket
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.3

Field Name : sslL4PolicyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Policy Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.2

Field Name : sslL4PolicyReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Policy Reset
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.1

Field Name : malformReqLineInvalidMethod
Field Type : CounterBasedGauge64
Field Status : current

Description : Malform Request Line Invalid Method
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.132

Field Name : malformReqLineTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : Malform Request Line Too Small
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.131

Field Name : headerProcessingIncomplete
Field Type : CounterBasedGauge64
Field Status : current
Description : Header Process Incomplete
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.130

Field Name : headerProcessingTime3
Field Type : CounterBasedGauge64
Field Status : current
Description : Header Process Time Larger or Equal to 30s
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.129

Field Name : headerProcessingTime2
Field Type : CounterBasedGauge64
Field Status : current
Description : Header Process Time Less Than 30s
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.128

Field Name : headerProcessingTime1
Field Type : CounterBasedGauge64
Field Status : current
Description : Header Process Time Less Than 10s
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.127

Field Name : headerProcessingTime0
Field Type : CounterBasedGauge64
Field Status : current
Description : Header Process Time Less Than 1s
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.126

Field Name : httpAuthResp
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Auth Responded
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.125

Field Name : httpAuthDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Auth Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.124

Field Name : uriFilterMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : URI Filter Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.123

Field Name : dstFilterActionReset

Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Action Reset
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.122

Field Name : dstFilterActionIgnore
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Action Ignore
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.121

Field Name : dstFilterRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Rate Exceed
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.120

Field Name : srcDstFilterActionWhitelist
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter Action WL
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.119

Field Name : srcDstFilterActionDefaultPass
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter Action Default Pass
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.118

Field Name : srcDstFilterActionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter Action Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.117

Field Name : srcDstFilterActionBlacklist
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter Action Blacklist
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.116

Field Name : srcDstFilterNotMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter No Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.115

Field Name : srcDstFilterMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.114

Field Name : srcFilterActionWhitelist
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter Action WL
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.113

Field Name : srcFilterActionDefaultPass
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter Action Default Pass
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.112

Field Name : srcFilterActionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter Action Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.111

Field Name : srcFilterActionBlacklist
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter Action Blacklist
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.110

Field Name : srcFilterNotMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter No Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.109

Field Name : srcFilterMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.108

Field Name : dstFilterActionWhitelist
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Action WL
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.107

Field Name : dstRespRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Response Rate Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.106

Field Name : srcPostRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Post Rate Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.105

Field Name : dstPostRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Post Rate Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.104

Field Name : dstFilterActionDefaultPass
Field Type : CounterBasedGauge64
Field Status : current

Description : Dst Filter Action Default Pass
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.103

Field Name : dstFilterActionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Action Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.102

Field Name : dstFilterActionBlacklist
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Action Blacklist
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.101

Field Name : dstFilterNotMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter No Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.100

Field Name : dstFilterMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.99

Field Name : refererFilterBlacklist
Field Type : CounterBasedGauge64
Field Status : current
Description : Referer Filter Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.98

Field Name : refererFilterMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Referer Filter Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.97

Field Name : agentFilterBlacklist
Field Type : CounterBasedGauge64
Field Status : current
Description : Agent Filter Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.96

Field Name : agentFilterMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Agent Filter Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.95

Field Name : useHdrIpAsSource
Field Type : CounterBasedGauge64
Field Status : current
Description : Use IP In Header As Src
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.94

Field Name : allocHdrFail

Field Type : CounterBasedGauge64
Field Status : current
Description : FAIL_ALLOC_HDR (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.93

Field Name : allocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Alloc Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.92

Field Name : windowSmallDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Window Size Small Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.91

Field Name : windowSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : Window Size Small
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.90

Field Name : malformTooManyHeaders
Field Type : CounterBasedGauge64
Field Status : current
Description : Malform Too Many Headers
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.89

Field Name : malformReqLineTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Malform Request Line Too Long
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.88

Field Name : malformLineTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Malform Line Too Long
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.87

Field Name : malformHeaderNameTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Malform Header Name Too Long
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.86

Field Name : malformContentLenTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Malform Content Length Too Long
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.85

Field Name : malformBadChunk
Field Type : CounterBasedGauge64
Field Status : current
Description : Malform Bad Chunk
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.84

Field Name : challengeJsFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Challenge Javascript Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.83

Field Name : challengeJsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Challenge Javascript Sent
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.82

Field Name : challengeUdFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Challenge URL Redirect Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.81

Field Name : challengeUdSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Challenge URL Redirect Sent
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.80

Field Name : challengeFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Challenge Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.79

Field Name : chunkBad
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad HTTP Chunk
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.78

Field Name : chunkSzGt4k
Field Type : CounterBasedGauge64
Field Status : current
Description : Payload Chunk Size Larger Than 4K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.77

Field Name : chunkSz4k
Field Type : CounterBasedGauge64
Field Status : current
Description : Payload Chunk Size Less Than or Equal to 4K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.76

Field Name : chunkSz2k
Field Type : CounterBasedGauge64
Field Status : current
Description : Payload Chunk Size Less Than or Equal to 2K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.75

Field Name : chunkSz1k
Field Type : CounterBasedGauge64
Field Status : current

Description : Payload Chunk Size Less Than or Equal to 1K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.74

Field Name : chunkSz512
Field Type : CounterBasedGauge64
Field Status : current
Description : Payload Chunk Size Less Than or Equal to 512
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.73

Field Name : hpsRspStatusUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : Status Code Unknown
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.72

Field Name : hpsRspStatus6xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status Code 6XX
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.71

Field Name : hpsRspStatus504AX
Field Type : CounterBasedGauge64
Field Status : current
Description : Status Code 504 AX-Gen
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.70

Field Name : hpsRspStatus5xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status Code 5XX
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.69

Field Name : hpsRspStatus4xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status Code 4XX
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.68

Field Name : hpsRspStatus3xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status Code 3XX
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.67

Field Name : hpsRspStatus2xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status Code 2XX
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.66

Field Name : hpsRspStatus1xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status Code 1XX
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.65

Field Name : hpsRspSz256kPlus

Field Type : CounterBasedGauge64
Field Status : current
Description : Response Payload Size Larger Than 256K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.64

Field Name : hpsRspSz256k
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Payload Size Less Than or Equal to 256K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.63

Field Name : hpsRspSz64k
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Payload Size Less Than or Equal to 64K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.62

Field Name : hpsRspSz32k
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Payload Size Less Than or Equal to 32K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.61

Field Name : hpsRspSz16k
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Payload Size Less Than or Equal to 16K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.60

Field Name : hpsRspSz8k
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Payload Size Less Than or Equal to 8K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.59

Field Name : hpsRspSz4k
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Payload Size Less Than or Equal to 4K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.58

Field Name : hpsRspSz2k
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Payload Size Less Than or Equal to 2K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.57

Field Name : hpsRspSz1k
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Payload Size Less Than or Equal to 1K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.56

Field Name : hpsRsp10
Field Type : CounterBasedGauge64
Field Status : current
Description : Response HTTP 1.0
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.55

Field Name : hpsRsp11
Field Type : CounterBasedGauge64
Field Status : current
Description : Response HTTP 1.1
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.54

Field Name : hpsReqSz256kPlus
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Payload Size Larger Than 256K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.53

Field Name : hpsReqSz256k
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Payload Size Less Than or Equal to 256K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.52

Field Name : hpsReqSz64k
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Payload Size Less Than or Equal to 64K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.51

Field Name : hpsReqSz32k
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Payload Size Less Than or Equal to 32K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.50

Field Name : hpsReqSz16k
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Payload Size Less Than or Equal to 16K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.49

Field Name : hpsReqSz8k
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Payload Size Less Than or Equal to 8K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.48

Field Name : hpsReqSz4k
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Payload Size Less Than or Equal to 4K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.47

Field Name : hpsReqSz2k
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Payload Size Less Than or Equal to 2K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.46

Field Name : hpsReqSz1k
Field Type : CounterBasedGauge64
Field Status : current

Description : Request Payload Size Less Than or Equal to 1K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.45

Field Name : httpUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Method UNKNOWN
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.44

Field Name : httpDel
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Method DELETE
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.43

Field Name : httpConnect
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Method CONNECT
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.42

Field Name : httpOptions
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Method OPTIONS
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.41

Field Name : httpTrace
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Method TRACE
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.40

Field Name : httpPost
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Method POST
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.39

Field Name : httpPut
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Method PUT
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.38

Field Name : httpHead
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Method HEAD
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.37

Field Name : httpGet
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Method GET
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.36

Field Name : rspChunk

Field Type : CounterBasedGauge64
Field Status : current
Description : Response Chunk
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.35

Field Name : http10
Field Type : CounterBasedGauge64
Field Status : current
Description : Request HTTP 1.0
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.34

Field Name : http11
Field Type : CounterBasedGauge64
Field Status : current
Description : Request HTTP 1.1
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.33

Field Name : errorCondition
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Condition
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.32

Field Name : policyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Policy Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.31

Field Name : ddosPolicyViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Policy Violation
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.30

Field Name : hpsServerRst
Field Type : CounterBasedGauge64
Field Status : current
Description : Server TCP RST Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.29

Field Name : clientRst
Field Type : CounterBasedGauge64
Field Status : current
Description : Client TCP RST Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.28

Field Name : lineTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Line Too Long
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.27

Field Name : invalidHdrVal
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Header Value Invalid
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.26

Field Name : invalidHdrName
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Header Name Invalid
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.25

Field Name : headerNameTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Header Name Too Long
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.24

Field Name : tooManyHeaders
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Header Too Many
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.23

Field Name : invalidHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Header Invalid
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.22

Field Name : negRspRemain
Field Type : CounterBasedGauge64
Field Status : current
Description : Negative Response Remain
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.21

Field Name : negReqRemain
Field Type : CounterBasedGauge64
Field Status : current
Description : Negative Request Remain
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.20

Field Name : parsereqFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Parse Request Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.19

Field Name : lowerThanMssExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Min Payload Size Fail Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.18

Field Name : dstReqRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Request Rate Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.17

Field Name : srcReqRateExceed
Field Type : CounterBasedGauge64
Field Status : current

Description : Src Request Rate Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.16

Field Name : reqContentLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Content-Length Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.15

Field Name : request
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Total
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.14

Field Name : reqRetrans
Field Type : CounterBasedGauge64
Field Status : current
Description : Retransmit Request
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.13

Field Name : retransRst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Retransmit RST
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.12

Field Name : retransPush
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Retransmit PSH
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.11

Field Name : retransFin
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Retransmit FIN
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.10

Field Name : retrans
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Retransmit
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.9

Field Name : newSyn
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.8

Field Name : httpIdleTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : Http Idle Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.7

Field Name : partialHdr

Field Type : CounterBasedGauge64
Field Status : current
Description : Partial Header
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.6

Field Name : ofo
Field Type : CounterBasedGauge64
Field Status : current
Description : Out-Of-Order Packets
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.5

Field Name : ofoQueueExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Out-Of-Order Queue Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.4

Field Name : ofoTimerExpired
Field Type : CounterBasedGauge64
Field Status : current
Description : Out-Of-Order Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.3

Field Name : reqOfo
Field Type : CounterBasedGauge64
Field Status : current
Description : Out-Of-Order Request
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.2

Field Name : reqProcessed
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets Processed
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.1

Field Name : nonQueryOpcodePassThrough
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Non Query Opcode Pass Through
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.59

Field Name : dnsOutboundQuerySessTimedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Outbound Query Session Timed Out
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.58

Field Name : dnsOutboundQueryResponseSizeExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Outbound Query Resp Size Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.57

Field Name : dnsDgRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Domain Group Domain Query Rate Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.56

Field Name : dnsQueryClassAny
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query Class ANY
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.55

Field Name : dnsQueryClassNone
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query Class NONE
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.54

Field Name : dnsQueryClassHs
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query Class HESIOD
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.53

Field Name : dnsQueryClassChaos
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query Class CHAOS
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.52

Field Name : dnsQueryClassCsnet
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query Class CSNET
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.51

Field Name : dnsQueryClassIn
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query Class INTERNET
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.50

Field Name : dnsMalform
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Malform Query (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.49

Field Name : dnsQueryClassWhitelistMiss
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query Class Whitelist Miss
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.48

Field Name : dnsNxExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : NXDOMAIN Response Rate Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.47

Field Name : dnsAuthUdpFailBl
Field Type : CounterBasedGauge64
Field Status : current

Description : DNS Auth UDP Fail Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.46

Field Name : forceTcpAuthConnHit
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Auth Force-TCP With UDP Auth Connection Hit
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.45

Field Name : dnsAuthResp
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Auth Responded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.44

Field Name : dnsAuthDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Auth Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.43

Field Name : forceTcpAuthTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Auth Force-TCP With UDP Auth Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.42

Field Name : dnsRrtypeDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Record Type Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.41

Field Name : dnsFqdnLabelCountExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : FQDN Label Count Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.40

Field Name : dnsPolicyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Policy Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.39

Field Name : dnsUdpAuthRetryGapDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Auth UDP Retry-Gap Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.38

Field Name : dnsFqdnRateByLabelCountExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : FQDN Rate by Label Count Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.37

Field Name : dnsFqdnRateByLabelCountCheck

Field Type : CounterBasedGauge64
Field Status : current
Description : FQDN Rate by Label Count Checked
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.36

Field Name : dnsDgActionDeny
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Domain Group Action Deny
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.35

Field Name : dnsDgActionPermit
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Domain Group Action Permit
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.34

Field Name : dnsQueryTypeOpt
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query Type OPT
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.33

Field Name : dnsQueryTypeSoa
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query Type SOA
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.32

Field Name : dnsQueryTypeMx
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query Type MX
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.31

Field Name : dnsQueryTypeSrv
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query Type SRV
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.30

Field Name : dnsQueryTypeAny
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query Type ANY
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.29

Field Name : dnsQueryTypeCname
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query Type CNAME
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.28

Field Name : dnsQueryTypeNs
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query Type NS
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.27

Field Name : dnsQueryTypeAaaa
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query Type AAAA
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.26

Field Name : dnsQueryTypeA
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query Type A
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.25

Field Name : dnsPktProcessed
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Packets Processed
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.24

Field Name : dnsFqdnLabelLenExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : FQDN Label Length Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.23

Field Name : dnsAuthUdpTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Auth UDP Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.22

Field Name : dnsAuthUdpFail
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Auth UDP Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.21

Field Name : dnsTcpAuthPass
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Auth Force-TCP Passed
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.20

Field Name : dnsNxBl
Field Type : CounterBasedGauge64
Field Status : current
Description : NXDOMAIN Query Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.19

Field Name : dnsNxDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : NXDOMAIN Query Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.18

Field Name : dnsIsNx
Field Type : CounterBasedGauge64
Field Status : current

Description : NXDOMAIN Response
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.17

Field Name : dnsFqdnStage2Exceed
Field Type : CounterBasedGauge64
Field Status : current
Description : FQDN Rate Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.16

Field Name : dnsAuthUdpPass
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Auth UDP Passed
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.15

Field Name : srcRateLimit4
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Request Rate 5 Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.14

Field Name : srcRateLimit3
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Request Rate 4 Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.13

Field Name : srcRateLimit2
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Request Rate 3 Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.12

Field Name : srcRateLimit1
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Request Rate 2 Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.11

Field Name : srcRateLimit0
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Request Rate 1 Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.10

Field Name : dstRateLimit4
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Request Rate 5 Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.9

Field Name : dstRateLimit3
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Request Rate 4 Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.8

Field Name : dstRateLimit2

Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Request Rate 3 Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.7

Field Name : dstRateLimit1
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Request Rate 2 Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.6

Field Name : dstRateLimit0
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Request Rate 1 Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.5

Field Name : dnsQryAnyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query ANY Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.4

Field Name : dnsMalformDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Malform Query Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.3

Field Name : dnsAuthUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Auth UDP
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.2

Field Name : forceTcpAuth
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Auth Force-TCP
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.1

Field Name : otherTotalBytesDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Total Bytes Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.49

Field Name : otherTotalBytesRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Total Bytes Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.48

Field Name : otherDropBl
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Blacklisted Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.47

Field Name : otherAnyExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.46

Field Name : srcDstOtherFilterActionWhitelist
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter Action WL
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.45

Field Name : srcDstOtherFilterActionDefaultPass
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter Action Default Pass
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.44

Field Name : srcDstOtherFilterActionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter Action Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.43

Field Name : srcDstOtherFilterActionBlacklist
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter Action Blacklist
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.42

Field Name : srcDstOtherFilterNotMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter No Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.41

Field Name : srcDstOtherFilterMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.40

Field Name : srcOtherFilterActionWhitelist
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter Action WL
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.39

Field Name : srcOtherFilterActionDefaultPass
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter Action Default Pass
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.38

Field Name : srcOtherFilterActionDrop
Field Type : CounterBasedGauge64
Field Status : current

Description : Src Filter Action Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.37

Field Name : srcOtherFilterActionBlacklist
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter Action Blacklist
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.36

Field Name : srcOtherFilterNotMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter No Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.35

Field Name : srcOtherFilterMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.34

Field Name : dstOtherFilterActionWhitelist
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Action WL
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.33

Field Name : dstOtherFilterActionDefaultPass
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Action Default Pass
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.32

Field Name : dstOtherFilterActionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Action Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.31

Field Name : dstOtherFilterActionBlacklist
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Action Blacklist
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.30

Field Name : dstOtherFilterNotMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter No Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.29

Field Name : dstOtherFilterMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.28

Field Name : otherExceedDropBrateSrcDst

Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER SrcDst KiBit Rate Drop (KiBit) (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.27

Field Name : otherExceedDropBrateSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Src KiBit Rate Drop (KiBit) (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.26

Field Name : otherExceedDropBrateDst
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Dst KiBit Rate Drop (KiBit) (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.25

Field Name : otherDropBlackUserCfgSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER SrcDst Blacklist User Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.24

Field Name : otherDropBlackSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER SrcDst Blacklist Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.23

Field Name : otherFragExceedDropSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER SrcDst Fragment Exceed Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.22

Field Name : otherExceedDropFprateSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER SrcDst Fragment Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.21

Field Name : otherExceedDropPrateSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER SrcDst Packet Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.20

Field Name : otherExceedDropAnySrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER SrcDst Exceed Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.19

Field Name : otherSrcDstDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER SrcDst Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.18

Field Name : otherDropBlackUserCfgSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Src Blacklist User Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.17

Field Name : otherDropBlackSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Src Blacklist Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.16

Field Name : otherFragExceedDropSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Src Fragment Exceed Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.15

Field Name : otherExceedDropFprateSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Src Fragment Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.14

Field Name : otherExceedDropPrateSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Src Packet Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.13

Field Name : otherExceedDropAnySrc
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Src Exceed Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.12

Field Name : otherSrcDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Src Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.11

Field Name : otherDropBlackDst
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Dst Blacklist Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.10

Field Name : otherFragExceedDropDst
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Dst Fragment Exceed Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.9

Field Name : otherExceedDropFprateDst
Field Type : CounterBasedGauge64
Field Status : current

Description : OTHER Dst Fragment Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.8

Field Name : otherExceedDropPrateDst
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Dst Packet Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.7

Field Name : otherExceedDropAnyDst
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Dst Exceed Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.6

Field Name : otherFragDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Frag Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.5

Field Name : otherDstDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Dst Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.4

Field Name : otherTotalDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Total Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.3

Field Name : otherFragRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Frag Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.2

Field Name : otherReceive
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Total Packets Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.1

Field Name : icmpTotalBytesDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Total Bytes Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.44

Field Name : icmpTotalDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Total Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.43

Field Name : icmpTotalBytesRcv

Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Total Bytes Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.42

Field Name : icmpFragDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Frag Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.41

Field Name : icmpFragRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Frag Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.40

Field Name : icmpDropBl
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Blacklisted Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.39

Field Name : icmpAnyExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.38

Field Name : icmpWildcard
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Type Wildcard
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.37

Field Name : icmpRateExceed2Bl
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Type Rate 3 Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.36

Field Name : icmpRateExceed2Drop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Type Rate 3 Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.35

Field Name : icmpRateExceed1Bl
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Type Rate 2 Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.34

Field Name : icmpRateExceed1Drop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Type Rate 2 Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.33

Field Name : icmpRateExceed0Bl
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Type Rate 1 Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.32

Field Name : icmpRateExceed0Drop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Type Rate 1 Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.31

Field Name : icmpTypeBl
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Type Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.30

Field Name : icmpType
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Type
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.29

Field Name : icmpExceedDropBrateSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP SrcDst KiBit Rate Drop (KiBit)(deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.28

Field Name : icmpExceedDropBrateSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Src KiBit Rate Drop (KiBit) (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.27

Field Name : icmpExceedDropBrateDst
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Dst KiBit Rate Drop (KiBit) (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.26

Field Name : icmpRateExceed2
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Type Rate 3 Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.25

Field Name : icmpRateExceed1
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Type Rate 2 Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.24

Field Name : icmpRateExceed0
Field Type : CounterBasedGauge64
Field Status : current

Description : ICMP Type Rate 1 Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.23

Field Name : icmpWildcardDenyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Type Wildcard Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.22

Field Name : icmpV6RfcUndefDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 RFC Undef Type Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.21

Field Name : icmpV4RfcUndefDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv4 RFC Undef Type Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.20

Field Name : icmpTypeDenyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Type Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.19

Field Name : icmpSrcDstBlDropUserCfg
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP SrcDst Blacklisted User Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.18

Field Name : icmpSrcDstBlDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP SrcDst Blacklist Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.17

Field Name : icmpSrcDstPktRateExceedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP SrcDst Packet Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.16

Field Name : icmpSrcDstAnyExceedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP SrcDst Exceed Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.15

Field Name : icmpSrcDstDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP SrcDst Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.14

Field Name : icmpDropBlackSrc

Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Src Blacklist Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.13

Field Name : icmpSrcPktRateExceedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Src Packet Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.12

Field Name : icmpSrcAnyExceedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Src Exceed Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.11

Field Name : icmpDstBlDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Dst Blacklist Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.10

Field Name : icmpExceedDropAnyDst
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Dst Exceed Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.9

Field Name : icmpOtherRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP other Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.8

Field Name : icmpEchoRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Echo Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.7

Field Name : icmpRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Total Packets Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.6

Field Name : srcIcmpBlUserConfig
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Src Blacklisted User Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.5

Field Name : icmpWildcardBl
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Type Wildcard Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.4

Field Name : icmpExceedDropPrateDst
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Dst Packet Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.3

Field Name : icmpDstDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Dst Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.2

Field Name : icmpSrcDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Src Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.1

Field Name : udpRetryGapDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Retry-Gap Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.83

Field Name : udpTotalBytesDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Total Bytes Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.82

Field Name : udpTotalBytesRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Total Bytes Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.81

Field Name : udpAuthDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Auth Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.80

Field Name : udpFragDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Frag Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.79

Field Name : udpFragRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Frag Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.78

Field Name : udpDropBl
Field Type : CounterBasedGauge64
Field Status : current

Description : UDP Blacklist Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.77

Field Name : udpAnyExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.76

Field Name : udpConnPrateBl
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Conn Pkt Rate Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.75

Field Name : udpConnPrateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Conn Pkt Rate Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.74

Field Name : ntpMonlistRespBl
Field Type : CounterBasedGauge64
Field Status : current
Description : NTP Monlist Response Blacklsited
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.73

Field Name : ntpMonlistResp
Field Type : CounterBasedGauge64
Field Status : current
Description : NTP Monlist Response
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.72

Field Name : ntpMonlistReqBl
Field Type : CounterBasedGauge64
Field Status : current
Description : NTP Monlist Request Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.71

Field Name : ntpMonlistReq
Field Type : CounterBasedGauge64
Field Status : current
Description : NTP Monlist Request
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.70

Field Name : udpPayloadTooSmallBl
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Payload Too Small Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.69

Field Name : udpPayloadTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Payload Too Small
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.68

Field Name : udpPayloadTooBigBl

Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Payload Too Large Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.67

Field Name : udpPayloadTooBig
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Payload Too Large
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.66

Field Name : udpRetryFailBl
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Retry Fail Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.65

Field Name : udpRetryPassWl
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Retry Pass WL
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.64

Field Name : udpWellknownSrcPortBl
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP SrcPort Wellknown Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.63

Field Name : udpWellknownSrcPort
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP SrcPort Wellknown
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.62

Field Name : srcDstUdpFilterActionWhitelist
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter Action WL
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.61

Field Name : srcDstUdpFilterActionDefaultPass
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter Action Default Pass
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.60

Field Name : srcDstUdpFilterActionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter Action Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.59

Field Name : srcDstUdpFilterActionBlacklist
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter Action Blacklist
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.58

Field Name : srcDstUdpFilterNotMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter No Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.57

Field Name : srcDstUdpFilterMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.56

Field Name : srcUdpFilterActionWhitelist
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter Action WL
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.55

Field Name : srcUdpFilterActionDefaultPass
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter Action Default Pass
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.54

Field Name : srcUdpFilterActionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter Action Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.53

Field Name : srcUdpFilterActionBlacklist
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter Action Blacklist
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.52

Field Name : srcUdpFilterNotMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter No Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.51

Field Name : srcUdpFilterMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.50

Field Name : exceedDropBrateSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP SrcDst KiBit Rate Drop (KiBit) (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.49

Field Name : exceedDropBrateSrc
Field Type : CounterBasedGauge64
Field Status : current

Description : UDP Src KiBit Rate Drop (KiBit) (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.48

Field Name : exceedDropBrateDst
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Dst KiBit Rate Drop (KiBit) (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.47

Field Name : udpOverLimitAuthSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP SrcDst Over Limit Authentication (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.46

Field Name : udpOverLimitAuthSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Src Over Limit Authentication (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.45

Field Name : udpOverLimitAuthDstPort
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Dst Port Over Limit Authentication (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.44

Field Name : udpOverLimitAuthDst
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Dst Over Limit Authentication (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.43

Field Name : udpAuthPass
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Auth Passed
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.42

Field Name : dstUdpFilterActionWhitelist
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Action WL
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.41

Field Name : dstUdpFilterActionDefaultPass
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Action Default Pass
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.40

Field Name : dstUdpFilterActionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Action Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.39

Field Name : dstUdpFilterActionBlacklist

Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Action Blacklist
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.38

Field Name : dstUdpFilterNotMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter No Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.37

Field Name : dstUdpFilterMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.36

Field Name : udpConnPrateDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Conn Pkt Rate Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.35

Field Name : ntpMonlistRespDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : NTP Monlist Response Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.34

Field Name : ntpMonlistReqDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : NTP Monlist Request Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.33

Field Name : udpPayloadTooSmallDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Payload Too Small Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.32

Field Name : udpPayloadTooBigDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Payload Too Large Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.31

Field Name : udpRetryTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Retry Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.30

Field Name : udpRetryFail
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Retry Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.29

Field Name : udpRetryPass
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Retry Passed
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.28

Field Name : udpRetryStart
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Retry Init
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.27

Field Name : udpWellknownSrcPortDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP SrcPort Wellknown Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.26

Field Name : udpPortZeroDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port 0 Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.25

Field Name : udpDropBlackUserCfgSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP SrcDst Blacklist User Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.24

Field Name : dropBlackSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP SrcDst Blacklist Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.23

Field Name : exceedDropClimitSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP SrcDst Connection Limit Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.22

Field Name : exceedDropCrateSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP SrcDst Connection Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.21

Field Name : exceedDropPrateSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP SrcDst Packet Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.20

Field Name : exceedAnySrcDst
Field Type : CounterBasedGauge64
Field Status : current

Description : UDP SrcDst Exceed Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.19

Field Name : udpSrcDstDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP SrcDst Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.18

Field Name : udpDropBlackUserCfgSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Src Blacklist User Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.17

Field Name : dropBlackSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Src Blacklist Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.16

Field Name : exceedDropClimitSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Src Connection Limit Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.15

Field Name : exceedDropCrateSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Src Connection Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.14

Field Name : exceedDropPrateSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Src Packet Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.13

Field Name : exceedAnySrc
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Src Exceed Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.12

Field Name : udpDropSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Src Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.11

Field Name : dropBlackDst
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Dst Blacklist Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.10

Field Name : exceedDropClimitDst

Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Dst Connection Limit Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.9

Field Name : exceedDropCrateDst
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Dst Connection Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.8

Field Name : exceedDropPrateDst
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Dst Packet Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.7

Field Name : exceedAnyDst
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Dst Exceed Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.6

Field Name : udpDropDst
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Dst Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.5

Field Name : udpTotalDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Total Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.4

Field Name : instateless
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Stateless Packets
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.3

Field Name : inudp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Total Packets Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.2

Field Name : udpSessCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.1

Field Name : hybridSynAuthAuthNoMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN Auth Hybrid Auth no match
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.148

Field Name : hybridSynAuthEntryAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN Auth Hybrid Entry Aged Out
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.147

Field Name : tcpSmallWindowDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Small-Window Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.146

Field Name : tcpSmallWindowBl
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Small-Window Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.145

Field Name : tcpSmallWindow
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Small-Window Total
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.144

Field Name : hybridSynAuthMethodChange
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN Auth Hybrid Method Change
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.143

Field Name : tcpInvalidSynackRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Invalid SYNACK Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.142

Field Name : hybridSynAuthValidFail
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN Auth Hybrid Valid SYNACK Auth Fail
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.141

Field Name : hybridSynAuthInvalidFail
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN Auth Hybrid Invalid SYNACK Auth Fail
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.140

Field Name : hybridSynAuthValidPass
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN Auth Hybrid Valid SYNACK Auth Pass
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.139

Field Name : hybridSynAuthInvalidPass
Field Type : CounterBasedGauge64
Field Status : current

Description : SYN Auth Hybrid Invalid SYNACK Auth Pass
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.138

Field Name : hybridSynAuthLookupFail
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN Auth Hybrid Lookup Fail
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.137

Field Name : hybridSynAuthFilterFull
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN Auth Hybrid Filter Full
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.136

Field Name : hybridSynAuthInvalidSaSent
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN Auth Hybrid Invalid SYNACK Sent
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.135

Field Name : hybridSynAuthValidSaSent
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN Auth Hybrid Valid SYNACK Sent
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.134

Field Name : hybridSynAuthUnknownFail
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN Auth Hybrid Unknown Auth Fail
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.133

Field Name : hybridSynAuthUnknownPass
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN Auth Hybrid Unknown Auth Pass
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.132

Field Name : tcpAuthRst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Auth Reset
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.131

Field Name : tcpProgressionViolationExceedReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Progression: Violation Exceeded Reset
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.130

Field Name : tcpProgressionViolationExceedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Progression: Violation Exceeded Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.129

Field Name : tcpProgressionViolationExceedBl

Field Type : CounterBasedGauge64
Field Status : current
Description : Progression: Violation Exceeded Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.128

Field Name : tcpProgressionViolationExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Progression: Violation Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.127

Field Name : tcpSynTfoRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN TFO Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.126

Field Name : tcpPerConnZwindowRateExceedBl
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Conn Zero-Window Rate Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.125

Field Name : tcpPerConnZwindowRateExceedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Conn Zero-Window Rate Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.124

Field Name : tcpPerConnRexmitRateExceedBl
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Conn Retransmit Rate Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.123

Field Name : tcpPerConnRexmitRateExceedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Conn Retransmit Rate Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.122

Field Name : tcpPerConnOfoRateExceedBl
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Conn Out-Of-Seq Rate Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.121

Field Name : tcpPerConnOfoRateExceedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Conn Out-Of-Seq Rate Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.120

Field Name : tcpActionOnSynBl
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Retry Timeout Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.119

Field Name : tcpActionOnAckBl
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP ACK Retry Timeout Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.118

Field Name : tcpTotalBytesDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Total Bytes Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.117

Field Name : tcpTotalBytesRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Total Bytes Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.116

Field Name : tcpAuthResp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Auth Responded
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.115

Field Name : tcpAuthDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Auth Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.114

Field Name : tcpFragDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Frag Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.113

Field Name : tcpFragRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Frag Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.112

Field Name : tcpDropBl
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Blacklist Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.111

Field Name : tcpAnyExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.110

Field Name : tcpPerConnPrateExceedBl
Field Type : CounterBasedGauge64
Field Status : current

Description : TCP Conn Pkt Rate Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.109

Field Name : tcpRetransmitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Retransmit Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.108

Field Name : tcpZeroWindowDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Zero-Window Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.107

Field Name : tcpOutOfSeqDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Out-Of-Seq Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.106

Field Name : synAuthPassWl
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Auth Pass WL
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.105

Field Name : srcDstTcpFilterActionWhitelist
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter Action WL
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.104

Field Name : srcDstTcpFilterActionDefaultPass
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter Action Default Pass
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.103

Field Name : srcDstTcpFilterActionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter Action Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.102

Field Name : srcDstTcpFilterActionBlacklist
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter Action Blacklist
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.101

Field Name : srcDstTcpFilterNotMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter No Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.100

Field Name : srcDstTcpFilterMatch

Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.99

Field Name : srcTcpFilterActionWhitelist
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter Action WL
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.98

Field Name : srcTcpFilterActionDefaultPass
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter Action Default Pass
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.97

Field Name : srcTcpFilterActionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter Action Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.96

Field Name : srcTcpFilterActionBlacklist
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter Action Blacklist
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.95

Field Name : srcTcpFilterNotMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter No Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.94

Field Name : srcTcpFilterMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.93

Field Name : dstTcpFilterActionWhitelist
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Action WL
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.92

Field Name : tcpConcurrent
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Concurrent Port Access
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.91

Field Name : tcpExceedDropBrateSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SrcDst KiBit Rate Drop (KiBit) (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.90

Field Name : tcpExceedDropBrateSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Src KiBit Rate Drop (KiBit) (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.89

Field Name : tcpExceedDropBrateDst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Dst KiBit Rate Drop (KiBit) (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.88

Field Name : tcpOverLimitSynCookieSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SrcDst Over Limit Cookie (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.87

Field Name : tcpOverLimitSynCookieSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Src Over Limit Cookie (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.86

Field Name : tcpOverLimitSynAuthSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SrcDst Over Limit Authentication (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.85

Field Name : tcpOverLimitSynAuthSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Src Over Limit Authentication (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.84

Field Name : dstTcpFilterActionDefaultPass
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Action Default Pass
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.83

Field Name : dstTcpFilterActionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Action Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.82

Field Name : dstTcpFilterActionBlacklist
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Action Blacklist
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.81

Field Name : dstTcpFilterNotMatch
Field Type : CounterBasedGauge64
Field Status : current

Description : Dst Filter No Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.80

Field Name : dstTcpFilterMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.79

Field Name : tcpUnauthRstDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Unauth RST Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.78

Field Name : tcpActionOnSynGapPass
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Retry Retry-Gap Passed
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.77

Field Name : tcpActionOnSynGapDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Retry Retry-Gap Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.76

Field Name : tcpActionOnSynReset
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Retry Timeout Reset
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.75

Field Name : tcpActionOnSynTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Retry Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.74

Field Name : tcpActionOnSynFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Retry Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.73

Field Name : tcpActionOnSynPassed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Retry Passed
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.72

Field Name : tcpActionOnSynStart
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Retry Init
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.71

Field Name : tcpNewConnAckRetryGapDrop

Field Type : CounterBasedGauge64
Field Status : current
Description : TCP New-Connection-Ack-Retry-Gap Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.70

Field Name : tcpNewConnAckRetryGapReset
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP New-Connection-Ack-Retry-Gap Reset (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.69

Field Name : tcpNewConnAckRetryGapTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP New-Connection-Ack-Retry-Gap Timeout (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.68

Field Name : tcpNewConnAckRetryGapFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP New-Connection-Ack-Retry-Gap Fail (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.67

Field Name : tcpNewConnAckRetryGapPassed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP New-Connection-Ack-Retry-Gap Pass (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.66

Field Name : tcpNewConnAckRetryGapStart
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP New-Connection-Ack-Retry-Gap Initialize (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.65

Field Name : tcpActionOnAckGapPass
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP ACK Retry Retry-Gap Passed
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.64

Field Name : tcpActionOnAckGapDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP ACK Retry Retry-Gap Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.63

Field Name : tcpPerConnPrateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Conn Pkt Rate Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.62

Field Name : tcpRexmitSynLimitBl
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Retransmit SYN Exceed Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.61

Field Name : tcpRetransmitBl
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Retransmit Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.60

Field Name : tcpOutOfSeqBl
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Out-Of-Seq Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.59

Field Name : tcpZeroWindowBl
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Zero-Window Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.58

Field Name : tcpRexmitSynLimitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Retransmit SYN Exceed Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.57

Field Name : tcpRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Retransmit Total
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.56

Field Name : tcpZeroWindow
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Zero-Window Total
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.55

Field Name : tcpOutOfSeq
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Out-Of-Seq Total
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.54

Field Name : tcpAckNoSyn
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP ACK No SYN
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.53

Field Name : tcpActionOnAckReset
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP ACK Retry Timeout Reset
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.52

Field Name : tcpActionOnAckTimeout
Field Type : CounterBasedGauge64
Field Status : current

Description : TCP ACK Retry Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.51

Field Name : tcpActionOnAckFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP ACK Retry Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.50

Field Name : tcpActionOnAckPassed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP ACK Retry Passed
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.49

Field Name : tcpActionOnAckMatched
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP ACK Retry Matched
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.48

Field Name : tcpActionOnAckStart
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP ACK Retry Init
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.47

Field Name : tcpOverLimitSynCookieDstPort
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Dst Port Over Limit Cookie (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.46

Field Name : tcpOverLimitSynAuthDstPort
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Dst Port Over Limit Authentication (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.45

Field Name : tcpOverLimitSynCookieDst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Dst Over Limit Cookie (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.44

Field Name : tcpOverLimitSynAuthDst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Dst Over Limit Authentication (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.43

Field Name : synAuthSkip
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Auth Skipped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.42

Field Name : synAuthPass

Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Auth Passed
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.41

Field Name : tcpSyncookiePass
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Cookie Passed
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.40

Field Name : tcpSyncookieFailBl
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Cookie Blacklist Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.39

Field Name : tcpSyncookieHwMissing
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Cookie HW Missed
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.38

Field Name : tcpSyncookieCheckFail
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Cookie Check Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.37

Field Name : tcpSyncookieSentFail
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Cookie Send Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.36

Field Name : tcpSyncookieSent
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Cookie Sent
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.35

Field Name : tcpPortZeroDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port 0 Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.34

Field Name : tcpDropBlackUserCfgSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SrcDst Blacklist User Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.33

Field Name : tcpDropBlackSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SrcDst Blacklist Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.32

Field Name : tcpExceedDropClimitSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SrcDst Connection Limit Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.31

Field Name : tcpExceedDropCrateSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SrcDst Connection Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.30

Field Name : tcpExceedDropPrateSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SrcDst Packet Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.29

Field Name : tcpExceedDropAnySrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SrcDst Exceed Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.28

Field Name : tcpSrcDstDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SrcDst Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.27

Field Name : tcpDropBlackUserCfgSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Src Blacklist User Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.26

Field Name : tcpDropBlackSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Src Blacklist Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.25

Field Name : tcpExceedDropClimitSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Src Connection Limit Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.24

Field Name : tcpExceedDropCrateSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Src Connection Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.23

Field Name : tcpExceedDropPrateSrc
Field Type : CounterBasedGauge64
Field Status : current

Description : TCP Src Packet Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.22

Field Name : tcpExceedDropAnySrc
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Src Exceed Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.21

Field Name : tcpSrcDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Src Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.20

Field Name : tcpDropBlackDst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Dst Blacklist Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.19

Field Name : tcpExceedDropClimitDst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Dst Connection Limit Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.18

Field Name : tcpExceedDropCrateDst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Dst Connection Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.17

Field Name : tcpExceedDropPrateDst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Dst Packet Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.16

Field Name : tcpExceedDropAnyDst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Dst Exceed Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.15

Field Name : tcpDstDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Dst Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.14

Field Name : tcpTotalDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Total Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.13

Field Name : tcpSynRate

Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Rate Per Sec
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.12

Field Name : tcpResetServer
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Reset Server
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.11

Field Name : tcpResetClient
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Reset Client
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.10

Field Name : tcpOutrst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Outbound RST
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.9

Field Name : tcpRstRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP RST Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.8

Field Name : tcpFinRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP FIN Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.7

Field Name : tcpAckRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP ACK Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.6

Field Name : tcpSynAckRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN ACK Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.5

Field Name : tcpInvalidSynRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Invalid SYN Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.4

Field Name : tcpSynRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.3

Field Name : intcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Total Packets Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.2

Field Name : tcpSessCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.1

Field Name : filterDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Extracted Filter Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.81.1.5

Field Name : filterMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Extracted Filter Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.81.1.4

Field Name : genericError
Field Type : CounterBasedGauge64
Field Status : current
Description : Pattern Recognition: Exceptions
OID : 1.3.6.1.4.1.22610.2.4.10.102.81.1.3

Field Name : notFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Pattern Recognition: Pattern Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.102.81.1.2

Field Name : proceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Pattern Recognition: Engine Started
OID : 1.3.6.1.4.1.22610.2.4.10.102.81.1.1

Field Name : quicCreateConnInitOnly
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Create Connection on Initial Only
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.30

Field Name : quicDcidPktRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC DCID Packet Rate Exceed
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.29

Field Name : quicAeadPktRateExceed
Field Type : CounterBasedGauge64
Field Status : current

Description : QUIC AEAD Packet Rate Exceed
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.28

Field Name : quic0rttDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC 0RTT Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.27

Field Name : quicDecryptSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Decrypt Success
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.26

Field Name : quicEncryptSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Encrypt Success
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.25

Field Name : quicDecryptFail
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Decrypt Fail
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.24

Field Name : quicEncryptFail
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Encrypt Fail
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.23

Field Name : quicShortHeadrActionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Short Header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.22

Field Name : quicShortHeaderReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Short Header Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.21

Field Name : quicInvalidRetryToken
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Invalid Retry Token
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.20

Field Name : quicConnectionCloseSent
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Connection Close Sent
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.19

Field Name : quicRetryAuthFail

Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Retry Auth Fail
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.18

Field Name : quicRetryAuthPass
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Retry Auth Pass
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.17

Field Name : quicRetryAuthSent
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Retry Auth Sent
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.16

Field Name : quicFixedBitNotSet
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Fixed Bit Not Set
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.15

Field Name : quicMalformedScidLenMaxExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Malformed SCID Len Max Exceed
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.14

Field Name : quicMalformedDcidLenMaxExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Malformed DCID Len Max Exceed
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.13

Field Name : quicMalformedActionBlacklist
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Malformed Action Blacklist
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.12

Field Name : quicMalformedActionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Malformed Action Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.11

Field Name : quicMalformedActionTaken
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Malformed Action Taken
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.10

Field Name : quicVersionMatchActionBlacklist
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Version Match Action Blacklist
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.9

Field Name : quicVersionMatchActionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Version Match Action Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.8

Field Name : quicVersionMatchActionTaken
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Version Match Action Taken
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.7

Field Name : quicHandshakeReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Handshake Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.6

Field Name : quic0rttRecevied
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC 0RTT Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.5

Field Name : quicRetryReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Retry Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.4

Field Name : quicVersionNegotiationReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Version Negotiation Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.3

Field Name : quicInitialReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Initial Packet Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.2

Field Name : quicPacketReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Packet Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.1

Field Name : aamAaaPolicySTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.3.1.1

Field Name : aamAaaPolicySEntry
Field Type : CounterBasedGauge64
Field Status : current

Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.3.1.1.1

Field Name : failureBypass
Field Type : CounterBasedGauge64
Field Status : current
Description : Auth Failure Bypass
OID : 1.3.6.1.4.1.22610.2.4.10.103.3.1.1.1.8

Field Name : error
Field Type : CounterBasedGauge64
Field Status : current
Description : Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.3.1.1.1.7

Field Name : reqSkip
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Skipped
OID : 1.3.6.1.4.1.22610.2.4.10.103.3.1.1.1.6

Field Name : reqBypass
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Bypassed
OID : 1.3.6.1.4.1.22610.2.4.10.103.3.1.1.1.5

Field Name : reqAuth
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Matching Authentication Template
OID : 1.3.6.1.4.1.22610.2.4.10.103.3.1.1.1.4

Field Name : reqReject
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Rejected
OID : 1.3.6.1.4.1.22610.2.4.10.103.3.1.1.1.3

Field Name : req
Field Type : CounterBasedGauge64
Field Status : current
Description : Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.3.1.1.1.2

Field Name : aamAaaPolicyName
Field Type : String
Field Status : current
Description : Specify AAA policy name
OID : 1.3.6.1.4.1.22610.2.4.10.103.3.1.1.1.1

Field Name : aamJwtAuthorizationSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.8.1.1

Field Name : aamJwtAuthorizationSEntry

Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.8.1.1.1

Field Name : jwtOtherError
Field Type : CounterBasedGauge64
Field Status : current
Description : JWT Other Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.8.1.1.1.9

Field Name : jwtSignatureFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : JWT Signature Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.8.1.1.1.8

Field Name : jwtTokenExpired
Field Type : CounterBasedGauge64
Field Status : current
Description : JWT Token Expired
OID : 1.3.6.1.4.1.22610.2.4.10.103.8.1.1.1.7

Field Name : jwtMissingClaim
Field Type : CounterBasedGauge64
Field Status : current
Description : JWT Missing Claim
OID : 1.3.6.1.4.1.22610.2.4.10.103.8.1.1.1.6

Field Name : jwtMissingToken
Field Type : CounterBasedGauge64
Field Status : current
Description : JWT Missing Token
OID : 1.3.6.1.4.1.22610.2.4.10.103.8.1.1.1.5

Field Name : jwtAuthorizeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : JWT Authorize Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.8.1.1.1.4

Field Name : jwtAuthorizeSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : JWT Authorize Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.8.1.1.1.3

Field Name : jwtRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : JWT Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.8.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Specify JWT authorization template name
OID : 1.3.6.1.4.1.22610.2.4.10.103.8.1.1.1.1

Field Name : aamAuthenticationRelaySamlSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.6.1.1

Field Name : aamAuthenticationRelaySamlSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.6.1.1.1

Field Name : aamAuthRelaySamlError
Field Type : CounterBasedGauge64
Field Status : current
Description : Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.6.1.1.1.5

Field Name : aamAuthRelaySamlFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.6.1.1.1.4

Field Name : aamAuthRelaySamlSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.6.1.1.1.3

Field Name : aamAuthRelaySamlRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.6.1.1.1.2

Field Name : aamAuthRelaySAMLName
Field Type : String
Field Status : current
Description : Specify SAML authentication relay name
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.6.1.1.1.1

Field Name : pollingControlError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Polling Control Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.1.13

Field Name : jobStartError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Job Start Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.1.12

Field Name : responseOther
Field Type : CounterBasedGauge64
Field Status : current

Description : Total Other Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.1.11

Field Name : responseTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Timeout Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.1.10

Field Name : responseError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Error Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.1.9

Field Name : responseFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Failure Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.1.8

Field Name : responseSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Success Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.1.7

Field Name : requestDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Dropped Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.1.6

Field Name : requestNormal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Normal Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.1.5

Field Name : otherError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Other Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.1.4

Field Name : timeoutError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.1.3

Field Name : responseGet
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Response Get
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.1.2

Field Name : requestSend

Field Type : CounterBasedGauge64
Field Status : current
Description : Total Request Send
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.1.1

Field Name : aamAuthRelayKerberosSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.2.1.1

Field Name : aamAuthRelayKerberosSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.2.1.1.1

Field Name : tickets
Field Type : CounterBasedGauge64
Field Status : current
Description : Tickets
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.2.1.1.1.5

Field Name : currentRequestsOfUser
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Pending Requests of User
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.2.1.1.1.4

Field Name : responseReceive
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Receive
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.2.1.1.1.3

Field Name : requestSend
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Send
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.2.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Specify Kerberos authentication relay name
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.2.1.1.1.1

Field Name : aamAuthenticationRelayOauthSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.7.1.1

Field Name : aamAuthenticationRelayOauthSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.7.1.1.1

Field Name : relayFail
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.7.1.1.1.4

Field Name : relaySucc
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.7.1.1.1.3

Field Name : relayReq
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.7.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Specify oauth authentication relay name
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.7.1.1.1.1

Field Name : aamAuthenticationServiceGroupSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.9.1.1

Field Name : aamAuthenticationServiceGroupSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.9.1.1.1

Field Name : serviceCurrConnOverflow
Field Type : CounterBasedGauge64
Field Status : current
Description : Current connection counter overflow count
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.9.1.1.1.13

Field Name : serviceResp5xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Group response 5xx count
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.9.1.1.1.12

Field Name : serviceResp4xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Group response 4xx count
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.9.1.1.1.11

Field Name : serviceResp3xx
Field Type : CounterBasedGauge64
Field Status : current

Description : Service Group response 3xx count
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.9.1.1.1.10

Field Name : serviceResp2xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Group response 2xx count
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.9.1.1.1.9

Field Name : serviceRespCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Group response count
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.9.1.1.1.8

Field Name : serviceReqCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Group request count
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.9.1.1.1.7

Field Name : serviceUnhealthyHost
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Group unhealthy host count
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.9.1.1.1.6

Field Name : serviceHealthyHost
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Group healthy host count
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.9.1.1.1.5

Field Name : servicePeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Peak connection count for the Service Group
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.9.1.1.1.4

Field Name : serverSelectionFailReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Resets sent out for Service selection failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.9.1.1.1.3

Field Name : serverSelectionFailDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Drops due to Service selection failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.9.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Specify AAM service group name
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.9.1.1.1.1

Field Name : otherError

Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.17.1.1.8

Field Name : relayFail
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.17.1.1.7

Field Name : relaySucc
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.17.1.1.6

Field Name : relayReq
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.17.1.1.5

Field Name : authError
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.17.1.1.4

Field Name : authFail
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.17.1.1.3

Field Name : authSucc
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.17.1.1.2

Field Name : authReq
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.17.1.1.1

Field Name : aamAuthSamlOtherError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Other Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.22

Field Name : aamAuthSamlGlobalRelayError
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.21

Field Name : aamAuthSamlGlobalRelayFailure
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.20

Field Name : aamAuthSamlGlobalRelaySuccess
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.19

Field Name : aamAuthSamlGlobalRelayRequest
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.18

Field Name : aamAuthSamlGlobalParSloSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Partial Logout Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.17

Field Name : aamAuthSamlGlobalLocSloSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Local Logout Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.16

Field Name : aamAuthSamlGlobalGloSloSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Global Logout Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.15

Field Name : aamAuthSamlGlobalSpSloReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SP-initiated Single Logout Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.14

Field Name : aamAuthSamlGlobalSloError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Single Logout Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.13

Field Name : aamAuthSamlGlobalSloSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Single Logout Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.12

Field Name : aamAuthSamlGlobalSloReq
Field Type : CounterBasedGauge64
Field Status : current

Description : Total Single Logout Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.11

Field Name : aamAuthSamlGlobalAcsError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SAML Single-Sign-On Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.10

Field Name : aamAuthSamlGlobalAcsAuthzFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SAML Single-Sign-On Authorization Fail
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.9

Field Name : aamAuthSamlGlobalAcsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SAML Single-Sign-On Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.8

Field Name : aamAuthSamlGlobalAcsReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SAML Single-Sign-On Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.7

Field Name : aamAuthSamlGlobalLoginAuthResp
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Login Authentication Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.6

Field Name : aamAuthSamlGlobalLoginAuthReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Login Authentication Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.5

Field Name : aamAuthSamlGlobalSpMetadataExportSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Toal Metadata Export Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.4

Field Name : aamAuthSamlGlobalSpMetadataExportReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Metadata Export Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.3

Field Name : responsesFromA10saml
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Response from A10 SAML Service
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.2

Field Name : requestsToA10saml

Field Type : CounterBasedGauge64
Field Status : current
Description : Total Request to A10 SAML Service
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.1

Field Name : aamAuthAcountResponseOther
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Other Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.7.1.7

Field Name : aamAuthAcountResponseTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Timeout Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.7.1.6

Field Name : aamAuthAcountResponseError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Error Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.7.1.5

Field Name : aamAuthAcountResponseFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Failure Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.7.1.4

Field Name : aamAuthAcountResponseSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Success Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.7.1.3

Field Name : aamAuthAcountRequestDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Dropped Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.7.1.2

Field Name : aamAuthAccountRequestNormal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Normal Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.7.1.1

Field Name : accountingFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Accounting Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.20

Field Name : accountingSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Accounting Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.19

Field Name : accountingRequestSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Accounting-Request Sent
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.18

Field Name : aamAuthServerRadiusPollingControlError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Polling Control Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.17

Field Name : aamAuthServerRadiusJobStartError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Job Start Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.16

Field Name : aamAuthServerRadiusResponseOther
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Other Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.15

Field Name : aamAuthServerRadiusResponseTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Timeout Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.14

Field Name : aamAuthServerRadiusResponseError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Error Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.13

Field Name : aamAuthServerRadiusResponseFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Failure Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.12

Field Name : aamAuthServerRadiusResponseSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Success Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.11

Field Name : aamAuthServerRadiusRequestDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Dropped Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.10

Field Name : aamAuthServerRadiusRequestNormal
Field Type : CounterBasedGauge64
Field Status : current

Description : Total Normal Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.9

Field Name : aamAuthServerRadiusRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.8

Field Name : aamAuthServerRadiusOtherError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Other Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.7

Field Name : aamAuthServerRadiusTimeoutError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.6

Field Name : accessChallenge
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Access-Challenge Message Receive
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.5

Field Name : aamAuthServerRadiusAuthorizeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Authorization Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.4

Field Name : aamAuthServerRadiusAuthorizeSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Authorization Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.3

Field Name : authenFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Authentication Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.2

Field Name : authenSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Authentication Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.1

Field Name : aamAuthServerRadiusSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.2.1.1

Field Name : aamAuthServerRadiusSEntry

Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.2.1.1.1

Field Name : accountingFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Accounting Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.2.1.1.1.12

Field Name : accountingSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Accounting Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.2.1.1.1.11

Field Name : accountingRequestSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Accounting-Request Sent
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.2.1.1.1.10

Field Name : request
Field Type : CounterBasedGauge64
Field Status : current
Description : Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.2.1.1.1.9

Field Name : otherError
Field Type : CounterBasedGauge64
Field Status : current
Description : Other Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.2.1.1.1.8

Field Name : timeoutError
Field Type : CounterBasedGauge64
Field Status : current
Description : Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.2.1.1.1.7

Field Name : accessChallenge
Field Type : CounterBasedGauge64
Field Status : current
Description : Access-Challenge Message Receive
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.2.1.1.1.6

Field Name : authorizeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Authorization Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.2.1.1.1.5

Field Name : authorizeSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Authorization Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.2.1.1.1.4

Field Name : authenFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Authentication Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.2.1.1.1.3

Field Name : authenSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Authentication Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.2.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Specify RADIUS authentication server name
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.2.1.1.1.1

Field Name : aamAuthServerOcspPollingControlError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total OCSP Polling Control Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.19

Field Name : aamAuthServerOcspJobStartError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total OCSP Job Start Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.18

Field Name : aamAuthServerOcspResponseOther
Field Type : CounterBasedGauge64
Field Status : current
Description : Total OCSP Other Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.17

Field Name : aamAuthServerOcspResponseTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : Total OCSP Timeout Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.16

Field Name : aamAuthServerOcspResponseError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total OCSP Error Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.15

Field Name : aamAuthServerOcspResponseFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total OCSP Failure Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.14

Field Name : aamAuthServerOcspResponseSuccess
Field Type : CounterBasedGauge64
Field Status : current

Description : Total OCSP Success Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.13

Field Name : aamAuthServerOcspRequestDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Total OCSP Dropped Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.12

Field Name : aamAuthServerOcspRequestNormal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total OSCP Normal Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.11

Field Name : staplingResponseOther
Field Type : CounterBasedGauge64
Field Status : current
Description : Total OCSP Stapling Other Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.10

Field Name : staplingResponseTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : Total OCSP Stapling Timeout Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.9

Field Name : staplingResponseError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total OCSP Stapling Error Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.8

Field Name : staplingResponseFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total OCSP Stapling Failure Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.7

Field Name : staplingResponseSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total OCSP Stapling Success Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.6

Field Name : staplingRequestDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Total OCSP Stapling Dropped Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.5

Field Name : staplingRequestNormal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total OSCP Stapling Normal Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.4

Field Name : staplingCertificateUnknown

Field Type : CounterBasedGauge64
Field Status : current
Description : Total OCSP Stapling Unknown Certificate Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.3

Field Name : staplingCertificateRevoked
Field Type : CounterBasedGauge64
Field Status : current
Description : Total OCSP Stapling Revoked Certificate Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.2

Field Name : staplingCertificateGood
Field Type : CounterBasedGauge64
Field Status : current
Description : Total OCSP Stapling Good Certificate Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.1

Field Name : authServerOcspSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.2.1.1

Field Name : authServerOcspSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.2.1.1.1

Field Name : staplingFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Handle OCSP response failed
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.2.1.1.1.13

Field Name : staplingTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSP Stapling Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.2.1.1.1.12

Field Name : staplingCertificateUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSP Stapling Unknown Certificate Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.2.1.1.1.11

Field Name : staplingCertificateRevoked
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSP Stapling Revoked Certificate Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.2.1.1.1.10

Field Name : staplingCertificateGood
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSP Stapling Good Certificate Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.2.1.1.1.9

Field Name : staplingRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSP Stapling Request Send
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.2.1.1.1.8

Field Name : fail
Field Type : CounterBasedGauge64
Field Status : current
Description : Handle OCSP response failed
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.2.1.1.1.7

Field Name : timeout
Field Type : CounterBasedGauge64
Field Status : current
Description : Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.2.1.1.1.6

Field Name : certificateUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : Unknown Certificate Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.2.1.1.1.5

Field Name : certificateRevoked
Field Type : CounterBasedGauge64
Field Status : current
Description : Revoked Certificate Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.2.1.1.1.4

Field Name : certificateGood
Field Type : CounterBasedGauge64
Field Status : current
Description : Good Certificate Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.2.1.1.1.3

Field Name : request
Field Type : CounterBasedGauge64
Field Status : current
Description : Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.2.1.1.1.2

Field Name : aamAuthServerOcspName
Field Type : String
Field Status : current
Description : Specify OCSP authentication server name
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.2.1.1.1.1

Field Name : pwChangeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total password change failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.27

Field Name : pwChangeSuccess
Field Type : CounterBasedGauge64
Field Status : current

Description : Total password change success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.26

Field Name : pwExpiry
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Password expiry
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.25

Field Name : ldapsInuseConnNum
Field Type : CounterBasedGauge64
Field Status : current
Description : LDAPS In-use Connection Number
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.24

Field Name : ldapsIdleConnNum
Field Type : CounterBasedGauge64
Field Status : current
Description : LDAPS Idle Connection Number
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.23

Field Name : sslSessionFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : TLS/SSL Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.22

Field Name : sslSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : TLS/SSL Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.21

Field Name : aamAuthServerLdapPollingControlError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Polling Control Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.20

Field Name : aamAuthServerLdapJobStartError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Job Start Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.19

Field Name : aamAuthServerLdapResponseOther
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Other Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.18

Field Name : aamAuthServerLdapResponseTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Timeout Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.17

Field Name : aamAuthServerLdapResponseError

Field Type : CounterBasedGauge64
Field Status : current
Description : Total Error Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.16

Field Name : aamAuthServerLdapResponseFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Failure Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.15

Field Name : aamAuthServerLdapResponseSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Success Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.14

Field Name : aamAuthServerLdapRequestDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Dropped Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.13

Field Name : aamAuthServerLdapRequestNormal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Normal Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.12

Field Name : aamAuthServerLdapRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.11

Field Name : aamAuthServerLdapOtherError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Other Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.10

Field Name : aamAuthServerLdapTimeoutError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.9

Field Name : aamAuthServerLdapAuthorizeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Authorization Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.8

Field Name : aamAuthServerLdapAuthorizeSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Authorization Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.7

Field Name : aamAuthServerLdapSearchFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Search Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.6

Field Name : aamAuthServerLdapSearchSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Search Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.5

Field Name : aamAuthServerLdapBindFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User Bind Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.4

Field Name : aamAuthServerLdapBindSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User Bind Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.3

Field Name : aamAuthServerLdapAdminBindFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Admin Bind Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.2

Field Name : aamAuthServerLdapAdminBindSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Admin Bind Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.1

Field Name : aamAuthServerLdapSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1

Field Name : aamAuthServerLdapSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1

Field Name : pwChangeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Password change failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.17

Field Name : pwChangeSuccess
Field Type : CounterBasedGauge64
Field Status : current

Description : Password change success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.16

Field Name : pwExpiry
Field Type : CounterBasedGauge64
Field Status : current
Description : Password expiry
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.15

Field Name : sslSessionFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : TLS/SSL Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.14

Field Name : sslSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : TLS/SSL Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.13

Field Name : request
Field Type : CounterBasedGauge64
Field Status : current
Description : Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.12

Field Name : aamAuthServerOtherError
Field Type : CounterBasedGauge64
Field Status : current
Description : Other Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.11

Field Name : aamAuthServerTimeoutError
Field Type : CounterBasedGauge64
Field Status : current
Description : Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.10

Field Name : authorizeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Authorization Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.9

Field Name : authorizeSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Authorization Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.8

Field Name : searchFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Search Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.7

Field Name : searchSuccess

Field Type : CounterBasedGauge64
Field Status : current
Description : Search Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.6

Field Name : bindFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : User Bind Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.5

Field Name : bindSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : User Bind Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.4

Field Name : adminBindFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Admin Bind Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.3

Field Name : adminBindSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Admin Bind Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Specify LDAP authentication server name
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.1

Field Name : kerberosKdcKeytabCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Kerberos KDC Keytab Count
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.42

Field Name : kerberosDeleteKdcKeytabFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos KDC Keytab Deletion Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.41

Field Name : kerberosDeleteKdcKeytabSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos KDC Keytab Deletion Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.40

Field Name : kerberosGenerateKdcKeytabFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos KDC Keytab Generation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.39

Field Name : kerberosGenerateKdcKeytabSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos KDC Keytab Generation Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.38

Field Name : kerberosValidateKdcFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos KDC Validation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.37

Field Name : kerberosValidateKdcSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos KDC Validation Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.36

Field Name : kerberosPwChangeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos password change failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.35

Field Name : kerberosPwChangeSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos password change success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.34

Field Name : kerberosPwExpiry
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos password expiry
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.33

Field Name : kerberosPollingControlError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos Polling Control Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.19

Field Name : kerberosJobStartError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos Job Start Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.18

Field Name : kerberosResponseOther
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos Other Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.17

Field Name : kerberosResponseTimeout
Field Type : CounterBasedGauge64
Field Status : current

Description : Total Kerberos Timeout Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.16

Field Name : kerberosResponseError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos Error Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.15

Field Name : kerberosResponseFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos Failure Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.14

Field Name : kerberosResponseSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos Success Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.13

Field Name : kerberosRequestDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos Dropped Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.12

Field Name : kerberosRequestNormal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos Normal Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.11

Field Name : kerberosOtherError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos Other Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.4

Field Name : kerberosTimeoutError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.3

Field Name : kerberosResponseGet
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.2

Field Name : kerberosRequestSend
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.1

Field Name : aamAuthServerWindowsSTable

Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.2.1.1

Field Name : aamAuthServerWindowsSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.2.1.1.1

Field Name : krbValidateKdcFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Kerberos KDC Validation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.2.1.1.1.20

Field Name : krbValidateKdcSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Kerberos KDC Validation Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.2.1.1.1.19

Field Name : krbPwChangeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Kerberos password change failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.2.1.1.1.8

Field Name : krbPwChangeSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Kerberos password change success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.2.1.1.1.7

Field Name : krbPwExpiry
Field Type : CounterBasedGauge64
Field Status : current
Description : Kerberos password expiry
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.2.1.1.1.6

Field Name : krbOtherError
Field Type : CounterBasedGauge64
Field Status : current
Description : Kerberos Other Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.2.1.1.1.5

Field Name : krbTimeoutError
Field Type : CounterBasedGauge64
Field Status : current
Description : Kerberos Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.2.1.1.1.4

Field Name : krbGetRespSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Kerberos Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.2.1.1.1.3

Field Name : krbSendReqSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Kerberos Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.2.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Specify Windows authentication server name
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.2.1.1.1.1

Field Name : authCtxNum
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Auth Contexts
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.25

Field Name : domainWlistUnmatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Total DOMAIN WHITELIST unmatch number
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.24

Field Name : domainWlistMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Total DOMAIN WHITELIST match number
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.23

Field Name : dnsResolveFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total AAM DNS resolve failed
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.22

Field Name : activeUser
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Active Users
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.21

Field Name : activeSession
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Active Auth-Sessions
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.20

Field Name : authzFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Authorization failure number
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.19

Field Name : authzSuccess
Field Type : CounterBasedGauge64
Field Status : current

Description : Total Authorization success number
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.18

Field Name : authnFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Authentication failure number
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.17

Field Name : authnSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Authentication success number
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.16

Field Name : aflexAuthzFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Authorization failure number in aFleX
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.15

Field Name : aflexAuthzSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Authorization success number in aFleX
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.14

Field Name : getSocketOptionFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total AAM Get Socket Option Failed
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.13

Field Name : totalRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Request Received by A10 Auth Service
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.12

Field Name : createTimerFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total AAM Timer Creation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.11

Field Name : createdTimer
Field Type : CounterBasedGauge64
Field Status : current
Description : Total AAM Timer Created
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.10

Field Name : aamAuthGlobalConnectFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total AAM Connect Failed
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.9

Field Name : connect

Field Type : CounterBasedGauge64
Field Status : current
Description : Total AAM Connection
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.8

Field Name : aamAuthGlobalOpenSocketFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total AAM Open Socket Failed
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.7

Field Name : openedSocket
Field Type : CounterBasedGauge64
Field Status : current
Description : Total AAM Socket Opened
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.6

Field Name : ocspStaplingResponsesFromA10authd
Field Type : CounterBasedGauge64
Field Status : current
Description : Total OCSP Stapling Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.5

Field Name : ocspStaplingRequestsToA10authd
Field Type : CounterBasedGauge64
Field Status : current
Description : Total OCSP Stapling Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.4

Field Name : misses
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Authentication Request Missed
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.3

Field Name : responses
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Authentication Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.2

Field Name : requests
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Authentication Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.1

Field Name : pollingControlError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Polling Control Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.18.1.16

Field Name : jobStartError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Job Start Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.18.1.15

Field Name : otherError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Other Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.18.1.14

Field Name : timeoutError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.18.1.13

Field Name : attrFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Attribute Check Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.18.1.12

Field Name : jsonFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Failure JSON Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.18.1.11

Field Name : parseFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Total JSON Response Parse Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.18.1.10

Field Name : verifySucc
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Verification Success Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.18.1.9

Field Name : request
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.18.1.8

Field Name : responseOther
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Other Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.18.1.7

Field Name : responseTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Timeout Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.18.1.6

Field Name : responseError
Field Type : CounterBasedGauge64
Field Status : current

Description : Total Error Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.18.1.5

Field Name : responseFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Failure Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.18.1.4

Field Name : responseSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Success Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.18.1.3

Field Name : requestDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Dropped Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.18.1.2

Field Name : requestNormal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Normal Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.18.1.1

Field Name : responseOther
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Other Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.7.1.7

Field Name : responseTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Timeout Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.7.1.6

Field Name : responseError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Error Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.7.1.5

Field Name : responseFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Failure Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.7.1.4

Field Name : responseSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Success Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.7.1.3

Field Name : requestDropped

Field Type : CounterBasedGauge64
Field Status : current
Description : Total Dropped Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.7.1.2

Field Name : requestNormal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Normal Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.7.1.1

Field Name : acosEventsCollectorGroupSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.104.4.1.1

Field Name : acosEventsCollectorGroupSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.104.4.1.1.1

Field Name : msgsDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of messages dropped for other reasons
OID : 1.3.6.1.4.1.22610.2.4.10.104.4.1.1.1.4

Field Name : msgsRateLimited
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of rate limited log messages
OID : 1.3.6.1.4.1.22610.2.4.10.104.4.1.1.1.3

Field Name : msgsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of log messages sent
OID : 1.3.6.1.4.1.22610.2.4.10.104.4.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Specify log server group name
OID : 1.3.6.1.4.1.22610.2.4.10.104.4.1.1.1.1

Field Name : acosEventsLogServerSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.104.3.1.1

Field Name : acosEventsLogServerSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.104.3.1.1.1

Field Name : msgsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of log messages sent
OID : 1.3.6.1.4.1.22610.2.4.10.104.3.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Server Name
OID : 1.3.6.1.4.1.22610.2.4.10.104.3.1.1.1.1

Field Name : outBytesCurrAgg
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Aggregate, Number of bytes sent to log-servers
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.49

Field Name : outLogsCurrAgg
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Aggregate, Number of logs sent to log servers
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.48

Field Name : inDiscardBytesCurrAgg
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Aggregate, Number of old bytes discarded to fit in new logs
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.47

Field Name : inDiscardLogsCurrAgg
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Aggregate, Number of old logs discarded to fit in new logs
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.46

Field Name : inBytesBacklogCurrAgg
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Aggregate, Number of backlog bytes loaded from disk
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.45

Field Name : inLogsBacklogCurrAgg
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Aggregate, Number of backlogs loaded from disk
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.44

Field Name : inBytesCurrAgg
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Aggregate, Number of bytes successfully stored
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.43

Field Name : inLogsCurrAgg
Field Type : CounterBasedGauge64
Field Status : current

Description : Current Aggregate, Number of logs successfully stored
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.42

Field Name : outRetryFailAgg
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Aggregate, Number of retries failed with error
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.41

Field Name : outRetryAgg
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Aggregate, Number of attempted retries to send logs
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.40

Field Name : outErrorAgg
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Aggregate, Number of errors during send
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.39

Field Name : outBytesAgg
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Aggregate, Number of bytes sent to log-servers
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.38

Field Name : outLogsAgg
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Aggregate, Number of logs sent to log servers
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.37

Field Name : inDiscardBytesAgg
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Aggregate, Number of old bytes discarded to fit in new logs
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.36

Field Name : inDiscardLogsAgg
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Aggregate, Number of old logs discarded to fit in new logs
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.35

Field Name : inStoreFailNoSpaceAgg
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Aggregate, Number of logs Dropped, failed without disk space
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.34

Field Name : inBytesBacklogAgg
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Aggregate, Number of backlog bytes loaded from disk
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.33

Field Name : inLogsBacklogAgg

Field Type : CounterBasedGauge64
Field Status : current
Description : Total Aggregate, Number of backlogs loaded from disk
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.32

Field Name : inBytesAgg
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Aggregate, Number of bytes successfully stored
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.31

Field Name : inLogsAgg
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Aggregate, Number of logs successfully stored
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.30

Field Name : currFsChunksDown
Field Type : CounterBasedGauge64
Field Status : current
Description : Current blocks in file system not loaded in memory
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.29

Field Name : currFsChunksUp
Field Type : CounterBasedGauge64
Field Status : current
Description : Current blocks in file system loaded in memory
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.28

Field Name : currFsChunks
Field Type : CounterBasedGauge64
Field Status : current
Description : Current blocks in file system
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.27

Field Name : currMemChunks
Field Type : CounterBasedGauge64
Field Status : current
Description : Current blocks in memory
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.26

Field Name : currTotalChunks
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Number of blocks
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.25

Field Name : outRetryFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of retries failed with error
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.24

Field Name : outRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of attempted retries to send logs
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.23

Field Name : movedToDelq
Field Type : CounterBasedGauge64
Field Status : current
Description : Local Logging moved to delq to be deleted
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.22

Field Name : remainingBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : Total number of remaining bytes yet to be sent
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.21

Field Name : remainingLogs
Field Type : CounterBasedGauge64
Field Status : current
Description : Total number of remaining logs yet to be sent
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.20

Field Name : outError
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of errors during send
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.19

Field Name : outBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of bytes sent to log-servers
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.18

Field Name : outLogs
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of logs sent to log servers
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.17

Field Name : inDiscardBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of old bytes discarded to fit in new logs
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.16

Field Name : inDiscardLogs
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of old logs discarded to fit in new logs
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.15

Field Name : inStoreFailNoSpace
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of logs Dropped, failed without disk space
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.14

Field Name : inBytesBacklog
Field Type : CounterBasedGauge64
Field Status : current

Description : Number of backlog bytes loaded from disk
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.13

Field Name : inLogsBacklog
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of backlogs loaded from disk
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.12

Field Name : inBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of bytes successfully stored
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.11

Field Name : inLogs
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of logs successfully stored
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.10

Field Name : storeFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of logs failed to be stored
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.9

Field Name : sentToStoreFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Logs sent to be stored Failed
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.8

Field Name : sentToStore
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of logs sent to be stored
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.7

Field Name : notInited
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of logs Dropped, Local logging not inited
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.6

Field Name : rateLimited
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of logs Dropped, Rate limited
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.5

Field Name : diskOverThres
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of logs Dropped, Disk reached threshold
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.4

Field Name : freed

Field Type : CounterBasedGauge64
Field Status : current
Description : Local logging Stopped
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.3

Field Name : initFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Local logging Init Fail
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.2

Field Name : initPass
Field Type : CounterBasedGauge64
Field Status : current
Description : Local logging Init Successful
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.1

Field Name : logdStatsAuditLogsDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Logd audit logs dropped
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.42

Field Name : logdStatsAuditLogs
Field Type : CounterBasedGauge64
Field Status : current
Description : Logd audit logs sent to hc
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.41

Field Name : logdStatsSystemLogsDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Logd system logs dropped
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.40

Field Name : logdStatsSystemLogs
Field Type : CounterBasedGauge64
Field Status : current
Description : Logd system logs sent to hc
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.39

Field Name : paramMsgEncodeFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Parameterized log AVRO encoding failed
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.38

Field Name : paramMsgSentFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Parameterized log send to HC failed
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.37

Field Name : paramMsgSentToHc
Field Type : CounterBasedGauge64
Field Status : current
Description : Parameterized log sent to HC
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.36

Field Name : acosEvtTestLogsTicks
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of ticks when running ACOS Event Test Logs
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.35

Field Name : msgDroppedInvalidPart
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, Invalid partition Id
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.34

Field Name : msgDroppedOtherLogd
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, unexpected error in Logd
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.33

Field Name : msgDroppedNoActiveMemberLogd
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, no active member in collector grp in Logd
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.32

Field Name : msgDroppedSendFailedLogd
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, send failed in Logd
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.31

Field Name : msgDroppedCraftFailLogd
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, msg crafting failed in Logd
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.30

Field Name : msgDroppedLostDuringConfigChangeLogd
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, lost during config change in Logd
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.29

Field Name : msgDroppedNoTemplateLogd
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, no active template in Logd
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.28

Field Name : msgSentRemoteCplane
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Sent, to remote in logd
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.27

Field Name : msgDroppedGrpNotUsed
Field Type : CounterBasedGauge64
Field Status : current

Description : Messages Dropped, Collector group not used
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.26

Field Name : msgDroppedLocalEnqueueFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, Enqueue to Logd failed
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.25

Field Name : msgDroppedRemoteDplaneLogRatelimit
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, Remote dplane log ratelimited
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.24

Field Name : msgDroppedRemoteCplaneLogRatelimit
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, Remote cplane log ratelimited
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.23

Field Name : msgDroppedTrylockFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, Trylock failed in axlog
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.22

Field Name : msgDroppedSendToLogdFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, send to Logd via IPC failed
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.21

Field Name : msgSentDirectSyslog
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages sent to syslog directly from axlog
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.20

Field Name : msgRetryAfterSocketFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages retried to be sent to Logd via IPC
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.19

Field Name : msgSentToLogd
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages sent to Logd via IPC
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.18

Field Name : localEnqueuePass
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages enqueue to Logd passed
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.17

Field Name : msgDroppedLostDuringConfigChange

Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, lost during config change
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.16

Field Name : noTemplate
Field Type : CounterBasedGauge64
Field Status : current
Description : Message API called, with no active template
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.15

Field Name : msgDroppedOther
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, unexpected error
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.14

Field Name : msgDroppedRouteFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, Route lookup failed
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.13

Field Name : msgDroppedNoActiveMember
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, no active member in collector grp
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.12

Field Name : msgDroppedSendFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, send failed
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.11

Field Name : msgDroppedRemoteLogRatelimit
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, remote log ratelimited
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.10

Field Name : msgDroppedLocalLogRatelimit
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, local log ratelimited
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.9

Field Name : msgDroppedCraftFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, msg crafting failed
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.8

Field Name : msgDroppedTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, invalid length
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.7

Field Name : msgDroppedSelector
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, selector does not enable msg
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.6

Field Name : msgDroppedNoTemplate
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, no active template
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.5

Field Name : msgDroppedMallocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, malloc failure
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.4

Field Name : msgDroppedFormatNotDefined
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, format not defined
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.3

Field Name : msgSentLogdb
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages sent, to LogDB
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.2

Field Name : msgSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages sent, to Remote
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.1

Field Name : lookupCacheMem
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.106.8.1.8

Field Name : rtuCacheMem
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.106.8.1.7

Field Name : dbMem
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.106.8.1.6

Field Name : lookupLatency
Field Type : CounterBasedGauge64
Field Status : current

Description :
OID : 1.3.6.1.4.1.22610.2.4.10.106.8.1.5

Field Name : rtuLookup
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.106.8.1.4

Field Name : cloudLookup
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.106.8.1.3

Field Name : cloudCacheLookup
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.106.8.1.2

Field Name : dbLookup
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.106.8.1.1

Field Name : webCategoryCategoryListSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1

Field Name : webCategoryCategoryListSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1

Field Name : illegalPornography
Field Type : CounterBasedGauge64
Field Status : current
Description : illegal pornography eg. child sexual abuse
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.92

Field Name : nudityArtistic
Field Type : CounterBasedGauge64
Field Status : current
Description : artistic nudity
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.91

Field Name : generativeAi
Field Type : CounterBasedGauge64
Field Status : current
Description : generative ai
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.90

Field Name : lowThcCannabisProducts

Field Type : CounterBasedGauge64
Field Status : current
Description : low-thc cannabis products category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.89

Field Name : dnsOverHttps
Field Type : CounterBasedGauge64
Field Status : current
Description : dns over https category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.88

Field Name : selfHarm
Field Type : CounterBasedGauge64
Field Status : current
Description : self harm category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.87

Field Name : dummyItem
Field Type : CounterBasedGauge64
Field Status : current
Description : dummy item category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.86

Field Name : foodAndDining
Field Type : CounterBasedGauge64
Field Status : current
Description : food and dining category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.85

Field Name : webHostingSites
Field Type : CounterBasedGauge64
Field Status : current
Description : web hosting sites category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.84

Field Name : motorVehicles
Field Type : CounterBasedGauge64
Field Status : current
Description : motor vehicles category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.83

Field Name : recreationAndHobbies
Field Type : CounterBasedGauge64
Field Status : current
Description : recreation and hobbies category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.82

Field Name : fashionAndBeauty
Field Type : CounterBasedGauge64
Field Status : current
Description : fashion and beauty category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.81

Field Name : imageAndVideoSearch
Field Type : CounterBasedGauge64
Field Status : current
Description : image and video search category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.80

Field Name : privateIPAddresses
Field Type : CounterBasedGauge64
Field Status : current
Description : private IP addresses category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.79

Field Name : alcoholAndTobacco
Field Type : CounterBasedGauge64
Field Status : current
Description : alcohol and tobacco category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.78

Field Name : parkedDomains
Field Type : CounterBasedGauge64
Field Status : current
Description : parked domains category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.77

Field Name : dynamicallyGeneratedContent
Field Type : CounterBasedGauge64
Field Status : current
Description : dynamically generated content category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.76

Field Name : openHTTPProxies
Field Type : CounterBasedGauge64
Field Status : current
Description : open HTTP proxies category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.75

Field Name : unconfirmedSPAMSources
Field Type : CounterBasedGauge64
Field Status : current
Description : unconfirmed SPAM sources category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.74

Field Name : spamUrls
Field Type : CounterBasedGauge64
Field Status : current
Description : SPAM URLs category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.73

Field Name : confirmedSPAMSources
Field Type : CounterBasedGauge64
Field Status : current
Description : confirmed SPAM sources category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.72

Field Name : healthAndMedicine
Field Type : CounterBasedGauge64
Field Status : current
Description : health and medicine category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.71

Field Name : abortion
Field Type : CounterBasedGauge64
Field Status : current

Description : abortion category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.70

Field Name : botNets
Field Type : CounterBasedGauge64
Field Status : current
Description : bot nets category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.69

Field Name : internetCommunications
Field Type : CounterBasedGauge64
Field Status : current
Description : internet communications category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.68

Field Name : cDNs
Field Type : CounterBasedGauge64
Field Status : current
Description : content delivery networks category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.67

Field Name : illegal
Field Type : CounterBasedGauge64
Field Status : current
Description : illegal category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.66

Field Name : newsAndMedia
Field Type : CounterBasedGauge64
Field Status : current
Description : news and media category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.65

Field Name : nudity
Field Type : CounterBasedGauge64
Field Status : current
Description : nudity category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.64

Field Name : government
Field Type : CounterBasedGauge64
Field Status : current
Description : government category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.63

Field Name : music
Field Type : CounterBasedGauge64
Field Status : current
Description : music category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.62

Field Name : spywareAndAdware
Field Type : CounterBasedGauge64
Field Status : current
Description : spyware and adware category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.61

Field Name : proxyAvoidAndAnonymizers

Field Type : CounterBasedGauge64
Field Status : current
Description : proxy avoid and anonymizers category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.60

Field Name : phishingAndOtherFraud
Field Type : CounterBasedGauge64
Field Status : current
Description : phishing and other fraud category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.59

Field Name : malwareSites
Field Type : CounterBasedGauge64
Field Status : current
Description : malware sites category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.58

Field Name : webBasedEmail
Field Type : CounterBasedGauge64
Field Status : current
Description : web based email category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.57

Field Name : gross
Field Type : CounterBasedGauge64
Field Status : current
Description : gross category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.56

Field Name : cheating
Field Type : CounterBasedGauge64
Field Status : current
Description : cheating category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.55

Field Name : webAdvertisements
Field Type : CounterBasedGauge64
Field Status : current
Description : web advertisements category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.54

Field Name : internetPortals
Field Type : CounterBasedGauge64
Field Status : current
Description : internet portals category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.53

Field Name : searchEngines
Field Type : CounterBasedGauge64
Field Status : current
Description : search engines category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.52

Field Name : keyloggersAndMonitoring
Field Type : CounterBasedGauge64
Field Status : current
Description : keyloggers and monitoring category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.51

Field Name : violence
Field Type : CounterBasedGauge64
Field Status : current
Description : violence category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.50

Field Name : personalStorage
Field Type : CounterBasedGauge64
Field Status : current
Description : personal storage category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.49

Field Name : hateAndRacism
Field Type : CounterBasedGauge64
Field Status : current
Description : hate and racism category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.48

Field Name : kids
Field Type : CounterBasedGauge64
Field Status : current
Description : kids category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.47

Field Name : questionable
Field Type : CounterBasedGauge64
Field Status : current
Description : questionable category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.46

Field Name : swimsuitsAndIntimateApparel
Field Type : CounterBasedGauge64
Field Status : current
Description : swimsuits and intimate apparel category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.45

Field Name : sports
Field Type : CounterBasedGauge64
Field Status : current
Description : sports category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.44

Field Name : onlineGreetingCards
Field Type : CounterBasedGauge64
Field Status : current
Description : online greeting cards category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.43

Field Name : educationalInstitutions
Field Type : CounterBasedGauge64
Field Status : current
Description : educational institutions category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.42

Field Name : society
Field Type : CounterBasedGauge64
Field Status : current

Description : society category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.41

Field Name : huntingAndFishing
Field Type : CounterBasedGauge64
Field Status : current
Description : hunting and fishing category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.40

Field Name : payToSurf
Field Type : CounterBasedGauge64
Field Status : current
Description : pay to surf category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.39

Field Name : weapons
Field Type : CounterBasedGauge64
Field Status : current
Description : weapons category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.38

Field Name : philosophyAndPolitics
Field Type : CounterBasedGauge64
Field Status : current
Description : philosophy and politics category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.37

Field Name : games
Field Type : CounterBasedGauge64
Field Status : current
Description : games category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.36

Field Name : hacking
Field Type : CounterBasedGauge64
Field Status : current
Description : hacking category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.35

Field Name : marijuana
Field Type : CounterBasedGauge64
Field Status : current
Description : marijuana category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.34

Field Name : peerToPeer
Field Type : CounterBasedGauge64
Field Status : current
Description : peer to peer category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.33

Field Name : sharewareAndFreeware
Field Type : CounterBasedGauge64
Field Status : current
Description : shareware and freeware category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.32

Field Name : referenceAndResearch

Field Type : CounterBasedGauge64
Field Status : current
Description : reference and research category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.31

Field Name : translation
Field Type : CounterBasedGauge64
Field Status : current
Description : translation category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.30

Field Name : gambling
Field Type : CounterBasedGauge64
Field Status : current
Description : gambling category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.29

Field Name : jobSearch
Field Type : CounterBasedGauge64
Field Status : current
Description : job search category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.28

Field Name : streamingMedia
Field Type : CounterBasedGauge64
Field Status : current
Description : streaming media category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.27

Field Name : localInformation
Field Type : CounterBasedGauge64
Field Status : current
Description : local information category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.26

Field Name : legal
Field Type : CounterBasedGauge64
Field Status : current
Description : legal category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.25

Field Name : personalSitesAndBlogs
Field Type : CounterBasedGauge64
Field Status : current
Description : personal sites and blogs category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.24

Field Name : entertainmentAndArts
Field Type : CounterBasedGauge64
Field Status : current
Description : entertainment and arts category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.23

Field Name : religion
Field Type : CounterBasedGauge64
Field Status : current
Description : religion category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.22

Field Name : sexEducation
Field Type : CounterBasedGauge64
Field Status : current
Description : sex education category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.21

Field Name : dating
Field Type : CounterBasedGauge64
Field Status : current
Description : dating category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.20

Field Name : trainingAndTools
Field Type : CounterBasedGauge64
Field Status : current
Description : training and tools category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.19

Field Name : stockAdviceAndTools
Field Type : CounterBasedGauge64
Field Status : current
Description : stock advice and tools category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.18

Field Name : deadSites
Field Type : CounterBasedGauge64
Field Status : current
Description : dead sites category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.17

Field Name : socialNetwork
Field Type : CounterBasedGauge64
Field Status : current
Description : social network category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.16

Field Name : military
Field Type : CounterBasedGauge64
Field Status : current
Description : military category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.15

Field Name : homeAndGarden
Field Type : CounterBasedGauge64
Field Status : current
Description : home and garden category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.14

Field Name : adultAndPornography
Field Type : CounterBasedGauge64
Field Status : current
Description : adult and pornography category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.13

Field Name : drugs
Field Type : CounterBasedGauge64
Field Status : current

Description : drugs category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.12

Field Name : travel
Field Type : CounterBasedGauge64
Field Status : current
Description : travel category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.11

Field Name : cultAndOccult
Field Type : CounterBasedGauge64
Field Status : current
Description : cult and occult category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.10

Field Name : shopping
Field Type : CounterBasedGauge64
Field Status : current
Description : shopping category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.9

Field Name : auctions
Field Type : CounterBasedGauge64
Field Status : current
Description : auctions category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.8

Field Name : computerAndInternetInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : computer and internet info category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.7

Field Name : businessAndEconomy
Field Type : CounterBasedGauge64
Field Status : current
Description : business and economy category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.6

Field Name : financialServices
Field Type : CounterBasedGauge64
Field Status : current
Description : financial services category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.5

Field Name : computerAndInternetSecurity
Field Type : CounterBasedGauge64
Field Status : current
Description : computer and internet security category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.4

Field Name : realEstate
Field Type : CounterBasedGauge64
Field Status : current
Description : real estate category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.3

Field Name : uncategorized

Field Type : CounterBasedGauge64
Field Status : current
Description : uncategorized category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Web Category List name
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.1

Field Name : webCategoryReputationScopeSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.106.9.1.1

Field Name : webCategoryReputationScopeSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.106.9.1.1.1

Field Name : malicious
Field Type : CounterBasedGauge64
Field Status : current
Description : Malicious level(1-20)
OID : 1.3.6.1.4.1.22610.2.4.10.106.9.1.1.1.6

Field Name : suspicious
Field Type : CounterBasedGauge64
Field Status : current
Description : Suspicious level(21-40)
OID : 1.3.6.1.4.1.22610.2.4.10.106.9.1.1.1.5

Field Name : moderateRisk
Field Type : CounterBasedGauge64
Field Status : current
Description : Moderate-risk level(41-60)
OID : 1.3.6.1.4.1.22610.2.4.10.106.9.1.1.1.4

Field Name : lowRisk
Field Type : CounterBasedGauge64
Field Status : current
Description : Low-risk level(61-80)
OID : 1.3.6.1.4.1.22610.2.4.10.106.9.1.1.1.3

Field Name : trustworthy
Field Type : CounterBasedGauge64
Field Status : current
Description : Trustworthy level(81-100)
OID : 1.3.6.1.4.1.22610.2.4.10.106.9.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Reputation Scope name
OID : 1.3.6.1.4.1.22610.2.4.10.106.9.1.1.1.1

Field Name : threatIntelThreatListSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.164.2.1.1

Field Name : threatIntelThreatListSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.164.2.1.1.1

Field Name : totalHits
Field Type : CounterBasedGauge64
Field Status : current
Description : Total hits for threat-list
OID : 1.3.6.1.4.1.22610.2.4.10.164.2.1.1.1.13

Field Name : torProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for tor-proxy
OID : 1.3.6.1.4.1.22610.2.4.10.164.2.1.1.1.12

Field Name : mobileThreats
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for mobile threats
OID : 1.3.6.1.4.1.22610.2.4.10.164.2.1.1.1.11

Field Name : proxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for proxy
OID : 1.3.6.1.4.1.22610.2.4.10.164.2.1.1.1.10

Field Name : phishing
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for phishing
OID : 1.3.6.1.4.1.22610.2.4.10.164.2.1.1.1.9

Field Name : reputation
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for reputation
OID : 1.3.6.1.4.1.22610.2.4.10.164.2.1.1.1.8

Field Name : dosAttacks
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for dos attacks
OID : 1.3.6.1.4.1.22610.2.4.10.164.2.1.1.1.7

Field Name : scanners
Field Type : CounterBasedGauge64
Field Status : current

Description : Hits for scanners
OID : 1.3.6.1.4.1.22610.2.4.10.164.2.1.1.1.6

Field Name : botnets
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for botnets
OID : 1.3.6.1.4.1.22610.2.4.10.164.2.1.1.1.5

Field Name : webAttacks
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for web attacks
OID : 1.3.6.1.4.1.22610.2.4.10.164.2.1.1.1.4

Field Name : windowsExploits
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for windows exploits
OID : 1.3.6.1.4.1.22610.2.4.10.164.2.1.1.1.3

Field Name : spamSources
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for spam sources
OID : 1.3.6.1.4.1.22610.2.4.10.164.2.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Threat category List name
OID : 1.3.6.1.4.1.22610.2.4.10.164.2.1.1.1.1

Field Name : nonMaliciousIps
Field Type : CounterBasedGauge64
Field Status : current
Description : IP's not found in database or RTU cache
OID : 1.3.6.1.4.1.22610.2.4.10.164.3.1.14

Field Name : databaseLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of lookups in database
OID : 1.3.6.1.4.1.22610.2.4.10.164.3.1.13

Field Name : rtuLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of lookups in RTU cache
OID : 1.3.6.1.4.1.22610.2.4.10.164.3.1.12

Field Name : torProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for tor-proxy
OID : 1.3.6.1.4.1.22610.2.4.10.164.3.1.11

Field Name : mobileThreats

Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for mobile threats
OID : 1.3.6.1.4.1.22610.2.4.10.164.3.1.10

Field Name : proxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for proxy
OID : 1.3.6.1.4.1.22610.2.4.10.164.3.1.9

Field Name : phishing
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for phishing
OID : 1.3.6.1.4.1.22610.2.4.10.164.3.1.8

Field Name : reputation
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for reputation
OID : 1.3.6.1.4.1.22610.2.4.10.164.3.1.7

Field Name : dosAttacks
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for dos attacks
OID : 1.3.6.1.4.1.22610.2.4.10.164.3.1.6

Field Name : scanners
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for scanners
OID : 1.3.6.1.4.1.22610.2.4.10.164.3.1.5

Field Name : botnets
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for botnets
OID : 1.3.6.1.4.1.22610.2.4.10.164.3.1.4

Field Name : webAttacks
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for web attacks
OID : 1.3.6.1.4.1.22610.2.4.10.164.3.1.3

Field Name : windowsExploits
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for windows exploits
OID : 1.3.6.1.4.1.22610.2.4.10.164.3.1.2

Field Name : spamSources
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for spam sources
OID : 1.3.6.1.4.1.22610.2.4.10.164.3.1.1

Field Name : parseError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total RPZ Parse Error
OID : 1.3.6.1.4.1.22610.2.4.10.108.89.1.2

Field Name : setBwError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total RPZ Set Class-list Error
OID : 1.3.6.1.4.1.22610.2.4.10.108.89.1.1

Field Name : errEntryMissingVport
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry missing Virtual-Port
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.43

Field Name : errCreateSslCtxFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Error in creating SSL CTX
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.42

Field Name : errMissingServerSslTemplate
Field Type : CounterBasedGauge64
Field Status : current
Description : Missing Server-SSL Template
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.41

Field Name : totalStartServerConnErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total start server connections error
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.40

Field Name : totalServerQuicConnErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total start server QUIC connections error
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.39

Field Name : totalServerQuicConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total start server QUIC connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.38

Field Name : smartNatReleaseFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total smart-nat release failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.37

Field Name : smartNatAllocFailed
Field Type : CounterBasedGauge64
Field Status : current

Description : Total smart-nat allocation failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.36

Field Name : smartNatRelease
Field Type : CounterBasedGauge64
Field Status : current
Description : Total smart-nat release successful
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.35

Field Name : smartNatAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Total smart-nat allocation successful
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.34

Field Name : errHttp2VerMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Error HTTP2 version mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.33

Field Name : errL7SessProcessTcpDataFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 session process TCP data failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.32

Field Name : errL7SessProcessTcpEstabFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 session process TCP established failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.31

Field Name : errHttp2Callback
Field Type : CounterBasedGauge64
Field Status : current
Description : Error HTTP2 callback
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.30

Field Name : errServerSynTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : Error SSL server SYN timeout
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.29

Field Name : errSslCertNameMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Error SSL cert name mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.28

Field Name : errNoHmEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Error no HM entry found
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.27

Field Name : totalWrongStatusReceived

Field Type : CounterBasedGauge64
Field Status : current
Description : Total HTTP received response with wrong response code
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.26

Field Name : totalMaintenanceReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Total maintenace response received
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.25

Field Name : totalMatchDefaultRespCode
Field Type : CounterBasedGauge64
Field Status : current
Description : Total HTTP received response with match 200 response code
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.24

Field Name : totalMatchRespCode
Field Type : CounterBasedGauge64
Field Status : current
Description : Total HTTP received response with match response code
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.23

Field Name : errEntryCreateSlbFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Error in creating HM internal SLB Resource
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.22

Field Name : entryDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry deleted
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.21

Field Name : hmTcpConnSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP connections sent for HM
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.20

Field Name : errHmTcpConnSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Error in initiating TCP connection for HM
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.19

Field Name : errL4SessAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Error allocating L4 session for HM
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.18

Field Name : errSmartNatPortAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Error obtaining smart-nat source port
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.17

Field Name : errSmartNatAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Error creating smart-nat instance
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.16

Field Name : totalTcpErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP errors in health-checks sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.15

Field Name : errEntryInsertFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry insert failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.8

Field Name : errEntryCreateOom
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry creation out of memory
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.7

Field Name : errEntryCreateFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry Creation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.6

Field Name : totalFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total HM entries freed
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.5

Field Name : currReadyToFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Current HM entries ready to free
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.4

Field Name : totalInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Total HM entries inserted
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.3

Field Name : totalCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total HM Entries Created
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.2

Field Name : currEntries
Field Type : CounterBasedGauge64
Field Status : current

Description : Current HM Entries
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.1

Field Name : probeTcpConnSent
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP connection sent for probe
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.20

Field Name : errProbeTcpConnSend
Field Type : CounterBasedGauge64
Field Status : current
Description : Error in initiating TCP connection for probe
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.19

Field Name : errL4SessAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Error allocating L4 session for probe
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.18

Field Name : errSmartNatPortAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Error obtaining Smart NAT source port
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.17

Field Name : errSmartNatAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Error creating Smart NAT Instance
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.16

Field Name : totalTcpErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP errors in probes sent out
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.15

Field Name : totalHttpResponseBad
Field Type : CounterBasedGauge64
Field Status : current
Description : Total HTTP responses not matching probe template config
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.14

Field Name : totalHttpResponseGood
Field Type : CounterBasedGauge64
Field Status : current
Description : Total HTTP responses matching probe template config
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.13

Field Name : totalHttpResponseReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Total HTTP responses received
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.12

Field Name : totalHttpProbesSent

Field Type : CounterBasedGauge64
Field Status : current
Description : Total HTTP Probes Sent out
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.11

Field Name : errTmplProbeCreateOom
Field Type : CounterBasedGauge64
Field Status : current
Description : Probe Template Creation Out of Memory
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.10

Field Name : errTmplProbeCreateFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Probe Template Creation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.9

Field Name : errEntryInsertFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry Insert Failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.8

Field Name : errEntryCreateOom
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry Creation Out of Memory
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.7

Field Name : errEntryCreateFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry Creation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.6

Field Name : totalFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Entry Freed
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.5

Field Name : totalReadyToFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Entry Ready To Free
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.4

Field Name : totalInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Entry Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.3

Field Name : totalCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Entry Created
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.2

Field Name : currEntries
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Entry Count
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.1

Field Name : errVportFailMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Failed to Match Vport
OID : 1.3.6.1.4.1.22610.2.4.10.108.75.1.16

Field Name : errEntryInsertFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry Insert Failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.75.1.15

Field Name : errEntryExtCreateOom
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry Extension Creation Out of Memory
OID : 1.3.6.1.4.1.22610.2.4.10.108.75.1.14

Field Name : errEntryCreateOom
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry Creation Out of Memory
OID : 1.3.6.1.4.1.22610.2.4.10.108.75.1.13

Field Name : errEntryCreateFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry Creation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.75.1.12

Field Name : otherThreadRefill
Field Type : CounterBasedGauge64
Field Status : current
Description : Other Thread Refilling
OID : 1.3.6.1.4.1.22610.2.4.10.108.75.1.11

Field Name : totalCreditExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Credit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.108.75.1.10

Field Name : totalRefill
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Refills
OID : 1.3.6.1.4.1.22610.2.4.10.108.75.1.9

Field Name : totalOverflowEntryHits
Field Type : CounterBasedGauge64
Field Status : current

Description : Total Overflow Entry Hits
OID : 1.3.6.1.4.1.22610.2.4.10.108.75.1.8

Field Name : totalLogs
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Logs
OID : 1.3.6.1.4.1.22610.2.4.10.108.75.1.7

Field Name : totalFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Entry Freed
OID : 1.3.6.1.4.1.22610.2.4.10.108.75.1.6

Field Name : totalReadyToFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Entry Ready To Free
OID : 1.3.6.1.4.1.22610.2.4.10.108.75.1.5

Field Name : totalWithdrew
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Entry Withdrew
OID : 1.3.6.1.4.1.22610.2.4.10.108.75.1.4

Field Name : totalInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Entry Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.108.75.1.3

Field Name : totalCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Entry Created
OID : 1.3.6.1.4.1.22610.2.4.10.108.75.1.2

Field Name : currEntries
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Entry Count
OID : 1.3.6.1.4.1.22610.2.4.10.108.75.1.1

Field Name : mlbServerDown
Field Type : CounterBasedGauge64
Field Status : current
Description : Server down
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.18

Field Name : mlbServerProbe
Field Type : CounterBasedGauge64
Field Status : current
Description : Server probe
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.17

Field Name : mlbDcmsgFree

Field Type : CounterBasedGauge64
Field Status : current
Description : Dcmsg free
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.16

Field Name : mlbDcmsgAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Dcmsg alloc
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.15

Field Name : mlbDcmsgError
Field Type : CounterBasedGauge64
Field Status : current
Description : Dcmsg error
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.14

Field Name : mlbDcmsgReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Dcmsg received
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.13

Field Name : mlbDcmsgSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Dcmsg sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.12

Field Name : msgRerouted
Field Type : CounterBasedGauge64
Field Status : current
Description : Message rerouted
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.11

Field Name : msgDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Message dropped
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.10

Field Name : clientConnNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Client connection not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.9

Field Name : clientConnClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : Client connection closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.8

Field Name : clientConnCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Client connection created
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.7

Field Name : serverConnClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : Server connection closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.6

Field Name : serverConnFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Server connection failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.5

Field Name : serverConnRst
Field Type : CounterBasedGauge64
Field Status : current
Description : Server connection reset
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.4

Field Name : serverConnCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Server connection created
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.3

Field Name : serverMsgReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Server message received
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.2

Field Name : clientMsgSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Client message sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.1

Field Name : totalLog
Field Type : CounterBasedGauge64
Field Status : current
Description : Total log sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.59.1.7

Field Name : totalReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Total rate exceed reset
OID : 1.3.6.1.4.1.22610.2.4.10.108.59.1.6

Field Name : totalDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total rate exceed drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.59.1.5

Field Name : freedSportip
Field Type : CounterBasedGauge64
Field Status : current

Description : Freed src port-ip entry
OID : 1.3.6.1.4.1.22610.2.4.10.108.59.1.4

Field Name : freedSport
Field Type : CounterBasedGauge64
Field Status : current
Description : Freed src port entry
OID : 1.3.6.1.4.1.22610.2.4.10.108.59.1.3

Field Name : allocSportip
Field Type : CounterBasedGauge64
Field Status : current
Description : Alloc'd src port-ip entry
OID : 1.3.6.1.4.1.22610.2.4.10.108.59.1.2

Field Name : allocSport
Field Type : CounterBasedGauge64
Field Status : current
Description : Alloc'd src port entry
OID : 1.3.6.1.4.1.22610.2.4.10.108.59.1.1

Field Name : totalValidPlayeridPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Valid playerid packets
OID : 1.3.6.1.4.1.22610.2.4.10.108.57.1.7

Field Name : totalInvalidPlayeridDrops
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid playerid packet drops
OID : 1.3.6.1.4.1.22610.2.4.10.108.57.1.6

Field Name : totalInvalidPlayeridPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid playerid packets
OID : 1.3.6.1.4.1.22610.2.4.10.108.57.1.5

Field Name : totalPktActivityAgeOuts
Field Type : CounterBasedGauge64
Field Status : current
Description : Playerid records idle timeout
OID : 1.3.6.1.4.1.22610.2.4.10.108.57.1.4

Field Name : totalAbsMaxAgeOuts
Field Type : CounterBasedGauge64
Field Status : current
Description : Playerid records max time aged out
OID : 1.3.6.1.4.1.22610.2.4.10.108.57.1.3

Field Name : totalPlayeridsDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Playerid records deleted
OID : 1.3.6.1.4.1.22610.2.4.10.108.57.1.2

Field Name : totalPlayeridsCreated

Field Type : CounterBasedGauge64
Field Status : current
Description : Playerid records created
OID : 1.3.6.1.4.1.22610.2.4.10.108.57.1.1

Field Name : rspBr
Field Type : CounterBasedGauge64
Field Status : current
Description : Responses from cache 200 OK - Brotli
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.32

Field Name : rspTypeStream
Field Type : CounterBasedGauge64
Field Status : current
Description : Responses from http2 server 200 OK - Stream
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.31

Field Name : cleanedEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry Cleaned
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.30

Field Name : agingEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry Aged Out
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.29

Field Name : replacedEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry Replaced
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.28

Field Name : entryNum
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry Cached
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.27

Field Name : memSize
Field Type : CounterBasedGauge64
Field Status : current
Description : Memory Used
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.26

Field Name : entryCreateFailures
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry Create failures
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.25

Field Name : contentToosmall
Field Type : CounterBasedGauge64
Field Status : current
Description : Policy Content Too Small
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.24

Field Name : contentToobig
Field Type : CounterBasedGauge64
Field Status : current
Description : Policy Content Too Big
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.23

Field Name : invalidateMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Policy URI invalidate
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.22

Field Name : match
Field Type : CounterBasedGauge64
Field Status : current
Description : Policy URI cache
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.21

Field Name : nocacheMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Policy URI nocache
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.20

Field Name : rspOther
Field Type : CounterBasedGauge64
Field Status : current
Description : Responses from cache Other
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.19

Field Name : rspDeflate
Field Type : CounterBasedGauge64
Field Status : current
Description : Responses from cache 200 OK - Deflate
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.18

Field Name : rspGzip
Field Type : CounterBasedGauge64
Field Status : current
Description : Responses from cache 200 OK - Gzip
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.17

Field Name : rspNoCompress
Field Type : CounterBasedGauge64
Field Status : current
Description : Responses from cache 200 OK - No Comp
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.16

Field Name : rspTypeOther
Field Type : CounterBasedGauge64
Field Status : current
Description : Responses from server 200 OK - Other
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.15

Field Name : rspType304
Field Type : CounterBasedGauge64
Field Status : current

Description : Responses from server 304 Not Modified
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.14

Field Name : rspTypeCE
Field Type : CounterBasedGauge64
Field Status : current
Description : Responses from server 200 OK - Chnk Enc
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.13

Field Name : rspTypeCL
Field Type : CounterBasedGauge64
Field Status : current
Description : Responses from server 200 OK - Cont Len
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.12

Field Name : nmResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Responses from cache 304 Not Modified
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.11

Field Name : imsRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : IMS Requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.10

Field Name : rvFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Revalidation Failures
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.9

Field Name : rvSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Revalidation Successes
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.8

Field Name : ncResHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : Not cacheable
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.7

Field Name : ncReqHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : No-cache Request
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.6

Field Name : cachingReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Cacheable Requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.5

Field Name : rcCacheGlobalTotalReq

Field Type : CounterBasedGauge64
Field Status : current
Description : Total Requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.4

Field Name : bytesServed
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes Served
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.3

Field Name : miss
Field Type : CounterBasedGauge64
Field Status : current
Description : Cache Misses
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.2

Field Name : rcCacheGlobalHits
Field Type : CounterBasedGauge64
Field Status : current
Description : Cache Hits
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.1

Field Name : slbProxyLineTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Line too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.31

Field Name : startServerConnFailTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : Fail Tuple Issue
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.30

Field Name : startServerConnFailServer
Field Type : CounterBasedGauge64
Field Status : current
Description : Fail Server issue
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.29

Field Name : startServerConnFailPersist
Field Type : CounterBasedGauge64
Field Status : current
Description : Fail Persistence
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.28

Field Name : startServerConnFailSnat
Field Type : CounterBasedGauge64
Field Status : current
Description : Failed Source NAT
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.27

Field Name : startServerConnFailMem
Field Type : CounterBasedGauge64
Field Status : current
Description : No memory
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.26

Field Name : startServerConnNoRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : No route to server
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.25

Field Name : startServerConnSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : Success
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.24

Field Name : startServerConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Start server conn
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.23

Field Name : errCbFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : App ERR callback failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.22

Field Name : wbufCbFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : App WBUF callback failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.21

Field Name : dataCbFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : App DATA callback failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.20

Field Name : estCbFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : App EST callback failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.19

Field Name : serviceFreeCbFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Service free callback failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.18

Field Name : serviceFreeCb
Field Type : CounterBasedGauge64
Field Status : current
Description : Service free callback
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.17

Field Name : serviceAllocCbFailed
Field Type : CounterBasedGauge64
Field Status : current

Description : Service alloc callback failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.16

Field Name : serviceAllocCb
Field Type : CounterBasedGauge64
Field Status : current
Description : Service alloc callback
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.15

Field Name : connNotExist
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn not exist
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.14

Field Name : eventFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Event failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.13

Field Name : queueDepthOverLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : Queue depth over limit
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.12

Field Name : slbProxyServerRst
Field Type : CounterBasedGauge64
Field Status : current
Description : Server RST
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.11

Field Name : slbProxyClientRst
Field Type : CounterBasedGauge64
Field Status : current
Description : Client RST
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.10

Field Name : noMem
Field Type : CounterBasedGauge64
Field Status : current
Description : No memory
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.9

Field Name : errEvent
Field Type : CounterBasedGauge64
Field Status : current
Description : Error occured
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.8

Field Name : wbufEvent
Field Type : CounterBasedGauge64
Field Status : current
Description : Ready to send data
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.7

Field Name : slbProxyServerFin

Field Type : CounterBasedGauge64
Field Status : current
Description : Server FIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.6

Field Name : slbProxyClientFin
Field Type : CounterBasedGauge64
Field Status : current
Description : Client FIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.5

Field Name : dataEvent
Field Type : CounterBasedGauge64
Field Status : current
Description : Data received
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.4

Field Name : estEvent
Field Type : CounterBasedGauge64
Field Status : current
Description : Connection established
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.3

Field Name : tcpEvent
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP stack event
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.2

Field Name : num
Field Type : CounterBasedGauge64
Field Status : current
Description : Num
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.1

Field Name : macMovement
Field Type : CounterBasedGauge64
Field Status : current
Description : MAC movement
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.117

Field Name : tls12Tls13IgnoreReq
Field Type : CounterBasedGauge64
Field Status : current
Description : TLS12-TLS13-Request-Per-Sec Limit ignored packets count
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.116

Field Name : tls12Tls13DropReq
Field Type : CounterBasedGauge64
Field Status : current
Description : TLS12--TLS13-Request-Per-Sec Limit Drop at ingress
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.115

Field Name : tls12IgnoreReq
Field Type : CounterBasedGauge64
Field Status : current
Description : TLS12-Request-Per-Sec Limit ignored packets count
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.114

Field Name : tls12DropReq
Field Type : CounterBasedGauge64
Field Status : current
Description : TLS12-Request-Per-Sec Limit Drop at ingress
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.113

Field Name : tls13IgnoreReq
Field Type : CounterBasedGauge64
Field Status : current
Description : TLS13-Request-Per-Sec Limit ignored packets count
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.112

Field Name : tls13DropReq
Field Type : CounterBasedGauge64
Field Status : current
Description : TLS13-Request-Per-Sec Limit Drop at ingress
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.111

Field Name : ipIcmpErrorDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : IP ICMP Error Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.110

Field Name : closedPortSynDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Linux Closed Port SYN Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.109

Field Name : ppslIgnoreLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet-Per-Sec Limit ignored packets count
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.108

Field Name : ppslDropIng
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet-Per-Sec Limit Drop at ingress
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.107

Field Name : ppslDropEgr
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet-Per-Sec Limit Drop at egress
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.106

Field Name : bwIgnoreLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : BW Limit ignored packets count
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.105

Field Name : ipv6NdiscDadPrefixMismatchDrop
Field Type : CounterBasedGauge64
Field Status : current

Description : IPv6 DAD on Advertise drop for prefix mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.104

Field Name : ipv6fragGreDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Frag gre Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.103

Field Name : unnumberedUnsupportedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Unsupported protocol for unnumbered
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.102

Field Name : unnumberedNatError
Field Type : CounterBasedGauge64
Field Status : current
Description : Unnumbered NAT error
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.101

Field Name : serviceChainRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Chain Packets Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.100

Field Name : serviceChainSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Chain Packets Sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.99

Field Name : lacpTxIntfErrDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : LACP interface error corrected
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.98

Field Name : devLinkDownArpDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ARP PKT dropped due to interface is down
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.97

Field Name : ipNotFoundArpDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ARP PKT dropped due to IP not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.96

Field Name : selfGratNatIpArpDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Self generated grat ARP PKT dropped for NAT IP
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.95

Field Name : selfGratArpDrop

Field Type : CounterBasedGauge64
Field Status : current
Description : Self generated grat ARP PKT dropped
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.94

Field Name : scaleoutHairpinArpDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ARP PKT dropped due to scaleout hairpin checks
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.93

Field Name : inactiveNatPoolArpDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ARP PKT dropped due to inactive nat pool
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.92

Field Name : inactiveStaticNatPoolArpDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ARP PKT dropped due to inactive static nat pool
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.91

Field Name : virtualIpNotFoundArpDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ARP PKT dropped due to virtual IP not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.90

Field Name : scaleoutArpDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ARP PKT dropped due to scaleout checks
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.89

Field Name : devBasedArpDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ARP PKT dropped due to interface state checks
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.88

Field Name : invalidSenderMacArpDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ARP PKT dropped due to invalid sender MAC
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.87

Field Name : invalidRxArpPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid ARP PKT Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.86

Field Name : ipFragSent
Field Type : CounterBasedGauge64
Field Status : current
Description : IP frag sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.85

Field Name : redirectSetupFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Redirect connection setup failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.84

Field Name : redirectRevSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Redirect succeeded in the rev direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.83

Field Name : redirectRevFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Redirect failed in the rev direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.82

Field Name : redirectFwdSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Redirect succeeded in the fwd direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.81

Field Name : redirectFwdFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Redirect failed in the fwd direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.80

Field Name : ipfragIpipDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Frag IPIP Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.79

Field Name : ipfragUdpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Frag UDP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.78

Field Name : ipfragTcpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Frag TCP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.77

Field Name : ipfragEsp
Field Type : CounterBasedGauge64
Field Status : current
Description : IP(ESP) Fragment Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.76

Field Name : ipfragOspf
Field Type : CounterBasedGauge64
Field Status : current

Description : IP(OSPF) Fragment Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.75

Field Name : ipfragIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : IP(ICMP) Fragment Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.74

Field Name : ipfragUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : IP(UDP) Fragment Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.73

Field Name : fwSmpZoneMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : FW SMP Zone Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.72

Field Name : urpfPktDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : URPF check packet drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.71

Field Name : spNonCtrlPktDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Shared IP mode non ctrl packet to linux drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.70

Field Name : ipv6NdiscOutOfMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 DAD Out-of-memory
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.69

Field Name : ipv6NdiscMacChanges
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 DAD MAC Changed
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.68

Field Name : ipv6NdiscDadAdverts
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 DAD on Adverts
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.67

Field Name : ipv6NdiscDadSolicits
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 DAD on Solicits
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.66

Field Name : ipipv6JumboFragDrop

Field Type : CounterBasedGauge64
Field Status : current
Description : IPIPv6 Jumbo Frag Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.65

Field Name : ipv6JumboFragDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Jumbo Frag Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.64

Field Name : jumboFragDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Jumbo Frag Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.63

Field Name : mgmtSvcDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Management Service Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.62

Field Name : l4InCtrlCpu
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 In Ctrl CPU
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.61

Field Name : ipv6fragEsp
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Frag ESP
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.60

Field Name : ipv6fragOspf
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Frag OSPF
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.59

Field Name : ipv6fragIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Frag ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.58

Field Name : ipv6fragTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Frag TCP
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.57

Field Name : maxArpDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Max ARP Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.56

Field Name : fpgaErrorPkt2
Field Type : CounterBasedGauge64
Field Status : current
Description : FPGA Error PKT2
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.55

Field Name : fpgaErrorPkt1
Field Type : CounterBasedGauge64
Field Status : current
Description : FPGA Error PKT1
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.54

Field Name : ipv6NovlanfwdDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 No L3 VLAN FWD Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.53

Field Name : ipv4NovlanfwdDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 No L3 VLAN FWD Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.52

Field Name : ipFragTooMany
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Fragment too many
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.51

Field Name : ipFragOversize
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Fragment oversize
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.50

Field Name : ipv6fragIpipDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Frag IPIP Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.49

Field Name : ipv6fragIpipOk
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Frag IPIP OKs
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.48

Field Name : ipv6fragTcpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Frag TCP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.47

Field Name : ipv6fragUdpDropped
Field Type : CounterBasedGauge64
Field Status : current

Description : IPv6 Frag UDP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.46

Field Name : ipv6fragUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Frag UDP
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.45

Field Name : noIpDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : No IP Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.44

Field Name : ipv4Frag6rdDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Frag 6RD Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.43

Field Name : ipv4Frag6rdOk
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Frag 6RD OK
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.42

Field Name : ipDefragInvalidLen
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Invalid Length Frag
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.41

Field Name : ctrlSynRateDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN rate exceeded Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.40

Field Name : bpduSent
Field Type : CounterBasedGauge64
Field Status : current
Description : BPDUs Sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.39

Field Name : bpduRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : BPDUs Received
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.38

Field Name : ipsecDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : IPSec Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.37

Field Name : tcpsynfinDrop

Field Type : CounterBasedGauge64
Field Status : current
Description : Anomaly TCP SYNFIN Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.36

Field Name : tcpsynfragDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Anomaly SYN Frag Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.35

Field Name : tcpnoflagDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Anomaly TCP noFlag Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.34

Field Name : allfragDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Anomaly All Frag Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.33

Field Name : pingofdeathDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Anomaly PingDeath Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.32

Field Name : badpktDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Pkt Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.31

Field Name : ipoptionsDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Anomaly IP OPT Drops
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.30

Field Name : landDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Anomaly Land Attack Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.29

Field Name : ipfragReasmfails
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Fragment Reasm Fails
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.28

Field Name : ipfragReasmoks
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Fragment Reasm OKs
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.27

Field Name : ipfragOverload
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Frag Overload Drops
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.26

Field Name : ipfragTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Fragment Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.25

Field Name : ipfragOverlap
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Fragment Overlap
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.24

Field Name : ipfragTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : IP(TCP) Fragment Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.23

Field Name : aclDeny
Field Type : CounterBasedGauge64
Field Status : current
Description : ACL Denys
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.22

Field Name : ipDefrag
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Defrag
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.21

Field Name : incorrectLenDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Incorrect Length Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.20

Field Name : sportDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SPORT Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.19

Field Name : linkdownDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Link Down Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.18

Field Name : ttlExceededDrop
Field Type : CounterBasedGauge64
Field Status : current

Description : TTL Exceeded Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.17

Field Name : unknownProtDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Unknown Prot Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.16

Field Name : l4Process
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 Process
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.15

Field Name : l3ForwardIpv6
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 IPv6 Forward
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.14

Field Name : l3ForwardIp
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 IP Forward
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.13

Field Name : l2Forward
Field Type : CounterBasedGauge64
Field Status : current
Description : L2 Forward
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.12

Field Name : protDownDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Prot Down Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.11

Field Name : ipv6NorouteDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 No Route Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.10

Field Name : ipv4NorouteDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 No Route Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.9

Field Name : l2DefVlanDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : L2 Default Vlan FWD Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.8

Field Name : vlanFlood

Field Type : CounterBasedGauge64
Field Status : current
Description : VLAN Flood
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.7

Field Name : rxArpResp
Field Type : CounterBasedGauge64
Field Status : current
Description : ARP RESP Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.6

Field Name : rxArpReq
Field Type : CounterBasedGauge64
Field Status : current
Description : ARP REQ Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.5

Field Name : rxKernel
Field Type : CounterBasedGauge64
Field Status : current
Description : Received kernel
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.4

Field Name : bwlDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : BW Limit Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.3

Field Name : licexpireDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : License Expire Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.2

Field Name : fwlb
Field Type : CounterBasedGauge64
Field Status : current
Description : FWLB
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.1

Field Name : controlToSsl
Field Type : CounterBasedGauge64
Field Status : current
Description : Control chn ssl
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.23

Field Name : request
Field Type : CounterBasedGauge64
Field Status : current
Description : Total POP3 Request
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.22

Field Name : clRequestErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Client RQ state error
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.21

Field Name : serverResponseErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Serv RESP state error
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.20

Field Name : serConnectingErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Serv CTNG state error
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.19

Field Name : clEstErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Client EST state erro
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.18

Field Name : insertTupleFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Serv Sel insert tuple fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.17

Field Name : smpV4Fail
Field Type : CounterBasedGauge64
Field Status : current
Description : Serv Sel SMPv4 fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.16

Field Name : smpV6Fail
Field Type : CounterBasedGauge64
Field Status : current
Description : Serv Sel SMPv6 fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.15

Field Name : rsvPersistConnFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Serv Sel Persist fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.14

Field Name : badSequence
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Sequence
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.13

Field Name : unsupportedCommand
Field Type : CounterBasedGauge64
Field Status : current
Description : Unsupported cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.12

Field Name : requestDontCare
Field Type : CounterBasedGauge64
Field Status : current

Description : other cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.11

Field Name : stls
Field Type : CounterBasedGauge64
Field Status : current
Description : stls cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.10

Field Name : invalidStartLine
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid start line
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.9

Field Name : lineMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : request line freed
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.8

Field Name : lineTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : line too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.7

Field Name : snatFail
Field Type : CounterBasedGauge64
Field Status : current
Description : source nat failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.6

Field Name : noRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : no route failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.5

Field Name : svrselFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Server selection failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.4

Field Name : total
Field Type : CounterBasedGauge64
Field Status : current
Description : Total proxy conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.3

Field Name : curr
Field Type : CounterBasedGauge64
Field Status : current
Description : Current proxy conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.2

Field Name : num

Field Type : CounterBasedGauge64
Field Status : current
Description : Num
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.1

Field Name : negativeError
Field Type : CounterBasedGauge64
Field Status : current
Description : Negative error
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.55

Field Name : boundaryError
Field Type : CounterBasedGauge64
Field Status : current
Description : Boundary error
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.54

Field Name : allocError
Field Type : CounterBasedGauge64
Field Status : current
Description : Alloc error
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.53

Field Name : reallocError
Field Type : CounterBasedGauge64
Field Status : current
Description : Realloc error
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.52

Field Name : login
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Login cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.51

Field Name : startTls
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Start TLS cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.50

Field Name : capability
Field Type : CounterBasedGauge64
Field Status : current
Description : Capability cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.49

Field Name : request
Field Type : CounterBasedGauge64
Field Status : current
Description : Total FTP Request
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.48

Field Name : dataServConnectedErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Serv CTED error
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.47

Field Name : dataServConnectingErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Serv CTNG error
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.46

Field Name : dataConnStartErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Start state error
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.45

Field Name : clRequestErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Client RQ state error
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.44

Field Name : serverResponseErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Serv RESP state error
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.43

Field Name : serConnectingErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Serv CTNG state error
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.42

Field Name : clEstErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Client EST state erro
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.41

Field Name : insertTupleFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Serv Sel insert tuple fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.40

Field Name : smpV4Fail
Field Type : CounterBasedGauge64
Field Status : current
Description : Serv Sel SMPv4 fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.39

Field Name : smpV6Fail
Field Type : CounterBasedGauge64
Field Status : current
Description : Serv Sel SMPv6 fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.38

Field Name : rsvPersistConnFail
Field Type : CounterBasedGauge64
Field Status : current

Description : Serv Sel Persist fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.37

Field Name : badSequence
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Sequence
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.36

Field Name : controlToSsl
Field Type : CounterBasedGauge64
Field Status : current
Description : Control chn ssl
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.35

Field Name : controlToClear
Field Type : CounterBasedGauge64
Field Status : current
Description : Control chn clear txt
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.34

Field Name : unsupportedCommand
Field Type : CounterBasedGauge64
Field Status : current
Description : Unsupported cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.33

Field Name : unsupportedProtValue
Field Type : CounterBasedGauge64
Field Status : current
Description : Unsupported PROT
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.32

Field Name : unsupportedPbszValue
Field Type : CounterBasedGauge64
Field Status : current
Description : Unsupported PBSZ
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.31

Field Name : adat
Field Type : CounterBasedGauge64
Field Status : current
Description : adat cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.30

Field Name : authUnsupported
Field Type : CounterBasedGauge64
Field Status : current
Description : Unsupported auth
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.29

Field Name : dataTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Data Proxy
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.28

Field Name : dataCurr

Field Type : CounterBasedGauge64
Field Status : current
Description : Current Data Proxy
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.27

Field Name : cantFindEpsv
Field Type : CounterBasedGauge64
Field Status : current
Description : cant find epsv
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.26

Field Name : epsv
Field Type : CounterBasedGauge64
Field Status : current
Description : epsv command
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.25

Field Name : dataSendFail
Field Type : CounterBasedGauge64
Field Status : current
Description : data send fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.24

Field Name : dataServerConnFail
Field Type : CounterBasedGauge64
Field Status : current
Description : data svr conn fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.23

Field Name : smpCreateFail
Field Type : CounterBasedGauge64
Field Status : current
Description : smp create fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.22

Field Name : pasvAddrNeServer
Field Type : CounterBasedGauge64
Field Status : current
Description : psv addr not equal to svr
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.21

Field Name : cantFindPasv
Field Type : CounterBasedGauge64
Field Status : current
Description : cant find pasv
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.20

Field Name : clientAuthTls
Field Type : CounterBasedGauge64
Field Status : current
Description : client auth tls
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.19

Field Name : requestDontCare
Field Type : CounterBasedGauge64
Field Status : current
Description : other cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.18

Field Name : port
Field Type : CounterBasedGauge64
Field Status : current
Description : port cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.17

Field Name : pasv
Field Type : CounterBasedGauge64
Field Status : current
Description : pasv cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.16

Field Name : pbsz
Field Type : CounterBasedGauge64
Field Status : current
Description : pbsz cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.15

Field Name : prot
Field Type : CounterBasedGauge64
Field Status : current
Description : prot cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.14

Field Name : authTls
Field Type : CounterBasedGauge64
Field Status : current
Description : auth tls cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.13

Field Name : invalidStartLine
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid start line
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.12

Field Name : lineMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : request line freed
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.11

Field Name : lineTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : line too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.10

Field Name : dataSsl
Field Type : CounterBasedGauge64
Field Status : current
Description : data ssl force
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.9

Field Name : cc
Field Type : CounterBasedGauge64
Field Status : current

Description : clear ctrl port packet
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.8

Field Name : feat
Field Type : CounterBasedGauge64
Field Status : current
Description : feat packet
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.7

Field Name : snatFail
Field Type : CounterBasedGauge64
Field Status : current
Description : source nat failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.6

Field Name : noRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : no route failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.5

Field Name : svrselFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Server selection failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.4

Field Name : total
Field Type : CounterBasedGauge64
Field Status : current
Description : Total proxy conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.3

Field Name : curr
Field Type : CounterBasedGauge64
Field Status : current
Description : Current proxy conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.2

Field Name : num
Field Type : CounterBasedGauge64
Field Status : current
Description : Num
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.1

Field Name : cantFindEprt
Field Type : CounterBasedGauge64
Field Status : current
Description : cant find eprt
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.64

Field Name : cantFindPort
Field Type : CounterBasedGauge64
Field Status : current
Description : cant find port
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.63

Field Name : eprt

Field Type : CounterBasedGauge64
Field Status : current
Description : eprt cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.62

Field Name : quit
Field Type : CounterBasedGauge64
Field Status : current
Description : quit cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.61

Field Name : pass
Field Type : CounterBasedGauge64
Field Status : current
Description : pass cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.60

Field Name : user
Field Type : CounterBasedGauge64
Field Status : current
Description : user cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.59

Field Name : site
Field Type : CounterBasedGauge64
Field Status : current
Description : site cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.58

Field Name : open
Field Type : CounterBasedGauge64
Field Status : current
Description : open cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.57

Field Name : dsFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Host Domain Name isn't resolved
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.56

Field Name : dsSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : Host Domain Name is resolved
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.55

Field Name : drop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total FTP Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.54

Field Name : fwdToSg
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Forward to Service-group
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.53

Field Name : fwdToInternet
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward to Internet
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.52

Field Name : authFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Auth Failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.51

Field Name : authSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : Auth Success
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.50

Field Name : authReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Auth Request
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.49

Field Name : request
Field Type : CounterBasedGauge64
Field Status : current
Description : Total FTP Request
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.48

Field Name : dataServConnectedErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Serv CTED error
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.47

Field Name : dataServConnectingErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Serv CTNG error
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.46

Field Name : dataConnStartErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Start state error
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.45

Field Name : clRequestErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Client RQ state error
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.44

Field Name : serverResponseErr
Field Type : CounterBasedGauge64
Field Status : current

Description : Serv RESP state error
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.43

Field Name : serConnectingErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Serv CTNG state error
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.42

Field Name : clEstErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Client EST state erro
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.41

Field Name : insertTupleFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Serv Sel insert tuple fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.40

Field Name : smpV4Fail
Field Type : CounterBasedGauge64
Field Status : current
Description : Serv Sel SMPv4 fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.39

Field Name : smpV6Fail
Field Type : CounterBasedGauge64
Field Status : current
Description : Serv Sel SMPv6 fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.38

Field Name : rsvPersistConnFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Serv Sel Persist fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.37

Field Name : badSequence
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Sequence
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.36

Field Name : controlToSsl
Field Type : CounterBasedGauge64
Field Status : current
Description : Control chn ssl
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.35

Field Name : controlToClear
Field Type : CounterBasedGauge64
Field Status : current
Description : Control chn clear txt
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.34

Field Name : unsupportedCommand

Field Type : CounterBasedGauge64
Field Status : current
Description : Unsupported cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.33

Field Name : unsupportedProtValue
Field Type : CounterBasedGauge64
Field Status : current
Description : Unsupported PROT
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.32

Field Name : unsupportedPbszValue
Field Type : CounterBasedGauge64
Field Status : current
Description : Unsupported PBSZ
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.31

Field Name : adat
Field Type : CounterBasedGauge64
Field Status : current
Description : adat cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.30

Field Name : authUnsupported
Field Type : CounterBasedGauge64
Field Status : current
Description : Unsupported auth
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.29

Field Name : dataTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Data Proxy
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.28

Field Name : dataCurr
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Data Proxy
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.27

Field Name : cantFindEpsv
Field Type : CounterBasedGauge64
Field Status : current
Description : cant find epsv
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.26

Field Name : epsv
Field Type : CounterBasedGauge64
Field Status : current
Description : epsv command
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.25

Field Name : dataSendFail
Field Type : CounterBasedGauge64
Field Status : current
Description : data send fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.24

Field Name : dataServerConnFail
Field Type : CounterBasedGauge64
Field Status : current
Description : data svr conn fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.23

Field Name : smpCreateFail
Field Type : CounterBasedGauge64
Field Status : current
Description : smp create fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.22

Field Name : pasvAddrNeServer
Field Type : CounterBasedGauge64
Field Status : current
Description : psv addr not equal to svr
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.21

Field Name : cantFindPasv
Field Type : CounterBasedGauge64
Field Status : current
Description : cant find pasv
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.20

Field Name : clientAuthTls
Field Type : CounterBasedGauge64
Field Status : current
Description : client auth tls
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.19

Field Name : requestDontCare
Field Type : CounterBasedGauge64
Field Status : current
Description : other cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.18

Field Name : slbFtpProxyPort
Field Type : CounterBasedGauge64
Field Status : current
Description : port cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.17

Field Name : pasv
Field Type : CounterBasedGauge64
Field Status : current
Description : pasv cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.16

Field Name : pbsz
Field Type : CounterBasedGauge64
Field Status : current
Description : pbsz cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.15

Field Name : prot
Field Type : CounterBasedGauge64
Field Status : current

Description : prot cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.14

Field Name : authTls
Field Type : CounterBasedGauge64
Field Status : current
Description : auth tls cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.13

Field Name : invalidStartLine
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid start line
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.12

Field Name : lineMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : request line freed
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.11

Field Name : slbFtpProxyLineTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : line too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.10

Field Name : dataSsl
Field Type : CounterBasedGauge64
Field Status : current
Description : data ssl force
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.9

Field Name : cc
Field Type : CounterBasedGauge64
Field Status : current
Description : clear ctrl port packet
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.8

Field Name : feat
Field Type : CounterBasedGauge64
Field Status : current
Description : feat packet
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.7

Field Name : slbFtpProxySnatFail
Field Type : CounterBasedGauge64
Field Status : current
Description : source nat failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.6

Field Name : slbFtpProxyNoRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : no route failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.5

Field Name : slbFtpProxySvrselFail

Field Type : CounterBasedGauge64
Field Status : current
Description : Server selection failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.4

Field Name : slbFtpProxyTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total proxy conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.3

Field Name : slbFtpProxyCurr
Field Type : CounterBasedGauge64
Field Status : current
Description : Current proxy conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.2

Field Name : num
Field Type : CounterBasedGauge64
Field Status : current
Description : Num
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.1

Field Name : httpPktsOfo
Field Type : CounterBasedGauge64
Field Status : current
Description : fHTTP Out of Order packets
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.269

Field Name : httpServerRetx
Field Type : CounterBasedGauge64
Field Status : current
Description : Server Re-Tx fHTTP packets
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.268

Field Name : httpClientRetx
Field Type : CounterBasedGauge64
Field Status : current
Description : Client Re-Tx fHTTP packets
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.267

Field Name : httpPktsRetx
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot Re-Tx fHTTP packets
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.266

Field Name : httpPktsInSeq
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot In-seq fHTTP packets
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.265

Field Name : decompressionAfter
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot data after decompress
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.264

Field Name : decompressionBefore
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot data before decompress
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.263

Field Name : skipInsertClientPort
Field Type : CounterBasedGauge64
Field Status : current
Description : Skip Insert Client Port
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.262

Field Name : skipInsertClientIp
Field Type : CounterBasedGauge64
Field Status : current
Description : Skip Insert Client IP
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.261

Field Name : nonHttpBypass
Field Type : CounterBasedGauge64
Field Status : current
Description : Non-HTTP bypass
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.260

Field Name : fullProxyPut
Field Type : CounterBasedGauge64
Field Status : current
Description : Full proxy PUT
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.259

Field Name : reqTrack
Field Type : CounterBasedGauge64
Field Status : current
Description : Method TRACK
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.258

Field Name : insertClientPort
Field Type : CounterBasedGauge64
Field Status : current
Description : Insert client Port
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.257

Field Name : reqOver5s
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time greater than equal to 5s
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.256

Field Name : req5s
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 5s
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.255

Field Name : req2s
Field Type : CounterBasedGauge64
Field Status : current

Description : Rsp time less than 2s
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.254

Field Name : req1s
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 1s
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.253

Field Name : req500m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 500m
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.252

Field Name : req200m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 200m
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.251

Field Name : req100m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 100m
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.250

Field Name : req50m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 50m
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.249

Field Name : req20m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 20m
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.248

Field Name : req10m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 10m
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.247

Field Name : req5m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 5m
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.246

Field Name : req2m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 2m
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.245

Field Name : req1m

Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 1m
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.244

Field Name : req500u
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 500u
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.243

Field Name : req200u
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 200u
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.242

Field Name : req100u
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 100u
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.241

Field Name : req50u
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 50u
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.240

Field Name : req20u
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 20u
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.239

Field Name : req10u
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 10u
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.238

Field Name : chunkBad
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Chunk
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.223

Field Name : pconnConnectingFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : pconn conn failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.222

Field Name : pconnConnected
Field Type : CounterBasedGauge64
Field Status : current
Description : pconn connected
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.221

Field Name : pconnConnecting
Field Type : CounterBasedGauge64
Field Status : current
Description : pconn connecting
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.220

Field Name : chunkSzGt4k
Field Type : CounterBasedGauge64
Field Status : current
Description : Chunk greater than 4K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.219

Field Name : chunkSz4k
Field Type : CounterBasedGauge64
Field Status : current
Description : Chunk less than equal to 4K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.218

Field Name : chunkSz2k
Field Type : CounterBasedGauge64
Field Status : current
Description : Chunk less than equal to 2K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.217

Field Name : chunkSz1k
Field Type : CounterBasedGauge64
Field Status : current
Description : Chunk less than equal to 1K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.216

Field Name : chunkSz512
Field Type : CounterBasedGauge64
Field Status : current
Description : Chunk less than equal to 512
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.215

Field Name : rspSzGt256k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp greater than 256K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.214

Field Name : rspSz256k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp less than equal to 256K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.213

Field Name : rspSz64k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp less than equal to 64K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.212

Field Name : rspSz32k
Field Type : CounterBasedGauge64
Field Status : current

Description : Resp less than equal to 32K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.211

Field Name : rspSz16k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp less than equal to 16K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.210

Field Name : rspSz8k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp less than equal to 8K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.209

Field Name : rspSz4k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp less than equal to 4K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.208

Field Name : rspSz2k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp less than equal to 2K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.207

Field Name : rspSz1k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp less than equal to 1K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.206

Field Name : reqSzGt256k
Field Type : CounterBasedGauge64
Field Status : current
Description : Req greater than 256K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.205

Field Name : reqSz256k
Field Type : CounterBasedGauge64
Field Status : current
Description : Req less than equal to 256K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.204

Field Name : reqSz64k
Field Type : CounterBasedGauge64
Field Status : current
Description : Req less than equal to 64K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.203

Field Name : reqSz32k
Field Type : CounterBasedGauge64
Field Status : current
Description : Req less than equal to 32K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.202

Field Name : reqSz16k

Field Type : CounterBasedGauge64
Field Status : current
Description : Req less than equal to 16K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.201

Field Name : reqSz8k
Field Type : CounterBasedGauge64
Field Status : current
Description : Req less than equal to 8K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.200

Field Name : reqSz4k
Field Type : CounterBasedGauge64
Field Status : current
Description : Req less than equal to 4K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.199

Field Name : reqSz2k
Field Type : CounterBasedGauge64
Field Status : current
Description : Req less than equal to 2K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.198

Field Name : reqSz1k
Field Type : CounterBasedGauge64
Field Status : current
Description : Req less than equal to 1K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.197

Field Name : reqHttp10Keepalive
Field Type : CounterBasedGauge64
Field Status : current
Description : 1.0 Keepalive
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.196

Field Name : closeOnDdos
Field Type : CounterBasedGauge64
Field Status : current
Description : Close on DDoS
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.195

Field Name : cacheRsp
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP req (cache succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.194

Field Name : compressRatioTooHigh
Field Type : CounterBasedGauge64
Field Status : current
Description : Compress ratio too high
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.193

Field Name : compressRespNoClOrCe
Field Type : CounterBasedGauge64
Field Status : current
Description : Compress resp no CL/CE
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.192

Field Name : compressRespLtMin
Field Type : CounterBasedGauge64
Field Status : current
Description : Compress resp less than min
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.191

Field Name : compressNoContentType
Field Type : CounterBasedGauge64
Field Status : current
Description : Compress no cont type
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.190

Field Name : compressContentTypeExcluded
Field Type : CounterBasedGauge64
Field Status : current
Description : Compress cont type excl
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.189

Field Name : compressRespAlreadyCompressed
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp already compressed
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.188

Field Name : compressDelAcceptEnc
Field Type : CounterBasedGauge64
Field Status : current
Description : Compress del accept enc
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.187

Field Name : compressRsp
Field Type : CounterBasedGauge64
Field Status : current
Description : Compress req
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.186

Field Name : reqChunk
Field Type : CounterBasedGauge64
Field Status : current
Description : Req chunk encoding
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.185

Field Name : rspChunk
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp chunk encoding
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.184

Field Name : rspContentLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp content len
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.183

Field Name : reqContentLen
Field Type : CounterBasedGauge64
Field Status : current

Description : Req content len
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.182

Field Name : reqUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : Method UNKNOWN
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.181

Field Name : reqDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : Method DELETE
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.180

Field Name : reqConnect
Field Type : CounterBasedGauge64
Field Status : current
Description : Method CONNECT
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.179

Field Name : reqOptions
Field Type : CounterBasedGauge64
Field Status : current
Description : Method OPTIONS
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.178

Field Name : reqTrace
Field Type : CounterBasedGauge64
Field Status : current
Description : Method TRACE
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.177

Field Name : reqPost
Field Type : CounterBasedGauge64
Field Status : current
Description : Method POST
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.176

Field Name : reqPut
Field Type : CounterBasedGauge64
Field Status : current
Description : Method PUT
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.175

Field Name : reqHead
Field Type : CounterBasedGauge64
Field Status : current
Description : Method HEAD
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.174

Field Name : reqGet
Field Type : CounterBasedGauge64
Field Status : current
Description : Method GET
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.173

Field Name : responseHttp11

Field Type : CounterBasedGauge64
Field Status : current
Description : Resp 1.1
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.172

Field Name : responseHttp10
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp 1.0
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.171

Field Name : reqHttp11
Field Type : CounterBasedGauge64
Field Status : current
Description : Request 1.1
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.170

Field Name : reqHttp10
Field Type : CounterBasedGauge64
Field Status : current
Description : Request 1.0
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.169

Field Name : responseUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code unknown
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.168

Field Name : response6xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 6XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.167

Field Name : response510
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 510
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.166

Field Name : response509
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 509
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.165

Field Name : response508
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 508
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.164

Field Name : response507
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 507
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.163

Field Name : response506
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 506
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.162

Field Name : response505
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 505
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.161

Field Name : response504
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 504
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.160

Field Name : response503
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 503
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.159

Field Name : response502
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 502
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.158

Field Name : response501
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 501
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.157

Field Name : response500
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 500
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.156

Field Name : response5xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 5XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.155

Field Name : response450
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 450
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.154

Field Name : response449
Field Type : CounterBasedGauge64
Field Status : current

Description : Status code 449
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.153

Field Name : response426
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 426
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.152

Field Name : response425
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 425
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.151

Field Name : response424
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 424
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.150

Field Name : response423
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 423
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.149

Field Name : response422
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 422
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.148

Field Name : response418
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 418
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.147

Field Name : response417
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 417
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.146

Field Name : response416
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 416
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.145

Field Name : response415
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 415
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.144

Field Name : response414

Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 414
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.143

Field Name : response413
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 413
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.142

Field Name : response412
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 412
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.141

Field Name : response411
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 411
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.140

Field Name : response410
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 410
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.139

Field Name : response409
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 409
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.138

Field Name : response408
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 408
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.137

Field Name : response407
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 407
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.136

Field Name : response406
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 406
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.135

Field Name : response405
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 405
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.134

Field Name : response404
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 404
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.133

Field Name : response403
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 403
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.132

Field Name : response402
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 402
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.131

Field Name : response401
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 401
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.130

Field Name : response400
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 400
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.129

Field Name : response4xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 4XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.128

Field Name : response307
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 307
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.127

Field Name : response306
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 306
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.126

Field Name : response305
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 305
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.125

Field Name : response304
Field Type : CounterBasedGauge64
Field Status : current

Description : Status code 304
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.124

Field Name : response303
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 303
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.123

Field Name : response302
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 302
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.122

Field Name : response301
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 301
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.121

Field Name : response300
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 300
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.120

Field Name : response3xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 3XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.119

Field Name : response207
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 207
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.118

Field Name : response206
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 206
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.117

Field Name : response205
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 205
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.116

Field Name : response204
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 204
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.115

Field Name : response203

Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 203
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.114

Field Name : response202
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 202
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.113

Field Name : response201
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 201
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.112

Field Name : response200
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 200
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.111

Field Name : response2xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 2XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.110

Field Name : response102
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 102
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.109

Field Name : response101
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 101
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.108

Field Name : response100
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 100
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.107

Field Name : response1xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 1XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.106

Field Name : compressionAfter
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot data after compress
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.104

Field Name : compressionBefore
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot data before compress
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.102

Field Name : serverReselFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Server re-select failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.101

Field Name : staleSess
Field Type : CounterBasedGauge64
Field Status : current
Description : Stale sess
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.100

Field Name : pktsRetransPush
Field Type : CounterBasedGauge64
Field Status : current
Description : retrans PSH
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.99

Field Name : pktsRetransRst
Field Type : CounterBasedGauge64
Field Status : current
Description : retrans RST
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.98

Field Name : pktsRetransFin
Field Type : CounterBasedGauge64
Field Status : current
Description : retrans FIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.97

Field Name : pktsRetransAckFinwait
Field Type : CounterBasedGauge64
Field Status : current
Description : retrans ACK FWAIT
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.96

Field Name : pktsRetrans
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets retrans
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.95

Field Name : pktsOfo
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets ofo
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.94

Field Name : connectingAck
Field Type : CounterBasedGauge64
Field Status : current

Description : Connecting ACK
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.93

Field Name : connectingRstOfo
Field Type : CounterBasedGauge64
Field Status : current
Description : Connecting RST ofo
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.92

Field Name : connectingRstRetrans
Field Type : CounterBasedGauge64
Field Status : current
Description : Connecting RST retran
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.91

Field Name : connectingRst
Field Type : CounterBasedGauge64
Field Status : current
Description : Connecting RST
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.90

Field Name : connectingFinOfo
Field Type : CounterBasedGauge64
Field Status : current
Description : Connecting FIN ofo
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.89

Field Name : connectingFinRetrans
Field Type : CounterBasedGauge64
Field Status : current
Description : Connecting FIN retran
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.88

Field Name : connectingFin
Field Type : CounterBasedGauge64
Field Status : current
Description : Connecting FIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.87

Field Name : clientReqUnexpFlag
Field Type : CounterBasedGauge64
Field Status : current
Description : Client req unexp flags
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.86

Field Name : asmSetcookieHeaderFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Asm set-cookie hdr fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.85

Field Name : asmSetcookieFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Assemble set-cookie fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.84

Field Name : asmCookieHeaderFail

Field Type : CounterBasedGauge64
Field Status : current
Description : Asm cookie header fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.83

Field Name : asmCookieFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Assemble cookie fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.82

Field Name : parseSetcookieFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Parse set-cookie fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.81

Field Name : parseCookieFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Parse cookie fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.80

Field Name : hugeCookieHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : Huge cookie headers
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.79

Field Name : hugeCookie
Field Type : CounterBasedGauge64
Field Status : current
Description : Huge cookies
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.78

Field Name : largeCookieHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : Large cookie headers
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.77

Field Name : largeCookie
Field Type : CounterBasedGauge64
Field Status : current
Description : Large cookies
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.76

Field Name : negativeRespRemain
Field Type : CounterBasedGauge64
Field Status : current
Description : Negative response remain
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.75

Field Name : negativeReqRemain
Field Type : CounterBasedGauge64
Field Status : current
Description : Negative request remain
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.74

Field Name : insertClientIp
Field Type : CounterBasedGauge64
Field Status : current
Description : Insert client IP
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.73

Field Name : headerDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : Header delete
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.72

Field Name : headerInsert
Field Type : CounterBasedGauge64
Field Status : current
Description : Header insert
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.71

Field Name : wrongRespHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : Wrong response header
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.70

Field Name : headerNameTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Header name too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.69

Field Name : lineTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Line too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.68

Field Name : tooManyHeaders
Field Type : CounterBasedGauge64
Field Status : current
Description : Too many headers
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.67

Field Name : invalidHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid header
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.66

Field Name : serverRstResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Server RST - response
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.65

Field Name : serverRstConnected
Field Type : CounterBasedGauge64
Field Status : current

Description : Server RST - connected
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.64

Field Name : serverRstConnecting
Field Type : CounterBasedGauge64
Field Status : current
Description : Server RST - connecting
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.63

Field Name : serverRstRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Server RST - request
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.62

Field Name : clientRstResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Client RST - response
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.61

Field Name : clientRstConnected
Field Type : CounterBasedGauge64
Field Status : current
Description : Client RST - connected
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.60

Field Name : clientRstConnecting
Field Type : CounterBasedGauge64
Field Status : current
Description : Client RST - connecting
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.59

Field Name : clientRstRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Client RST - request
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.58

Field Name : aflexLbReselectOk
Field Type : CounterBasedGauge64
Field Status : current
Description : aFleX lb reselect (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.57

Field Name : aflexLbReselect
Field Type : CounterBasedGauge64
Field Status : current
Description : aFleX lb reselect
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.56

Field Name : aflexRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : aFleX http retry
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.55

Field Name : retry503

Field Type : CounterBasedGauge64
Field Status : current
Description : Retry on 503
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.54

Field Name : lbSwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : Normal LB switch. (enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.53

Field Name : hostSwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : Host switching (enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.52

Field Name : urlSwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : URL switching (enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.51

Field Name : httpPolicySwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Policy switching (enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.50

Field Name : aflexSwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : aFleX switching (enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.49

Field Name : cookieSwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie switching (enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.48

Field Name : l4SwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 switching (enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.47

Field Name : lbSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : Normal LB switch. (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.46

Field Name : hostSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : Host switching (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.45

Field Name : urlSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : URL switching (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.44

Field Name : httpPolicySwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Policy switching (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.43

Field Name : aflexSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : aFleX switching (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.42

Field Name : cookieSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie switching (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.41

Field Name : l4SwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 switching (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.40

Field Name : lbSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : Normal LB switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.39

Field Name : hostSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : Host switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.38

Field Name : urlSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : URL switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.37

Field Name : httpPolicySwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Policy switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.36

Field Name : aflexSwitching
Field Type : CounterBasedGauge64
Field Status : current

Description : aFleX switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.35

Field Name : cookieSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.34

Field Name : l4Switching
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.33

Field Name : reqRateOverLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : Request rate over limit
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.32

Field Name : reqOverLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : Request over limit
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.31

Field Name : fullProxyFpgaErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Full proxy fpga err
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.30

Field Name : fullProxyPipeline
Field Type : CounterBasedGauge64
Field Status : current
Description : Full proxy pipeline
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.29

Field Name : fullProxyPost
Field Type : CounterBasedGauge64
Field Status : current
Description : Full proxy POST
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.28

Field Name : fullProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Full proxy tot
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.27

Field Name : tcpoutrst
Field Type : CounterBasedGauge64
Field Status : current
Description : Out RSTs
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.26

Field Name : slbFastHttpProxySnatFail

Field Type : CounterBasedGauge64
Field Status : current
Description : Source NAT failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.25

Field Name : newSvrconn
Field Type : CounterBasedGauge64
Field Status : current
Description : Server conn made
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.24

Field Name : svrPremClose
Field Type : CounterBasedGauge64
Field Status : current
Description : Server premature close
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.23

Field Name : serverResel
Field Type : CounterBasedGauge64
Field Status : current
Description : Server reselection
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.22

Field Name : slbFastHttpProxyReqOfo
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets ofo
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.21

Field Name : slbFastHttpProxyReqRetran
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets retrans
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.20

Field Name : fwdreqdataFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req data fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.19

Field Name : fwdreqFailTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - tuple
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.18

Field Name : fwdreqFailServer
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - server
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.17

Field Name : fwdreqFailPersist
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - persist
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.16

Field Name : fwdreqFailRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - route
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.15

Field Name : fwdreqFailRport
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - rport
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.14

Field Name : fwdreqFailBuff
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - buff
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.13

Field Name : fwdreqFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.12

Field Name : slbFastHttpProxySrvSelFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Server selection fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.11

Field Name : parsereqFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Parse req fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.10

Field Name : notuple
Field Type : CounterBasedGauge64
Field Status : current
Description : No tuple error
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.9

Field Name : slbFastHttpProxyServerRst
Field Type : CounterBasedGauge64
Field Status : current
Description : Server RST
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.8

Field Name : slbFastHttpProxyClientRst
Field Type : CounterBasedGauge64
Field Status : current
Description : Client RST
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.7

Field Name : noproxy
Field Type : CounterBasedGauge64
Field Status : current

Description : No proxy error
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.6

Field Name : reqSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP requests(succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.5

Field Name : slbFastHttpProxyReq
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.4

Field Name : slbFastHttpProxyTotalProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Proxy Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.3

Field Name : slbFastHttpProxyCurrProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr Proxy Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.2

Field Name : num
Field Type : CounterBasedGauge64
Field Status : current
Description : Num
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.1

Field Name : fastPathL2Reroute
Field Type : CounterBasedGauge64
Field Status : current
Description : Fast Path L2 Reroute
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.138

Field Name : fastPathReroute
Field Type : CounterBasedGauge64
Field Status : current
Description : Fast Path Reroute
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.137

Field Name : pbslbEntryLimitExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : pbslb entry limit Exceed
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.136

Field Name : slbGtpProxyRetxRequests
Field Type : CounterBasedGauge64
Field Status : current
Description : SLB GTP proxy retx requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.135

Field Name : slbGtpProxySmpFreed

Field Type : CounterBasedGauge64
Field Status : current
Description : SLB GTP proxy session helper freed
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.134

Field Name : slbGtpProxySmpFreeNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : SLB GTP proxy session helper not found during cleanup
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.133

Field Name : slbGtpProxySmpCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : SLB GTP proxy helper session created
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.132

Field Name : slbGtpProxySmpCreationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : SLB GTP proxy helper session creation failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.131

Field Name : slbGtpProxyCProcessLocalRr
Field Type : CounterBasedGauge64
Field Status : current
Description : SLB GTP proxy messageprocessed locally on RR
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.130

Field Name : slbGtpProxySmpNoMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SLB GTP proxy helper session not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.129

Field Name : slbGtpProxySmpMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SLB GTP proxy helper session found
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.128

Field Name : slbGtpProxyPktRcvRr
Field Type : CounterBasedGauge64
Field Status : current
Description : SLB GTP proxy packet received on RR
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.127

Field Name : proxyProtDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : PROXY protocol drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.126

Field Name : proxyProtError
Field Type : CounterBasedGauge64
Field Status : current
Description : PROXY protocol error
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.125

Field Name : proxyHeaderRexmit
Field Type : CounterBasedGauge64
Field Status : current
Description : PROXY protocol header retransmitted
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.124

Field Name : proxyHeaderInsert
Field Type : CounterBasedGauge64
Field Status : current
Description : PROXY protocol header inserted
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.123

Field Name : snatForcePreserveFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Snat port preserve freed
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.122

Field Name : snatForcePreserveAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Snat port preserve allocated
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.121

Field Name : snatPortOverloadFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Snat port overload fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.120

Field Name : reselectSvrselfail
Field Type : CounterBasedGauge64
Field Status : current
Description : Server reselect failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.119

Field Name : gtpCInvalidMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : Non Create Session/PDP Context Request/Response Received on GTP VIP
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.118

Field Name : gtpCInvalidHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid Header Received on GTP VIP
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.117

Field Name : gtpCInvalidPort
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid Packet Received on GTP VIP
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.116

Field Name : tcpConnectionsClosed
Field Type : CounterBasedGauge64
Field Status : current

Description : TCP Connections Closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.115

Field Name : rateDropResetUnkn
Field Type : CounterBasedGauge64
Field Status : current
Description : Rate Drop reset
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.114

Field Name : dnssecSwitch
Field Type : CounterBasedGauge64
Field Status : current
Description : DNSSEC SG switch
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.113

Field Name : serverDownDel
Field Type : CounterBasedGauge64
Field Status : current
Description : Server Down Del switch
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.112

Field Name : dnsIdSwitch
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS query id switch
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.111

Field Name : synreceivedHw
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN (HW SYN cookie)
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.110

Field Name : skipInsertClientIp
Field Type : CounterBasedGauge64
Field Status : current
Description : Skip Insert-client-ip
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.109

Field Name : syncookieBuffQueue
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN cookie buff queue
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.108

Field Name : syncookieBuffDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN cookie buff drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.107

Field Name : synRate
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN rate per sec
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.106

Field Name : synattack

Field Type : CounterBasedGauge64
Field Status : current
Description : L4 SYN attack
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.105

Field Name : tcpEst
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 TCP Established
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.104

Field Name : outSeqAckDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of sequence ACK drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.103

Field Name : udpRespOneplus
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 UDP rsps
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.102

Field Name : udpReqOneplus
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 UDP reqs
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.101

Field Name : udpRespMoreReq
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 UDP rsps greater than reqs
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.100

Field Name : udpReqMoreResp
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 UDP req greater than rsps
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.99

Field Name : udpReqRespNotmatch
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 UDP req/rsp not match
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.98

Field Name : udpReqOneOneplusResp
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 UDP req rsps
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.97

Field Name : udpReqOneplusNoResp
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 UDP reqs no rsp
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.96

Field Name : tcpRevRst
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 rcv rev RST
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.95

Field Name : tcpFwdRst
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 rcv fwd RST
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.94

Field Name : tcpRevAckfin
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 rcv rev FIN|ACK
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.93

Field Name : tcpRevFinDup
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 rcv rev FIN dup
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.92

Field Name : tcpFwdFinDup
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 rcv fwd FIN dup
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.91

Field Name : tcpRexmitSynackDelq
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 rcv rexmit SYN|ACK DQ
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.90

Field Name : tcpRexmitSynack
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 rcv rexmit SYN|ACK
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.89

Field Name : tcpRexmitSynDelq
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 rcv rexmit SYN (delq)
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.88

Field Name : tcpRexmitSyn
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 rcv rexmit SYN
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.87

Field Name : tcpSessNoestSsynXmitAgedOut
Field Type : CounterBasedGauge64
Field Status : current

Description : no-Est SSYN snt aged out
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.86

Field Name : tcpSessNoestCsynRcvAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : no-Est CSYN rcv aged out
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.85

Field Name : tcpSessNoestAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP no-Est Sess aged out
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.84

Field Name : tcpSynRcvRst
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 rcv RST on SYN
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.83

Field Name : tcpSynRcvAck
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 rcv ACK on SYN
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.82

Field Name : tcpAxRexmitSyn
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 AX re-xmit SYN
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.81

Field Name : statelessConnTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 stateless Conn TO
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.80

Field Name : svrSynHandshakeFail
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 server handshake fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.79

Field Name : concurrentConnExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : L3V Conn Limit Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.78

Field Name : sslWatermarkDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL TPT-Watermark drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.77

Field Name : sslTptExceed

Field Type : CounterBasedGauge64
Field Status : current
Description : SSL TPT exceed drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.76

Field Name : sslCpsExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL CPS exceed drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.75

Field Name : l7CpsExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 CPS exceed drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.74

Field Name : natCpsExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT CPS exceed drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.73

Field Name : l4CpsExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 CPS exceed drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.72

Field Name : bwWatermarkDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : BW-Watermark drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.71

Field Name : bwRateLimitExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : BW-Limit Exceed drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.70

Field Name : tcpotherflagsDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Other Flags Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.69

Field Name : tcpsyndataDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN With Data Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.68

Field Name : portPreserveSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT Port Preserve Succ
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.67

Field Name : portPreserveAttempt
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT Port Preserve Try
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.66

Field Name : l3Dsr
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 DSR received
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.65

Field Name : l2Dsr
Field Type : CounterBasedGauge64
Field Status : current
Description : L2 DSR received
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.64

Field Name : ignoreMsl
Field Type : CounterBasedGauge64
Field Status : current
Description : ignore msl
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.63

Field Name : resetL7OnFailover
Field Type : CounterBasedGauge64
Field Status : current
Description : RST L7 on failover
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.62

Field Name : resetUnknownConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Reset unknown conn
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.61

Field Name : noResourseDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : No resource drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.60

Field Name : anomalyPbslbDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Anomaly pbslb drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.59

Field Name : anomalyBadContent
Field Type : CounterBasedGauge64
Field Status : current
Description : Anomaly bad content
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.58

Field Name : anomalyZeroWin
Field Type : CounterBasedGauge64
Field Status : current

Description : Anomaly zero window
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.57

Field Name : anomalyOutSeq
Field Type : CounterBasedGauge64
Field Status : current
Description : Anomaly out of sequence
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.56

Field Name : tcpInvalidDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP invalid drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.55

Field Name : dnsPolicyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Policy Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.54

Field Name : fastAgingReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Fast aging reset
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.53

Field Name : fastAgingSet
Field Type : CounterBasedGauge64
Field Status : current
Description : Fast aging set
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.52

Field Name : autoReassign
Field Type : CounterBasedGauge64
Field Status : current
Description : Auto-reselect server
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.51

Field Name : inbandHmReassign
Field Type : CounterBasedGauge64
Field Status : current
Description : Inband HM reassign
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.50

Field Name : inbandHmRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : Inband HM retry
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.49

Field Name : dropGslb
Field Type : CounterBasedGauge64
Field Status : current
Description : Drop GSLB
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.48

Field Name : throttleSyn

Field Type : CounterBasedGauge64
Field Status : current
Description : SYN Throttle
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.47

Field Name : udpNoSlb
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP no SLB
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.46

Field Name : tcpNoSlb
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP no SLB
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.45

Field Name : otherSessAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Other Session aged out
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.44

Field Name : udpSessAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Session aged out
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.43

Field Name : tcpSessAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Session aged out
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.42

Field Name : sessAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Session aged out
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.41

Field Name : dropAflex
Field Type : CounterBasedGauge64
Field Status : current
Description : aFleX drops
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.40

Field Name : proxyNosockDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Proxy no sock drops
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.39

Field Name : connRateLimitReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn rate limit resets
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.38

Field Name : connRateLimitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn rate limit drops
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.37

Field Name : connlimitReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Limit resets
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.36

Field Name : connlimitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Limit drops
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.35

Field Name : nosynDropAck
Field Type : CounterBasedGauge64
Field Status : current
Description : No SYN pkt drops - ACK
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.34

Field Name : nosynDropRst
Field Type : CounterBasedGauge64
Field Status : current
Description : No SYN pkt drops - RST
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.33

Field Name : nosynDropFin
Field Type : CounterBasedGauge64
Field Status : current
Description : No SYN pkt drops - FIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.32

Field Name : nosynDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : No SYN pkt drops
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.31

Field Name : noVportDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : vport not matching drops
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.30

Field Name : novportDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT no session drops
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.29

Field Name : syncookiescheckfailed
Field Type : CounterBasedGauge64
Field Status : current

Description : TCP SYN cookie failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.28

Field Name : smartNatIdMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Auto NAT id mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.27

Field Name : snatIcmpNoMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Source NAT ICMP No Match
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.26

Field Name : snatIcmpErrorProcess
Field Type : CounterBasedGauge64
Field Status : current
Description : Source NAT ICMP Process
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.25

Field Name : snatNoRevRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : Source NAT no rev route
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.24

Field Name : snatNoFwdRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : Source NAT no fwd route
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.23

Field Name : snatFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Source NAT failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.22

Field Name : noroute
Field Type : CounterBasedGauge64
Field Status : current
Description : IP out noroute
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.21

Field Name : svrselfail
Field Type : CounterBasedGauge64
Field Status : current
Description : Server sel failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.20

Field Name : outrstTcpproxy
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP out RST TCP proxy
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.19

Field Name : synStaleSess

Field Type : CounterBasedGauge64
Field Status : current
Description : SYN stale sess drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.18

Field Name : outrstStaleSess
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP out RST stale sess
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.17

Field Name : outrstAflex
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP out RST aFleX
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.16

Field Name : outrstAckAttack
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP out RST ACK attack
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.15

Field Name : outrstBroker
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP out RST L4 proxy
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.14

Field Name : outrstNosyn
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP out RST no SYN
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.13

Field Name : outrst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP out RST
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.12

Field Name : syncookiessentfailed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN cookie snt fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.11

Field Name : syncookiessentTs
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN cookie snt ts
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.10

Field Name : syncookiessent
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN cookie snt
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.9

Field Name : inudp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP received
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.8

Field Name : tcpFwdAckfin
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 rcv fwd FIN|ACK
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.7

Field Name : tcpFwdFin
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 rcv fwd FIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.6

Field Name : tcpRevFin
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 rcv rev FIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.5

Field Name : tcpRevLastAck
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 rcv rev last ACK
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.4

Field Name : tcpFwdLastAck
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 rcv fwd last ACK
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.3

Field Name : synreceived
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN received
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.2

Field Name : intcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP received
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.1

Field Name : localLogDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Local log dropped due to rate-limit
OID : 1.3.6.1.4.1.22610.2.4.10.108.47.1.15

Field Name : noRepeatMsg
Field Type : CounterBasedGauge64
Field Status : current

Description : No repeat message
OID : 1.3.6.1.4.1.22610.2.4.10.108.47.1.14

Field Name : connAllocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Log-session alloc fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.47.1.13

Field Name : freeConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Log-session free
OID : 1.3.6.1.4.1.22610.2.4.10.108.47.1.12

Field Name : allocConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Log-session alloc
OID : 1.3.6.1.4.1.22610.2.4.10.108.47.1.11

Field Name : buffSendFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Buffer send fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.47.1.10

Field Name : slbRateLimitLogNoRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : No route
OID : 1.3.6.1.4.1.22610.2.4.10.108.47.1.9

Field Name : buffAllocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Buffer alloc fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.47.1.8

Field Name : msgTooBig
Field Type : CounterBasedGauge64
Field Status : current
Description : Log message too big
OID : 1.3.6.1.4.1.22610.2.4.10.108.47.1.7

Field Name : remoteLogRate
Field Type : CounterBasedGauge64
Field Status : current
Description : Remote rate (per sec)
OID : 1.3.6.1.4.1.22610.2.4.10.108.47.1.6

Field Name : localLogRate
Field Type : CounterBasedGauge64
Field Status : current
Description : Local rate (per sec)
OID : 1.3.6.1.4.1.22610.2.4.10.108.47.1.5

Field Name : remoteLogMsg

Field Type : CounterBasedGauge64
Field Status : current
Description : Remote log messages
OID : 1.3.6.1.4.1.22610.2.4.10.108.47.1.4

Field Name : localLogMsg
Field Type : CounterBasedGauge64
Field Status : current
Description : Local log messages
OID : 1.3.6.1.4.1.22610.2.4.10.108.47.1.3

Field Name : totalLogMsg
Field Type : CounterBasedGauge64
Field Status : current
Description : Total log messages
OID : 1.3.6.1.4.1.22610.2.4.10.108.47.1.2

Field Name : totalLogTimes
Field Type : CounterBasedGauge64
Field Status : current
Description : Total log times
OID : 1.3.6.1.4.1.22610.2.4.10.108.47.1.1

Field Name : transactionLimited
Field Type : CounterBasedGauge64
Field Status : current
Description : Transaction limited
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.359

Field Name : reqHttp11NewProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Request 1.1 (new proxy)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.358

Field Name : delH2cHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : H2C header deletion
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.357

Field Name : upgradeToNewProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : H2C upgrade
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.356

Field Name : httpAllowedMethods
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP allowed methods
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.355

Field Name : httpDisallowedMethods
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP disallowed methods
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.354

Field Name : http2ClientIdleTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP2 client idle timeout
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.353

Field Name : http1ClientIdleTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP1 client idle timeout
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.352

Field Name : headerFilterRuleHit
Field Type : CounterBasedGauge64
Field Status : current
Description : Hit header filter rule
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.351

Field Name : responseHttp3
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp 3.0
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.350

Field Name : reqHttp3
Field Type : CounterBasedGauge64
Field Status : current
Description : Request 3.0
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.349

Field Name : h2upWithHostAndAuth
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP2 with host header and authority header
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.348

Field Name : getAndPayload
Field Type : CounterBasedGauge64
Field Status : current
Description : GET method with content-length header or transfer-encoding header
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.347

Field Name : transferEncodingAndContentLength
Field Type : CounterBasedGauge64
Field Status : current
Description : Transfer-encoding header with Content-Length header
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.346

Field Name : multipleTransferEncoding
Field Type : CounterBasedGauge64
Field Status : current
Description : Multiple transfer-encoding headers
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.345

Field Name : multipleContentLength
Field Type : CounterBasedGauge64
Field Status : current

Description : Multiple content-length headers
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.344

Field Name : h2upWithTransferEncoding
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP2 with transfer-encoding header
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.343

Field Name : malformedH2upSchemeValue
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed HTTP2 scheme value
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.342

Field Name : malformedH2upHeaderValue
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed HTTP2 header value
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.341

Field Name : h2upContentLengthAlias
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP2 content length alias
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.340

Field Name : compressRspTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Compress req
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.339

Field Name : compressRspBr
Field Type : CounterBasedGauge64
Field Status : current
Description : Compress req with brotli
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.338

Field Name : decompressionAfterTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot data after decompress
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.336

Field Name : decompressionBeforeTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot data before decompress
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.335

Field Name : decompressionAfterBr
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot data after brotli decompress
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.334

Field Name : decompressionBeforeBr

Field Type : CounterBasedGauge64
Field Status : current
Description : Tot data before brotli decompress
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.333

Field Name : compressionAfterTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot data after compress
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.332

Field Name : compressionBeforeTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot data before compress
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.331

Field Name : compressionAfterBr
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot data after brotli compress
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.330

Field Name : compressionBeforeBr
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot data before brotli compress
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.329

Field Name : dohDnsRespRcodeOther
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH DNS Response rcode OTHER
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.328

Field Name : dohDnsRespRcodeNotzone
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH DNS Response rcode NOTZONE
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.327

Field Name : dohDnsRespRcodeNotauth
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH DNS Response rcode NOTAUTH
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.326

Field Name : dohDnsRespRcodeNxrrset
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH DNS Response rcode NXRRSET
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.325

Field Name : dohDnsRespRcodeYxrrset
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH DNS Response rcode YXRRSET
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.324

Field Name : dohDnsRespRcodeYxdomain
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH DNS Response rcode YXDOMAIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.323

Field Name : dohDnsRespRcodeRefuse
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH DNS Response rcode REFUSE
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.322

Field Name : dohDnsRespRcodeErrType
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH DNS Response rcode ERR_TYPE
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.321

Field Name : dohDnsRespRcodeErrName
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH DNS Response rcode ERR_NAME
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.320

Field Name : dohDnsRespRcodeErrServer
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH DNS Response rcode ERR_SERVER
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.319

Field Name : dohDnsRespRcodeErrFormat
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH DNS Response rcode ERR_FORMAT
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.318

Field Name : dohDnsMalformedQuery
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH DNS Malformed Query
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.317

Field Name : dohPostPayloadTooLarge
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH POST Payload too large
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.316

Field Name : dohGetUriTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH GET URI too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.315

Field Name : dohRetryWTcp
Field Type : CounterBasedGauge64
Field Status : current

Description : DoH Retry with TCP SG
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.314

Field Name : dohServSelFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Server Select Failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.313

Field Name : dohRespTcpFrags
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH TCP Frags Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.312

Field Name : dohRespUdpFrags
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH UDP Frags Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.311

Field Name : dohRespQueFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Resp queue failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.310

Field Name : dohRespHeaderAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Resp hdr alloc failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.309

Field Name : dohRespSetupFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Response setup failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.308

Field Name : dohDnsQueryTypeOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Query type Others
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.307

Field Name : dohDnsQueryTypeSoa
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Query type SOA
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.306

Field Name : dohDnsQueryTypeMx
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Query type MX
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.305

Field Name : dohDnsQueryTypeSrv

Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Query type SRV
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.304

Field Name : dohDnsQueryTypeAny
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Query type ANY
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.303

Field Name : dohDnsQueryTypeCname
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Query type CNAME
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.302

Field Name : dohDnsQueryTypeNs
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Query type NS
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.301

Field Name : dohDnsQueryTypeAaaa
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Query type AAAA
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.300

Field Name : dohDnsQueryTypeA
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Query type A
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.299

Field Name : dohQueryTimeOut
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH serv Query timed out
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.298

Field Name : dohUdpSendFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH serv UDP DNS send failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.297

Field Name : dohTcpSendFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH serv TCP DNS send failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.296

Field Name : dohNonDohMethod
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Non DoH HTTP request method rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.295

Field Name : dohPostPayloadExtractFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH POST payload extract failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.294

Field Name : dohPostPayloadNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH POST payload not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.293

Field Name : dohPostContentTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH POST content-type not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.292

Field Name : dohGetBase64DecodeFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH GET base64url decode failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.291

Field Name : dohGetDnsArgFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH GET dns arg not found in uri
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.290

Field Name : dohPathNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH URI Path not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.289

Field Name : dohSnatFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Source NAT failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.288

Field Name : dohReqTcpRetryFail
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH TCP Retry failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.287

Field Name : dohReqTcpRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH TCP Retry
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.286

Field Name : dohReqUdpRetryFail
Field Type : CounterBasedGauge64
Field Status : current

Description : DoH UDP Retry failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.285

Field Name : dohReqUdpRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH UDP Retry
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.284

Field Name : dohMallocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Memory alloc failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.283

Field Name : dohRespSendFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Response Send Failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.282

Field Name : dohReqSendFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Request Send Failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.281

Field Name : dohTcpDnsResp
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH TCP DNS Responses
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.280

Field Name : dohTcpDnsReq
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH TCP DNS Requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.279

Field Name : dohUdpDnsResp
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH UDP DNS Responses
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.278

Field Name : dohUdpDnsReq
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH UDP DNS Requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.277

Field Name : dohTcResp
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH TC Responses
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.276

Field Name : dohResp

Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Responses
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.275

Field Name : dohNonDohReqPost
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH non DoH POST Requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.274

Field Name : dohNonDohReqGet
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH non DoH GET Requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.273

Field Name : dohNonDohReq
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH non DoH Requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.272

Field Name : dohReqPost
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH POST Requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.271

Field Name : dohReqGet
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH GET Requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.270

Field Name : dohReq
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.269

Field Name : reqTimeoutClose
Field Type : CounterBasedGauge64
Field Status : current
Description : Close on Req Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.268

Field Name : reqTimeoutRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : Retry on Req Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.267

Field Name : responseHttp2
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp 2.0
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.266

Field Name : reqHttp2
Field Type : CounterBasedGauge64
Field Status : current
Description : Request 2.0
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.265

Field Name : decompressionAfter
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot data after decompress
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.264

Field Name : decompressionBefore
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot data before decompress
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.263

Field Name : nonHttpBypass
Field Type : CounterBasedGauge64
Field Status : current
Description : Non-HTTP bypass
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.261

Field Name : reqEnterSsli
Field Type : CounterBasedGauge64
Field Status : current
Description : Total HTTP requests enter SSLi
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.260

Field Name : connectReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Total HTTP CONNECT requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.259

Field Name : reqTrack
Field Type : CounterBasedGauge64
Field Status : current
Description : Method TRACK
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.258

Field Name : insertClientPort
Field Type : CounterBasedGauge64
Field Status : current
Description : Insert client Port
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.257

Field Name : reqOver5s
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time greater than equal to 5s
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.256

Field Name : req5s
Field Type : CounterBasedGauge64
Field Status : current

Description : Rsp time less than 5s
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.255

Field Name : req2s
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 2s
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.254

Field Name : req1s
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 1s
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.253

Field Name : req500m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 500m
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.252

Field Name : req200m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 200m
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.251

Field Name : req100m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 100m
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.250

Field Name : req50m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 50m
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.249

Field Name : req20m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 20m
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.248

Field Name : req10m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 10m
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.247

Field Name : req5m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 5m
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.246

Field Name : req2m

Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 2m
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.245

Field Name : req1m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 1m
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.244

Field Name : req500u
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 500u
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.243

Field Name : req200u
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 200u
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.242

Field Name : req100u
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 100u
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.241

Field Name : req50u
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 50u
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.240

Field Name : req20u
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 20u
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.239

Field Name : req10u
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 10u
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.238

Field Name : chunkBad
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Chunk
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.223

Field Name : pconnConnectingFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : pconn conn failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.222

Field Name : pconnConnected
Field Type : CounterBasedGauge64
Field Status : current
Description : pconn connected
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.221

Field Name : pconnConnecting
Field Type : CounterBasedGauge64
Field Status : current
Description : pconn connecting
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.220

Field Name : chunkSzGt4k
Field Type : CounterBasedGauge64
Field Status : current
Description : Chunk greater than 4K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.219

Field Name : chunkSz4k
Field Type : CounterBasedGauge64
Field Status : current
Description : Chunk less than equal to 4K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.218

Field Name : chunkSz2k
Field Type : CounterBasedGauge64
Field Status : current
Description : Chunk less than equal to 2K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.217

Field Name : chunkSz1k
Field Type : CounterBasedGauge64
Field Status : current
Description : Chunk less than equal to 1K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.216

Field Name : chunkSz512
Field Type : CounterBasedGauge64
Field Status : current
Description : Chunk less than equal to 512
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.215

Field Name : rspSzGt256k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp greater than 256K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.214

Field Name : rspSz256k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp less than equal to 256K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.213

Field Name : rspSz64k
Field Type : CounterBasedGauge64
Field Status : current

Description : Resp less than equal to 64K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.212

Field Name : rspSz32k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp less than equal to 32K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.211

Field Name : rspSz16k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp less than equal to 16K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.210

Field Name : rspSz8k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp less than equal to 8K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.209

Field Name : rspSz4k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp less than equal to 4K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.208

Field Name : rspSz2k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp less than equal to 2K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.207

Field Name : rspSz1k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp less than equal to 1K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.206

Field Name : reqSzGt256k
Field Type : CounterBasedGauge64
Field Status : current
Description : Req greater than 256K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.205

Field Name : reqSz256k
Field Type : CounterBasedGauge64
Field Status : current
Description : Req less than equal to 256K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.204

Field Name : reqSz64k
Field Type : CounterBasedGauge64
Field Status : current
Description : Req less than equal to 64K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.203

Field Name : reqSz32k

Field Type : CounterBasedGauge64
Field Status : current
Description : Req less than equal to 32K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.202

Field Name : reqSz16k
Field Type : CounterBasedGauge64
Field Status : current
Description : Req less than equal to 16K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.201

Field Name : reqSz8k
Field Type : CounterBasedGauge64
Field Status : current
Description : Req less than equal to 8K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.200

Field Name : reqSz4k
Field Type : CounterBasedGauge64
Field Status : current
Description : Req less than equal to 4K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.199

Field Name : reqSz2k
Field Type : CounterBasedGauge64
Field Status : current
Description : Req less than equal to 2K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.198

Field Name : reqSz1k
Field Type : CounterBasedGauge64
Field Status : current
Description : Req less than equal to 1K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.197

Field Name : reqHttp10Keepalive
Field Type : CounterBasedGauge64
Field Status : current
Description : 1.0 Keepalive
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.196

Field Name : slbHttpProxyCloseOnDdos
Field Type : CounterBasedGauge64
Field Status : current
Description : Close on DDoS
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.195

Field Name : cacheRsp
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP req (cache succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.194

Field Name : compressRatioTooHigh
Field Type : CounterBasedGauge64
Field Status : current
Description : Compress ratio too high
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.193

Field Name : compressRespNoClOrCe
Field Type : CounterBasedGauge64
Field Status : current
Description : Compress resp no CL/CE
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.192

Field Name : compressRespLtMin
Field Type : CounterBasedGauge64
Field Status : current
Description : Compress resp less than min
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.191

Field Name : compressNoContentType
Field Type : CounterBasedGauge64
Field Status : current
Description : Compress no cont type
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.190

Field Name : compressContentTypeExcluded
Field Type : CounterBasedGauge64
Field Status : current
Description : Compress cont type excl
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.189

Field Name : compressRespAlreadyCompressed
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp already compressed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.188

Field Name : compressDelAcceptEnc
Field Type : CounterBasedGauge64
Field Status : current
Description : Compress del accept enc
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.187

Field Name : compressRsp
Field Type : CounterBasedGauge64
Field Status : current
Description : Compress req
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.186

Field Name : reqChunk
Field Type : CounterBasedGauge64
Field Status : current
Description : Req chunk encoding
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.185

Field Name : rspChunk
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp chunk encoding
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.184

Field Name : rspContentLen
Field Type : CounterBasedGauge64
Field Status : current

Description : Resp content len
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.183

Field Name : reqContentLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Req content len
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.182

Field Name : reqUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : Method UNKNOWN
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.181

Field Name : reqDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : Method DELETE
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.180

Field Name : reqConnect
Field Type : CounterBasedGauge64
Field Status : current
Description : Method CONNECT
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.179

Field Name : reqOptions
Field Type : CounterBasedGauge64
Field Status : current
Description : Method OPTIONS
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.178

Field Name : reqTrace
Field Type : CounterBasedGauge64
Field Status : current
Description : Method TRACE
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.177

Field Name : reqPost
Field Type : CounterBasedGauge64
Field Status : current
Description : Method POST
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.176

Field Name : reqPut
Field Type : CounterBasedGauge64
Field Status : current
Description : Method PUT
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.175

Field Name : reqHead
Field Type : CounterBasedGauge64
Field Status : current
Description : Method HEAD
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.174

Field Name : reqGet

Field Type : CounterBasedGauge64
Field Status : current
Description : Method GET
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.173

Field Name : responseHttp11
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp 1.1
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.172

Field Name : responseHttp10
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp 1.0
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.171

Field Name : reqHttp11
Field Type : CounterBasedGauge64
Field Status : current
Description : Request 1.1
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.170

Field Name : reqHttp10
Field Type : CounterBasedGauge64
Field Status : current
Description : Request 1.0
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.169

Field Name : responseUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code unknown
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.168

Field Name : response6xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 6XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.167

Field Name : response510
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 510
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.166

Field Name : response509
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 509
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.165

Field Name : response508
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 508
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.164

Field Name : response507
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 507
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.163

Field Name : response506
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 506
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.162

Field Name : response505
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 505
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.161

Field Name : response504
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 504
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.160

Field Name : response503
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 503
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.159

Field Name : response502
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 502
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.158

Field Name : response501
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 501
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.157

Field Name : response500
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 500
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.156

Field Name : response5xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 5XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.155

Field Name : response450
Field Type : CounterBasedGauge64
Field Status : current

Description : Status code 450
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.154

Field Name : response449
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 449
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.153

Field Name : response426
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 426
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.152

Field Name : response425
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 425
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.151

Field Name : response424
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 424
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.150

Field Name : response423
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 423
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.149

Field Name : response422
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 422
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.148

Field Name : response418
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 418
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.147

Field Name : response417
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 417
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.146

Field Name : response416
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 416
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.145

Field Name : response415

Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 415
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.144

Field Name : response414
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 414
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.143

Field Name : response413
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 413
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.142

Field Name : response412
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 412
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.141

Field Name : response411
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 411
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.140

Field Name : response410
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 410
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.139

Field Name : response409
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 409
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.138

Field Name : response408
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 408
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.137

Field Name : response407
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 407
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.136

Field Name : response406
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 406
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.135

Field Name : response405
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 405
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.134

Field Name : response404
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 404
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.133

Field Name : response403
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 403
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.132

Field Name : response402
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 402
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.131

Field Name : response401
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 401
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.130

Field Name : response400
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 400
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.129

Field Name : response4xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 4XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.128

Field Name : response307
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 307
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.127

Field Name : response306
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 306
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.126

Field Name : response305
Field Type : CounterBasedGauge64
Field Status : current

Description : Status code 305
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.125

Field Name : response304
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 304
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.124

Field Name : response303
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 303
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.123

Field Name : response302
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 302
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.122

Field Name : response301
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 301
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.121

Field Name : response300
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 300
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.120

Field Name : response3xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 3XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.119

Field Name : response207
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 207
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.118

Field Name : response206
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 206
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.117

Field Name : response205
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 205
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.116

Field Name : response204

Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 204
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.115

Field Name : response203
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 203
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.114

Field Name : response202
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 202
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.113

Field Name : response201
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 201
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.112

Field Name : response200
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 200
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.111

Field Name : response2xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 2XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.110

Field Name : response102
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 102
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.109

Field Name : response101
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 101
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.108

Field Name : response100
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 100
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.107

Field Name : response1xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 1XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.106

Field Name : compressionAfter
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot data after compress
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.104

Field Name : compressionBefore
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot data before compress
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.102

Field Name : serverReselFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Server re-select failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.101

Field Name : staleSess
Field Type : CounterBasedGauge64
Field Status : current
Description : Stale sess
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.100

Field Name : pktsRetransPush
Field Type : CounterBasedGauge64
Field Status : current
Description : retrans PSH
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.99

Field Name : pktsRetransRst
Field Type : CounterBasedGauge64
Field Status : current
Description : retrans RST
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.98

Field Name : pktsRetransFin
Field Type : CounterBasedGauge64
Field Status : current
Description : retrans FIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.97

Field Name : pktsRetransAckFinwait
Field Type : CounterBasedGauge64
Field Status : current
Description : retrans ACK FWAIT
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.96

Field Name : pktsRetrans
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets retrans
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.95

Field Name : pktsOfo
Field Type : CounterBasedGauge64
Field Status : current

Description : Packets ofo
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.94

Field Name : connectingAck
Field Type : CounterBasedGauge64
Field Status : current
Description : Connecting ACK
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.93

Field Name : connectingRstOfo
Field Type : CounterBasedGauge64
Field Status : current
Description : Connecting RST ofo
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.92

Field Name : connectingRstRetrans
Field Type : CounterBasedGauge64
Field Status : current
Description : Connecting RST retran
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.91

Field Name : connectingRst
Field Type : CounterBasedGauge64
Field Status : current
Description : Connecting RST
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.90

Field Name : connectingFinOfo
Field Type : CounterBasedGauge64
Field Status : current
Description : Connecting FIN ofo
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.89

Field Name : connectingFinRetrans
Field Type : CounterBasedGauge64
Field Status : current
Description : Connecting FIN retran
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.88

Field Name : connectingFin
Field Type : CounterBasedGauge64
Field Status : current
Description : Connecting FIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.87

Field Name : clientReqUnexpFlag
Field Type : CounterBasedGauge64
Field Status : current
Description : Client req unexp flags
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.86

Field Name : asmSetcookieHeaderFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Asm set-cookie hdr fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.85

Field Name : asmSetcookieFail

Field Type : CounterBasedGauge64
Field Status : current
Description : Assemble set-cookie fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.84

Field Name : asmCookieHeaderFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Asm cookie header fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.83

Field Name : asmCookieFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Assemble cookie fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.82

Field Name : parseSetcookieFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Parse set-cookie fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.81

Field Name : parseCookieFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Parse cookie fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.80

Field Name : hugeCookieHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : Huge cookie headers
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.79

Field Name : hugeCookie
Field Type : CounterBasedGauge64
Field Status : current
Description : Huge cookies
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.78

Field Name : largeCookieHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : Large cookie headers
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.77

Field Name : largeCookie
Field Type : CounterBasedGauge64
Field Status : current
Description : Large cookies
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.76

Field Name : negativeRespRemain
Field Type : CounterBasedGauge64
Field Status : current
Description : Negative response remain
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.75

Field Name : negativeReqRemain
Field Type : CounterBasedGauge64
Field Status : current
Description : Negative request remain
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.74

Field Name : insertClientIp
Field Type : CounterBasedGauge64
Field Status : current
Description : Insert client IP
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.73

Field Name : headerDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : Header delete
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.72

Field Name : headerInsert
Field Type : CounterBasedGauge64
Field Status : current
Description : Header insert
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.71

Field Name : wrongRespHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : Wrong response header
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.70

Field Name : headerNameTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Header name too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.69

Field Name : lineTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Line too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.68

Field Name : tooManyHeaders
Field Type : CounterBasedGauge64
Field Status : current
Description : Too many headers
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.67

Field Name : invalidHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid header
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.66

Field Name : serverRstResponse
Field Type : CounterBasedGauge64
Field Status : current

Description : Server RST - response
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.65

Field Name : serverRstConnected
Field Type : CounterBasedGauge64
Field Status : current
Description : Server RST - connected
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.64

Field Name : serverRstConnecting
Field Type : CounterBasedGauge64
Field Status : current
Description : Server RST - connecting
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.63

Field Name : serverRstRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Server RST - request
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.62

Field Name : clientRstResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Client RST - response
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.61

Field Name : clientRstConnected
Field Type : CounterBasedGauge64
Field Status : current
Description : Client RST - connected
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.60

Field Name : clientRstConnecting
Field Type : CounterBasedGauge64
Field Status : current
Description : Client RST - connecting
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.59

Field Name : clientRstRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Client RST - request
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.58

Field Name : aflexLbReselectOk
Field Type : CounterBasedGauge64
Field Status : current
Description : aFleX lb reselect (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.57

Field Name : aflexLbReselect
Field Type : CounterBasedGauge64
Field Status : current
Description : aFleX lb reselect
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.56

Field Name : aflexRetry

Field Type : CounterBasedGauge64
Field Status : current
Description : aFleX http retry
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.55

Field Name : retry503
Field Type : CounterBasedGauge64
Field Status : current
Description : Retry on 503
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.54

Field Name : lbSwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : Normal LB switch. (enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.53

Field Name : hostSwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : Host switching (enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.52

Field Name : urlSwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : URL switching (enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.51

Field Name : httpPolicySwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Policy switching (enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.50

Field Name : aflexSwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : aFleX switching (enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.49

Field Name : cookieSwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie switching (enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.48

Field Name : l4SwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 switching (enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.47

Field Name : lbSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : Normal LB switch. (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.46

Field Name : hostSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : Host switching (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.45

Field Name : urlSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : URL switching (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.44

Field Name : httpPolicySwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Policy switching (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.43

Field Name : aflexSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : aFleX switching (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.42

Field Name : cookieSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie switching (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.41

Field Name : l4SwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 switching (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.40

Field Name : lbSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : Normal LB switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.39

Field Name : hostSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : Host switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.38

Field Name : urlSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : URL switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.37

Field Name : httpPolicySwitching
Field Type : CounterBasedGauge64
Field Status : current

Description : HTTP Policy switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.36

Field Name : aflexSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : aFleX switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.35

Field Name : cookieSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.34

Field Name : l4Switching
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.33

Field Name : slbHttpProxyReqRateOverLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : Request rate over limit
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.32

Field Name : slbHttpProxyReqOverLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : Request over limit
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.31

Field Name : fullProxyFpgaErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Full proxy fpga err
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.30

Field Name : fullProxyPipeline
Field Type : CounterBasedGauge64
Field Status : current
Description : Full proxy pipeline
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.29

Field Name : fullProxyPost
Field Type : CounterBasedGauge64
Field Status : current
Description : Full proxy POST
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.28

Field Name : fullProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Full proxy tot
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.27

Field Name : tcpoutrst

Field Type : CounterBasedGauge64
Field Status : current
Description : Out RSTs
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.26

Field Name : slbHttpProxySnatFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Source NAT failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.25

Field Name : slbHttpProxyNewSvnConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Server conn made
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.24

Field Name : slbHttpProxySvrPremClose
Field Type : CounterBasedGauge64
Field Status : current
Description : Server premature close
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.23

Field Name : slbHttpProxyServerResel
Field Type : CounterBasedGauge64
Field Status : current
Description : Server reselection
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.22

Field Name : slbHttpProxyReqOfo
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets ofo
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.21

Field Name : slbHttpProxyReqRetran
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets retrans
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.20

Field Name : slbHttpProxyFwdreqdataFail
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.19

Field Name : fwdreqFailTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - tuple
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.18

Field Name : fwdreqFailServer
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - server
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.17

Field Name : fwdreqFailPersist
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - persist
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.16

Field Name : fwdreqFailRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - route
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.15

Field Name : fwdreqFailRport
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - rport
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.14

Field Name : fwdreqFailBuff
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - buff
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.13

Field Name : slbHttpProxyFwdreqFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.12

Field Name : slbHttpProxySvrselFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Server selection fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.11

Field Name : slbHttpProxyParsereqFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Parse req fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.10

Field Name : slbHttpProxyNotuple
Field Type : CounterBasedGauge64
Field Status : current
Description : No tuple error
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.9

Field Name : slbHttpProxyServerRst
Field Type : CounterBasedGauge64
Field Status : current
Description : Server RST
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.8

Field Name : slbHttpProxyClientRst
Field Type : CounterBasedGauge64
Field Status : current

Description : Client RST
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.7

Field Name : slbHttpProxyNoProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : No proxy error
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.6

Field Name : slbHttpProxyReqSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP requests(succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.5

Field Name : slbHttpProxyReq
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.4

Field Name : slbHttpProxyTotalProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Proxy Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.3

Field Name : slbHttpProxyCurrProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr Proxy Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.2

Field Name : num
Field Type : CounterBasedGauge64
Field Status : current
Description : Num
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.1

Field Name : cookieInvalid
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid persist cookie
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.53

Field Name : cookiePassThru
Field Type : CounterBasedGauge64
Field Status : current
Description : Persist cookie Pass-thru
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.52

Field Name : cookieNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Persist cookie not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.51

Field Name : cookiePersistFail

Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie persist fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.50

Field Name : cookiePersistOk
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie persist ok
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.49

Field Name : sslSidSessionFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Create SSL SID fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.48

Field Name : sslSidSessionOk
Field Type : CounterBasedGauge64
Field Status : current
Description : Create SSL SID ok
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.47

Field Name : sslSidPersistFail
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL SID persist fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.46

Field Name : sslSidPersistOk
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL SID persist ok
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.45

Field Name : ssslSidNotMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Server SSL SID not match
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.44

Field Name : ssslSidMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Server SSL SID match
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.43

Field Name : ssslSidReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Server SSL SID reset
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.42

Field Name : ssslSidNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Server SSL SID not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.41

Field Name : csslSidNotMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Client SSL SID not match
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.40

Field Name : csslSidMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Client SSL SID match
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.39

Field Name : csslSidNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Client SSL SID not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.38

Field Name : dstIpHashFail
Field Type : CounterBasedGauge64
Field Status : current
Description : DST IP hash persist fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.37

Field Name : dstIpHashSec
Field Type : CounterBasedGauge64
Field Status : current
Description : DST IP hash persist(sec)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.36

Field Name : dstIpHashEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : DST IP hash persist(enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.35

Field Name : dstIpHashPri
Field Type : CounterBasedGauge64
Field Status : current
Description : DST IP hash persist(pri)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.34

Field Name : dstIpNewSessSelFail
Field Type : CounterBasedGauge64
Field Status : current
Description : DST IP new sess fail (s)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.33

Field Name : dstIpNewSessSel
Field Type : CounterBasedGauge64
Field Status : current
Description : DST IP new sess (select)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.32

Field Name : dstIpNewSessCacheFail
Field Type : CounterBasedGauge64
Field Status : current

Description : DST IP new sess fail (c)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.31

Field Name : dstIpNewSessCache
Field Type : CounterBasedGauge64
Field Status : current
Description : DST IP new sess (cache)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.30

Field Name : dstIpFail
Field Type : CounterBasedGauge64
Field Status : current
Description : DST IP persist fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.29

Field Name : dstIpEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : DST IP persist enqueue
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.28

Field Name : dstIp
Field Type : CounterBasedGauge64
Field Status : current
Description : DST IP persist ok
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.27

Field Name : srcIpEnforce
Field Type : CounterBasedGauge64
Field Status : current
Description : Enforce higher priority
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.26

Field Name : srcIpHashFail
Field Type : CounterBasedGauge64
Field Status : current
Description : SRC IP hash persist fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.25

Field Name : srcIpHashSec
Field Type : CounterBasedGauge64
Field Status : current
Description : SRC IP hash persist(sec)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.24

Field Name : srcIpHashEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : SRC IP hash persist(enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.23

Field Name : srcIpHashPri
Field Type : CounterBasedGauge64
Field Status : current
Description : SRC IP hash persist(pri)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.22

Field Name : srcIpNewSessSelFail

Field Type : CounterBasedGauge64
Field Status : current
Description : SRC IP new sess fail (s)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.21

Field Name : srcIpNewSessSel
Field Type : CounterBasedGauge64
Field Status : current
Description : SRC IP new sess (select)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.20

Field Name : srcIpNewSessCacheFail
Field Type : CounterBasedGauge64
Field Status : current
Description : SRC IP new sess fail (c)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.19

Field Name : srcIpNewSessCache
Field Type : CounterBasedGauge64
Field Status : current
Description : SRC IP new sess (cache)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.18

Field Name : srcIpFail
Field Type : CounterBasedGauge64
Field Status : current
Description : SRC IP persist fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.17

Field Name : srcIpEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : SRC IP persist enqueue
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.16

Field Name : srcIp
Field Type : CounterBasedGauge64
Field Status : current
Description : SRC IP persist ok
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.15

Field Name : headerHashFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Header hash persist fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.14

Field Name : headerHashSec
Field Type : CounterBasedGauge64
Field Status : current
Description : Header hash persist(sec)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.13

Field Name : headerHashEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : Header hash persist(enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.12

Field Name : headerHashPri
Field Type : CounterBasedGauge64
Field Status : current
Description : Header hash persist(pri)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.11

Field Name : urlHashFail
Field Type : CounterBasedGauge64
Field Status : current
Description : URL hash persist fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.10

Field Name : urlHashSec
Field Type : CounterBasedGauge64
Field Status : current
Description : URL hash persist (sec)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.9

Field Name : urlHashEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : URL hash persist (enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.8

Field Name : urlHashPri
Field Type : CounterBasedGauge64
Field Status : current
Description : URL hash persist (pri)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.7

Field Name : hashTblRstAdddel
Field Type : CounterBasedGauge64
Field Status : current
Description : Hash tbl reset (add/del)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.6

Field Name : hashTblRstUpdown
Field Type : CounterBasedGauge64
Field Status : current
Description : Hash tbl reset (up/down)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.5

Field Name : hashTblFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Hash tbl free
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.4

Field Name : hashTblCreateFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Hash tbl create fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.3

Field Name : hashTblCreateOk
Field Type : CounterBasedGauge64
Field Status : current

Description : Hash tbl create ok
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.2

Field Name : hashTblTrylockFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Hash tbl lock fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.1

Field Name : algPortHelperNatFree
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT helper NAT free
OID : 1.3.6.1.4.1.22610.2.4.10.108.44.1.8

Field Name : algPasvHelperFreedUnused
Field Type : CounterBasedGauge64
Field Status : current
Description : PASV helper freed unused
OID : 1.3.6.1.4.1.22610.2.4.10.108.44.1.7

Field Name : algPortHelperFreedUnused
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT helper freed unused
OID : 1.3.6.1.4.1.22610.2.4.10.108.44.1.6

Field Name : algPasvHelperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total PASV helper sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.44.1.5

Field Name : algPortHelperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total PORT helper sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.44.1.4

Field Name : algPktsXmittedNum
Field Type : CounterBasedGauge64
Field Status : current
Description : ALG packets rexmitted
OID : 1.3.6.1.4.1.22610.2.4.10.108.44.1.3

Field Name : algPktsNum
Field Type : CounterBasedGauge64
Field Status : current
Description : Total ALG packets
OID : 1.3.6.1.4.1.22610.2.4.10.108.44.1.2

Field Name : sessionsNum
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Control Sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.44.1.1

Field Name : databaseError

Field Type : CounterBasedGauge64
Field Status : current
Description : Database error
OID : 1.3.6.1.4.1.22610.2.4.10.108.109.1.5

Field Name : databaseBusy
Field Type : CounterBasedGauge64
Field Status : current
Description : Database busy
OID : 1.3.6.1.4.1.22610.2.4.10.108.109.1.4

Field Name : entryDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Total deleted cache entry
OID : 1.3.6.1.4.1.22610.2.4.10.108.109.1.3

Field Name : entrySaved
Field Type : CounterBasedGauge64
Field Status : current
Description : Total saved cache entry
OID : 1.3.6.1.4.1.22610.2.4.10.108.109.1.2

Field Name : totalEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Total persistent cache entry
OID : 1.3.6.1.4.1.22610.2.4.10.108.109.1.1

Field Name : hitRatePerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : Cache hit rate per second
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.25

Field Name : qps
Field Type : CounterBasedGauge64
Field Status : current
Description : Cache Queries-per-second
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.24

Field Name : truncatedR
Field Type : CounterBasedGauge64
Field Status : current
Description : Response with Truncation bit set
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.23

Field Name : resolverQueueFull
Field Type : CounterBasedGauge64
Field Status : current
Description : Resolver task queue full
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.22

Field Name : currentDataAllocate
Field Type : CounterBasedGauge64
Field Status : current
Description : Current data allocate
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.21

Field Name : currentAllocate
Field Type : CounterBasedGauge64
Field Status : current
Description : Current allocate
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.20

Field Name : dnsTotalFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total freed
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.19

Field Name : totalAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Total allocated
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.18

Field Name : totalLog
Field Type : CounterBasedGauge64
Field Status : current
Description : Total stats log sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.17

Field Name : ageoutWeight
Field Type : CounterBasedGauge64
Field Status : current
Description : Total aged for lower weight
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.16

Field Name : badAnswer
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Answer
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.15

Field Name : ageout
Field Type : CounterBasedGauge64
Field Status : current
Description : Total aged out
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.14

Field Name : ttlR
Field Type : CounterBasedGauge64
Field Status : current
Description : Response with short TTL
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.13

Field Name : answerR
Field Type : CounterBasedGauge64
Field Status : current
Description : Response with multiple answers
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.12

Field Name : multipleR
Field Type : CounterBasedGauge64
Field Status : current

Description : Response with multiple questions
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.11

Field Name : encodeR
Field Type : CounterBasedGauge64
Field Status : current
Description : Response encoded
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.10

Field Name : oversizeR
Field Type : CounterBasedGauge64
Field Status : current
Description : Response exceed cache size
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.9

Field Name : badR
Field Type : CounterBasedGauge64
Field Status : current
Description : Response not passed
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.8

Field Name : oversizeQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Query exceed cache size
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.7

Field Name : multipleQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Query with multiple questions
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.6

Field Name : encodeQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Query encoded
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.5

Field Name : badQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Query not passed
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.4

Field Name : hit
Field Type : CounterBasedGauge64
Field Status : current
Description : Total cache hit
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.3

Field Name : totalR
Field Type : CounterBasedGauge64
Field Status : current
Description : Total server response
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.2

Field Name : totalQ

Field Type : CounterBasedGauge64
Field Status : current
Description : Total query
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.1

Field Name : slbDnsEdnsEcsInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of ecs inserted
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.36

Field Name : slbDnsEdnsEcsReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of ecs from client received
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.35

Field Name : invalidQLenToUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid query length to conver to UDP
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.34

Field Name : natSlbDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : (NAT)DNS requests drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.33

Field Name : slbDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS requests drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.32

Field Name : rpzActionLocalData
Field Type : CounterBasedGauge64
Field Status : current
Description : RPZ Action Local Data
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.31

Field Name : rpzActionNodata
Field Type : CounterBasedGauge64
Field Status : current
Description : RPZ Action NODATA
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.30

Field Name : rpzActionNxdomain
Field Type : CounterBasedGauge64
Field Status : current
Description : RPZ Action NXDOMAIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.29

Field Name : rpzActionTcpOnly
Field Type : CounterBasedGauge64
Field Status : current
Description : RPZ Action TCP Only
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.28

Field Name : rpzActionPassThru
Field Type : CounterBasedGauge64
Field Status : current
Description : RPZ Action Pass Through
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.27

Field Name : rpzActionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : RPZ Action Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.26

Field Name : slbDnsUdpRetransmitFail
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.25

Field Name : slbDnsUdpRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.24

Field Name : slbDnsEdnsSubnetToServerRemoved
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.23

Field Name : slbDnsPaddingToClientAdded
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.22

Field Name : slbDnsPaddingToServerRemoved
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.21

Field Name : slbDnsUdpConnSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : No. of backend udp conn established
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.20

Field Name : slbDnsUdpConn
Field Type : CounterBasedGauge64
Field Status : current
Description : No. of backend udp connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.19

Field Name : slbDnsServerSslSucc
Field Type : CounterBasedGauge64
Field Status : current

Description : No. of server ssl success
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.18

Field Name : slbDnsClientSslSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : No. of client ssl success
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.17

Field Name : filterTypeAnyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Query ANY Type Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.16

Field Name : filterClassDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Query Class Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.15

Field Name : filterTypeDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Query Type Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.14

Field Name : natXidReused
Field Type : CounterBasedGauge64
Field Status : current
Description : (NAT) No. of requests reusing a transaction id
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.13

Field Name : natNoResource
Field Type : CounterBasedGauge64
Field Status : current
Description : (NAT) No. of resource failures
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.12

Field Name : natRespNoMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : (NAT) No. of requests with no response
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.11

Field Name : natReqRexmit
Field Type : CounterBasedGauge64
Field Status : current
Description : (NAT) No. of request retransmits
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.10

Field Name : natNoResp
Field Type : CounterBasedGauge64
Field Status : current
Description : (NAT) No. of resource failures
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.9

Field Name : natResp

Field Type : CounterBasedGauge64
Field Status : current
Description : (NAT) No. of responses
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.8

Field Name : natReq
Field Type : CounterBasedGauge64
Field Status : current
Description : (NAT) No. of requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.7

Field Name : slbNoResource
Field Type : CounterBasedGauge64
Field Status : current
Description : No. of resource failures
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.6

Field Name : slbRespNoMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : No. of requests and responses with no match
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.5

Field Name : slbReqRexmit
Field Type : CounterBasedGauge64
Field Status : current
Description : No. of requests retransmit
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.4

Field Name : slbNoResp
Field Type : CounterBasedGauge64
Field Status : current
Description : No. of requests with no response
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.3

Field Name : slbResp
Field Type : CounterBasedGauge64
Field Status : current
Description : No. of responses
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.2

Field Name : slbReq
Field Type : CounterBasedGauge64
Field Status : current
Description : No. of requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.1

Field Name : slbGenericProxyDiameterTooBusyOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of DIAMETER_TOO_BUSY out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.75

Field Name : slbGenericProxyDiameterTooBusyIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of DIAMETER_TOO_BUSY in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.74

Field Name : slbGenericProxyDpaIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of DPAs in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.73

Field Name : slbGenericProxyDpaOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of DPAs out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.72

Field Name : slbGenericProxyDprIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of DPRs in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.71

Field Name : slbGenericProxyDprOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of DPRs out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.70

Field Name : slbGenericProxyReplyErrorInfoFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Fail to reply error info to peer
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.69

Field Name : slbGenericProxyReplyUnableToDeliver
Field Type : CounterBasedGauge64
Field Status : current
Description : Reply with unable to deliver error info
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.68

Field Name : slbGenericProxyReplyInvalidAVPValue
Field Type : CounterBasedGauge64
Field Status : current
Description : Reply with invalid AVP error info
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.67

Field Name : slbGenericProxyConnClosedByServer
Field Type : CounterBasedGauge64
Field Status : current
Description : Server initiates TCP close/reset
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.66

Field Name : slbGenericProxyConnClosedByClient
Field Type : CounterBasedGauge64
Field Status : current
Description : Client initiates TCP close/reset
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.65

Field Name : slbGenericProxyReselectRevTuple
Field Type : CounterBasedGauge64
Field Status : current

Description : Original server tuple does not exist so reselect another one
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.64

Field Name : slbGenericProxyReselectFwdTupleOtherCPU
Field Type : CounterBasedGauge64
Field Status : current
Description : Original client tuple does not exist so reselect another one on other CPUs
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.63

Field Name : slbGenericProxyReselectFwdTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : Original client tuple does not exist so reselect another one
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.62

Field Name : slbGenericProxyInvalidAVP
Field Type : CounterBasedGauge64
Field Status : current
Description : AVP value contains illegal chars
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.61

Field Name : slbGenericProxyCloseConnWhenVportDown
Field Type : CounterBasedGauge64
Field Status : current
Description : Close client conn when virtual port is down
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.60

Field Name : slbGenericProxyClientSelectFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Fail to select client
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.59

Field Name : slbGenericProxyUpdateLatestServer
Field Type : CounterBasedGauge64
Field Status : current
Description : Update to the latest server that used a session id
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.58

Field Name : slbGenericProxyForwardUnknownSessionID
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward server side message with unknown session id
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.57

Field Name : slbGenericProxyTermCCAT
Field Type : CounterBasedGauge64
Field Status : current
Description : Diameter terminate on cca_t
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.56

Field Name : slbGenericProxyCcaT
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of CCAs terminate
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.55

Field Name : slbGenericProxyCcrT

Field Type : CounterBasedGauge64
Field Status : current
Description : Number of CCRs terminate
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.54

Field Name : slbGenericProxyCcrU
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of CCRs update
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.53

Field Name : slbGenericProxyCcrI
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of CCRs initial
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.52

Field Name : slbGenericProxyCcaIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of CCAs in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.51

Field Name : slbGenericProxyCcaOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of CCAs out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.50

Field Name : slbGenericProxyCcrIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of CCRs in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.49

Field Name : slbGenericProxyCcrOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of CCRs out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.48

Field Name : slbGenericProxyReplyUnknownSessionID
Field Type : CounterBasedGauge64
Field Status : current
Description : Reply with unknown session ID error info
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.47

Field Name : slbGenericProxyDiaRetryFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Diameter retry client request fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.46

Field Name : slbGenericProxyDiaRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : Diameter retry client request
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.45

Field Name : slbGenericProxyDiaDcmsgErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Diameter cross cpu error
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.44

Field Name : slbGenericProxyDiaDcmsgRevOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Diameter cross cpu rev out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.43

Field Name : slbGenericProxyDiaDcmsgRevIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Diameter cross cpu rev in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.42

Field Name : slbGenericProxyDiaDcmsgFwdOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Diameter cross cpu fwd out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.41

Field Name : slbGenericProxyDiaDcmsgFwdIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Diameter cross cpu fwd in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.40

Field Name : slbGenericProxyDiaNoRev
Field Type : CounterBasedGauge64
Field Status : current
Description : Diameter no rev tuple matched
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.39

Field Name : slbGenericProxyDiaNoFwd
Field Type : CounterBasedGauge64
Field Status : current
Description : Diameter no fwd tuple matched
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.38

Field Name : slbGenericProxyDiaNoID
Field Type : CounterBasedGauge64
Field Status : current
Description : Diameter no session id avp
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.37

Field Name : slbGenericProxyDiaUnkCmd
Field Type : CounterBasedGauge64
Field Status : current
Description : Diameter unkown cmd code
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.36

Field Name : slbGenericProxyDiaRevId
Field Type : CounterBasedGauge64
Field Status : current

Description : Diameter mismatch rev session id
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.35

Field Name : slbGenericProxyDiaFwdId
Field Type : CounterBasedGauge64
Field Status : current
Description : Diameter mismatch fwd session id
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.34

Field Name : totalHttpReqEnterGen
Field Type : CounterBasedGauge64
Field Status : current
Description : Total number of HTTP requests enter generic proxy
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.33

Field Name : slbGenericProxyOtherIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of other messages in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.32

Field Name : slbGenericProxyOtherOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of other messages out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.31

Field Name : slbGenericProxyAsaIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of ASAs in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.30

Field Name : slbGenericProxyAsaOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of ASAs out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.29

Field Name : slbGenericProxyAsrIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of ASRs in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.28

Field Name : slbGenericProxyAsrOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of ASRs out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.27

Field Name : slbGenericProxyStaIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of STAs in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.26

Field Name : slbGenericProxyStaOut

Field Type : CounterBasedGauge64
Field Status : current
Description : Number of STAs out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.25

Field Name : slbGenericProxyStrIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of STRs in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.24

Field Name : slbGenericProxyStrOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of STRs out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.23

Field Name : slbGenericProxyDwaIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of DWAs in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.22

Field Name : slbGenericProxyDwaOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of DWAs out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.21

Field Name : slbGenericProxyDwrIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of DWRs in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.20

Field Name : slbGenericProxyDwrOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of DWRs out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.19

Field Name : slbGenericProxyCerIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of CERs in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.18

Field Name : slbGenericProxyCerOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of CERs out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.17

Field Name : slbGenericProxyCeaIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of CEAs in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.16

Field Name : slbGenericProxyCeaOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of CEAs out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.15

Field Name : slbGenericProxyAcaIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of ACAs in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.14

Field Name : slbGenericProxyAcaOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of ACAs out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.13

Field Name : slbGenericProxyAcrIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of ACRs in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.12

Field Name : slbGenericProxyAcrOUt
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of ACRs out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.11

Field Name : slbGenericProxyUserSession
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of user sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.10

Field Name : slbGenericProxyNoSess
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of no sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.9

Field Name : slbGenericProxyServerFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of server failures
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.8

Field Name : slbGenericProxyClientFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of client failures
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.7

Field Name : slbGenericProxySnatFail
Field Type : CounterBasedGauge64
Field Status : current

Description : Number of snat failures
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.6

Field Name : slbGenericProxyNoRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of no routes
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.5

Field Name : slbGenericProxySvrselFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of server selection failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.4

Field Name : slbGenericProxyTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.3

Field Name : slbGenericProxyCurr
Field Type : CounterBasedGauge64
Field Status : current
Description : Current
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.2

Field Name : slbGenericProxyNum
Field Type : CounterBasedGauge64
Field Status : current
Description : Number
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.1

Field Name : logMsgSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Log messages sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.40.1.9

Field Name : lockoutDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Lockout drops
OID : 1.3.6.1.4.1.22610.2.4.10.108.40.1.8

Field Name : thresholdExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Threshold exceeded count
OID : 1.3.6.1.4.1.22610.2.4.10.108.40.1.7

Field Name : permitted
Field Type : CounterBasedGauge64
Field Status : current
Description : Honor threshold count
OID : 1.3.6.1.4.1.22610.2.4.10.108.40.1.6

Field Name : called

Field Type : CounterBasedGauge64
Field Status : current
Description : Threshold check count
OID : 1.3.6.1.4.1.22610.2.4.10.108.40.1.5

Field Name : tooManySessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Too many sessions consumed
OID : 1.3.6.1.4.1.22610.2.4.10.108.40.1.4

Field Name : outOfSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.40.1.3

Field Name : sessionsFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.108.40.1.2

Field Name : sessionsAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Sessions allocated
OID : 1.3.6.1.4.1.22610.2.4.10.108.40.1.1

Field Name : authFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Authentication Failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.39.1.13

Field Name : authSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Authentication Success
OID : 1.3.6.1.4.1.22610.2.4.10.108.39.1.12

Field Name : commands
Field Type : CounterBasedGauge64
Field Status : current
Description : DB commands reply
OID : 1.3.6.1.4.1.22610.2.4.10.108.39.1.11

Field Name : queries
Field Type : CounterBasedGauge64
Field Status : current
Description : DB Queries
OID : 1.3.6.1.4.1.22610.2.4.10.108.39.1.10

Field Name : sessionErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Session err
OID : 1.3.6.1.4.1.22610.2.4.10.108.39.1.9

Field Name : serverFin
Field Type : CounterBasedGauge64
Field Status : current
Description : Server FIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.39.1.8

Field Name : clientFin
Field Type : CounterBasedGauge64
Field Status : current
Description : Client FIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.39.1.7

Field Name : totalFeEnc
Field Type : CounterBasedGauge64
Field Status : current
Description : Total FE Encryption Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.39.1.6

Field Name : currFeEnc
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr FE Encryption Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.39.1.5

Field Name : totalBeEnc
Field Type : CounterBasedGauge64
Field Status : current
Description : Total BE Encryption Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.39.1.4

Field Name : currBeEnc
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr BE Encryption Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.39.1.3

Field Name : totalProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Proxy Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.39.1.2

Field Name : currProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr Proxy Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.39.1.1

Field Name : slbMysqlCommands
Field Type : CounterBasedGauge64
Field Status : current
Description : DB commands reply
OID : 1.3.6.1.4.1.22610.2.4.10.108.38.1.11

Field Name : slbMysqlQueries
Field Type : CounterBasedGauge64
Field Status : current

Description : DB Queries
OID : 1.3.6.1.4.1.22610.2.4.10.108.38.1.10

Field Name : slbMysqlSessionErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Session err
OID : 1.3.6.1.4.1.22610.2.4.10.108.38.1.9

Field Name : slbMysqlServerFin
Field Type : CounterBasedGauge64
Field Status : current
Description : Server FIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.38.1.8

Field Name : slbMysqlClientFin
Field Type : CounterBasedGauge64
Field Status : current
Description : Client FIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.38.1.7

Field Name : slbMysqlTotalFeEnc
Field Type : CounterBasedGauge64
Field Status : current
Description : Total FE Encryption Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.38.1.6

Field Name : slbMysqlCurrFeEnc
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr FE Encryption Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.38.1.5

Field Name : slbMysqlTotalBeEnc
Field Type : CounterBasedGauge64
Field Status : current
Description : Total BE Encryption Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.38.1.4

Field Name : slbMysqlCurrBeEnc
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr BE Encryption Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.38.1.3

Field Name : slbMysqlTotalProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Proxy Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.38.1.2

Field Name : slbMysqlCurrProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr Proxy Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.38.1.1

Field Name : currPconn

Field Type : CounterBasedGauge64
Field Status : current
Description : Persistent connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.37.1.7

Field Name : slbPassthroughTotalRevPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse packets
OID : 1.3.6.1.4.1.22610.2.4.10.108.37.1.6

Field Name : slbPassthroughTotalRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse bytes
OID : 1.3.6.1.4.1.22610.2.4.10.108.37.1.5

Field Name : slbPassthroughTotalFwdPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward packets
OID : 1.3.6.1.4.1.22610.2.4.10.108.37.1.4

Field Name : slbPassthroughTotalFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward bytes
OID : 1.3.6.1.4.1.22610.2.4.10.108.37.1.3

Field Name : slbPassthroughTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.37.1.2

Field Name : slbPassthroughCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Current connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.37.1.1

Field Name : totalTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Total health-check timeout
OID : 1.3.6.1.4.1.22610.2.4.10.108.36.1.3

Field Name : totalRetrySent
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Total health-check retry sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.36.1.2

Field Name : totalSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Total health-check sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.36.1.1

Field Name : timeoutWithPacket
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of pin timeouts while socket has packets
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.30

Field Name : sslPostHandshakePacket
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of ssl post handshake packets before client sends request
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.29

Field Name : configHealthRate
Field Type : CounterBasedGauge64
Field Status : current
Description : Config health rate
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.28

Field Name : runningTime
Field Type : CounterBasedGauge64
Field Status : current
Description : Running time
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.27

Field Name : statusOther
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of other status
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.26

Field Name : statusUnkn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of status unknowns
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.25

Field Name : statusDown
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of status downs
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.24

Field Name : statusUp
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of status ups
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.23

Field Name : totalNumber
Field Type : CounterBasedGauge64
Field Status : current
Description : Total number
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.22

Field Name : extHealthRateVal
Field Type : CounterBasedGauge64
Field Status : current

Description : External health rate value
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.21

Field Name : extHealthRate
Field Type : CounterBasedGauge64
Field Status : current
Description : External health rate
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.20

Field Name : currHealthRate
Field Type : CounterBasedGauge64
Field Status : current
Description : Current health rate
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.19

Field Name : sockCloseWithoutNotify
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of sockets closed without notify
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.18

Field Name : sockCloseBefore17
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of sockets closed before l7
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.17

Field Name : connImdtSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of connection immediete success
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.16

Field Name : unexpectedError
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of unexpected errors
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.15

Field Name : timeout
Field Type : CounterBasedGauge64
Field Status : current
Description : Timouet value
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.14

Field Name : retryTimes
Field Type : CounterBasedGauge64
Field Status : current
Description : Retry times
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.13

Field Name : recvPacketFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of failed packet receives
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.12

Field Name : recvPacket

Field Type : CounterBasedGauge64
Field Status : current
Description : Number of received packets
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.11

Field Name : sendPacketFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of packet send failures
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.10

Field Name : sendPacket
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of packets sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.9

Field Name : connectFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of failed connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.8

Field Name : closeSocket
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of closed sockets
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.7

Field Name : openSocketFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of failed open sockets
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.6

Field Name : openSocket
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of open sockets
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.5

Field Name : avgJiffie
Field Type : CounterBasedGauge64
Field Status : current
Description : Average number of jiffies
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.4

Field Name : minJiffie
Field Type : CounterBasedGauge64
Field Status : current
Description : Minimum number of jiffies
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.3

Field Name : maxJiffie
Field Type : CounterBasedGauge64
Field Status : current
Description : Maximum number of jiffies
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.2

Field Name : numBurst
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of burst
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.1

Field Name : drop
Field Type : CounterBasedGauge64
Field Status : current
Description : Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.108.104.1.15

Field Name : cache
Field Type : CounterBasedGauge64
Field Status : current
Description : Cache
OID : 1.3.6.1.4.1.22610.2.4.10.108.104.1.14

Field Name : adjust
Field Type : CounterBasedGauge64
Field Status : current
Description : Translated
OID : 1.3.6.1.4.1.22610.2.4.10.108.104.1.13

Field Name : respLocal
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Local
OID : 1.3.6.1.4.1.22610.2.4.10.108.104.1.12

Field Name : respEmpty
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Empty
OID : 1.3.6.1.4.1.22610.2.4.10.108.104.1.11

Field Name : respErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Error
OID : 1.3.6.1.4.1.22610.2.4.10.108.104.1.10

Field Name : respChg
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Changed
OID : 1.3.6.1.4.1.22610.2.4.10.108.104.1.9

Field Name : respBadQr
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Bad Query
OID : 1.3.6.1.4.1.22610.2.4.10.108.104.1.8

Field Name : respBadPkt
Field Type : CounterBasedGauge64
Field Status : current

Description : Response Bad Packet
OID : 1.3.6.1.4.1.22610.2.4.10.108.104.1.7

Field Name : resp
Field Type : CounterBasedGauge64
Field Status : current
Description : Response
OID : 1.3.6.1.4.1.22610.2.4.10.108.104.1.6

Field Name : queryPassive
Field Type : CounterBasedGauge64
Field Status : current
Description : Query Passive
OID : 1.3.6.1.4.1.22610.2.4.10.108.104.1.5

Field Name : queryParallel
Field Type : CounterBasedGauge64
Field Status : current
Description : Query Parallel
OID : 1.3.6.1.4.1.22610.2.4.10.108.104.1.4

Field Name : queryChg
Field Type : CounterBasedGauge64
Field Status : current
Description : Query Changed
OID : 1.3.6.1.4.1.22610.2.4.10.108.104.1.3

Field Name : queryBadPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : Query Bad Packet
OID : 1.3.6.1.4.1.22610.2.4.10.108.104.1.2

Field Name : query
Field Type : CounterBasedGauge64
Field Status : current
Description : Query
OID : 1.3.6.1.4.1.22610.2.4.10.108.104.1.1

Field Name : maxOutstandingSubmitCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Max queued submit count
OID : 1.3.6.1.4.1.22610.2.4.10.108.34.1.8

Field Name : maxOutstandingRequestCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Max queued request count
OID : 1.3.6.1.4.1.22610.2.4.10.108.34.1.7

Field Name : ringFullCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Compression queue full
OID : 1.3.6.1.4.1.22610.2.4.10.108.34.1.6

Field Name : failureCode

Field Type : CounterBasedGauge64
Field Status : current
Description : Last failure code
OID : 1.3.6.1.4.1.22610.2.4.10.108.34.1.5

Field Name : failureCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Total failure count
OID : 1.3.6.1.4.1.22610.2.4.10.108.34.1.4

Field Name : responseCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Total response count
OID : 1.3.6.1.4.1.22610.2.4.10.108.34.1.3

Field Name : submitCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Total submit count
OID : 1.3.6.1.4.1.22610.2.4.10.108.34.1.2

Field Name : requestCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Total request count
OID : 1.3.6.1.4.1.22610.2.4.10.108.34.1.1

Field Name : processErrorWhenMessageSwitch
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.161

Field Name : smpCallIdRtpSessionNotMatch
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.160

Field Name : smpCallIdRtpSessionMatch
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.159

Field Name : updateSmpCallIdRtp
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.158

Field Name : saveSmpCallIdRtp
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.157

Field Name : haFailCloneSipSession
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.156

Field Name : haFailAllocCallId
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.155

Field Name : haFailAllocSipSession
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.154

Field Name : haInvalidPkt
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.153

Field Name : haUpdateSipSessionOk
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.152

Field Name : haInsertSipSessionOk
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.151

Field Name : haRecvSipSession
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.150

Field Name : haFailGetMsgHeader
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.149

Field Name : haSendSipSessionOk
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.148

Field Name : haSendSipSession
Field Type : CounterBasedGauge64
Field Status : current

Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.147

Field Name : response6XX
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.146

Field Name : response5XX
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.145

Field Name : response4XX
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.144

Field Name : response3XX
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.143

Field Name : response2XX
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.142

Field Name : response1XX
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.141

Field Name : responseUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.140

Field Name : requestUpdate
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.139

Field Name : requestMessage
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.138

Field Name : requestRefer

Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.137

Field Name : requestInfo
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.136

Field Name : requestPublish
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.135

Field Name : requestNotify
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.134

Field Name : requestSubscribe
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.133

Field Name : requestPrack
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.132

Field Name : requestOptions
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.131

Field Name : requestBye
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.130

Field Name : requestCancel
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.129

Field Name : requestAck
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.128

Field Name : requestInvite
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.127

Field Name : requestRegister
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.126

Field Name : msgTransBody
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.125

Field Name : msgTransStartHeaders
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.124

Field Name : msgTransStartLine
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.123

Field Name : msgTranslationFail
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.122

Field Name : msgTranslation
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.121

Field Name : saveCallIdOk
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.120

Field Name : saveCallId
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.119

Field Name : saveUriOk
Field Type : CounterBasedGauge64
Field Status : current

Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.118

Field Name : saveUri
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.117

Field Name : concatenateMsg
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.116

Field Name : clientRequestOk
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.115

Field Name : clientRequest
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.114

Field Name : axHealthCheckReceived
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.113

Field Name : serverKeepaliveSend
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.112

Field Name : clientKeepaliveSend
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.111

Field Name : serverKeepaliveReceived
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.110

Field Name : clientKeepaliveReceived
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.109

Field Name : failSplitFragment

Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.108

Field Name : sizeTooLarge
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.107

Field Name : wrongIpVersion
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.106

Field Name : assembleFragFailed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.105

Field Name : aclDenied
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.104

Field Name : clientSelectFailed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.103

Field Name : uriSelectClient
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.102

Field Name : callIdSelectClient
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.101

Field Name : xForwardedForClient
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.100

Field Name : selectClientConn
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.99

Field Name : selectServerConnFailed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.98

Field Name : selectServerConnByRevTuple
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.97

Field Name : selectServerConnByUri
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.96

Field Name : selectServerConnByCallid
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.95

Field Name : selectServerConn
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.94

Field Name : failInsertHeader
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.93

Field Name : failInsertUriSession
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.92

Field Name : failInsertCallidSession
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.91

Field Name : deprecatedMsg
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.90

Field Name : noSipRequest
Field Type : CounterBasedGauge64
Field Status : current

Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.89

Field Name : identifyDirFailed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.88

Field Name : msgNoCallId
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.87

Field Name : failGetCounter
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.86

Field Name : bodyTooBig
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.85

Field Name : headerNameTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.84

Field Name : invalidHeader
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.83

Field Name : tooManyHeaders
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.82

Field Name : failParseHeaders
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.81

Field Name : requestUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.80

Field Name : responseUnknownVersion

Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.79

Field Name : requestUnknownVersion
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.78

Field Name : invalidStartLine
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.77

Field Name : failParseStartLine
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.76

Field Name : failReadStartLine
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.75

Field Name : lineTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.74

Field Name : smsgNoUriSession
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.73

Field Name : sgNoUriHeader
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.72

Field Name : cmsgNoUriSession
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.71

Field Name : cmsgNoUriHeader
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.70

Field Name : tableMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.69

Field Name : tableMemAllocd
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.68

Field Name : lineMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.67

Field Name : lineMemAllocd
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.66

Field Name : sessionCallidFreed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.65

Field Name : sessionCallidAllocd
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.64

Field Name : connFreed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.63

Field Name : connAllocd
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.62

Field Name : sessionInvalid
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.61

Field Name : sessionInRml
Field Type : CounterBasedGauge64
Field Status : current

Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.60

Field Name : sessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Session freed
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.59

Field Name : slbSipSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Session created
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.58

Field Name : msgProxyServerReset
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.57

Field Name : msgProxyClientReset
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.56

Field Name : msgProxyPiplineMsg
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.55

Field Name : msgProxySplitPkt
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.54

Field Name : msgProxyHoldMsg
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.53

Field Name : msgProxyDeprecatedConn
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.52

Field Name : msgProxyFailDcmsg
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.51

Field Name : msgProxyMagBack

Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.50

Field Name : msgProxyL7ToL4
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.49

Field Name : msgProxyL4FromL4Send
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.48

Field Name : msgProxyToL4SendPkt
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.47

Field Name : msgProxyL4FromL7
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.46

Field Name : msgProxyL4ToL7
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.45

Field Name : msgProxyL7CpuFailed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.44

Field Name : msgProxyUnexpectedErr
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.43

Field Name : msgProxyFailAllocMem
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.42

Field Name : msgProxyFailSelectServer
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.41

Field Name : msgProxyNoVport
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.40

Field Name : msgProxyProcessMsgFail
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.39

Field Name : msgProxyParseMsgFail
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.38

Field Name : msgProxyFailInsertServerConn
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.37

Field Name : msgProxyServerConnAlreadyExists
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.36

Field Name : msgProxyStartServerConnFailed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.35

Field Name : msgProxyFailReservePconn
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.34

Field Name : msgProxyFailConstructServerConn
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.33

Field Name : msgProxyServerConnFailSnat
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.32

Field Name : slbSipMsgProxyFailStartServerConn
Field Type : CounterBasedGauge64
Field Status : current

Description : Number of server connection create failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.31

Field Name : slbSipMsgProxyStartServerConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of server connection created successfully
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.30

Field Name : slbSipMsgProxyCreateServerConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of server connection system tries to create
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.29

Field Name : msgProxyServerFailSendPkt
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.28

Field Name : msgProxyServerExceedTmpBuff
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.27

Field Name : msgProxyServerFailSnat
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.26

Field Name : msgProxyServerFailSelecConnt
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.25

Field Name : msgProxyServerFailProcess
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.24

Field Name : msgProxyServerFailParse
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.23

Field Name : slbSipMsgProxyServerFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of SIP messages received from server but failed to forward to client
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.22

Field Name : slbSipMsgProxyServerDrop

Field Type : CounterBasedGauge64
Field Status : current
Description : Number of AX drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.21

Field Name : slbSipMsgProxyServerIncomplete
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of packet which contains incomplete message
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.20

Field Name : slbSipMsgProxyServerSendSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of SIP messages received from server and forwarded to client
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.19

Field Name : slbSipMsgProxyServerRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of SIP messages received from server
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.18

Field Name : msgProxyClientFailStartServerConn
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.17

Field Name : msgProxyClientFailSendPkt
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.16

Field Name : msgProxyClientExceedTmpBuff
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.15

Field Name : msgProxyClientFailSnat
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.14

Field Name : msgProxyClientFailProcess
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.13

Field Name : msgProxyClientFailParse
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.12

Field Name : slbSipMsgProxyClientFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of SIP messages received from client but failed to forward to server
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.11

Field Name : slbSipMsgProxyClientConnection
Field Type : CounterBasedGauge64
Field Status : current
Description : Connecting server
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.10

Field Name : slbSipMsgProxyClientDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of AX drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.9

Field Name : slbSipMsgProxyClientIncomplete
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of packet which contains incomplete message
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.8

Field Name : slbSipMsgProxyClientSendSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of SIP messages received from client and forwarded to server
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.7

Field Name : slbSipMsgProxyClientRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of SIP messages received from client
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.6

Field Name : msgProxyMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.5

Field Name : msgProxyMemCached
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.4

Field Name : msgProxyMemAllocd
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.3

Field Name : slbSipMsgProxyTotal
Field Type : CounterBasedGauge64
Field Status : current

Description : Total number of sip proxy connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.2

Field Name : slbSipMsgProxyCurrent
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of current sip proxy connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.1

Field Name : statusUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code unknown
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.63

Field Name : status6xx
Field Type : CounterBasedGauge64
Field Status : current
Description : status code 6XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.62

Field Name : status5xx
Field Type : CounterBasedGauge64
Field Status : current
Description : status code 5XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.61

Field Name : status4xx
Field Type : CounterBasedGauge64
Field Status : current
Description : status code 4XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.60

Field Name : status3xx
Field Type : CounterBasedGauge64
Field Status : current
Description : status code 3XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.59

Field Name : status2xx
Field Type : CounterBasedGauge64
Field Status : current
Description : status code 2XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.58

Field Name : status1xx
Field Type : CounterBasedGauge64
Field Status : current
Description : status code 1XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.57

Field Name : status510
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 510
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.56

Field Name : status509

Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 509
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.55

Field Name : status508
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 508
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.54

Field Name : status507
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 507
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.53

Field Name : status506
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 506
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.52

Field Name : status505
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 505
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.51

Field Name : status504
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 504
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.50

Field Name : status503
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 503
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.49

Field Name : status502
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 502
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.48

Field Name : status501
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 501
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.47

Field Name : status500
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 500
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.46

Field Name : status450
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 450
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.45

Field Name : status449
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 449
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.44

Field Name : status426
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 426
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.43

Field Name : status425
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 425
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.42

Field Name : status424
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 424
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.41

Field Name : status423
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 423
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.40

Field Name : status422
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 422
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.39

Field Name : status418
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 418
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.38

Field Name : status417
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 417
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.37

Field Name : status416
Field Type : CounterBasedGauge64
Field Status : current

Description : Status code 416
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.36

Field Name : status415
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 415
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.35

Field Name : status414
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 414
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.34

Field Name : status413
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 413
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.33

Field Name : status412
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 412
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.32

Field Name : status411
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 411
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.31

Field Name : status410
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 410
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.30

Field Name : status409
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 409
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.29

Field Name : status408
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 408
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.28

Field Name : status407
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 407
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.27

Field Name : status406

Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 406
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.26

Field Name : status405
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 405
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.25

Field Name : status404
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 404
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.24

Field Name : status403
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 403
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.23

Field Name : status402
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 402
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.22

Field Name : status401
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 401
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.21

Field Name : status400
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 400
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.20

Field Name : status307
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 307
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.19

Field Name : status306
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 306
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.18

Field Name : status305
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 305
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.17

Field Name : status304
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 304
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.16

Field Name : status303
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 303
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.15

Field Name : status302
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 302
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.14

Field Name : status301
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 301
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.13

Field Name : status300
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 300
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.12

Field Name : status102
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 102
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.11

Field Name : status101
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 101
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.10

Field Name : status100
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 100
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.9

Field Name : status207
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 207
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.8

Field Name : status206
Field Type : CounterBasedGauge64
Field Status : current

Description : Status code 206
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.7

Field Name : status205
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 205
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.6

Field Name : status204
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 204
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.5

Field Name : status203
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 203
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.4

Field Name : status202
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 202
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.3

Field Name : status201
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 201
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.2

Field Name : status200
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 200
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.1

Field Name : httpConnectReqmodRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP CONNECT Reqmod Request Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.105

Field Name : recvOptionResp
Field Type : CounterBasedGauge64
Field Status : current
Description : Send Option Req Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.104

Field Name : httpRespHdrErr
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Resp Hdr Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.103

Field Name : httpRespLineParseErr

Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Response Line Parse Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.102

Field Name : httpRespLineReadErr
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Response Line Read Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.101

Field Name : noStatusCodeErr
Field Type : CounterBasedGauge64
Field Status : current
Description : No Status Code Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.100

Field Name : reqHdrIncompleteErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Req Hdr Incomplete Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.99

Field Name : respHdrErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp Hdr Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.98

Field Name : respLineParseErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp Line Parse Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.97

Field Name : respLineReadErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp Line Read Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.96

Field Name : noIcapRespErr
Field Type : CounterBasedGauge64
Field Status : current
Description : No ICAP Resp Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.95

Field Name : encapHdrIncompleteErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Encap HDR Incomplete Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.94

Field Name : icapLineErr
Field Type : CounterBasedGauge64
Field Status : current
Description : ICAP Line Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.93

Field Name : icapVerErr
Field Type : CounterBasedGauge64
Field Status : current
Description : ICAP Ver Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.92

Field Name : prepReqFailErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Prepare ICAP req fail Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.91

Field Name : startIcapConnFailErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Start ICAP conn fail Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.90

Field Name : servSelFailErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Server Select Fail Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.89

Field Name : respHdrIncompleteErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp Hdr Incomplete Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.88

Field Name : noPayloadBuffErr
Field Type : CounterBasedGauge64
Field Status : current
Description : No Payload Buff Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.87

Field Name : noPayloadNextBuffErr
Field Type : CounterBasedGauge64
Field Status : current
Description : No Payload In Next Buff Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.86

Field Name : chunkBadTrailErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Chunk Bad Trail Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.85

Field Name : chunk2HdrErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Chunk Hdr Err2 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.84

Field Name : chunk1HdrErr
Field Type : CounterBasedGauge64
Field Status : current

Description : Chunk Hdr Err1 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.83

Field Name : appServConnErr
Field Type : CounterBasedGauge64
Field Status : current
Description : App Server Conn Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.82

Field Name : appServConnNoPcbErr
Field Type : CounterBasedGauge64
Field Status : current
Description : App Server Conn no ES PCB Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.81

Field Name : sendOptionReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Send Option Req Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.80

Field Name : statusUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : Status Unknown Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.79

Field Name : status6xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 6xx Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.78

Field Name : status510
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 510 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.77

Field Name : status509
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 509 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.76

Field Name : status508
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 508 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.75

Field Name : status507
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 507 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.74

Field Name : status506

Field Type : CounterBasedGauge64
Field Status : current
Description : Status 506 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.73

Field Name : status505
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 505 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.72

Field Name : status504
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 504 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.71

Field Name : status503
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 503 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.70

Field Name : status502
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 502 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.69

Field Name : status501
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 501 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.68

Field Name : status500
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 500 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.67

Field Name : status5xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 5xx Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.66

Field Name : status450
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 450 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.65

Field Name : status449
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 449 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.64

Field Name : status426
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 426 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.63

Field Name : status425
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 425 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.62

Field Name : status424
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 424 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.61

Field Name : status423
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 423 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.60

Field Name : status422
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 422 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.59

Field Name : status420
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 420 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.58

Field Name : status419
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 419 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.57

Field Name : status418
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 418 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.56

Field Name : status417
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 417 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.55

Field Name : status416
Field Type : CounterBasedGauge64
Field Status : current

Description : Status 416 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.54

Field Name : status415
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 415 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.53

Field Name : status414
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 414 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.52

Field Name : status413
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 413 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.51

Field Name : status412
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 412 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.50

Field Name : status411
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 411 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.49

Field Name : status410
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 410 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.48

Field Name : status409
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 409 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.47

Field Name : status408
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 408 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.46

Field Name : status407
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 407 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.45

Field Name : status406

Field Type : CounterBasedGauge64
Field Status : current
Description : Status 406 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.44

Field Name : status405
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 405 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.43

Field Name : status404
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 404 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.42

Field Name : status403
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 403 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.41

Field Name : status402
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 402 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.40

Field Name : status401
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 401 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.39

Field Name : status400
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 400 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.38

Field Name : status4xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 4xx Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.37

Field Name : status307
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 307 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.36

Field Name : status306
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 306 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.35

Field Name : status305
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 305 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.34

Field Name : status304
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 304 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.33

Field Name : status303
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 303 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.32

Field Name : status302
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 302 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.31

Field Name : status301
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 301 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.30

Field Name : status300
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 300 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.29

Field Name : status3xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 3xx Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.28

Field Name : status102
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 102 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.27

Field Name : status101
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 101 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.26

Field Name : status100
Field Type : CounterBasedGauge64
Field Status : current

Description : Status 100 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.25

Field Name : status1xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 1xx Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.24

Field Name : status207
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 207 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.23

Field Name : status206
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 206 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.22

Field Name : status205
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 205 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.21

Field Name : status204
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 204 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.20

Field Name : status203
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 203 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.19

Field Name : status202
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 202 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.18

Field Name : status201
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 201 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.17

Field Name : status200
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 200 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.16

Field Name : status2xx

Field Type : CounterBasedGauge64
Field Status : current
Description : Status 2xx Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.15

Field Name : resultOther
Field Type : CounterBasedGauge64
Field Status : current
Description : Result Other Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.14

Field Name : result100Continue
Field Type : CounterBasedGauge64
Field Status : current
Description : Result 100 Continue Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.13

Field Name : resultIcapResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Result ICAP Response Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.12

Field Name : resultContinue
Field Type : CounterBasedGauge64
Field Status : current
Description : Result Continue Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.11

Field Name : lenExceedNoAllow204
Field Type : CounterBasedGauge64
Field Status : current
Description : Length Exceeded so no Allow 204 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.10

Field Name : chunkNoAllow204
Field Type : CounterBasedGauge64
Field Status : current
Description : Chunk so no Allow 204 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.9

Field Name : respmodResponseAfter100
Field Type : CounterBasedGauge64
Field Status : current
Description : Respmod Response After 100 Cont Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.8

Field Name : reqmodResponseAfter100
Field Type : CounterBasedGauge64
Field Status : current
Description : Reqmod Response After 100 Cont Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.7

Field Name : respmodResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Respmod Response Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.6

Field Name : reqmodResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Reqmod Response Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.5

Field Name : respmodRequestAfter100
Field Type : CounterBasedGauge64
Field Status : current
Description : Respmod Request Sent After 100 Cont Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.4

Field Name : reqmodRequestAfter100
Field Type : CounterBasedGauge64
Field Status : current
Description : Reqmod Request Sent After 100 Cont Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.3

Field Name : respmodRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Respmod Request Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.2

Field Name : reqmodRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Reqmod Request Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.1

Field Name : insertionSuccessful
Field Type : CounterBasedGauge64
Field Status : current
Description : Insertion successful
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.30

Field Name : insertionFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Insertion failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.29

Field Name : sessionExist
Field Type : CounterBasedGauge64
Field Status : current
Description : Session already exist
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.28

Field Name : clientIdNull
Field Type : CounterBasedGauge64
Field Status : current
Description : Null client id
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.27

Field Name : connNull
Field Type : CounterBasedGauge64
Field Status : current

Description : Null conn
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.26

Field Name : tupleAlreadyLinked
Field Type : CounterBasedGauge64
Field Status : current
Description : tuple-already-linked failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.25

Field Name : tupleNotLinked
Field Type : CounterBasedGauge64
Field Status : current
Description : tuple-not-linked failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.24

Field Name : parseUnsubscribeFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Parse unsubscribe failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.23

Field Name : parseSubscribeFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Parse subscribe failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.22

Field Name : parsePublishFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Parse publish failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.21

Field Name : parseConnectFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Parse connect failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.20

Field Name : request
Field Type : CounterBasedGauge64
Field Status : current
Description : Total MQTT Commands
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.19

Field Name : totalProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Total proxy conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.18

Field Name : currProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Current proxy conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.17

Field Name : recvMqttOther

Field Type : CounterBasedGauge64
Field Status : current
Description : MQTT Unknown
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.16

Field Name : recvMqttAuth
Field Type : CounterBasedGauge64
Field Status : current
Description : MQTT Auth
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.15

Field Name : recvMqttDisconnect
Field Type : CounterBasedGauge64
Field Status : current
Description : MQTT Disconnect
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.14

Field Name : recvMqttPingresp
Field Type : CounterBasedGauge64
Field Status : current
Description : MQTT Pingresp
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.13

Field Name : recvMqttPingreq
Field Type : CounterBasedGauge64
Field Status : current
Description : MQTT Pingreq
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.12

Field Name : recvMqttUnsuback
Field Type : CounterBasedGauge64
Field Status : current
Description : MQTT Unsuback
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.11

Field Name : recvMqttUnsubscribe
Field Type : CounterBasedGauge64
Field Status : current
Description : MQTT Unsubscribe
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.10

Field Name : recvMqttSuback
Field Type : CounterBasedGauge64
Field Status : current
Description : MQTT Suback
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.9

Field Name : recvMqttSubscribe
Field Type : CounterBasedGauge64
Field Status : current
Description : MQTT Subscribe
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.8

Field Name : recvMqttPubcomp
Field Type : CounterBasedGauge64
Field Status : current
Description : MQTT Pubcomp
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.7

Field Name : recvMqttPubrel
Field Type : CounterBasedGauge64
Field Status : current
Description : MQTT Pubrel
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.6

Field Name : recvMqttPubrec
Field Type : CounterBasedGauge64
Field Status : current
Description : MQTT Pubrec
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.5

Field Name : recvMqttPuback
Field Type : CounterBasedGauge64
Field Status : current
Description : MQTT Puback
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.4

Field Name : recvMqttPublish
Field Type : CounterBasedGauge64
Field Status : current
Description : MQTT Publish
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.3

Field Name : recvMqttConnack
Field Type : CounterBasedGauge64
Field Status : current
Description : MQTT Connack
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.2

Field Name : recvMqttConnect
Field Type : CounterBasedGauge64
Field Status : current
Description : MQTT Connect
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.1

Field Name : clientEhloSaved
Field Type : CounterBasedGauge64
Field Status : current
Description : Client EHLO saved
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.75

Field Name : dropServerEhloOk
Field Type : CounterBasedGauge64
Field Status : current
Description : Server EHLO_OK dropped
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.74

Field Name : aflexMailFail
Field Type : CounterBasedGauge64
Field Status : current
Description : aFlex Mail event failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.73

Field Name : failToSaveClientEhlo
Field Type : CounterBasedGauge64
Field Status : current

Description : Failed to save client EHLO
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.72

Field Name : sendServerEhlo
Field Type : CounterBasedGauge64
Field Status : current
Description : Proxy sends server EHLO
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.71

Field Name : recvClientCommandETRN
Field Type : CounterBasedGauge64
Field Status : current
Description : Recv client ETRN
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.70

Field Name : recvClientCommandTURN
Field Type : CounterBasedGauge64
Field Status : current
Description : Recv client TURN
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.69

Field Name : rserverSTARTTLSDisable
Field Type : CounterBasedGauge64
Field Status : current
Description : real server not support STARTTLS
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.68

Field Name : serverSTARTTLSFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Server side STARTTLS fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.67

Field Name : serverSTARTTLSInit
Field Type : CounterBasedGauge64
Field Status : current
Description : Init server side STARTTLS
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.66

Field Name : aflexLbReselectOk
Field Type : CounterBasedGauge64
Field Status : current
Description : aFleX lb reselect (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.65

Field Name : aflexLbReselect
Field Type : CounterBasedGauge64
Field Status : current
Description : aFleX lb reselect
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.64

Field Name : parseResonseLineFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Parse response line fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.63

Field Name : removeResonseLineFail

Field Type : CounterBasedGauge64
Field Status : current
Description : Del response line fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.62

Field Name : insertResonseLineFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Ins response line fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.61

Field Name : parseRequestLineFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Parse request line fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.60

Field Name : lineTableExtendFail
Field Type : TABLE
Field Status : current
Description : Table extend fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.59

Field Name : lineTableExtend
Field Type : TABLE
Field Status : current
Description : Table extend
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.58

Field Name : lineExtendFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Line extend fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.57

Field Name : lineExtend
Field Type : CounterBasedGauge64
Field Status : current
Description : Line extend
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.56

Field Name : lineAcrossPacket
Field Type : CounterBasedGauge64
Field Status : current
Description : Line across packets
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.55

Field Name : lineTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Line too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.54

Field Name : tooManyHeaders
Field Type : CounterBasedGauge64
Field Status : current
Description : Too many headers
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.53

Field Name : getAllHeadersFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Get all headers fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.52

Field Name : readRequestLineFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Read request line fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.51

Field Name : lbSwitchOk
Field Type : CounterBasedGauge64
Field Status : current
Description : LB switching (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.50

Field Name : lbSwitch
Field Type : CounterBasedGauge64
Field Status : current
Description : LB switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.49

Field Name : clientDomainSwitchOk
Field Type : CounterBasedGauge64
Field Status : current
Description : Client domain sw (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.48

Field Name : clientDomainSwitch
Field Type : CounterBasedGauge64
Field Status : current
Description : Client domain switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.47

Field Name : recvServerUnknowReplyCode
Field Type : CounterBasedGauge64
Field Status : current
Description : Recv server unknown-code
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.46

Field Name : recvServerServiceNotReady
Field Type : CounterBasedGauge64
Field Status : current
Description : Recv server serv-not-rdy
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.45

Field Name : l4Switched
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.44

Field Name : tlsEstablished
Field Type : CounterBasedGauge64
Field Status : current

Description : SSL session established
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.43

Field Name : sendServerCmdReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Sent server RSET
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.42

Field Name : sendClientNoCommand
Field Type : CounterBasedGauge64
Field Status : current
Description : Sent client no-such-cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.41

Field Name : sendClientTLSNotAvailable
Field Type : CounterBasedGauge64
Field Status : current
Description : Sent client TLS-not-aval
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.40

Field Name : sendClientStartTLSFirst
Field Type : CounterBasedGauge64
Field Status : current
Description : Sent client STARTTLS-1st
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.39

Field Name : sendClientGoAhead
Field Type : CounterBasedGauge64
Field Status : current
Description : Sent client go-ahead
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.38

Field Name : sendClientCloseConnection
Field Type : CounterBasedGauge64
Field Status : current
Description : Sent client close-conn
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.37

Field Name : sendClientServiceNotReady
Field Type : CounterBasedGauge64
Field Status : current
Description : Sent client serv-not-rdy
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.36

Field Name : sendClientServiceReady
Field Type : CounterBasedGauge64
Field Status : current
Description : Sent client serv-rdy
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.35

Field Name : recvClientCommandOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Recv client other cmds
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.34

Field Name : recvClientCommandSTARTTLS

Field Type : CounterBasedGauge64
Field Status : current
Description : Recv client STARTTLS
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.33

Field Name : recvClientCommandQUIT
Field Type : CounterBasedGauge64
Field Status : current
Description : Recv client QUIT
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.32

Field Name : recvClientCommandNOOP
Field Type : CounterBasedGauge64
Field Status : current
Description : Recv client NOOP
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.31

Field Name : recvClientCommandHELP
Field Type : CounterBasedGauge64
Field Status : current
Description : Recv client HELP
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.30

Field Name : recvClientCommandEXPN
Field Type : CounterBasedGauge64
Field Status : current
Description : Recv client EXPN
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.29

Field Name : recvClientCommandVRFY
Field Type : CounterBasedGauge64
Field Status : current
Description : Recv client VRFY
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.28

Field Name : recvClientCommandRSET
Field Type : CounterBasedGauge64
Field Status : current
Description : Recv client RSET
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.27

Field Name : recvClientCommandDATA
Field Type : CounterBasedGauge64
Field Status : current
Description : Recv client DATA
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.26

Field Name : recvClientCommandRCPT
Field Type : CounterBasedGauge64
Field Status : current
Description : Recv client RCPT
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.25

Field Name : recvClientCommandMAIL
Field Type : CounterBasedGauge64
Field Status : current
Description : Recv client MAIL
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.24

Field Name : recvClientCommandHELO
Field Type : CounterBasedGauge64
Field Status : current
Description : Recv client HELO
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.23

Field Name : recvClientCommandEHLO
Field Type : CounterBasedGauge64
Field Status : current
Description : Recv client EHLO
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.22

Field Name : aflexSwitchedOk
Field Type : CounterBasedGauge64
Field Status : current
Description : aFleX switching (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.21

Field Name : aflexSwitched
Field Type : CounterBasedGauge64
Field Status : current
Description : aFleX switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.20

Field Name : tcpOutReset
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP out reset
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.19

Field Name : slbSmtpSnatFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Source NAT failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.18

Field Name : newServerConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Server connection made
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.17

Field Name : serverPremClose
Field Type : CounterBasedGauge64
Field Status : current
Description : Server premature close
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.16

Field Name : serverReselect
Field Type : CounterBasedGauge64
Field Status : current
Description : Server reselection
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.15

Field Name : reqOfo
Field Type : CounterBasedGauge64
Field Status : current

Description : Request pkt out-of-order
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.14

Field Name : reqRetran
Field Type : CounterBasedGauge64
Field Status : current
Description : Request retransmit
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.13

Field Name : forwardReqDataFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward REQ data failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.12

Field Name : forwardReqFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward request failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.11

Field Name : serverSelectFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Server selection failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.10

Field Name : parseReqFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Parse request failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.9

Field Name : noTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : No tuple error
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.8

Field Name : serverReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Server reset
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.7

Field Name : clientReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Client reset
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.6

Field Name : noProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : No proxy error
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.5

Field Name : requestSuccess

Field Type : CounterBasedGauge64
Field Status : current
Description : SMTP requests (success)
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.4

Field Name : slbSmtpRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : SMTP requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.3

Field Name : slbSmtpTotalProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Total proxy conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.2

Field Name : slbSmtpCurrProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Current proxy conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.1

Field Name : failBindMsg
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.85

Field Name : singleMsg
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.84

Field Name : serverConnFailBind
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.83

Field Name : serverConnGetFromList
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.82

Field Name : serverConnPutInList
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.81

Field Name : clientConnGetFromList
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.80

Field Name : clientConnPutInList
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.79

Field Name : enquireLinkRespSend
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.78

Field Name : enquireLinkSend
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.77

Field Name : enquireLinkRespRecv
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.76

Field Name : enquireLinkRecv
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.75

Field Name : unbindConn
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.74

Field Name : bindConn
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.73

Field Name : selectServerFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Fail to select server conn
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.72

Field Name : selectServerByConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Select server conn by client conn
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.71

Field Name : selectServerFromList
Field Type : CounterBasedGauge64
Field Status : current

Description : Select by roundbin
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.70

Field Name : selectServerByReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Select by request
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.69

Field Name : selectServerConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Server conn selection
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.68

Field Name : selectClientFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Select failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.67

Field Name : selectClientByConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Select by conn
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.66

Field Name : selectClientFromList
Field Type : CounterBasedGauge64
Field Status : current
Description : Select by roundbin
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.65

Field Name : selectClientByReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Select by request
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.64

Field Name : selectClientConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Client conn selection
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.63

Field Name : acosRespDirectly
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of packet which AX responds directly
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.62

Field Name : invalidSeq
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.61

Field Name : pktTooSmall

Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.60

Field Name : payloadFreed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.59

Field Name : payloadAllocd
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.58

Field Name : msgProxyServerReset
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.57

Field Name : msgProxyClientReset
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.56

Field Name : msgProxyPiplineMsg
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.55

Field Name : msgProxySplitPkt
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.54

Field Name : msgProxyHoldMsg
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.53

Field Name : msgProxyDeprecatedConn
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.52

Field Name : msgProxyFailDcmsg
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.51

Field Name : msgProxyMagBack
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.50

Field Name : msgProxyL7ToL4
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.49

Field Name : msgProxyL4FromL4Send
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.48

Field Name : msgProxyToL4SendPkt
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.47

Field Name : msgProxyL4FromL7
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.46

Field Name : msgProxyL4ToL7
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.45

Field Name : msgProxyL7CpuFailed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.44

Field Name : msgProxyUnexpectedErr
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.43

Field Name : msgProxyFailAllocMem
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.42

Field Name : msgProxyFailSelectServer
Field Type : CounterBasedGauge64
Field Status : current

Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.41

Field Name : msgProxyNoVport
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.40

Field Name : msgProxyProcessMsgFail
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.39

Field Name : msgProxyParseMsgFail
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.38

Field Name : msgProxyFailInsertServerConn
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.37

Field Name : msgProxyServerConnAlreadyExists
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.36

Field Name : msgProxyStartServerConnFailed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.35

Field Name : msgProxyFailReservePconn
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.34

Field Name : msgProxyFailConstructServerConn
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.33

Field Name : msgProxyServerConnFailSnat
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.32

Field Name : msgProxyFailStartServerConn

Field Type : CounterBasedGauge64
Field Status : current
Description : Number of server connection created failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.31

Field Name : msgProxyStartServerConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of server connection created successfully
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.30

Field Name : msgProxyCreateServerConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Server conn created
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.29

Field Name : msgProxyServerFailSendPkt
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.28

Field Name : msgProxyServerExceedTmpBuff
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.27

Field Name : msgProxyServerFailSnat
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.26

Field Name : msgProxyServerFailSelecConnt
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.25

Field Name : msgProxyServerFailProcess
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.24

Field Name : msgProxyServerFailParse
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.23

Field Name : msgProxyServerFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of SMPP messages received from server but failed to forward to client
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.22

Field Name : msgProxyServerDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of the packet AX drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.21

Field Name : msgProxyServerIncomplete
Field Type : CounterBasedGauge64
Field Status : current
Description : Incomplete
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.20

Field Name : msgProxyServerSendSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Sent to client
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.19

Field Name : msgProxyServerRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : Server message rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.18

Field Name : msgProxyClientFailStartServerConn
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.17

Field Name : msgProxyClientFailSendPkt
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.16

Field Name : msgProxyClientExceedTmpBuff
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.15

Field Name : msgProxyClientFailSnat
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.14

Field Name : msgProxyClientFailProcess
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.13

Field Name : msgProxyClientFailParse
Field Type : CounterBasedGauge64
Field Status : current

Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.12

Field Name : msgProxyClientFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of SMPP messages received from client but failed to forward to server
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.11

Field Name : msgProxyClientConnection
Field Type : CounterBasedGauge64
Field Status : current
Description : Connecting server
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.10

Field Name : msgProxyClientDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : AX responds directly
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.9

Field Name : msgProxyClientIncomplete
Field Type : CounterBasedGauge64
Field Status : current
Description : Incomplete
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.8

Field Name : msgProxyClientSendSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Sent to server
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.7

Field Name : msgProxyClientRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : Client message rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.6

Field Name : msgProxyMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.5

Field Name : msgProxyMemCached
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.4

Field Name : msgProxyMemAllocd
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.3

Field Name : msgProxyTotal

Field Type : CounterBasedGauge64
Field Status : current
Description : Total SMPP Proxy
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.2

Field Name : msgProxyCurrent
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr SMPP Proxy
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.1

Field Name : invalidServer
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid server - tuple
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.47

Field Name : clientNotCleaned
Field Type : CounterBasedGauge64
Field Status : current
Description : Client not cleaned - tuple
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.46

Field Name : serverNotCleaned
Field Type : CounterBasedGauge64
Field Status : current
Description : Server not cleaned - tuple
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.45

Field Name : oldServerCleaned
Field Type : CounterBasedGauge64
Field Status : current
Description : Old server cleaned - tuple
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.44

Field Name : transactionCleaned
Field Type : CounterBasedGauge64
Field Status : current
Description : Transaction cleaned - tuple
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.43

Field Name : udpDataEvent
Field Type : CounterBasedGauge64
Field Status : current
Description : Data event from UDP
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.42

Field Name : hpsFwdreqFailTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - tuple
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.41

Field Name : hpsFwdreqFailServer
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - server
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.40

Field Name : hpsFwdreqFailPersist
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - persist
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.39

Field Name : hpsFwdreqFailRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - route
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.38

Field Name : hpsFwdreqFailRport
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - rport
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.37

Field Name : hpsFwdreqFailBuff
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - buff
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.36

Field Name : hpsFwdreqFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.35

Field Name : dataCbFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Data event callback fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.34

Field Name : estCbFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Est event callback fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.33

Field Name : estEvent
Field Type : CounterBasedGauge64
Field Status : current
Description : Est event from TCP
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.32

Field Name : serverSelectFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Server selection fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.31

Field Name : totalProxyEs
Field Type : CounterBasedGauge64
Field Status : current

Description : Total proxy conn - ES
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.30

Field Name : totalProxyServer
Field Type : CounterBasedGauge64
Field Status : current
Description : Total proxy conn - server
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.29

Field Name : totalProxyClient
Field Type : CounterBasedGauge64
Field Status : current
Description : Total proxy conn - client
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.28

Field Name : totalProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Total proxy conn
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.27

Field Name : currProxyEs
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr proxy conn - ES
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.26

Field Name : currProxyServer
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr proxy conn - server
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.25

Field Name : currProxyClient
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr proxy conn - client
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.24

Field Name : currProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr proxy conn
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.23

Field Name : proxyV2Connection
Field Type : CounterBasedGauge64
Field Status : current
Description : counter for Proxy v2 connection
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.22

Field Name : proxyV1Connection
Field Type : CounterBasedGauge64
Field Status : current
Description : counter for Proxy v1 connection
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.21

Field Name : serverRstRsp

Field Type : CounterBasedGauge64
Field Status : current
Description : RST from server - response
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.20

Field Name : serverRstConnected
Field Type : CounterBasedGauge64
Field Status : current
Description : RST from server - connected
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.19

Field Name : serverRstConnecting
Field Type : CounterBasedGauge64
Field Status : current
Description : RST from server - connecting
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.18

Field Name : serverRstReq
Field Type : CounterBasedGauge64
Field Status : current
Description : RST from server - request
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.17

Field Name : clientRstRsp
Field Type : CounterBasedGauge64
Field Status : current
Description : RST from client - response
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.16

Field Name : clientRstConnected
Field Type : CounterBasedGauge64
Field Status : current
Description : RST from client - connected
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.15

Field Name : clientRstConnecting
Field Type : CounterBasedGauge64
Field Status : current
Description : RST from client - connecting
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.14

Field Name : clientRstReq
Field Type : CounterBasedGauge64
Field Status : current
Description : RST from client - request
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.13

Field Name : serverRst
Field Type : CounterBasedGauge64
Field Status : current
Description : RST from server
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.12

Field Name : clientRst
Field Type : CounterBasedGauge64
Field Status : current
Description : RST from client
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.11

Field Name : serverConnFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Server connection failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.10

Field Name : errCbFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Err event callback failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.9

Field Name : errEvent
Field Type : CounterBasedGauge64
Field Status : current
Description : Err event from TCP
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.8

Field Name : wbufCbFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Wbuf event callback failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.7

Field Name : wbufEvent
Field Type : CounterBasedGauge64
Field Status : current
Description : Wbuf event from TCP
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.6

Field Name : serverFin
Field Type : CounterBasedGauge64
Field Status : current
Description : FIN from server
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.5

Field Name : clientFin
Field Type : CounterBasedGauge64
Field Status : current
Description : FIN from client
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.4

Field Name : dataEvent
Field Type : CounterBasedGauge64
Field Status : current
Description : Data event from TCP
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.3

Field Name : connNotExist
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn does not exist
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.2

Field Name : startServerConnSucc
Field Type : CounterBasedGauge64
Field Status : current

Description : Start Server Conn Success
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.1

Field Name : slbHttp3Rejected
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP3 Rejected
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.102

Field Name : allocFailTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Memory Allocation Failures
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.101

Field Name : connAllocError
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP/3 Connection Allocation Error
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.100

Field Name : slbHttp3Fatal
Field Type : CounterBasedGauge64
Field Status : current
Description : Fatal Error
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.99

Field Name : slbHttp3H3StreamCreationError
Field Type : CounterBasedGauge64
Field Status : current
Description : H3 Stream Creation Error
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.98

Field Name : slbHttp3H3SettingsError
Field Type : CounterBasedGauge64
Field Status : current
Description : H3 Settings Error
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.97

Field Name : slbHttp3H3IdError
Field Type : CounterBasedGauge64
Field Status : current
Description : H3 Id Error
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.96

Field Name : slbHttp3H3GeneralProtocolError
Field Type : CounterBasedGauge64
Field Status : current
Description : H3 General Protocol Error
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.95

Field Name : slbHttp3H3ClosedCriticalStream
Field Type : CounterBasedGauge64
Field Status : current
Description : H3 Closed Critical Stream
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.94

Field Name : slbHttp3H3InternalError

Field Type : CounterBasedGauge64
Field Status : current
Description : H3 Internal Error
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.93

Field Name : slbHttp3H3MissingSettings
Field Type : CounterBasedGauge64
Field Status : current
Description : H3 Missing Settings
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.92

Field Name : slbHttp3H3FrameError
Field Type : CounterBasedGauge64
Field Status : current
Description : H3 Frame Error
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.91

Field Name : slbHttp3H3FrameUnexpected
Field Type : CounterBasedGauge64
Field Status : current
Description : H3 Frame Unexpected
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.90

Field Name : slbHttp3QpackDecoderStreamError
Field Type : CounterBasedGauge64
Field Status : current
Description : Qpack Decoder Stream Error
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.89

Field Name : slbHttp3QpackEncoderStreamError
Field Type : CounterBasedGauge64
Field Status : current
Description : Qpack Encoder Stream Error
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.88

Field Name : slbHttp3QpackDecompressionFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Qpack Decompression Failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.87

Field Name : slbHttp3IgnorePushPromise
Field Type : CounterBasedGauge64
Field Status : current
Description : Ignore Push Promise
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.86

Field Name : slbHttp3StreamNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.85

Field Name : slbHttp3IgnoreStream
Field Type : CounterBasedGauge64
Field Status : current
Description : Ignore Stream
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.84

Field Name : slbHttp3QpackHeaderTooLarge
Field Type : CounterBasedGauge64
Field Status : current
Description : Qpack Header Too Large
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.83

Field Name : slbHttp3QpackFatal
Field Type : CounterBasedGauge64
Field Status : current
Description : Qpack Fatal
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.82

Field Name : slbHttp3TooLate
Field Type : CounterBasedGauge64
Field Status : current
Description : Too Late
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.81

Field Name : slbHttp3MalformedHttpMessaging
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed Http Messaging
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.80

Field Name : slbHttp3RemoveHttpHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : Remove Http Header
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.79

Field Name : slbHttp3MalformedHttpHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed Http Header
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.78

Field Name : slbHttp3PushIdBlocked
Field Type : CounterBasedGauge64
Field Status : current
Description : Push Id Blocked
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.77

Field Name : slbHttp3StreamInUse
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream In Use
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.76

Field Name : slbHttp3Wouldblock
Field Type : CounterBasedGauge64
Field Status : current
Description : Wouldblock
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.75

Field Name : slbHttp3InvalidState
Field Type : CounterBasedGauge64
Field Status : current

Description : Invalid State
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.74

Field Name : slbHttp3InvalidArgument
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid Argument
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.73

Field Name : serverTotalBytesSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Bytes sent on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.72

Field Name : serverTotalBytesRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Bytes received on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.71

Field Name : serverHeadingBytesSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes sent in HEADERS/DATA frame/stream heading on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.70

Field Name : serverHeadingBytesRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes received in HEADERS/DATA frame/stream heading on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.69

Field Name : serverOtherFrameBytesSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes sent in other frames (SETTINGS, GOAWAY, PUSH_PROMISE etc) on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.68

Field Name : serverOtherFrameBytesRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes received in other frames (SETTINGS, GOAWAY, PUSH_PROMISE etc) on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.67

Field Name : serverDataBytesSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes sent in DATA frames on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.66

Field Name : serverDataBytesRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes received in DATA frames on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.65

Field Name : serverHeaderBytesSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes sent in HEADER frames on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.64

Field Name : serverHeaderBytesRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes received in HEADER frames on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.63

Field Name : serverDataFramesToApp
Field Type : CounterBasedGauge64
Field Status : current
Description : DATA Frames passed to HTTP layer on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.62

Field Name : serverHeaderFramesToApp
Field Type : CounterBasedGauge64
Field Status : current
Description : HEADER Frames passed to HTTP layer on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.61

Field Name : slbHttpServerFrameTypeUnknownRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Unknown Frame received on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.60

Field Name : slbHttpServerFrameTypeMaxPushIdSent
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX PUSH ID Frame sent on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.59

Field Name : slbHttpServerFrameTypeMaxPushIdRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX PUSH ID Frame received on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.58

Field Name : slbHttpServerFrameTypeGoawaySent
Field Type : CounterBasedGauge64
Field Status : current
Description : GOAWAY Frame sent on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.57

Field Name : slbHttpServerFrameTypeGoawayRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : GOAWAY Frame received on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.56

Field Name : slbHttpServerFrameTypePushPromiseSent
Field Type : CounterBasedGauge64
Field Status : current

Description : PUSH PROMISE Frame sent on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.55

Field Name : slbHttpServerFrameTypePushPromiseRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : PUSH PROMISE Frame received on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.54

Field Name : slbHttpServerFrameTypeSettingsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : SETTINGS Frame sent on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.53

Field Name : slbHttpServerFrameTypeSettingsRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : SETTINGS Frame received on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.52

Field Name : slbHttpServerFrameTypeCancelPushSent
Field Type : CounterBasedGauge64
Field Status : current
Description : CANCEL PUSH Frame sent on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.51

Field Name : slbHttpServerFrameTypeCancelPushRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : CANCEL PUSH Frame received on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.50

Field Name : slbHttpServerFrameTypeDataSent
Field Type : CounterBasedGauge64
Field Status : current
Description : DATA Frame sent on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.49

Field Name : slbHttpServerFrameTypeDataRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : DATA Frame received on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.48

Field Name : slbHttpServerFrameTypeHeadersSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HEADERS Frame sent on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.47

Field Name : slbHttpServerFrameTypeHeadersRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : HEADERS Frame received on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.46

Field Name : clientTotalBytesSent

Field Type : CounterBasedGauge64
Field Status : current
Description : Total Bytes sent on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.45

Field Name : clientTotalBytesRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Bytes received on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.44

Field Name : clientHeadingBytesSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes sent in HEADERS/DATA frame/stream heading on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.43

Field Name : clientHeadingBytesRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes received in HEADERS/DATA frame/stream heading on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.42

Field Name : clientOtherFrameBytesSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes sent in other frames (SETTINGS, GOAWAY, PUSH_PROMISE etc) on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.41

Field Name : clientOtherFrameBytesRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes received in other frames (SETTINGS, GOAWAY, PUSH_PROMISE etc) on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.40

Field Name : clientDataBytesSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes sent in DATA frames on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.39

Field Name : clientDataBytesRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes received in DATA frames on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.38

Field Name : clientHeaderBytesSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes sent in HEADER frames on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.37

Field Name : clientHeaderBytesRcvd
Field Type : CounterBasedGauge64
Field Status : current

Description : Bytes received in HEADER frames on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.36

Field Name : clientDataFramesToApp
Field Type : CounterBasedGauge64
Field Status : current
Description : DATA Frames passed to HTTP layer on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.35

Field Name : clientHeaderFramesToApp
Field Type : CounterBasedGauge64
Field Status : current
Description : HEADER Frames passed to HTTP layer on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.34

Field Name : slbHttpClientFrameTypeUnknownRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Unknown Frame received on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.33

Field Name : slbHttpClientFrameTypeMaxPushIdSent
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX PUSH ID Frame sent on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.32

Field Name : slbHttpClientFrameTypeMaxPushIdRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX PUSH ID Frame received on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.31

Field Name : slbHttpClientFrameTypeGoawaySent
Field Type : CounterBasedGauge64
Field Status : current
Description : GOAWAY Frame sent on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.30

Field Name : slbHttpClientFrameTypeGoawayRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : GOAWAY Frame received on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.29

Field Name : slbHttpClientFrameTypePushPromiseSent
Field Type : CounterBasedGauge64
Field Status : current
Description : PUSH PROMISE Frame sent on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.28

Field Name : slbHttpClientFrameTypePushPromiseRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : PUSH PROMISE Frame received on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.27

Field Name : slbHttpClientFrameTypeSettingsSent

Field Type : CounterBasedGauge64
Field Status : current
Description : SETTINGS Frame sent on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.26

Field Name : slbHttpClientFrameTypeSettingsRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : SETTINGS Frame received on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.25

Field Name : slbHttpClientFrameTypeCancelPushSent
Field Type : CounterBasedGauge64
Field Status : current
Description : CANCEL PUSH Frame sent on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.24

Field Name : slbHttpClientFrameTypeCancelPushRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : CANCEL PUSH Frame received on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.23

Field Name : slbHttpClientFrameTypeDataSent
Field Type : CounterBasedGauge64
Field Status : current
Description : DATA Frame sent on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.22

Field Name : slbHttpClientFrameTypeDataRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : DATA Frame received on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.21

Field Name : slbHttpClientFrameTypeHeadersSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HEADERS Frame sent on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.20

Field Name : slbHttpClientFrameTypeHeadersRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : HEADERS Frame received on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.19

Field Name : slbHttp3ServerOtherStreamsTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Other Streams on server side (control, decoder, encoder)
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.18

Field Name : slbHttp3ClientOtherStreamsTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Other Streams on client side (control, decoder, encoder)
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.17

Field Name : slbHttp3ServerOtherStreamsCurr
Field Type : CounterBasedGauge64
Field Status : current
Description : urrent Other Streams on server side (control, decoder, encoder)
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.16

Field Name : slbHttp3ClientOtherStreamsCurr
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Other Streams on client side (control, decoder, encoder)
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.15

Field Name : slbHttp3ServerPushStreamsTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Push Streams on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.14

Field Name : slbHttp3ClientPushStreamsTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Push Streams on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.13

Field Name : slbHttp3ServerPushStreamsCurr
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Push Streams on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.12

Field Name : slbHttp3ClientPushStreamsCurr
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Push Streams on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.11

Field Name : slbHttp3ServerRequestStreamsTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Request Streams on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.10

Field Name : slbHttp3ClientRequestStreamsTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Request Streams on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.9

Field Name : slbHttp3ServerRequestStreamsCurr
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Request Streams on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.8

Field Name : slbHttp3ClientRequestStreamsCurr
Field Type : CounterBasedGauge64
Field Status : current

Description : Current Request Streams on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.7

Field Name : slbHttp3ServerConnPeak
Field Type : CounterBasedGauge64
Field Status : current
Description : Peak HTTP/3 Server Connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.6

Field Name : slbHttp3ClientConnPeak
Field Type : CounterBasedGauge64
Field Status : current
Description : Peak HTTP/3 Client Connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.5

Field Name : slbHttp3ServerConnTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total HTTP/3 Server Connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.4

Field Name : slbHttp3ClientConnTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total HTTP/3 Client Connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.3

Field Name : slbHttp3ServerConnCurr
Field Type : CounterBasedGauge64
Field Status : current
Description : Current HTTP/3 Server Connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.2

Field Name : slbHttp3ClientConnCurr
Field Type : CounterBasedGauge64
Field Status : current
Description : Current HTTP/3 Client Connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.1

Field Name : streamCancelFloodDetected
Field Type : CounterBasedGauge64
Field Status : current
Description : stream cancel flood detected
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.123

Field Name : frameFloodDetected
Field Type : CounterBasedGauge64
Field Status : current
Description : frame flood detected
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.122

Field Name : transactionLimited
Field Type : CounterBasedGauge64
Field Status : current
Description : transaction_limited
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.121

Field Name : endStreamSent

Field Type : CounterBasedGauge64
Field Status : current
Description : End Stream Sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.120

Field Name : endStreamRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : End Stream Recieved
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.119

Field Name : streamFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream Free
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.118

Field Name : streamCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream Create
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.117

Field Name : currentStream
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Streams
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.116

Field Name : http2Rejected
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP2 Rejected
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.115

Field Name : errSentHttp11Required
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Sent - HTTP_1_1_REQUIRED
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.113

Field Name : errSentInadequateSecurity
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Sent - INADEQUATE_SECURITY
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.112

Field Name : errSentYourCalm
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Sent - ENHANCE_YOUR_CALM
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.111

Field Name : errSentConnectErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Sent - CONNECT_ERROR
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.110

Field Name : errSentCompressionErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Sent - COMPRESSION_ERROR
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.109

Field Name : errSentCancel
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Sent - CANCEL
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.108

Field Name : errSentRefusedStream
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Sent - REFUSED_STREAM
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.107

Field Name : errSentFrameSizeErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Sent - FRAME_SIZE_ERROR
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.106

Field Name : errSentStreamClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Sent - STREAM_CLOSED
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.105

Field Name : errSentSettingTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Sent - SETTINGS_TIMEOUT
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.104

Field Name : errSentFlowControl
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Sent - FLOW_CONTROL_ERROR
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.103

Field Name : errSentInternalErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Sent - INTERNAL_ERROR
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.102

Field Name : errSentProtoErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Sent - PROTOCOL_ERROR
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.101

Field Name : errSentTotal
Field Type : CounterBasedGauge64
Field Status : current

Description : Error Rent - Total
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.100

Field Name : errRcvdTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Rcvd - Total
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.99

Field Name : allocFailTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Alloc Fail - Total
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.98

Field Name : emptySettingsRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Empty SETTINGS Frame Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.97

Field Name : settingsAckRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : SETTINGS ACK Frame Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.96

Field Name : priorityFrameSent
Field Type : CounterBasedGauge64
Field Status : current
Description : PRIORITY Frame Sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.95

Field Name : headersFrameSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HEADERS Frame Sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.94

Field Name : dataFrameSent
Field Type : CounterBasedGauge64
Field Status : current
Description : DATA Frame Sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.93

Field Name : continuationFrameSent
Field Type : CounterBasedGauge64
Field Status : current
Description : CONTINUATION Frame Sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.92

Field Name : controlFrameSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Control Frame Sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.91

Field Name : slbHttp2PeakProxy

Field Type : CounterBasedGauge64
Field Status : current
Description : Peak Proxy Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.90

Field Name : totalBytesSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP/2 total bytes sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.89

Field Name : totalBytesReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP/2 total bytes received
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.88

Field Name : dataBytesSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP/2 data bytes sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.87

Field Name : dataBytesReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP/2 data bytes received
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.86

Field Name : headerBytesSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP/2 header bytes sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.85

Field Name : headerBytesReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP/2 header bytes received
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.84

Field Name : controlBytesSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP/2 control frame bytes sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.83

Field Name : controlBytesReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP/2 control frame bytes received
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.82

Field Name : frameHeaderBytesSent
Field Type : CounterBasedGauge64
Field Status : current
Description : frame header bytes sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.81

Field Name : frameHeaderBytesReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : frame header bytes received
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.80

Field Name : invalidWindowUpdate
Field Type : CounterBasedGauge64
Field Status : current
Description : window-update value out of range
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.79

Field Name : invalidSettingValue
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid setting-frame value
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.78

Field Name : trailersNoEndStream
Field Type : CounterBasedGauge64
Field Status : current
Description : trailers not marked as end-of-stream
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.77

Field Name : headersInterleaved
Field Type : CounterBasedGauge64
Field Status : current
Description : headers interleaved on streams
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.76

Field Name : invalidStreamId
Field Type : CounterBasedGauge64
Field Status : current
Description : received invalid stream ID
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.75

Field Name : invalidPushPromise
Field Type : CounterBasedGauge64
Field Status : current
Description : unexpected PUSH_PROMISE frame
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.74

Field Name : pushPromiseFrameSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Push Promise Frame Sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.114

Field Name : headersAfterContinuation
Field Type : CounterBasedGauge64
Field Status : current
Description : headers frame before CONTINUATION was complete
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.73

Field Name : invalidFrameDuringHeaders
Field Type : CounterBasedGauge64
Field Status : current

Description : frame before headers were complete
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.72

Field Name : continuationBeforeHeaders
Field Type : CounterBasedGauge64
Field Status : current
Description : CONTINUATION frame with no headers frame
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.71

Field Name : streamClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : stream closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.70

Field Name : exceedsMaxWindowSizeStream
Field Type : CounterBasedGauge64
Field Status : current
Description : Window Update with increment that results in exceeding max window
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.68

Field Name : zeroWindowSizeOnStream
Field Type : CounterBasedGauge64
Field Status : current
Description : Window Update with zero increment rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.66

Field Name : closedStateUnexpectedFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Unexpected frame received in closed state
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.65

Field Name : halfClosedRemoteStateUnexpectedFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Unexpected frame received in half closed remote state
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.64

Field Name : reservedRemoteStateUnexpectedFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Unexpected frame received in reserved remote state
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.63

Field Name : reservedLocalStateUnexpectedFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Unexpected frame received in reserved local state
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.62

Field Name : idleStateUnexpectedFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Unxpected frame received in idle state
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.61

Field Name : streamsGtMaxConcurStreams

Field Type : CounterBasedGauge64
Field Status : current
Description : Streams greater than max allowed concurrent streams
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.60

Field Name : headerPadlenGtFramePayload
Field Type : CounterBasedGauge64
Field Status : current
Description : Header padlen greater than frame payload size
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.59

Field Name : headerNoStream
Field Type : CounterBasedGauge64
Field Status : current
Description : header no stream
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.58

Field Name : cantAllocateWindowFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Cant allocate WINDOW_UPDATE frame
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.57

Field Name : cantAllocateStream
Field Type : CounterBasedGauge64
Field Status : current
Description : Cant allocate stream
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.56

Field Name : cantAllocatePingFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Cant allocate PING frame
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.55

Field Name : cantAllocateGoawayFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Cant allocate GOAWAY frame
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.54

Field Name : cantAllocateRstFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Cant allocate RST_STREAM frame
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.53

Field Name : buffAllocError
Field Type : CounterBasedGauge64
Field Status : current
Description : Buff alloc error
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.52

Field Name : dataQueueAllocError
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Queue Alloc Error
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.51

Field Name : wrongStreamState
Field Type : CounterBasedGauge64
Field Status : current
Description : Wrong Stream State
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.50

Field Name : badFrameTypeForStreamState
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad frame type for stream state
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.49

Field Name : cantAllocateSettingsFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Cant allocate SETTINGS frame
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.48

Field Name : cantAllocateControlFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Cant allocate control frame
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.47

Field Name : badConnectionPreface
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Connection Preface
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.46

Field Name : inflateHeaderFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Inflate Header Fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.45

Field Name : inflateAllocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : inflate alloc fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.44

Field Name : deflateAllocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : deflate alloc fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.43

Field Name : http11Required
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP1.1 Required
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.42

Field Name : inadequateSecurity
Field Type : CounterBasedGauge64
Field Status : current

Description : inadequate security
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.41

Field Name : enhanceYourCalm
Field Type : CounterBasedGauge64
Field Status : current
Description : enhance your calm error
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.40

Field Name : connectError
Field Type : CounterBasedGauge64
Field Status : current
Description : connect error
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.39

Field Name : compressionError
Field Type : CounterBasedGauge64
Field Status : current
Description : compression error
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.38

Field Name : cancel
Field Type : CounterBasedGauge64
Field Status : current
Description : cancel
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.37

Field Name : refusedStream
Field Type : CounterBasedGauge64
Field Status : current
Description : Refused Stream
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.36

Field Name : frameSizeError
Field Type : CounterBasedGauge64
Field Status : current
Description : Frame Size Error
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.35

Field Name : settingsTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : Settings Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.34

Field Name : flowControlError
Field Type : CounterBasedGauge64
Field Status : current
Description : Flow Control Error
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.33

Field Name : dataNoStream
Field Type : CounterBasedGauge64
Field Status : current
Description : DATA Frame Rcvd on non-existent stream
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.32

Field Name : errorMaxInvalidStream

Field Type : CounterBasedGauge64
Field Status : current
Description : Max Invalid Stream Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.31

Field Name : invalidFrameSize
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid Frame Size Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.29

Field Name : splitBuffFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Splitting Buffer Failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.28

Field Name : proxyAllocError
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP2 Proxy alloc Error
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.27

Field Name : internalError
Field Type : CounterBasedGauge64
Field Status : current
Description : Internal Error
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.26

Field Name : protocolError
Field Type : CounterBasedGauge64
Field Status : current
Description : Protocol Error
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.25

Field Name : dataToApp
Field Type : CounterBasedGauge64
Field Status : current
Description : DATA Frame to HTTP
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.24

Field Name : headerToApp
Field Type : CounterBasedGauge64
Field Status : current
Description : HEADER Frame to HTTP
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.23

Field Name : goawayFrameSent
Field Type : CounterBasedGauge64
Field Status : current
Description : GOAWAY Frame Sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.22

Field Name : rstFrameSent
Field Type : CounterBasedGauge64
Field Status : current
Description : RST_STREAM Frame Sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.21

Field Name : windowUpdateFrameSent
Field Type : CounterBasedGauge64
Field Status : current
Description : WINDOW_UPDATE Frame Sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.20

Field Name : pingFrameSent
Field Type : CounterBasedGauge64
Field Status : current
Description : PING Frame Sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.19

Field Name : emptySettingsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Empty SETTINGS Frame Sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.18

Field Name : settingsAckSent
Field Type : CounterBasedGauge64
Field Status : current
Description : SETTINGS ACK Frame Sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.17

Field Name : settingsFrameSent
Field Type : CounterBasedGauge64
Field Status : current
Description : SETTINGS Frame Sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.16

Field Name : connectionPrefaceSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Connection preface sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.15

Field Name : unknownFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Unknown Frame Recvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.14

Field Name : dataFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : DATA Frame Recvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.13

Field Name : priorityFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : PRIORITY Frame Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.12

Field Name : goawayFrame
Field Type : CounterBasedGauge64
Field Status : current

Description : GOAWAY Frame Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.11

Field Name : pingFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : PING Frame Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.10

Field Name : windowUpdateFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : WINDOW_UPDATE Frame Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.9

Field Name : settingsFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : SETTINGS Frame Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.8

Field Name : rstFrameRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : RST_STREAM Frame Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.7

Field Name : continuationFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : CONTINUATION Frame Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.6

Field Name : headersFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : HEADERS Frame Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.5

Field Name : controlFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Control Frame Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.4

Field Name : connectionPrefaceRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Connection preface rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.3

Field Name : slbHttp2TotalProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Proxy Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.2

Field Name : slbHttp2CurrProxy

Field Type : CounterBasedGauge64
Field Status : current
Description : Curr Proxy Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.1

Field Name : sessionClose
Field Type : CounterBasedGauge64
Field Status : current
Description : Session close
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.84

Field Name : httpDataStreamClose
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP data stream already closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.83

Field Name : httpHdrStreamClose
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP header stream already closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.82

Field Name : httpErrStreamClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP error stream already closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.81

Field Name : httpCloseStreamClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP close stream already closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.80

Field Name : finStreamClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP FIN stream already closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.79

Field Name : newStreamSessionDel
Field Type : CounterBasedGauge64
Field Status : current
Description : New Stream after Session delete
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.78

Field Name : sessionNeedsRequeue
Field Type : CounterBasedGauge64
Field Status : current
Description : Session needs requeue
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.77

Field Name : closeStreamNotHttpProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Close Stream not http-proxy
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.76

Field Name : httpDataStreamNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP data stream not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.75

Field Name : httpDataSessionClose
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP data session close
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.74

Field Name : headerCompressFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Header compress fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.73

Field Name : compressCtxAllocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Compression context allocation fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.72

Field Name : headerAfterSessionClose
Field Type : CounterBasedGauge64
Field Status : current
Description : Header after session close
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.71

Field Name : invalidVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid version
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.70

Field Name : invalidFrameSize
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid frame size
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.69

Field Name : dataOnClosedStream
Field Type : CounterBasedGauge64
Field Status : current
Description : Data on closed stream
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.68

Field Name : unknownControlFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Unknown control frame
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.67

Field Name : invalidWindowSize
Field Type : CounterBasedGauge64
Field Status : current

Description : Invalid window size
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.66

Field Name : windowNoStream
Field Type : CounterBasedGauge64
Field Status : current
Description : Window update no stream found
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.65

Field Name : clientRstNostream
Field Type : CounterBasedGauge64
Field Status : current
Description : Close RST stream not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.64

Field Name : synReplyAlrRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN reply already received
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.63

Field Name : synUnidir
Field Type : CounterBasedGauge64
Field Status : current
Description : Unidirectional SYN
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.62

Field Name : synStreamExistOrEven
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream already exists
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.61

Field Name : streamLtPrev
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream id less than previous
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.60

Field Name : synAfterGoaway
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN after goaway
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.59

Field Name : decompressFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Decompress fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.58

Field Name : nameValueNoMustHave
Field Type : CounterBasedGauge64
Field Status : current
Description : Name value no must have
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.57

Field Name : nameValueTrasnferEncod

Field Type : CounterBasedGauge64
Field Status : current
Description : Name value transfer encoding
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.56

Field Name : nameValueProxyConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Name value proxy-connection
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.55

Field Name : nameValueKeepalive
Field Type : CounterBasedGauge64
Field Status : current
Description : Name value keep alive
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.54

Field Name : nameValueConnection
Field Type : CounterBasedGauge64
Field Status : current
Description : Name value connection
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.53

Field Name : nameValueInvalidHttpVer
Field Type : CounterBasedGauge64
Field Status : current
Description : Name value invalid http version
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.52

Field Name : nameValueZeroLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Name value zero name length
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.51

Field Name : nameValueTotalLenEx
Field Type : CounterBasedGauge64
Field Status : current
Description : Name value total length exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.50

Field Name : requestHeaderAllocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Request/Header allocation fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.49

Field Name : httpConnAllocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP connection allocation fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.48

Field Name : streamAllocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream alloc fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.47

Field Name : maxConcurrentStreamLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : Max concurrent stream limit
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.46

Field Name : closeSessionAlreadyClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : Closing closed session
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.45

Field Name : closeStreamSessionClose
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream close session close
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.44

Field Name : closeStreamAlreadyClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : Closing closed stream
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.43

Field Name : closeStreamStreamNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Close stream stream not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.42

Field Name : closeStreamSessionNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Close stream session not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.41

Field Name : streamFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream found
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.40

Field Name : serverRstCloseStream
Field Type : CounterBasedGauge64
Field Status : current
Description : Server RST close stream
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.39

Field Name : finCloseSession
Field Type : CounterBasedGauge64
Field Status : current
Description : FIN close session
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.38

Field Name : ctxAllocFail
Field Type : CounterBasedGauge64
Field Status : current

Description : Context alloc fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.37

Field Name : dataCbNoTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : Data callback no tuple
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.36

Field Name : estCbNoTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : Est callback no tuple
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.35

Field Name : dataNoStreamGoawayClose
Field Type : CounterBasedGauge64
Field Status : current
Description : Data no stream and no goaway and close session
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.34

Field Name : dataNoStreamNoGoaway
Field Type : CounterBasedGauge64
Field Status : current
Description : Data no stream and no goaway
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.33

Field Name : dataNoStream
Field Type : CounterBasedGauge64
Field Status : current
Description : Data no stream found
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.32

Field Name : dataFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Data frame received
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.31

Field Name : pingFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Ping frame received
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.30

Field Name : windowFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Window update frame received
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.29

Field Name : settingsFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Setting frame received
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.28

Field Name : headersFrame

Field Type : CounterBasedGauge64
Field Status : current
Description : Headers frame received
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.27

Field Name : synReplyFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN reply frame received
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.26

Field Name : synFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN stream frame received
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.25

Field Name : controlFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Control frame received
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.24

Field Name : slbSpdyProxySessionErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Session err
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.23

Field Name : streamErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream err
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.22

Field Name : streamClose
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream close
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.21

Field Name : slbSpdyProxyServerFin
Field Type : CounterBasedGauge64
Field Status : current
Description : Server FIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.20

Field Name : slbSpdyProxyClientFin
Field Type : CounterBasedGauge64
Field Status : current
Description : Client FIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.19

Field Name : streamNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : STREAM not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.18

Field Name : pingSent
Field Type : CounterBasedGauge64
Field Status : current
Description : PING sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.17

Field Name : deflateCtx
Field Type : CounterBasedGauge64
Field Status : current
Description : Deflate context
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.16

Field Name : inflateCtx
Field Type : CounterBasedGauge64
Field Status : current
Description : Inflate context
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.15

Field Name : tcpErr
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP sock error
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.14

Field Name : serverGoaway
Field Type : CounterBasedGauge64
Field Status : current
Description : Server GOAWAY sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.13

Field Name : clientGoaway
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.12

Field Name : serverRst
Field Type : CounterBasedGauge64
Field Status : current
Description : Server RST sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.11

Field Name : clientRst
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.10

Field Name : totalStreamSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : Streams(succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.9

Field Name : totalStream
Field Type : CounterBasedGauge64
Field Status : current

Description : Total Streams
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.8

Field Name : currStream
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr Streams
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.7

Field Name : totalV3Proxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Version 3 Streams
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.6

Field Name : totalV2Proxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Version 2 Streams
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.5

Field Name : totalHttpProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Total HTTP Proxy Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.4

Field Name : currHttpProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr HTTP Proxy Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.3

Field Name : slbSpdyProxyTotalProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Proxy Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.2

Field Name : slbSpdyProxyCurrProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr Proxy Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.1

Field Name : serverTlsConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Server TLS conn
OID : 1.3.6.1.4.1.22610.2.4.10.108.27.1.14

Field Name : clientTlsConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Client TLS conn
OID : 1.3.6.1.4.1.22610.2.4.10.108.27.1.13

Field Name : targetSwitching

Field Type : CounterBasedGauge64
Field Status : current
Description : Target ID switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.27.1.12

Field Name : senderSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : Sender ID switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.27.1.11

Field Name : defaultSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : Default switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.27.1.10

Field Name : insertClientip
Field Type : CounterBasedGauge64
Field Status : current
Description : Insert client IP
OID : 1.3.6.1.4.1.22610.2.4.10.108.27.1.9

Field Name : serverErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Server fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.27.1.7

Field Name : clientErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Client fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.27.1.6

Field Name : slbFixSnatFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Source NAT failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.27.1.5

Field Name : slbFixNoroute
Field Type : CounterBasedGauge64
Field Status : current
Description : No route failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.27.1.4

Field Name : slbFixSvrselFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Server selection failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.27.1.3

Field Name : slbFixTotalProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Total proxy conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.27.1.2

Field Name : slbFixCurrProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Current proxy conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.27.1.1

Field Name : incAflowLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : Inc aFlow limit
OID : 1.3.6.1.4.1.22610.2.4.10.108.26.1.11

Field Name : reuseServerIdleConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Reuse idle server conn
OID : 1.3.6.1.4.1.22610.2.4.10.108.26.1.10

Field Name : openNewServerConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Open new server conn
OID : 1.3.6.1.4.1.22610.2.4.10.108.26.1.9

Field Name : errorResumeConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Resume conn by error
OID : 1.3.6.1.4.1.22610.2.4.10.108.26.1.8

Field Name : retryResumeConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Resume conn by retry
OID : 1.3.6.1.4.1.22610.2.4.10.108.26.1.7

Field Name : tryToResumeConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Resume conn by trying
OID : 1.3.6.1.4.1.22610.2.4.10.108.26.1.6

Field Name : timerResumeConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Resume conn by timer
OID : 1.3.6.1.4.1.22610.2.4.10.108.26.1.5

Field Name : eventResumeConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Resume conn by event
OID : 1.3.6.1.4.1.22610.2.4.10.108.26.1.4

Field Name : resumeConn
Field Type : CounterBasedGauge64
Field Status : current

Description : Resume connection
OID : 1.3.6.1.4.1.22610.2.4.10.108.26.1.3

Field Name : pauseConnFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Pause connection fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.26.1.2

Field Name : pauseConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Pause connection
OID : 1.3.6.1.4.1.22610.2.4.10.108.26.1.1

Field Name : currentHttp2ConnInThePool
Field Type : CounterBasedGauge64
Field Status : current
Description : Current http2 conn in the pool
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.19

Field Name : currentHttp1ConnInThePool
Field Type : CounterBasedGauge64
Field Status : current
Description : Current http1 conn in the pool
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.18

Field Name : zeroPconnBindValue
Field Type : CounterBasedGauge64
Field Status : current
Description : Zero current pconn bind counter value
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.17

Field Name : zeroPconnValue
Field Type : CounterBasedGauge64
Field Status : current
Description : Zero current pconn counter value
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.16

Field Name : notRemoveFromRport
Field Type : CounterBasedGauge64
Field Status : current
Description : Not remove from list
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.15

Field Name : slbConnectionReuseResumeConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Resume request
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.14

Field Name : slbConnectionReusePauseConnFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Pause request fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.13

Field Name : slbConnectionReusePauseConn

Field Type : CounterBasedGauge64
Field Status : current
Description : Pause request
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.12

Field Name : unboundDataRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : Unbound data rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.11

Field Name : missResp
Field Type : CounterBasedGauge64
Field Status : current
Description : Missed resp
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.10

Field Name : longResp
Field Type : CounterBasedGauge64
Field Status : current
Description : Long resp
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.9

Field Name : delayUnbind
Field Type : CounterBasedGauge64
Field Status : current
Description : Delayed unbind
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.8

Field Name : ntermiErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total terminated by err
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.7

Field Name : ntermi
Field Type : CounterBasedGauge64
Field Status : current
Description : Total terminated
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.6

Field Name : nestab
Field Type : CounterBasedGauge64
Field Status : current
Description : Total established
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.5

Field Name : nunbind
Field Type : CounterBasedGauge64
Field Status : current
Description : Total unbind
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.4

Field Name : nbind
Field Type : CounterBasedGauge64
Field Status : current
Description : Total bind
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.3

Field Name : currentActive
Field Type : CounterBasedGauge64
Field Status : current
Description : Active persist
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.2

Field Name : currentOpen
Field Type : CounterBasedGauge64
Field Status : current
Description : Open persist
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.1

Field Name : portOutOfRange
Field Type : CounterBasedGauge64
Field Status : current
Description : Drop Data Port out of range
OID : 1.3.6.1.4.1.22610.2.4.10.108.24.1.2

Field Name : slbFtpDataSessionNum
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Data Sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.24.1.1

Field Name : slbVirtualServerPortSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1

Field Name : slbVirtualServerPortSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1

Field Name : dnsrrlNxExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Response-Rate-Limiting NX Responses Exceed Limit
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.101

Field Name : http2ClientIdleTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP2 Client Idle Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.100

Field Name : http1ClientIdleTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP1 Client Idle Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.99

Field Name : dnsrrlTotalTc
Field Type : CounterBasedGauge64
Field Status : current

Description : DNS Response-Rate-Limiting Total Responses Replied With Truncated
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.98

Field Name : compressionMissTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of requests NOT compressed
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.97

Field Name : compressionHitTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of requests compressed
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.96

Field Name : compressionMissBr
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of requests NOT compressed with brotli
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.95

Field Name : compressionHitBr
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of requests compressed with brotli
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.94

Field Name : compressionBytesAfterTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Data out of compression engine
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.93

Field Name : compressionBytesBeforeTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Data into compression engine
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.92

Field Name : compressionBytesAfterBr
Field Type : CounterBasedGauge64
Field Status : current
Description : Data out of brotli compression engine
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.91

Field Name : compressionBytesBeforeBr
Field Type : CounterBasedGauge64
Field Status : current
Description : Data into brotli compression engine
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.90

Field Name : dnsRpzTriggerNsName
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS RPZ Trigger NS Name
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.89

Field Name : dnsRpzTriggerQname

Field Type : CounterBasedGauge64
Field Status : current
Description : DNS RPZ Trigger Qname IP
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.88

Field Name : dnsRpzTriggerNsIp
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS RPZ Trigger NS IP
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.87

Field Name : dnsRpzTriggerRespIp
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS RPZ Trigger Response IP
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.86

Field Name : dnsRpzTriggerClientIp
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS RPZ Trigger Client IP
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.85

Field Name : dnsRpzActionLocalData
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS RPZ Action Local Data
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.84

Field Name : dnsRpzActionNodata
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS RPZ Action NODATA
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.83

Field Name : dnsRpzActionNxdomain
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS RPZ Action NXDOMAIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.82

Field Name : dnsRpzActionTcpOnly
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS RPZ Action TCP Only
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.81

Field Name : dnsRpzActionPassThru
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS RPZ Action Pass Through
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.80

Field Name : dnsRpzActionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS RPZ Action Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.79

Field Name : dnsFilterClassOthersDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Filter Class OTHERS Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.78

Field Name : dnsFilterClassAnyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Filter Class ANY Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.77

Field Name : dnsFilterClassNoneDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Filter Class NONE Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.76

Field Name : dnsFilterClassHesiodDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Filter Class HESIOD Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.75

Field Name : dnsFilterClassChaosDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Filter Class CHAOS Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.74

Field Name : dnsFilterClassInternetDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Filter Class INTERNET Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.73

Field Name : dnsFilterTypeOthersDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Filter Type OTHERS Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.72

Field Name : dnsFilterTypeAnyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Filter Type Any Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.71

Field Name : dnsFilterTypeTxtDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Filter Type TXT Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.70

Field Name : dnsFilterTypeSoaDrop
Field Type : CounterBasedGauge64
Field Status : current

Description : DNS Filter Type SOA Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.69

Field Name : dnsFilterTypePtrDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Filter Type PTR Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.68

Field Name : dnsFilterTypeSrvDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Filter Type SRV Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.67

Field Name : dnsFilterTypeNsDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Filter Type NS Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.66

Field Name : dnsFilterTypeMxDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Filter Type MX Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.65

Field Name : dnsFilterTypeCnameDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Filter Type CNAME Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.64

Field Name : dnsFilterTypeAaaaDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Filter Type AAAA Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.63

Field Name : dnsFilterTypeADrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Filter Type A Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.62

Field Name : totalDnsFilterClassDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total DNS Filter Class Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.61

Field Name : totalDnsFilterTypeDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total DNS Filter Type Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.60

Field Name : ipOnlyLbRevPkts

Field Type : CounterBasedGauge64
Field Status : current
Description : IP-Only-LB Packets processed in reverse direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.59

Field Name : ipOnlyLbFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : IP-Only-LB Packets processed in forward direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.58

Field Name : ipOnlyLbRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : IP-Only-LB Bytes processed in reverse direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.57

Field Name : ipOnlyLbFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : IP-Only-LB Bytes processed in forward direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.56

Field Name : dynamicMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : dynamic memory (bytes) used by the vport(alloc-free)
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.55

Field Name : dynamicMemoryFree
Field Type : CounterBasedGauge64
Field Status : current
Description : dynamic memory (bytes) allocated by the vport
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.54

Field Name : dynamicMemoryAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : dynamic memory (bytes) allocated by the vport
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.53

Field Name : throughputBitsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : Throughput in bits/sec
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.52

Field Name : dnsrrlBadFqdn
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Response-Rate-Limiting Bad FQDN
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.51

Field Name : dnsrrlTotalSlipped
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Response-Rate-Limiting Total Responses Slipped
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.50

Field Name : dnsrrlTotalDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Response-Rate-Limiting Total Responses Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.49

Field Name : dnsrrlTotalAllowed
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Response-Rate-Limiting Total Responses Allowed
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.48

Field Name : currRespRate
Field Type : CounterBasedGauge64
Field Status : current
Description : Current response rate
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.47

Field Name : totalRespSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : Total successful responses
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.46

Field Name : totalResp
Field Type : CounterBasedGauge64
Field Status : current
Description : Total response
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.45

Field Name : currResp
Field Type : CounterBasedGauge64
Field Status : current
Description : Current response
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.44

Field Name : currReqRate
Field Type : CounterBasedGauge64
Field Status : current
Description : Current request rate
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.43

Field Name : totalRevPktsOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets processed in reverse direction (outbound)
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.42

Field Name : totalRevBytesOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes processed in reverse direction (outbound)
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.41

Field Name : totalFwdPktsOut
Field Type : CounterBasedGauge64
Field Status : current

Description : Packets processed in forward direction (outbound)
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.40

Field Name : totalFwdBytesOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes processed in forward direction (outbound)
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.39

Field Name : outLatency
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Latency at Thunder
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.38

Field Name : inLatency
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Latency at Thunder
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.37

Field Name : backendTimeToLastByte
Field Type : CounterBasedGauge64
Field Status : current
Description : Backend Time from Request to Response Last Byte
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.36

Field Name : backendTimeToFirstByte
Field Type : CounterBasedGauge64
Field Status : current
Description : Backend Time from Request to Response First Byte
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.35

Field Name : totalSslConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.34

Field Name : currSslConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Current SSL connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.33

Field Name : locConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Geo-location Connection count
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.32

Field Name : locDeny
Field Type : CounterBasedGauge64
Field Status : current
Description : Geo-location Deny count
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.31

Field Name : locPermit

Field Type : CounterBasedGauge64
Field Status : current
Description : Geo-location Permit count
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.30

Field Name : slowestRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : Slowest response time
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.29

Field Name : fastestRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : Fastest response time
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.28

Field Name : lastRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : Last response time
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.27

Field Name : currConnRate
Field Type : CounterBasedGauge64
Field Status : current
Description : Current connection rate
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.26

Field Name : slbSrvPortPeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Peak connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.25

Field Name : totalReqSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : Total successful requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.24

Field Name : slbSrvPortTotalReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Total requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.23

Field Name : currReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Current requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.22

Field Name : compressionMissTemplateExclusion
Field Type : CounterBasedGauge64
Field Status : current
Description : Compression miss template exclusion
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.21

Field Name : compressionMissNoClient
Field Type : CounterBasedGauge64
Field Status : current
Description : Compression miss no client
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.20

Field Name : compressionMiss
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of requests NOT compressed
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.19

Field Name : compressionHit
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of requests compressed
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.18

Field Name : compressionBytesAfter
Field Type : CounterBasedGauge64
Field Status : current
Description : Data out of gzip compression engine
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.17

Field Name : compressionBytesBefore
Field Type : CounterBasedGauge64
Field Status : current
Description : Data into gzip compression engine
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.16

Field Name : esTotalFailureActions
Field Type : CounterBasedGauge64
Field Status : current
Description : Total failure actions
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.15

Field Name : totalMfDnsPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Total MF DNS packets
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.14

Field Name : totalDnsPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Total DNS packets processed
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.13

Field Name : totalRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets processed in reverse direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.12

Field Name : totalRevBytes
Field Type : CounterBasedGauge64
Field Status : current

Description : Bytes processed in reverse direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.11

Field Name : totalFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets processed in forward direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.10

Field Name : totalFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes processed in forward direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.9

Field Name : slbSrvPortTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total connections established
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.8

Field Name : totalTcpConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP connections established
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.7

Field Name : totalL7Conn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total L7 connections established
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.6

Field Name : totalL4Conn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total L4 connections established
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.5

Field Name : slbSrvPortCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Current established connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.4

Field Name : protocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.3

Field Name : portNumber
Field Type : INTEGER
Field Status : current
Description : Port
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.2

Field Name : name

Field Type : String
Field Status : current
Description : SLB Virtual Server Name
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.1

Field Name : slbServerGroupSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.87.1.1

Field Name : slbServerGroupSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.87.1.1.1

Field Name : slbServerCurrRate
Field Type : CounterBasedGauge64
Field Status : current
Description : Current established connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.87.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : server-group name
OID : 1.3.6.1.4.1.22610.2.4.10.108.87.1.1.1.1

Field Name : slbServiceGroupSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.1.1

Field Name : slbServiceGroupSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.1.1.1

Field Name : serviceCurrConnOverflow
Field Type : CounterBasedGauge64
Field Status : current
Description : Current connection counter overflow count
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.1.1.1.13

Field Name : serviceResp5xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Group response 5xx count
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.1.1.1.12

Field Name : serviceResp4xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Group response 4xx count
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.1.1.1.11

Field Name : serviceResp3xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Group response 3xx count
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.1.1.1.10

Field Name : serviceResp2xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Group response 2xx count
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.1.1.1.9

Field Name : serviceRespCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Group response count
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.1.1.1.8

Field Name : serviceReqCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Group request count
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.1.1.1.7

Field Name : serviceUnhealthyHost
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Group unhealthy host count
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.1.1.1.6

Field Name : serviceHealthyHost
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Group healthy host count
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.1.1.1.5

Field Name : servicePeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Peak connection count for the Service Group
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.1.1.1.4

Field Name : serverSelectionFailReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Resets sent out for Service selection failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.1.1.1.3

Field Name : serverSelectionFailDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Drops due to Service selection failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.1.1.1.2

Field Name : slbServiceGroupName
Field Type : String
Field Status : current

Description : SLB Service Name
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.1.1.1.1

Field Name : slbServiceGroupMemberSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1

Field Name : slbServiceGroupMemberSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1

Field Name : stateFlaps
Field Type : CounterBasedGauge64
Field Status : current
Description : State flaps count
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.23

Field Name : currConnOverflow
Field Type : CounterBasedGauge64
Field Status : current
Description : Current connection counter overflow count
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.22

Field Name : totalSslConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.21

Field Name : currSslConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Current SSL connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.20

Field Name : slbServiceGroupMemberSlowestRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : Slowest response time
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.19

Field Name : slbServiceGroupMemberFastestRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : Fastest response time
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.18

Field Name : slbServiceGroupMemberResponseTime
Field Type : CounterBasedGauge64
Field Status : current
Description : Response time
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.17

Field Name : slbServiceGroupMemberPeakConn

Field Type : CounterBasedGauge64
Field Status : current
Description : Peak connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.16

Field Name : slbServiceGroupMemberTotalReqSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : Total requests successful
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.15

Field Name : slbServiceGroupMemberTotalReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Total requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.14

Field Name : slbServiceGroupMemberCurrReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Current requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.13

Field Name : slbServiceGroupMemberTotalRevPktsInspectedStatusCodeNon5xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Total reverse packets inspected status code non 5xx
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.12

Field Name : slbServiceGroupMemberTotalRevPktsInspectedStatusCode2xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Total reverse packets inspected status code 2xx
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.11

Field Name : slbServiceGroupMemberTotalRevPktsInspected
Field Type : CounterBasedGauge64
Field Status : current
Description : Total reverse packets inspected
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.10

Field Name : slbServiceGroupMemberTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total established connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.9

Field Name : slbServiceGroupMemberTotalRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets processed in reverse direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.8

Field Name : slbServiceGroupMemberTotalRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes processed in reverse direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.7

Field Name : slbServiceGroupMemberTotalFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets processed in forward direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.6

Field Name : slbServiceGroupMemberTotalFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes processed in forward direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.5

Field Name : currConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Current established connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.4

Field Name : slbServiceGroupMemberPort
Field Type : INTEGER
Field Status : current
Description : Port number
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.3

Field Name : slbServiceGroupMemberName
Field Type : String
Field Status : current
Description : Member name
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.2

Field Name : slbServiceGroupName
Field Type : String
Field Status : current
Description : SLB Service Name
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.1

Field Name : slbServerSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1

Field Name : slbServerSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1

Field Name : ipOnlyLbRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : IP-Only-LB Packets processed in reverse direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.18

Field Name : ipOnlyLbFwdPkts
Field Type : CounterBasedGauge64
Field Status : current

Description : IP-Only-LB Packets processed in forward direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.17

Field Name : ipOnlyLbRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : IP-Only-LB Bytes processed in reverse direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.16

Field Name : ipOnlyLbFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : IP-Only-LB Bytes processed in forward direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.15

Field Name : totalRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets processed in reverse direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.14

Field Name : totalFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets processed in forward direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.13

Field Name : totalRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes processed in reverse direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.12

Field Name : totalFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes processed in forward direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.11

Field Name : totalSslConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL connections established
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.10

Field Name : currSslConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Current SSL connections established
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.9

Field Name : totalReqSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Requests succeeded
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.8

Field Name : totalReq

Field Type : CounterBasedGauge64
Field Status : current
Description : Total Requests processed
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.7

Field Name : slbServerPeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Peak number of established connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.6

Field Name : slbServerRevPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Packets Processed
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.5

Field Name : slbServerFwdPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Packets Processed
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.4

Field Name : slbServerTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total established connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.3

Field Name : slbServerCurrRate
Field Type : CounterBasedGauge64
Field Status : current
Description : Current established connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.2

Field Name : slbServerName
Field Type : String
Field Status : current
Description : Server Name
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.1

Field Name : slbTemplateServerSshSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.17.1.1

Field Name : slbTemplateServerSshSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.17.1.1.1

Field Name : forwardingErrors
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.17.1.1.1.4

Field Name : failedHandshakes
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.17.1.1.1.3

Field Name : successfulHandshakes
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.17.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Server SSH Template Name
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.17.1.1.1.1

Field Name : slbTemplatePolicySTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.13.1.1

Field Name : slbTemplatePolicySEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.13.1.1.1

Field Name : expClientHelloNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Expected Client HELLO requests not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.13.1.1.1.11

Field Name : fwdPolicySourceMatchNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward-policy requests without matching source rule
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.13.1.1.1.10

Field Name : fwdPolicyPolicyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of forward-policy requests dropped
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.13.1.1.1.9

Field Name : fwdPolicyForwardToProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of forward-policy requests forwarded to proxy
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.13.1.1.1.8

Field Name : fwdPolicyForwardToServiceGroup
Field Type : CounterBasedGauge64
Field Status : current

Description : Number of forward-policy requests forwarded to service group
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.13.1.1.1.7

Field Name : fwdPolicyForwardToInternet
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of forward-policy requests forwarded to internet
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.13.1.1.1.6

Field Name : fwdPolicyHits
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of forward-policy requests for this policy template
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.13.1.1.1.5

Field Name : fwdPolicySnatFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward-policy source-nat translation failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.13.1.1.1.4

Field Name : fwdPolicyDnsOutstanding
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward-policy current DNS outstanding requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.13.1.1.1.3

Field Name : fwdPolicyDnsUnresolved
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward-policy unresolved DNS queries
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.13.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Policy template name
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.13.1.1.1.1

Field Name : slbTemplateClientSshSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.5.1.1

Field Name : slbTemplateClientSshSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.5.1.1.1

Field Name : forwardingErrors
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.5.1.1.1.4

Field Name : failedHandshakes

Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.5.1.1.1.3

Field Name : successfulHandshakes
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.5.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Client SSH Template Name
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.5.1.1.1.1

Field Name : slbTemplateClientSslSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1

Field Name : slbTemplateClientSslSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1

Field Name : malicious
Field Type : CounterBasedGauge64
Field Status : current
Description : Malicious level(1-20)
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.98

Field Name : suspicious
Field Type : CounterBasedGauge64
Field Status : current
Description : Suspicious level(21-40)
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.97

Field Name : moderateRisk
Field Type : CounterBasedGauge64
Field Status : current
Description : Moderate-risk level(41-60)
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.96

Field Name : lowRisk
Field Type : CounterBasedGauge64
Field Status : current
Description : Low-risk level(61-80)
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.95

Field Name : trustworthy
Field Type : CounterBasedGauge64
Field Status : current
Description : Trustworthy level(81-100)
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.94

Field Name : otherCategory
Field Type : CounterBasedGauge64
Field Status : current
Description : other category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.93

Field Name : uncategorised
Field Type : CounterBasedGauge64
Field Status : current
Description : uncategorised
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.92

Field Name : illegalPornography
Field Type : CounterBasedGauge64
Field Status : current
Description : illegal pornography eg. child sexual abuse
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.91

Field Name : nudityArtistic
Field Type : CounterBasedGauge64
Field Status : current
Description : artistic nudity
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.90

Field Name : generativeAi
Field Type : CounterBasedGauge64
Field Status : current
Description : generative ai category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.89

Field Name : lowThcCannabisProducts
Field Type : CounterBasedGauge64
Field Status : current
Description : low-thc cannabis products
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.88

Field Name : dnsOverHttps
Field Type : CounterBasedGauge64
Field Status : current
Description : dns over https category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.87

Field Name : selfHarm
Field Type : CounterBasedGauge64
Field Status : current
Description : self harm category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.86

Field Name : dummyItem
Field Type : CounterBasedGauge64
Field Status : current
Description : dummy item category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.85

Field Name : foodAndDining
Field Type : CounterBasedGauge64
Field Status : current

Description : food and dining category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.84

Field Name : webHostingSites
Field Type : CounterBasedGauge64
Field Status : current
Description : web hosting sites category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.83

Field Name : motorVehicles
Field Type : CounterBasedGauge64
Field Status : current
Description : motor vehicles category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.82

Field Name : recreationAndHobbies
Field Type : CounterBasedGauge64
Field Status : current
Description : recreation and hobbies category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.81

Field Name : fashionAndBeauty
Field Type : CounterBasedGauge64
Field Status : current
Description : fashion and beauty category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.80

Field Name : imageAndVideoSearch
Field Type : CounterBasedGauge64
Field Status : current
Description : image and video search category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.79

Field Name : privateIPAddresses
Field Type : CounterBasedGauge64
Field Status : current
Description : private IP addresses category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.78

Field Name : alcoholAndTobacco
Field Type : CounterBasedGauge64
Field Status : current
Description : alcohol and tobacco category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.77

Field Name : parkedDomains
Field Type : CounterBasedGauge64
Field Status : current
Description : parked domains category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.76

Field Name : dynamicallyGeneratedContent
Field Type : CounterBasedGauge64
Field Status : current
Description : dynamically generated content category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.75

Field Name : openHTTPProxies

Field Type : CounterBasedGauge64
Field Status : current
Description : open HTTP proxies category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.74

Field Name : unconfirmedSPAMSources
Field Type : CounterBasedGauge64
Field Status : current
Description : unconfirmed SPAM sources category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.73

Field Name : spamUrlHits
Field Type : CounterBasedGauge64
Field Status : current
Description : SPAM URLs category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.72

Field Name : confirmedSPAMSources
Field Type : CounterBasedGauge64
Field Status : current
Description : confirmed SPAM sources category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.71

Field Name : healthAndMedicine
Field Type : CounterBasedGauge64
Field Status : current
Description : health and medicine category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.70

Field Name : abortion
Field Type : CounterBasedGauge64
Field Status : current
Description : abortion category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.69

Field Name : botNets
Field Type : CounterBasedGauge64
Field Status : current
Description : bot nets category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.68

Field Name : internetCommunications
Field Type : CounterBasedGauge64
Field Status : current
Description : internet communications category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.67

Field Name : cdnHits
Field Type : CounterBasedGauge64
Field Status : current
Description : content delivery networks category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.66

Field Name : illegal
Field Type : CounterBasedGauge64
Field Status : current
Description : illegal category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.65

Field Name : newsAndMedia
Field Type : CounterBasedGauge64
Field Status : current
Description : news and media category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.64

Field Name : nudity
Field Type : CounterBasedGauge64
Field Status : current
Description : nudity category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.63

Field Name : government
Field Type : CounterBasedGauge64
Field Status : current
Description : government category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.62

Field Name : music
Field Type : CounterBasedGauge64
Field Status : current
Description : music category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.61

Field Name : spywareAndAdware
Field Type : CounterBasedGauge64
Field Status : current
Description : spyware and adware category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.60

Field Name : proxyAvoidAndAnonymizers
Field Type : CounterBasedGauge64
Field Status : current
Description : proxy avoid and anonymizers category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.59

Field Name : phishingAndOtherFraud
Field Type : CounterBasedGauge64
Field Status : current
Description : phishing and other fraud category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.58

Field Name : malwareSites
Field Type : CounterBasedGauge64
Field Status : current
Description : malware sites category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.57

Field Name : webBasedEmail
Field Type : CounterBasedGauge64
Field Status : current
Description : web based email category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.56

Field Name : gross
Field Type : CounterBasedGauge64
Field Status : current

Description : gross category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.55

Field Name : cheating
Field Type : CounterBasedGauge64
Field Status : current
Description : cheating category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.54

Field Name : webAdvertisements
Field Type : CounterBasedGauge64
Field Status : current
Description : web advertisements category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.53

Field Name : internetPortals
Field Type : CounterBasedGauge64
Field Status : current
Description : internet portals category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.52

Field Name : searchEngines
Field Type : CounterBasedGauge64
Field Status : current
Description : search engines category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.51

Field Name : keyloggersAndMonitoring
Field Type : CounterBasedGauge64
Field Status : current
Description : keyloggers and monitoring category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.50

Field Name : violence
Field Type : CounterBasedGauge64
Field Status : current
Description : violence category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.49

Field Name : personalStorage
Field Type : CounterBasedGauge64
Field Status : current
Description : personal storage category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.48

Field Name : hateAndRacism
Field Type : CounterBasedGauge64
Field Status : current
Description : hate and racism category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.47

Field Name : kids
Field Type : CounterBasedGauge64
Field Status : current
Description : kids category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.46

Field Name : questionable

Field Type : CounterBasedGauge64
Field Status : current
Description : questionable category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.45

Field Name : swimsuitsAndIntimateApparel
Field Type : CounterBasedGauge64
Field Status : current
Description : swimsuits and intimate apparel category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.44

Field Name : sports
Field Type : CounterBasedGauge64
Field Status : current
Description : sports category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.43

Field Name : onlineGreetingCards
Field Type : CounterBasedGauge64
Field Status : current
Description : online greeting cards category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.42

Field Name : educationalInstitutions
Field Type : CounterBasedGauge64
Field Status : current
Description : educational institutions category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.41

Field Name : society
Field Type : CounterBasedGauge64
Field Status : current
Description : society category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.40

Field Name : huntingAndFishing
Field Type : CounterBasedGauge64
Field Status : current
Description : hunting and fishing category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.39

Field Name : payToSurf
Field Type : CounterBasedGauge64
Field Status : current
Description : pay to surf category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.38

Field Name : weapons
Field Type : CounterBasedGauge64
Field Status : current
Description : weapons category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.37

Field Name : philosophyAndPolitics
Field Type : CounterBasedGauge64
Field Status : current
Description : philosophy and politics category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.36

Field Name : games
Field Type : CounterBasedGauge64
Field Status : current
Description : games category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.35

Field Name : hacking
Field Type : CounterBasedGauge64
Field Status : current
Description : hacking category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.34

Field Name : marijuana
Field Type : CounterBasedGauge64
Field Status : current
Description : marijuana category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.33

Field Name : peerToPeer
Field Type : CounterBasedGauge64
Field Status : current
Description : peer to peer category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.32

Field Name : sharewareAndFreeware
Field Type : CounterBasedGauge64
Field Status : current
Description : shareware and freeware category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.31

Field Name : referenceAndResearch
Field Type : CounterBasedGauge64
Field Status : current
Description : reference and research category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.30

Field Name : translation
Field Type : CounterBasedGauge64
Field Status : current
Description : translation category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.29

Field Name : gambling
Field Type : CounterBasedGauge64
Field Status : current
Description : gambling category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.28

Field Name : jobSearch
Field Type : CounterBasedGauge64
Field Status : current
Description : job search category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.27

Field Name : streamingMedia
Field Type : CounterBasedGauge64
Field Status : current

Description : streaming media category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.26

Field Name : localInformation
Field Type : CounterBasedGauge64
Field Status : current
Description : local information category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.25

Field Name : legal
Field Type : CounterBasedGauge64
Field Status : current
Description : legal category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.24

Field Name : personalSitesAndBlogs
Field Type : CounterBasedGauge64
Field Status : current
Description : personal sites and blogs category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.23

Field Name : entertainmentAndArts
Field Type : CounterBasedGauge64
Field Status : current
Description : entertainment and arts category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.22

Field Name : religion
Field Type : CounterBasedGauge64
Field Status : current
Description : religion category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.21

Field Name : sexEducation
Field Type : CounterBasedGauge64
Field Status : current
Description : sex education category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.20

Field Name : dating
Field Type : CounterBasedGauge64
Field Status : current
Description : dating category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.19

Field Name : trainingAndTools
Field Type : CounterBasedGauge64
Field Status : current
Description : training and tools category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.18

Field Name : stockAdviceAndTools
Field Type : CounterBasedGauge64
Field Status : current
Description : stock advice and tools category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.17

Field Name : deadSites

Field Type : CounterBasedGauge64
Field Status : current
Description : dead sites category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.16

Field Name : socialNetwork
Field Type : CounterBasedGauge64
Field Status : current
Description : social network category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.15

Field Name : military
Field Type : CounterBasedGauge64
Field Status : current
Description : military category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.14

Field Name : homeAndGarden
Field Type : CounterBasedGauge64
Field Status : current
Description : home and garden category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.13

Field Name : adultAndPornography
Field Type : CounterBasedGauge64
Field Status : current
Description : adult and pornography category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.12

Field Name : drugs
Field Type : CounterBasedGauge64
Field Status : current
Description : drugs category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.11

Field Name : travel
Field Type : CounterBasedGauge64
Field Status : current
Description : travel category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.10

Field Name : cultAndOccult
Field Type : CounterBasedGauge64
Field Status : current
Description : cult and occult category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.9

Field Name : shopping
Field Type : CounterBasedGauge64
Field Status : current
Description : shopping category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.8

Field Name : auctions
Field Type : CounterBasedGauge64
Field Status : current
Description : auctions category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.7

Field Name : computerAndInternetInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : computer and internet info category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.6

Field Name : businessAndEconomy
Field Type : CounterBasedGauge64
Field Status : current
Description : business and economy category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.5

Field Name : financialServices
Field Type : CounterBasedGauge64
Field Status : current
Description : financial services category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.4

Field Name : computerAndInternetSecurity
Field Type : CounterBasedGauge64
Field Status : current
Description : computer and internet security category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.3

Field Name : realEstate
Field Type : CounterBasedGauge64
Field Status : current
Description : real estate category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.2

Field Name : slbTemplateClientSslName
Field Type : String
Field Status : current
Description : Client SSL Template Name
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.1

Field Name : slbTemplateCacheSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1

Field Name : slbTemplateCacheSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1

Field Name : slbTemplateCacheRspBr
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.34

Field Name : slbTemplateCacheHeaderSaveError
Field Type : CounterBasedGauge64
Field Status : current

Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.33

Field Name : slbTemplateCacheRspTypeStream
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.32

Field Name : slbTemplateCacheCleanedEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.31

Field Name : slbTemplateCacheAgingEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.30

Field Name : slbTemplateCacheReplacedEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.29

Field Name : slbTemplateCacheEntryNum
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.28

Field Name : slbTemplateCacheMemSize
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.27

Field Name : entryCreateFailures
Field Type : CounterBasedGauge64
Field Status : current
Description : slbTemplateCacheEntryCreateFailures, help entry_create_failures
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.26

Field Name : contentToosmall
Field Type : CounterBasedGauge64
Field Status : current
Description : slbTemplateCacheContentToosmall, help content_toosmall
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.25

Field Name : contentToobig
Field Type : CounterBasedGauge64
Field Status : current
Description : slbTemplateCacheContentToobig, help content_toobig
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.24

Field Name : slbTemplateCacheInvalidateMatch

Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.23

Field Name : slbTemplateCacheMatch
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.22

Field Name : slbTemplateCacheNocacheMatch
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.21

Field Name : slbTemplateCacheRspOther
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.20

Field Name : slbTemplateCacheRspDeflate
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.19

Field Name : slbTemplateCacheRspGzip
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.18

Field Name : slbTemplateCacheRspNoCompress
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.17

Field Name : slbTemplateCacheRspTypeOther
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.16

Field Name : slbTemplateCacheRspType304
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.15

Field Name : slbTemplateCacheRspTypeCE
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.14

Field Name : slbTemplateCacheRspTypeCL
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.13

Field Name : slbTemplateCacheNmResponse
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.12

Field Name : slbTemplateCacheImsRequest
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.11

Field Name : rvFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : slbTemplateCacheRvFailure, help rv_failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.10

Field Name : slbTemplateCacheRvSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.9

Field Name : ncResHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : slbTemplateCacheNcResHeader, help nc_res_header
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.8

Field Name : ncReqHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : slbTemplateCacheNcReqHeader, help nc_req_header
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.7

Field Name : slbTemplateCacheCachingReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Total requests to cache
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.6

Field Name : slbTemplateCacheTotalReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Total requests received
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.5

Field Name : slbTemplateCacheBytesServed
Field Type : CounterBasedGauge64
Field Status : current

Description : Bytes served from cache
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.4

Field Name : slbTemplateCacheMiss
Field Type : CounterBasedGauge64
Field Status : current
Description : Cache misses
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.3

Field Name : slbTemplateCacheHits
Field Type : CounterBasedGauge64
Field Status : current
Description : Cache hits
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.2

Field Name : slbTemplateCache
Field Type : String
Field Status : current
Description : Specify cache template name
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.1

Field Name : slbTemplateLinkCostSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.39.1.1

Field Name : slbTemplateLinkCostSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.39.1.1.1

Field Name : intervalMaxThroughput
Field Type : CounterBasedGauge64
Field Status : current
Description : Link Cost max throughput per interval
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.39.1.1.1.6

Field Name : intervalAvgThroughput
Field Type : CounterBasedGauge64
Field Status : current
Description : Link Cost average throughput per interval
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.39.1.1.1.5

Field Name : linkTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Link Cost total connection
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.39.1.1.1.4

Field Name : intervalFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : Link Cost bytes processed in forward direction per interval
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.39.1.1.1.3

Field Name : linkTotalFwdBytes

Field Type : CounterBasedGauge64
Field Status : current
Description : Total bytes fwd for link
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.39.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Server Link-Cost Template Name
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.39.1.1.1.1

Field Name : nRespFInvalid
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with invalid rcode
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.25

Field Name : nRespFBadcookie
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode BADCOOKIE
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.24

Field Name : nRespFBadtrunc
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode BADTRUNC
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.23

Field Name : nRespFBadalg
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode BADALG
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.22

Field Name : nRespFBadname
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode BADNAME
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.21

Field Name : nRespFBadmode
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode BADMODE
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.20

Field Name : nRespFBadtime
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode BADTIME
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.19

Field Name : nRespFBadkey
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode BADKEY
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.18

Field Name : nRespFBadvers
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode BADVERS
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.17

Field Name : nRespFDsotypeni
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode DSOTYPENI
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.16

Field Name : nRespFNotzone
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode NotZone
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.15

Field Name : nRespFNotauth
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode NotAuth
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.14

Field Name : nRespFNxrrset
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode NXRRSet
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.13

Field Name : nRespFYxrrset
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode YXRRSet
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.12

Field Name : nRespFYxdomain
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode YXDomain
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.11

Field Name : nRespFRefused
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode Refused
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.10

Field Name : nRespFNotimp
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode NotImp
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.9

Field Name : nRespFNxdomain
Field Type : CounterBasedGauge64
Field Status : current

Description : Number of response failure with rcode NXDomain
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.8

Field Name : nRespFServfail
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode ServFail
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.7

Field Name : nRespFFormerr
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode FormErr
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.6

Field Name : nRespErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response errors
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.5

Field Name : nResp
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of responses
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.4

Field Name : nQueryDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of queries dropped due to full queue
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.3

Field Name : nQueryErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of query errors
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.2

Field Name : nQuery
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of queries
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.1

Field Name : secureGamingDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Secure Gaming dropped
OID : 1.3.6.1.4.1.22610.2.4.10.108.92.1.2

Field Name : secureGamingPass
Field Type : CounterBasedGauge64
Field Status : current
Description : Secure Gaming passed
OID : 1.3.6.1.4.1.22610.2.4.10.108.92.1.1

Field Name : bypassServerIpSessions

Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass Server IP sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.36

Field Name : bypassClientIpSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass Client IP sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.35

Field Name : certInCache
Field Type : CounterBasedGauge64
Field Status : current
Description : Certificates in cache used by HC SSLi App
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.34

Field Name : asyncConnLimitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SSLi Async connections failures due to limit
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.33

Field Name : asyncConnTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : SSLi Async connections failures due to timeout
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.32

Field Name : currConnInBuff
Field Type : CounterBasedGauge64
Field Status : current
Description : Current buffered async connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.31

Field Name : totConnInBuff
Field Type : CounterBasedGauge64
Field Status : current
Description : Total buffered async connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.30

Field Name : bypassAdGroupSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass AD-group sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.29

Field Name : bypassUsernameSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass Username sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.28

Field Name : dropEsniSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Drop ESNI sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.27

Field Name : bypassEsniSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass ESNI sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.26

Field Name : resetNoSniSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Reset No SNI sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.25

Field Name : bypassNoSniSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass NO SNI sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.24

Field Name : bypassCertSanSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass Cert SAN sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.23

Field Name : bypassCertIssuerSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass Cert issuer sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.22

Field Name : bypassCertSubjectSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass Cert Subject sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.21

Field Name : aflexBypass
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass triggered by aFleX
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.20

Field Name : connectionsFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Connections failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.19

Field Name : certificatesInCache
Field Type : CounterBasedGauge64
Field Status : current
Description : Certificates in cache
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.18

Field Name : unsupportedSslVersion
Field Type : CounterBasedGauge64
Field Status : current

Description : Unsupported SSL version
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.17

Field Name : revokedOcspResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Revoked OCSP Response
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.16

Field Name : invalidOcspStaplingResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid OCSP Stapling Response
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.15

Field Name : failedInCertificateSigning
Field Type : CounterBasedGauge64
Field Status : current
Description : Failed in Certificate signing
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.14

Field Name : failedInCertificateVerification
Field Type : CounterBasedGauge64
Field Status : current
Description : Failed in Certificate verification
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.13

Field Name : failedInTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Failed in TCP
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.12

Field Name : failedInCryptoOperations
Field Type : CounterBasedGauge64
Field Status : current
Description : Failed in crypto operations
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.11

Field Name : failedInSslHandshakes
Field Type : CounterBasedGauge64
Field Status : current
Description : Failed in SSL handshakes
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.10

Field Name : bypassClientAuthSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass Client Auth sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.9

Field Name : bypassSniSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass SNI sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.8

Field Name : bypassFailsafeSslSessions

Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass Failsafe SSL sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.7

Field Name : connInspect
Field Type : CounterBasedGauge64
Field Status : current
Description : Connections inspected
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.6

Field Name : connBypass
Field Type : CounterBasedGauge64
Field Status : current
Description : Connections bypassed
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.5

Field Name : certMiss
Field Type : CounterBasedGauge64
Field Status : current
Description : Certificate cache miss
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.4

Field Name : certHit
Field Type : CounterBasedGauge64
Field Status : current
Description : Certificate cache hits
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.3

Field Name : certExpr
Field Type : CounterBasedGauge64
Field Status : current
Description : Certificates expired
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.2

Field Name : certCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : Certificates created
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.1

Field Name : l7ProxyTransPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 Proxy Transactions/sec
OID : 1.3.6.1.4.1.22610.2.4.10.108.13.1.15

Field Name : l7ProxyConnsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 Proxy Connections/sec
OID : 1.3.6.1.4.1.22610.2.4.10.108.13.1.14

Field Name : gifwConnsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : GiFW Connections/sec
OID : 1.3.6.1.4.1.22610.2.4.10.108.13.1.13

Field Name : fwConnsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : FW Connections/sec
OID : 1.3.6.1.4.1.22610.2.4.10.108.13.1.12

Field Name : servSslConnsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : Server SSL Connections/sec
OID : 1.3.6.1.4.1.22610.2.4.10.108.13.1.11

Field Name : l7Bandwidth
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 Bandwidth in bits/sec
OID : 1.3.6.1.4.1.22610.2.4.10.108.13.1.10

Field Name : l4Bandwidth
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 Bandwidth in bits/sec
OID : 1.3.6.1.4.1.22610.2.4.10.108.13.1.9

Field Name : totalCurrConns
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Current Established Connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.13.1.8

Field Name : totalNewConnsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : Total New Connections Established/sec
OID : 1.3.6.1.4.1.22610.2.4.10.108.13.1.7

Field Name : ipNatConnsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : IP NAT Connections/sec
OID : 1.3.6.1.4.1.22610.2.4.10.108.13.1.6

Field Name : sslConnsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL Connections/sec
OID : 1.3.6.1.4.1.22610.2.4.10.108.13.1.5

Field Name : l7TransPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 Transactions/sec
OID : 1.3.6.1.4.1.22610.2.4.10.108.13.1.4

Field Name : l7ConnsPerSec
Field Type : CounterBasedGauge64
Field Status : current

Description : L7 Connections/sec
OID : 1.3.6.1.4.1.22610.2.4.10.108.13.1.3

Field Name : l4ConnsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 Connections/sec
OID : 1.3.6.1.4.1.22610.2.4.10.108.13.1.2

Field Name : totalThroughputBitsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Throughput in bits/sec
OID : 1.3.6.1.4.1.22610.2.4.10.108.13.1.1

Field Name : crlOtherError
Field Type : CounterBasedGauge64
Field Status : current
Description : CRL other errors
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.32

Field Name : crlCacheStatusRevoked
Field Type : CounterBasedGauge64
Field Status : current
Description : CRL cache status revoked
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.31

Field Name : crlCacheStatusGood
Field Type : CounterBasedGauge64
Field Status : current
Description : CRL cache status good
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.30

Field Name : crlResponseStatusUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : CRL response status unknown
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.29

Field Name : crlResponseStatusRevoked
Field Type : CounterBasedGauge64
Field Status : current
Description : CRL response status revoked
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.28

Field Name : crlResponseStatusGood
Field Type : CounterBasedGauge64
Field Status : current
Description : CRL response status good
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.27

Field Name : crlUriUnsupported
Field Type : CounterBasedGauge64
Field Status : current
Description : CRL URI unsupported
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.26

Field Name : crlUriHttps

Field Type : CounterBasedGauge64
Field Status : current
Description : CRL URI https
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.25

Field Name : crlUriNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : CRL URI not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.24

Field Name : crlConnectionError
Field Type : CounterBasedGauge64
Field Status : current
Description : CRL connection errors
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.23

Field Name : crlResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : CRL responses
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.22

Field Name : crlRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : CRL requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.21

Field Name : ocspResponseNonceError
Field Type : CounterBasedGauge64
Field Status : current
Description : Log OCSP other errors
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.20

Field Name : ocspResponseNoNonce
Field Type : CounterBasedGauge64
Field Status : current
Description : Log OCSP other errors
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.19

Field Name : ocspOtherError
Field Type : CounterBasedGauge64
Field Status : current
Description : Log OCSP other errors
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.18

Field Name : ocspCacheExpired
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSP cache expired
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.17

Field Name : ocspCacheMiss
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSP cache miss
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.16

Field Name : ocspCacheStatusRevoked
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSP cache status revoked
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.15

Field Name : ocspCacheStatusGood
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSP cache status good
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.14

Field Name : ocspResponseStatusUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSP response status unknown
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.13

Field Name : ocspResponseStatusRevoked
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSP response status revoked
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.12

Field Name : ocspResponseStatusGood
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSP response status good
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.11

Field Name : ocspUriUnsupported
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSP URI unsupported
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.10

Field Name : ocspUriHttps
Field Type : CounterBasedGauge64
Field Status : current
Description : Log OCSP URI https
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.9

Field Name : ocspUriNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSP URI not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.8

Field Name : ocspConnectionError
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSP connection error
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.7

Field Name : ocspResponse
Field Type : CounterBasedGauge64
Field Status : current

Description : OCSP responses
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.6

Field Name : ocspRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSP requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.5

Field Name : ocspChainStatusUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : Certificate chain status unknown
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.4

Field Name : ocspChainStatusRevoked
Field Type : CounterBasedGauge64
Field Status : current
Description : Certificate chain status revoked
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.3

Field Name : ocspChainStatusGood
Field Type : CounterBasedGauge64
Field Status : current
Description : Certificate chain status good
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.2

Field Name : ocspStaplingResponseGood
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSP stapling response good
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.1

Field Name : badHandshakeLength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad handshake length
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.245

Field Name : unsupportedDigestType
Field Type : CounterBasedGauge64
Field Status : current
Description : unsupported digest type
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.244

Field Name : noRequiredDigest
Field Type : CounterBasedGauge64
Field Status : current
Description : no required digest
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.243

Field Name : unsupportedEllipticCurve
Field Type : CounterBasedGauge64
Field Status : current
Description : unsupported elliptic curve
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.242

Field Name : cookieMismatch

Field Type : CounterBasedGauge64
Field Status : current
Description : cookie mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.241

Field Name : badEcpoint
Field Type : CounterBasedGauge64
Field Status : current
Description : bad ecpoint
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.240

Field Name : badEcdsaSig
Field Type : CounterBasedGauge64
Field Status : current
Description : bad ecdsa sig
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.239

Field Name : badEccCert
Field Type : CounterBasedGauge64
Field Status : current
Description : bad ecc cert
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.238

Field Name : tlsInvalidEcpointformatList
Field Type : CounterBasedGauge64
Field Status : current
Description : tls invalid ecpointformat list
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.237

Field Name : multipleSgcRestarts
Field Type : CounterBasedGauge64
Field Status : current
Description : multiple sgc restarts
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.236

Field Name : ssl3ExtInvalidServernameType
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl3 ext invalid servername type
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.235

Field Name : ssl3ExtInvalidServername
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl3 ext invalid servername
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.234

Field Name : serverhelloTlsext
Field Type : CounterBasedGauge64
Field Status : current
Description : serverhello tlsext
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.233

Field Name : parseTlsext
Field Type : CounterBasedGauge64
Field Status : current
Description : parse tlsext
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.232

Field Name : clienthelloTlsext
Field Type : CounterBasedGauge64
Field Status : current
Description : clienthello tlsext
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.231

Field Name : x509VerificationSetupProblems
Field Type : CounterBasedGauge64
Field Status : current
Description : x509 verification setup problems
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.230

Field Name : x509Lib
Field Type : CounterBasedGauge64
Field Status : current
Description : x509 lib
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.229

Field Name : wrongVersionCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : wrong version counter
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.228

Field Name : wrongSslVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : wrong ssl version
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.227

Field Name : wrongSignatureSize
Field Type : CounterBasedGauge64
Field Status : current
Description : wrong signature size
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.226

Field Name : wrongSignatureLength
Field Type : CounterBasedGauge64
Field Status : current
Description : wrong signature length
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.225

Field Name : wrongCounterOfKeyBits
Field Type : CounterBasedGauge64
Field Status : current
Description : wrong counter of key bits
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.224

Field Name : wrongMessageType
Field Type : CounterBasedGauge64
Field Status : current
Description : wrong message type
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.223

Field Name : wrongCipherReturned
Field Type : CounterBasedGauge64
Field Status : current

Description : wrong cipher returned
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.222

Field Name : writeBioNotSet
Field Type : CounterBasedGauge64
Field Status : current
Description : write bio not set
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.221

Field Name : unsupportedStatusType
Field Type : CounterBasedGauge64
Field Status : current
Description : unsupported status type
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.220

Field Name : unsupportedSslVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : unsupported ssl version
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.219

Field Name : unsupportedProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : unsupported protocol
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.218

Field Name : unsupportedOption
Field Type : CounterBasedGauge64
Field Status : current
Description : unsupported option
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.217

Field Name : unsupportedCompressionAlgorithm
Field Type : CounterBasedGauge64
Field Status : current
Description : unsupported compression algorithm
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.216

Field Name : unsupportedCipher
Field Type : CounterBasedGauge64
Field Status : current
Description : unsupported cipher
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.215

Field Name : unknownState
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown state
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.214

Field Name : unknownSslVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown ssl version
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.213

Field Name : unknownRemoteErrorType

Field Type : CounterBasedGauge64
Field Status : current
Description : unknown remote error type
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.212

Field Name : unknownProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown protocol
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.211

Field Name : unknownPkeyType
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown pkey type
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.210

Field Name : unknownKeyExchangeType
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown key exchange type
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.209

Field Name : unknownCipherType
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown cipher type
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.208

Field Name : unknownCipherReturned
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown cipher returned
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.207

Field Name : unknownCertificateType
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown certificate type
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.206

Field Name : unknownAlertType
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown alert type
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.205

Field Name : uninitialized
Field Type : CounterBasedGauge64
Field Status : current
Description : uninitialized
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.204

Field Name : unexpectedRecord
Field Type : CounterBasedGauge64
Field Status : current
Description : unexpected record
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.203

Field Name : unexpectedMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : unexpected message
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.202

Field Name : unableToLoadSsl3Sha1Routines
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to load ssl3 sha1 routines
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.201

Field Name : unableToLoadSsl3Md5Routines
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to load ssl3 md5 routines
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.200

Field Name : unableToLoadSsl2Md5Routines
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to load ssl2 md5 routines
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.199

Field Name : unableToFindSslMethod
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to find ssl method
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.198

Field Name : unableToFindPublicKeyParameters
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to find public key parameters
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.197

Field Name : unableToFindDhParameters
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to find dh parameters
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.196

Field Name : unableToExtractPublicKey
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to extract public key
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.195

Field Name : unableToDecodeDhCerts
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to decode dh certs
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.194

Field Name : triedToUseUnsupportedCipher
Field Type : CounterBasedGauge64
Field Status : current

Description : tried to use unsupported cipher
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.193

Field Name : tlsRsaEncryptedValueLengthIsWrong
Field Type : CounterBasedGauge64
Field Status : current
Description : tls rsa encrypted value length is wrong
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.192

Field Name : tlsPeerDidNotRespondWithCertList
Field Type : CounterBasedGauge64
Field Status : current
Description : tls peer did not respond with cert list
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.191

Field Name : tlsClientCertReqWithAnonCipher
Field Type : CounterBasedGauge64
Field Status : current
Description : tls client cert req with anon cipher
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.190

Field Name : tlsv1AlertUserCancelled
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert user cancelled
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.189

Field Name : tlsv1AlertUnknownCa
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert unknown ca
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.188

Field Name : tlsv1AlertRecordOverflow
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert record overflow
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.187

Field Name : tlsv1AlertProtocolVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert protocol version
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.186

Field Name : tlsv1AlertNoRenegotiation
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert no renegotiation
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.185

Field Name : tlsv1AlertInternalError
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert internal error
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.184

Field Name : tlsv1AlertInsufficientSecurity

Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert insufficient security
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.183

Field Name : tlsv1AlertExportRestriction
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert export restriction
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.182

Field Name : tlsv1AlertDecryptError
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert decrypt error
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.181

Field Name : tlsv1AlertDecryptionFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert decryption failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.180

Field Name : tlsv1AlertDecodeError
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert decode error
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.179

Field Name : tlsv1AlertAccessDenied
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert access denied
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.178

Field Name : sslSessionIdIsDifferent
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl session id is different
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.177

Field Name : sslSessionIdHasBadLength
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl session id has bad length
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.176

Field Name : sslSessionIdContextTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl session id context too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.175

Field Name : sslSessionIdConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl session id conflict
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.174

Field Name : sslSessionIdCallbackFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl session id callback failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.173

Field Name : sslLibraryHasNoCiphers
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl library has no ciphers
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.172

Field Name : sslHandshakeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl handshake failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.171

Field Name : sslCtxHasNoDefaultSslVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl ctx has no default ssl version
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.170

Field Name : sslv3AlertUnspportedCert
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert unspported cert
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.169

Field Name : sslv3AlertUnknownRemoteErrType
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert unknown remote err type
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.168

Field Name : sslv3AlertUnexpectedMsg
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert unexpected msg
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.167

Field Name : sslv3AlertPeerErrorUnsuppCertType
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert peer error unsupp cert type
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.166

Field Name : sslv3AlertPeerErrorNoCipher
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert peer error no cipher
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.165

Field Name : sslv3AlertPeerErrorNoCert
Field Type : CounterBasedGauge64
Field Status : current

Description : sslv3 alert peer error no cert
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.164

Field Name : sslv3AlertPeerErrorCert
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert peer error cert
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.163

Field Name : sslv3AlertNoCertificate
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert no certificate
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.162

Field Name : sslv3AlertIllegalParameter
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert illegal parameter
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.161

Field Name : sslv3AlertHandshakeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert handshake failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.160

Field Name : sslv3AlertDecompressionFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert decompression failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.159

Field Name : sslv3AlertCertificateUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert certificate unknown
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.158

Field Name : sslv3AlertCertificateRevoked
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert certificate revoked
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.157

Field Name : sslv3AlertCertificateExpired
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert certificate expired
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.156

Field Name : sslv3AlertBadRecordMac
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert bad record mac
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.155

Field Name : sslv3AlertBadCertificate

Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert bad certificate
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.154

Field Name : ssl3SessionIdTooShort
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl3 session id too short
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.153

Field Name : ssl3SessionIdTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl3 session id too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.152

Field Name : ssl2ConnectionIdTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl2 connection id too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.151

Field Name : ssl23DoingSessionIdReuse
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl23 doing session id reuse
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.150

Field Name : signatureForNonSigningCertificate
Field Type : CounterBasedGauge64
Field Status : current
Description : signature for non signing certificate
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.149

Field Name : shortRead
Field Type : CounterBasedGauge64
Field Status : current
Description : short read
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.148

Field Name : sessionIdContextUninitialized
Field Type : CounterBasedGauge64
Field Status : current
Description : session id context uninitialized
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.147

Field Name : scsvReceivedWhenRenegotiating
Field Type : CounterBasedGauge64
Field Status : current
Description : scsv received when renegotiating
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.146

Field Name : reuseCipherListNotZero
Field Type : CounterBasedGauge64
Field Status : current
Description : reuse cipher list not zero
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.145

Field Name : reuseCertTypeNotZero
Field Type : CounterBasedGauge64
Field Status : current
Description : reuse cert type not zero
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.144

Field Name : reuseCertLengthNotZero
Field Type : CounterBasedGauge64
Field Status : current
Description : reuse cert length not zero
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.143

Field Name : requiredCipherMissing
Field Type : CounterBasedGauge64
Field Status : current
Description : required cipher missing
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.142

Field Name : recordTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : record too small
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.141

Field Name : recordTooLarge
Field Type : CounterBasedGauge64
Field Status : current
Description : record too large
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.140

Field Name : recordLengthMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : record length mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.139

Field Name : readWrongPacketType
Field Type : CounterBasedGauge64
Field Status : current
Description : read wrong packet type
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.138

Field Name : readBioNotSet
Field Type : CounterBasedGauge64
Field Status : current
Description : read bio not set
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.137

Field Name : publicKeyNotRsa
Field Type : CounterBasedGauge64
Field Status : current
Description : public key not rsa
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.136

Field Name : publicKeyIsNotRsa
Field Type : CounterBasedGauge64
Field Status : current

Description : public key is not rsa
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.135

Field Name : publicKeyEncryptError
Field Type : CounterBasedGauge64
Field Status : current
Description : public key encrypt error
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.134

Field Name : protocolIsShutdown
Field Type : CounterBasedGauge64
Field Status : current
Description : protocol is shutdown
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.133

Field Name : problemsMappingCipherFunctions
Field Type : CounterBasedGauge64
Field Status : current
Description : problems mapping cipher functions
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.132

Field Name : preMacLengthTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : pre mac length too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.131

Field Name : peerErrorUnsupportedCertificateType
Field Type : CounterBasedGauge64
Field Status : current
Description : peer error unsupported certificate type
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.130

Field Name : peerErrorNoCipher
Field Type : CounterBasedGauge64
Field Status : current
Description : peer error no cipher
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.129

Field Name : peerErrorNoCertificate
Field Type : CounterBasedGauge64
Field Status : current
Description : peer error no certificate
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.128

Field Name : peerErrorCertificate
Field Type : CounterBasedGauge64
Field Status : current
Description : peer error certificate
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.127

Field Name : peerError
Field Type : CounterBasedGauge64
Field Status : current
Description : peer error
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.126

Field Name : peerDidNotReturnACertificate

Field Type : CounterBasedGauge64
Field Status : current
Description : peer did not return a certificate
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.125

Field Name : pathTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : path too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.124

Field Name : packetLengthTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : packet length too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.123

Field Name : oldSessionCipherNotReturned
Field Type : CounterBasedGauge64
Field Status : current
Description : old session cipher not returned
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.122

Field Name : nullSslMethodPassed
Field Type : CounterBasedGauge64
Field Status : current
Description : null ssl method passed
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.121

Field Name : nullSslCtx
Field Type : CounterBasedGauge64
Field Status : current
Description : null ssl ctx
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.120

Field Name : noVerifyCallback
Field Type : CounterBasedGauge64
Field Status : current
Description : no verify callback
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.119

Field Name : noSharedCipher
Field Type : CounterBasedGauge64
Field Status : current
Description : no shared cipher
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.118

Field Name : noPublickey
Field Type : CounterBasedGauge64
Field Status : current
Description : no publickey
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.117

Field Name : noProtocolsAvailable
Field Type : CounterBasedGauge64
Field Status : current
Description : no protocols available
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.116

Field Name : noPrivateKeyAssigned
Field Type : CounterBasedGauge64
Field Status : current
Description : no private key assigned
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.115

Field Name : noPrivatekey
Field Type : CounterBasedGauge64
Field Status : current
Description : no privatekey
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.114

Field Name : noMethodSpecified
Field Type : CounterBasedGauge64
Field Status : current
Description : no method specified
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.113

Field Name : noCompressionSpecified
Field Type : CounterBasedGauge64
Field Status : current
Description : no compression specified
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.112

Field Name : noClientCertReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : no client cert received
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.111

Field Name : noCipherMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : no cipher match
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.110

Field Name : noCipherList
Field Type : CounterBasedGauge64
Field Status : current
Description : no cipher list
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.109

Field Name : noCiphersSpecified
Field Type : CounterBasedGauge64
Field Status : current
Description : no ciphers specified
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.108

Field Name : noCiphersPassed
Field Type : CounterBasedGauge64
Field Status : current
Description : no ciphers passed
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.107

Field Name : noCiphersAvailable
Field Type : CounterBasedGauge64
Field Status : current

Description : no ciphers available
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.106

Field Name : noCertificateSpecified
Field Type : CounterBasedGauge64
Field Status : current
Description : no certificate specified
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.105

Field Name : noCertificateSet
Field Type : CounterBasedGauge64
Field Status : current
Description : no certificate set
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.104

Field Name : noCertificateReturned
Field Type : CounterBasedGauge64
Field Status : current
Description : no certificate returned
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.103

Field Name : noCertificateAssigned
Field Type : CounterBasedGauge64
Field Status : current
Description : no certificate assigned
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.102

Field Name : noCertificatesReturned
Field Type : CounterBasedGauge64
Field Status : current
Description : no certificates returned
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.101

Field Name : nonSslv2InitialPacket
Field Type : CounterBasedGauge64
Field Status : current
Description : non sslv2 initial packet
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.100

Field Name : missingVerifyMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : missing verify message
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.99

Field Name : missingTmpRsaPkey
Field Type : CounterBasedGauge64
Field Status : current
Description : missing tmp rsa pkey
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.98

Field Name : missingTmpRsaKey
Field Type : CounterBasedGauge64
Field Status : current
Description : missing tmp rsa key
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.97

Field Name : missingTmpDhKey

Field Type : CounterBasedGauge64
Field Status : current
Description : missing tmp dh key
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.96

Field Name : missingRsaSigningCert
Field Type : CounterBasedGauge64
Field Status : current
Description : missing rsa signing cert
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.95

Field Name : missingRsaEncryptingCert
Field Type : CounterBasedGauge64
Field Status : current
Description : missing rsa encrypting cert
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.94

Field Name : missingRsaCertificate
Field Type : CounterBasedGauge64
Field Status : current
Description : missing rsa certificate
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.93

Field Name : missingExportTmpRsaKey
Field Type : CounterBasedGauge64
Field Status : current
Description : missing export tmp rsa key
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.92

Field Name : missingExportTmpDhKey
Field Type : CounterBasedGauge64
Field Status : current
Description : missing export tmp dh key
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.91

Field Name : missingDsaSigningCert
Field Type : CounterBasedGauge64
Field Status : current
Description : missing dsa signing cert
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.90

Field Name : missingDhRsaCert
Field Type : CounterBasedGauge64
Field Status : current
Description : missing dh rsa cert
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.89

Field Name : missingDhKey
Field Type : CounterBasedGauge64
Field Status : current
Description : missing dh key
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.88

Field Name : missingDhDsaCert
Field Type : CounterBasedGauge64
Field Status : current
Description : missing dh dsa cert
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.87

Field Name : messageTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : message too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.86

Field Name : mastKeyTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : mast key too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.85

Field Name : libraryHasNoCiphers
Field Type : CounterBasedGauge64
Field Status : current
Description : library has no ciphers
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.84

Field Name : libraryBug
Field Type : CounterBasedGauge64
Field Status : current
Description : library bug
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.83

Field Name : lengthTooShort
Field Type : CounterBasedGauge64
Field Status : current
Description : length too short
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.82

Field Name : lengthMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : length mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.81

Field Name : krb5ServerTktSkew
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 server tkt skew
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.80

Field Name : krb5ServerTktNotYetValid
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 server tkt not yet valid
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.79

Field Name : krb5ServerTktExpired
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 server tkt expired
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.78

Field Name : krb5ServerRdReq
Field Type : CounterBasedGauge64
Field Status : current

Description : krb5 server rd_req
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.77

Field Name : krb5ServerInit
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 server init
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.76

Field Name : krb5ServerBadTicket
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 server bad ticket
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.75

Field Name : krb5ClientMkReq
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 client mk_req
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.74

Field Name : krb5ClientInit
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 client init
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.73

Field Name : krb5ClientGetCred
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 client get cred
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.72

Field Name : krb5ClientCcPrincipal
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 client cc principal
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.71

Field Name : krb5
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.70

Field Name : keyArgTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : key arg too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.69

Field Name : invalidTrust
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid trust
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.68

Field Name : invalidStatusResponse

Field Type : CounterBasedGauge64
Field Status : current
Description : invalid status response
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.67

Field Name : invalidPurpose
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid purpose
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.66

Field Name : invalidCommand
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid command
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.65

Field Name : invalidChallengeLength
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid challenge length
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.64

Field Name : inappropriateFallback
Field Type : CounterBasedGauge64
Field Status : current
Description : inappropriate fallback
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.63

Field Name : illegalPadding
Field Type : CounterBasedGauge64
Field Status : current
Description : illegal padding
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.62

Field Name : httpRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : http request
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.61

Field Name : httpsProxyRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : https proxy request
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.60

Field Name : gotAFinBeforeACcs
Field Type : CounterBasedGauge64
Field Status : current
Description : got a fin before a ccs
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.59

Field Name : extraDataInMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : extra data in message
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.58

Field Name : excessiveMessageSize
Field Type : CounterBasedGauge64
Field Status : current
Description : excessive message size
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.57

Field Name : errorInReceivedCipherList
Field Type : CounterBasedGauge64
Field Status : current
Description : error in received cipher list
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.56

Field Name : errorGeneratingTmpRsaKey
Field Type : CounterBasedGauge64
Field Status : current
Description : error generating tmp rsa key
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.55

Field Name : encryptedLengthTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : encrypted length too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.54

Field Name : digestCheckFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : digest check failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.53

Field Name : dhPublicValueLengthIsWrong
Field Type : CounterBasedGauge64
Field Status : current
Description : dh public value length is wrong
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.52

Field Name : decryptionFailedOrBadRecordMac
Field Type : CounterBasedGauge64
Field Status : current
Description : decryption failed or bad record mac
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.51

Field Name : decryptionFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : decryption failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.50

Field Name : dataLengthTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : data length too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.49

Field Name : dataBetweenCcsAndFinished
Field Type : CounterBasedGauge64
Field Status : current

Description : data between ccs and finished
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.48

Field Name : connectionTypeNotSet
Field Type : CounterBasedGauge64
Field Status : current
Description : connection type not set
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.47

Field Name : connectionIdIsDifferent
Field Type : CounterBasedGauge64
Field Status : current
Description : connection id is different
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.46

Field Name : compressionLibraryError
Field Type : CounterBasedGauge64
Field Status : current
Description : compression library error
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.45

Field Name : compressionFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : compression failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.44

Field Name : compressedLengthTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : compressed length too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.43

Field Name : cipherTableSrcError
Field Type : TABLE
Field Status : current
Description : cipher table src error
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.42

Field Name : cipherOrHashUnavailable
Field Type : CounterBasedGauge64
Field Status : current
Description : cipher or hash unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.41

Field Name : cipherCodeWrongLength
Field Type : CounterBasedGauge64
Field Status : current
Description : cipher code wrong length
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.40

Field Name : challengeIsDifferent
Field Type : CounterBasedGauge64
Field Status : current
Description : challenge is different
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.39

Field Name : certLengthMismatch

Field Type : CounterBasedGauge64
Field Status : current
Description : cert length mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.38

Field Name : certificateVerifyFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : certificate verify failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.37

Field Name : ccsReceivedEarly
Field Type : CounterBasedGauge64
Field Status : current
Description : ccs received early
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.36

Field Name : caDnTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : ca dn too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.35

Field Name : caDnLengthMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : ca dn length mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.34

Field Name : bnLib
Field Type : CounterBasedGauge64
Field Status : current
Description : bn lib
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.33

Field Name : blockCipherPadIsWrong
Field Type : CounterBasedGauge64
Field Status : current
Description : block cipher pad is wrong
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.32

Field Name : bioNotSet
Field Type : CounterBasedGauge64
Field Status : current
Description : bio not set
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.31

Field Name : badWriteRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : bad write retry
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.30

Field Name : badState
Field Type : CounterBasedGauge64
Field Status : current
Description : bad state
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.29

Field Name : badSslSessionIdLength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad ssl session id length
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.28

Field Name : badSslFiletype
Field Type : CounterBasedGauge64
Field Status : current
Description : bad ssl filetype
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.27

Field Name : badSignature
Field Type : CounterBasedGauge64
Field Status : current
Description : bad signature
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.26

Field Name : badRsaSignature
Field Type : CounterBasedGauge64
Field Status : current
Description : bad rsa signature
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.25

Field Name : badRsaModulusLength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad rsa modulus length
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.24

Field Name : badRsaELength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad rsa e length
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.23

Field Name : badRsaEncrypt
Field Type : CounterBasedGauge64
Field Status : current
Description : bad rsa encrypt
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.22

Field Name : badRsaDecrypt
Field Type : CounterBasedGauge64
Field Status : current
Description : bad rsa decrypt
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.21

Field Name : badResponseArgument
Field Type : CounterBasedGauge64
Field Status : current
Description : bad response argument
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.20

Field Name : badProtocolVersionCounter
Field Type : CounterBasedGauge64
Field Status : current

Description : bad protocol version counter
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.19

Field Name : badPacketLength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad packet length
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.18

Field Name : badMessageType
Field Type : CounterBasedGauge64
Field Status : current
Description : bad message type
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.17

Field Name : badMacDecode
Field Type : CounterBasedGauge64
Field Status : current
Description : bad mac decode
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.16

Field Name : badLength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad length
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.15

Field Name : badHelloRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : bad hello request
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.14

Field Name : badDsaSignature
Field Type : CounterBasedGauge64
Field Status : current
Description : bad dsa signature
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.13

Field Name : badDigestLength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad digest length
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.12

Field Name : badDhPLength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad dh p length
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.11

Field Name : badDhPubKeyLength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad dh pub key length
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.10

Field Name : badDhGLength

Field Type : CounterBasedGauge64
Field Status : current
Description : bad dh g length
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.9

Field Name : badDecompression
Field Type : CounterBasedGauge64
Field Status : current
Description : bad decompression
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.8

Field Name : badDataReturnedByCallback
Field Type : CounterBasedGauge64
Field Status : current
Description : bad data returned by callback
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.7

Field Name : badChecksum
Field Type : CounterBasedGauge64
Field Status : current
Description : bad checksum
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.6

Field Name : badChangeCipherSpec
Field Type : CounterBasedGauge64
Field Status : current
Description : bad change cipher spec
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.5

Field Name : badAuthenticationType
Field Type : CounterBasedGauge64
Field Status : current
Description : bad authentication type
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.4

Field Name : badAlertRecord
Field Type : CounterBasedGauge64
Field Status : current
Description : bad alert record
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.3

Field Name : attemptToReuseSessInDiffContext
Field Type : CounterBasedGauge64
Field Status : current
Description : attempt to reuse sess in diff context
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.2

Field Name : appDataInHandshake
Field Type : CounterBasedGauge64
Field Status : current
Description : app data in handshake
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.1

Field Name : keyUpdateTx
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC TLS key update sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.165

Field Name : keyUpdateRx
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC TLS key update received
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.164

Field Name : invalidCidSig
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid CID Signature
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.163

Field Name : cidCpuHash
Field Type : CounterBasedGauge64
Field Status : current
Description : CID CPU Hash
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.162

Field Name : cidZero
Field Type : CounterBasedGauge64
Field Status : current
Description : CID Zero
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.161

Field Name : quicLb
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC LB
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.160

Field Name : quickMallocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : quick malloc failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.153

Field Name : quicMallocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC malloc failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.152

Field Name : quicFree
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC free
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.151

Field Name : quicMalloc
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC malloc
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.150

Field Name : delayAlarm
Field Type : CounterBasedGauge64
Field Status : current

Description : delay timeout
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.222

Field Name : closeAlarm
Field Type : CounterBasedGauge64
Field Status : current
Description : close timeout
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.221

Field Name : ackAlarm
Field Type : CounterBasedGauge64
Field Status : current
Description : ack timeout
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.148

Field Name : idleAlarm
Field Type : CounterBasedGauge64
Field Status : current
Description : conn idle timeout
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.147

Field Name : onLdTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : lost detection timeout
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.146

Field Name : noWSocket
Field Type : CounterBasedGauge64
Field Status : current
Description : no w socket
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.220

Field Name : noWEngine
Field Type : CounterBasedGauge64
Field Status : current
Description : no w engine
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.184

Field Name : noOtherSideSocket
Field Type : CounterBasedGauge64
Field Status : current
Description : no other side socket
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.180

Field Name : noA10Socket
Field Type : CounterBasedGauge64
Field Status : current
Description : no a10 socket
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.179

Field Name : a10SocketClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : a10 socket closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.143

Field Name : a10SocketCreated

Field Type : CounterBasedGauge64
Field Status : current
Description : a10 socket created
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.142

Field Name : wsocketClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : wsocket closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.141

Field Name : wsocketCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : wsocket created
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.140

Field Name : noTxQueue
Field Type : CounterBasedGauge64
Field Status : current
Description : No tx queue
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.178

Field Name : iovSystem
Field Type : CounterBasedGauge64
Field Status : current
Description : Iov System
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.224

Field Name : iovIO
Field Type : CounterBasedGauge64
Field Status : current
Description : Iov IO
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.223

Field Name : iovAllocLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Iov alloc len
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.175

Field Name : iovBufferDup
Field Type : CounterBasedGauge64
Field Status : current
Description : Iov buffer dup
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.174

Field Name : iovBufferUnbind
Field Type : CounterBasedGauge64
Field Status : current
Description : Iov buffer unbind
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.167

Field Name : iovBufferBind
Field Type : CounterBasedGauge64
Field Status : current
Description : Iov buffer bind
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.166

Field Name : appBufferQueueFull
Field Type : CounterBasedGauge64
Field Status : current
Description : App buffer queue full
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.136

Field Name : appBufferDeq
Field Type : CounterBasedGauge64
Field Status : current
Description : App buffer dequeued
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.135

Field Name : appBufferEnq
Field Type : CounterBasedGauge64
Field Status : current
Description : App buffer enqueued
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.134

Field Name : txBufferDeq
Field Type : CounterBasedGauge64
Field Status : current
Description : Tx buffer dequeued
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.133

Field Name : txBufferEnq
Field Type : CounterBasedGauge64
Field Status : current
Description : Tx buffer enqueued
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.132

Field Name : ackedPacketFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Acked packet freed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.225

Field Name : pnDeleteFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Pn delete failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.219

Field Name : pnInsertFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Pn insert failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.218

Field Name : pktAckedFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Pkt_acked_failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.217

Field Name : serverRxHandshakeDone
Field Type : CounterBasedGauge64
Field Status : current

Description : Server_rx_handshake_done
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.216

Field Name : errProtocolViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Err_protocol_violation
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.215

Field Name : errFlowControl
Field Type : CounterBasedGauge64
Field Status : current
Description : Err_flow_control
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.214

Field Name : errFrameFinalSize
Field Type : CounterBasedGauge64
Field Status : current
Description : Err_frame_final_size
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.213

Field Name : errFrameDecb
Field Type : CounterBasedGauge64
Field Status : current
Description : Err_frame_decb
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.212

Field Name : errFrameDec
Field Type : CounterBasedGauge64
Field Status : current
Description : Err_frame_dec
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.211

Field Name : errFrameDec1
Field Type : CounterBasedGauge64
Field Status : current
Description : Err_frame_dec1
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.210

Field Name : zeroFramePacket
Field Type : CounterBasedGauge64
Field Status : current
Description : Zero_frame_packet
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.209

Field Name : serverReceiveNewToken
Field Type : CounterBasedGauge64
Field Status : current
Description : Server_receive_new_token
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.207

Field Name : tokenLenTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Token_len_too_long
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.206

Field Name : noNextScid

Field Type : CounterBasedGauge64
Field Status : current
Description : No_next_scid
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.205

Field Name : cannotRetireCid
Field Type : CounterBasedGauge64
Field Status : current
Description : Cannot_retire_cid
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.204

Field Name : cannotInsertSrt
Field Type : CounterBasedGauge64
Field Status : current
Description : Cannot_insert_srt
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.203

Field Name : cannotInsertCid
Field Type : CounterBasedGauge64
Field Status : current
Description : Cannot_insert_cid
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.202

Field Name : illegalTokenLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Illegal_token_len
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.208

Field Name : illegalLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Illegal_len
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.201

Field Name : illegalRpt
Field Type : CounterBasedGauge64
Field Status : current
Description : Illegal_rpt
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.200

Field Name : illegalSeq
Field Type : CounterBasedGauge64
Field Status : current
Description : Illegal_seq
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.199

Field Name : illegalReasonLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Illegal_reason_len
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.194

Field Name : illegalStreamLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Illegal_stream_len
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.186

Field Name : newConnIdLenNonZero
Field Type : CounterBasedGauge64
Field Status : current
Description : New_conn_id_len_non_zero
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.198

Field Name : newConnIdLenZero
Field Type : CounterBasedGauge64
Field Status : current
Description : New_conn_id_len_zero
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.197

Field Name : streamBlocked
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream_blocked
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.196

Field Name : maxStreamTooBig
Field Type : CounterBasedGauge64
Field Status : current
Description : Max_stream_too_big
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.195

Field Name : tooNoisyFuzzing
Field Type : CounterBasedGauge64
Field Status : current
Description : Too_noisy_fuzzing
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.192

Field Name : ackRngHuge3
Field Type : CounterBasedGauge64
Field Status : current
Description : Ack_rng_huge_3
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.193

Field Name : ackRngHuge2
Field Type : CounterBasedGauge64
Field Status : current
Description : Ack_rng_huge_2
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.191

Field Name : ackRngHuge1
Field Type : CounterBasedGauge64
Field Status : current
Description : Ack_rng_huge_1
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.190

Field Name : ackDelayHuge
Field Type : CounterBasedGauge64
Field Status : current
Description : Ack_delay_huge
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.189

Field Name : streamIdMismatch
Field Type : CounterBasedGauge64
Field Status : current

Description : Stream_id_mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.188

Field Name : exceedMaxStreamId
Field Type : CounterBasedGauge64
Field Status : current
Description : Exceed_max_stream_id
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.187

Field Name : cryptoStreamNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Crypto stream not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.185

Field Name : exceedFlowControl
Field Type : CounterBasedGauge64
Field Status : current
Description : Exceed flow control
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.181

Field Name : decodeStreamError
Field Type : CounterBasedGauge64
Field Status : current
Description : Decode stream error
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.177

Field Name : decodeFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Decode failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.176

Field Name : encodeError
Field Type : CounterBasedGauge64
Field Status : current
Description : Encode error
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.171

Field Name : quicPacketDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Quic packet drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.170

Field Name : packetOutOfOrder
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet out of order
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.131

Field Name : packetRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet retransmit
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.130

Field Name : packetDrop

Field Type : CounterBasedGauge64
Field Status : current
Description : Packet drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.129

Field Name : packetLost
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet lost
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.128

Field Name : statelessReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Stateless resert
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.127

Field Name : invalidSessionPacket
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid session packet
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.149

Field Name : invalidConnMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid conn match
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.145

Field Name : invalidPacket
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid packet
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.126

Field Name : invalidVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid version
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.125

Field Name : packetTooShort
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet_too_short
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.124

Field Name : dcidMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Dcid mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.123

Field Name : unknownScid
Field Type : CounterBasedGauge64
Field Status : current
Description : Unknown scid
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.122

Field Name : errorClose
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn closed of error
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.121

Field Name : parseError
Field Type : CounterBasedGauge64
Field Status : current
Description : Parse error
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.120

Field Name : receiveWndLimited
Field Type : CounterBasedGauge64
Field Status : current
Description : Receive window limited
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.144

Field Name : packetLoopLimited
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet loop limited
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.137

Field Name : burstLimited
Field Type : CounterBasedGauge64
Field Status : current
Description : Burst limited
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.119

Field Name : noCongestWnd
Field Type : CounterBasedGauge64
Field Status : current
Description : No congestion window
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.118

Field Name : congestWndDec
Field Type : CounterBasedGauge64
Field Status : current
Description : Congestion window decrease
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.117

Field Name : congestWndInc
Field Type : CounterBasedGauge64
Field Status : current
Description : Congestion window increase
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.116

Field Name : packetTxFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet send failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.115

Field Name : packetTx
Field Type : CounterBasedGauge64
Field Status : current

Description : Packet send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.114

Field Name : packetRx
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.113

Field Name : delayedAck
Field Type : CounterBasedGauge64
Field Status : current
Description : Delayed ACK
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.112

Field Name : needsAck
Field Type : CounterBasedGauge64
Field Status : current
Description : Needs ACK
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.111

Field Name : rTTUpdated
Field Type : CounterBasedGauge64
Field Status : current
Description : RTT updated
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.110

Field Name : vERTx
Field Type : CounterBasedGauge64
Field Status : current
Description : Version send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.109

Field Name : vERRx
Field Type : CounterBasedGauge64
Field Status : current
Description : Version receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.108

Field Name : rETRYTx
Field Type : CounterBasedGauge64
Field Status : current
Description : RETRY send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.107

Field Name : rETRYRx
Field Type : CounterBasedGauge64
Field Status : current
Description : RETRY receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.106

Field Name : hANDSHAKETx
Field Type : CounterBasedGauge64
Field Status : current
Description : HANDSHAKE send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.105

Field Name : hANDSHAKERx

Field Type : CounterBasedGauge64
Field Status : current
Description : HANDSHAKE receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.104

Field Name : rTT0Tx
Field Type : CounterBasedGauge64
Field Status : current
Description : RTT_0 send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.103

Field Name : rTT0Rx
Field Type : CounterBasedGauge64
Field Status : current
Description : RTT_0 receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.102

Field Name : iNITIALTx
Field Type : CounterBasedGauge64
Field Status : current
Description : INITIAL send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.101

Field Name : iNITIALRx
Field Type : CounterBasedGauge64
Field Status : current
Description : INITIAL receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.100

Field Name : streamFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream freed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.173

Field Name : streamCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream created
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.172

Field Name : streamStopSend
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream stop send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.231

Field Name : streamNotSend
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream not send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.99

Field Name : streamResumeData
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream resume data
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.98

Field Name : streamPauseData
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream pause data
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.97

Field Name : streamOpen
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream open
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.96

Field Name : streamCongest
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream congest
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.95

Field Name : streamFinSend
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream FIN send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.94

Field Name : streamFinDown
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream FIN down
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.139

Field Name : streamFinUp
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream FIN up
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.138

Field Name : streamFinReceive
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream FIN receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.93

Field Name : unknownFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Unknown frame
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.92

Field Name : handshakeDoneFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : handshake done frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.91

Field Name : handshakeDoneFrameRx
Field Type : CounterBasedGauge64
Field Status : current

Description : handshake done frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.90

Field Name : appConnCloseFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : app conn close frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.89

Field Name : appConnCloseFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : app conn close frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.88

Field Name : connCloseFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : conn close frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.87

Field Name : connCloseFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : conn close frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.86

Field Name : pathResponseFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : path response frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.85

Field Name : pathResponseFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : path response frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.84

Field Name : pathChallengeFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : path challenge frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.83

Field Name : pathChallengeFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : path challenge frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.82

Field Name : retireConnIdFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : retire conn id frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.81

Field Name : retireConnIdFrameRx

Field Type : CounterBasedGauge64
Field Status : current
Description : retire conn id frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.80

Field Name : newConnIdFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : new conn id frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.79

Field Name : newConnIdFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : new conn id frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.78

Field Name : uniStreamDataBlockedFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : uni stream data blocked frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.77

Field Name : uniStreamDataBlockedFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : uni stream data blocked frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.76

Field Name : biStreamDataBlockedFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : bi stream data blocked frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.75

Field Name : biStreamDataBlockedFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : bi stream data blocked frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.74

Field Name : streamDataBlockedFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream data blocked frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.73

Field Name : streamDataBlockedFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream data blocked frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.72

Field Name : dataBlockedFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : data blocked frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.71

Field Name : dataBlockedFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : data blocked frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.70

Field Name : maxUniStreamFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : max uni stream frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.69

Field Name : maxUniStreamFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : max uni stream frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.68

Field Name : maxBiStreamFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : max bi stream frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.67

Field Name : maxBiStreamFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : max bi stream frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.66

Field Name : maxStreamDataFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : max stream data frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.65

Field Name : maxStreamDataFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : max stream data frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.64

Field Name : maxDataFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : max data frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.63

Field Name : maxDataFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : max data frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.62

Field Name : stream0fFrameTx
Field Type : CounterBasedGauge64
Field Status : current

Description : stream 0f frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.61

Field Name : stream0fFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream 0f frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.60

Field Name : stream0eFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream 0e frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.59

Field Name : stream0eFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream 0e frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.58

Field Name : stream0dFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream 0d frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.57

Field Name : stream0dFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream 0d frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.56

Field Name : stream0cFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream 0c frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.55

Field Name : stream0cFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream 0c frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.54

Field Name : stream0bFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream 0b frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.53

Field Name : stream0bFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream 0b frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.52

Field Name : stream0aFrameTx

Field Type : CounterBasedGauge64
Field Status : current
Description : stream 0a frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.51

Field Name : stream0aFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream 0a frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.50

Field Name : stream09FrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream 09 frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.49

Field Name : stream09FrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream 09 frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.48

Field Name : streamFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.47

Field Name : streamFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.46

Field Name : newTokenFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : new token frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.45

Field Name : newTokenFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : new token frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.44

Field Name : cryptoFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : crypto frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.43

Field Name : cryptoFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : crypto frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.42

Field Name : streamStopFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream stop frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.41

Field Name : streamStopFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream stop frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.40

Field Name : streamRstFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream reset frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.39

Field Name : streamRstFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream reset frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.38

Field Name : ackEcnFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : ack enc frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.37

Field Name : ackEcnFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : ack enc frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.36

Field Name : ackFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : ack frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.35

Field Name : ackFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : ack frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.34

Field Name : pingFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : ping frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.33

Field Name : pingFrameRx
Field Type : CounterBasedGauge64
Field Status : current

Description : ping frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.32

Field Name : paddingFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : padding frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.31

Field Name : paddingFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : padding frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.30

Field Name : streamFailToInsert
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream fail to insert
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.226

Field Name : streamError
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream error
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.26

Field Name : remoteUniStreamClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : Remote uni-stream closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.183

Field Name : localUniStreamClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : Local uni-stream closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.25

Field Name : remoteUniStreamCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Remote uni-stream created
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.24

Field Name : localUniStreamCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Local uni-stream created
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.23

Field Name : remoteUniStreamCurrent
Field Type : CounterBasedGauge64
Field Status : current
Description : Current remote uni-stream
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.230

Field Name : localUniStreamCurrent

Field Type : CounterBasedGauge64
Field Status : current
Description : Current local uni-stream
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.229

Field Name : remoteBiStreamClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : Remote bi-stream closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.182

Field Name : localBiStreamClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : Local bi-stream closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.22

Field Name : remoteBiStreamCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Remote bi-stream created
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.21

Field Name : localBiStreamCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Local bi-stream created
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.20

Field Name : remoteBiStreamCurrent
Field Type : CounterBasedGauge64
Field Status : current
Description : Current remote bi-stream
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.228

Field Name : localBiStreamCurrent
Field Type : CounterBasedGauge64
Field Status : current
Description : Current local bi-stream
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.227

Field Name : qConnFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Q connection freed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.169

Field Name : qConnCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Q connection created
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.168

Field Name : serverConnFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Server connection failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.12

Field Name : serverConnRemoteClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : Server connection remote closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.11

Field Name : serverConnLocalClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : Server connection local closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.10

Field Name : serverConnCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Server connection created
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.9

Field Name : serverConnHandshake
Field Type : CounterBasedGauge64
Field Status : current
Description : Server connection handshake
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.8

Field Name : serverConnAttempted
Field Type : CounterBasedGauge64
Field Status : current
Description : Server connection attempted
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.7

Field Name : clientConnFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Client connection failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.6

Field Name : clientConnRemoteClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : Client connection remote closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.5

Field Name : clientConnLocalClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : Client connection local closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.4

Field Name : clientConnCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Client connection created
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.3

Field Name : clientConnHandshake
Field Type : CounterBasedGauge64
Field Status : current

Description : Client connection handshake
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.2

Field Name : clientConnAttempted
Field Type : CounterBasedGauge64
Field Status : current
Description : Client connection attempted
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.1

Field Name : wafRuleSetSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1

Field Name : wafRuleSetSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1

Field Name : phase4Other
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set other hits in phase 4
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.27

Field Name : phase4Redirect
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set redirect hits in phase 4
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.26

Field Name : phase4Drop
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set drop hits in phase 4
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.25

Field Name : phase4Deny
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set deny hits in phase 4
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.24

Field Name : phase4Allow
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set allow hits in phase 4
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.23

Field Name : phase4Pass
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set pass hits in phase 4
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.22

Field Name : phase3Other

Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set other hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.21

Field Name : phase3Redirect
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set redirect hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.20

Field Name : phase3Drop
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set drop hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.19

Field Name : phase3Deny
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set deny hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.18

Field Name : phase3Allow
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set allow hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.17

Field Name : phase3Pass
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set pass hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.16

Field Name : phase2Other
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set other hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.15

Field Name : phase2Redirect
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set redirect hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.14

Field Name : phase2Drop
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set drop hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.13

Field Name : phase2Deny
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set deny hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.12

Field Name : phase2Allow
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set allow hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.11

Field Name : phase2Pass
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set pass hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.10

Field Name : phase1Other
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set other hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.9

Field Name : phase1Redirect
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set redirect hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.8

Field Name : phase1Drop
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set drop hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.7

Field Name : phase1Deny
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set deny hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.6

Field Name : phase1Allow
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set allow hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.5

Field Name : phase1Pass
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set pass hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.4

Field Name : response
Field Type : CounterBasedGauge64
Field Status : current
Description : Responses hanlded by WAF rule set
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.3

Field Name : request
Field Type : CounterBasedGauge64
Field Status : current

Description : Requests hanlded by WAF rule set
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : WAF Rule set name
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.1

Field Name : phase4Other
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set other hits in phase 4
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.363

Field Name : phase4Redirect
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set redirect hits in phase 4
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.362

Field Name : phase4Drop
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set drop hits in phase 4
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.361

Field Name : phase4Deny
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set deny hits in phase 4
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.360

Field Name : phase4Allow
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set allow hits in phase 4
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.359

Field Name : phase4Pass
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set pass hits in phase 4
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.358

Field Name : phase3Other
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set other hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.357

Field Name : phase3Redirect
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set redirect hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.356

Field Name : phase3Drop

Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set drop hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.355

Field Name : phase3Deny
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set deny hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.354

Field Name : phase3Allow
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set allow hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.353

Field Name : phase3Pass
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set pass hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.352

Field Name : phase2Other
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set other hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.351

Field Name : phase2Redirect
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set redirect hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.350

Field Name : phase2Drop
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set drop hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.349

Field Name : phase2Deny
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set deny hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.348

Field Name : phase2Allow
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set allow hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.347

Field Name : phase2Pass
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set pass hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.346

Field Name : phase1Other
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set other hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.345

Field Name : phase1Redirect
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set redirect hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.344

Field Name : phase1Drop
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set drop hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.343

Field Name : phase1Deny
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set deny hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.342

Field Name : phase1Allow
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set allow hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.341

Field Name : phase1Pass
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set pass hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.340

Field Name : ruleSetResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Responses hanlded by WAF rule set
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.339

Field Name : ruleSetRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Requests hanlded by WAF rule set
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.338

Field Name : cookieSecurityAddSamesiteViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - samesite attribute violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.337

Field Name : cookieSecurityAddSamesiteSuccess
Field Type : CounterBasedGauge64
Field Status : current

Description : Cookie Security - samesite attribute added successfully
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.336

Field Name : httpProtocolNonSslCookiePrefixViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Name Prefix check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.335

Field Name : httpProtocolNonSslCookiePrefixSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Name Prefix check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.334

Field Name : httpProtocolBodyWithoutContentTypeViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Body without content type check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.333

Field Name : httpProtocolBodyWithoutContentTypeSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Body without content type check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.332

Field Name : httpProtocolPostWithoutContentTypeViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : POST without content type check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.331

Field Name : httpProtocolPostWithoutContentTypeSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : POST without content type check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.330

Field Name : actionResponseLog
Field Type : CounterBasedGauge64
Field Status : current
Description : Log response violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.329

Field Name : actionResponseLearn
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Learning Updates
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.328

Field Name : actionResponseDenyCustomResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Deny with custom response
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.327

Field Name : actionResponseDrop

Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Dropped Responses
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.326

Field Name : actionResponseDenyReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Deny with Resets
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.325

Field Name : actionResponseDenyRedirect
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Deny with Redirect
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.324

Field Name : actionResponseDeny403
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Deny with 403
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.323

Field Name : actionResponseDeny200
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Deny with 200
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.322

Field Name : actionResponseAllow
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Action allowed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.321

Field Name : xmlCheckMaxEntityDepthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Entity Depth violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.320

Field Name : xmlCheckMaxEntityDepthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Entity Depth check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.319

Field Name : xmlCheckMaxEntityDeclViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Entity Decl violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.318

Field Name : xmlCheckMaxEntityDeclSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Entity Decl check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.317

Field Name : formResponseNonPostSanitize
Field Type : CounterBasedGauge64
Field Status : current
Description : Changed response form method to POST
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.316

Field Name : formResponseNonPostViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Response form method was not POST
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.315

Field Name : formResponseNonPostSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Response form method was POST
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.314

Field Name : cookieSecurityDecryptInGracePeriodViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Decrypt violation but in grace period
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.313

Field Name : requestCheckCommandInjectionFormBodyViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Command Injection Check form body arguments violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.312

Field Name : requestCheckCommandInjectionFormBodySuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Command Injection Check form body arguments passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.311

Field Name : requestCheckCommandInjectionUriQueryViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Command Injection Check url query arguments violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.310

Field Name : requestCheckCommandInjectionUriQuerySuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Command Injection Check url query arguments passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.309

Field Name : requestCheckCommandInjectionHeadersViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Command Injection Check headers violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.308

Field Name : requestCheckCommandInjectionHeadersSuccess
Field Type : CounterBasedGauge64
Field Status : current

Description : Command Injection Check headers passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.307

Field Name : requestCheckCommandInjectionCookiesViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Command Injection Check cookies violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.306

Field Name : requestCheckCommandInjectionCookiesSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Command Injection Check cookies passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.305

Field Name : regexViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Regular expression failure
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.304

Field Name : tooManySessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Too many sessions consumed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.303

Field Name : outOfSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of sessions
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.302

Field Name : sessionsFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.301

Field Name : sessionsAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Sessions allocated
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.300

Field Name : policyLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Policy limit exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.299

Field Name : actionLog
Field Type : CounterBasedGauge64
Field Status : current
Description : Log request violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.298

Field Name : actionLearn

Field Type : CounterBasedGauge64
Field Status : current
Description : Request Learning Updates
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.297

Field Name : actionDenyCustomResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Deny with custom response
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.296

Field Name : actionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Dropped Requests
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.295

Field Name : actionDenyReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Deny with Resets
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.294

Field Name : actionDenyRedirect
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Deny with Redirect
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.293

Field Name : actionDeny403
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Deny with 403
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.292

Field Name : actionDeny200
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Deny with 200
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.291

Field Name : actionAllow
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Action allowed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.290

Field Name : learningListFull
Field Type : CounterBasedGauge64
Field Status : current
Description : Learning list is full
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.289

Field Name : xmlContentCheckWsdlViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : WSDL violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.288

Field Name : xmlContentCheckWsdlSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : WSDL passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.287

Field Name : xmlContentCheckSchemaViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Schema violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.286

Field Name : xmlContentCheckSchemaSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Schema passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.285

Field Name : xmlCheckXssViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML XSS Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.284

Field Name : xmlCheckXssSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML XSS Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.283

Field Name : xmlCheckSqliaViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Sqlia Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.282

Field Name : xmlCheckSqliaSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Sqlia Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.281

Field Name : xmlCheckNamespaceUriLenViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Namespace URI Length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.280

Field Name : xmlCheckNamespaceUriLenSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Namespace URI Length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.279

Field Name : xmlCheckMaxNamespaceViolation
Field Type : CounterBasedGauge64
Field Status : current

Description : XML Limit Namespace violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.278

Field Name : xmlCheckMaxNamespaceSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Namespace check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.277

Field Name : xmlCheckMaxEntityExpDepthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Entities Depth violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.276

Field Name : xmlCheckMaxEntityExpDepthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Entities Depth check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.275

Field Name : xmlCheckMaxEntityExpViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Entity Expansions violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.274

Field Name : xmlCheckMaxEntityExpSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Entity Expansions check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.273

Field Name : xmlCheckMaxElemNameLenViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Element Name Length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.272

Field Name : xmlCheckMaxElemNameLenSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Element Name Length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.271

Field Name : xmlCheckMaxElemDepthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Element Depth violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.270

Field Name : xmlCheckMaxElemDepthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Element Depth check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.269

Field Name : xmlCheckMaxElemChildViolation

Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Element Child violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.268

Field Name : xmlCheckMaxElemChildSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Element Child check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.267

Field Name : xmlCheckMaxElemViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Element violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.266

Field Name : xmlCheckMaxElemSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Element check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.265

Field Name : xmlCheckMaxCdataLenViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit CData Length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.264

Field Name : xmlCheckMaxCdataLenSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit CData Length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.263

Field Name : xmlCheckMaxAttrValueLenViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Value Length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.262

Field Name : xmlCheckMaxAttrValueLenSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Value Length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.261

Field Name : xmlCheckMaxAttrNameLenViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Name Length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.260

Field Name : xmlCheckMaxAttrNameLenSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Name Length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.259

Field Name : xmlCheckMaxAttrViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Attribute violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.258

Field Name : xmlCheckMaxAttrSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Attribute check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.257

Field Name : xmlCheckFormatViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.256

Field Name : xmlCheckFormatSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.255

Field Name : soapCheckViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Soap Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.254

Field Name : soapCheckSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Soap Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.253

Field Name : responseCloakingFilterHeadersViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Headers Filter violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.252

Field Name : responseCloakingFilterHeadersSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Headers Filter check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.251

Field Name : responseCloakingHideStatusCodeViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Hide Code violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.250

Field Name : responseCloakingHideStatusCodeSuccess
Field Type : CounterBasedGauge64
Field Status : current

Description : Response Hide Code check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.249

Field Name : requestCheckXssPostBodySanitize
Field Type : CounterBasedGauge64
Field Status : current
Description : XSS Check Post Sanitized
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.248

Field Name : requestCheckXssPostBodyViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XSS Check Post violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.247

Field Name : requestCheckXssPostBodySuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XSS Check Post passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.246

Field Name : requestCheckXssUrlSanitize
Field Type : CounterBasedGauge64
Field Status : current
Description : XSS Check URL Sanitized
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.245

Field Name : requestCheckXssUrlViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XSS Check URL violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.244

Field Name : requestCheckXssUrlSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XSS Check URL passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.243

Field Name : requestCheckXssCookieSanitize
Field Type : CounterBasedGauge64
Field Status : current
Description : XSS Check Cookie Sanitized
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.242

Field Name : requestCheckXssCookieViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XSS Check Cookie violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.241

Field Name : requestCheckXssCookieSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XSS Check Cookie passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.240

Field Name : requestCheckUrlBlacklistViolation

Field Type : CounterBasedGauge64
Field Status : current
Description : URI Black List violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.239

Field Name : requestCheckUrlBlacklistSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : URI Black List passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.238

Field Name : requestCheckUrlWhitelistViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : URI White List violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.237

Field Name : requestCheckUrlWhitelistSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : URI White List passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.236

Field Name : requestCheckUrlListLearn
Field Type : CounterBasedGauge64
Field Status : current
Description : URL Check Learn
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.235

Field Name : requestCheckUrlListViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : URL Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.234

Field Name : requestCheckUrlListSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : URL Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.233

Field Name : requestCheckSqliaPostBodySanitize
Field Type : CounterBasedGauge64
Field Status : current
Description : SQLIA Check Post Sanitized
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.232

Field Name : requestCheckSqliaPostBodyViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : SQLIA Check Post violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.231

Field Name : requestCheckSqliaPostBodySuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : SQLIA Check Post passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.230

Field Name : requestCheckSqliaUrlSanitize
Field Type : CounterBasedGauge64
Field Status : current
Description : SQLIA Check URL Sanitized
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.229

Field Name : requestCheckSqliaUrlViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : SQLIA Check URL violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.228

Field Name : requestCheckSqliaUrlSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : SQLIA Check URL passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.227

Field Name : requestCheckSessionCheckViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.226

Field Name : requestCheckSessionCheckSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.225

Field Name : requestCheckSessionCheckNone
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.224

Field Name : requestCheckRefererRedirect
Field Type : CounterBasedGauge64
Field Status : current
Description : Referer Check Redirect
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.223

Field Name : requestCheckRefererViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Referer Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.222

Field Name : requestCheckRefererSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Referer Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.221

Field Name : requestCheckRedirectWlistLearn
Field Type : CounterBasedGauge64
Field Status : current

Description : Redirect Whitelist Learn
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.220

Field Name : requestCheckRedirectWlistViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Redirect Whitelist violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.219

Field Name : requestCheckRedirectWlistSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Redirect Whitelist passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.218

Field Name : requestCheckBotViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Bot check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.217

Field Name : requestCheckBotSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Bot check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.216

Field Name : jsonCheckMaxStringViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Limit String violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.215

Field Name : jsonCheckMaxStringSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Limit String check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.214

Field Name : jsonCheckMaxObjectMemberCountViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Limit Object Number Count violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.213

Field Name : jsonCheckMaxObjectMemberCountSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Limit Object Number Count check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.212

Field Name : jsonCheckMaxDepthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Limit Depth violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.211

Field Name : jsonCheckMaxDepthSuccess

Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Limit Depth check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.210

Field Name : jsonCheckMaxArrayValueCountViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Limit Array Value Count violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.209

Field Name : jsonCheckMaxArrayValueCountSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Limit Array Value Count check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.208

Field Name : jsonCheckFormatViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.207

Field Name : jsonCheckFormatSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.206

Field Name : httpProtocolViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.205

Field Name : httpProtocolSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.204

Field Name : httpProtocolPostWithoutContentViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : POST without content check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.203

Field Name : httpProtocolPostWithoutContentSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : POST without content check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.202

Field Name : httpProtocolPostWith0ContentViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : POST with 0 content check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.201

Field Name : httpProtocolPostWith0ContentSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : POST with 0 content check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.200

Field Name : httpProtocolMultipleContentLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Multiple content-length headers check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.199

Field Name : httpProtocolMultipleContentLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Multiple content-length headers check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.198

Field Name : httpProtocolMissingHostHeaderViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Missing host header check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.197

Field Name : httpProtocolMissingHostHeaderSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Missing host header check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.196

Field Name : httpProtocolMissingHeaderValueViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Missing header value check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.195

Field Name : httpProtocolMissingHeaderValueSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Missing header value check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.194

Field Name : httpProtocolMalformedRequestLineViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed request line check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.193

Field Name : httpProtocolMalformedRequestLineSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed request line check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.192

Field Name : httpProtocolMalformedRequestViolation
Field Type : CounterBasedGauge64
Field Status : current

Description : Malformed request check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.191

Field Name : httpProtocolMalformedRequestSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed request check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.190

Field Name : httpProtocolMalformedParameterViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed parameter check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.189

Field Name : httpProtocolMalformedParameterSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed parameter check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.188

Field Name : httpProtocolMalformedHeaderViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed header check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.187

Field Name : httpProtocolMalformedHeaderSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed header check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.186

Field Name : httpProtocolMalformedContentLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed content-length check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.185

Field Name : httpProtocolMalformedContentLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed content-length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.184

Field Name : httpProtocolInvalidUrlEncodingViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid url encoding check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.183

Field Name : httpProtocolInvalidUrlEncodingSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid url encoding check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.182

Field Name : httpProtocolHostHeaderWithIpViolation

Field Type : CounterBasedGauge64
Field Status : current
Description : Host header with IP check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.181

Field Name : httpProtocolHostHeaderWithIpSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Host header with IP check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.180

Field Name : httpProtocolHeadWithContentViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : HEAD with content check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.179

Field Name : httpProtocolHeadWithContentSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HEAD with content check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.178

Field Name : httpProtocolGetWithContentViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : GET with content check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.177

Field Name : httpProtocolGetWithContentSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : GET with content check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.176

Field Name : httpProtocolBadMultipartRequestViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad multi-part request check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.175

Field Name : httpProtocolBadMultipartRequestSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad multi-part request check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.174

Field Name : httpProtocolAllowedMethodCheckViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Method Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.173

Field Name : httpProtocolAllowedMethodCheckSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Method Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.172

Field Name : httpProtocolAllowedVersionsViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP versions check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.171

Field Name : httpProtocolAllowedVersionsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP versions check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.170

Field Name : httpProtocolAllowedHeadersViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP headers check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.169

Field Name : httpProtocolAllowedHeadersSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP headers check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.168

Field Name : maxUrlLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX URL length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.167

Field Name : maxUrlLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX URL length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.166

Field Name : httpLimitMaxRequestLineLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX request line length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.165

Field Name : httpLimitMaxRequestLineLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX request line length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.164

Field Name : httpLimitMaxRequestLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX request length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.163

Field Name : httpLimitMaxRequestLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current

Description : Limit check - MAX request length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.162

Field Name : httpLimitMaxQueryLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX query length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.161

Field Name : httpLimitMaxQueryLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX query length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.160

Field Name : httpLimitMaxPostLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX POST length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.159

Field Name : httpLimitMaxPostLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX POST length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.158

Field Name : httpLimitMaxParamsLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX parameters total length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.157

Field Name : httpLimitMaxParamsLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX parameters total length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.156

Field Name : httpLimitMaxParamsViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX parameters violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.155

Field Name : httpLimitMaxParamsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX parameters check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.154

Field Name : httpLimitMaxParamValueLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX parameter value length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.153

Field Name : httpLimitMaxParamValueLengthSuccess

Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX parameter value length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.152

Field Name : httpLimitMaxParamNameLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX parameter name length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.151

Field Name : httpLimitMaxParamNameLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX parameter name length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.150

Field Name : httpLimitMaxHeadersLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX headers length check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.149

Field Name : httpLimitMaxHeadersLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX headers length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.148

Field Name : httpLimitMaxHeadersViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Headers violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.147

Field Name : httpLimitMaxHeadersSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX headers count check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.146

Field Name : httpLimitMaxHeaderValueLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX header value length check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.145

Field Name : httpLimitMaxHeaderValueLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX header value length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.144

Field Name : httpLimitMaxHeaderNameLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX header name length check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.143

Field Name : httpLimitMaxHeaderNameLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX header name length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.142

Field Name : httpLimitMaxHeaderLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX header length check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.141

Field Name : httpLimitMaxHeaderLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX header length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.140

Field Name : httpLimitMaxEntitiesViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Entities violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.139

Field Name : httpLimitMaxEntitiesSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Entities check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.138

Field Name : httpLimitMaxDataParseViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Buffer Overflow - Max Data Parse violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.137

Field Name : httpLimitMaxDataParseSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Buffer Overflow - Max Data Parse check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.136

Field Name : httpLimitMaxCookiesLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX cookies length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.135

Field Name : httpLimitMaxCookiesLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX cookies length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.134

Field Name : httpLimitMaxCookiesViolation
Field Type : CounterBasedGauge64
Field Status : current

Description : Max Cookies violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.133

Field Name : httpLimitMaxCookiesSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Cookies check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.132

Field Name : httpLimitMaxCookieValueLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX cookie value length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.131

Field Name : httpLimitMaxCookieValueLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX cookie value length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.130

Field Name : httpLimitMaxCookieNameLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX cookie name length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.129

Field Name : httpLimitMaxCookieNameLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX cookie name length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.128

Field Name : httpLimitMaxCookieHeaderLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX cookie header length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.127

Field Name : httpLimitMaxCookieHeaderLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX cookie header length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.126

Field Name : httpLimitMaxContentLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX content-length check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.125

Field Name : httpLimitMaxContentLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX content-length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.124

Field Name : evasionCheckRemoveSpacesViolation

Field Type : CounterBasedGauge64
Field Status : current
Description : Remove Spaces check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.123

Field Name : evasionCheckRemoveSpacesSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Remove Spaces check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.122

Field Name : evasionCheckRemoveCommentsViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Remove Comments check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.121

Field Name : evasionCheckRemoveCommentsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Remove Comments check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.120

Field Name : evasionCheckMaxLevelsViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Levels check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.119

Field Name : evasionCheckMaxLevelsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Levels check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.118

Field Name : evasionCheckMultipleSlashesViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Multiple Slashes check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.117

Field Name : evasionCheckMultipleSlashesSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Multiple Slashes check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.116

Field Name : evasionCheckMultipleEncodingLevelsViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Multiple Encoding Levels check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.115

Field Name : evasionCheckMultipleEncodingLevelsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Multiple Encoding Levels check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.114

Field Name : evasionCheckInvalidHexEncodingViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid Hex Encoding check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.113

Field Name : evasionCheckInvalidHexEncodingSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid Hex Encoding check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.112

Field Name : evasionCheckHighAsciiBytesViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : High Ascii Bytes check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.111

Field Name : evasionCheckHighAsciiBytesSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : High Ascii Bytes check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.110

Field Name : evasionCheckDirTraversalViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Dir traversal check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.109

Field Name : evasionCheckDirTraversalSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Dir traversal check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.108

Field Name : evasionCheckDecodeUnicodeCharsViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Decode Unicode Chars check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.107

Field Name : evasionCheckDecodeUnicodeCharsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Decode Unicode Chars check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.106

Field Name : evasionCheckDecodeEscapedCharsViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Decode Escaped Chars check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.105

Field Name : evasionCheckDecodeEscapedCharsSuccess
Field Type : CounterBasedGauge64
Field Status : current

Description : Decode Escaped Chars check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.104

Field Name : evasionCheckDecodeEntitiesViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Decode Entities check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.103

Field Name : evasionCheckDecodeEntitiesSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Decode Entities check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.102

Field Name : evasionCheckApacheWhitespaceViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Apache Whitespace check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.101

Field Name : evasionCheckApacheWhitespaceSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Apache Whitespace check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.100

Field Name : dlpPcreMasked
Field Type : CounterBasedGauge64
Field Status : current
Description : PCRE Mask violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.99

Field Name : dlpPcreViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : PCRE Mask violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.98

Field Name : dlpPcreSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : PCRE Mask check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.97

Field Name : dlpSsnViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Social Security Number Mask violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.96

Field Name : dlpSsnSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Social Security Number Mask check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.95

Field Name : dlpCcnJcbMasked

Field Type : CounterBasedGauge64
Field Status : current
Description : JCB Credit Card Number Masked
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.94

Field Name : dlpCcnJcbViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : JCB Credit Card Number Detected
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.93

Field Name : dlpCcnDiscoverMasked
Field Type : CounterBasedGauge64
Field Status : current
Description : Discover Credit Card Number Masked
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.92

Field Name : dlpCcnDiscoverViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Discover Credit Card Number Detected
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.91

Field Name : dlpCcnMastercardMasked
Field Type : CounterBasedGauge64
Field Status : current
Description : MasterCard Credit Card Number Masked
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.90

Field Name : dlpCcnMastercardViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MasterCard Credit Card Number Detected
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.89

Field Name : dlpCcnVisaMasked
Field Type : CounterBasedGauge64
Field Status : current
Description : Visa Credit Card Number Masked
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.88

Field Name : dlpCcnVisaViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Visa Credit Card Number Detected
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.87

Field Name : dlpCcnDinersMasked
Field Type : CounterBasedGauge64
Field Status : current
Description : Diners Club Credit Card Number Masked
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.86

Field Name : dlpCcnDinersViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Diners Club Credit Card Number Detected
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.85

Field Name : dlpCcnAmexMasked
Field Type : CounterBasedGauge64
Field Status : current
Description : Amex Credit Card Number Masked
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.84

Field Name : dlpCcnAmexViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Amex Credit Card Number Detected
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.83

Field Name : dlpCcnSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Credit Card Number check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.82

Field Name : formSetNoCache
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Set No Cache violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.81

Field Name : formSetNoCacheSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Set No Cache check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.80

Field Name : formPasswordAutocompleteViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Password Autocomplete violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.79

Field Name : formPasswordAutocompleteSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Password Autocomplete check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.78

Field Name : formNonSslPasswordViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Non SSL Password violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.77

Field Name : formNonSslPasswordSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Non SSL Password check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.76

Field Name : formNonMaskedPasswordViolation
Field Type : CounterBasedGauge64
Field Status : current

Description : Form Non Masked Password violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.75

Field Name : formNonMaskedPasswordSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Non Masked Password check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.74

Field Name : formCheckSanitize
Field Type : CounterBasedGauge64
Field Status : current
Description : Post Form Check Sanitized
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.73

Field Name : formCheckViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Post Form Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.72

Field Name : formCheckSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Post Form Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.71

Field Name : formRequestNonPostViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Method being Non Post in Request violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.70

Field Name : formRequestNonPostSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Method being Non Post in Request passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.69

Field Name : formNonSslViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Non SSL violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.68

Field Name : formNonSslSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Non SSL check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.67

Field Name : formTagInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Form A10 Tag Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.66

Field Name : formConsistencyViolation

Field Type : CounterBasedGauge64
Field Status : current
Description : Form Consistency violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.65

Field Name : formConsistencySuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Consistency passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.64

Field Name : formCsrfTagViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Form CSRF tag violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.63

Field Name : formCsrfTagSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Form CSRF tag passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.62

Field Name : cspHeaderInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : CSP header Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.61

Field Name : cspHeaderSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : CSP header found
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.60

Field Name : cspHeaderViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : CSP header_missing
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.59

Field Name : cookieSecurityDisallowedPersistentSetCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - disallowed persistent Set-Cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.58

Field Name : cookieSecurityDisallowedSessionSetCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - disallowed session Set-Cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.57

Field Name : cookieSecurityAllowedPersistentSetCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - allowed persistent Set-Cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.56

Field Name : cookieSecurityAllowedSessionSetCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - allowed session Set-Cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.55

Field Name : cookieSecurityDisallowedPersistentCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - disallowed persistent cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.54

Field Name : cookieSecurityDisallowedSessionCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - disallowed session cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.53

Field Name : cookieSecurityAllowedPersistentCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - allowed persistent cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.52

Field Name : cookieSecurityAllowedSessionCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - allowed session cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.51

Field Name : cookieSecuritySessionCookiesSigned
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - signed session cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.50

Field Name : cookieSecuritySessionCookiesEncrypted
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - encrypted session cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.49

Field Name : cookieSecuritySessionCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - session cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.48

Field Name : cookieSecurityPersistentCookiesSigned
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - signed persistent cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.47

Field Name : cookieSecurityPersistentCookiesEncrypted
Field Type : CounterBasedGauge64
Field Status : current

Description : Cookie Security - encrypted persistent cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.46

Field Name : cookieSecurityPersistentCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - persistent cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.45

Field Name : cookieSecurityCookiePolicyViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - cookie policy violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.44

Field Name : cookieSecurityCookiePolicySuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - cookie policy passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.43

Field Name : cookieSecurityUnrecognizedCookieViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - unrecognized cookie violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.42

Field Name : cookieSecurityUnrecognizedCookieSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - request with unrecognized cookie
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.41

Field Name : cookieSecurityMissingCookieViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - missing cookie violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.40

Field Name : cookieSecurityMissingCookieSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - request with missing cookie
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.39

Field Name : cookieSecurityAddSecureViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - secure flag violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.38

Field Name : cookieSecurityAddSecureSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - secure flag added successfully
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.37

Field Name : cookieSecurityAddHttpOnlyViolation

Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - http-only flag violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.36

Field Name : cookieSecurityAddHttpOnlySuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - http-only flag added successfully
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.35

Field Name : cookieSecuritySignatureCheckViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - signature check failed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.34

Field Name : cookieSecuritySignatureCheckSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - signature check successful
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.33

Field Name : cookieSecuritySignSkipRcache
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - signing skipped - RAM cache
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.32

Field Name : cookieSecuritySignLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - signing limit exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.31

Field Name : cookieSecuritySignViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - signing violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.30

Field Name : cookieSecuritySignSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - signing successful
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.29

Field Name : cookieSecurityDecryptViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - decrypt violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.28

Field Name : cookieSecurityDecryptSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - decrypt successful
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.27

Field Name : cookieSecurityEncryptSkipRcache
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - encrypt skipped - RAM cache
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.26

Field Name : cookieSecurityEncryptLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - encrypt limit exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.25

Field Name : cookieSecurityEncryptViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - encrypt violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.24

Field Name : cookieSecurityEncryptSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - encrypt successful
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.23

Field Name : bruteForceResponseStringTriggered
Field Type : CounterBasedGauge64
Field Status : current
Description : Brute Force Response string Triggered
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.22

Field Name : bruteForceResponseHeadersTriggered
Field Type : CounterBasedGauge64
Field Status : current
Description : Brute Force Response Headers Triggered
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.21

Field Name : bruteForceResponseCodesTriggered
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Codes Triggered
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.20

Field Name : bruteForceChallengeLimitViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Lockout limit violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.19

Field Name : bruteForceChallengeLimitSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Lockout limit check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.18

Field Name : bruteForceLockoutLimitViolation
Field Type : CounterBasedGauge64
Field Status : current

Description : Lockout limit violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.17

Field Name : bruteForceLockoutLimitSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Lockout limit check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.16

Field Name : bruteForceChallengeCaptchaViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Captcha challenge violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.15

Field Name : bruteForceChallengeCaptchaSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Captcha challenge check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.14

Field Name : bruteForceChallengeCaptchaSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Captcha challenge sent
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.13

Field Name : bruteForceChallengeJavascriptViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : JavaScript challenge violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.12

Field Name : bruteForceChallengeJavascriptSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : JavaScript challenge check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.11

Field Name : bruteForceChallengeJavascriptSent
Field Type : CounterBasedGauge64
Field Status : current
Description : JavaScript challenge sent
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.10

Field Name : bruteForceChallengeCookieViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie challenge violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.9

Field Name : bruteForceChallengeCookieSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Challenge check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.8

Field Name : bruteForceChallengeCookieSent

Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Challenge Sent
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.7

Field Name : bruteForceViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Brute-Force checks violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.6

Field Name : bruteForceSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Brute-Force checks passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.5

Field Name : respDenied
Field Type : CounterBasedGauge64
Field Status : current
Description : Responses Denied
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.4

Field Name : reqDenied
Field Type : CounterBasedGauge64
Field Status : current
Description : Requests Denied
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.3

Field Name : reqAllowed
Field Type : CounterBasedGauge64
Field Status : current
Description : Requests Allowed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.2

Field Name : totalReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Requests
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.1

Field Name : wafTemplateSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1

Field Name : wafTemplateSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1

Field Name : phase4Other
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set other hits in phase 4
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.364

Field Name : phase4Redirect
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set redirect hits in phase 4
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.363

Field Name : phase4Drop
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set drop hits in phase 4
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.362

Field Name : phase4Deny
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set deny hits in phase 4
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.361

Field Name : phase4Allow
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set allow hits in phase 4
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.360

Field Name : phase4Pass
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set pass hits in phase 4
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.359

Field Name : phase3Other
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set other hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.358

Field Name : phase3Redirect
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set redirect hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.357

Field Name : phase3Drop
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set drop hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.356

Field Name : phase3Deny
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set deny hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.355

Field Name : phase3Allow
Field Type : CounterBasedGauge64
Field Status : current

Description : WAF rule set allow hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.354

Field Name : phase3Pass
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set pass hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.353

Field Name : phase2Other
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set other hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.352

Field Name : phase2Redirect
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set redirect hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.351

Field Name : phase2Drop
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set drop hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.350

Field Name : phase2Deny
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set deny hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.349

Field Name : phase2Allow
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set allow hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.348

Field Name : phase2Pass
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set pass hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.347

Field Name : phase1Other
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set other hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.346

Field Name : phase1Redirect
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set redirect hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.345

Field Name : phase1Drop

Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set drop hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.344

Field Name : phase1Deny
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set deny hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.343

Field Name : phase1Allow
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set allow hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.342

Field Name : phase1Pass
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set pass hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.341

Field Name : ruleSetResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Responses hanlded by WAF rule set
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.340

Field Name : ruleSetRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Requests hanlded by WAF rule set
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.339

Field Name : wafTemplatecookieSecurityAddSamesiteViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - samesite attribute violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.338

Field Name : wafTemplatecookieSecurityAddSamesiteSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - samesite attribute added successfully
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.337

Field Name : wafTemplatehttpProtocolNonSslCookiePrefixViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Name Prefix check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.336

Field Name : wafTemplatehttpProtocolNonSslCookiePrefixSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Name Prefix check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.335

Field Name : wafTemplatehttpProtocolBodyWithoutContentTypeViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Body without content type check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.334

Field Name : wafTemplatehttpProtocolBodyWithoutContentTypeSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Body without content type check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.333

Field Name : wafTemplatehttpProtocolPostWithoutContentTypeViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : POST without content type check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.332

Field Name : wafTemplatehttpProtocolPostWithoutContentTypeSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : POST without content type check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.331

Field Name : wafTemplateResponseActionLog
Field Type : CounterBasedGauge64
Field Status : current
Description : Log response violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.330

Field Name : wafTemplateResponseActionLearn
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Learning Updates
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.329

Field Name : wafTemplateResponseActionDenyCustomResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Deny with custom response
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.328

Field Name : wafTemplateResponseActionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Dropped Responses
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.327

Field Name : wafTemplateResponseActionDenyReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Deny with Resets
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.326

Field Name : wafTemplateResponseActionDenyRedirect
Field Type : CounterBasedGauge64
Field Status : current

Description : Response Deny with Redirect
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.325

Field Name : wafTemplateResponseActionDeny403
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Deny with 403
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.324

Field Name : wafTemplateResponseActionDeny200
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Deny with 200
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.323

Field Name : wafTemplateResponseActionAllow
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Action allowed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.322

Field Name : wafTemplatexmlCheckMaxEntityDepthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Entity Depth violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.321

Field Name : wafTemplatexmlCheckMaxEntityDepthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Entity Depth check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.320

Field Name : wafTemplatexmlCheckMaxEntityDeclViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Entity Decl violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.319

Field Name : wafTemplatexmlCheckMaxEntityDeclSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Entity Decl check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.318

Field Name : wafTemplateformResponseNonPostSanitize
Field Type : CounterBasedGauge64
Field Status : current
Description : Changed response form method to POST
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.317

Field Name : wafTemplateformResponseNonPostViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Response form method was not POST
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.316

Field Name : wafTemplateformResponseNonPostSuccess

Field Type : CounterBasedGauge64
Field Status : current
Description : Response form method was POST
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.315

Field Name : wafTemplatecookieSecurityDecryptInGracePeriodViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Decrypt violation but in grace period
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.314

Field Name : wafTemplateRequestCheckCommandInjectionFormBodyViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Command Injection Check form body arguments violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.313

Field Name : wafTemplateRequestCheckCommandInjectionFormBodySuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Command Injection Check form body arguments passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.312

Field Name : wafTemplateRequestCheckCommandInjectionUrlQueryViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Command Injection Check url query arguments violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.311

Field Name : wafTemplateRequestCheckCommandInjectionUrlQuerySuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Command Injection Check url query arguments passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.310

Field Name : wafTemplateRequestCheckCommandInjectionHeadersViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Command Injection Check headers violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.309

Field Name : wafTemplateRequestCheckCommandInjectionHeadersSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Command Injection Check headers passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.308

Field Name : wafTemplateRequestCheckCommandInjectionCookiesViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Command Injection Check cookies violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.307

Field Name : wafTemplateRequestCheckCommandInjectionCookiesSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Command Injection Check cookies passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.306

Field Name : wafTemplateregexViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Regular expression failure
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.305

Field Name : wafTemplatetooManySessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Too many sessions consumed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.304

Field Name : wafTemplateoutOfSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of sessions
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.303

Field Name : wafTemplatesessionsFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.302

Field Name : wafTemplatesessionsAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Sessions allocated
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.301

Field Name : wafTemplatepolicyLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Policy limit exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.300

Field Name : wafTemplateactionLog
Field Type : CounterBasedGauge64
Field Status : current
Description : Log request violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.299

Field Name : wafTemplateactionLearn
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Learning Updates
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.298

Field Name : wafTemplateactionDenyCustomResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Deny with custom response
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.297

Field Name : wafTemplateactionDrop
Field Type : CounterBasedGauge64
Field Status : current

Description : Number of Dropped Requests
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.296

Field Name : wafTemplateactionDenyReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Deny with Resets
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.295

Field Name : wafTemplateactionDenyRedirect
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Deny with Redirect
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.294

Field Name : wafTemplateactionDeny403
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Deny with 403
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.293

Field Name : wafTemplateactionDeny200
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Deny with 200
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.292

Field Name : wafTemplateactionAllow
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Action allowed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.291

Field Name : wafTemplatelearningListFull
Field Type : CounterBasedGauge64
Field Status : current
Description : Learning list is full
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.290

Field Name : wafTemplatexmlContentCheckWsdlViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : WSDL violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.289

Field Name : wafTemplatexmlContentCheckWsdlSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : WSDL passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.288

Field Name : wafTemplatexmlContentCheckSchemaViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Schema violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.287

Field Name : wafTemplatexmlContentCheckSchemaSuccess

Field Type : CounterBasedGauge64
Field Status : current
Description : XML Schema passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.286

Field Name : wafTemplatexmlCheckXssViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML XSS Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.285

Field Name : wafTemplatexmlCheckXssSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML XSS Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.284

Field Name : wafTemplatexmlCheckSqliaViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Sqlia Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.283

Field Name : wafTemplatexmlCheckSqliaSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Sqlia Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.282

Field Name : wafTemplatexmlCheckNamespaceUriLenViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Namespace URI Length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.281

Field Name : wafTemplatexmlCheckNamespaceUriLenSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Namespace URI Length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.280

Field Name : wafTemplatexmlCheckMaxNamespaceViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Namespace violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.279

Field Name : wafTemplatexmlCheckMaxNamespaceSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Namespace check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.278

Field Name : wafTemplatexmlCheckMaxEntityExpDepthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Entities Depth violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.277

Field Name : wafTemplatexmlCheckMaxEntityExpDepthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Entities Depth check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.276

Field Name : wafTemplatexmlCheckMaxEntityExpViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Entity Decl violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.275

Field Name : wafTemplatexmlCheckMaxEntityExpSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Entity Decl check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.274

Field Name : wafTemplatexmlCheckMaxElemNameLenViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Element Name Length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.273

Field Name : wafTemplatexmlCheckMaxElemNameLenSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Element Name Length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.272

Field Name : wafTemplatexmlCheckMaxElemDepthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Element Depth violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.271

Field Name : wafTemplatexmlCheckMaxElemDepthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Element Depth check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.270

Field Name : wafTemplatexmlCheckMaxElemChildViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Element Child violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.269

Field Name : wafTemplatexmlCheckMaxElemChildSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Element Child check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.268

Field Name : wafTemplatexmlCheckMaxElemViolation
Field Type : CounterBasedGauge64
Field Status : current

Description : XML Limit Element violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.267

Field Name : wafTemplatexmlCheckMaxElemSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Element check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.266

Field Name : wafTemplatexmlCheckMaxCdataLenViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit CData Length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.265

Field Name : wafTemplatexmlCheckMaxCdataLenSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit CData Length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.264

Field Name : wafTemplatexmlCheckMaxAttrValueLenViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Value Length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.263

Field Name : wafTemplatexmlCheckMaxAttrValueLenSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Value Length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.262

Field Name : wafTemplatexmlCheckMaxAttrNameLenViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Name Length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.261

Field Name : wafTemplatexmlCheckMaxAttrNameLenSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Name Length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.260

Field Name : wafTemplatexmlCheckMaxAttrViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Attribute violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.259

Field Name : wafTemplatexmlCheckMaxAttrSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Attribute check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.258

Field Name : wafTemplatexmlCheckFormatViolation

Field Type : CounterBasedGauge64
Field Status : current
Description : XML Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.257

Field Name : wafTemplatexmlCheckFormatSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.256

Field Name : wafTemplatesoapCheckViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Soap Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.255

Field Name : wafTemplatesoapCheckSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Soap Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.254

Field Name : wafTemplateresponseCloakingFilterHeadersViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Headers Filter violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.253

Field Name : wafTemplateresponseCloakingFilterHeadersSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Headers Filter check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.252

Field Name : wafTemplateresponseCloakingHideStatusCodeViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Hide Code violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.251

Field Name : wafTemplateresponseCloakingHideStatusCodeSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Hide Code check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.250

Field Name : wafTemplaterequestCheckXssPostBodySanitize
Field Type : CounterBasedGauge64
Field Status : current
Description : XSS Check Post Sanitized
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.249

Field Name : wafTemplaterequestCheckXssPostBodyViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XSS Check Post violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.248

Field Name : wafTemplaterequestCheckXssPostBodySuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XSS Check Post passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.247

Field Name : wafTemplaterequestCheckXssUrlSanitize
Field Type : CounterBasedGauge64
Field Status : current
Description : XSS Check URL Sanitized
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.246

Field Name : wafTemplaterequestCheckXssUrlViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XSS Check URL violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.245

Field Name : wafTemplaterequestCheckXssUrlSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XSS Check URL passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.244

Field Name : wafTemplaterequestCheckXssCookieSanitize
Field Type : CounterBasedGauge64
Field Status : current
Description : XSS Check Cookie Sanitized
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.243

Field Name : wafTemplaterequestCheckXssCookieViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XSS Check Cookie violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.242

Field Name : wafTemplaterequestCheckXssCookieSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XSS Check Cookie passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.241

Field Name : wafTemplaterequestCheckUrlBlacklistViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : URI Black List violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.240

Field Name : wafTemplaterequestCheckUrlBlacklistSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : URI Black List passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.239

Field Name : wafTemplaterequestCheckUrlWhitelistViolation
Field Type : CounterBasedGauge64
Field Status : current

Description : URI White List violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.238

Field Name : wafTemplaterequestCheckUrlWhitelistSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : URI White List passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.237

Field Name : wafTemplaterequestCheckUrlListLearn
Field Type : CounterBasedGauge64
Field Status : current
Description : URL Check Learn
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.236

Field Name : wafTemplaterequestCheckUrlListViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : URL Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.235

Field Name : wafTemplaterequestCheckUrlListSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : URL Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.234

Field Name : wafTemplaterequestCheckSqliaPostBodySanitize
Field Type : CounterBasedGauge64
Field Status : current
Description : SQLIA Check Post Sanitized
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.233

Field Name : wafTemplaterequestCheckSqliaPostBodyViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : SQLIA Check Post violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.232

Field Name : wafTemplaterequestCheckSqliaPostBodySuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : SQLIA Check Post passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.231

Field Name : wafTemplaterequestCheckSqliaUrlSanitize
Field Type : CounterBasedGauge64
Field Status : current
Description : SQLIA Check URL Sanitized
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.230

Field Name : wafTemplaterequestCheckSqliaUrlViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : SQLIA Check URL violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.229

Field Name : wafTemplaterequestCheckSqliaUrlSuccess

Field Type : CounterBasedGauge64
Field Status : current
Description : SQLIA Check URL passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.228

Field Name : wafTemplaterequestCheckSessionCheckViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.227

Field Name : wafTemplaterequestCheckSessionCheckSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.226

Field Name : wafTemplaterequestCheckSessionCheckNone
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.225

Field Name : wafTemplaterequestCheckRefererRedirect
Field Type : CounterBasedGauge64
Field Status : current
Description : Referer Check Redirect
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.224

Field Name : wafTemplaterequestCheckRefererViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Referer Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.223

Field Name : wafTemplaterequestCheckRefererSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Referer Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.222

Field Name : wafTemplaterequestCheckRedirectWlistLearn
Field Type : CounterBasedGauge64
Field Status : current
Description : Redirect Whitelist Learn
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.221

Field Name : wafTemplaterequestCheckRedirectWlistViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Redirect Whitelist violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.220

Field Name : wafTemplaterequestCheckRedirectWlistSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Redirect Whitelist passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.219

Field Name : wafTemplaterequestCheckBotViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Bot check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.218

Field Name : wafTemplaterequestCheckBotSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Bot check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.217

Field Name : wafTemplatejsonCheckMaxStringViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Limit String violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.216

Field Name : wafTemplatejsonCheckMaxStringSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Limit String check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.215

Field Name : wafTemplatejsonCheckMaxObjectMemberCountViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Limit Object Number Count violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.214

Field Name : wafTemplatejsonCheckMaxObjectMemberCountSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Limit Object Number Count check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.213

Field Name : wafTemplatejsonCheckMaxDepthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Limit Depth violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.212

Field Name : wafTemplatejsonCheckMaxDepthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Limit Depth check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.211

Field Name : wafTemplatejsonCheckMaxArrayValueCountViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Limit Array Value Count violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.210

Field Name : wafTemplatejsonCheckMaxArrayValueCountSuccess
Field Type : CounterBasedGauge64
Field Status : current

Description : JSON Limit Array Value Count check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.209

Field Name : wafTemplatejsonCheckFormatViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.208

Field Name : wafTemplatejsonCheckFormatSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.207

Field Name : wafTemplatehttpProtocolViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.206

Field Name : wafTemplatehttpProtocolSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.205

Field Name : wafTemplatehttpProtocolPostWithoutContentViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : POST without content check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.204

Field Name : wafTemplatehttpProtocolPostWithoutContentSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : POST without content check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.203

Field Name : wafTemplatehttpProtocolPostWith0ContentViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : POST with 0 content check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.202

Field Name : wafTemplatehttpProtocolPostWith0ContentSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : POST with 0 content check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.201

Field Name : wafTemplatehttpProtocolMultipleContentLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Multiple content-length headers check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.200

Field Name : wafTemplatehttpProtocolMultipleContentLengthSuccess

Field Type : CounterBasedGauge64
Field Status : current
Description : Multiple content-length headers check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.199

Field Name : wafTemplatehttpProtocolMissingHostHeaderViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Missing host header check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.198

Field Name : wafTemplatehttpProtocolMissingHostHeaderSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Missing host header check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.197

Field Name : wafTemplatehttpProtocolMissingHeaderValueViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Missing header value check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.196

Field Name : wafTemplatehttpProtocolMissingHeaderValueSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Missing header value check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.195

Field Name : wafTemplatehttpProtocolMalformedRequestLineViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed request line check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.194

Field Name : wafTemplatehttpProtocolMalformedRequestLineSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed request line check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.193

Field Name : wafTemplatehttpProtocolMalformedRequestViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed request check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.192

Field Name : wafTemplatehttpProtocolMalformedRequestSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed request check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.191

Field Name : wafTemplatehttpProtocolMalformedParameterViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed parameter check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.190

Field Name : wafTemplatehttpProtocolMalformedParameterSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed parameter check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.189

Field Name : wafTemplatehttpProtocolMalformedHeaderViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed header check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.188

Field Name : wafTemplatehttpProtocolMalformedHeaderSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed header check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.187

Field Name : wafTemplatehttpProtocolMalformedContentLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed content-length check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.186

Field Name : wafTemplatehttpProtocolMalformedContentLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed content-length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.185

Field Name : wafTemplatehttpProtocolInvalidUrlEncodingViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid url encoding check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.184

Field Name : wafTemplatehttpProtocolInvalidUrlEncodingSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid url encoding check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.183

Field Name : wafTemplatehttpProtocolHostHeaderWithIpViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Host header with IP check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.182

Field Name : wafTemplatehttpProtocolHostHeaderWithIpSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Host header with IP check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.181

Field Name : wafTemplatehttpProtocolHeadWithContentViolation
Field Type : CounterBasedGauge64
Field Status : current

Description : HEAD with content check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.180

Field Name : wafTemplatehttpProtocolHeadWithContentSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HEAD with content check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.179

Field Name : wafTemplatehttpProtocolGetWithContentViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : GET with content check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.178

Field Name : wafTemplatehttpProtocolGetWithContentSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : GET with content check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.177

Field Name : wafTemplatehttpProtocolBadMultipartRequestViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad multi-part request check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.176

Field Name : wafTemplatehttpProtocolBadMultipartRequestSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad multi-part request check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.175

Field Name : wafTemplatehttpProtocolAllowedMethodCheckViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Method Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.174

Field Name : wafTemplatehttpProtocolAllowedMethodCheckSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Method Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.173

Field Name : wafTemplatehttpProtocolAllowedVersionsViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP versions check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.172

Field Name : wafTemplatehttpProtocolAllowedVersionsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP versions check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.171

Field Name : wafTemplatehttpProtocolAllowedHeadersViolation

Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP headers check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.170

Field Name : wafTemplatehttpProtocolAllowedHeadersSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP headers check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.169

Field Name : wafTemplatemaxUrlLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX URL length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.168

Field Name : wafTemplatemaxUrlLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX URL length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.167

Field Name : wafTemplatehttpLimitMaxRequestLineLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX request line length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.166

Field Name : wafTemplatehttpLimitMaxRequestLineLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX request line length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.165

Field Name : wafTemplatehttpLimitMaxRequestLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX request length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.164

Field Name : wafTemplatehttpLimitMaxRequestLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX request length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.163

Field Name : wafTemplatehttpLimitMaxQueryLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX query length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.162

Field Name : wafTemplatehttpLimitMaxQueryLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX query length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.161

Field Name : wafTemplatehttpLimitMaxPostLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX POST length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.160

Field Name : wafTemplatehttpLimitMaxPostLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX POST length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.159

Field Name : wafTemplatehttpLimitMaxParamsLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX parameters total length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.158

Field Name : wafTemplatehttpLimitMaxParamsLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX parameters total length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.157

Field Name : wafTemplatehttpLimitMaxParamsViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX parameters violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.156

Field Name : wafTemplatehttpLimitMaxParamsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX parameters check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.155

Field Name : wafTemplatehttpLimitMaxParamValueLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX parameter value length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.154

Field Name : wafTemplatehttpLimitMaxParamValueLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX parameter value length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.153

Field Name : wafTemplatehttpLimitMaxParamNameLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX parameter name length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.152

Field Name : wafTemplatehttpLimitMaxParamNameLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current

Description : Limit check - MAX parameter name length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.151

Field Name : wafTemplatehttpLimitMaxHeadersLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX headers length check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.150

Field Name : wafTemplatehttpLimitMaxHeadersLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX headers length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.149

Field Name : wafTemplatehttpLimitMaxHeadersViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Headers violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.148

Field Name : wafTemplatehttpLimitMaxHeadersSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX headers count check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.147

Field Name : wafTemplatehttpLimitMaxHeaderValueLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX header value length check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.146

Field Name : wafTemplatehttpLimitMaxHeaderValueLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX header value length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.145

Field Name : wafTemplatehttpLimitMaxHeaderNameLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX header name length check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.144

Field Name : wafTemplatehttpLimitMaxHeaderNameLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX header name length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.143

Field Name : wafTemplatehttpLimitMaxHeaderLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX header length check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.142

Field Name : wafTemplatehttpLimitMaxHeaderLengthSuccess

Field Type : CounterBasedGauge64
Field Status : current
Description : MAX header length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.141

Field Name : wafTemplatehttpLimitMaxEntitiesViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Entities violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.140

Field Name : wafTemplatehttpLimitMaxEntitiesSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Entities check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.139

Field Name : wafTemplatehttpLimitMaxDataParseViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Buffer Overflow - Max Data Parse violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.138

Field Name : wafTemplatehttpLimitMaxDataParseSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Buffer Overflow - Max Data Parse check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.137

Field Name : wafTemplatehttpLimitMaxCookiesLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX cookies length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.136

Field Name : wafTemplatehttpLimitMaxCookiesLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX cookies length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.135

Field Name : wafTemplatehttpLimitMaxCookiesViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Cookies violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.134

Field Name : wafTemplatehttpLimitMaxCookiesSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Cookies check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.133

Field Name : wafTemplatehttpLimitMaxCookieValueLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX cookie value length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.132

Field Name : wafTemplatehttpLimitMaxCookieValueLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX cookie value length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.131

Field Name : wafTemplatehttpLimitMaxCookieNameLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX cookie name length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.130

Field Name : wafTemplatehttpLimitMaxCookieNameLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX cookie name length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.129

Field Name : wafTemplatehttpLimitMaxCookieHeaderLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX cookie header length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.128

Field Name : wafTemplatehttpLimitMaxCookieHeaderLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX cookie header length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.127

Field Name : wafTemplatehttpLimitMaxContentLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX content-length check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.126

Field Name : wafTemplatehttpLimitMaxContentLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX content-length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.125

Field Name : wafTemplateevasionCheckRemoveSpacesViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Remove Spaces check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.124

Field Name : wafTemplateevasionCheckRemoveSpacesSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Remove Spaces check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.123

Field Name : wafTemplateevasionCheckRemoveCommentsViolation
Field Type : CounterBasedGauge64
Field Status : current

Description : Remove Comments check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.122

Field Name : wafTemplateevasionCheckRemoveCommentsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Remove Comments check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.121

Field Name : wafTemplateevasionCheckMaxLevelsViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Levels check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.120

Field Name : wafTemplateevasionCheckMaxLevelsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Levels check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.119

Field Name : wafTemplateevasionCheckMultipleSlashesViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Multiple Slashes check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.118

Field Name : wafTemplateevasionCheckMultipleSlashesSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Multiple Slashes check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.117

Field Name : wafTemplateevasionCheckMultipleEncodingLevelsViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Multiple Encoding Levels check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.116

Field Name : wafTemplateevasionCheckMultipleEncodingLevelsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Multiple Encoding Levels check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.115

Field Name : wafTemplateevasionCheckInvalidHexEncodingViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid Hex Encoding check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.114

Field Name : wafTemplateevasionCheckInvalidHexEncodingSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid Hex Encoding check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.113

Field Name : wafTemplateevasionCheckHighAsciiBytesViolation

Field Type : CounterBasedGauge64
Field Status : current
Description : High Ascii Bytes check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.112

Field Name : wafTemplateevasionCheckHighAsciiBytesSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : High Ascii Bytes check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.111

Field Name : wafTemplateevasionCheckDirTraversalViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Dir traversal check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.110

Field Name : wafTemplateevasionCheckDirTraversalSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Dir traversal check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.109

Field Name : wafTemplateevasionCheckDecodeUnicodeCharsViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Decode Unicode Chars check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.108

Field Name : wafTemplateevasionCheckDecodeUnicodeCharsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Decode Unicode Chars check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.107

Field Name : wafTemplateevasionCheckDecodeEscapedCharsViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Decode Escaped Chars check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.106

Field Name : wafTemplateevasionCheckDecodeEscapedCharsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Decode Escaped Chars check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.105

Field Name : wafTemplateevasionCheckDecodeEntitiesViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Decode Entities check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.104

Field Name : wafTemplateevasionCheckDecodeEntitiesSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Decode Entities check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.103

Field Name : wafTemplateevasionCheckApacheWhitespaceViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Apache Whitespace check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.102

Field Name : wafTemplateevasionCheckApacheWhitespaceSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Apache Whitespace check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.101

Field Name : wafTemplatedlpPcreMasked
Field Type : CounterBasedGauge64
Field Status : current
Description : PCRE Mask violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.100

Field Name : wafTemplatedlpPcreViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : PCRE Mask violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.99

Field Name : wafTemplatedlpPcreSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : PCRE Mask check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.98

Field Name : wafTemplatedlpSsnViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Social Security Number Mask violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.97

Field Name : wafTemplatedlpSsnSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Social Security Number Mask check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.96

Field Name : wafTemplatedlpCcnJcbMasked
Field Type : CounterBasedGauge64
Field Status : current
Description : JCB Credit Card Number Masked
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.95

Field Name : wafTemplatedlpCcnJcbViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : JCB Credit Card Number Detected
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.94

Field Name : wafTemplatedlpCcnDiscoverMasked
Field Type : CounterBasedGauge64
Field Status : current

Description : Discover Credit Card Number Masked
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.93

Field Name : wafTemplatedlpCcnDiscoverViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Discover Credit Card Number Detected
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.92

Field Name : wafTemplatedlpCcnMastercardMasked
Field Type : CounterBasedGauge64
Field Status : current
Description : MasterCard Credit Card Number Masked
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.91

Field Name : wafTemplatedlpCcnMastercardViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MasterCard Credit Card Number Detected
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.90

Field Name : wafTemplatedlpCcnVisaMasked
Field Type : CounterBasedGauge64
Field Status : current
Description : Visa Credit Card Number Masked
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.89

Field Name : wafTemplatedlpCcnVisaViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Visa Credit Card Number Detected
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.88

Field Name : wafTemplatedlpCcnDinersMasked
Field Type : CounterBasedGauge64
Field Status : current
Description : Diners Club Credit Card Number Masked
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.87

Field Name : wafTemplatedlpCcnDinersViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Diners Club Credit Card Number Detected
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.86

Field Name : wafTemplatedlpCcnAmexMasked
Field Type : CounterBasedGauge64
Field Status : current
Description : Amex Credit Card Number Masked
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.85

Field Name : wafTemplatedlpCcnAmexViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Amex Credit Card Number Detected
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.84

Field Name : wafTemplatedlpCcnSuccess

Field Type : CounterBasedGauge64
Field Status : current
Description : Credit Card Number check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.83

Field Name : wafTemplateformSetNoCache
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Set No Cache violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.82

Field Name : wafTemplateformSetNoCacheSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Set No Cache check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.81

Field Name : wafTemplateformPasswordAutocompleteViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Password Autocomplete violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.80

Field Name : wafTemplateformPasswordAutocompleteSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Password Autocomplete check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.79

Field Name : wafTemplateformNonSslPasswordViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Non SSL Password violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.78

Field Name : wafTemplateformNonSslPasswordSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Non SSL Password check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.77

Field Name : wafTemplateformNonMaskedPasswordViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Non Masked Password violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.76

Field Name : wafTemplateformNonMaskedPasswordSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Non Masked Password check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.75

Field Name : wafTemplateformCheckSanitize
Field Type : CounterBasedGauge64
Field Status : current
Description : Post Form Check Sanitized
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.74

Field Name : wafTemplateformCheckViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Post Form Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.73

Field Name : wafTemplateformCheckSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Post Form Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.72

Field Name : wafTemplateformNonPostViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Method being Non Post in Request violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.71

Field Name : wafTemplateformNonPostSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Method being Non Post in Request passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.70

Field Name : wafTemplateformNonSslViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Non SSL violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.69

Field Name : wafTemplateformNonSslSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Non SSL check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.68

Field Name : wafTemplateformTagInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Form A10 Tag Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.67

Field Name : wafTemplateformConsistencyViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Consistency violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.66

Field Name : wafTemplateformConsistencySuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Consistency passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.65

Field Name : wafTemplateformCsrfTagViolation
Field Type : CounterBasedGauge64
Field Status : current

Description : Form CSRF tag violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.64

Field Name : wafTemplateformCsrfTagSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Form CSRF tag passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.63

Field Name : wafTemplatecspHeaderInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : CSP header Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.62

Field Name : wafTemplatecspHeaderSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : CSP header found
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.61

Field Name : wafTemplatecspHeaderViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : CSP header missing
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.60

Field Name : wafTemplatecookieSecurityDisallowedPersistentSetCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - disallowed persistent Set-Cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.59

Field Name : wafTemplatecookieSecurityDisallowedSessionSetCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - disallowed session Set-Cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.58

Field Name : wafTemplatecookieSecurityAllowedPersistentSetCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - disallowed persistent Set-Cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.57

Field Name : wafTemplatecookieSecurityAllowedSessionSetCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - disallowed session Set-Cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.56

Field Name : wafTemplatecookieSecurityDisallowedPersistentCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - disallowed persistent cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.55

Field Name : wafTemplatecookieSecurityDisallowedSessionCookies

Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - disallowed session cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.54

Field Name : wafTemplatecookieSecurityAllowedPersistentCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - allowed persistent cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.53

Field Name : wafTemplatecookieSecurityAllowedSessionCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - allowed session cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.52

Field Name : wafTemplatecookieSecuritySessionCookiesSigned
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - signed session cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.51

Field Name : wafTemplatecookieSecuritySessionCookiesEncrypted
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - encrypted session cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.50

Field Name : wafTemplatecookieSecuritySessionCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - session cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.49

Field Name : wafTemplatecookieSecurityPersistentCookiesSigned
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - signed persistent cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.48

Field Name : wafTemplatecookieSecurityPersistentCookiesEncrypted
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - encrypted persistent cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.47

Field Name : wafTemplatecookieSecurityPersistentCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - persistent cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.46

Field Name : wafTemplatecookieSecurityCookiePolicyViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - cookie policy violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.45

Field Name : wafTemplatecookieSecurityCookiePolicySuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - cookie policy passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.44

Field Name : wafTemplatecookieSecurityUnrecognizedCookieViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - unrecognized cookie violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.43

Field Name : wafTemplatecookieSecurityUnrecognizedCookieSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - request with unrecognized cookie
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.42

Field Name : wafTemplatecookieSecurityMissingCookieViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - missing cookie violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.41

Field Name : wafTemplatecookieSecurityMissingCookieSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - request with missing cookie
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.40

Field Name : wafTemplatecookieSecurityAddSecureViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - secure flag violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.39

Field Name : wafTemplatecookieSecurityAddSecureSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - secure flag added
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.38

Field Name : wafTemplatecookieSecurityAddHttpOnlyViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - http-only flag violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.37

Field Name : wafTemplatecookieSecurityAddHttpOnlySuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - http-only flag added
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.36

Field Name : wafTemplatecookieSecuritySignatureCheckViolation
Field Type : CounterBasedGauge64
Field Status : current

Description : Cookie Security - signature check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.35

Field Name : wafTemplatecookieSecuritySignatureCheckSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - signature check successful
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.34

Field Name : wafTemplatecookieSecuritySignSkipRcache
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - signing skipped - RAM Cache
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.33

Field Name : wafTemplatecookieSecuritySignLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - signing limit exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.32

Field Name : wafTemplatecookieSecuritySignViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - signing violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.31

Field Name : wafTemplatecookieSecuritySignSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - signing successful
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.30

Field Name : wafTemplatecookieSecurityDecryptViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - decrypt violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.29

Field Name : wafTemplatecookieSecurityDecryptSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - decrypt successful
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.28

Field Name : wafTemplatecookieSecurityEncryptSkipRcache
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - encrypt skipped - RAM cache
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.27

Field Name : wafTemplatecookieSecurityEncryptLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - encrypt limit exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.26

Field Name : wafTemplatecookieSecurityEncryptViolation

Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - encrypt violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.25

Field Name : wafTemplatecookieSecurityEncryptSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - encrypt successful
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.24

Field Name : wafTemplatebruteForceResponseStringTriggered
Field Type : CounterBasedGauge64
Field Status : current
Description : Brute Force Response string Triggered
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.23

Field Name : wafTemplatebruteForceResponseHeadersTriggered
Field Type : CounterBasedGauge64
Field Status : current
Description : Brute Force Response Headers Triggered
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.22

Field Name : wafTemplatebruteForceResponseCodesTriggered
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Codes Triggered
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.21

Field Name : wafTemplatebruteForceChallengeLimitViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Lockout limit violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.20

Field Name : wafTemplatebruteForceChallengeLimitSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Lockout limit check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.19

Field Name : wafTemplatebruteForceLockoutLimitViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Lockout limit violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.18

Field Name : wafTemplatebruteForceLockoutLimitSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Lockout limit check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.17

Field Name : wafTemplatebruteForceChallengeCaptchaViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Captcha challenge violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.16

Field Name : wafTemplatebruteForceChallengeCaptchaSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Captcha challenge check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.15

Field Name : wafTemplatebruteForceChallengeCaptchaSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Captcha challenge sent
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.14

Field Name : wafTemplatebruteForceChallengeJavascriptViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : JavaScript challenge violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.13

Field Name : wafTemplatebruteForceChallengeJavascriptSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : JavaScript challenge check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.12

Field Name : wafTemplatebruteForceChallengeJavascriptSent
Field Type : CounterBasedGauge64
Field Status : current
Description : JavaScript challenge sent
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.11

Field Name : wafTemplatebruteForceChallengeCookieViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie challenge violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.10

Field Name : wafTemplatebruteForceChallengeCookieSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Challenge check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.9

Field Name : wafTemplatebruteForceChallengeCookieSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Challenge Sent
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.8

Field Name : wafTemplatebruteForceViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Brute-Force checks violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.7

Field Name : wafTemplatebruteForceSuccess
Field Type : CounterBasedGauge64
Field Status : current

Description : Brute-Force checks passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.6

Field Name : wafTemplaterespDenied
Field Type : CounterBasedGauge64
Field Status : current
Description : Responses Denied
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.5

Field Name : wafTemplatereqDenied
Field Type : CounterBasedGauge64
Field Status : current
Description : Requests Denied
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.4

Field Name : wafTemplatereqAllowed
Field Type : CounterBasedGauge64
Field Status : current
Description : Requests Allowed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.3

Field Name : wafTemplatetotalReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Requests
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.2

Field Name : wafTemplateName
Field Type : String
Field Status : current
Description : WAF Template Name
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.1

Field Name : ngWafStatsSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1

Field Name : ngWafStatsSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1

Field Name : custom64
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 64
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.115

Field Name : custom63
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 63
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.114

Field Name : custom62

Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 62
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.113

Field Name : custom61
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 61
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.112

Field Name : custom60
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 60
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.111

Field Name : custom59
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 59
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.110

Field Name : custom58
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 58
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.109

Field Name : custom57
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 57
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.108

Field Name : custom56
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 56
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.107

Field Name : custom55
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 55
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.106

Field Name : custom54
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 54
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.105

Field Name : custom53
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 53
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.104

Field Name : custom52
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 52
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.103

Field Name : custom51
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 51
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.102

Field Name : custom50
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 50
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.101

Field Name : custom49
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 49
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.100

Field Name : custom48
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 48
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.99

Field Name : custom47
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 47
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.98

Field Name : custom46
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 46
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.97

Field Name : custom45
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 45
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.96

Field Name : custom44
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 44
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.95

Field Name : custom43
Field Type : CounterBasedGauge64
Field Status : current

Description : Custom signal 43
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.94

Field Name : custom42
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 42
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.93

Field Name : custom41
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 41
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.92

Field Name : custom40
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 40
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.91

Field Name : custom39
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 39
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.90

Field Name : custom38
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 38
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.89

Field Name : custom37
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 37
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.88

Field Name : custom36
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 36
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.87

Field Name : custom35
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 35
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.86

Field Name : custom34
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 34
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.85

Field Name : custom33

Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 33
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.84

Field Name : custom32
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 32
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.83

Field Name : custom31
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 31
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.82

Field Name : custom30
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 30
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.81

Field Name : custom29
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 29
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.80

Field Name : custom28
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 28
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.79

Field Name : custom27
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 27
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.78

Field Name : custom26
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 26
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.77

Field Name : custom25
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 25
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.76

Field Name : custom24
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 24
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.75

Field Name : custom23
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 23
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.74

Field Name : custom22
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 22
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.73

Field Name : custom21
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 21
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.72

Field Name : custom20
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 20
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.71

Field Name : custom19
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 19
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.70

Field Name : custom18
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 18
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.69

Field Name : custom17
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 17
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.68

Field Name : custom16
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 16
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.67

Field Name : custom15
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 15
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.66

Field Name : custom14
Field Type : CounterBasedGauge64
Field Status : current

Description : Custom signal 14
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.65

Field Name : custom13
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 13
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.64

Field Name : custom12
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 12
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.63

Field Name : custom11
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 11
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.62

Field Name : custom10
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 10
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.61

Field Name : custom9
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 9
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.60

Field Name : custom8
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 8
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.59

Field Name : custom7
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 7
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.58

Field Name : custom6
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 6
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.57

Field Name : custom5
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 5
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.56

Field Name : custom4

Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 4
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.55

Field Name : custom3
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 3
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.54

Field Name : custom2
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 2
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.53

Field Name : custom1
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 1
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.52

Field Name : other
Field Type : CounterBasedGauge64
Field Status : current
Description : Unknown Attack
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.40

Field Name : xmlError
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Encoding Error
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.51

Field Name : weaktls
Field Type : CounterBasedGauge64
Field Status : current
Description : Weak TLS
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.39

Field Name : tornode
Field Type : CounterBasedGauge64
Field Status : current
Description : Tor Traffic
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.38

Field Name : siteFlaggedIp
Field Type : CounterBasedGauge64
Field Status : current
Description : Site Flagged IP
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.50

Field Name : impostor
Field Type : CounterBasedGauge64
Field Status : current
Description : SearchBot Impostor
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.37

Field Name : scanner
Field Type : CounterBasedGauge64
Field Status : current
Description : Scanner
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.36

Field Name : privatefile
Field Type : CounterBasedGauge64
Field Status : current
Description : Private File
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.35

Field Name : nullbyte
Field Type : CounterBasedGauge64
Field Status : current
Description : Null Byte
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.34

Field Name : noua
Field Type : CounterBasedGauge64
Field Status : current
Description : No User Agent
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.33

Field Name : noCtype
Field Type : CounterBasedGauge64
Field Status : current
Description : Missing Content-Type Request Header
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.32

Field Name : sigsciIp
Field Type : CounterBasedGauge64
Field Status : current
Description : Network Effect
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.31

Field Name : sans
Field Type : CounterBasedGauge64
Field Status : current
Description : Malicious IP Traffic
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.30

Field Name : malformed
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed Data in the Request Body
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.29

Field Name : jsonError
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Encoding Error
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.49

Field Name : notutf8
Field Type : CounterBasedGauge64
Field Status : current

Description : Invalid Encoding
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.28

Field Name : respsplit
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Response Splitting
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.27

Field Name : http5xx
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP 5xx Errors
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.26

Field Name : http503
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP 503 Errors
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.25

Field Name : http500
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP 500 Errors
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.24

Field Name : http4xx
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP 4xx Errors
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.23

Field Name : http429
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP 429 Errors
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.22

Field Name : http404
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP 404 Errors
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.21

Field Name : http403
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP 403 Errors
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.20

Field Name : graphqlUnusedVariables
Field Type : CounterBasedGauge64
Field Status : current
Description : GRAPHQL-UNUSED-VARIABLES
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.48

Field Name : graphqlIntrospection

Field Type : CounterBasedGauge64
Field Status : current
Description : GraphQL Introspection
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.47

Field Name : graphqlIde
Field Type : CounterBasedGauge64
Field Status : current
Description : GraphQL IDE
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.46

Field Name : fbrowing
Field Type : CounterBasedGauge64
Field Status : current
Description : Forceful Browsing
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.19

Field Name : duplicateHeaders
Field Type : CounterBasedGauge64
Field Status : current
Description : Duplicate Header Names
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.45

Field Name : doubleenc
Field Type : CounterBasedGauge64
Field Status : current
Description : Double Encoding
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.18

Field Name : datacenter
Field Type : CounterBasedGauge64
Field Status : current
Description : Datacenter Traffic
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.17

Field Name : codei
Field Type : CounterBasedGauge64
Field Status : current
Description : Code Injection PHP
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.16

Field Name : block
Field Type : CounterBasedGauge64
Field Status : current
Description : Blocked Requests
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.15

Field Name : bhh
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Hop Headers
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.14

Field Name : abnormalpath
Field Type : CounterBasedGauge64
Field Status : current
Description : Abnormal Path
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.44

Field Name : sqli
Field Type : CounterBasedGauge64
Field Status : current
Description : SQL Injection
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.13

Field Name : log4jJndi
Field Type : CounterBasedGauge64
Field Status : current
Description : Log4J JNDI
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.43

Field Name : graphqlDepth
Field Type : CounterBasedGauge64
Field Status : current
Description : GraphQL Max Depth
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.42

Field Name : traversal
Field Type : CounterBasedGauge64
Field Status : current
Description : Directory Traversal
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.12

Field Name : xss
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross Site Scripting
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.11

Field Name : cmdexe
Field Type : CounterBasedGauge64
Field Status : current
Description : Command Execution
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.10

Field Name : backdoor
Field Type : CounterBasedGauge64
Field Status : current
Description : Backdoor
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.9

Field Name : awsSsrf
Field Type : CounterBasedGauge64
Field Status : current
Description : AWS SSRF
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.8

Field Name : useragent
Field Type : CounterBasedGauge64
Field Status : current
Description : Attack Tooling
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.7

Field Name : error
Field Type : CounterBasedGauge64
Field Status : current

Description : Error Happened
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.6

Field Name : reqBypass
Field Type : CounterBasedGauge64
Field Status : current
Description : Requests Bypassed
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.5

Field Name : reqMarked
Field Type : CounterBasedGauge64
Field Status : current
Description : Requests Marked
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.41

Field Name : reqRedirected
Field Type : CounterBasedGauge64
Field Status : current
Description : Requests Redirected
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.116

Field Name : reqBlocked
Field Type : CounterBasedGauge64
Field Status : current
Description : Requests Blocked
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.4

Field Name : reqForward
Field Type : CounterBasedGauge64
Field Status : current
Description : Requests Forwarded
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.3

Field Name : reqReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Requests Received
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : ng-waf name
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.1

Field Name : cgnv6MapTranslationDomainSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1

Field Name : cgnv6MapTranslationDomainSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1

Field Name : activeDhcpv6Leases

Field Type : CounterBasedGauge64
Field Status : current
Description : Active DHCPv6 leases
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.16

Field Name : helperCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Helper Count
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.15

Field Name : bmrPrefixrulesConfigured
Field Type : CounterBasedGauge64
Field Status : current
Description : BMR prefix rules configured
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.18

Field Name : interfaceNotConfigured
Field Type : CounterBasedGauge64
Field Status : current
Description : Interfaces not Configured Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.14

Field Name : fragIcmpSent
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Packet Too Big Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.13

Field Name : packetMtuExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet Exceeded MTU
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.12

Field Name : outboundDestUnreachable
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound IPv4 Destination Address Unreachable
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.11

Field Name : outboundRevLookupFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound IPv6 Reverse Route Lookup Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.10

Field Name : outboundAddrValidationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound IPv6 Source Address Validation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.9

Field Name : outboundFragPacketReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound IPv6 Fragment Packets Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.8

Field Name : outboundPacketReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound IPv6 Packets Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.7

Field Name : inboundDestUnreachable
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound IPv6 Destination Address Unreachable
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.6

Field Name : inboundRevLookupFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound IPv4 Reverse Route Lookup Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.5

Field Name : inboundAddrPortValidationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound IPv4 Destination Address Port Validation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.4

Field Name : inboundFragPacketReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound IPv4 Fragment Packets Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.3

Field Name : inboundPacketReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound IPv4 Packets Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : MAP-T domain name
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.1

Field Name : cgnv6MapEncapsulationDomainSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1

Field Name : cgnv6MapEncapsulationDomainSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.1

Field Name : activeDhcpv6Leases
Field Type : CounterBasedGauge64
Field Status : current

Description : Active DHCPv6 leases
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.1.16

Field Name : helperCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Helper Count
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.1.15

Field Name : bmrPrefixrulesConfigured
Field Type : CounterBasedGauge64
Field Status : current
Description : BMR prefix rules configured
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.1.18

Field Name : interfaceNotConfigured
Field Type : CounterBasedGauge64
Field Status : current
Description : Interfaces not Configured Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.1.14

Field Name : fragIcmpSent
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Packet Too Big Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.1.13

Field Name : packetMtuExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet Exceeded MTU
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.1.12

Field Name : outboundDestUnreachable
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound IPv4 Destination Address Unreachable
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.1.11

Field Name : outboundRevLookupFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound IPv6 Reverse Route Lookup Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.1.10

Field Name : outboundAddrValidationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound IPv6 Source Address Validation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.1.9

Field Name : outboundFragPacketReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound IPv6 Fragment Packets Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.1.8

Field Name : outboundPacketReceived

Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound IPv6 Packets Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.1.7

Field Name : inboundDestUnreachable
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound IPv6 Destination Address Unreachable
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.1.6

Field Name : inboundRevLookupFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound IPv4 Reverse Route Lookup Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.1.5

Field Name : inboundAddrPortValidationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound IPv4 Destination Address Port Validation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.1.4

Field Name : inboundFragPacketReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound IPv4 Fragment Packets Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.1.3

Field Name : inboundPacketReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound IPv4 Packets Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : MAP-E domain name
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.1.1

Field Name : drop
Field Type : CounterBasedGauge64
Field Status : current
Description : Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.31.1.15

Field Name : cache
Field Type : CounterBasedGauge64
Field Status : current
Description : Cache
OID : 1.3.6.1.4.1.22610.2.4.10.115.31.1.14

Field Name : adjust
Field Type : CounterBasedGauge64
Field Status : current
Description : Translated
OID : 1.3.6.1.4.1.22610.2.4.10.115.31.1.13

Field Name : respLocal
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Local
OID : 1.3.6.1.4.1.22610.2.4.10.115.31.1.12

Field Name : respEmpty
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Empty
OID : 1.3.6.1.4.1.22610.2.4.10.115.31.1.11

Field Name : respErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.31.1.10

Field Name : respChg
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Changed
OID : 1.3.6.1.4.1.22610.2.4.10.115.31.1.9

Field Name : respBadQr
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Bad Query
OID : 1.3.6.1.4.1.22610.2.4.10.115.31.1.8

Field Name : respBadPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Bad Packet
OID : 1.3.6.1.4.1.22610.2.4.10.115.31.1.7

Field Name : resp
Field Type : CounterBasedGauge64
Field Status : current
Description : Response
OID : 1.3.6.1.4.1.22610.2.4.10.115.31.1.6

Field Name : queryPassive
Field Type : CounterBasedGauge64
Field Status : current
Description : Query Passive
OID : 1.3.6.1.4.1.22610.2.4.10.115.31.1.5

Field Name : queryParallel
Field Type : CounterBasedGauge64
Field Status : current
Description : Query Parallel
OID : 1.3.6.1.4.1.22610.2.4.10.115.31.1.4

Field Name : queryChg
Field Type : CounterBasedGauge64
Field Status : current

Description : Query Changed
OID : 1.3.6.1.4.1.22610.2.4.10.115.31.1.3

Field Name : queryBadPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : Query Bad Packet
OID : 1.3.6.1.4.1.22610.2.4.10.115.31.1.2

Field Name : query
Field Type : CounterBasedGauge64
Field Status : current
Description : Query
OID : 1.3.6.1.4.1.22610.2.4.10.115.31.1.1

Field Name : noQueue
Field Type : CounterBasedGauge64
Field Status : current
Description : No Queue
OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.19

Field Name : headerRemovalFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Buff Removal Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.18

Field Name : headerInsertionFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Buff Insertion Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.17

Field Name : buffSpiltFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Buff Split Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.16

Field Name : buffResent
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet Resent from Queue
OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.15

Field Name : outOfOrderDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet Out-of-Order Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.14

Field Name : queueLenExceedDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Queue Length Exceed Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.13

Field Name : outOfMemoryDropped

Field Type : CounterBasedGauge64
Field Status : current
Description : Out-of-Memory Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.12

Field Name : radiusResponseDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Query Response Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.11

Field Name : radiusResponseReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Query Response Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.10

Field Name : radiusRequstDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Query Request Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.9

Field Name : radiusRequstSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Query Request Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.8

Field Name : radiusQueryFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : MSISDN Query Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.7

Field Name : radiusQuerySucceed
Field Type : CounterBasedGauge64
Field Status : current
Description : MSISDN Query Succeed
OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.6

Field Name : queuedSessionTooMany
Field Type : CounterBasedGauge64
Field Status : current
Description : Queued Session Exceed Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.5

Field Name : requestInsertMsisdnUnavailable
Field Type : CounterBasedGauge64
Field Status : current
Description : Inserted MSISDN is 0000 (MSISDN Unavailable)
OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.4

Field Name : requestInsertClientIpPerformed
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Client IP Insertion Performed
OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.3

Field Name : requestInsertMsisdnPerformed
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP MSISDN Insertion Performed
OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.2

Field Name : requestProcessed
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Request Processed
OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.1

Field Name : errorIpMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP IP address mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.37

Field Name : errorToPoolDropV6
Field Type : CounterBasedGauge64
Field Status : current
Description : Error to IPv6 Pool Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.36

Field Name : echoToPoolDropV6
Field Type : CounterBasedGauge64
Field Status : current
Description : Ping6 to Pool Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.35

Field Name : echoToPoolReplyV6
Field Type : CounterBasedGauge64
Field Status : current
Description : Ping6 to Pool Reply
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.34

Field Name : errorToPoolDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Error to Pool Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.33

Field Name : echoToPoolDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Ping to Pool Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.32

Field Name : echoToPoolReply
Field Type : CounterBasedGauge64
Field Status : current
Description : Ping to Pool Reply
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.31

Field Name : staticNat
Field Type : CounterBasedGauge64
Field Status : current

Description : ICMP Static NAT
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.30

Field Name : icmpv6ToIcmpv6UnknownL4
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 to ICMPv6 Embedded Unknown L4 Protocol
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.29

Field Name : icmpv6ToIcmpUnknownL4
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 to ICMP Embedded Unknown L4 Protocol
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.28

Field Name : icmpToIcmpv6UnknownL4
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP to ICMPv6 Embedded Unknown L4 Protocol
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.27

Field Name : icmpToIcmpUnknownL4
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Embedded Unknown L4 Protocol
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.26

Field Name : encapCrossCpuPreprocessErr
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Embedded Cross CPU Preprocess Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.25

Field Name : encapCrossCpuNoMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Embedded Cross CPU No Matching Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.24

Field Name : icmpv6ToIcmpv6Err
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 to ICMPv6 Conversion Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.23

Field Name : icmpv6ToIcmpErr
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 to ICMP Conversion Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.22

Field Name : icmpToIcmpv6Err
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP to ICMPv6 Conversion Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.21

Field Name : icmpToIcmpErr

Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP to ICMP Conversion Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.20

Field Name : cgnv6Icmp46BadEncapIpHeaderLen
Field Type : CounterBasedGauge64
Field Status : current
Description : 4to6 Bad Encapsulated IP Header Length
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.19

Field Name : cgnv6Icmp46NoPrefixForIpv4
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Reverse No Prefix Match for IPv4
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.18

Field Name : cgnv6Icmp46UnknownDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Reverse Known ICMPv6 Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.17

Field Name : cgnv6Icmp46KnownDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Reverse Known ICMP Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.16

Field Name : cgnv6Icmp64MidpointHop
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Forward Unknown Source Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.15

Field Name : cgnv6Icmp64UnknownDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Forward Unknown ICMPv6 Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.14

Field Name : cgnv6Icmp64KnownDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Forward Known ICMPv6 Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.13

Field Name : icmpv6BadType
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Embedded ICMPv6 Type
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.12

Field Name : icmpBadType
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Embedded ICMP Type
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.11

Field Name : icmpv6ToIcmpv6
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 to ICMPv6 Conversion
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.10

Field Name : cgnv6IcmpIcmpv6ToIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 to ICMP Conversion
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.9

Field Name : cgnv6IcmpIcmpToIcmpv6
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP to ICMPv6 Conversion
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.8

Field Name : icmpToIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP to ICMP Conversion
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.7

Field Name : icmpv6NoSessionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 No Matching Session Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.6

Field Name : icmpv6NoPortInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 Port Info Not Included
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.5

Field Name : icmpv6UnknownType
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 Unknown Type
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.4

Field Name : icmpNoSessionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP No Matching Session Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.3

Field Name : icmpNoPortInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Port Info Not Included
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.2

Field Name : icmpUnknownType
Field Type : CounterBasedGauge64
Field Status : current

Description : ICMP Unknown Type
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.1

Field Name : fwNextActionIncorrectDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : FW Next Action Incorrect Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.63

Field Name : natRangeListAclPermit
Field Type : CounterBasedGauge64
Field Status : current
Description : Nat range-list ACL permit
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.62

Field Name : natRangeListAclDeny
Field Type : CounterBasedGauge64
Field Status : current
Description : Nat range-list ACL deny
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.61

Field Name : fwZoneMismatchReroutingDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Rerouting Zone Mismatch Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.60

Field Name : l3Ipv6DstInvalidUnicast
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 L3 Destination Invalid Unicast
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.59

Field Name : l3Ipv6SrcInvalidUnicast
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 L3 Source Invalid Unicast
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.58

Field Name : l3IpDstInvalidUnicast
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 L3 Destination Invalid Unicast
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.57

Field Name : l3IpSrcInvalidUnicast
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 L3 Source Invalid Unicast
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.56

Field Name : dstNatPoolNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst NAT Pool Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.55

Field Name : srcNatPoolNotFound

Field Type : CounterBasedGauge64
Field Status : current
Description : Src NAT Pool Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.54

Field Name : ipUnknownProcess
Field Type : CounterBasedGauge64
Field Status : current
Description : Process IP Unknown
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.53

Field Name : fwMatchNoRuleDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Firewall Matched No CGNv6 Rule Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.52

Field Name : processError
Field Type : CounterBasedGauge64
Field Status : current
Description : Process Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.51

Field Name : processContinue
Field Type : CounterBasedGauge64
Field Status : current
Description : Process Continue
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.50

Field Name : processSpecial
Field Type : CounterBasedGauge64
Field Status : current
Description : Process Special
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.49

Field Name : preprocessError
Field Type : CounterBasedGauge64
Field Status : current
Description : Preprocess Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.48

Field Name : processL4
Field Type : CounterBasedGauge64
Field Status : current
Description : Process L4
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.47

Field Name : staticNatFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Static NAT Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.46

Field Name : staticNatAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Static NAT Alloc
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.45

Field Name : tcpRstLoopDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : RST Loop Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.44

Field Name : invalidNat64TranslatedAddr
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid NAT64 Translated IPv4 Address
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.43

Field Name : dstNatNeededDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Destination NAT Needed Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.42

Field Name : staticNatFastSetupErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Static NAT Fast Setup Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.41

Field Name : staticNatFastSetup
Field Type : CounterBasedGauge64
Field Status : current
Description : Static NAT Fast Setup Attempt
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.40

Field Name : fixedNatFastSetupMtuTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT Fast Setup MTU Too Small
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.39

Field Name : fixedNatFastSetupDelayedErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT Fast Setup Delayed Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.38

Field Name : fixedNatDsliteFastSetupErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT Fast Setup Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.37

Field Name : fixedNatDsliteFastSetup
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT Fast Setup Attempt
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.36

Field Name : fixedNat64FastSetupErr
Field Type : CounterBasedGauge64
Field Status : current

Description : Fixed NAT Fast Setup Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.35

Field Name : fixedNat64FastSetup
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT Fast Setup Attempt
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.34

Field Name : fixedNat44FastSetupErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT Fast Setup Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.33

Field Name : fixedNat44FastSetup
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT Fast Setup Attempt
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.32

Field Name : fastSetupMtuTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : Fast Setup MTU Too Small
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.31

Field Name : fastSetupDelayedErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Fast Setup Delayed Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.30

Field Name : dsliteFastSetupErr
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite Fast Setup Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.29

Field Name : dsliteFastSetup
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite Fast Setup Attempt
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.28

Field Name : nat64FastSetupErr
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Fast Setup Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.27

Field Name : nat64FastSetup
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Fast Setup Attempt
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.26

Field Name : lsnFastSetupErr

Field Type : CounterBasedGauge64
Field Status : current
Description : LSN Fast Setup Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.25

Field Name : lsnFastSetup
Field Type : CounterBasedGauge64
Field Status : current
Description : LSN Fast Setup Attempt
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.24

Field Name : crossCpuAlgGrePreprocessErr
Field Type : CounterBasedGauge64
Field Status : current
Description : ALG GRE Cross CPU Preprocess Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.23

Field Name : crossCpuAlgGreNoMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : ALG GRE Cross CPU No Matching Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.22

Field Name : ttlExceededSent
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP TTL Exceeded Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.21

Field Name : outOfStateDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 Out of State packets
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.20

Field Name : icmpv6ReplySent
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 Echo Reply Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.19

Field Name : icmpReplySent
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Echo Reply Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.18

Field Name : specialIpv6NoRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : Stateless IPv6 No Forward Route
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.17

Field Name : specialIpv4NoRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : Stateless IPv4 No Forward Route
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.16

Field Name : badL3Protocol
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Layer 3 Protocol
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.15

Field Name : rateDropResetUnkn
Field Type : CounterBasedGauge64
Field Status : current
Description : Rate Drop reset
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.14

Field Name : ipv6DstInvalidUnicast
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Destination Not Valid Unicast
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.13

Field Name : ipv6SrcInvalidUnicast
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Source Not Valid Unicast
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.12

Field Name : ipDstInvalidUnicast
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Destination Not Valid Unicast
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.11

Field Name : ipSrcInvalidUnicast
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Source Not Valid Unicast
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.10

Field Name : ipipTruncated
Field Type : CounterBasedGauge64
Field Status : current
Description : IPIP Truncated Packet
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.9

Field Name : icmpReplyNoSessionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Reply No Session Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.8

Field Name : icmpHostUnreachableSent
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Host Unreachable Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.7

Field Name : icmpFilteredSent
Field Type : CounterBasedGauge64
Field Status : current

Description : ICMP Administratively Filtered Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.6

Field Name : ipipIcmpReplySent
Field Type : CounterBasedGauge64
Field Status : current
Description : IPIP ICMP Echo Reply Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.5

Field Name : tcpRstSent
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP RST Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.4

Field Name : outOfSessionMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of Session Memory
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.3

Field Name : noRevRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : No Reverse Route for Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.2

Field Name : noFwdRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : No Forward Route for Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.1

Field Name : iddosL4EntryDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : iDDoS L4 Entry Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.83

Field Name : iddosL4EntryCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : iDDoS L4 Entry Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.82

Field Name : iddosL3EntryDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : iDDoS L3 Entry Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.81

Field Name : iddosL3EntryCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : iDDoS L3 Entry Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.80

Field Name : httpSpmFreeType4

Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Conn SPM Type 4 free
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.79

Field Name : httpSpmFreeType3
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Conn SPM Type 3 free
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.78

Field Name : httpSpmFreeType2
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Conn SPM Type 2 free
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.77

Field Name : httpSpmFreeType1
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Conn SPM Type 1 free
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.76

Field Name : httpSpmFreeType0
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Conn SPM Type 0 free
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.75

Field Name : httpSpmAllocType4
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Conn SPM Type 4 allocate
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.74

Field Name : httpSpmAllocType3
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Conn SPM Type 3 allocate
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.73

Field Name : httpSpmAllocType2
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Conn SPM Type 2 allocate
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.72

Field Name : httpSpmAllocType1
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Conn SPM Type 1 allocate
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.71

Field Name : httpSpmAllocType0
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Conn SPM Type 0 allocate
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.70

Field Name : httpMfree
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP mem free
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.69

Field Name : httpMalloc
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP mem allocate
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.68

Field Name : httpFragMergeFailedDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP frag merge failed dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.67

Field Name : httpAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Request Info Allocation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.66

Field Name : httpOutOfOrderDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP out-of-order dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.65

Field Name : logMessageTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Log message too long
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.64

Field Name : portBlockAccountingAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Allocation Accounting Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.63

Field Name : portBlockAccountingFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Allocation Accounting Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.62

Field Name : udpPortBatchInterimUpdated
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Batch Interim Updated
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.61

Field Name : tcpPortBatchInterimUpdated
Field Type : CounterBasedGauge64
Field Status : current

Description : TCP Port Batch Interim Updated
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.60

Field Name : interimUpdateNoBuffRetried
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Allocation Interim Update Memory Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.59

Field Name : interimUpdateMemoryFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Allocation Interim Update Memory Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.58

Field Name : interimUpdateTerminated
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Allocation Interim Update Terminated
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.57

Field Name : interimUpdateScheduleFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Allocation Interim Update Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.56

Field Name : interimUpdateScheduled
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Allocation Interim Update Scheduled
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.55

Field Name : ipv6FragFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Fragmentation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.54

Field Name : ipv6FragApplied
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Fragmentation Applied
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.53

Field Name : ipv4FragFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Fragmentation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.52

Field Name : ipv4FragApplied
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Fragmentation Applied
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.51

Field Name : connTcpCreateFailed

Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Connection Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.50

Field Name : rtspPortFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : RTSP UDP Port Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.49

Field Name : rtspPortAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : RTSP UDP Port Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.48

Field Name : addMsgFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Add Message to Buffer Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.47

Field Name : outOfBuffers
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of Buffers
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.46

Field Name : reducedLogsByDestination
Field Type : CounterBasedGauge64
Field Status : current
Description : Reduced Logs by Destination Protocol and Port
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.45

Field Name : httpRequestLogged
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Request Logged
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.44

Field Name : udpPortOverloadingFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Overloading Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.43

Field Name : udpPortOverloadingAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Overloading Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.42

Field Name : tcpPortOverloadingFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Overloading Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.41

Field Name : tcpPortOverloadingAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Overloading Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.40

Field Name : connTcpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Connection Lost
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.39

Field Name : connTcpEstablished
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Connection Established
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.38

Field Name : logDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.37

Field Name : logSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Packets Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.36

Field Name : enhancedUserLog
Field Type : CounterBasedGauge64
Field Status : current
Description : Enhanced User Log
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.35

Field Name : fixedNatInterimUpdated
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT Interim Updated
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.34

Field Name : fixedNatPeriodicConfigLogged
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT Disabled Config Logs Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.33

Field Name : fixedNatPeriodicConfigLogsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT Disabled Configs Logged
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.32

Field Name : fixedNatDisableConfigLogsSent
Field Type : CounterBasedGauge64
Field Status : current

Description : Fixed NAT Periodic Config Logs Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.31

Field Name : fixedNatDisableConfigLogged
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT Periodic Configs Logged
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.30

Field Name : fixedNatUserPorts
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT Inside User Port Mapping
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.29

Field Name : espResourceFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP Resource Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.28

Field Name : espResourceAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP Resource Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.27

Field Name : espSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP Session Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.26

Field Name : espSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.25

Field Name : greResourceFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Resource Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.24

Field Name : greResourceAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Resource Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.23

Field Name : greSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Session Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.22

Field Name : cgnv6LoggingGreSessionCreated

Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.21

Field Name : icmpv6ResourceFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPV6 Resource Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.20

Field Name : icmpv6ResourceAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPV6 Resource Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.19

Field Name : icmpv6SessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPV6 Session Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.18

Field Name : icmpv6SessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPV6 Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.17

Field Name : icmpResourceFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Resource Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.16

Field Name : icmpResourceAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Resource Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.15

Field Name : icmpSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Session Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.14

Field Name : icmpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.13

Field Name : udpPortBatchFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Batch Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.12

Field Name : udpPortBatchAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Batch Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.11

Field Name : udpPortFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.10

Field Name : udpPortAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.9

Field Name : udpSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Session Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.8

Field Name : udpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.7

Field Name : tcpPortBatchFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Batch Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.6

Field Name : tcpPortBatchAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Batch Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.5

Field Name : tcpPortFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.4

Field Name : tcpPortAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.3

Field Name : tcpSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current

Description : TCP Session Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.2

Field Name : tcpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.1

Field Name : cgnv6Nptv6DomainSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.26.2.1.1

Field Name : cgnv6Nptv6DomainSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.26.2.1.1.1

Field Name : packetsDestUnreachable
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets Destination Unreachable
OID : 1.3.6.1.4.1.22610.2.4.10.115.26.2.1.1.1.7

Field Name : inboundPacketsNoMap
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound Packets No Map
OID : 1.3.6.1.4.1.22610.2.4.10.115.26.2.1.1.1.6

Field Name : addressNotValidForTranslation
Field Type : CounterBasedGauge64
Field Status : current
Description : Address Not Valid For Translation
OID : 1.3.6.1.4.1.22610.2.4.10.115.26.2.1.1.1.5

Field Name : hairpinPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : Hairpin Packets
OID : 1.3.6.1.4.1.22610.2.4.10.115.26.2.1.1.1.4

Field Name : inboundPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound Packets
OID : 1.3.6.1.4.1.22610.2.4.10.115.26.2.1.1.1.3

Field Name : outboundPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound Packets
OID : 1.3.6.1.4.1.22610.2.4.10.115.26.2.1.1.1.2

Field Name : name

Field Type : String
Field Status : current
Description : Name of NPTv6 domain
OID : 1.3.6.1.4.1.22610.2.4.10.115.26.2.1.1.1.1

Field Name : interBoardPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : PCP Inter board packets
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.41

Field Name : mapFilterDeny
Field Type : CounterBasedGauge64
Field Status : current
Description : PCP MAP Filter Deny Inbound
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.40

Field Name : mapFilterSet
Field Type : CounterBasedGauge64
Field Status : current
Description : PCP MAP Filter Set
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.39

Field Name : clientNonceMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : PCP Client Nonce Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.38

Field Name : fullconeExtReuse
Field Type : CounterBasedGauge64
Field Status : current
Description : PCP Fullcone Extension Reuse
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.37

Field Name : fullconeExtNotfound
Field Type : CounterBasedGauge64
Field Status : current
Description : PCP Fullcone Extension Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.36

Field Name : fullconeExtAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : PCP Fullcone Extension Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.35

Field Name : fullconeExtFree
Field Type : CounterBasedGauge64
Field Status : current
Description : PCP Fullcone Extension Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.34

Field Name : fullconeExtAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : PCP Fullcone Extension Alloc
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.33

Field Name : haSyncEpochRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Sync PCP Epoch Recv
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.32

Field Name : haSyncEpochSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Sync PCP Epoch Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.31

Field Name : unsolAnceSentFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Unsolicited Announce Send Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.30

Field Name : unsolAnceSentSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : Unsolicited Announce Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.29

Field Name : internalErrorDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Internal Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.28

Field Name : l4ProcessError
Field Type : CounterBasedGauge64
Field Status : current
Description : L3/L4 Process Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.27

Field Name : pktNotFromNatInside
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet Dropped For Not Coming From NAT Inside
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.26

Field Name : excessiveRemotePeers
Field Type : CounterBasedGauge64
Field Status : current
Description : Excessive Remote Peers
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.25

Field Name : addressMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : PCP Client Address Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.24

Field Name : cannotProvideSuggest
Field Type : CounterBasedGauge64
Field Status : current

Description : Cannot Provide Suggested Port When PREFER_FAILURE
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.23

Field Name : userQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : User Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.22

Field Name : unsuppProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : Unsupported Mapping Protocol
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.21

Field Name : noResources
Field Type : CounterBasedGauge64
Field Status : current
Description : No System or NAT Resources
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.20

Field Name : malformOption
Field Type : CounterBasedGauge64
Field Status : current
Description : PCP Option Malformed
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.19

Field Name : unsuppOption
Field Type : CounterBasedGauge64
Field Status : current
Description : Unsupported PCP Option
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.18

Field Name : unsuppOpcode
Field Type : CounterBasedGauge64
Field Status : current
Description : Unsupported PCP Opcode
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.17

Field Name : malformRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : PCP Request Malformed
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.16

Field Name : notAuthorized
Field Type : CounterBasedGauge64
Field Status : current
Description : PCP Request Not Authorized
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.15

Field Name : unsupportedVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : Unsupported PCP version
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.14

Field Name : norouteDrop

Field Type : CounterBasedGauge64
Field Status : current
Description : Response No Route
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.13

Field Name : pktTooShortDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet Too Short
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.12

Field Name : pktNotRequestDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet Not a PCP Request
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.11

Field Name : nat64AnnounceProcessSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : PCP ANNOUNCE Request Processing Success (NAT64)
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.10

Field Name : dsliteAnnounceProcessSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : PCP ANNOUNCE Request Processing Success (DS-Lite)
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.9

Field Name : lsnAnnounceProcessSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : PCP ANNOUNCE Request Processing Success (NAT44)
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.8

Field Name : nat64PeerProcessSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : PCP PEER Request Processing Success (NAT64)
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.7

Field Name : dslitePeerProcessSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : PCP PEER Request Processing Success (DS-Lite)
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.6

Field Name : lsnPeerProcessSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : PCP PEER Request Processing Success (NAT44)
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.5

Field Name : nat64MapProcessSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : PCP MAP Request Processing Success (NAT64)
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.4

Field Name : dsliteMapProcessSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : PCP MAP Request Processing Success (DS-Lite)
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.3

Field Name : lsnMapProcessSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : PCP MAP Request Processing Success (NAT44)
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.2

Field Name : packetsRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.1

Field Name : helperInRml
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Session in Remove List
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.7.1.7

Field Name : helperAlreadyUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Session already used
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.7.1.6

Field Name : helperFreedUnused
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Sessions freed unused
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.7.1.5

Field Name : helperFreedUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Sessions freed used
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.7.1.4

Field Name : helperFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.7.1.3

Field Name : helperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.7.1.2

Field Name : sessionCreated
Field Type : CounterBasedGauge64
Field Status : current

Description : TFTP Client Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.7.1.1

Field Name : tcpOutOfOrderDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Out-of-Order Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.19

Field Name : rewriteFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP Message Rewrite Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.18

Field Name : modifyFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP Message Modify Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.17

Field Name : sdpAllocPortMapFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP Alloc SDP Port Map Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.16

Field Name : sdpAllocPortMapSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP Alloc SDP Port Map Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.15

Field Name : sdpOpFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP Operate SDP Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.14

Field Name : sdpProcessCandidateFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP Operate SDP Media Candidate Attribute Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.13

Field Name : thirdPartySdp
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP Third-Party SDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.12

Field Name : connExtCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP Create Connection Extension Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.11

Field Name : parseError

Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP Message Parse Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.10

Field Name : rsip
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP RSIP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.9

Field Name : rqnt
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP RQNT
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.8

Field Name : ntfy
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP NTFY
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.7

Field Name : mdcx
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP MDCX
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.6

Field Name : epcf
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP EPCF
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.5

Field Name : dlcx
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP DLCX
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.4

Field Name : crcx
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP CRCX
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.3

Field Name : aucx
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP AUCX
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.2

Field Name : auep
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP AUEP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.1

Field Name : helperFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.43

Field Name : helperFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Conn Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.42

Field Name : helperDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Conn Already Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.41

Field Name : helperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Conn Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.40

Field Name : helperFound
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Conn Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.39

Field Name : smpConnAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Conn Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.38

Field Name : tcpOutOfOrderDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Out-of-Order Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.37

Field Name : rewriteFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Message Rewrite Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.36

Field Name : modifyFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Message Modify Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.35

Field Name : sdpAllocPortMapFailure
Field Type : CounterBasedGauge64
Field Status : current

Description : SIP Alloc SDP Port Map Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.34

Field Name : sdpAllocPortMapSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Alloc SDP Port Map Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.33

Field Name : sdpOpFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate SDP Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.32

Field Name : sdpProcessCandidateFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate SDP Media Candidate Attribute Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.31

Field Name : thirdPartySdp
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Third-Party SDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.30

Field Name : insideContactPortMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Inside Contact Port Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.29

Field Name : outsideContactPortMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Outside Contact Port Mismatch NAT Port
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.28

Field Name : allocContactPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Alloc Contact Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.27

Field Name : connExtCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Create Connection Extension Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.26

Field Name : thirdPartyRegistration
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Third-Party Registration
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.25

Field Name : contentLengthHdrOpFailrue

Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate Content-Length Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.24

Field Name : recordRouteHdrOpFailrue
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate Record-Route Header Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.23

Field Name : routeHdrOpFailrue
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate Route Header Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.22

Field Name : toHdrOpFailrue
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate To Header Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.21

Field Name : fromHdrOpFailrue
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate From Header Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.20

Field Name : contactHdrOpFailrue
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate Contact Header Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.19

Field Name : viaHdrOpFailrue
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate Via Header Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.18

Field Name : reqUriOpFailrue
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate Request Uri Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.17

Field Name : parseError
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Message Parse Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.16

Field Name : cgnv6FixedNatAlgSipMethodUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method UNKNOWN
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.15

Field Name : cgnv6FixedNatAlgSipMethodUpdate
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method UPDATE
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.14

Field Name : cgnv6FixedNatAlgSipMethodMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method MESSAGE
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.13

Field Name : cgnv6FixedNatAlgSipMethodRefer
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method REFER
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.12

Field Name : cgnv6FixedNatAlgSipMethodInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method INFO
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.11

Field Name : cgnv6FixedNatAlgSipMethodPublish
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method PUBLISH
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.10

Field Name : cgnv6FixedNatAlgSipMethodNotify
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method NOTIFY
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.9

Field Name : cgnv6FixedNatAlgSipMethodSubscribe
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method SUBSCRIBE
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.8

Field Name : cgnv6FixedNatAlgSipMethodPrack
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method PRACK
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.7

Field Name : methodOptions
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method OPTIONS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.6

Field Name : cgnv6FixedNatAlgSipMethodBye
Field Type : CounterBasedGauge64
Field Status : current

Description : SIP Method BYE
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.5

Field Name : cgnv6FixedNatAlgSipMethodCancel
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method CANCEL
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.4

Field Name : cgnv6FixedNatAlgSipMethodAck
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method ACK
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.3

Field Name : cgnv6FixedNatAlgSipMethodInvite
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method INVITE
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.2

Field Name : cgnv6FixedNatAlgSipMethodRegister
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method REGISTER
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.1

Field Name : smpAppTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP ALG App Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.41

Field Name : haStreamSmpAcquireFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : HA SMP Session Acquire Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.40

Field Name : haStreamSmpReused
Field Type : CounterBasedGauge64
Field Status : current
Description : HA SMP Session Reused
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.39

Field Name : haExtensionFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Conn Extension Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.38

Field Name : haDataExists
Field Type : CounterBasedGauge64
Field Status : current
Description : HA New Data Session Already Exists
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.37

Field Name : haControlClosed

Field Type : CounterBasedGauge64
Field Status : current
Description : HA New Data Control Session Closed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.36

Field Name : haDataNoSmp
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Data Session SMP Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.35

Field Name : haDataSessionRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Data Session Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.34

Field Name : haDataSessionSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Data Session Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.33

Field Name : haPortAllocationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Stream Port Allocation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.32

Field Name : haStreamExists
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Stream Already Exists
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.31

Field Name : haStreamIncompatible
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Incompatible Streams Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.30

Field Name : haStreamsRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Streams Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.29

Field Name : haStreamsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Streams Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.28

Field Name : dataFreeSmpNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Free SMP Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.27

Field Name : dataFreeSmpRetryLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Free SMP Retry Lookup
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.26

Field Name : crossCpuRcvFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Receive Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.25

Field Name : crossCpuCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Creation
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.24

Field Name : crossCpuNoSession
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU No Session Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.23

Field Name : crossCpuRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.22

Field Name : crossCpuSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.21

Field Name : rtcpReversed
Field Type : CounterBasedGauge64
Field Status : current
Description : RTCP Reverse Creation
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.20

Field Name : rtpReversed
Field Type : CounterBasedGauge64
Field Status : current
Description : RTP Reverse Creation
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.19

Field Name : dataSessionCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : New Data Session Creation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.18

Field Name : dataSessionExists
Field Type : CounterBasedGauge64
Field Status : current

Description : New Session Already Exists
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.17

Field Name : controlClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : New Session Closed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.16

Field Name : smpDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : New Session SMP Already Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.15

Field Name : fixedNatLidStandby
Field Type : CounterBasedGauge64
Field Status : current
Description : New Session Fixed NAT LID Standby
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.14

Field Name : smpReused
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Session Reused
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.13

Field Name : smpRemoved
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Session Removed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.12

Field Name : smpInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Session Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.11

Field Name : noSessionMem
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Creation Failures
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.10

Field Name : cgnv6FixedNatAlgRtspDataSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.9

Field Name : cgnv6FixedNatAlgRtspDataSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.8

Field Name : unknownClientPortFromServer

Field Type : CounterBasedGauge64
Field Status : current
Description : Server Replies With Unknown Client Ports
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.7

Field Name : portAllocationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream Client Port Allocation Failures
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.6

Field Name : portsFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream Client Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.5

Field Name : portsAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream Client Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.4

Field Name : streamCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream Creation Failures
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.3

Field Name : streamsFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Streams Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.2

Field Name : streamsCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Streams Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.1

Field Name : controlFreeSmpAppTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Control Free SMP App Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.44

Field Name : controlFreeNoSmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Control Free No SMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.43

Field Name : controlFreeNoExt
Field Type : CounterBasedGauge64
Field Status : current
Description : Control Free No Ext
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.42

Field Name : controlFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Control Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.41

Field Name : greFreeSmpAppTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Free SMP App Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.40

Field Name : greFreeNoSmp
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Free No SMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.39

Field Name : greFreeNoExt
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Free No Ext
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.38

Field Name : greConnAlreadyExists
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Conn Already Exists
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.37

Field Name : greNoControlConn
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE No Control Conn
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.36

Field Name : greNoRevRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE No Rev Route
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.35

Field Name : greNoFwdRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE No Fwd Route
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.34

Field Name : greConnExtCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Conn Ext Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.33

Field Name : greConnCreationFailure
Field Type : CounterBasedGauge64
Field Status : current

Description : GRE Conn Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.32

Field Name : smpAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Session Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.31

Field Name : smpClientCallIdMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Client Call ID Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.30

Field Name : callReplyExtAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Request Ext Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.29

Field Name : callReplyRetransmitAcquired
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Reply Retransmit Acquired
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.28

Field Name : callReplyRetransmitWrongControl
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Reply Retransmit Wrong Control
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.27

Field Name : callReplyRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Reply Retransmit
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.26

Field Name : callReplyCallIdUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Reply Unknown Client Call ID
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.25

Field Name : callReqExtAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Request Ext Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.24

Field Name : callReqNew
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Request New
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.23

Field Name : callReqRetransmit

Field Type : CounterBasedGauge64
Field Status : current
Description : Call Request Retransmit
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.22

Field Name : callReplyPnsCallIdMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Call ID Mismatch on Call Reply
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.21

Field Name : callReqPnsCallIdMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Call ID Mismatch on Call Request
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.20

Field Name : smpAppTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP ALG App Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.19

Field Name : haSmpInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : HA SMP Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.18

Field Name : haSmpConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : HA SMP Conflicts
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.17

Field Name : haCallRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Call Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.16

Field Name : haCallSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Call Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.15

Field Name : haOverwrite
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Call ID Overwrites
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.14

Field Name : haConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Call ID Conflicts
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.13

Field Name : haNoMem
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Memory Allocation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.12

Field Name : haRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Info Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.11

Field Name : haSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Info Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.10

Field Name : extensionCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Extension Creation Failures
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.9

Field Name : smpSessionCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Session Creation Failures
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.8

Field Name : smpSessionsFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Sessions Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.7

Field Name : smpSessionsCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.6

Field Name : noGreSessionMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : No Matching GRE Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.5

Field Name : greSessionsFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Sessions Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.4

Field Name : greSessionsCreated
Field Type : CounterBasedGauge64
Field Status : current

Description : GRE Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.3

Field Name : cgnv6FixedNatAlgPptpMismatched
Field Type : CounterBasedGauge64
Field Status : current
Description : Mismatched PNS Call ID
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.2

Field Name : cgnv6FixedNatAlgPptpCallsEstablished
Field Type : CounterBasedGauge64
Field Status : current
Description : Calls Established
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.1

Field Name : smpAppTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP ALG App Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.18

Field Name : getConnExtFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Get Conn Extension Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.17

Field Name : pasvHelperCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Passive Helper Creation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.16

Field Name : portHelperCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Helper Creation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.15

Field Name : pasvHelperUnused
Field Type : CounterBasedGauge64
Field Status : current
Description : Passive Mode Helper Unused
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.14

Field Name : portHelperUnused
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Mode Helper Unused
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.13

Field Name : pasvHelperFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Passive Mode Helper Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.12

Field Name : portHelperFreed

Field Type : CounterBasedGauge64
Field Status : current
Description : Port Mode Helper Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.11

Field Name : pasvHelperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Passive Mode Helper Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.10

Field Name : portHelperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Mode Helper Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.9

Field Name : pasvRetransmits
Field Type : CounterBasedGauge64
Field Status : current
Description : Passive Mode Reply Retransmits
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.8

Field Name : portRetransmits
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Mode Request Retransmits
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.7

Field Name : cgnv6FixedNatAlgFtpLpsvReplies
Field Type : CounterBasedGauge64
Field Status : current
Description : LPSV Replies From Server
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.6

Field Name : cgnv6FixedNatAlgFtpEpsvReplies
Field Type : CounterBasedGauge64
Field Status : current
Description : EPSV Replies From Server
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.5

Field Name : cgnv6FixedNatAlgFtpPasvReplies
Field Type : CounterBasedGauge64
Field Status : current
Description : PASV Replies From Server
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.4

Field Name : cgnv6FixedNatAlgFtpLprtRequests
Field Type : CounterBasedGauge64
Field Status : current
Description : LPRT Requests From Client
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.3

Field Name : cgnv6FixedNatAlgFtpEprtRequests
Field Type : CounterBasedGauge64
Field Status : current
Description : EPRT Requests From Client
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.2

Field Name : cgnv6FixedNatAlgFtpPortRequests
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT Requests From Client
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.1

Field Name : placeholderDebug
Field Type : CounterBasedGauge64
Field Status : current
Description : Placeholder Debug
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.1.1.2

Field Name : cgnv6FixedNatAlgEspSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.1.1.1

Field Name : h245DynamicAddrExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 H245 Dynamic Address Exceed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.8.1.11

Field Name : tcpOutOfOrderDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Out-of-Order Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.8.1.10

Field Name : rewriteFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 Message Rewrite Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.8.1.9

Field Name : connExtCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 Packet Rewrite Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.8.1.8

Field Name : messageCrossMultiPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 Message Cross Multiple Packets
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.8.1.7

Field Name : parseError
Field Type : CounterBasedGauge64
Field Status : current
Description : Message Parse Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.8.1.6

Field Name : fastStart
Field Type : CounterBasedGauge64
Field Status : current

Description : H323 FastStart
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.8.1.5

Field Name : h245Tunneled
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 H245 Tunnelled Message
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.8.1.4

Field Name : h245ctlMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 H245 Media Control Message
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.8.1.3

Field Name : h225csMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 H225 Call Signaling Message
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.8.1.2

Field Name : h225rasMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 H225 RAS Message
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.8.1.1

Field Name : configNotFoundInCtx
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT Config Pointer Not Found in MY_CTX
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.343

Field Name : cgnv6FixednatGlobalActiveSubscriberRemoved
Field Type : CounterBasedGauge64
Field Status : current
Description : Active Subscriber Removed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.342

Field Name : cgnv6FixednatGlobalActiveSubscriberAdded
Field Type : CounterBasedGauge64
Field Status : current
Description : Active Subscriber Added
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.341

Field Name : fnatdsliteRevEgressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Egress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.340

Field Name : fnatdsliteRevEgressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Egress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.339

Field Name : fnatdsliteRevEgressPktSizeRange2

Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Egress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.338

Field Name : fnatdsliteRevEgressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Egress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.337

Field Name : fnatdsliteRevIngressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Ingress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.336

Field Name : fnatdsliteRevIngressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Ingress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.335

Field Name : fnatdsliteRevIngressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Ingress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.334

Field Name : fnatdsliteRevIngressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Ingress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.333

Field Name : fnatdsliteFwdEgressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Egress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.332

Field Name : fnatdsliteFwdEgressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Egress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.331

Field Name : fnatdsliteFwdEgressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Egress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.330

Field Name : fnatdsliteFwdEgressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Egress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.329

Field Name : fnatdsliteFwdIngressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Ingress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.328

Field Name : fnatdsliteFwdIngressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Ingress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.327

Field Name : fnatdsliteFwdIngressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Ingress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.326

Field Name : fnatdsliteFwdIngressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Ingress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.325

Field Name : fnatdsliteRevEgressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Egress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.324

Field Name : fnatdsliteRevIngressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Ingress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.323

Field Name : fnatdsliteFwdEgressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Egress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.322

Field Name : fnatdsliteFwdIngressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Ingress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.321

Field Name : fnatdsliteRevEgressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Egress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.320

Field Name : fnatdsliteRevIngressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current

Description : Fixed DS-Lite Reverse Ingress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.319

Field Name : fnatdsliteFwdEgressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Egress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.318

Field Name : fnatdsliteFwdIngressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Ingress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.317

Field Name : fnatdsliteRevEgressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Egress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.316

Field Name : fnatdsliteRevIngressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Ingress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.315

Field Name : fnatdsliteFwdEgressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Egress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.314

Field Name : fnatdsliteFwdIngressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Ingress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.313

Field Name : fnatdsliteRevEgressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Egress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.312

Field Name : fnatdsliteRevIngressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Ingress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.311

Field Name : fnatdsliteFwdEgressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Egress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.310

Field Name : fnatdsliteFwdIngressPacketsIcmp

Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Ingress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.309

Field Name : fnatdsliteRevEgressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Egress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.308

Field Name : fnatdsliteRevIngressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Ingress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.307

Field Name : fnatdsliteFwdEgressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Egress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.306

Field Name : fnatdsliteFwdIngressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Ingress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.305

Field Name : fnatdsliteRevEgressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Egress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.304

Field Name : fnatdsliteRevIngressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Ingress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.303

Field Name : fnatdsliteFwdEgressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Egress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.302

Field Name : fnatdsliteFwdIngressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Ingress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.301

Field Name : fnatdsliteRevEgressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Egress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.300

Field Name : fnatdsliteRevIngressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Ingress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.299

Field Name : fnatdsliteFwdEgressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Egress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.298

Field Name : fnatdsliteFwdIngressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Ingress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.297

Field Name : fnatdsliteRevEgressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Egress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.296

Field Name : fnatdsliteRevIngressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Ingress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.295

Field Name : fnatdsliteFwdEgressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Egress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.294

Field Name : fnatdsliteFwdIngressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Ingress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.293

Field Name : fnat64RevEgressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Egress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.292

Field Name : fnat64RevEgressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Egress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.291

Field Name : fnat64RevEgressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current

Description : Fixed NAT64 Reverse Egress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.290

Field Name : fnat64RevEgressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Egress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.289

Field Name : fnat64RevIngressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Ingress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.288

Field Name : fnat64RevIngressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Ingress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.287

Field Name : fnat64RevIngressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Ingress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.286

Field Name : fnat64RevIngressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Ingress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.285

Field Name : fnat64FwdEgressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Egress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.284

Field Name : fnat64FwdEgressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Egress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.283

Field Name : fnat64FwdEgressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Egress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.282

Field Name : fnat64FwdEgressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Egress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.281

Field Name : fnat64FwdIngressPktSizeRange4

Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Ingress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.280

Field Name : fnat64FwdIngressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Ingress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.279

Field Name : fnat64FwdIngressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Ingress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.278

Field Name : fnat64FwdIngressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Ingress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.277

Field Name : fnat64RevEgressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Egress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.276

Field Name : fnat64RevIngressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Ingress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.275

Field Name : fnat64FwdEgressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Egress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.274

Field Name : fnat64FwdIngressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Ingress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.273

Field Name : fnat64RevEgressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Egress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.272

Field Name : fnat64RevIngressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Ingress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.271

Field Name : fnat64FwdEgressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Egress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.270

Field Name : fnat64FwdIngressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Ingress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.269

Field Name : fnat64RevEgressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Egress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.268

Field Name : fnat64RevIngressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Ingress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.267

Field Name : fnat64FwdEgressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Egress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.266

Field Name : fnat64FwdIngressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Ingress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.265

Field Name : fnat64RevEgressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Egress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.264

Field Name : fnat64RevIngressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Ingress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.263

Field Name : fnat64FwdEgressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Egress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.262

Field Name : fnat64FwdIngressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current

Description : Fixed NAT64 Forward Ingress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.261

Field Name : fnat64RevEgressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Egress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.260

Field Name : fnat64RevIngressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Ingress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.259

Field Name : fnat64FwdEgressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Egress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.258

Field Name : fnat64FwdIngressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Ingress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.257

Field Name : fnat64RevEgressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Egress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.256

Field Name : fnat64RevIngressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Ingress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.255

Field Name : fnat64FwdEgressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Egress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.254

Field Name : fnat64FwdIngressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Ingress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.253

Field Name : fnat64RevEgressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Egress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.252

Field Name : fnat64RevIngressBytesTcp

Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Ingress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.251

Field Name : fnat64FwdEgressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Egress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.250

Field Name : fnat64FwdIngressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Ingress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.249

Field Name : fnat64RevEgressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Egress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.248

Field Name : fnat64RevIngressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Ingress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.247

Field Name : fnat64FwdEgressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Egress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.246

Field Name : fnat64FwdIngressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Ingress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.245

Field Name : fnat44RevEgressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Egress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.244

Field Name : fnat44RevEgressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Egress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.243

Field Name : fnat44RevEgressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Egress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.242

Field Name : fnat44RevEgressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Egress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.241

Field Name : fnat44RevIngressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Ingress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.240

Field Name : fnat44RevIngressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Ingress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.239

Field Name : fnat44RevIngressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Ingress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.238

Field Name : fnat44RevIngressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Ingress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.237

Field Name : fnat44FwdEgressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Egress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.236

Field Name : fnat44FwdEgressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Egress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.235

Field Name : fnat44FwdEgressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Egress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.234

Field Name : fnat44FwdEgressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Egress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.233

Field Name : fnat44FwdIngressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current

Description : Fixed NAT44 Forward Ingress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.232

Field Name : fnat44FwdIngressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Ingress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.231

Field Name : fnat44FwdIngressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Ingress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.230

Field Name : fnat44FwdIngressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Ingress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.229

Field Name : fnat44RevEgressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Egress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.228

Field Name : fnat44RevIngressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Ingress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.227

Field Name : fnat44FwdEgressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Egress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.226

Field Name : fnat44FwdIngressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Ingress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.225

Field Name : fnat44RevEgressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Egress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.224

Field Name : fnat44RevIngressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Ingress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.223

Field Name : fnat44FwdEgressPacketsOthers

Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Egress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.222

Field Name : fnat44FwdIngressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Ingress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.221

Field Name : fnat44RevEgressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Egress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.220

Field Name : fnat44RevIngressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Ingress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.219

Field Name : fnat44FwdEgressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Egress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.218

Field Name : fnat44FwdIngressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Ingress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.217

Field Name : fnat44RevEgressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Egress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.216

Field Name : fnat44RevIngressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Ingress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.215

Field Name : fnat44FwdEgressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Egress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.214

Field Name : fnat44FwdIngressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Ingress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.213

Field Name : fnat44RevEgressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Egress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.212

Field Name : fnat44RevIngressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Ingress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.211

Field Name : fnat44FwdEgressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Egress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.210

Field Name : fnat44FwdIngressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Ingress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.209

Field Name : fnat44RevEgressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Egress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.208

Field Name : fnat44RevIngressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Ingress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.207

Field Name : fnat44FwdEgressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Egress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.206

Field Name : fnat44FwdIngressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Ingress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.205

Field Name : fnat44RevEgressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Egress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.204

Field Name : fnat44RevIngressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current

Description : Fixed NAT44 Reverse Ingress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.203

Field Name : fnat44FwdEgressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Egress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.202

Field Name : fnat44FwdIngressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Ingress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.201

Field Name : fnat44RevEgressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Egress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.200

Field Name : fnat44RevIngressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Ingress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.199

Field Name : fnat44FwdEgressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Egress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.198

Field Name : fnat44FwdIngressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Ingress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.197

Field Name : cgnv6FixednatGlobalNatPortUnavailableIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : HA ICMP NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.196

Field Name : cgnv6FixednatGlobalNatPortUnavailableUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : HA UDP NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.195

Field Name : cgnv6FixednatGlobalNatPortUnavailableTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : HA TCP NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.194

Field Name : haIcmpUserQuotaExceeded

Field Type : CounterBasedGauge64
Field Status : current
Description : HA ICMP User Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.193

Field Name : haUdpUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : HA UDP User Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.192

Field Name : haTcpUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : HA TCP User Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.191

Field Name : icmpUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP User Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.190

Field Name : udpUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP User Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.189

Field Name : tcpUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP User Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.188

Field Name : haSessionUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Sessions User Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.187

Field Name : totalUdpFreeOverloadShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP freed via overload shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.186

Field Name : totalTcpFreeOverloadShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP freed via overload shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.185

Field Name : totalUdpAllocOverloadShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP allocated via overload shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.184

Field Name : totalTcpAllocOverloadShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP allocated via overload shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.183

Field Name : totalUdpOverloadReleasedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP ports released from port overloading shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.182

Field Name : totalTcpOverloadReleasedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP ports released from port overloading shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.181

Field Name : totalUdpOverloadAcquiredShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP ports acquired for port overloading shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.180

Field Name : totalTcpOverloadAcquiredShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP ports acquired for port overloading shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.179

Field Name : portOverloadFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Port overload failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.178

Field Name : portOverloadFreeSmpNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Port overload free SMP conn not found
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.177

Field Name : portOverloadSmpFreeNoLid
Field Type : CounterBasedGauge64
Field Status : current
Description : Port overload SMP conn free no lid
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.176

Field Name : portOverloadSmpFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Port overload SMP conn free
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.175

Field Name : portOverloadOutOfMemory
Field Type : CounterBasedGauge64
Field Status : current

Description : Port overload out of memory
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.174

Field Name : portOverloadSmpMemAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Port overload SMP mem allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.173

Field Name : portOverloadSmpDeleteScheduled
Field Type : CounterBasedGauge64
Field Status : current
Description : Port overload SMP conn delete scheduled
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.172

Field Name : totalUdpFreeOverload
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP ports freed via overload
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.171

Field Name : totalTcpFreeOverload
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP ports freed via overload
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.170

Field Name : totalUdpAllocOverload
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP ports allocated via overload
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.169

Field Name : totalTcpAllocOverload
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP ports allocated via overload
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.168

Field Name : totalUdpOverloadReleased
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP ports released from port overloading
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.167

Field Name : totalTcpOverloadReleased
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP ports released from port overloading
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.166

Field Name : totalUdpOverloadAcquired
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP ports acquired for port overloading
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.165

Field Name : totalTcpOverloadAcquired

Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP ports acquired for port overloading
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.164

Field Name : dsliteTunnelFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Fragment DS-Lite Packet
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.163

Field Name : ipdDisabled
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT IPD disabled
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.162

Field Name : ipv6UserUnusable
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT IPv6 User Marked Unusable
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.161

Field Name : ipv4UserUnusable
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT IPv4 User Marked Unusable
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.160

Field Name : userUnusableDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT User Unusable Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.159

Field Name : mgcpAlgCreateRtcpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Create RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.158

Field Name : mgcpAlgCreateRtpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Create RTP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.157

Field Name : mgcpAlgSingleRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Single RTCP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.156

Field Name : mgcpAlgReuseRtpRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Reuse RTP/RTCP Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.155

Field Name : mgcpAlgRtcpFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG RTCP Full-cone NAT Port Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.154

Field Name : mgcpAlgSingleRtpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Single RTP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.153

Field Name : mgcpAlgCreateFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Create Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.152

Field Name : mgcpAlgFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Full-cone Session Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.151

Field Name : mgcpAlgReuseFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Reuse Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.150

Field Name : h323AlgCreateRtcpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Create RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.149

Field Name : h323AlgCreateRtpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Create RTP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.148

Field Name : h323AlgSingleRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Single RTCP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.147

Field Name : h323AlgReuseRtpRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Reuse RTP/RTCP Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.146

Field Name : h323AlgRtcpFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current

Description : H323 ALG RTCP Full-cone NAT Port Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.145

Field Name : h323AlgSingleRtpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Single RTP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.144

Field Name : h323AlgCreateFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Create Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.143

Field Name : h323AlgFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Full-cone Session Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.142

Field Name : h323AlgReuseFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Reuse Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.141

Field Name : dsliteUdpAlgFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite UDP ALG Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.140

Field Name : dsliteUdpAlgFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite UDP ALG Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.139

Field Name : dsliteUdpFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite UDP Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.138

Field Name : dsliteUdpFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite UDP Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.137

Field Name : dsliteTcpFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite TCP Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.136

Field Name : dsliteTcpFullconeCreatedShadow

Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite TCP Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.135

Field Name : nat64UdpAlgFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 UDP ALG Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.134

Field Name : nat64UdpAlgFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 UDP ALG Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.133

Field Name : nat64UdpFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 UDP Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.132

Field Name : nat64UdpFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 UDP Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.131

Field Name : nat64TcpFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 TCP Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.130

Field Name : nat64TcpFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 TCP Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.129

Field Name : nat44UdpAlgFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 UDP ALG Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.128

Field Name : nat44UdpAlgFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 UDP ALG Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.127

Field Name : nat44UdpFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 UDP Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.126

Field Name : nat44UdpFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 UDP Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.125

Field Name : nat44TcpFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 TCP Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.124

Field Name : nat44TcpFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 TCP Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.123

Field Name : dsliteDataSessionFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite Data Sessions Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.122

Field Name : dsliteDataSessionCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite Data Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.121

Field Name : nat64DataSessionFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Data Sessions Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.120

Field Name : nat64DataSessionCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Data Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.119

Field Name : nat44DataSessionFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 Data Sessions Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.118

Field Name : nat44DataSessionCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 Data Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.117

Field Name : totalIcmpFreedShadow
Field Type : CounterBasedGauge64
Field Status : current

Description : Total ICMP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.116

Field Name : totalIcmpAllocatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total ICMP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.115

Field Name : totalUdpFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.114

Field Name : totalUdpAllocatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.113

Field Name : totalTcpFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.112

Field Name : totalTcpAllocatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.111

Field Name : natEspIpConflicts
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT ESP IP Conflicts
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.110

Field Name : icmpOutOfStateUqeDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User Queue Exceeded ICMP notification dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.109

Field Name : icmpOutOfStateUqeHostUnreachableSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User Quota Exceeded ICMP host unreachable sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.108

Field Name : icmpOutOfStateUqeAdminFilteredSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User Quota Exceeded ICMP admin filtered sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.107

Field Name : sipAlgCreateRtcpFullconeFailure

Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Create RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.106

Field Name : sipAlgCreateRtpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Create RTP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.105

Field Name : sipAlgSingleRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Single RTCP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.104

Field Name : sipAlgReuseRtpRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Reuse RTP/RTCP Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.103

Field Name : sipAlgRtcpFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG RTCP Full-cone NAT Port Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.102

Field Name : sipAlgSingleRtpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Single RTP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.101

Field Name : sipAlgCreateContactFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Create Contact Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.100

Field Name : sipAlgContactFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Contact Full-cone Session Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.99

Field Name : sipAlgReuseContactFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Reuse Contact Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.98

Field Name : disableLogMsgFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT Disable Log Msg Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.97

Field Name : disableLogMsgAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT Disable Log Msg Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.96

Field Name : periodicLogMsgFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT Periodic Log Msg Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.95

Field Name : periodicLogMsgAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT Periodic Log Msg Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.94

Field Name : fragIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Packet Too Big Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.93

Field Name : frag
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragmented Packets
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.92

Field Name : mtuExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet Exceeded MTU
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.91

Field Name : udpAlgAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP ALG Port Allocation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.90

Field Name : udpAlgNoNatIp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP ALG User-Quota Unknown NAT IP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.89

Field Name : udpAlgEimMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP ALG Endpoint-Independent Mapping Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.88

Field Name : haEndpointIndepMapMatch
Field Type : CounterBasedGauge64
Field Status : current

Description : HA Endpoint-Independent-Mapping Match
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.87

Field Name : haFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Full-Cone Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.86

Field Name : haNatPortUnavailable
Field Type : CounterBasedGauge64
Field Status : current
Description : HA NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.85

Field Name : haDnatMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Destination NAT Config Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.84

Field Name : haFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Full-Cone Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.83

Field Name : haUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : HA User Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.82

Field Name : haConfigMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Fixed NAT Config Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.81

Field Name : fullconeOverflowEif
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone EIF Overflow
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.80

Field Name : fullconeOverflowEim
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone EIM Overflow
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.79

Field Name : fullconeNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone session not found
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.78

Field Name : fullconeRetryLookup

Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone session retry look-up
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.77

Field Name : fullconeInboundIdxMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-Cone Session Fixed NAT LID mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.76

Field Name : fullconeOverflow
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-Cone Session Conn-Count Overflow
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.75

Field Name : fullconeInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-Cone Session in Delete Queue
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.74

Field Name : configNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT Config not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.73

Field Name : crossCpuSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Packets Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.72

Field Name : crossCpuHelperCpuMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper CPU Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.71

Field Name : crossCpuHelperFixedNatLidStandby
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Fixed NAT LID Standby
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.70

Field Name : crossCpuHelperDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Session Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.69

Field Name : crossCpuNoSession
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU no Session Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.68

Field Name : crossCpuBadL4
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Unsupported L4
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.67

Field Name : crossCpuBadL3
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Unsupported L3
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.66

Field Name : crossCpuRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Packets Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.65

Field Name : crossCpuHelperFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.64

Field Name : crossCpuHelperFreeNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Session Free not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.63

Field Name : crossCpuHelperFreeRetryLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Session Free Retry Lookup
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.62

Field Name : crossCpuHelperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.61

Field Name : destRlistSnatDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT Dest Rules List Source NAT Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.60

Field Name : destRlistPassThrough
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT Dest Rule List Pass-Through
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.59

Field Name : destRlistDrop
Field Type : CounterBasedGauge64
Field Status : current

Description : Fixed NAT Dest Rule List Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.58

Field Name : cgnv6FixednatGlobal6rdDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT IPv6 in IPv4 Packet Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.57

Field Name : fixedNatFullconeSelfHairpinningDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Self-Hairpinning Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.56

Field Name : standbyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT LID Standby Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.55

Field Name : dsliteHairpin
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite Hairpin Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.54

Field Name : nat64Hairpin
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Hairpin Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.53

Field Name : nat44Hairpin
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 Hairpin Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.52

Field Name : dsliteEifLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite Endpoint-Independent-Filtering Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.51

Field Name : nat64EifLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Endpoint-Independent-Filtering Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.50

Field Name : nat44EifLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 Endpoint-Independent-Filtering Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.49

Field Name : dsliteInboundFiltered

Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite Endpoint-Dependent Filtering Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.48

Field Name : nat64InboundFiltered
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Endpoint-Dependent Filtering Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.47

Field Name : nat44InboundFiltered
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 Endpoint-Dependent Filtering Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.46

Field Name : dsliteEifMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite Endpoint-Independent-Filtering Matched
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.45

Field Name : nat64EifMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Endpoint-Independent-Filtering Matched
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.44

Field Name : nat44EifMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 Endpoint-Independent-Filtering Matched
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.43

Field Name : dsliteEimMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite Endpoint-Independent-Mapping Matched
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.42

Field Name : nat64EimMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Endpoint-Independent-Mapping Matched
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.41

Field Name : nat44EimMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 Endpoint-Independent-Mapping Matched
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.40

Field Name : cgnv6FixednatGlobalFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-Cone Session Creation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.39

Field Name : dsliteUdpAlgFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite UDP ALG Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.38

Field Name : dsliteUdpAlgFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite UDP ALG Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.37

Field Name : dsliteUdpFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite UDP Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.36

Field Name : dsliteUdpFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite UDP Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.35

Field Name : dsliteTcpFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite TCP Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.34

Field Name : dsliteTcpFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite TCP Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.33

Field Name : nat64UdpAlgFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 UDP ALG Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.32

Field Name : nat64UdpAlgFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 UDP ALG Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.31

Field Name : nat64UdpFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 UDP Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.30

Field Name : nat64UdpFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current

Description : NAT64 UDP Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.29

Field Name : nat64TcpFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 TCP Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.28

Field Name : nat64TcpFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 TCP Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.27

Field Name : nat44UdpAlgFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 UDP ALG Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.26

Field Name : nat44UdpAlgFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 UDP ALG Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.25

Field Name : nat44UdpFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 UDP Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.24

Field Name : nat44UdpFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 UDP Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.23

Field Name : nat44TcpFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 TCP Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.22

Field Name : nat44TcpFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 TCP Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.21

Field Name : sessionUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Sessions User Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.20

Field Name : cgnv6FixednatGlobalNatPortUnavailableIcmp

Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.16

Field Name : cgnv6FixednatGlobalNatPortUnavailableUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.15

Field Name : cgnv6FixednatGlobalNatPortUnavailableTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.14

Field Name : dsliteDataSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite Data Sessions Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.13

Field Name : dsliteDataSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite Data Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.12

Field Name : nat64DataSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Data Sessions Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.11

Field Name : nat64DataSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Data Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.10

Field Name : nat44DataSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 Data Sessions Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.9

Field Name : nat44DataSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 Data Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.8

Field Name : cgnv6FixednatGlobalTotalTotalIcmpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total ICMP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.7

Field Name : cgnv6FixednatGlobalTotalIcmpAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total ICMP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.6

Field Name : cgnv6FixednatGlobalTotalUdpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.5

Field Name : cgnv6FixednatGlobalTotalUdpAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.4

Field Name : cgnv6FixednatGlobalTotalTcpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.3

Field Name : cgnv6FixednatGlobalTotalTcpAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.2

Field Name : totalNatInUse
Field Type : CounterBasedGauge64
Field Status : current
Description : Total NAT Addresses in-use
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.1

Field Name : tcamCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : TCAM Flow Count
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.20

Field Name : tcamFree
Field Type : CounterBasedGauge64
Field Status : current
Description : TCAM Flows Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.19

Field Name : tcamCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : TCAM Flows Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.18

Field Name : entryInvalidateServerDown
Field Type : CounterBasedGauge64
Field Status : current

Description : HW Entries Invalidate due to server down
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.17

Field Name : entryForceHwInvalidate
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Force HW Invalidate
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.16

Field Name : entryAgeOutInvalidDst
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out - invalid dst
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.15

Field Name : entryAgeOutTcpRst
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out - TCP RST
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.14

Field Name : entryAgeOutTcpFin
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out - TCP FIN
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.13

Field Name : entryAgeOutIdle
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out - idle timeout
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.12

Field Name : entryAgeOut
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.11

Field Name : entryCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Count
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.10

Field Name : entryFreeNoSwEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Freed - no software entry
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.9

Field Name : entryFreeNoConn
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Freed - no matched conn
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.8

Field Name : entryFreeNoHwProg

Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Freed - no HW prog
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.7

Field Name : entryFreeOppEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Freed - opposite tuple entry aged-out
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.6

Field Name : entryFree
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.5

Field Name : entryCreateFailMaxEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Creation Failed - max entries exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.4

Field Name : entryCreateFailServerDown
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Creation Failed - server down
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.3

Field Name : entryCreateFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Creation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.2

Field Name : entryCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.1

Field Name : connCount
Field Type : CounterBasedGauge64
Field Status : current
Description : conn count
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.19

Field Name : nat46StatelessOtherError
Field Type : CounterBasedGauge64
Field Status : current
Description : Other errors
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.18

Field Name : haStandby
Field Type : CounterBasedGauge64
Field Status : current
Description : HA is standby
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.17

Field Name : icmpToIcmpv6Error
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP to ICMPv6 errors
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.16

Field Name : icmpToIcmpv6
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP to ICMPv6
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.15

Field Name : icmpv6ToIcmpError
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 to ICMP errors
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.14

Field Name : icmpv6ToIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 to ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.13

Field Name : fragmentError
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment processing errors
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.12

Field Name : packetTooBig
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet too big
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.11

Field Name : inboundIpv4Fragmented
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound IPv4 packets fragmented
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.10

Field Name : inboundIpv4Unreachable
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound IPv4 destination unreachable
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.9

Field Name : inboundIpv6FragmentReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound IPv6 fragment packets received
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.8

Field Name : inboundIpv6Drop
Field Type : CounterBasedGauge64
Field Status : current

Description : Inbound IPv6 packets dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.7

Field Name : inboundIpv6Received
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound IPv6 packets received
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.6

Field Name : outboundIpv6Fragmented
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound IPv6 packets fragmented
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.5

Field Name : outboundIpv6Unreachable
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound IPv6 destination unreachable
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.4

Field Name : outboundIpv4FragmentReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound IPv4 fragment packets received
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.3

Field Name : outboundIpv4Drop
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound IPv4 packets dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.2

Field Name : outboundIpv4Received
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound IPv4 packets received
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.1

Field Name : haStandbySessionEif
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Standby Session EIF
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.58

Field Name : haStandbySessionEim
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Standby Session EIM
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.57

Field Name : haStandbySessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Standby Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.56

Field Name : eifFiltered

Field Type : CounterBasedGauge64
Field Status : current
Description : EIF Filtered
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.55

Field Name : eifProcessFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : EIF Process Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.54

Field Name : eifDisableDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : EIF Disable Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.53

Field Name : eifLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : EIF Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.52

Field Name : fullconeFreeNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone Free Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.51

Field Name : fullconeFreeRetryLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone Retry Look-up
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.50

Field Name : fullconeFreeFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone Free Found From Conn
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.49

Field Name : fullconeOverflowEif
Field Type : CounterBasedGauge64
Field Status : current
Description : EIF Overflow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.48

Field Name : fullconeOverflowEim
Field Type : CounterBasedGauge64
Field Status : current
Description : EIM Overflow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.47

Field Name : fullconeInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone Found in Delete Queue
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.46

Field Name : udpFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Full-cone Freed Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.45

Field Name : udpFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Full-cone Created Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.44

Field Name : tcpFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Full-cone Freed Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.43

Field Name : tcpFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Full-cone Created Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.42

Field Name : ctlMemFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Memory Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.41

Field Name : ctlMemAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Memory Alloc
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.40

Field Name : badSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Session Proto on Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.39

Field Name : sessionCreationFailureShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Creation Failure Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.38

Field Name : otherSessionFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Other Session Freed Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.37

Field Name : otherSessionCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current

Description : Other Session Created Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.36

Field Name : udpSessionFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Session Freed Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.35

Field Name : udpSessionCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Session Created Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.34

Field Name : tcpSessionFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Session Freed Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.33

Field Name : tcpSessionCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Session Created Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.32

Field Name : inboundSessionFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound Session Freed Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.31

Field Name : inboundSessionCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound Session Created Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.30

Field Name : outboundSessionFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound Session Freed Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.29

Field Name : outboundSessionCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound Session Created Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.28

Field Name : cgnv6StatefullFirewallGlobalNoClassListMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : No Class-List Match Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.27

Field Name : oneArmDrop

Field Type : CounterBasedGauge64
Field Status : current
Description : One-Arm Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.26

Field Name : eifProcess
Field Type : CounterBasedGauge64
Field Status : current
Description : Endpnt-Independent Filter Matched
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.25

Field Name : fullconeCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-Cone Creation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.24

Field Name : cgnv6StateFullFirewallGlobalUdpFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Full-cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.23

Field Name : cgnv6StateFullFirewallGlobalUdpFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Full-cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.22

Field Name : cgnv6StateFullFirewallGlobalTcpFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Full-cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.21

Field Name : cgnv6StateFullFirewallGlobalTcpFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Full-cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.20

Field Name : packetStandbyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Standby Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.19

Field Name : cgnv6StateFullFirewallGlobalNoRevRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : No Reverse Route
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.18

Field Name : cgnv6StateFullFirewallGlobalNoFwdRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : No Forward Route
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.17

Field Name : sessionCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Creation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.16

Field Name : otherSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Other Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.15

Field Name : otherSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Other Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.14

Field Name : udpSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.13

Field Name : cgnv6StateFullFirewallGlobalUdpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.12

Field Name : tcpSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.11

Field Name : cgnv6StateFullFirewallGlobalTcpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.10

Field Name : inboundSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.9

Field Name : inboundSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.8

Field Name : outboundSessionFreed
Field Type : CounterBasedGauge64
Field Status : current

Description : Outbound Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.7

Field Name : outboundSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.6

Field Name : packetProcessFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet Error Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.5

Field Name : packetInboundDeny
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound Packet Denied
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.4

Field Name : otherPacketProcess
Field Type : CounterBasedGauge64
Field Status : current
Description : Other Packet Process
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.3

Field Name : udpPacketProcess
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Packet Process
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.2

Field Name : tcpPacketProcess
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Packet Process
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.1

Field Name : rtpEim
Field Type : CounterBasedGauge64
Field Status : current
Description : RTP EIM
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.35

Field Name : rtpAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : RTP Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.34

Field Name : rtpNew
Field Type : CounterBasedGauge64
Field Status : current
Description : RTP Alloc
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.33

Field Name : contactEimSet

Field Type : CounterBasedGauge64
Field Status : current
Description : Contact EIM Set
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.32

Field Name : contactEim
Field Type : CounterBasedGauge64
Field Status : current
Description : Contact EIM
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.31

Field Name : contactAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Contact Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.30

Field Name : contactNew
Field Type : CounterBasedGauge64
Field Status : current
Description : Contact Alloc
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.29

Field Name : contactPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Contact Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.28

Field Name : contactPortSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Contact Port Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.27

Field Name : contactPortNoOp
Field Type : CounterBasedGauge64
Field Status : current
Description : Contact Port No Op
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.26

Field Name : rtcpPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : RTCP Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.25

Field Name : rtpPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : RTP Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.24

Field Name : rtpRtcpPortSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : RTP RTCP Port Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.23

Field Name : rtpPortNoOp
Field Type : CounterBasedGauge64
Field Status : current
Description : RTP Port No Op
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.22

Field Name : sdpError
Field Type : CounterBasedGauge64
Field Status : current
Description : SDP Process Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.21

Field Name : contactError
Field Type : CounterBasedGauge64
Field Status : current
Description : Contact Process Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.20

Field Name : keepAlive
Field Type : CounterBasedGauge64
Field Status : current
Description : Keep Alive
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.19

Field Name : parseError
Field Type : CounterBasedGauge64
Field Status : current
Description : Message Parse Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.18

Field Name : methodUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : Method Unknown
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.17

Field Name : methodUpdate
Field Type : CounterBasedGauge64
Field Status : current
Description : Method UPDATE
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.16

Field Name : methodMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : Method MESSAGE
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.15

Field Name : methodRefer
Field Type : CounterBasedGauge64
Field Status : current
Description : Method REFER
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.14

Field Name : methodInfo
Field Type : CounterBasedGauge64
Field Status : current

Description : Method INFO
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.13

Field Name : methodPublish
Field Type : CounterBasedGauge64
Field Status : current
Description : Method PUBLISH
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.12

Field Name : methodNotify
Field Type : CounterBasedGauge64
Field Status : current
Description : Method NOTIFY
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.11

Field Name : methodSubscribe
Field Type : CounterBasedGauge64
Field Status : current
Description : Method SUBSCRIBE
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.10

Field Name : methodPrack
Field Type : CounterBasedGauge64
Field Status : current
Description : Method PRACK
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.9

Field Name : methodPortConfig
Field Type : CounterBasedGauge64
Field Status : current
Description : Method OPTIONS
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.8

Field Name : methodBye
Field Type : CounterBasedGauge64
Field Status : current
Description : Method BYE
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.7

Field Name : methodCancel
Field Type : CounterBasedGauge64
Field Status : current
Description : Method CANCEL
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.6

Field Name : methodAck
Field Type : CounterBasedGauge64
Field Status : current
Description : Method ACK
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.5

Field Name : methodInvite
Field Type : CounterBasedGauge64
Field Status : current
Description : Method INVITE
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.4

Field Name : methodRegister

Field Type : CounterBasedGauge64
Field Status : current
Description : Method REGISTER
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.3

Field Name : statResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.2

Field Name : statRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.1

Field Name : haDataSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Data Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.35

Field Name : haControlSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Control Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.34

Field Name : haControlExtCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Control Extension Creation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.33

Field Name : dataSessionFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Freed Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.32

Field Name : dataSessionCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Created Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.31

Field Name : transportNotFoundOnDataFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Not Found Data
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.30

Field Name : transportRetryLookupOnDataFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Retry Lookup Data
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.29

Field Name : transportDoubleReleaseFromData
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Double Release Data
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.28

Field Name : transportReleasedFromData
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Released Data
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.27

Field Name : transportAcquireFailureFromData
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Acquire Failure Data
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.26

Field Name : transportAcquiredFromData
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Acquired Data
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.25

Field Name : transportDoubleReleaseFromControl
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Double Release Control
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.24

Field Name : transportReleasedFromControl
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Released Control
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.23

Field Name : transportAcquireFailureFromControl
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Acquire Failure Control
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.22

Field Name : transportFoundFromPrevControl
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Found From Prev Control
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.21

Field Name : transportAcquiredFromControl
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Acquired Control
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.20

Field Name : transportFreedShadow
Field Type : CounterBasedGauge64
Field Status : current

Description : Transport Freed Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.19

Field Name : transportPutInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Put in Delete Queue
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.18

Field Name : transportAllocFailureShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Alloc Failure Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.17

Field Name : transportCreationRace
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Create Race
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.16

Field Name : transportInsertedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Inserted Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.15

Field Name : transportLinkExtFailureData
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Link to Extension Failure Data
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.14

Field Name : transportLinkExtData
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Link to Extension Data
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.13

Field Name : transportLinkExtFailureControl
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Link to Extension Failure Control
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.12

Field Name : transportExists
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Already Exists
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.11

Field Name : transportAlreadyInExt
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Already in Extension
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.10

Field Name : transportTooMany

Field Type : CounterBasedGauge64
Field Status : current
Description : Too Many Transports for Control Conn
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.9

Field Name : transportRemovedFromExt
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Removed from Extension
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.8

Field Name : transportAddToExt
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Added to Extension
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.7

Field Name : extCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Extension Creation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.6

Field Name : cgnv6StatefullFireWallAlgRtspDataSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.5

Field Name : cgnv6StatefullFireWallAlgRtspDataSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.4

Field Name : transportAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.3

Field Name : transportFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.2

Field Name : transportInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.1

Field Name : controlFreeSmpAppTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Control Free SMP App Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.29

Field Name : controlFreeNoSmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Control Free No SMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.28

Field Name : controlFreeNoExt
Field Type : CounterBasedGauge64
Field Status : current
Description : Control Free No Ext
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.27

Field Name : controlFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Control Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.26

Field Name : greFreeSmpAppTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Free SMP App Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.25

Field Name : greFreeNoSmp
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Free No SMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.24

Field Name : greFreeNoExt
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Free No Ext
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.23

Field Name : greConnAlreadyExists
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Conn Already Exists
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.22

Field Name : greNoControlConn
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE No Control Conn
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.21

Field Name : greNoRevRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE No Rev Route
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.20

Field Name : greNoFwdRoute
Field Type : CounterBasedGauge64
Field Status : current

Description : GRE No Fwd Route
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.19

Field Name : greConnExtCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Conn Ext Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.18

Field Name : greConnCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Conn Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.17

Field Name : smpAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Session Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.16

Field Name : smpSessionsFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.15

Field Name : smpSessionsCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.14

Field Name : smpClientCallIdMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Client Call ID Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.13

Field Name : smpAppTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP App Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.12

Field Name : callReplyExtExtAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Request Ext Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.11

Field Name : callReplyRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Reply Retransmit
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.10

Field Name : callReplyCallIdUnknown

Field Type : CounterBasedGauge64
Field Status : current
Description : Call Reply Unknown Client Call ID
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.9

Field Name : callReqExtAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Request Ext Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.8

Field Name : callReqNew
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Request New
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.7

Field Name : callReqRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Request Retransmit
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.6

Field Name : greSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.5

Field Name : greSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.4

Field Name : callReplyPnsCallIdMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Call ID Mismatch on Call Reply
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.3

Field Name : callReqPnsCallIdMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Call ID Mismatch on Call Request
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.2

Field Name : callsEstablished
Field Type : CounterBasedGauge64
Field Status : current
Description : Calls Established
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.1

Field Name : pasvHelperFreedUnused
Field Type : CounterBasedGauge64
Field Status : current
Description : PASV Helper Freed Unused
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.19

Field Name : pasvHelperFreedUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : PASV Helper Freed Used
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.18

Field Name : portHelperFreedUnused
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT Helper Freed Unused
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.17

Field Name : portHelperFreedUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT Helper Freed Used
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.16

Field Name : pasvHelperAcquireAlreadyUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : PASV Helper Acquire Already Used
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.15

Field Name : pasvHelperAcquireInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : PASV Helper Acquire In Del Queue
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.14

Field Name : portHelperAcquireAlreadyUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT Helper Acquire Already Used
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.13

Field Name : portHelperAcquireInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT Helper Acquire In Del Queue
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.12

Field Name : pasvHelperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : PASV Helper Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.11

Field Name : portHelperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT Helper Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.10

Field Name : smpConnAllocFailure
Field Type : CounterBasedGauge64
Field Status : current

Description : SMP Helper Conn Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.9

Field Name : retransmitSanityCheckFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Retransmit Sanity Check Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.8

Field Name : smpAppTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP App Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.7

Field Name : pasvRetransmits
Field Type : CounterBasedGauge64
Field Status : current
Description : PASV Retransmits
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.6

Field Name : portRetransmits
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT Retransmits
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.5

Field Name : serverEpsvReply
Field Type : CounterBasedGauge64
Field Status : current
Description : EPSV Replies From Server
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.4

Field Name : serverPasvReply
Field Type : CounterBasedGauge64
Field Status : current
Description : PASV Replies From Server
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.3

Field Name : clientEprtRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : EPRT Requests From Client
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.2

Field Name : clientPortRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT Requests From Client
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.1

Field Name : helperInRml
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Session in Remove List
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.6.1.7

Field Name : helperAlreadyUsed

Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Session already used
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.6.1.6

Field Name : helperFreedUnused
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Sessions freed unused
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.6.1.5

Field Name : helperFreedUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Sessions freed used
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.6.1.4

Field Name : helperFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.6.1.3

Field Name : helperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.6.1.2

Field Name : cgnv6StateFullFirewallAlgTftpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Client Sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.6.1.1

Field Name : systemAddressDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : LW-4over6 System Address Drops
OID : 1.3.6.1.4.1.22610.2.4.10.115.21.1.1.13

Field Name : sessionCount
Field Type : CounterBasedGauge64
Field Status : current
Description : LW-4over6 Session Count
OID : 1.3.6.1.4.1.22610.2.4.10.115.21.1.1.12

Field Name : noBindingTableMatchesRev
Field Type : TABLE
Field Status : current
Description : No Reverse Binding Table Entry Match Drops
OID : 1.3.6.1.4.1.22610.2.4.10.115.21.1.1.11

Field Name : noBindingTableMatchesFwd
Field Type : TABLE
Field Status : current
Description : No Forward Binding Table Entry Match Drops
OID : 1.3.6.1.4.1.22610.2.4.10.115.21.1.1.10

Field Name : interfaceNotConfigured
Field Type : CounterBasedGauge64
Field Status : current
Description : LW-4over6 Interfaces not Configured Drops
OID : 1.3.6.1.4.1.22610.2.4.10.115.21.1.1.9

Field Name : revLookupFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Route Lookup Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.21.1.1.8

Field Name : fwdLookupFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Route Lookup Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.21.1.1.7

Field Name : icmpInboundDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound ICMP Drops
OID : 1.3.6.1.4.1.22610.2.4.10.115.21.1.1.6

Field Name : noMatchIcmpSent
Field Type : CounterBasedGauge64
Field Status : current
Description : No-Reverse-Match ICMP Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.21.1.1.5

Field Name : noMatchIcmpv6Sent
Field Type : CounterBasedGauge64
Field Status : current
Description : No-Forward-Match ICMPv6 Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.21.1.1.4

Field Name : allHairpinningDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : All Hairpinning Drops
OID : 1.3.6.1.4.1.22610.2.4.10.115.21.1.1.3

Field Name : selfHairpinningDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Self-Hairpinning Drops
OID : 1.3.6.1.4.1.22610.2.4.10.115.21.1.1.2

Field Name : entryCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Entries Configured
OID : 1.3.6.1.4.1.22610.2.4.10.115.21.1.1.1

Field Name : cgnv6SixrdDomainSTable
Field Type : TABLE
Field Status : current

Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1

Field Name : cgnv6SixrdDomainSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1

Field Name : cgnv6SixrdDomainOtherError
Field Type : CounterBasedGauge64
Field Status : current
Description : Other errors
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.22

Field Name : cgnv6SixrdDomainFragmentError
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment processing errors
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.21

Field Name : notLocalIp
Field Type : CounterBasedGauge64
Field Status : current
Description : Not local IP
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.20

Field Name : cgnv6SixrdDomainPacketTooBig
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet too big
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.19

Field Name : unknownDelegatedPrefix
Field Type : CounterBasedGauge64
Field Status : current
Description : Unknown 6rd delegated prefix
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.18

Field Name : vportMatched
Field Type : CounterBasedGauge64
Field Status : current
Description : Traffic match SLB virtual port
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.17

Field Name : inboundTunnelFragmentIpv6
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound Fragmented IPv6 in tunnel
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.16

Field Name : inboundFragmentIpv4
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound Fragmented IPv4
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.15

Field Name : inboundIpv4DestUnreachable

Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound IPv4 destination unreachable
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.14

Field Name : inboundPacketsDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound packets dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.13

Field Name : inboundOtherPacketsReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound other packets received
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.12

Field Name : inboundIcmpPacketsReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound ICMP packets received
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.11

Field Name : inboundUdpPacketsReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound UDP packets received
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.10

Field Name : inboundTcpPacketsReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound TCP packets received
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.9

Field Name : outboundFragmentIpv6
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound Fragmented IPv6
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.8

Field Name : outboundIpv6DestUnreachable
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound IPv6 destination unreachable
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.7

Field Name : outboundPacketsDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound packets dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.6

Field Name : outboundOtherPacketsReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound other packets received
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.5

Field Name : outboundIcmpPacketsReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound ICMP packets received
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.4

Field Name : outboundUdpPacketsReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound UDP packets received
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.3

Field Name : outboundTcpPacketsReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound TCP packets received
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.2

Field Name : cgnv6SixrdDomainName
Field Type : String
Field Status : current
Description : 6rd Domain name
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.1

Field Name : portOverloadingPortFreeUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Overloading NAT Port Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.316

Field Name : portOverloadingPortFreeTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Overloading NAT Port Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.315

Field Name : portOverloadingPortUdpInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading NAT Port UDP Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.314

Field Name : portOverloadingPortTcpInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading NAT Port TCP Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.313

Field Name : prefixQuotaMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Prefix Quota NAT IP Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.312

Field Name : revEgressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current

Description : Reverse Egress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.311

Field Name : revEgressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.310

Field Name : revEgressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.309

Field Name : revEgressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.308

Field Name : revIngressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.307

Field Name : revIngressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.306

Field Name : revIngressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.305

Field Name : revIngressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.304

Field Name : fwdEgressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.303

Field Name : fwdEgressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.302

Field Name : fwdEgressPktSizeRange2

Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.301

Field Name : fwdEgressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.300

Field Name : fwdIngressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.299

Field Name : fwdIngressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.298

Field Name : fwdIngressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.297

Field Name : fwdIngressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.296

Field Name : revEgressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.295

Field Name : revIngressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.294

Field Name : fwdEgressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.293

Field Name : fwdIngressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.292

Field Name : revEgressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.291

Field Name : revIngressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.290

Field Name : fwdEgressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.289

Field Name : fwdIngressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.288

Field Name : revEgressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.287

Field Name : revIngressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.286

Field Name : fwdEgressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.285

Field Name : fwdIngressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.284

Field Name : revEgressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.283

Field Name : revIngressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current

Description : Reverse Ingress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.282

Field Name : fwdEgressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.281

Field Name : fwdIngressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.280

Field Name : revEgressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.279

Field Name : revIngressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.278

Field Name : fwdEgressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.277

Field Name : fwdIngressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.276

Field Name : revEgressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.275

Field Name : revIngressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.274

Field Name : fwdEgressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.273

Field Name : fwdIngressPacketsUdp

Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.272

Field Name : revEgressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.271

Field Name : revIngressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.270

Field Name : fwdEgressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.269

Field Name : fwdIngressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.268

Field Name : revEgressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.267

Field Name : revIngressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.266

Field Name : fwdEgressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.265

Field Name : fwdIngressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.264

Field Name : natPoolSamePortBatchUdpFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Simultaneous Batch Allocation UDP Port Allocation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.263

Field Name : userQuotaUnusable
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Marked Unusable
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.262

Field Name : userQuotaUnusableDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Unusable Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.261

Field Name : mgcpAlgPortPairAllocFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Port Pair Allocated From Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.260

Field Name : mgcpAlgPortPairAllocFromQuotaPartitionError
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Port Pair Allocated From Quota Partition Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.259

Field Name : mgcpAlgPortPairAllocFromQuotaPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Port Pair Allocated From Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.258

Field Name : mgcpAlgPortPairAllocFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Port Pair Allocated From Quota Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.257

Field Name : mgcpAlgPortPairAllocFromPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Port Pair Allocated From Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.256

Field Name : mgcpAlgPortPairAllocFromPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Port Pair Allocated From Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.255

Field Name : mgcpAlgPortPairAllocFromConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Port Pair Allocated From Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.254

Field Name : mgcpAlgCreateRtcpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current

Description : MGCP ALG Create RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.253

Field Name : mgcpAlgCreateRtpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Create RTP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.252

Field Name : mgcpAlgCreateSingleFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Create Single RTP or RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.251

Field Name : mgcpAlgAllocSinglePortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Alloc Single RTP or RTCP NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.250

Field Name : mgcpAlgAllocRtpRtcpPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Alloc RTP/RTCP NAT Ports Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.249

Field Name : mgcpAlgReuseRtpRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Reuse RTP/RTCP Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.248

Field Name : mgcpAlgRtcpFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG RTCP Full-cone NAT Port Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.247

Field Name : mgcpAlgSingleRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Single RTCP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.246

Field Name : mgcpAlgSingleRtpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Single RTP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.245

Field Name : mgcpAlgReleasePortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Release NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.244

Field Name : mgcpAlgCreateFullconeFailure

Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Create Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.243

Field Name : mgcpAlgAllocPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Alloc NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.242

Field Name : mgcpAlgFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Full-cone Session Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.241

Field Name : mgcpAlgReuseFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Reuse Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.240

Field Name : mgcpAlgNoNatIp
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Unknown NAT IP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.239

Field Name : mgcpAlgQuotaIncFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.238

Field Name : mgcpAlgNoQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG User-Quota Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.237

Field Name : natPoolAddFreeBatchFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Add Batch to Quota Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.236

Field Name : natPoolAttemptAddingMultipleFreeBatches
Field Type : CounterBasedGauge64
Field Status : current
Description : Attempt Adding Multiple Free Batches to Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.235

Field Name : fragListBadL4Len
Field Type : CounterBasedGauge64
Field Status : current
Description : Frag List Bad L4 Len
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.234

Field Name : jumboListBadL4Len
Field Type : CounterBasedGauge64
Field Status : current
Description : Jumbo List Bad L4 Len
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.233

Field Name : l4ChecksumBadDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 Checksum Bad Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.232

Field Name : l4ChecksumFixed
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 Checksum Fixed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.231

Field Name : l4ChecksumVerified
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 Checksum Verified
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.230

Field Name : ipFragChecksumFixed
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Frag Checksum Fixed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.229

Field Name : ipChecksumBadDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Checksum Bad Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.228

Field Name : ipChecksumFixed
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Checksum Fixed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.227

Field Name : ipChecksumVerified
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Checksum Verified
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.226

Field Name : badIpTotLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad IPv4 Total Length
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.225

Field Name : fullconeInboundNatPoolMismatch
Field Type : CounterBasedGauge64
Field Status : current

Description : Full-cone Session NAT Pool Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.224

Field Name : standbyClassListDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Standby Class-List Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.223

Field Name : natPoolNotFoundOnFree
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT Pool Not Found on Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.222

Field Name : quotaExtTooMany
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Ext Too Many
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.221

Field Name : natPoolForceDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT Pool Force Delete
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.220

Field Name : haPortOverloadingForNewUserSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for New User Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.219

Field Name : haPortOverloadingForNewUser
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for New User
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.218

Field Name : haPortOverloadingForQuotaExceededRaceSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for Quota Exceeded Race Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.217

Field Name : haPortOverloadingForQuotaExceededRace
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for Quota Exceeded Race
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.216

Field Name : haPortOverloadingForQuotaExceededSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for Quota Exceeded Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.215

Field Name : haPortOverloadingForQuotaExceeded

Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.214

Field Name : haPortOverloadingForNoPortsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for No Ports Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.213

Field Name : haPortOverloadingForNoPorts
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for No Ports
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.212

Field Name : haPortOverloadingAttemptFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading Attempt Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.211

Field Name : portOverloadingForNewUserSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for New User Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.210

Field Name : portOverloadingForNewUser
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for New User
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.209

Field Name : portOverloadingForQuotaExceededRaceSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for Quota Exceeded Race Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.208

Field Name : portOverloadingForQuotaExceededRace
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for Quota Exceeded Race
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.207

Field Name : portOverloadingForQuotaExceededSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for Quota Exceeded Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.206

Field Name : portOverloadingForQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.205

Field Name : portOverloadingForNoPortsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for No Ports Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.204

Field Name : portOverloadingForNoPorts
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for No Ports
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.203

Field Name : portOverloadingSmpFreePortFromQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Free Port From Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.202

Field Name : portOverloadingSmpFreePort
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Free Port
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.201

Field Name : portOverloadingSmpFreeNoQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Free No Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.200

Field Name : portOverloadingSmpFreeDecFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Free Dec Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.199

Field Name : portOverloadingSmpPutInDelQFromConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Free From Conn
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.198

Field Name : portOverloadingSmpFreeUdpShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Port Overloading SMP UDP Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.197

Field Name : portOverloadingSmpFreeTcpShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Port Overloading SMP TCP Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.196

Field Name : portOverloadingSmpInsertedUdpShadow
Field Type : CounterBasedGauge64
Field Status : current

Description : Total Port Overloading SMP UDP Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.195

Field Name : portOverloadingSmpInsertedTcpShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Port Overloading SMP TCP Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.194

Field Name : portOverloadingSmpInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.193

Field Name : portOverloadingSmpMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.192

Field Name : portOverloadingSmpMemAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Session Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.191

Field Name : portOverloadingConnFreeNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Conn Free Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.190

Field Name : portOverloadingConnFreeRetryLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Conn Free Retry Lookup
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.189

Field Name : portOverloadingAttemptFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Attempt Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.188

Field Name : portOverloadingAttemptDiffPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading on Different Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.187

Field Name : portOverloadingAttemptSamePartition
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading on Same Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.186

Field Name : portOverloadingAttemptConsecutivePorts

Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading on Consecutive Ports
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.185

Field Name : portOverloadingIncOverflow
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Inc Overflow
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.184

Field Name : portOverloadingFreePortBatchOnConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Free Port Batch on Conflict
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.183

Field Name : portOverloadingFreePortOnConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Free Port on Conflict
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.182

Field Name : portOverloadingDecOnFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Port Decrement on Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.181

Field Name : portOverloadingDecOnConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Port Decrement on Conflict
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.180

Field Name : portOverloadingInc
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Port Increment
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.179

Field Name : portOverloadingAssignUserPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Port Assign User Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.178

Field Name : portOverloadingAssignUser
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Port Assign User
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.177

Field Name : portOverloadingOutOfMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Out of Memory
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.176

Field Name : portOverloadingDestinationConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Destination Conflict
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.175

Field Name : portBatchContainerAllocRaceFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Container Race Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.174

Field Name : portBatchContainerAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Container Alloc Out of Memory
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.173

Field Name : specificPortAllocatedFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Specific Port Allocated from Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.172

Field Name : specificPortAllocatedFromQuotaPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : Specific Port Allocated from Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.171

Field Name : specificPortAllocatedFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : Specific Port Allocated from Quota Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.170

Field Name : portBatchFreedFromQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Freed From Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.169

Field Name : portBatchAllocatedToQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Allocated to Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.168

Field Name : portFreedFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.167

Field Name : portFreedFromQuotaPartition
Field Type : CounterBasedGauge64
Field Status : current

Description : Port Freed from Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.166

Field Name : portFreedFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Quota Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.165

Field Name : portAllocatedFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Allocated from Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.164

Field Name : portAllocatedFromQuotaPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Allocated from Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.163

Field Name : portAllocatedFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Allocated from Quota Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.162

Field Name : poolPortBatchPortFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.161

Field Name : partitionPortFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.160

Field Name : consecutivePortFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Consecutive Pool
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.159

Field Name : badPortToFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Freeing Bad Port
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.158

Field Name : haRcvPortNotInPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Not in Port Batch on Sync Rcv
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.157

Field Name : haSendPortBatchNotFound

Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Batch Not Found on Sync Send
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.156

Field Name : haSyncPortBatchRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Batch Extension Sync Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.155

Field Name : haSyncPortBatchSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Batch Extension Sync Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.154

Field Name : quotaExtensionRemoveNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Extension Not Found on Remove
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.153

Field Name : quotaExtensionRemoved
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Extension Removed from Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.152

Field Name : quotaExtensionAdded
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Extension Added to Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.151

Field Name : radiusQueryQuotaExtAllocRaceFree
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Query Container Alloc Race Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.150

Field Name : radiusQueryQuotaExtAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Query Container Alloc (No Memoty)
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.149

Field Name : portBatchFreeWrongPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Free Wrong Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.148

Field Name : portBatchFreePortNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Port Not Found on Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.147

Field Name : portBatchFreeQuotaNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Quota Not Found on Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.146

Field Name : portBatchQuotaExtensionAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Extension Alloc Failure (No memory)
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.145

Field Name : h323AlgPortPairAllocFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.144

Field Name : h323AlgPortPairAllocFromQuotaPartitionError
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Quota Partition Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.143

Field Name : h323AlgPortPairAllocFromQuotaPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.142

Field Name : h323AlgPortPairAllocFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Quota Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.141

Field Name : h323AlgPortPairAllocFromPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.140

Field Name : h323AlgPortPairAllocFromPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.139

Field Name : h323AlgPortPairAllocFromConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.138

Field Name : h323AlgCreateRtcpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current

Description : H323 ALG Create RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.137

Field Name : h323AlgCreateRtpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Create RTP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.136

Field Name : h323AlgCreateSingleFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Create Single RTP or RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.135

Field Name : h323AlgAllocSinglePortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Alloc Single RTP or RTCP NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.134

Field Name : h323AlgAllocRtpRtcpPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Alloc RTP/RTCP NAT Ports Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.133

Field Name : h323AlgReuseRtpRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Reuse RTP/RTCP Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.132

Field Name : h323AlgRtcpFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG RTCP Full-cone NAT Port Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.131

Field Name : h323AlgSingleRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Single RTCP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.130

Field Name : h323AlgSingleRtpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Single RTP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.129

Field Name : h323AlgReleasePortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Release NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.128

Field Name : h323AlgCreateFullconeFailure

Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Create Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.127

Field Name : h323AlgAllocPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Alloc NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.126

Field Name : h323AlgFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Full-cone Session Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.125

Field Name : h323AlgReuseFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Reuse Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.124

Field Name : h323AlgNoNatIp
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Unknown NAT IP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.123

Field Name : h323AlgQuotaIncFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.122

Field Name : h323AlgNoQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG User-Quota Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.121

Field Name : sipAlgPortPairAllocFromQuotaPoolPortBatchWithFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Quota Port Batch Version 2 with Frag Free Ports
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.120

Field Name : sipAlgPortPairAllocFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.119

Field Name : sipAlgPortPairAllocFromQuotaPartitionError
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Quota Partition Error

OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.118

Field Name : sipAlgPortPairAllocFromQuotaPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.117

Field Name : sipAlgPortPairAllocFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Quota Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.116

Field Name : sipAlgPortPairAllocFromPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.115

Field Name : sipAlgPortPairAllocFromPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.114

Field Name : sipAlgPortPairAllocFromConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.113

Field Name : sipAlgCreateRtcpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Create RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.112

Field Name : sipAlgCreateRtpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Create RTP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.111

Field Name : sipAlgCreateSingleFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Create Single RTP or RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.110

Field Name : sipAlgAllocSinglePortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Alloc Single RTP or RTCP NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.109

Field Name : sipAlgAllocRtpRtcpPortFailure
Field Type : CounterBasedGauge64

Field Status : current
Description : SIP ALG Alloc RTP/RTCP NAT Ports Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.108

Field Name : sipAlgReuseRtpRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Reuse RTP/RTCP Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.107

Field Name : sipAlgRtcpFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG RTCP Full-cone NAT Port Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.106

Field Name : sipAlgSingleRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Single RTCP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.105

Field Name : sipAlgSingleRtpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Single RTP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.104

Field Name : sipAlgReleaseContactPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Release Contact NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.103

Field Name : sipAlgCreateContactFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Create Contact Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.102

Field Name : sipAlgAllocContactPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Alloc Contact NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.101

Field Name : sipAlgContactFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Contact Full-cone Session Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.100

Field Name : sipAlgReuseContactFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Reuse Contact Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.99

Field Name : sipAlgNoNatIp
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Unknown NAT IP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.98

Field Name : sipAlgQuotaIncFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.97

Field Name : sipAlgNoQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG User-Quota Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.96

Field Name : udpAlgAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP ALG Port Allocation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.95

Field Name : udpAlgNoNatIp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP ALG User-Quota Unknown NAT IP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.94

Field Name : udpAlgEimMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP ALG Endpoint-Independent Mapping Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.93

Field Name : udpAlgNoQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP ALG User-Quota Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.92

Field Name : totalIcmpFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total ICMP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.91

Field Name : totalIcmpAllocatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total ICMP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.90

Field Name : totalUdpFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Ports Freed

OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.89

Field Name : totalUdpAllocatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.88

Field Name : totalTcpFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.87

Field Name : totalTcpAllocatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.86

Field Name : newUserResourceUnavailableOther
Field Type : CounterBasedGauge64
Field Status : current
Description : Other New User NAT Resource Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.85

Field Name : newUserResourceUnavailableIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP New User NAT Resource Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.84

Field Name : newUserResourceUnavailableUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP New User NAT Resource Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.83

Field Name : newUserResourceUnavailableTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP New User NAT Resource Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.82

Field Name : natPortUnavailable
Field Type : CounterBasedGauge64
Field Status : current
Description : Total NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.81

Field Name : natPortUnavailableOther
Field Type : CounterBasedGauge64
Field Status : current
Description : Other NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.80

Field Name : extendedQuotaMismatched
Field Type : CounterBasedGauge64

Field Status : current
Description : Extended User-Quota Mismatched
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.79

Field Name : dataSessionUserQuotaMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Counter Per User Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.78

Field Name : dataSessionFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Data Sessions Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.77

Field Name : dataSessionCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Data Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.76

Field Name : fullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Full-cone sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.75

Field Name : fullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Full-cone sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.74

Field Name : udpAlgFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP ALG Full-cone sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.73

Field Name : udpAlgFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP ALG Full-cone sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.72

Field Name : udpFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Full-cone sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.71

Field Name : udpFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Full-cone sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.70

Field Name : tcpFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Full-cone sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.69

Field Name : tcpFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Full-cone sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.68

Field Name : userQuotaNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.67

Field Name : icmpOutOfStateUqeDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User Queue Exceeded ICMP notification dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.66

Field Name : icmpOutOfStateUqeHostUnreachableSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User Quota Exceeded ICMP host unreachable sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.65

Field Name : icmpOutOfStateUqeAdminFilteredSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User Quota Exceeded ICMP admin filtered sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.64

Field Name : tcpOutOfStateRstDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Out of State TCP RST dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.63

Field Name : tcpOutOfStateRstSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Out of State TCP RST sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.62

Field Name : totalUserQuotaFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Quota Structure Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.61

Field Name : totalUserQuotaPutInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Quota Structure Freed

OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.60

Field Name : totalUserQuotaCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Quota Structure Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.59

Field Name : prefixQuotaFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Prefix Quota Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.58

Field Name : prefixQuotaPutInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Prefix Quota Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.57

Field Name : prefixQuotaCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Prefix Quota Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.56

Field Name : userQuotaPutInDelQShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User-Quota Put In Del Q
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.55

Field Name : quotaDeleteNotInBucket
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Delete Not In Bucket
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.54

Field Name : quotaMarkedDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Marked Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.53

Field Name : userQuotaCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User-Quota Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.52

Field Name : userQuotaMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Memory Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.51

Field Name : userQuotaMemAllocated
Field Type : CounterBasedGauge64

Field Status : current
Description : User-Quota Memory Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.50

Field Name : classListPermitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Permit Class-List Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.49

Field Name : noClassListMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : No Class-List Match
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.48

Field Name : lidPassThrough
Field Type : CounterBasedGauge64
Field Status : current
Description : LSN LID Pass-through
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.47

Field Name : lidDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : LSN LID Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.46

Field Name : truncatedPacket
Field Type : CounterBasedGauge64
Field Status : current
Description : Truncated Packet
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.45

Field Name : noRadiusProfileMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : No RADIUS Profile Match
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.44

Field Name : haNatPoolBatchTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : HA NAT Pool Batch Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.43

Field Name : cgnv6DsliteGlobalHaNatPoolUnusable
Field Type : CounterBasedGauge64
Field Status : current
Description : HA NAT Pool Unusable
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.42

Field Name : cgnv6DsliteGlobalNatPoolUnusable
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT Pool Unusable
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.41

Field Name : cgnv6DsliteGlobalPortOverloadingSmpFreeUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Overloading Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.40

Field Name : cgnv6DsliteGlobalPortOverloadingSmpFreeTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Overloading Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.39

Field Name : cgnv6DsliteGlobalPortOverloadingSmpInsertedUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Overloading Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.38

Field Name : cgnv6DsliteGlobalPortOverloadingSmpInsertedTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Overloading Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.37

Field Name : cgnv6DsliteGlobalTotalUdpOverloaded
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Overloaded
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.36

Field Name : cgnv6DsliteGlobalTotalTcpOverloaded
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Overloaded
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.35

Field Name : cgnv6DsliteGlobalEifLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Endpoint-Independent Filtering Inbound Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.33

Field Name : cgnv6DsliteGlobalInboundFiltered
Field Type : CounterBasedGauge64
Field Status : current
Description : Endpoint-Dependent Filtering Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.32

Field Name : cgnv6DsliteGlobalEndpointIndepFilterMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Endpoint-Independent Filtering Matched
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.31

Field Name : cgnv6DsliteGlobalEndpointIndepMapMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Endpoint-Independent Mapping Matched

OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.30

Field Name : cgnv6DsliteGlobalFullconeSelfHairpinningDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Self-Hairpinning Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.29

Field Name : cgnv6DsliteGlobalHairpin
Field Type : CounterBasedGauge64
Field Status : current
Description : Hairpin Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.28

Field Name : cgnv6DsliteGlobalFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone Session Creation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.27

Field Name : cgnv6DsliteGlobalUdpFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Full-cone Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.26

Field Name : cgnv6DsliteGlobalUdpFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Full-cone Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.25

Field Name : cgnv6DsliteGlobalTcpFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Full-cone Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.24

Field Name : cgnv6DsliteGlobalTcpFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Full-cone Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.23

Field Name : cgnv6DsliteGlobalDataSesnRateUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Rate User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.22

Field Name : cgnv6DsliteGlobalDataSesnUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.21

Field Name : cgnv6DsliteGlobalExtendedQuotaExceeded
Field Type : CounterBasedGauge64

Field Status : current
Description : Extended User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.20

Field Name : cgnv6DsliteGlobalExtendedQuotaMatched
Field Type : CounterBasedGauge64
Field Status : current
Description : Extended User-Quota Matched
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.19

Field Name : cgnv6DsliteGlobalIcmpUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.18

Field Name : cgnv6DsliteGlobalUdpUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.17

Field Name : cgnv6DsliteGlobalTcpUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.16

Field Name : cgnv6DsliteGlobalNewUserResourceUnavailable
Field Type : CounterBasedGauge64
Field Status : current
Description : New User NAT Resource Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.15

Field Name : cgnv6DsliteGlobalNatPortUnavailableIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.14

Field Name : cgnv6DsliteGlobalNatPortUnavailableUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.13

Field Name : cgnv6DsliteGlobalNatPortUnavailableTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.12

Field Name : cgnv6DsliteGlobalUserQuotaFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Creation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.11

Field Name : cgnv6DsliteGlobalTotalUserQuotaPuInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.10

Field Name : cgnv6DsliteGlobalUserQuotaCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.9

Field Name : cgnv6DsliteGlobalDataSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.8

Field Name : cgnv6DsliteGlobalDataSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.7

Field Name : cgnv6DsliteGlobalTotalIcmpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total ICMP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.6

Field Name : cgnv6DsliteGlobalTotalIcmpAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total ICMP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.5

Field Name : cgnv6DsliteGlobalTotalUdpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.4

Field Name : cgnv6DsliteGlobalTotalUdpAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.3

Field Name : cgnv6DsliteGlobalTotalTcpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.2

Field Name : cgnv6DsliteGlobalTotalTcpAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Ports Allocated

OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.1

Field Name : natIpConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT IP Conflict
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.2.1.1.2

Field Name : sessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.2.1.1.1

Field Name : portOverloadingPortFreeUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Overloading NAT Port Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.311

Field Name : portOverloadingPortFreeTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Overloading NAT Port Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.310

Field Name : portOverloadingPortUdpInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading NAT Port UDP Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.309

Field Name : portOverloadingPortTcpInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading NAT Port TCP Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.308

Field Name : prefixQuotaMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Prefix Quota NAT IP Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.307

Field Name : revEgressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.306

Field Name : revEgressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.305

Field Name : revEgressPktSizeRange2
Field Type : CounterBasedGauge64

Field Status : current
Description : Reverse Egress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.304

Field Name : revEgressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.303

Field Name : revIngressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.302

Field Name : revIngressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.301

Field Name : revIngressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.300

Field Name : revIngressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.299

Field Name : fwdEgressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.298

Field Name : fwdEgressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.297

Field Name : fwdEgressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.296

Field Name : fwdEgressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.295

Field Name : fwdIngressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.294

Field Name : fwdIngressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.293

Field Name : fwdIngressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.292

Field Name : fwdIngressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.291

Field Name : revEgressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.290

Field Name : revIngressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.289

Field Name : fwdEgressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.288

Field Name : fwdIngressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.287

Field Name : revEgressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.286

Field Name : revIngressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packets OTHERS

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.285

Field Name : fwdEgressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.284

Field Name : fwdIngressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.283

Field Name : revEgressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.282

Field Name : revIngressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.281

Field Name : fwdEgressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.280

Field Name : fwdIngressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.279

Field Name : revEgressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.278

Field Name : revIngressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.277

Field Name : fwdEgressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.276

Field Name : fwdIngressPacketsIcmp
Field Type : CounterBasedGauge64

Field Status : current
Description : Forward Ingress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.275

Field Name : revEgressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.274

Field Name : revIngressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.273

Field Name : fwdEgressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.272

Field Name : fwdIngressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.271

Field Name : revEgressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.270

Field Name : revIngressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.269

Field Name : fwdEgressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.268

Field Name : fwdIngressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.267

Field Name : revEgressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.266

Field Name : revIngressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.265

Field Name : fwdEgressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.264

Field Name : fwdIngressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.263

Field Name : revEgressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.262

Field Name : revIngressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.261

Field Name : fwdEgressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.260

Field Name : fwdIngressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.259

Field Name : adcPortAllocationIneligible
Field Type : CounterBasedGauge64
Field Status : current
Description : ADC Port Allocation Not Allowed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.258

Field Name : adcPortAllocationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : ADC Port Allocation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.257

Field Name : natPoolSamePortBatchUdpFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Simultaneous Batch Allocation UDP Port Allocation Failed

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.256

Field Name : userQuotaUnusable
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Marked Unusable
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.255

Field Name : userQuotaUnusableDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Unusable Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.254

Field Name : mgcpAlgPortPairAllocFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Port Pair Allocated From Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.253

Field Name : mgcpAlgPortPairAllocFromQuotaPartitionError
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Port Pair Allocated From Quota Partition Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.252

Field Name : mgcpAlgPortPairAllocFromQuotaPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Port Pair Allocated From Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.251

Field Name : mgcpAlgPortPairAllocFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Port Pair Allocated From Quota Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.250

Field Name : mgcpAlgPortPairAllocFromPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Port Pair Allocated From Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.249

Field Name : mgcpAlgPortPairAllocFromPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Port Pair Allocated From Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.248

Field Name : mgcpAlgPortPairAllocFromConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Port Pair Allocated From Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.247

Field Name : mgcpAlgCreateRtcpFullconeFailure
Field Type : CounterBasedGauge64

Field Status : current
Description : MGCP ALG Create RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.246

Field Name : mgcpAlgCreateRtpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Create RTP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.245

Field Name : mgcpAlgCreateSingleFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Create Single RTP or RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.244

Field Name : mgcpAlgAllocSinglePortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Alloc Single RTP or RTCP NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.243

Field Name : mgcpAlgAllocRtpRtcpPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Alloc RTP/RTCP NAT Ports Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.242

Field Name : mgcpAlgReuseRtpRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Reuse RTP/RTCP Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.241

Field Name : mgcpAlgRtcpFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG RTCP Full-cone NAT Port Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.240

Field Name : mgcpAlgSingleRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Single RTCP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.239

Field Name : mgcpAlgSingleRtpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Single RTP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.238

Field Name : mgcpAlgReleasePortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Release NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.237

Field Name : mgcpAlgCreateFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Create Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.236

Field Name : mgcpAlgAllocPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Alloc NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.235

Field Name : mgcpAlgFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Full-cone Session Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.234

Field Name : mgcpAlgReuseFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Reuse Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.233

Field Name : mgcpAlgNoNatIp
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Unknown NAT IP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.232

Field Name : mgcpAlgQuotaIncFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.231

Field Name : mgcpAlgNoQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG User-Quota Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.230

Field Name : natPoolAddFreeBatchFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Add Batch to Quota Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.229

Field Name : natPoolAttemptAddingMultipleFreeBatches
Field Type : CounterBasedGauge64
Field Status : current
Description : Attempt Adding Multiple Free Batches to Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.228

Field Name : haPrefixNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : HA No Matching Prefix Found

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.227

Field Name : sixRdNoMatchDomainDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Sixrd Packets Domain Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.226

Field Name : fullconeInboundNatPoolMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone Session NAT Pool Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.225

Field Name : dstPrefixMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Destination Prefix Mismatch Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.224

Field Name : standbyClassListDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Standby Class-List Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.223

Field Name : natPoolNotFoundOnFree
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT Pool Not Found on Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.222

Field Name : quotaExtTooMany
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Ext Too Many
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.221

Field Name : natPoolForceDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT Pool Force Delete
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.220

Field Name : haPortOverloadingForNewUserSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for New User Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.219

Field Name : haPortOverloadingForNewUser
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for New User
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.218

Field Name : haPortOverloadingForQuotaExceededRaceSuccess
Field Type : CounterBasedGauge64

Field Status : current
Description : HA Port Overloading for Quota Exceeded Race Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.217

Field Name : haPortOverloadingForQuotaExceededRace
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for Quota Exceeded Race
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.216

Field Name : haPortOverloadingForQuotaExceededSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for Quota Exceeded Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.215

Field Name : haPortOverloadingForQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.214

Field Name : haPortOverloadingForNoPortsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for No Ports Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.213

Field Name : haPortOverloadingForNoPorts
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for No Ports
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.212

Field Name : haPortOverloadingAttemptFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading Attempt Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.211

Field Name : portOverloadingForNewUserSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for New User Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.210

Field Name : portOverloadingForNewUser
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for New User
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.209

Field Name : portOverloadingForQuotaExceededRaceSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for Quota Exceeded Race Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.208

Field Name : portOverloadingForQuotaExceededRace
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for Quota Exceeded Race
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.207

Field Name : portOverloadingForQuotaExceededSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for Quota Exceeded Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.206

Field Name : portOverloadingForQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.205

Field Name : portOverloadingForNoPortsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for No Ports Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.204

Field Name : portOverloadingForNoPorts
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for No Ports
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.203

Field Name : portOverloadingSmpFreePortFromQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Free Port From Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.202

Field Name : portOverloadingSmpFreePort
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Free Port
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.201

Field Name : portOverloadingSmpFreeNoQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Free No Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.200

Field Name : portOverloadingSmpFreeDecFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Free Dec Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.199

Field Name : portOverloadingSmpPutInDelQFromConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Free From Conn

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.198

Field Name : portOverloadingSmpFreeUdpShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Port Overloading SMP UDP Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.197

Field Name : portOverloadingSmpFreeTcpShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Port Overloading SMP TCP Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.196

Field Name : portOverloadingSmpInsertedUdpShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Port Overloading SMP UDP Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.195

Field Name : portOverloadingSmpInsertedTcpShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Port Overloading SMP TCP Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.194

Field Name : portOverloadingSmpInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.193

Field Name : portOverloadingSmpMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.192

Field Name : portOverloadingSmpMemAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Session Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.191

Field Name : portOverloadingConnFreeNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Conn Free Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.190

Field Name : portOverloadingConnFreeRetryLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Conn Free Retry Lookup
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.189

Field Name : portOverloadingAttemptFailed
Field Type : CounterBasedGauge64

Field Status : current
Description : Port Overloading Attempt Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.188

Field Name : portOverloadingAttemptDiffPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading on Different Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.187

Field Name : portOverloadingAttemptSamePartition
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading on Same Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.186

Field Name : portOverloadingAttemptConsecutivePorts
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading on Consecutive Ports
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.185

Field Name : portOverloadingIncOverflow
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Inc Overflow
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.184

Field Name : portOverloadingFreePortBatchOnConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Free Port Batch on Conflict
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.183

Field Name : portOverloadingFreePortOnConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Free Port on Conflict
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.182

Field Name : portOverloadingDecOnFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Port Decrement on Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.181

Field Name : portOverloadingDecOnConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Port Decrement on Conflict
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.180

Field Name : portOverloadingInc
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Port Increment
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.179

Field Name : portOverloadingAssignUserPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Port Assign User Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.178

Field Name : portOverloadingAssignUser
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Port Assign User
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.177

Field Name : portOverloadingOutOfMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Out of Memory
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.176

Field Name : portOverloadingDestinationConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Destination Conflict
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.175

Field Name : portBatchContainerAllocRaceFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Container Race Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.174

Field Name : portBatchContainerAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Container Alloc Out of Memory
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.173

Field Name : specificPortAllocatedFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Specific Port Allocated from Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.172

Field Name : specificPortAllocatedFromQuotaPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : Specific Port Allocated from Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.171

Field Name : specificPortAllocatedFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : Specific Port Allocated from Quota Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.170

Field Name : portBatchFreedFromQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Freed From Quota

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.169

Field Name : portBatchAllocatedToQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Allocated to Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.168

Field Name : portFreedFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.167

Field Name : portFreedFromQuotaPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.166

Field Name : portFreedFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Quota Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.165

Field Name : portAllocatedFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Allocated from Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.164

Field Name : portAllocatedFromQuotaPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Allocated from Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.163

Field Name : portAllocatedFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Allocated from Quota Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.162

Field Name : poolPortBatchPortFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.161

Field Name : partitionPortFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.160

Field Name : consecutivePortFree
Field Type : CounterBasedGauge64

Field Status : current
Description : Port Freed from Consecutive Pool
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.159

Field Name : badPortToFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Freeing Bad Port
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.158

Field Name : haRcvPortNotInPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Not in Port Batch on Sync Rcv
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.157

Field Name : haSendPortBatchNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Batch Not Found on Sync Send
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.156

Field Name : haSyncPortBatchRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Batch Extension Sync Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.155

Field Name : haSyncPortBatchSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Batch Extension Sync Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.154

Field Name : quotaExtensionRemoveNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Extension Not Found on Remove
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.153

Field Name : quotaExtensionRemoved
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Extension Removed from Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.152

Field Name : quotaExtensionAdded
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Extension Added to Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.151

Field Name : radiusQueryQuotaExtAllocRaceFree
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Query Container Alloc Race Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.150

Field Name : radiusQueryQuotaExtAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Query Container Alloc (No Memoty)
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.149

Field Name : portBatchFreeWrongPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Free Wrong Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.148

Field Name : portBatchFreePortNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Port Not Found on Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.147

Field Name : portBatchFreeQuotaNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Quota Not Found on Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.146

Field Name : portBatchQuotaExtensionAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Extension Alloc Failure (No memory)
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.145

Field Name : h323AlgPortPairAllocFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.144

Field Name : h323AlgPortPairAllocFromQuotaPartitionError
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Quota Partition Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.143

Field Name : h323AlgPortPairAllocFromQuotaPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.142

Field Name : h323AlgPortPairAllocFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Quota Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.141

Field Name : h323AlgPortPairAllocFromPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Pool Port Batch

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.140

Field Name : h323AlgPortPairAllocFromPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.139

Field Name : h323AlgPortPairAllocFromConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.138

Field Name : h323AlgCreateRtcpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Create RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.137

Field Name : h323AlgCreateRtpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Create RTP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.136

Field Name : h323AlgCreateSingleFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Create Single RTP or RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.135

Field Name : h323AlgAllocSinglePortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Alloc Single RTP or RTCP NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.134

Field Name : h323AlgAllocRtpRtcpPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Alloc RTP/RTCP NAT Ports Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.133

Field Name : h323AlgReuseRtpRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Reuse RTP/RTCP Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.132

Field Name : h323AlgRtcpFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG RTCP Full-cone NAT Port Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.131

Field Name : h323AlgSingleRtcpFullcone
Field Type : CounterBasedGauge64

Field Status : current
Description : H323 ALG Single RTCP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.130

Field Name : h323AlgSingleRtpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Single RTP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.129

Field Name : h323AlgReleasePortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Release NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.128

Field Name : h323AlgCreateFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Create Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.127

Field Name : h323AlgAllocPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Alloc NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.126

Field Name : h323AlgFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Full-cone Session Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.125

Field Name : h323AlgReuseFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Reuse Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.124

Field Name : h323AlgNoNatIp
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Unknown NAT IP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.123

Field Name : h323AlgQuotaIncFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.122

Field Name : h323AlgNoQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG User-Quota Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.121

Field Name : sipAlgPortPairAllocFromQuotaPoolPortBatchWithFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Quota Port Batch Version 2 with Frag Free Ports
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.120

Field Name : sipAlgPortPairAllocFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.119

Field Name : sipAlgPortPairAllocFromQuotaPartitionError
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Quota Partition Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.118

Field Name : sipAlgPortPairAllocFromQuotaPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.117

Field Name : sipAlgPortPairAllocFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Quota Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.116

Field Name : sipAlgPortPairAllocFromPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.115

Field Name : sipAlgPortPairAllocFromPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.114

Field Name : sipAlgPortPairAllocFromConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.113

Field Name : sipAlgCreateRtcpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Create RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.112

Field Name : sipAlgCreateRtpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current

Description : SIP ALG Create RTP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.111

Field Name : sipAlgCreateSingleFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Create Single RTP or RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.110

Field Name : sipAlgAllocSinglePortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Alloc Single RTP or RTCP NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.109

Field Name : sipAlgAllocRtpRtcpPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Alloc RTP/RTCP NAT Ports Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.108

Field Name : sipAlgReuseRtpRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Reuse RTP/RTCP Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.107

Field Name : sipAlgRtcpFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG RTCP Full-cone NAT Port Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.106

Field Name : sipAlgSingleRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Single RTCP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.105

Field Name : sipAlgSingleRtpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Single RTP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.104

Field Name : sipAlgReleaseContactPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Release Contact NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.103

Field Name : sipAlgCreateContactFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Create Contact Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.102

Field Name : sipAlgAllocContactPortFailure

Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Alloc Contact NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.101

Field Name : sipAlgContactFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Contact Full-cone Session Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.100

Field Name : sipAlgReuseContactFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Reuse Contact Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.99

Field Name : sipAlgNoNatIp
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Unknown NAT IP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.98

Field Name : sipAlgQuotaIncFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.97

Field Name : sipAlgNoQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG User-Quota Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.96

Field Name : udpAlgAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP ALG Port Allocation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.95

Field Name : udpAlgNoNatIp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP ALG User-Quota Unknown NAT IP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.94

Field Name : udpAlgEimMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP ALG Endpoint-Independent Mapping Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.93

Field Name : udpAlgNoQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP ALG User-Quota Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.92

Field Name : totalIcmpFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total ICMP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.91

Field Name : totalIcmpAllocatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total ICMP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.90

Field Name : totalUdpFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.89

Field Name : totalUdpAllocatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.88

Field Name : totalTcpFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.87

Field Name : totalTcpAllocatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.86

Field Name : newUserResourceUnavailableOther
Field Type : CounterBasedGauge64
Field Status : current
Description : Other New User NAT Resource Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.85

Field Name : newUserResourceUnavailableIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP New User NAT Resource Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.84

Field Name : newUserResourceUnavailableUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP New User NAT Resource Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.83

Field Name : newUserResourceUnavailableTcp
Field Type : CounterBasedGauge64
Field Status : current

Description : TCP New User NAT Resource Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.82

Field Name : natPortUnavailable
Field Type : CounterBasedGauge64
Field Status : current
Description : Total NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.81

Field Name : natPortUnavailableOther
Field Type : CounterBasedGauge64
Field Status : current
Description : Other NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.80

Field Name : extendedQuotaMismatched
Field Type : CounterBasedGauge64
Field Status : current
Description : Extended User-Quota Mismatched
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.79

Field Name : dataSessionUserQuotaMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Counter Per User Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.78

Field Name : dataSessionFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Data Sessions Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.77

Field Name : dataSessionCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Data Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.76

Field Name : fullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Full-cone sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.75

Field Name : fullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Full-cone sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.74

Field Name : udpAlgFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP ALG Full-cone sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.73

Field Name : udpAlgFullconeCreated

Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP ALG Full-cone sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.72

Field Name : udpFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Full-cone sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.71

Field Name : udpFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Full-cone sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.70

Field Name : tcpFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Full-cone sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.69

Field Name : tcpFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Full-cone sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.68

Field Name : userQuotaNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.67

Field Name : icmpOutOfStateUqeDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User Queue Exceeded ICMP notification dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.66

Field Name : icmpOutOfStateUqeHostUnreachableSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User Quota Exceeded ICMP host unreachable sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.65

Field Name : icmpOutOfStateUqeAdminFilteredSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User Quota Exceeded ICMP admin filtered sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.64

Field Name : tcpOutOfStateRstDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Out of State TCP RST dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.63

Field Name : tcpOutOfStateRstSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Out of State TCP RST sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.62

Field Name : totalUserQuotaFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Quota Structure Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.61

Field Name : totalUserQuotaPutInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Quota Structure Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.60

Field Name : totalUserQuotaCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Quota Structure Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.59

Field Name : prefixQuotaFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Prefix Quota Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.58

Field Name : prefixQuotaPutInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Prefix Quota Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.57

Field Name : prefixQuotaCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Prefix Quota Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.56

Field Name : userQuotaPutInDelQShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User-Quota Put In Del Q
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.55

Field Name : quotaDeleteNotInBucket
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Delete Not In Bucket
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.54

Field Name : quotaMarkedDeleted
Field Type : CounterBasedGauge64
Field Status : current

Description : User-Quota Marked Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.53

Field Name : userQuotaCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User-Quota Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.52

Field Name : userQuotaMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Memory Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.51

Field Name : userQuotaMemAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Memory Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.50

Field Name : noClassListMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : No Class-List Match
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.49

Field Name : lidPassThrough
Field Type : CounterBasedGauge64
Field Status : current
Description : LSN LID Pass-through
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.48

Field Name : lidDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : LSN LID Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.47

Field Name : sourceMatchesPrefix
Field Type : CounterBasedGauge64
Field Status : current
Description : Source Address Prefix Match Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.46

Field Name : l3
Field Type : CounterBasedGauge64
Field Status : current
Description : Layer 3 Forwarded Packets
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.45

Field Name : noRadiusProfileMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : No RADIUS Profile Match
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.44

Field Name : haNatPoolBatchTypeMismatch

Field Type : CounterBasedGauge64
Field Status : current
Description : HA NAT Pool Batch Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.43

Field Name : haNatPoolUnusable
Field Type : CounterBasedGauge64
Field Status : current
Description : HA NAT Pool Unusable
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.42

Field Name : natPoolUnusable
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT Pool Unusable
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.41

Field Name : portOverloadingSmpFreeUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Overloading Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.40

Field Name : portOverloadingSmpFreeTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Overloading Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.39

Field Name : portOverloadingSmpInsertedUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Overloading Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.38

Field Name : portOverloadingSmpInsertedTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Overloading Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.37

Field Name : totalUdpOverloaded
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Overloaded
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.36

Field Name : totalTcpOverloaded
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Overloaded
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.35

Field Name : eifLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Endpoint-Independent Filtering Inbound Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.33

Field Name : inboundFiltered
Field Type : CounterBasedGauge64
Field Status : current
Description : Endpoint-Dependent Filtering Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.32

Field Name : endpointIndepFilterMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Endpoint-Independent Filtering Matched
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.31

Field Name : endpointIndepMapMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Endpoint-Independent Mapping Matched
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.30

Field Name : fullconeSelfHairpinningDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Self-Hairpinning Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.29

Field Name : hairpin
Field Type : CounterBasedGauge64
Field Status : current
Description : Hairpin Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.28

Field Name : fullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone Session Creation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.27

Field Name : udpFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Full-cone Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.26

Field Name : udpFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Full-cone Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.25

Field Name : tcpFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Full-cone Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.24

Field Name : tcpFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current

Description : TCP Full-cone Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.23

Field Name : dataSesnRateUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Rate User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.22

Field Name : dataSesnUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.21

Field Name : extendedQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Extended User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.20

Field Name : extendedQuotaMatched
Field Type : CounterBasedGauge64
Field Status : current
Description : Extended User-Quota Matched
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.19

Field Name : icmpUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.18

Field Name : udpUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.17

Field Name : tcpUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.16

Field Name : newUserResourceUnavailable
Field Type : CounterBasedGauge64
Field Status : current
Description : New User NAT Resource Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.15

Field Name : natPortUnavailableIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.14

Field Name : natPortUnavailableUdp

Field Type : CounterBasedGauge64
Field Status : current
Description : UDP NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.13

Field Name : natPortUnavailableTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.12

Field Name : userQuotaFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Creation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.11

Field Name : userQuotaPutInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.10

Field Name : userQuotaCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.9

Field Name : dataSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.8

Field Name : dataSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.7

Field Name : totalIcmpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total ICMP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.6

Field Name : totalIcmpAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total ICMP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.5

Field Name : totalUdpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.4

Field Name : totalUdpAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.3

Field Name : totalTcpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.2

Field Name : totalTcpAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.1

Field Name : tcamCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : TCAM Flow Count
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.20

Field Name : tcamFree
Field Type : CounterBasedGauge64
Field Status : current
Description : TCAM Flows Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.19

Field Name : tcamCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : TCAM Flows Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.18

Field Name : entryInvalidateServerDown
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Invalidate due to server down
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.17

Field Name : entryForceHwInvalidate
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Force HW Invalidate
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.16

Field Name : entryAgeOutInvalidDst
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out - invalid dst
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.15

Field Name : entryAgeOutTcpRst
Field Type : CounterBasedGauge64
Field Status : current

Description : HW Entries Aged Out - TCP RST
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.14

Field Name : entryAgeOutTcpFin
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out - TCP FIN
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.13

Field Name : entryAgeOutIdle
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out - idle timeout
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.12

Field Name : entryAgeOut
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.11

Field Name : entryCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Count
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.10

Field Name : entryFreeNoSwEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Freed - no software entry
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.9

Field Name : entryFreeNoConn
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Freed - no matched conn
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.8

Field Name : entryFreeNoHwProg
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Freed - no HW prog
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.7

Field Name : entryFreeOppEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Freed - opposite tuple entry aged-out
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.6

Field Name : entryFree
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.5

Field Name : entryCreateFailMaxEntry

Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Creation Failed - max entries exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.4

Field Name : entryCreateFailServerDown
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Creation Failed - server down
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.3

Field Name : entryCreateFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Creation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.2

Field Name : entryCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.1

Field Name : haAllocMapConflicts
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Standby Allocate Mapping Conflicts
OID : 1.3.6.1.4.1.22610.2.4.10.115.14.1.1.9

Field Name : haSelectAddrFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Standby Allocate Address Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.14.1.1.8

Field Name : haMapMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Standby Mapping Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.14.1.1.7

Field Name : mapNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Mapping to be Released Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.14.1.1.6

Field Name : allocMapRace
Field Type : CounterBasedGauge64
Field Status : current
Description : Mapping Exists When Allocating Address Mapping
OID : 1.3.6.1.4.1.22610.2.4.10.115.14.1.1.5

Field Name : mapDblFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Address Mapping Double Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.14.1.1.4

Field Name : mapAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : One-to-One Address Mapping Allocation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.14.1.1.3

Field Name : totalMapFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total One-to-One Address Mapping Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.14.1.1.2

Field Name : totalMapAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total One-to-One Address Mapping Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.14.1.1.1

Field Name : cgnv6OneToOnePoolSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.14.2.1.1

Field Name : cgnv6OneToOnePoolSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.14.2.1.1.1

Field Name : freeAddress
Field Type : CounterBasedGauge64
Field Status : current
Description : Free Address
OID : 1.3.6.1.4.1.22610.2.4.10.115.14.2.1.1.1.4

Field Name : usedAddress
Field Type : CounterBasedGauge64
Field Status : current
Description : Used Address
OID : 1.3.6.1.4.1.22610.2.4.10.115.14.2.1.1.1.3

Field Name : totalAddress
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Address
OID : 1.3.6.1.4.1.22610.2.4.10.115.14.2.1.1.1.2

Field Name : cgnv6OneToOnePoolName
Field Type : String
Field Status : current
Description : Specify pool name or pool group
OID : 1.3.6.1.4.1.22610.2.4.10.115.14.2.1.1.1.1

Field Name : cgnv6Dns64VServerPortSTable
Field Type : TABLE
Field Status : current

Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1

Field Name : cgnv6Dns64VServerPortSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1

Field Name : cgnv6Dns64VirtualServerPortSlowestRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : Slowest response time
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.29

Field Name : cgnv6Dns64VirtualServerPortFastestRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : Fastest response time
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.28

Field Name : lastRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : Last response time
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.27

Field Name : currConnRate
Field Type : CounterBasedGauge64
Field Status : current
Description : Current connection rate
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.26

Field Name : cgnv6Dns64VirtualServerPortPeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Peak connections
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.25

Field Name : totalReqSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : Total successful requests
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.24

Field Name : cgnv6Dns64VirtualServerPortTotalReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Total requests
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.23

Field Name : cgnv6Dns64VirtualServerPortCurrentReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Current requests
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.22

Field Name : compressionMissTemplateExclusion

Field Type : CounterBasedGauge64
Field Status : current
Description : Compression miss template exclusion
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.21

Field Name : compressionMissNoClient
Field Type : CounterBasedGauge64
Field Status : current
Description : Compression miss no client
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.20

Field Name : compressionMiss
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of requests NOT compressed
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.19

Field Name : compressionHit
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of requests compressed
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.18

Field Name : compressionBytesAfter
Field Type : CounterBasedGauge64
Field Status : current
Description : Data out of compression engine
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.17

Field Name : compressionBytesBefore
Field Type : CounterBasedGauge64
Field Status : current
Description : Data into compression engine
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.16

Field Name : esTotalFailureActions
Field Type : CounterBasedGauge64
Field Status : current
Description : Total failure actions
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.15

Field Name : totalMfDnsPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Total MF DNS packets
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.14

Field Name : totalDnsPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Total DNS packets
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.13

Field Name : cgnv6Dns64VServerPortTotalRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Total reverse packets
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.12

Field Name : cgnv6Dns64VServerPortTotalRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : Total reverse bytes
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.11

Field Name : cgnv6Dns64VServerPortTotalFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Total forward packets
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.10

Field Name : cgnv6VServerPortTotalFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : Total forward bytes
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.9

Field Name : cgnv6Dns64VServerPortTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total connections
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.8

Field Name : toatalTcpConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP connections
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.7

Field Name : cgnv6Dns64VServerPortTotalL7Conn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total L7 connections
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.6

Field Name : cgnv6Dns64VServerPortTotalL4Conn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total L4 connections
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.5

Field Name : cgnv6Dns64VServerPortCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Current connection
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.4

Field Name : cgnv6Dns64VServerProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.3

Field Name : cgnv6Dns64VServerPortNumber
Field Type : INTEGER
Field Status : current

Description : Port
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.2

Field Name : cgnv6Dns64VirtualserverName
Field Type : String
Field Status : current
Description : CGNV6 Virtual Server Name
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.1

Field Name : cgnv6NatPoolSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1

Field Name : cgnv6NatPoolSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1

Field Name : ipTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Total
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.29

Field Name : ipFree
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.28

Field Name : ipUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Used
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.27

Field Name : tcpPortOverloadFree
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Overloading Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.26

Field Name : tcpPortOverloadCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Overloading Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.25

Field Name : tcpPortOverloaded
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Overloaded
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.24

Field Name : tcpHitFull

Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Hit Full
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.23

Field Name : tcpPeak
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Peak
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.22

Field Name : tcpRsvd
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Reserved
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.21

Field Name : tcpTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP total
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.20

Field Name : tcpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.19

Field Name : tcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.18

Field Name : udpPortOverloadFree
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Overloading Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.17

Field Name : udpPortOverloadCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Overloading Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.16

Field Name : udpPortOverloaded
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Overloaded
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.15

Field Name : udpHitFull
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Hit Full
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.14

Field Name : udpPeak
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Peak
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.13

Field Name : udpRsvd
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Reserved
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.12

Field Name : udpTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Total
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.11

Field Name : udpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.10

Field Name : udp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.9

Field Name : icmpHitFull
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Hit Full
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.8

Field Name : icmpPeak
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Peak
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.7

Field Name : icmpRsvd
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Reserved
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.6

Field Name : icmpTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Total
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.5

Field Name : icmpFreed
Field Type : CounterBasedGauge64
Field Status : current

Description : ICMP Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.4

Field Name : icmp
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.3

Field Name : users
Field Type : CounterBasedGauge64
Field Status : current
Description : Users
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.2

Field Name : cgnv6NatPoolPoolName
Field Type : String
Field Status : current
Description : Specify pool name
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.1

Field Name : radiusInterCardDupRedir
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS packet dropped as redirected by other blade (SO)
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.44

Field Name : radiusPacketsDroppedNotLo
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS packets dropped dest not loopback (SO)
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.43

Field Name : radiusPacketsProcessLocal
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS packets processed locally without redirection (SO)
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.42

Field Name : radiusPacketsRedirectFailDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS packets dropped due to redirect failure (SO)
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.41

Field Name : radiusPacketsRedirected
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS packets redirected (SO)
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.40

Field Name : interCardMsgFailDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Inter-Card Message Fail Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.39

Field Name : haSyncNoKeyVapDropped

Field Type : CounterBasedGauge64
Field Status : current
Description : HA Record Sync No key dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.38

Field Name : ipAddRaceDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Radius Entry IP Add Race Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.37

Field Name : ipMismatchDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : Radius Entry IP Mismatch Delete
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.36

Field Name : acctOnDupRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Duplicate RADIUS Acct On Request
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.35

Field Name : acctOnFiltersFull
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Acct On Request Ignored(Filters Full)
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.34

Field Name : haSyncDeleteRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Record Sync Delete Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.33

Field Name : haSyncCreateRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Record Sync Create Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.32

Field Name : haSyncDeleteSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Record Sync Delete Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.31

Field Name : haSyncCreateSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Record Sync Create Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.30

Field Name : memFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Memory Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.29

Field Name : memAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Memory Allocation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.28

Field Name : memAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Memory Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.27

Field Name : smpInRml
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS SMP in RML
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.26

Field Name : smpMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS SMP Memory Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.25

Field Name : smpMemAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS SMP Memory Allocation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.24

Field Name : smpMemAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS SMP Memory Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.23

Field Name : smpDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS SMP Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.17

Field Name : smpCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS SMP Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.16

Field Name : invalidKey
Field Type : CounterBasedGauge64
Field Status : current
Description : Radius Request has Invalid Key Field
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.15

Field Name : ipv6PrefixLengthMismatch
Field Type : CounterBasedGauge64
Field Status : current

Description : Framed IPV6 Prefix Length Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.14

Field Name : haStandbyDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Standby Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.13

Field Name : secretNotConfiguredDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Secret Not Configured Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.12

Field Name : radiusTableFull
Field Type : TABLE
Field Status : current
Description : RADIUS Request Dropped (Table Full)
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.11

Field Name : requestIgnored
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request Ignored
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.10

Field Name : requestMalformedDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request Malformed Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.9

Field Name : requestNoKeyVapDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request No Key Attribute Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.8

Field Name : requestBadSecretDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request Bad Secret Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.7

Field Name : radiusRequestDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request Dropped (Malformed Packet)
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.6

Field Name : radiusRequestReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.5

Field Name : customReceived

Field Type : CounterBasedGauge64
Field Status : current
Description : Custom attribute Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.4

Field Name : imsiReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : IMSI Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.3

Field Name : imeiReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : IMEI Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.2

Field Name : msisdnReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : MSISDN Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.1

Field Name : h245DynamicAddrExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 H245 Dynamic Address Exceed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.8.1.11

Field Name : tcpOutOfOrderDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Out-of-Order Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.8.1.10

Field Name : rewriteFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 Message Rewrite Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.8.1.9

Field Name : connExtCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 Packet Rewrite Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.8.1.8

Field Name : messageCrossMultiPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 Message Cross Multiple Packets
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.8.1.7

Field Name : parseError
Field Type : CounterBasedGauge64
Field Status : current
Description : Message Parse Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.8.1.6

Field Name : fastStart
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 FastStart
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.8.1.5

Field Name : h245Tunneled
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 H245 Tunnelled Message
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.8.1.4

Field Name : h245ctlMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 H245 Media Control Message
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.8.1.3

Field Name : h225csMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 H225 Call Signaling Message
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.8.1.2

Field Name : h225rasMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 H225 RAS Message
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.8.1.1

Field Name : tcpOutOfOrderDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Out-of-Order Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.19

Field Name : rewriteFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP Message Rewrite Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.18

Field Name : modifyFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP Message Modify Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.17

Field Name : sdpAllocPortMapFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP Alloc SDP Port Map Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.16

Field Name : sdpAllocPortMapSuccess
Field Type : CounterBasedGauge64
Field Status : current

Description : MGCP Alloc SDP Port Map Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.15

Field Name : sdpOpFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP Operate SDP Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.14

Field Name : sdpProcessCandidateFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP Operate SDP Media Candidate Attribute Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.13

Field Name : thirdPartySdp
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP Third-Party SDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.12

Field Name : connExtCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP Create Connection Extension Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.11

Field Name : parseError
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP Message Parse Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.10

Field Name : rsip
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP RSIP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.9

Field Name : rqnt
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP RQNT
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.8

Field Name : ntfy
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP NTFY
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.7

Field Name : mdcx
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP MDCX
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.6

Field Name : epcf

Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP EPCF
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.5

Field Name : dlcx
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP DLCX
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.4

Field Name : crcx
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP CRCX
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.3

Field Name : aucx
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP AUCX
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.2

Field Name : auep
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP AUEP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.1

Field Name : helperFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.43

Field Name : helperFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Conn Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.42

Field Name : helperDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Conn Already Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.41

Field Name : helperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Conn Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.40

Field Name : helperFound
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Conn Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.39

Field Name : smpConnAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Conn Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.38

Field Name : tcpOutOfOrderDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Out-of-Order Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.37

Field Name : rewriteFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Message Rewrite Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.36

Field Name : modifyFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Message Modify Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.35

Field Name : sdpAllocPortMapFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Alloc SDP Port Map Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.34

Field Name : sdpAllocPortMapSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Alloc SDP Port Map Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.33

Field Name : sdpOpFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate SDP Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.32

Field Name : sdpProcessCandidateFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate SDP Media Candidate Attribute Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.31

Field Name : thirdPartySdp
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Third-Party SDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.30

Field Name : insideContactPortMismatch
Field Type : CounterBasedGauge64
Field Status : current

Description : SIP Inside Contact Port Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.29

Field Name : outsideContactPortMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Outside Contact Port Mismatch NAT Port
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.28

Field Name : allocContactPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Alloc Contact Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.27

Field Name : connExtCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Create Connection Extension Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.26

Field Name : thirdPartyRegistration
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Third-Party Registration
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.25

Field Name : contentLengthHdrOpFailrue
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate Content-Length Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.24

Field Name : recordRouteHdrOpFailrue
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate Record-Route Header Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.23

Field Name : routeHdrOpFailrue
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate Route Header Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.22

Field Name : toHdrOpFailrue
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate To Header Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.21

Field Name : fromHdrOpFailrue
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate From Header Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.20

Field Name : contactHdrOpFailrue

Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate Contact Header Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.19

Field Name : viaHdrOpFailrue
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate Via Header Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.18

Field Name : reqUriOpFailrue
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate Request Uri Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.17

Field Name : parseError
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Message Parse Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.16

Field Name : lsnAlgSipMethodUnkown
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method UNKNOWN
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.15

Field Name : lsnAlgSipMethodUpdate
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method UPDATE
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.14

Field Name : lsnAlgSipMethodMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method MESSAGE
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.13

Field Name : lsnAlgSipMethodRefer
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method REFER
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.12

Field Name : lsnAlgSipMethodInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method INFO
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.11

Field Name : lsnAlgSipMethodPublish
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method PUBLISH
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.10

Field Name : lsnAlgSipMethodNotify
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method NOTIFY
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.9

Field Name : lsnAlgSipMethodSubscribe
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method SUBSCRIBE
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.8

Field Name : lsnAlgSipMethodPrack
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method PRACK
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.7

Field Name : lsnAlgSipMethodOption
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method OPTIONS
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.6

Field Name : lsnAlgSipMethodBye
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method BYE
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.5

Field Name : lsnAlgSipMethodCancel
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method CANCEL
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.4

Field Name : lsnAlgSipMethodAck
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method ACK
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.3

Field Name : lsnAlgSipMethodInvite
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method INVITE
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.2

Field Name : lsnAlgSipMethodRegister
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method REGISTER
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.1

Field Name : smpAppTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current

Description : SMP ALG App Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.43

Field Name : haStreamSmpAcquireFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : HA SMP Session Acquire Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.42

Field Name : haStreamSmpReused
Field Type : CounterBasedGauge64
Field Status : current
Description : HA SMP Session Reused
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.41

Field Name : haExtensionFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Conn Extension Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.40

Field Name : haDataExists
Field Type : CounterBasedGauge64
Field Status : current
Description : HA New Data Session Already Exists
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.39

Field Name : haControlClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : HA New Data Control Session Closed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.38

Field Name : haDataNoSmp
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Data Session SMP Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.37

Field Name : haDataSessionRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Data Session Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.36

Field Name : haDataSessionSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Data Session Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.35

Field Name : haPortAllocationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Stream Port Allocation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.34

Field Name : haStreamExists

Field Type : CounterBasedGauge64
Field Status : current
Description : HA Stream Already Exists
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.33

Field Name : haStreamIncompatible
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Incompatible Streams Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.32

Field Name : haStreamsRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Streams Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.31

Field Name : haStreamsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Streams Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.30

Field Name : dataFreeSmpNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Free SMP Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.29

Field Name : dataFreeSmpRetryLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Free SMP Retry Lookup
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.28

Field Name : crossCpuRcvFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Receive Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.27

Field Name : crossCpuCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Creation
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.26

Field Name : crossCpuNoSession
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU No Session Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.25

Field Name : crossCpuRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.24

Field Name : crossCpuSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.23

Field Name : rtcpReversed
Field Type : CounterBasedGauge64
Field Status : current
Description : RTCP Reverse Creation
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.22

Field Name : rtpReversed
Field Type : CounterBasedGauge64
Field Status : current
Description : RTP Reverse Creation
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.21

Field Name : dataSessionCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : New Data Session Creation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.20

Field Name : dataSessionExists
Field Type : CounterBasedGauge64
Field Status : current
Description : New Session Already Exists
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.19

Field Name : controlClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : New Session Closed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.18

Field Name : smpDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : New Session SMP Already Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.17

Field Name : natPoolStandby
Field Type : CounterBasedGauge64
Field Status : current
Description : New Session NAT Pool Standby
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.16

Field Name : smpReused
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Session Reused
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.15

Field Name : smpRemoved
Field Type : CounterBasedGauge64
Field Status : current

Description : SMP Session Removed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.14

Field Name : smpInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Session Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.13

Field Name : haRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : HA RCV
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.12

Field Name : haSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.11

Field Name : cgnv6LsnAlgRtspNoSessionMem
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Creation Failures
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.10

Field Name : cgnv6LsnAlgRtspDataSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.9

Field Name : cgnv6LsnAlgRtspDataSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.8

Field Name : cgnv6LsnAlgRtspUnknownClientPortFromServer
Field Type : CounterBasedGauge64
Field Status : current
Description : Server Replies With Unknown Client Ports
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.7

Field Name : cgnv6LsnAlgRtspPortAllocationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream Client Port Allocation Failures
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.6

Field Name : cgnv6LsnAlgRtspPortsFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream Client Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.5

Field Name : cgnv6LsnAlgRtspPortsAllocated

Field Type : CounterBasedGauge64
Field Status : current
Description : Stream Client Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.4

Field Name : cgnv6LsnAlgRtspStreamsCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream Creation Failures
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.3

Field Name : cgnv6LsnAlgRtspStreamsFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Streams Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.2

Field Name : cgnv6LsnAlgRtspStreamsCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Streams Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.1

Field Name : controlFreeSmpAppTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Control Free SMP App Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.48

Field Name : controlFreeNoSmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Control Free No SMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.47

Field Name : controlFreeNoExt
Field Type : CounterBasedGauge64
Field Status : current
Description : Control Free No Ext
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.46

Field Name : controlFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Control Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.45

Field Name : greFreeSmpAppTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Free SMP App Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.44

Field Name : greFreeNoSmp
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Free No SMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.43

Field Name : greFreeNoExt
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Free No Ext
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.42

Field Name : greConnAlreadyExists
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Conn Already Exists
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.41

Field Name : greNoControlConn
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE No Control Conn
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.40

Field Name : greNoRevRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE No Rev Route
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.39

Field Name : greNoFwdRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE No Fwd Route
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.38

Field Name : greConnExtCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Conn Ext Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.37

Field Name : greConnCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Conn Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.36

Field Name : smpAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Session Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.35

Field Name : smpClientCallIdMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Client Call ID Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.34

Field Name : callReplyExtAllocFailure
Field Type : CounterBasedGauge64
Field Status : current

Description : Call Request Ext Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.33

Field Name : callReplyRetransmitAcquired
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Reply Retransmit Acquired
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.32

Field Name : callReplyRetransmitWrongControl
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Reply Retransmit Wrong Control
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.31

Field Name : callReplyRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Reply Retransmit
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.30

Field Name : callReplyCallIdUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Reply Unknown Client Call ID
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.29

Field Name : callReqExtAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Request Ext Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.28

Field Name : callReqNew
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Request New
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.27

Field Name : callReqRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Request Retransmit
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.26

Field Name : callReplyPnsCallIdMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Call ID Mismatch on Call Reply
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.25

Field Name : callReqPnsCallIdMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Call ID Mismatch on Call Request
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.24

Field Name : quotaDecNotFound

Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Not Found on Decrement
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.23

Field Name : quotaIncNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Not Found on Increment
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.22

Field Name : quotaDec
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Decremented
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.21

Field Name : quotaInc
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Incremented
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.20

Field Name : smpAppTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP ALG App Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.19

Field Name : haSmpInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : HA SMP Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.18

Field Name : haSmpConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : HA SMP Conflicts
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.17

Field Name : haCallRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Call Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.16

Field Name : haCallSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Call Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.15

Field Name : haOverwrite
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Call ID Overwrites
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.14

Field Name : haConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Call ID Conflicts
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.13

Field Name : haNoMem
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Memory Allocation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.12

Field Name : haRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Info Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.11

Field Name : haSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Info Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.10

Field Name : extensionCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Extension Creation Failures
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.9

Field Name : smpSessionCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Session Creation Failures
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.8

Field Name : smpSessionsFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Sessions Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.7

Field Name : smpSessionsCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.6

Field Name : cgnv6LsnAlgPtptNoGreSessionMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : No Matching GRE Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.5

Field Name : cgnv6LsnAlgPtptGreSessionsFreed
Field Type : CounterBasedGauge64
Field Status : current

Description : GRE Sessions Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.4

Field Name : cgnv6LsnAlgPtptGreSessionsCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.3

Field Name : cgnv6LsnAlgPptpMismatchedPnsCallId
Field Type : CounterBasedGauge64
Field Status : current
Description : Mismatched PNS Call ID
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.2

Field Name : cgnv6LsnAlgPptpCallsEstablished
Field Type : CounterBasedGauge64
Field Status : current
Description : Calls Established
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.1

Field Name : smpAppTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP ALG App Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.18

Field Name : getConnExtFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Get Conn Extension Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.17

Field Name : pasvHelperCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Passive Helper Creation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.16

Field Name : portHelperCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Helper Creation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.15

Field Name : pasvHelperUnused
Field Type : CounterBasedGauge64
Field Status : current
Description : Passive Mode Helper Unused
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.14

Field Name : portHelperUnused
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Mode Helper Unused
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.13

Field Name : pasvHelperFreed

Field Type : CounterBasedGauge64
Field Status : current
Description : Passive Mode Helper Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.12

Field Name : portHelperFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Mode Helper Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.11

Field Name : pasvHelperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Passive Mode Helper Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.10

Field Name : portHelperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Mode Helper Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.9

Field Name : pasvRetransmits
Field Type : CounterBasedGauge64
Field Status : current
Description : Passive Mode Reply Retransmits
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.8

Field Name : portRetransmits
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Mode Request Retransmits
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.7

Field Name : lpsvReplies
Field Type : CounterBasedGauge64
Field Status : current
Description : LPSV Replies From Server
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.6

Field Name : epsvReplies
Field Type : CounterBasedGauge64
Field Status : current
Description : EPSV Replies From Server
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.5

Field Name : pasvReplies
Field Type : CounterBasedGauge64
Field Status : current
Description : PASV Replies From Server
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.4

Field Name : lprtRequests
Field Type : CounterBasedGauge64
Field Status : current
Description : LPRT Requests From Client
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.3

Field Name : eprtRequests
Field Type : CounterBasedGauge64
Field Status : current
Description : EPRT Requests From Client
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.2

Field Name : portRequests
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT Requests From Client
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.1

Field Name : natIpConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT IP Conflict
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.1.1.3

Field Name : placeholderDebug
Field Type : CounterBasedGauge64
Field Status : current
Description : Placeholder Debug
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.1.1.2

Field Name : cgnv6LsnAlgEspSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.1.1.1

Field Name : helperInRml
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Session in Remove List
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.9.1.7

Field Name : helperAlreadyUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Session already used
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.9.1.6

Field Name : helperFreedUnused
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Sessions freed unused
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.9.1.5

Field Name : helperFreedUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Sessions freed used
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.9.1.4

Field Name : helperFreed
Field Type : CounterBasedGauge64
Field Status : current

Description : TFTP Helper Sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.9.1.3

Field Name : helperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.9.1.2

Field Name : cgnv6LsnAlgTftpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Client Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.9.1.1

Field Name : chassisIncorrectPu
Field Type : CounterBasedGauge64
Field Status : current
Description : chassis incorrect pu
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.388

Field Name : cgnv6lsnGlobalPortOverloadingPortFreeUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Overloading NAT Port Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.387

Field Name : cgnv6lsnGlobalPortOverloadingPortFreeTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Overloading NAT Port Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.386

Field Name : cgnv6lsnGlobalPortOverloadingPortInsertedUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading NAT Port UDP Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.385

Field Name : cgnv6lsnGlobalPortOverloadingPortInsertedTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading NAT Port TCP Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.384

Field Name : revEgressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.383

Field Name : revEgressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.382

Field Name : revEgressPktSizeRange2

Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.381

Field Name : revEgressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.380

Field Name : revIngressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.379

Field Name : revIngressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.378

Field Name : revIngressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.377

Field Name : revIngressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.376

Field Name : fwdEgressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.375

Field Name : fwdEgressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.374

Field Name : fwdEgressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.373

Field Name : fwdEgressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.372

Field Name : fwdIngressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.371

Field Name : fwdIngressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.370

Field Name : fwdIngressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.369

Field Name : fwdIngressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.368

Field Name : revEgressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.367

Field Name : revIngressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.366

Field Name : fwdEgressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.365

Field Name : fwdIngressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.364

Field Name : revEgressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.363

Field Name : revIngressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current

Description : Reverse Ingress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.362

Field Name : fwdEgressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.361

Field Name : fwdIngressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.360

Field Name : revEgressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.359

Field Name : revIngressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.358

Field Name : fwdEgressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.357

Field Name : fwdIngressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.356

Field Name : revEgressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.355

Field Name : revIngressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.354

Field Name : fwdEgressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.353

Field Name : fwdIngressPacketsIcmp

Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.352

Field Name : revEgressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.351

Field Name : revIngressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.350

Field Name : fwdEgressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.349

Field Name : fwdIngressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.348

Field Name : revEgressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.347

Field Name : revIngressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.346

Field Name : fwdEgressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.345

Field Name : fwdIngressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.344

Field Name : revEgressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.343

Field Name : revIngressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.342

Field Name : fwdEgressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.341

Field Name : fwdIngressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.340

Field Name : revEgressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.339

Field Name : revIngressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.338

Field Name : fwdEgressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.337

Field Name : fwdIngressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.336

Field Name : aclHttpDomainNodeExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : ACL HTTP Domain Node Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.335

Field Name : adcPortAllocationIneligible
Field Type : CounterBasedGauge64
Field Status : current
Description : ADC Port Allocation Not Allowed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.334

Field Name : adcPortAllocationFailed
Field Type : CounterBasedGauge64
Field Status : current

Description : ADC Port Allocation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.333

Field Name : crossCpuHelperFreeNotFoundUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Cross CPU Helper Free Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.332

Field Name : crossCpuHelperFreeNotFoundTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Cross CPU Helper Free Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.331

Field Name : crossCpuHelperFreeNotFoundIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Cross CPU Helper Free Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.330

Field Name : crossCpuHelperFreeNotFoundIp
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Cross CPU Helper Free Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.329

Field Name : crossCpuHelperCreatedIp
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Cross CPU Session Helper Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.328

Field Name : crossCpuHelperCreatedIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Cross CPU Session Helper Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.327

Field Name : crossCpuHelperCreatedTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Cross CPU Session Helper Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.326

Field Name : crossCpuHelperCreatedUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Cross CPU Session Helper Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.325

Field Name : crossCpuHelperCreatedEif
Field Type : CounterBasedGauge64
Field Status : current
Description : EIF Cross CPU Session Helper Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.324

Field Name : crossCpuHelperCreatedEim

Field Type : CounterBasedGauge64
Field Status : current
Description : EIM Cross CPU Session Helper Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.323

Field Name : natPoolSamePortBatchUdpFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Simultaneous Batch Allocation UDP Port Allocation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.322

Field Name : userQuotaUnusable
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Marked Unusable
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.321

Field Name : userQuotaUnusableDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Unusable Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.320

Field Name : mgcpAlgPortPairAllocFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Port Pair Allocated From Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.319

Field Name : mgcpAlgPortPairAllocFromQuotaPartitionError
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Port Pair Allocated From Quota Partition Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.318

Field Name : mgcpAlgPortPairAllocFromQuotaPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Port Pair Allocated From Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.317

Field Name : mgcpAlgPortPairAllocFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Port Pair Allocated From Quota Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.316

Field Name : mgcpAlgPortPairAllocFromPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Port Pair Allocated From Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.315

Field Name : mgcpAlgPortPairAllocFromPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Port Pair Allocated From Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.314

Field Name : mgcpAlgPortPairAllocFromConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Port Pair Allocated From Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.313

Field Name : mgcpAlgCreateRtcpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Create RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.312

Field Name : mgcpAlgCreateRtpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Create RTP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.311

Field Name : mgcpAlgCreateSingleFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Create Single RTP or RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.310

Field Name : mgcpAlgAllocSinglePortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Alloc Single RTP or RTCP NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.309

Field Name : mgcpAlgAllocRtpRtcpPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Alloc RTP/RTCP NAT Ports Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.308

Field Name : mgcpAlgReuseRtpRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Reuse RTP/RTCP Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.307

Field Name : mgcpAlgRtcpFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG RTCP Full-cone NAT Port Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.306

Field Name : mgcpAlgSingleRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Single RTCP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.305

Field Name : mgcpAlgSingleRtpFullcone
Field Type : CounterBasedGauge64
Field Status : current

Description : MGCP ALG Single RTP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.304

Field Name : mgcpAlgReleasePortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Release NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.303

Field Name : mgcpAlgCreateFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Create Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.302

Field Name : mgcpAlgAllocPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Alloc NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.301

Field Name : mgcpAlgFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Full-cone Session Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.300

Field Name : mgcpAlgReuseFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Reuse Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.299

Field Name : mgcpAlgNoNatIp
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Unknown NAT IP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.298

Field Name : mgcpAlgQuotaIncFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.297

Field Name : mgcpAlgNoQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG User-Quota Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.296

Field Name : natPoolAddFreeBatchFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Add Batch to Quota Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.295

Field Name : natPoolAttemptAddingMultipleFreeBatches

Field Type : CounterBasedGauge64
Field Status : current
Description : Attempt Adding Multiple Free Batches to Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.294

Field Name : fullconeExtTooMany
Field Type : CounterBasedGauge64
Field Status : current
Description : LSN Fullcone Extension Too Many
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.293

Field Name : fullconeExtAdded
Field Type : CounterBasedGauge64
Field Status : current
Description : LSN Fullcone Extension Added
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.292

Field Name : fullconeExtMemAllocInitFaulure
Field Type : CounterBasedGauge64
Field Status : current
Description : LSN Fullcone Extension Initialization Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.291

Field Name : fullconeExtMemAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : LSN Fullcone Extension Memory Allocate Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.290

Field Name : fullconeExtMemAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : LSN Fullcone Extension Memory Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.289

Field Name : fullconeExtMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : LSN Fullcone Extension Memory Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.288

Field Name : natPoolNotFoundOnFree
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT Pool Not Found on Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.287

Field Name : quotaExtTooMany
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Ext Too Many
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.286

Field Name : natPoolForceDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT Pool Force Delete
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.285

Field Name : haPortOverloadingForNewUserSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for New User Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.284

Field Name : haPortOverloadingForNewUser
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for New User
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.283

Field Name : haPortOverloadingForQuotaExceededRaceSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for Quota Exceeded Race Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.282

Field Name : haPortOverloadingForQuotaExceededRace
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for Quota Exceeded Race
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.281

Field Name : haPortOverloadingForQuotaExceededSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for Quota Exceeded Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.280

Field Name : haPortOverloadingForQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.279

Field Name : haPortOverloadingForNoPortsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for No Ports Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.278

Field Name : haPortOverloadingForNoPorts
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for No Ports
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.277

Field Name : haPortOverloadingAttemptFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading Attempt Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.276

Field Name : portOverloadingForNewUserSuccess
Field Type : CounterBasedGauge64
Field Status : current

Description : Port Overloading for New User Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.275

Field Name : portOverloadingForNewUser
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for New User
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.274

Field Name : portOverloadingForQuotaExceededRaceSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for Quota Exceeded Race Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.273

Field Name : portOverloadingForQuotaExceededRace
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for Quota Exceeded Race
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.272

Field Name : portOverloadingForQuotaExceededSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for Quota Exceeded Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.271

Field Name : portOverloadingForQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.270

Field Name : portOverloadingForNoPortsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for No Ports Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.269

Field Name : portOverloadingForNoPorts
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for No Ports
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.268

Field Name : portOverloadingSmpFreePortFromQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Free Port From Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.267

Field Name : portOverloadingSmpFreePort
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Free Port
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.266

Field Name : portOverloadingSmpFreeNoQuota

Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Free No Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.265

Field Name : portOverloadingSmpFreeDecFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Free Dec Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.264

Field Name : portOverloadingSmpPutInDelQFromConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Free From Conn
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.263

Field Name : portOverloadingSmpFreeUdpShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Port Overloading SMP UDP Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.262

Field Name : portOverloadingSmpFreeTcpShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Port Overloading SMP TCP Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.261

Field Name : portOverloadingSmpInsertedUdpShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Port Overloading SMP UDP Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.260

Field Name : portOverloadingSmpInsertedTcpShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Port Overloading SMP TCP Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.259

Field Name : portOverloadingSmpInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.258

Field Name : portOverloadingSmpMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.257

Field Name : portOverloadingSmpMemAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Session Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.256

Field Name : portOverloadingConnFreeNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Conn Free Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.255

Field Name : portOverloadingConnFreeRetryLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Conn Free Retry Lookup
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.254

Field Name : cgnv6lsnGlobalPortOverloadingAttemptFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Attempt Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.253

Field Name : portOverloadingAttemptDiffPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading on Different Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.252

Field Name : portOverloadingAttemptSamePartition
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading on Same Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.251

Field Name : portOverloadingAttemptConsecutivePorts
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading on Consecutive Ports
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.250

Field Name : portOverloadingIncOverflow
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Inc Overflow
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.249

Field Name : portOverloadingFreePortBatchOnConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Free Port Batch on Conflict
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.248

Field Name : portOverloadingFreePortOnConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Free Port on Conflict
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.247

Field Name : portOverloadingDecOnFree
Field Type : CounterBasedGauge64
Field Status : current

Description : Port Overloading Port Decrement on Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.246

Field Name : portOverloadingDecOnConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Port Decrement on Conflict
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.245

Field Name : portOverloadingInc
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Port Increment
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.244

Field Name : portOverloadingAssignUserPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Port Assign User Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.243

Field Name : portOverloadingAssignUser
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Port Assign User
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.242

Field Name : portOverloadingOutOfMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Out of Memory
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.241

Field Name : portOverloadingDestinationConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Destination Conflict
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.240

Field Name : portBatchContainerAllocRaceFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Container Race Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.239

Field Name : portBatchContainerAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Container Alloc Out of Memory
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.238

Field Name : specificPortAllocatedFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Specific Port Allocated from Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.237

Field Name : specificPortAllocatedFromQuotaPartition

Field Type : CounterBasedGauge64
Field Status : current
Description : Specific Port Allocated from Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.236

Field Name : specificPortAllocatedFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : Specific Port Allocated from Quota Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.235

Field Name : portBatchFreedFromQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Freed From Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.234

Field Name : portBatchAllocatedToQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Allocated to Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.233

Field Name : portFreedFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.232

Field Name : portFreedFromQuotaPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.231

Field Name : portFreedFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Quota Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.230

Field Name : portAllocatedFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Allocated from Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.229

Field Name : portAllocatedFromQuotaPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Allocated from Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.228

Field Name : portAllocatedFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Allocated from Quota Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.227

Field Name : poolPortBatchPortFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.226

Field Name : partitionPortFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.225

Field Name : consecutivePortFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Consecutive Pool
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.224

Field Name : badPortToFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Freeing Bad Port
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.223

Field Name : haRcvPortNotInPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Not in Port Batch on Sync Rcv
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.222

Field Name : haSendPortBatchNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Batch Not Found on Sync Send
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.221

Field Name : haSyncPortBatchRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Batch Extension Sync Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.220

Field Name : haSyncPortBatchSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Batch Extension Sync Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.219

Field Name : quotaExtensionRemoveNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Extension Not Found on Remove
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.218

Field Name : quotaExtensionRemoved
Field Type : CounterBasedGauge64
Field Status : current

Description : Quota Extension Removed from Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.217

Field Name : quotaExtensionAdded
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Extension Added to Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.216

Field Name : radiusQueryQuotaExtAllocRaceFree
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Query Container Alloc Race Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.215

Field Name : radiusQueryQuotaExtAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Query Container Alloc (No Memoty)
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.214

Field Name : portBatchFreeWrongPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Free Wrong Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.213

Field Name : portBatchFreePortNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Port Not Found on Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.212

Field Name : portBatchFreeQuotaNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Quota Not Found on Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.211

Field Name : portBatchQuotaExtensionAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Extension Alloc Failure (No memory)
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.210

Field Name : h323AlgPortPairAllocFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.209

Field Name : h323AlgPortPairAllocFromQuotaPartitionError
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Quota Partition Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.208

Field Name : h323AlgPortPairAllocFromQuotaPartition

Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.207

Field Name : h323AlgPortPairAllocFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Quota Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.206

Field Name : h323AlgPortPairAllocFromPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.205

Field Name : h323AlgPortPairAllocFromPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.204

Field Name : h323AlgPortPairAllocFromConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.203

Field Name : h323AlgCreateRtcpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Create RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.202

Field Name : h323AlgCreateRtpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Create RTP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.201

Field Name : h323AlgCreateSingleFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Create Single RTP or RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.200

Field Name : h323AlgAllocSinglePortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Alloc Single RTP or RTCP NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.199

Field Name : h323AlgAllocRtpRtcpPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Alloc RTP/RTCP NAT Ports Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.198

Field Name : h323AlgReuseRtpRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Reuse RTP/RTCP Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.197

Field Name : h323AlgRtcpFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG RTCP Full-cone NAT Port Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.196

Field Name : h323AlgSingleRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Single RTCP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.195

Field Name : h323AlgSingleRtpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Single RTP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.194

Field Name : h323AlgReleasePortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Release NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.193

Field Name : h323AlgCreateFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Create Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.192

Field Name : h323AlgAllocPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Alloc NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.191

Field Name : h323AlgFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Full-cone Session Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.190

Field Name : h323AlgReuseFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Reuse Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.189

Field Name : h323AlgNoNatIp
Field Type : CounterBasedGauge64
Field Status : current

Description : H323 ALG Unknown NAT IP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.188

Field Name : h323AlgQuotaIncFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.187

Field Name : h323AlgNoQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG User-Quota Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.186

Field Name : sipAlgPortPairAllocFromQuotaPoolPortBatchWithFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Quota Port Batch Version 2 with Frag Free Ports
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.185

Field Name : sipAlgPortPairAllocFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.184

Field Name : sipAlgPortPairAllocFromQuotaPartitionError
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Quota Partition Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.183

Field Name : sipAlgPortPairAllocFromQuotaPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.182

Field Name : sipAlgPortPairAllocFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Quota Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.181

Field Name : sipAlgPortPairAllocFromPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.180

Field Name : sipAlgPortPairAllocFromPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.179

Field Name : sipAlgPortPairAllocFromConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.178

Field Name : sipAlgCreateRtcpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Create RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.177

Field Name : sipAlgCreateRtpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Create RTP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.176

Field Name : sipAlgCreateSingleFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Create Single RTP or RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.175

Field Name : sipAlgAllocSinglePortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Alloc Single RTP or RTCP NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.174

Field Name : sipAlgAllocRtpRtcpPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Alloc RTP/RTCP NAT Ports Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.173

Field Name : sipAlgReuseRtpRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Reuse RTP/RTCP Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.172

Field Name : sipAlgRtcpFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG RTCP Full-cone NAT Port Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.171

Field Name : sipAlgSingleRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Single RTCP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.170

Field Name : sipAlgSingleRtpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Single RTP Full-cone Found

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.169

Field Name : sipAlgReleaseContactPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Release Contact NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.168

Field Name : sipAlgCreateContactFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Create Contact Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.167

Field Name : sipAlgAllocContactPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Alloc Contact NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.166

Field Name : sipAlgContactFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Contact Full-cone Session Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.165

Field Name : sipAlgReuseContactFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Reuse Contact Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.164

Field Name : sipAlgNoNatIp
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Unknown NAT IP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.163

Field Name : sipAlgQuotaIncFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.162

Field Name : sipAlgNoQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG User-Quota Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.161

Field Name : udpAlgAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP ALG Port Allocation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.160

Field Name : udpAlgNoNatIp
Field Type : CounterBasedGauge64

Field Status : current
Description : UDP ALG User-Quota Unknown NAT IP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.159

Field Name : udpAlgEimMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP ALG Endpoint-Independent Mapping Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.158

Field Name : udpAlgNoQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP ALG User-Quota Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.157

Field Name : totalIcmpFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total ICMP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.156

Field Name : totalIcmpAllocatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total ICMP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.155

Field Name : totalUdpFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.154

Field Name : totalUdpAllocatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.153

Field Name : totalTcpFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.152

Field Name : totalTcpAllocatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.151

Field Name : newUserResourceUnavailableOther
Field Type : CounterBasedGauge64
Field Status : current
Description : Other New User NAT Resource Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.150

Field Name : newUserResourceUnavailableIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP New User NAT Resource Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.149

Field Name : newUserResourceUnavailableUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP New User NAT Resource Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.148

Field Name : newUserResourceUnavailableTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP New User NAT Resource Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.147

Field Name : natPortUnavailable
Field Type : CounterBasedGauge64
Field Status : current
Description : Total NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.146

Field Name : natPortUnavailableOther
Field Type : CounterBasedGauge64
Field Status : current
Description : Other NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.145

Field Name : extendedQuotaMismatched
Field Type : CounterBasedGauge64
Field Status : current
Description : Extended User-Quota Mismatched
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.144

Field Name : dataSessionUserQuotaMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Counter Per User Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.143

Field Name : dataSessionFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Data Sessions Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.142

Field Name : dataSessionCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Data Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.141

Field Name : fullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Full-cone sessions freed

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.140

Field Name : fullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Full-cone sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.139

Field Name : udpAlgFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP ALG Full-cone sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.138

Field Name : udpAlgFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP ALG Full-cone sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.137

Field Name : udpFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Full-cone sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.136

Field Name : udpFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Full-cone sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.135

Field Name : tcpFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Full-cone sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.134

Field Name : tcpFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Full-cone sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.133

Field Name : userQuotaNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.132

Field Name : icmpOutOfStateUqeDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User Queue Exceeded ICMP notification dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.131

Field Name : icmpOutOfStateUqeHostUnreachableSent
Field Type : CounterBasedGauge64

Field Status : current
Description : Total User Quota Exceeded ICMP host unreachable sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.130

Field Name : icmpOutOfStateUqeAdminFilteredSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User Quota Exceeded ICMP admin filtered sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.129

Field Name : tcpOutOfStateRstDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Out of State TCP RST dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.128

Field Name : tcpOutOfStateRstSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Out of State TCP RST sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.127

Field Name : userQuotaPutInDelQShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User-Quota Put In Del Q
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.126

Field Name : quotaDeleteNotInBucket
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Delete Not In Bucket
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.125

Field Name : quotaMarkedDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Marked Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.124

Field Name : userQuotaCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User-Quota Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.123

Field Name : userQuotaMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Memory Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.122

Field Name : userQuotaMemAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Memory Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.121

Field Name : fullconeForceDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone Session Force Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.120

Field Name : ipSlbCrossCpuSent
Field Type : CounterBasedGauge64
Field Status : current
Description : IP SLB Cross CPU Packets Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.119

Field Name : staticNatHaMapMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Static NAT Mapping Mismatch on HA Standby
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.118

Field Name : staticNatCrossCpuHelperFreeNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Static NAT Cross CPU Helper Free Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.117

Field Name : staticNatCrossCpuHelperFreeRetryLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : Static NAT Cross CPU Helper Free Retry Lookup
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.116

Field Name : staticNatCrossCpuHelperFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Static NAT Cross CPU Helper Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.115

Field Name : staticNatCrossCpuNoSession
Field Type : CounterBasedGauge64
Field Status : current
Description : Static NAT Cross CPU No Session Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.114

Field Name : staticNatCrossCpuBadL4
Field Type : CounterBasedGauge64
Field Status : current
Description : Static NAT Cross CPU Unsupported L4
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.113

Field Name : staticNatCrossCpuBadL3
Field Type : CounterBasedGauge64
Field Status : current
Description : Static NAT Cross CPU Unsupported L3
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.112

Field Name : staticNatCrossCpuRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : Static NAT Cross CPU Helper Packets Received

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.111

Field Name : staticNatCrossCpuSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Static NAT Cross CPU Helper Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.110

Field Name : staticNatCrossCpuHelperCpuMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Static NAT Cross CPU Helper CPU Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.109

Field Name : staticNatCrossCpuHelperStandby
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Static NAT Standby
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.108

Field Name : staticNatCrossCpuHelperDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Deleted for Static NAT
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.107

Field Name : staticNatCrossCpuHelperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Created for Static NAT
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.106

Field Name : freePortFromQuotaNoPortInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : Free Port From Quota No Port Info
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.105

Field Name : freePortFromQuotaNoContainer
Field Type : CounterBasedGauge64
Field Status : current
Description : Free Port from Quota No Container
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.104

Field Name : portPairAllocBadMath
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Pair Alloc Bad Math
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.103

Field Name : portBatchIntervalMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Specific Port Batch Port Interval Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.102

Field Name : portBatchNumMismatch
Field Type : CounterBasedGauge64

Field Status : current
Description : Specific Port Batch Num Ports Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.101

Field Name : quotaExtPutInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Extension Put in Delete Queue
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.100

Field Name : quotaExtMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Extension Memory Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.99

Field Name : quotaExtMemAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Extension Out of Memory
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.98

Field Name : quotaExtMemAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Extension Memory Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.97

Field Name : fragTunnelIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite ICMP Packet Too Big Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.96

Field Name : fragIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Packet Too Big Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.95

Field Name : sixrdTunnelFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Fragment IPv6-in-IPv4 Packet
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.94

Field Name : dsliteTunnelFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Fragment DS-Lite Packet
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.93

Field Name : frag
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragmented Packets
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.92

Field Name : mtuExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet Exceeded MTU
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.91

Field Name : crossCpuHelperDoubleAdd
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Double Add Attempt
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.90

Field Name : crossCpuHelperNatPoolStandby
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper NAT Pool Standby
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.89

Field Name : crossCpuHelperCpuMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper CPU Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.88

Field Name : crossCpuHelperDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.87

Field Name : crossCpuHelperFreeNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Free Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.86

Field Name : crossCpuHelperFreeRetryLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Free Retry Lookup
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.85

Field Name : crossCpuHelperFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.84

Field Name : crossCpuNoSession
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU No Session Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.83

Field Name : crossCpuBadL4
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Unsupported L4

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.82

Field Name : crossCpuBadL3
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Unsupported L3
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.81

Field Name : crossCpuRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Packets Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.80

Field Name : crossCpuSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Packets Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.79

Field Name : crossCpuHelperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Session Helper Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.78

Field Name : fullconeOverflowEif
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone Session EIF Overflow
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.77

Field Name : fullconeOverflowEim
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone Session EIM Overflow
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.76

Field Name : fullconeInboundNatPoolMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone Session NAT Pool Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.75

Field Name : badSmpTupleNatIp
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad NAT IP from SMP tuple
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.74

Field Name : badTupleNatIp
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad NAT IP from tuple
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.73

Field Name : standbyClassListDrop
Field Type : CounterBasedGauge64

Field Status : current
Description : HA Standby Class-List drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.72

Field Name : haEndpointIndepMapMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Endpoint-independent Matching
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.71

Field Name : haFullconeCreateRaceFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Full-cone Create Race Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.70

Field Name : haFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.69

Field Name : haUnknownNatIp
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Unknown NAT IP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.68

Field Name : haNatPortUnavailable
Field Type : CounterBasedGauge64
Field Status : current
Description : HA NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.67

Field Name : haDnatMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Destination NAT Config Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.66

Field Name : haPortMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.65

Field Name : haFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Full-cone Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.64

Field Name : haUserQuotaMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : HA User-Quota Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.63

Field Name : haClasslistMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Class-list Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.62

Field Name : greUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE User-Quota exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.61

Field Name : udpAlgUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP ALG User-Quota exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.60

Field Name : espUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP User-Quota exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.59

Field Name : natEspNoControlSesn
Field Type : CounterBasedGauge64
Field Status : current
Description : LSN NAT ESP No Control Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.58

Field Name : natEspIpConflicts
Field Type : CounterBasedGauge64
Field Status : current
Description : LSN NAT ESP IP Conflicts
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.57

Field Name : natPoolDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT Pool Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.56

Field Name : natPortFreedFromDiffCpu
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT Port Freed On Different CPU
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.55

Field Name : natPortChunkFreedFromCpu
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT Port Chunks Freed From CPU
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.54

Field Name : natPortDoubleFree
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT Port Double Free

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.53

Field Name : fullconeNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone session not found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.52

Field Name : fullconeRetryLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone session retry look-up
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.51

Field Name : fullconeInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone session found in delete queue
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.50

Field Name : lidPassThrough
Field Type : CounterBasedGauge64
Field Status : current
Description : LSN LID Pass-through
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.49

Field Name : lidDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : LSN LID Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.48

Field Name : noClassListMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : No Class-List Match
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.47

Field Name : natIpMaxUdpPortsAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT IP UDP Max Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.46

Field Name : natIpMaxTcpPortsAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT IP TCP Max Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.45

Field Name : noRadiusProfileMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : No RADIUS Profile Match
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.44

Field Name : haNatPoolBatchTypeMismatch
Field Type : CounterBasedGauge64

Field Status : current
Description : HA NAT Pool Batch Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.43

Field Name : cgnv6lsnGlobalHaNatPoolUnusable
Field Type : CounterBasedGauge64
Field Status : current
Description : HA NAT Pool Unusable
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.42

Field Name : cgnv6lsnGlobalNatPoolUnsable
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT Pool Unusable
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.41

Field Name : cgnv6lsnGlobalPortOverloadingSmpFreeUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Overloading Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.40

Field Name : cgnv6lsnGlobalPortOverloadingSmpFreeTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Overloading Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.39

Field Name : cgnv6lsnGlobalPortOverloadingSmpInsertedUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Overloading Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.38

Field Name : cgnv6lsnGlobalPortOverloadingSmpInsertedTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Overloading Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.37

Field Name : cgnv6LsnGlobalTotalUdpOverloaded
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Overloaded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.36

Field Name : cgnv6lsnGlobalTotalTcpOverloaded
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Overloaded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.35

Field Name : cgnv6lsnGlobalEifLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Endpoint-Independent Filtering Inbound Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.33

Field Name : cgnv6lsnGlobalInboundFiltered
Field Type : CounterBasedGauge64
Field Status : current
Description : Endpoint-Dependent Filtering Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.32

Field Name : cgnv6lsnGlobalEndpointIndepFilterMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Endpoint-Independent Filtering Matched
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.31

Field Name : cgnv6lsnGlobalEndpointIndepMapMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Endpoint-Independent Mapping Matched
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.30

Field Name : cgnv6lsnGlobalFullconeSelfHairpinningDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Self-Hairpinning Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.29

Field Name : cgnv6lsnGlobalHairpin
Field Type : CounterBasedGauge64
Field Status : current
Description : Hairpin Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.28

Field Name : cgnv6lsnGlobalFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone Session Creation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.27

Field Name : cgnv6lsnGlobalUdpFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Full-cone Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.26

Field Name : cgnv6lsnGlobalUdpFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Full-cone Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.25

Field Name : cgnv6lsnGlobalTcpFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Full-cone Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.24

Field Name : cgnv6lsnGlobalTcpFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Full-cone Session Created

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.23

Field Name : cgnv6lsnGlobalDataSesnRateUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Rate User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.22

Field Name : cgnv6lsnGlobalDataSesnUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.21

Field Name : cgnv6lsnGlobalExtendedQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Extended User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.20

Field Name : cgnv6lsnGlobalExtendedQuotaMatched
Field Type : CounterBasedGauge64
Field Status : current
Description : Extended User-Quota Matched
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.19

Field Name : cgnv6lsnGlobalIcmpUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.18

Field Name : cgnv6lsnGlobalUdpUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.17

Field Name : cgnv6lsnGlobalTcpUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.16

Field Name : cgnv6lsnGlobalNewUserResourceUnavailable
Field Type : CounterBasedGauge64
Field Status : current
Description : New User NAT Resource Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.15

Field Name : cgnv6lsnGlobalNatPortUnavailableIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.14

Field Name : cgnv6lsnGlobalNatPortUnavailableUdp
Field Type : CounterBasedGauge64

Field Status : current
Description : UDP NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.13

Field Name : cgnv6lsnGlobalNatPortUnavailableTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.12

Field Name : cgnv6lsnGlobalUserQuotaFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Creation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.11

Field Name : cgnv6lsnGlobalUserQuotaPutInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.10

Field Name : cgnv6lsnGlobalTotalUserQuotaCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.9

Field Name : cgnv6lsnGlobalDataSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.8

Field Name : cgnv6lsnGlobalDataSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.7

Field Name : cgnv6lsnGlobalTotalIcmpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total ICMP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.6

Field Name : cgnv6lsnGlobalTotalIcmpAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total ICMP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.5

Field Name : cgnv6lsnGlobalTotalUdpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.4

Field Name : cgnv6lsnGlobalTotalUdpAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.3

Field Name : cgnv6lsnGlobalTotalTcpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.2

Field Name : cgnv6lsnGlobalTotalTcpAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.1

Field Name : userQuoteCreatedPreviousEpochLast
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.2.1.9

Field Name : fullconeCreatedPreviousEpochLast
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.2.1.8

Field Name : dataSessionsPreviousEpochLast
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.2.1.7

Field Name : userQuoteCreatedPreviousEpochFirst
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.2.1.6

Field Name : fullconeCreatedPreviousEpochFirst
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.2.1.5

Field Name : dataSessionsPreviousEpochFirst
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.2.1.4

Field Name : userQuoteCreatedCurrentEpoch
Field Type : CounterBasedGauge64
Field Status : current
Description :

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.2.1.3

Field Name : fullconeCreatedCurrentEpoch
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.2.1.2

Field Name : dataSessionsCurrentEpoch
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.2.1.1

Field Name : tcamCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : TCAM Flow Count
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.20

Field Name : tcamFree
Field Type : CounterBasedGauge64
Field Status : current
Description : TCAM Flows Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.19

Field Name : tcamCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : TCAM Flows Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.18

Field Name : entryInvalidateServerDown
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Invalidate due to server down
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.17

Field Name : entryForceHwInvalidate
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Force HW Invalidate
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.16

Field Name : entryAgeOutInvalidDst
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out - invalid dst
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.15

Field Name : entryAgeOutTcpRst
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out - TCP RST
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.14

Field Name : entryAgeOutTcpFin
Field Type : CounterBasedGauge64

Field Status : current
Description : HW Entries Aged Out - TCP FIN
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.13

Field Name : entryAgeOutIdle
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out - idle timeout
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.12

Field Name : entryAgeOut
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.11

Field Name : entryCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Count
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.10

Field Name : entryFreeNoSwEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Freed - no software entry
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.9

Field Name : entryFreeNoConn
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Freed - no matched conn
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.8

Field Name : entryFreeNoHwProg
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Freed - no HW prog
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.7

Field Name : entryFreeOppEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Freed - opposite tuple entry aged-out
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.6

Field Name : entryFree
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.5

Field Name : entryCreateFailMaxEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Creation Failed - max entries exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.4

Field Name : entryCreateFailServerDown
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Creation Failed - server down
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.3

Field Name : entryCreateFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Creation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.2

Field Name : entryCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.1

Field Name : synCookieConnSetupFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN cookie connection setup failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.39

Field Name : synCookieVerificationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN cookie verification failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.38

Field Name : synCookieVerificationPassed
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN cookie verification passed
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.37

Field Name : synCookieSynAckSent
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN cookie SYN ACK sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.36

Field Name : l3EntryAddToHwFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 entry HW add failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.35

Field Name : l3EntryRemoveFromBgpFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 entry BGP remove failures
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.34

Field Name : l3EntryAddToBgpFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 Entry BGP add failures

OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.33

Field Name : entryInvalidated
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry invalidated
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.32

Field Name : entryAddedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry added shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.31

Field Name : ipOtherBlockAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Other block alloc failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.30

Field Name : ipOtherBlockFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Other block free
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.29

Field Name : ipOtherBlockAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Other block alloc
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.28

Field Name : ipPortBlockAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port block alloc failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.27

Field Name : ipPortBlockFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Port block free
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.26

Field Name : ipPortBlockAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Port block alloc
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.25

Field Name : ipNodeAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Node alloc failures
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.24

Field Name : ipNodeFree
Field Type : CounterBasedGauge64

Field Status : current
Description : Node free
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.23

Field Name : ipNodeAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Node alloc
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.22

Field Name : l4EntryListAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 Entry list alloc failures
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.21

Field Name : l4EntryListFree
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 Entry list free
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.20

Field Name : l4EntryListAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 Entry list alloc
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.19

Field Name : l4EntryDropMaxHwExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 Entry Drop due to HW Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.18

Field Name : l4EntryMatchDropHw
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 HW Entry match drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.17

Field Name : l4EntryMatchDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 Entry match drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.16

Field Name : l4HwOutOfEntries
Field Type : CounterBasedGauge64
Field Status : current
Description : HW out of L4 entries
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.15

Field Name : l4EntryRemovedFromHw
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 Entry removed from HW
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.14

Field Name : l4EntryAddedToHw
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 Entry added to HW
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.13

Field Name : l4EntryDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 Entry deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.12

Field Name : l4EntryAdded
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 Entry added
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.11

Field Name : l3EntryDropMaxHwExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 Entry Drop due to HW Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.10

Field Name : l3EntryMatchDropHw
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 HW entry match drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.9

Field Name : l3EntryMatchDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 Entry match drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.8

Field Name : l3EntryTooMany
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 Too many entries
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.7

Field Name : l3EntryRemovedFromHw
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 Entry removed from HW
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.6

Field Name : l3EntryAddedToHw
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 Entry added to HW
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.5

Field Name : l3EntryRemovedFromBgp
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry removed from BGP

OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.4

Field Name : l3EntryAddedToBgp
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 Entry added to BGP
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.3

Field Name : l3EntryDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 Entry Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.2

Field Name : l3EntryAdded
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 Entry Added
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.1

Field Name : cgnv6ServiceGroupSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.3.1.1

Field Name : cgnv6ServiceGroupSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.3.1.1.1

Field Name : cgnv6ServicePeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Service peak connection
OID : 1.3.6.1.4.1.22610.2.4.10.115.3.1.1.1.4

Field Name : cgnv6ServerSelectionFailReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Service selection fail reset
OID : 1.3.6.1.4.1.22610.2.4.10.115.3.1.1.1.3

Field Name : cgnv6ServerSelectionFailDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Service selection fail drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.3.1.1.1.2

Field Name : cgnv6ServiceGroupName
Field Type : String
Field Status : current
Description : CGNV6 Service Name
OID : 1.3.6.1.4.1.22610.2.4.10.115.3.1.1.1.1

Field Name : cgnv6ServerSTable
Field Type : TABLE

Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.2.1.1

Field Name : cgnv6ServerSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.2.1.1.1

Field Name : peakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Peak connections
OID : 1.3.6.1.4.1.22610.2.4.10.115.2.1.1.1.6

Field Name : revPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Packets
OID : 1.3.6.1.4.1.22610.2.4.10.115.2.1.1.1.5

Field Name : fwdPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward packets
OID : 1.3.6.1.4.1.22610.2.4.10.115.2.1.1.1.4

Field Name : totalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total connections
OID : 1.3.6.1.4.1.22610.2.4.10.115.2.1.1.1.3

Field Name : cgnv6ServerCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Current connections
OID : 1.3.6.1.4.1.22610.2.4.10.115.2.1.1.1.2

Field Name : cgnv6Name
Field Type : String
Field Status : current
Description : Server Name
OID : 1.3.6.1.4.1.22610.2.4.10.115.2.1.1.1.1

Field Name : icmpTotalPortsAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total ICMP ports allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.1.1.3

Field Name : udpTotalPortsAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP ports allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.1.1.2

Field Name : tcpTotalPortsAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP ports allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.1.1.1

Field Name : rcvNotSupportedOption
Field Type : CounterBasedGauge64
Field Status : current
Description : PNot supported options received
OID : 1.3.6.1.4.1.22610.2.4.10.115.33.2.1.16

Field Name : rcvNotSupportedMsg
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets with not supported messages sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.33.2.1.15

Field Name : noBindingMsgsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : NO_BINDING messages sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.33.2.1.14

Field Name : noPrefixAvailSent
Field Type : CounterBasedGauge64
Field Status : current
Description : NO_PREFIX_AVAILABLE messages sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.33.2.1.13

Field Name : pktsDroppedDuringClear
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets dropped during clear bindings process
OID : 1.3.6.1.4.1.22610.2.4.10.115.33.2.1.12

Field Name : packetsDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.33.2.1.11

Field Name : informationReqRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : Information request messages received
OID : 1.3.6.1.4.1.22610.2.4.10.115.33.2.1.10

Field Name : relayReplySent
Field Type : CounterBasedGauge64
Field Status : current
Description : Relay reply messages sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.33.2.1.9

Field Name : replySent
Field Type : CounterBasedGauge64
Field Status : current
Description : Reply messages sent

OID : 1.3.6.1.4.1.22610.2.4.10.115.33.2.1.8

Field Name : advertiseSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Advertise messages sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.33.2.1.7

Field Name : relayForwRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : Relay forward message received
OID : 1.3.6.1.4.1.22610.2.4.10.115.33.2.1.6

Field Name : releaseRev
Field Type : CounterBasedGauge64
Field Status : current
Description : Release messages received
OID : 1.3.6.1.4.1.22610.2.4.10.115.33.2.1.5

Field Name : rebindRev
Field Type : CounterBasedGauge64
Field Status : current
Description : Rebind messages received
OID : 1.3.6.1.4.1.22610.2.4.10.115.33.2.1.4

Field Name : renewRev
Field Type : CounterBasedGauge64
Field Status : current
Description : Renew messages received
OID : 1.3.6.1.4.1.22610.2.4.10.115.33.2.1.3

Field Name : requestRev
Field Type : CounterBasedGauge64
Field Status : current
Description : Request messages received
OID : 1.3.6.1.4.1.22610.2.4.10.115.33.2.1.2

Field Name : solicitRev
Field Type : CounterBasedGauge64
Field Status : current
Description : Solicit messages received
OID : 1.3.6.1.4.1.22610.2.4.10.115.33.2.1.1

Field Name : fwTopThrSrcDb
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log Firewall top threat and source summary database
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.37

Field Name : fwTopThrDb
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log Firewall top threat summary database
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.36

Field Name : queryError
Field Type : CounterBasedGauge64

Field Status : current
Description : Total local-log axapi query error
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.35

Field Name : response
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log axapi response
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.34

Field Name : query
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log axapi query
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.33

Field Name : dbErro
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log database create error
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.32

Field Name : fwTopCategoryDb
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log Firewall top category summary database
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.31

Field Name : fwTopAppSrcDb
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log Firewall top application and source summary database
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.30

Field Name : fwTopSrcDb
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log Firewall top source summary database
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.29

Field Name : fwTopAppDb
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log Firewall top application summary database
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.28

Field Name : epTopHostDb
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log EP top host summary database
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.22

Field Name : epTopWebCategoryDb
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log EP top web-category summary database
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.21

Field Name : epTopDomainDb
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log EP top domain summary database
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.20

Field Name : epTopDstDb
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log EP top destination summary database
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.19

Field Name : epTopSrcDb
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log EP top client summary database
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.18

Field Name : epTopUserDb
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log EP top user summary database
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.17

Field Name : aamTopUserDb
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log AAM top user summary database
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.16

Field Name : fwDb
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log Firewall raw database
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.15

Field Name : epDb
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log EP raw database
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.13

Field Name : aamDb
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log AAM raw database
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.12

Field Name : logSummarizedError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log summarization error
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.11

Field Name : l2LogSummarized
Field Type : CounterBasedGauge64
Field Status : current
Description : Total layer 2 log summarized

OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.10

Field Name : l1LogSummarized
Field Type : CounterBasedGauge64
Field Status : current
Description : Total layer 1 log summarized
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.9

Field Name : logSummarized
Field Type : CounterBasedGauge64
Field Status : current
Description : Total raw log summarized
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.8

Field Name : rawLogError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total raw log logging error
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.7

Field Name : rawLog
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log raw logs
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.6

Field Name : dequeueError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log dequeue processing error
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.5

Field Name : dequeue
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log dequeue
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.4

Field Name : enqueueError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log enqueue error
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.3

Field Name : enqueueFull
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log queue full
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.2

Field Name : enqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log enqueue
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.1

Field Name : gslbSiteSTable
Field Type : TABLE

Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.119.9.1.1

Field Name : gslbSiteSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.119.9.1.1.1

Field Name : gslbSiteHits
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of times the site was selected
OID : 1.3.6.1.4.1.22610.2.4.10.119.9.1.1.1.2

Field Name : siteName
Field Type : String
Field Status : current
Description : Specify GSLB site name
OID : 1.3.6.1.4.1.22610.2.4.10.119.9.1.1.1.1

Field Name : gslbServiceIpSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.119.4.1.1

Field Name : gslbServiceIpSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.119.4.1.1.1

Field Name : recent
Field Type : CounterBasedGauge64
Field Status : current
Description : Recent hits
OID : 1.3.6.1.4.1.22610.2.4.10.119.4.1.1.1.3

Field Name : gslbServiceIpHits
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of times the service IP has been selected
OID : 1.3.6.1.4.1.22610.2.4.10.119.4.1.1.1.2

Field Name : nodeName
Field Type : String
Field Status : current
Description : Service-IP Name
OID : 1.3.6.1.4.1.22610.2.4.10.119.4.1.1.1.1

Field Name : metricSiteConnectionCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Connection Count by Site Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.34

Field Name : metricRoundRobin
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Round Robin Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.33

Field Name : metricAdminIp
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Admin IP Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.32

Field Name : metricLeastReponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Least Reponse Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.31

Field Name : metricUser
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric User Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.30

Field Name : metricBandwidthCost
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Bandwidth Cost Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.29

Field Name : metricBandwidthQuality
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Bandwidth Quality Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.28

Field Name : metricAdminPreference
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Admin Preference Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.27

Field Name : metricActiveWeight
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Active Weight Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.26

Field Name : metricNumberOfSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Number of Sessions Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.25

Field Name : metricConnectionLoad
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Connection Load Hit

OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.24

Field Name : metricGeographic
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Geographic Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.23

Field Name : metricActiveRdt
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Active RDT Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.22

Field Name : metricEasyRdt
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Easy RDT Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.21

Field Name : metricActiveServer
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Active Server Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.20

Field Name : metricCapacity
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Capacity Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.19

Field Name : metricWeightedSite
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Weighted Site Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.18

Field Name : metricWeightedIp
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Weighted IP Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.17

Field Name : metricHealthCheck
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Health Check Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.16

Field Name : noAnswer
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of replies with unknown server IP
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.15

Field Name : badTypeResponse
Field Type : CounterBasedGauge64

Field Status : current
Description : Number of replies with incorrect type
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.14

Field Name : badTypeQuery
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of queries with incorrect type
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.13

Field Name : badClassResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of replies with incorrect class
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.12

Field Name : badClassQuery
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of queries with incorrect class
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.11

Field Name : badServiceResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of replies with unknown service
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.10

Field Name : badServiceQuery
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of queries with unknown service
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.9

Field Name : badFormatResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of replies with incorrect format
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.8

Field Name : badFormatQuery
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of queries with incorrect format
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.7

Field Name : badHeaderResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of replies with incorrect header
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.6

Field Name : badHeaderQuery
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of queries with incorrect header
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.5

Field Name : badPacketResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of replies with incorrect data length
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.4

Field Name : badPacketQuery
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of queries with incorrect data length
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.3

Field Name : totalResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Total number of DNS replies sent to clients
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.2

Field Name : totalQuery
Field Type : CounterBasedGauge64
Field Status : current
Description : Total number of DNS queries received
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.1

Field Name : gslbZoneSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.119.11.1.1

Field Name : gslbZoneSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.119.11.1.1.1

Field Name : smruleRedirFromSvcMiss
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Number of DNS queries redirected to the service by service-matching rule and the query originally doesn't hit a service
OID : 1.3.6.1.4.1.22610.2.4.10.119.11.1.1.1.10

Field Name : smruleRedirFromSvcHit
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Number of DNS queries redirected to the service by service-matching rule and the query originally hits a service
OID : 1.3.6.1.4.1.22610.2.4.10.119.11.1.1.1.9

Field Name : backupModeResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Number of DNS replies sent to clients by the ACOS device in backup mode
OID : 1.3.6.1.4.1.22610.2.4.10.119.11.1.1.1.8

Field Name : stickyModeResponse

Field Type : CounterBasedGauge64
Field Status : current
Description : Total Number of DNS replies sent to clients by the ACOS device to keep the clients on the same site. (This statistic applies on
OID : 1.3.6.1.4.1.22610.2.4.10.119.11.1.1.1.7

Field Name : serverModeResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Number of DNS replies sent to clients by the ACOS device as a DNS server for the zone. (This statistic applies only if th
OID : 1.3.6.1.4.1.22610.2.4.10.119.11.1.1.1.6

Field Name : cacheModeResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Number of cached DNS replies sent to clients by the ACOS device for the zone. (This statistic applies only if the DNS cac
OID : 1.3.6.1.4.1.22610.2.4.10.119.11.1.1.1.5

Field Name : proxyModeResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Number of DNS replies sent to clients by the ACOS device as a DNS proxy for the zone
OID : 1.3.6.1.4.1.22610.2.4.10.119.11.1.1.1.4

Field Name : sentResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Number of DNS replies sent to clients for the zone
OID : 1.3.6.1.4.1.22610.2.4.10.119.11.1.1.1.3

Field Name : receivedQuery
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Number of DNS queries received for the zone
OID : 1.3.6.1.4.1.22610.2.4.10.119.11.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Specify the name for the DNS zone
OID : 1.3.6.1.4.1.22610.2.4.10.119.11.1.1.1.1

Field Name : totalSflowPacketsDropMgmt
Field Type : CounterBasedGauge64
Field Status : current
Description : sflow packets dropped because of rate limit via Mgmt Interface
OID : 1.3.6.1.4.1.22610.2.4.10.125.7.1.6

Field Name : totalSflowPacketsSentMgmt
Field Type : CounterBasedGauge64
Field Status : current
Description : Total sflow packets sent via Mgmt Interface
OID : 1.3.6.1.4.1.22610.2.4.10.125.7.1.5

Field Name : totalSflowLocalPacketsSent

Field Type : CounterBasedGauge64
Field Status : current
Description : Total sflow packets sent desc {}
OID : 1.3.6.1.4.1.22610.2.4.10.125.7.1.4

Field Name : totalSflowPacketsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total sflow packets sent
OID : 1.3.6.1.4.1.22610.2.4.10.125.7.1.3

Field Name : totalCounterSampleRecords
Field Type : CounterBasedGauge64
Field Status : current
Description : Total counter sample records
OID : 1.3.6.1.4.1.22610.2.4.10.125.7.1.2

Field Name : totalPacketSampleRecords
Field Type : CounterBasedGauge64
Field Status : current
Description : Total packet sample records
OID : 1.3.6.1.4.1.22610.2.4.10.125.7.1.1

Field Name : netflowMonitorSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1

Field Name : netflowMonitorSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1

Field Name : ddosHttpStatRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.130

Field Name : ddosHttpStatRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.129

Field Name : ddosGeneralStatRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.128

Field Name : ddosGeneralStatRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.127

Field Name : customGtpRateLimitPeriodicRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom GTP Rate Limit Periodic Records Sent Failure
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.126

Field Name : customGtpRateLimitPeriodicRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom GTP Rate Limit Periodic Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.125

Field Name : customNatIddosL4EntryDeletedRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom NAT iDDoS L4 Entry Deleted Records Sent Failure
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.124

Field Name : customNatIddosL4EntryDeletedRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom NAT iDDoS L4 Entry Deleted Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.123

Field Name : customNatIddosL4EntryCreatedRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom NAT iDDoS L4 Entry Created Records Sent Failure
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.122

Field Name : customNatIddosL4EntryCreatedRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom NAT iDDoS L4 Entry Created Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.121

Field Name : customNatIddosL3EntryDeletedRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom NAT iDDoS L3 Entry Deleted Records Sent Failure
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.120

Field Name : customNatIddosL3EntryDeletedRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom NAT iDDoS L3 Entry Deleted Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.119

Field Name : customNatIddosL3EntryCreatedRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom NAT iDDoS L3 Entry Created Records Sent Failure
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.118

Field Name : customNatIddosL3EntryCreatedRecordsSent
Field Type : CounterBasedGauge64
Field Status : current

Description : Custom NAT iDDoS L3 Entry Created Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.117

Field Name : customFwSesnLimitExceededRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW Session Limit Exceeded Records Sent Failure
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.116

Field Name : customFwSesnLimitExceededRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW Session Limit Exceeded Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.115

Field Name : customFwIddosEntryDeletedRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW iDDoS Entry Deleted Records Sent Failure
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.114

Field Name : customFwIddosEntryDeletedRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW iDDoS Entry Deleted Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.113

Field Name : customFwIddosEntryCreatedRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW iDDoS Entry Created Records Sent Failure
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.112

Field Name : customFwIddosEntryCreatedRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW iDDoS Entry Created Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.111

Field Name : customGtpInfoEventRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom GTP Info Records Sent Failure
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.110

Field Name : customGtpInfoEventRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom GTP Info Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.109

Field Name : customGtpDenyEventRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom GTP Deny Records Sent Failure
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.108

Field Name : customGtpDenyEventRecordsSent

Field Type : CounterBasedGauge64
Field Status : current
Description : Custom GTP Deny Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.107

Field Name : customGtpUTunnelEventRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom GTP U Tunnel Records Sent Failure
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.106

Field Name : customGtpUTunnelEventRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom GTP U Tunnel Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.105

Field Name : customGtpCTunnelEventRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom GTP C Tunnel Records Sent Failure
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.104

Field Name : customGtpCTunnelEventRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom GTP C Tunnel Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.103

Field Name : reducedLogsByDestination
Field Type : CounterBasedGauge64
Field Status : current
Description : Reduced Logs by Destination Protocol and Port
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.102

Field Name : customPortBatchingV2DsliteDeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Dslite Port Batch V2 Deletion Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.101

Field Name : customPortBatchingV2DsliteDeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Dslite Port Batch V2 Deletion Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.100

Field Name : customPortBatchingV2Nat64DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat64 Port Batch V2 Deletion Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.99

Field Name : customPortBatchingV2Nat64DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat64 Port Batch V2 Deletion Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.98

Field Name : customPortBatchingV2Nat44DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat44 Port Batch V2 Deletion Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.97

Field Name : customPortBatchingV2Nat44DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat44 Port Batch V2 Deletion Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.96

Field Name : customPortBatchingV2DsliteCreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Dslite Port Batch V2 Creation Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.95

Field Name : customPortBatchingV2DsliteCreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Dslite Port Batch V2 Creation Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.94

Field Name : customPortBatchingV2Nat64CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat64 Port Batch V2 Creation Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.93

Field Name : customPortBatchingV2Nat64CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat64 Port Batch V2 Creation Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.92

Field Name : customPortBatchingV2Nat44CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat44 Port Batch V2 Creation Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.91

Field Name : customPortBatchingV2Nat44CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat44 Port Batch V2 Creation Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.90

Field Name : customPortBatchingDsliteDeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Dslite Port Batch Deletion Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.89

Field Name : customPortBatchingDsliteDeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current

Description : Custom Dslite Port Batch Deletion Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.88

Field Name : customPortBatchingNat64DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat64 Port Batch Deletion Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.87

Field Name : customPortBatchingNat64DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat64 Port Batch Deletion Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.86

Field Name : customPortBatchingNat44DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat44 Port Batch Deletion Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.85

Field Name : customPortBatchingNat44DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat44 Port Batch Deletion Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.84

Field Name : customPortBatchingDsliteCreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Dslite Port Batch Creation Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.83

Field Name : customPortBatchingDsliteCreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Dslite Port Batch Creation Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.82

Field Name : customPortBatchingNat64CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat64 Port Batch Creation Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.81

Field Name : customPortBatchingNat64CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat64 Port Batch Creation Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.80

Field Name : customPortBatchingNat44CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat44 Port Batch Creation Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.79

Field Name : customPortBatchingNat44CreationRecordsSent

Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat44 Port Batch Creation Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.78

Field Name : customPortMappingDsliteDeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Dslite Port Map Deletion Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.77

Field Name : customPortMappingDsliteDeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Dslite Port Map Deletion Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.76

Field Name : customPortMappingNat64DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat64 Port Map Deletion Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.75

Field Name : customPortMappingNat64DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat64 Port Map Deletion Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.74

Field Name : customPortMappingNat44DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat44 Port Map Deletion Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.73

Field Name : customPortMappingNat44DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat44 Port Map Deletion Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.72

Field Name : customPortMappingDsliteCreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Dslite Port Map Creation Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.71

Field Name : customPortMappingDsliteCreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Dslite Port Map Creation Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.70

Field Name : customPortMappingNat64CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat64 Port Map Creation Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.69

Field Name : customPortMappingNat64CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat64 Port Map Creation Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.68

Field Name : customPortMappingNat44CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat44 Port Map Creation Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.67

Field Name : customPortMappingNat44CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat44 Port Map Creation Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.66

Field Name : customDenyResetEventFw6RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW6 Deny/Reset Event Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.65

Field Name : customDenyResetEventFw6RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW6 Deny/Reset Event Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.64

Field Name : customDenyResetEventFw4RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW4 Deny/Reset Event Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.63

Field Name : customDenyResetEventFw4RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW4 Deny/Reset Event Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.62

Field Name : customSessionEventFw6DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW6 Session Deletion Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.61

Field Name : customSessionEventFw6DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW6 Session Deletion Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.60

Field Name : customSessionEventFw4DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current

Description : Custom FW4 Session Deletion Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.59

Field Name : customSessionEventFw4DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW4 Session Deletion Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.58

Field Name : customSessionEventFw6CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW6 Session Creation Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.57

Field Name : customSessionEventFw6CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW6 Session Creation Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.56

Field Name : customSessionEventFw4CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW4 Session Creation Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.55

Field Name : customSessionEventFw4CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW4 Session Creation Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.54

Field Name : customSessionEventDsliteDeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Dslite Session Deletion Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.53

Field Name : customSessionEventDsliteDeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Dslite Session Deletion Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.52

Field Name : customSessionEventNat64DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat64 Session Deletion Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.51

Field Name : customSessionEventNat64DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat64 Session Deletion Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.50

Field Name : customSessionEventNat44DeletionRecordsSentFailure

Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat44 Session Deletion Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.49

Field Name : customSessionEventNat44DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat44 Session Deletion Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.48

Field Name : customSessionEventDsliteCreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Dslite Session Creation Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.47

Field Name : customSessionEventDsliteCreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Dslite Session Creation Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.46

Field Name : customSessionEventNat64CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat64 Session Creation Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.45

Field Name : customSessionEventNat64CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat64 Session Creation Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.44

Field Name : customSessionEventNat44CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat44 Session Creation Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.43

Field Name : customSessionEventNat44CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat44 Session Creation Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.42

Field Name : portBatchingV2DsliteRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batching V2 Dslite Records Falied
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.41

Field Name : portBatchingV2DsliteRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batching V2 Dslite Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.40

Field Name : portBatchingV2Nat64RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batching V2 Nat64 Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.39

Field Name : portBatchingV2Nat64RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batching V2 Nat64 Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.38

Field Name : portBatchingV2Nat44RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batching V2 Nat44 Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.37

Field Name : portBatchingV2Nat44RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batching V2 Nat44 Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.36

Field Name : portBatchingDsliteRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batching Dslite Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.35

Field Name : portBatchingDsliteRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batching Dslite Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.34

Field Name : portBatchingNat64RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batching Nat64 Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.33

Field Name : portBatchingNat64RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batching Nat64 Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.32

Field Name : portBatchingNat44RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batching Nat44 Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.31

Field Name : portBatchingNat44RecordsSent
Field Type : CounterBasedGauge64
Field Status : current

Description : Port Batching Nat44 Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.30

Field Name : netflowV5ExtRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Netflow v5 Ext Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.29

Field Name : netflowV5ExtRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Netflow v5 Ext Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.28

Field Name : netflowV5RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Netflow v5 Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.27

Field Name : netflowV5RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Netflow v5 Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.26

Field Name : portMappingDsliteRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Mapping Dslite Event Records failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.25

Field Name : portMappingDsliteRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Mapping Dslite Event Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.24

Field Name : portMappingNat64RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Mapping Nat64 Event Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.23

Field Name : portMappingNat64RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Mapping Nat64 Event Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.22

Field Name : portMappingNat44RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Mapping Nat44 Event Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.21

Field Name : portMappingNat44RecordsSent

Field Type : CounterBasedGauge64
Field Status : current
Description : Port Mapping Nat44 Event Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.20

Field Name : sessionEventFw6RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : FW6 Session Event Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.19

Field Name : sessionEventFw6RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : FW6 Session Event Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.18

Field Name : sessionEventFw4RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : FW4 Session Event Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.17

Field Name : sessionEventFw4RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : FW4 Session Event Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.16

Field Name : sessionEventDsliteRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Dslite Session Event Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.15

Field Name : sessionEventDsliteRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Dslite Session Event Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.14

Field Name : sessionEventNat64RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Nat64 Session Event Records Falied
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.13

Field Name : sessionEventNat64RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Nat64 Session Event Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.12

Field Name : sessionEventNat44RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Nat44 Session Event Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.11

Field Name : sessionEventNat44RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Nat44 Session Event Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.10

Field Name : dsliteRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Dslite Flow Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.9

Field Name : dsliteRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Dslite Flow Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.8

Field Name : nat64RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Flow Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.7

Field Name : nat64RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Flow Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.6

Field Name : nat44RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 Flow Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.5

Field Name : nat44RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 Flow Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.4

Field Name : bytesSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sent Bytes Count
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.3

Field Name : packetsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sent Packets Count
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.2

Field Name : netflowMonitorName
Field Type : String
Field Status : current

Description : Name of netflow monitor
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.1

Field Name : templatesRemovedFromDelq
Field Type : CounterBasedGauge64
Field Status : current
Description : Netflow Templates Removed From Delete Queue
OID : 1.3.6.1.4.1.22610.2.4.10.126.3.1.1.8

Field Name : templatesAddedToDelq
Field Type : CounterBasedGauge64
Field Status : current
Description : Netflow Templates Added To Delete Queue
OID : 1.3.6.1.4.1.22610.2.4.10.126.3.1.1.7

Field Name : templateDropOutOfMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : Netflow Templates Dropped OOM
OID : 1.3.6.1.4.1.22610.2.4.10.126.3.1.1.6

Field Name : templateDropExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Netflow Templates Dropped Maximum Limit Reached
OID : 1.3.6.1.4.1.22610.2.4.10.126.3.1.1.5

Field Name : v10TemplatesDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Netflow v10(IPFIX) Templates Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.126.3.1.1.4

Field Name : v10TemplatesCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Netflow v10(IPFIX) Templates Created
OID : 1.3.6.1.4.1.22610.2.4.10.126.3.1.1.3

Field Name : v9TemplatesDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Netflow v9 Templates Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.126.3.1.1.2

Field Name : v9TemplatesCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Netflow v9 Templates Created
OID : 1.3.6.1.4.1.22610.2.4.10.126.3.1.1.1

Field Name : overlayTunnelVtepSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1

Field Name : overlayTunnelVtepSEntry

Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1

Field Name : lifUnInitRx
Field Type : CounterBasedGauge64
Field Status : current
Description : Lif uninitialized packets in
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.38

Field Name : fragDropPktsTx
Field Type : CounterBasedGauge64
Field Status : current
Description : Frag dropped packets out
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.37

Field Name : badInnerIpv6LenRx
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad inner ipv6 packet len
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.36

Field Name : badInnerIpv4LenRx
Field Type : CounterBasedGauge64
Field Status : current
Description : bad inner ipv4 packet len
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.35

Field Name : reassembledPktsRx
Field Type : CounterBasedGauge64
Field Status : current
Description : Reassembled packets in
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.34

Field Name : fragPktsTx
Field Type : CounterBasedGauge64
Field Status : current
Description : Frag packets out
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.33

Field Name : dot1qPktsRx
Field Type : CounterBasedGauge64
Field Status : current
Description : Dot1q packets in
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.32

Field Name : largePktsRx
Field Type : CounterBasedGauge64
Field Status : current
Description : Too large packets in
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.31

Field Name : droppedPktsTx
Field Type : CounterBasedGauge64
Field Status : current
Description : Dropped packets out
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.30

Field Name : mcastPktTx
Field Type : CounterBasedGauge64
Field Status : current
Description : Multicast packets out
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.29

Field Name : bcastPktTx
Field Type : CounterBasedGauge64
Field Status : current
Description : Broadcast packets out
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.28

Field Name : unicastPktTx
Field Type : CounterBasedGauge64
Field Status : current
Description : Unicast packets out
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.27

Field Name : totalBytesTx
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet bytes out
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.26

Field Name : pktsOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets out
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.25

Field Name : requeuePktsIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Requeued packets in
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.24

Field Name : badChksumPksRx
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad checksum in received packets
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.23

Field Name : encapMissPktsRx
Field Type : CounterBasedGauge64
Field Status : current
Description : Encap missed in received packets
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.22

Field Name : droppedPktRx
Field Type : CounterBasedGauge64
Field Status : current
Description : Dropped received packets
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.21

Field Name : mcastPktRx
Field Type : CounterBasedGauge64
Field Status : current

Description : Total multicast packets in
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.20

Field Name : bcastPktRx
Field Type : CounterBasedGauge64
Field Status : current
Description : Total broadcast packets in
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.19

Field Name : unicastPktRx
Field Type : CounterBasedGauge64
Field Status : current
Description : Total unicast packets in
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.18

Field Name : totalBytesRx
Field Type : CounterBasedGauge64
Field Status : current
Description : Total packet bytes in
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.17

Field Name : totalPktsRx
Field Type : CounterBasedGauge64
Field Status : current
Description : Total packets out
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.16

Field Name : unhandledPktTx
Field Type : CounterBasedGauge64
Field Status : current
Description : Unhandled packets out
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.15

Field Name : unhandledPktRx
Field Type : CounterBasedGauge64
Field Status : current
Description : Unhandled packets in
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.14

Field Name : unknownVtepRx
Field Type : CounterBasedGauge64
Field Status : current
Description : Vtep Unkown rx
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.13

Field Name : unknownVtepTx
Field Type : CounterBasedGauge64
Field Status : current
Description : Vtep unknown tx
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.12

Field Name : invalidLifTx
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid Lif pkts out
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.11

Field Name : invalidLifRx

Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid Lif pkts in
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.10

Field Name : vtepHostLearnError
Field Type : CounterBasedGauge64
Field Status : current
Description : Host learn error
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.9

Field Name : vtepHostLearned
Field Type : CounterBasedGauge64
Field Status : current
Description : Hosts learned
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.8

Field Name : arpReqSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Arp request sent
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.7

Field Name : unknownEncapTxPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : Encap miss tx pkts
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.6

Field Name : unknownEncapRxPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : Encap miss rx pkts
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.5

Field Name : encapUnresolvedCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Encap unresolved failures
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.4

Field Name : floodedPktCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Flooded packet count
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.3

Field Name : cfgErrCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Config errors
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.2

Field Name : id
Field Type : INTEGER
Field Status : current
Description : VTEP Identifier
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.1

Field Name : ruleSetSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.138.1.1

Field Name : ruleSetSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.138.1.1.1

Field Name : reset
Field Type : CounterBasedGauge64
Field Status : current
Description : Reset counter
OID : 1.3.6.1.4.1.22610.2.4.10.138.1.1.1.5

Field Name : deny
Field Type : CounterBasedGauge64
Field Status : current
Description : Denied counter
OID : 1.3.6.1.4.1.22610.2.4.10.138.1.1.1.4

Field Name : permit
Field Type : CounterBasedGauge64
Field Status : current
Description : Permitted counter
OID : 1.3.6.1.4.1.22610.2.4.10.138.1.1.1.3

Field Name : unmatchedDrops
Field Type : CounterBasedGauge64
Field Status : current
Description : Unmatched drops counter
OID : 1.3.6.1.4.1.22610.2.4.10.138.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Rule set name
OID : 1.3.6.1.4.1.22610.2.4.10.138.1.1.1.1

Field Name : tcamCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : TCAM Flow Count
OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.20

Field Name : tcamFree
Field Type : CounterBasedGauge64
Field Status : current
Description : TCAM Flows Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.19

Field Name : tcamCreate
Field Type : CounterBasedGauge64
Field Status : current

Description : TCAM Flows Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.18

Field Name : entryInvalidateServerDown
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Invalidate due to server down
OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.17

Field Name : entryForceHwInvalidate
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Force HW Invalidate
OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.16

Field Name : entryAgeOutInvalidDst
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out - invalid dst
OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.15

Field Name : entryAgeOutTcpRst
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out - TCP RST
OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.14

Field Name : entryAgeOutTcpFin
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out - TCP FIN
OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.13

Field Name : entryAgeOutIdle
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out - idle timeout
OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.12

Field Name : entryAgeOut
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out
OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.11

Field Name : entryCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Count
OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.10

Field Name : entryFreeNoSwEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Freed - no software entry
OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.9

Field Name : entryFreeNoConn

Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Freed - no matched conn
OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.8

Field Name : entryFreeNoHwProg
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Freed - no HW prog
OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.7

Field Name : entryFreeOppEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Freed - opposite tuple entry aged-out
OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.6

Field Name : entryFree
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.5

Field Name : entryCreateFailMaxEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Creation Failed - max entries exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.4

Field Name : entryCreateFailServerDown
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Creation Failed - server down
OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.3

Field Name : entryCreateFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Creation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.2

Field Name : entryCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.1

Field Name : ddosPacketDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : DDOS Packet Drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.31.1.8

Field Name : ddosEntryRemoveFromBgpFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : DDOS entry BGP remove failures
OID : 1.3.6.1.4.1.22610.2.4.10.139.31.1.7

Field Name : ddosEntryAddToBgpFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : DDoS Entry BGP add failures
OID : 1.3.6.1.4.1.22610.2.4.10.139.31.1.6

Field Name : ddosEntryRemovedFromBgp
Field Type : CounterBasedGauge64
Field Status : current
Description : DDoS Entry Removed from BGP
OID : 1.3.6.1.4.1.22610.2.4.10.139.31.1.5

Field Name : ddosEntryAddedToBgp
Field Type : CounterBasedGauge64
Field Status : current
Description : DDoS Entry added to BGP
OID : 1.3.6.1.4.1.22610.2.4.10.139.31.1.4

Field Name : ddosEntryRemoved
Field Type : CounterBasedGauge64
Field Status : current
Description : DDOS entry removed
OID : 1.3.6.1.4.1.22610.2.4.10.139.31.1.3

Field Name : ddosEntryAdded
Field Type : CounterBasedGauge64
Field Status : current
Description : DDOS entry added
OID : 1.3.6.1.4.1.22610.2.4.10.139.31.1.2

Field Name : ddosEntriesTooMany
Field Type : CounterBasedGauge64
Field Status : current
Description : Too many DDOS entries
OID : 1.3.6.1.4.1.22610.2.4.10.139.31.1.1

Field Name : connSetupFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN cookie connection setup failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.19.3.1.4

Field Name : verificationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN cookie verification failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.19.3.1.3

Field Name : verificationPassed
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN cookie verification passed
OID : 1.3.6.1.4.1.22610.2.4.10.139.19.3.1.2

Field Name : synAckSent
Field Type : CounterBasedGauge64
Field Status : current

Description : SYN cookie SYN ACK sent
OID : 1.3.6.1.4.1.22610.2.4.10.139.19.3.1.1

Field Name : radiusInterCardDupRedir
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS packet dropped as redirected by other blade (SO)
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.44

Field Name : radiusPacketsDroppedNotLo
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS packets dropped dest not loopback (SO)
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.43

Field Name : radiusPacketsProcessLocal
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS packets processed locally without redirection (SO)
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.42

Field Name : radiusPacketsRedirectFailDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS packets dropped due to redirect failure (SO)
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.41

Field Name : radiusPacketsRedirected
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS packets redirected (SO)
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.40

Field Name : interCardMsgFailDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Inter-Card Message Fail Drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.39

Field Name : haSyncNoKeyVapDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Record Sync No key dropped
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.38

Field Name : ipAddRaceDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Radius Entry IP Add Race Drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.37

Field Name : ipMismatchDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : Radius Entry IP Mismatch Delete
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.36

Field Name : acctOnDupRequest

Field Type : CounterBasedGauge64
Field Status : current
Description : Duplicate RADIUS Acct On Request
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.35

Field Name : acctOnFiltersFull
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Acct On Request Ignored(Filters Full)
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.34

Field Name : haSyncDeleteRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Record Sync Delete Received
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.33

Field Name : haSyncCreateRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Record Sync Create Received
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.32

Field Name : haSyncDeleteSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Record Sync Delete Sent
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.31

Field Name : haSyncCreateSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Record Sync Create Sent
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.30

Field Name : memFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Memory Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.29

Field Name : memAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Memory Allocation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.28

Field Name : memAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Memory Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.27

Field Name : smpDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS SMP Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.26

Field Name : smpInRml
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS SMP in RML
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.25

Field Name : smpCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS SMP Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.24

Field Name : smpMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS SMP Memory Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.23

Field Name : smpMemAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS SMP Memory Allocation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.22

Field Name : smpMemAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS SMP Memory Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.21

Field Name : invalidKey
Field Type : CounterBasedGauge64
Field Status : current
Description : Radius Request has Invalid Key Field
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.15

Field Name : ipv6PrefixLengthMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Framed IPV6 Prefix Length Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.14

Field Name : haStandbyDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Standby Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.13

Field Name : secretNotConfiguredDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Secret Not Configured Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.12

Field Name : radiusTableFull
Field Type : TABLE
Field Status : current

Description : RADIUS Request Dropped (Table Full)
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.11

Field Name : requestIgnored
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request Table Full Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.10

Field Name : requestMalformedDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request Malformed Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.9

Field Name : requestNoKeyVapDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request No Key Attribute Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.8

Field Name : requestBadSecretDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request Bad Secret Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.7

Field Name : radiusRequestDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request Dropped (Malformed Packet)
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.6

Field Name : radiusRequestReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request Received
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.5

Field Name : customReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom attribute Received
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.4

Field Name : imsiReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : IMSI Received
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.3

Field Name : imeiReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : IMEI Received
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.2

Field Name : msisdnReceived

Field Type : CounterBasedGauge64
Field Status : current
Description : MSISDN Received
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.1

Field Name : outsideWindow
Field Type : CounterBasedGauge64
Field Status : current
Description : packet dropped counter for outside of tcp window
OID : 1.3.6.1.4.1.22610.2.4.10.139.12.1.1

Field Name : helperFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.40

Field Name : sipHelperFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Conn Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.39

Field Name : sipHelperDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Conn Already Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.38

Field Name : sipHelperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Conn Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.37

Field Name : helperFound
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Conn Found
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.36

Field Name : rtpEim
Field Type : CounterBasedGauge64
Field Status : current
Description : RTP EIM
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.35

Field Name : rtpAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : RTP Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.34

Field Name : rtpNew
Field Type : CounterBasedGauge64
Field Status : current
Description : RTP Alloc
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.33

Field Name : contactEimSet
Field Type : CounterBasedGauge64
Field Status : current
Description : Contact EIM Set
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.32

Field Name : contactEim
Field Type : CounterBasedGauge64
Field Status : current
Description : Contact EIM
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.31

Field Name : contactAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Contact Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.30

Field Name : contactNew
Field Type : CounterBasedGauge64
Field Status : current
Description : Contact Alloc
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.29

Field Name : contactPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Contact Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.28

Field Name : contactPortSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Contact Port Success
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.27

Field Name : contactPortNoOp
Field Type : CounterBasedGauge64
Field Status : current
Description : Contact Port No Op
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.26

Field Name : rtcpPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : RTCP Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.25

Field Name : rtpPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : RTP Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.24

Field Name : rtpRtcpPortSuccess
Field Type : CounterBasedGauge64
Field Status : current

Description : RTP RTCP Port Success
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.23

Field Name : rtpPortNoOp
Field Type : CounterBasedGauge64
Field Status : current
Description : RTP Port No Op
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.22

Field Name : sdpError
Field Type : CounterBasedGauge64
Field Status : current
Description : SDP Process Error
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.21

Field Name : contactError
Field Type : CounterBasedGauge64
Field Status : current
Description : Contact Process Error
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.20

Field Name : keepAlive
Field Type : CounterBasedGauge64
Field Status : current
Description : Keep Alive
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.19

Field Name : parseError
Field Type : CounterBasedGauge64
Field Status : current
Description : Message Parse Error
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.18

Field Name : methodUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : Method Unknown
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.17

Field Name : methodUpdate
Field Type : CounterBasedGauge64
Field Status : current
Description : Method UPDATE
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.16

Field Name : methodMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : Method MESSAGE
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.15

Field Name : methodRefer
Field Type : CounterBasedGauge64
Field Status : current
Description : Method REFER
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.14

Field Name : methodInfo

Field Type : CounterBasedGauge64
Field Status : current
Description : Method INFO
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.13

Field Name : methodPublish
Field Type : CounterBasedGauge64
Field Status : current
Description : Method PUBLISH
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.12

Field Name : methodNotify
Field Type : CounterBasedGauge64
Field Status : current
Description : Method NOTIFY
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.11

Field Name : methodSubscribe
Field Type : CounterBasedGauge64
Field Status : current
Description : Method SUBSCRIBE
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.10

Field Name : methodPrack
Field Type : CounterBasedGauge64
Field Status : current
Description : Method PRACK
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.9

Field Name : methodOptions
Field Type : CounterBasedGauge64
Field Status : current
Description : Method OPTIONS
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.8

Field Name : methodBye
Field Type : CounterBasedGauge64
Field Status : current
Description : Method BYE
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.7

Field Name : methodCancel
Field Type : CounterBasedGauge64
Field Status : current
Description : Method CANCEL
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.6

Field Name : methodAck
Field Type : CounterBasedGauge64
Field Status : current
Description : Method ACK
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.5

Field Name : methodInvite
Field Type : CounterBasedGauge64
Field Status : current
Description : Method INVITE
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.4

Field Name : methodRegister
Field Type : CounterBasedGauge64
Field Status : current
Description : Method REGISTER
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.3

Field Name : statResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Received
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.2

Field Name : statRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Received
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.1

Field Name : controlFreeSmpAppTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Control Free SMP App Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.29

Field Name : controlFreeNoSmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Control Free No SMP
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.28

Field Name : controlFreeNoExt
Field Type : CounterBasedGauge64
Field Status : current
Description : Control Free No Ext
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.27

Field Name : controlFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Control Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.26

Field Name : greFreeSmpAppTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Free SMP App Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.25

Field Name : greFreeNoSmp
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Free No SMP
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.24

Field Name : greFreeNoExt
Field Type : CounterBasedGauge64
Field Status : current

Description : GRE Free No Ext
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.23

Field Name : greConnAlreadyExists
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Conn Already Exists
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.22

Field Name : greNoControlConn
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE No Control Conn
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.21

Field Name : greNoRevRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE No Rev Route
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.20

Field Name : greNoFwdRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE No Fwd Route
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.19

Field Name : greConnExtCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Conn Ext Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.18

Field Name : greConnCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Conn Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.17

Field Name : smpAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Session Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.16

Field Name : smpSessionsFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.15

Field Name : smpSessionsCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.14

Field Name : smpClientCallIdMismatch

Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Client Call ID Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.13

Field Name : smpAppTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP App Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.12

Field Name : callReplyExtExtAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Request Ext Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.11

Field Name : callReplyRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Reply Retransmit
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.10

Field Name : callReplyCallIdUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Reply Unknown Client Call ID
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.9

Field Name : callReqExtAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Request Ext Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.8

Field Name : callReqNew
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Request New
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.7

Field Name : callReqRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Request Retransmit
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.6

Field Name : greSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.5

Field Name : greSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.4

Field Name : callReplyPnsCallIdMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Call ID Mismatch on Call Reply
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.3

Field Name : callReqPnsCallIdMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Call ID Mismatch on Call Request
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.2

Field Name : callsEstablished
Field Type : CounterBasedGauge64
Field Status : current
Description : Calls Established
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.1

Field Name : haDataSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Data Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.35

Field Name : haControlSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Control Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.34

Field Name : haControlExtCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Control Extension Creation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.33

Field Name : rstpDataSessionFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Freed Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.32

Field Name : rstpDataSessionCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Created Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.31

Field Name : transportNotFoundOnDataFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Not Found Data
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.30

Field Name : transportRetryLookupOnDataFree
Field Type : CounterBasedGauge64
Field Status : current

Description : Transport Retry Lookup Data
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.29

Field Name : transportDoubleReleaseFromData
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Double Release Data
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.28

Field Name : transportReleasedFromData
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Released Data
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.27

Field Name : transportAcquireFailureFromData
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Acquire Failure Data
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.26

Field Name : transportAcquiredFromData
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Acquired Data
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.25

Field Name : transportDoubleReleaseFromControl
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Double Release Control
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.24

Field Name : transportReleasedFromControl
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Released Control
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.23

Field Name : transportAcquireFailureFromControl
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Acquire Failure Control
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.22

Field Name : transportFoundFromPrevControl
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Found From Prev Control
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.21

Field Name : transportAcquiredFromControl
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Acquired Control
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.20

Field Name : transportFreedShadow

Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Freed Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.19

Field Name : transportPutInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Put in Delete Queue
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.18

Field Name : transportAllocFailureShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Alloc Failure Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.17

Field Name : transportCreationRace
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Create Race
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.16

Field Name : transportInsertedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Inserted Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.15

Field Name : transportLinkExtFailureData
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Link to Extension Failure Data
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.14

Field Name : transportLinkExtData
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Link to Extension Data
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.13

Field Name : transportLinkExtFailureControl
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Link to Extension Failure Control
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.12

Field Name : transportExists
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Already Exists
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.11

Field Name : transportAlreadyInExt
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Already in Extension
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.10

Field Name : transportTooMany
Field Type : CounterBasedGauge64
Field Status : current
Description : Too Many Transports for Control Conn
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.9

Field Name : transportRemovedFromExt
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Removed from Extension
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.8

Field Name : transportAddToExt
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Added to Extension
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.7

Field Name : extCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Extension Creation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.6

Field Name : cgnv6StatefullFireWallAlgRtspDataSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.5

Field Name : cgnv6StatefullFireWallAlgRtspDataSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.4

Field Name : transportAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.3

Field Name : transportFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.2

Field Name : transportInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.1

Field Name : helperInRml
Field Type : CounterBasedGauge64
Field Status : current

Description : TFTP Helper Session in Remove List
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.3.1.7

Field Name : helperAlreadyUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Session already used
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.3.1.6

Field Name : helperFreedUnused
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Sessions freed unused
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.3.1.5

Field Name : helperFreedUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Sessions freed used
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.3.1.4

Field Name : helperFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.3.1.3

Field Name : helperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.3.1.2

Field Name : sessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Client Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.3.1.1

Field Name : pasvHelperFreedUnused
Field Type : CounterBasedGauge64
Field Status : current
Description : PASV Helper Freed Unused
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.19

Field Name : pasvHelperFreedUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : PASV Helper Freed Used
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.18

Field Name : portHelperFreedUnused
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT Helper Freed Unused
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.17

Field Name : portHelperFreedUsed

Field Type : CounterBasedGauge64
Field Status : current
Description : PORT Helper Freed Used
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.16

Field Name : pasvHelperAcquireAlreadyUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : PASV Helper Acquire Already Used
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.15

Field Name : pasvHelperAcquireInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : PASV Helper Acquire In Del Queue
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.14

Field Name : portHelperAcquireAlreadyUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT Helper Acquire Already Used
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.13

Field Name : portHelperAcquireInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT Helper Acquire In Del Queue
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.12

Field Name : pasvHelperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : PASV Helper Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.11

Field Name : portHelperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT Helper Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.10

Field Name : smpConnAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Conn Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.9

Field Name : retransmitSanityCheckFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Retransmit Sanity Check Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.8

Field Name : ftpSmpAppTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP App Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.7

Field Name : pasvRetransmits
Field Type : CounterBasedGauge64
Field Status : current
Description : PASV Retransmits
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.6

Field Name : portRetransmits
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT Retransmits
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.5

Field Name : serverEpsvReply
Field Type : CounterBasedGauge64
Field Status : current
Description : EPSV Replies From Server
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.4

Field Name : serverPasvReply
Field Type : CounterBasedGauge64
Field Status : current
Description : PASV Replies From Server
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.3

Field Name : clientEprtRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : EPRT Requests From Client
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.2

Field Name : clientPortRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT Requests From Client
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.1

Field Name : helperInRml
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP Helper Session in Remove List
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.9.1.7

Field Name : helperAlreadyUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP Helper Session already used
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.9.1.6

Field Name : helperFreedUnused
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP Helper Sessions freed unused
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.9.1.5

Field Name : helperFreedUsed
Field Type : CounterBasedGauge64
Field Status : current

Description : ESP Helper Sessions freed used
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.9.1.4

Field Name : helperFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP Helper Sessions Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.9.1.3

Field Name : helperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP Helper Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.9.1.2

Field Name : sessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.9.1.1

Field Name : ratelimitEntryCountParentRadiusUserid
Field Type : CounterBasedGauge64
Field Status : current
Description : The total number of parent rate-limiting entries with the scope RADIUS user ID.
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.28

Field Name : ratelimitEntryCountRadiusUserid
Field Type : CounterBasedGauge64
Field Status : current
Description : The total number of rate-limiting entries with the scope RADIUS user ID.
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.27

Field Name : ratelimitEntryCountParentRadiusUsergroup
Field Type : CounterBasedGauge64
Field Status : current
Description : The total number of parent rate-limiting entries with the scope RADIUS user group.
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.26

Field Name : ratelimitEntryCountRadiusUsergroup
Field Type : CounterBasedGauge64
Field Status : current
Description : The total number of rate-limiting entries with the scope RADIUS user group.
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.25

Field Name : ratelimitEntryCountParentIp
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Parent Rate-limit Entries with Scope IP
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.24

Field Name : ratelimitEntryCountRuleIp
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Rate-limit Entries with Scope IP
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.23

Field Name : ratelimitEntryCountFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Rate-limit Entries Freed Totally
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.22

Field Name : ratelimitEntryCountAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Rate-limit Entries Allocated Totally
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.21

Field Name : ratelimitInfraGenericErrors
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Number of Generic Errors Encountered in Ratelimit Infra
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.20

Field Name : ratelimitEntryCountParentIpv6Prefix
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Parent Rate-limit Entries with Scope IPv6 Prefix
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.19

Field Name : ratelimitEntryCountParentIpv4Prefix
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Parent Rate-limit Entries with Scope IPv4 Prefix
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.18

Field Name : ratelimitEntryCountParentUid
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Parent Rate-limit Entries with Scope Aggregate
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.17

Field Name : ratelimitEntryCountRuleIpv6Prefix
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Rate-limit Entries with Scope IPv6 Prefix
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.16

Field Name : ratelimitEntryCountRuleIpv4Prefix
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Rate-limit Entries with Scope IPv4 Prefix
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.15

Field Name : ratelimitEntryCountSessionId
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Rate-limit Entries with Scope Session ID
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.14

Field Name : ratelimitEntryCountIp6Addr
Field Type : CounterBasedGauge64
Field Status : current

Description : Number of Rate-limit Entries with Scope IPv6 Address
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.13

Field Name : ratelimitEntryCountIpAddr
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Rate-limit Entries with Scope IPv4 Address
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.12

Field Name : ratelimitEntryCountFwRuleUid
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Rate-limit Entries with Scope Aggregate
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.11

Field Name : ratelimitEntryCountT2Key
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Total Rate-limit Entries
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.10

Field Name : ratelimitEntryAllocFailMetricCountGtSupported
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Number of Failures to Create High-Perf Rate-limit Entries Because of Too Many Metrics
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.9

Field Name : ratelimitEntryAllocFailRateTooHigh
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Number of Attempts to Configure Too High Rate Limits
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.8

Field Name : ratelimitHighPerfEntrySecondaryAllocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Number of Failures to Allocate Additional Memory to Existing High-Perf Rate-limit Entries
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.7

Field Name : ratelimitHighPerfEntryAllocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Number of Failures to Create High-Perf Rate-limit Entries Due to Memory Allocation Failures
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.6

Field Name : ratelimitHighAccurateEntryAllocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Number of Failures to Create Highly Accurate Rate-limit Entries Due to Memory Allocation Failures
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.5

Field Name : ratelimitEntryAllocFrmSpmMem
Field Type : CounterBasedGauge64
Field Status : current

Description : Total Number of Rate-limit Entries created using SPM Memory
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.4

Field Name : ratelimitUsedHeapMem
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Heap Memory Used For Rate-limiting Infra in Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.3

Field Name : ratelimitUsedSpmMem
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SPM Memory Used For Rate-limiting Infra in Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.2

Field Name : ratelimitUsedTotalMem
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Memory Used For Rate-limiting (bytes)
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.1

Field Name : revEgressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.94

Field Name : revEgressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.93

Field Name : revEgressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.92

Field Name : revEgressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.91

Field Name : revIngressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.90

Field Name : revIngressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.89

Field Name : revIngressPktSizeRange2

Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.88

Field Name : revIngressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.87

Field Name : fwdEgressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.86

Field Name : fwdEgressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.85

Field Name : fwdEgressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.84

Field Name : fwdEgressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.83

Field Name : fwdIngressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.82

Field Name : fwdIngressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.81

Field Name : fwdIngressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.80

Field Name : fwdIngressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.79

Field Name : revEgressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.78

Field Name : revIngressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.77

Field Name : fwdEgressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.76

Field Name : fwdIngressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.75

Field Name : revEgressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.74

Field Name : revIngressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.73

Field Name : fwdEgressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.72

Field Name : fwdIngressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.71

Field Name : revEgressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.70

Field Name : revIngressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current

Description : Reverse Ingress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.69

Field Name : fwdEgressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.68

Field Name : fwdIngressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.67

Field Name : revEgressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.66

Field Name : revIngressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.65

Field Name : fwdEgressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.64

Field Name : fwdIngressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.63

Field Name : revEgressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.62

Field Name : revIngressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.61

Field Name : fwdEgressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.60

Field Name : fwdIngressBytesUdp

Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.59

Field Name : revEgressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.58

Field Name : revIngressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.57

Field Name : fwdEgressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.56

Field Name : fwdIngressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.55

Field Name : revEgressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.54

Field Name : revIngressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.53

Field Name : fwdEgressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.52

Field Name : fwdIngressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.51

Field Name : revEgressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.50

Field Name : revIngressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.49

Field Name : fwdEgressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.48

Field Name : fwdIngressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.47

Field Name : limitEntryAlreadyAddedToDelQueue
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit Entry Added twice to delete queue
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.148

Field Name : fwInsideClIdMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : fw inside CL ID mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.147

Field Name : fwInsideClTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : fw inside CL TYPE mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.146

Field Name : noFwClassListMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : No FW inside Class-List Match
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.145

Field Name : fwInsideClEntryUpdate
Field Type : CounterBasedGauge64
Field Status : current
Description : fw inside CL entry update is called
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.144

Field Name : fwInsideEntriesRemovedDmzUntagedFirst
Field Type : CounterBasedGauge64
Field Status : current
Description : lookup entries removed, when CL is bound and dmz intf is untagged
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.143

Field Name : fwInsideEntrieAddClBoundFirst
Field Type : CounterBasedGauge64
Field Status : current

Description : lookup entries added when CL is bound first and intf is dmz tagged later
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.142

Field Name : fwInsideEntriesNotAddedNoDmzIntf
Field Type : CounterBasedGauge64
Field Status : current
Description : no dmz interface found and lookup entries are not added
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.141

Field Name : fwInsideClLoad
Field Type : CounterBasedGauge64
Field Status : current
Description : fw inside CL is loaded
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.140

Field Name : fwInsideClResetIdx
Field Type : CounterBasedGauge64
Field Status : current
Description : inside CL index reset
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.139

Field Name : fwInsideRemoveV6Entry
Field Type : CounterBasedGauge64
Field Status : current
Description : FW inside remove v6 lookup entry
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.138

Field Name : fwInsideRemoveV4Entry
Field Type : CounterBasedGauge64
Field Status : current
Description : FW inside remove v4 lookup entry
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.137

Field Name : fwInsideUpdateV6Entry
Field Type : CounterBasedGauge64
Field Status : current
Description : FW inside update v6 lookup entry
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.136

Field Name : fwInsideUpdateV4Entry
Field Type : CounterBasedGauge64
Field Status : current
Description : FW inside update v4 lookup entry
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.135

Field Name : fwInsidePopulateV6Entry
Field Type : CounterBasedGauge64
Field Status : current
Description : FW inside populate v6 lookup entry
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.134

Field Name : fwInsidePopulateV4Entry
Field Type : CounterBasedGauge64
Field Status : current
Description : FW inside populate v4 lookup entry
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.133

Field Name : fwInsideClUnbound

Field Type : CounterBasedGauge64
Field Status : current
Description : FW client CL unbound
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.132

Field Name : fwInsideClBound
Field Type : CounterBasedGauge64
Field Status : current
Description : FW client ips bound via Classlist
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.131

Field Name : fwInsideSubnetEntryDelError
Field Type : CounterBasedGauge64
Field Status : current
Description : FW inside error in entry deletion from brcm
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.130

Field Name : fwInsideSubnetEntryCreationError
Field Type : CounterBasedGauge64
Field Status : current
Description : FW inside error in entry creation in brcm
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.129

Field Name : fwInsideSubnetV6EntriesDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : FW inside v6 subnet entries are deleted from brcm
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.128

Field Name : fwInsideSingleV6EntriesDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : FW inside v6 single ip entries are deleted from brcm
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.127

Field Name : fwInsideSubnetV4EntriesDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : FW inside v4 subnet entries are deleted from brcm
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.126

Field Name : fwInsideSingleV4EntriesDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : FW inside v4 single ip entries are deleted from brcm
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.125

Field Name : fwInsideSubnetV6EntriesAdded
Field Type : CounterBasedGauge64
Field Status : current
Description : FW inside v6 subnet entries are added to brcm
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.124

Field Name : fwInsideSingleV6EntriesAdded
Field Type : CounterBasedGauge64
Field Status : current
Description : FW inside v6 single ip entries are added to brcm
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.123

Field Name : fwInsideSubnetV4EntriesAdded
Field Type : CounterBasedGauge64
Field Status : current
Description : FW inside v4 subnet entries are added to brcm
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.122

Field Name : fwInsideSingleV4EntriesAdded
Field Type : CounterBasedGauge64
Field Status : current
Description : FW inside v4 single ip entries are added to brcm
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.121

Field Name : urpfPktDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : URPF check packet drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.46

Field Name : l2VlanChanged
Field Type : CounterBasedGauge64
Field Status : current
Description : L2 forwarding vlan changed after session create
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.110

Field Name : l2DstInOutSame
Field Type : CounterBasedGauge64
Field Status : current
Description : L2 route to same port as received
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.109

Field Name : noRevL2Dst
Field Type : CounterBasedGauge64
Field Status : current
Description : No Reverse Mac Entry
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.45

Field Name : noFwdL2Dst
Field Type : CounterBasedGauge64
Field Status : current
Description : No Forward Mac Entry
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.44

Field Name : noRevRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : No Reverse Route
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.43

Field Name : noFwdRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : No Forward Route
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.42

Field Name : algDefaultPortDisable
Field Type : CounterBasedGauge64
Field Status : current

Description :
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.41

Field Name : limitEntryPerCpuMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit Entry Memory Freed (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.40

Field Name : limitEntryPerCpuMemAllocationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit Entry Memory Allocation Failed (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.39

Field Name : limitEntryPerCpuMemAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit Entry Memory Allocated (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.38

Field Name : limitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Per Second Limit Exceeded (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.37

Field Name : cpsLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Connections Per Second Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.101

Field Name : totalThroughputLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Throughput Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.100

Field Name : downlinkThroughputLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Downlink Throughput Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.99

Field Name : uplinkThroughputLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Uplink Throughput Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.98

Field Name : totalPpsLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Total PPS Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.97

Field Name : downlinkPpsLimitExceeded

Field Type : CounterBasedGauge64
Field Status : current
Description : Downlink PPS Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.96

Field Name : uplinkPpsLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Uplink PPS Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.95

Field Name : srcSessionLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Concurrent Session Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.36

Field Name : invalidLidDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid Lid Drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.35

Field Name : nonSynPktFwdAllowed
Field Type : CounterBasedGauge64
Field Status : current
Description : Non-SYN pkt forward allowed
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.111

Field Name : undeterminedRuleCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Undetermined rule detected
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.108

Field Name : limitEntryDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit Entry Marked Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.34

Field Name : limitEntryNotInBucket
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit Entry Not in Bucket
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.33

Field Name : limitEntryFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit Entry Found
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.103

Field Name : limitEntryCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit Entry Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.32

Field Name : limitEntryMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit Entry Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.31

Field Name : limitEntryAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit Entry Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.30

Field Name : limitEntryFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit Entry Creation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.29

Field Name : firewallGlobalActiveFullconeSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Active Full-cone sessions
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.28

Field Name : dataSessionFreedShadowLocal
Field Type : CounterBasedGauge64
Field Status : current
Description : Shadow Data Sessions Freed Local
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.107

Field Name : dataSessionFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Shadow Data Sessions Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.27

Field Name : dataSessionCreatedShadowLocal
Field Type : CounterBasedGauge64
Field Status : current
Description : Shadow Data Sessions Created Local
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.106

Field Name : dataSessionCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Shadow Data Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.26

Field Name : haFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.25

Field Name : fullconeExtAdded
Field Type : CounterBasedGauge64
Field Status : current

Description : Fullcone Extension Added
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.24

Field Name : fullconeExtMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Fullcone Extension Memory Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.23

Field Name : fullconeExtMemAllocInitFaulure
Field Type : CounterBasedGauge64
Field Status : current
Description : Fullcone Extension Initialization Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.22

Field Name : fullconeExtMemAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Fullcone Extension Memory Allocate Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.21

Field Name : fullconeExtMemAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Fullcone Extension Memory Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.20

Field Name : fullconeExtTooMany
Field Type : CounterBasedGauge64
Field Status : current
Description : Fullcone Extension Too Many
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.19

Field Name : fullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Full-cone sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.18

Field Name : fullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Full-cone sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.17

Field Name : tcpFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Full-cone sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.16

Field Name : udpFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Full-cone sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.15

Field Name : tcpFullconeCreatedShadow

Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Full-cone sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.14

Field Name : udpFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Full-cone sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.13

Field Name : fullconeOverflowEif
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone Session EIF Overflow
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.12

Field Name : fullconeOverflowEim
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone Session EIM Overflow
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.11

Field Name : fullconeNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone session not found
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.10

Field Name : fullconeRetryLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone session retry look-up
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.9

Field Name : fullconeInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone session found in delete queue
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.8

Field Name : fwDefPktDir
Field Type : CounterBasedGauge64
Field Status : current
Description : default direction assigned to packet irrespective of interface tags
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.120

Field Name : firewallGlobalDynBlistNoActivePolicy
Field Type : CounterBasedGauge64
Field Status : current
Description : Dynamic Blacklist - No Active Policy
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.119

Field Name : firewallGlobalDynBlistVersionMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Dynamic Blacklist - Version Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.118

Field Name : firewallGlobalDynBlistPktRateHigh
Field Type : CounterBasedGauge64
Field Status : current
Description : Dynamic Blacklist - Pkt Rate High
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.116

Field Name : firewallGlobalDynBlistPktRateLow
Field Type : CounterBasedGauge64
Field Status : current
Description : Dynamic Blacklist - Pkt Rate Low
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.115

Field Name : firewallGlobalDynBlistPktDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Dynamic Blacklist - Packet Drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.114

Field Name : firewallGlobalDynBlistSessFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dynamic Blacklist Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.113

Field Name : firewallGlobalDynBlistSessCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Dynamic Blacklist Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.112

Field Name : firewallGlobalDataSessionFreedLocal
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Freed Local
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.105

Field Name : firewallGlobalDataSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.7

Field Name : firewallGlobalDynBlistSessSP
Field Type : CounterBasedGauge64
Field Status : current
Description : Dynamic Blacklist Session (Slowpath)
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.117

Field Name : firewallGlobalDataSessionCreatedLocal
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Created Local
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.104

Field Name : firewallGlobalDataSessionCreated
Field Type : CounterBasedGauge64
Field Status : current

Description : Data Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.6

Field Name : firewallGlobalFullconeCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-Cone Creation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.5

Field Name : firewallGlobalUdpFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Full-cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.4

Field Name : firewallGlobalUdpFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Full-cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.3

Field Name : firewallGlobalTcpFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Full-cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.2

Field Name : firewallGlobalTcpFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Full-cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.1

Field Name : sessionLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.45

Field Name : iddosBlackholeEntryDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : iDDoS IP Entry Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.44

Field Name : iddosBlackholeEntryCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : iDDoS IP Entry Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.43

Field Name : tcpLoggingPortAllocationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Logging Port Allocation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.42

Field Name : tcpLoggingPortFreed

Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Logging Port Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.41

Field Name : tcpLoggingPortAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Logging Port Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.40

Field Name : logTypeSctpInnerProtoFilter
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event Type SCTP Inner Proto Filter
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.37

Field Name : sctpSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Session Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.36

Field Name : sctpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.35

Field Name : httpAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Request Info Allocation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.34

Field Name : httpOutOfOrderDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP out-of-order dropped
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.33

Field Name : logMessageTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Log message too long
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.32

Field Name : tcpLoggingConnDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Logging Conn Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.31

Field Name : tcpLoggingConnCreateFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Logging Conn Create Failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.30

Field Name : tcpLoggingConnEstablished
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Logging Conn Established
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.29

Field Name : addMsgFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Add Message to Buffer Failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.28

Field Name : outOfBuffers
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of Buffers
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.27

Field Name : ipv6FragFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Fragmentation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.26

Field Name : ipv6FragApplied
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Fragmentation Applied
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.25

Field Name : ipv4FragFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Fragmentation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.24

Field Name : ipv4FragApplied
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Fragmentation Applied
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.23

Field Name : templateError
Field Type : CounterBasedGauge64
Field Status : current
Description : Template Error
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.22

Field Name : algOverridePermit
Field Type : CounterBasedGauge64
Field Status : current
Description : Alg Override Permit
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.21

Field Name : dcmsgPermit
Field Type : CounterBasedGauge64
Field Status : current

Description : Dcmsg Permit
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.20

Field Name : httpLoggingInvalidFormat
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Logging Invalid Format Error
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.19

Field Name : httpRequestLogged
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Request Logged
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.18

Field Name : otherSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Other Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.17

Field Name : otherSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Other Session Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.16

Field Name : icmpv6SessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPV6 Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.15

Field Name : icmpv6SessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPV6 Session Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.14

Field Name : icmpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.13

Field Name : icmpSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Session Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.12

Field Name : udpSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Session Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.11

Field Name : udpSessionCreated

Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.10

Field Name : tcpSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Session Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.9

Field Name : tcpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.8

Field Name : logDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.7

Field Name : ruleNotLogged
Field Type : CounterBasedGauge64
Field Status : current
Description : Firewall Rule Not Logged
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.6

Field Name : logTypeSessionOpened
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event Type Session Open
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.5

Field Name : logTypeSessionClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event Type Session Close
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.4

Field Name : logTypeDeny
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event Type Deny
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.3

Field Name : logTypeReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event Type Reset
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.2

Field Name : logMessageSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Packet Sent
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.1

Field Name : logTypeGtpInvalidPorts
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event mismatch of GTP message and ports
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.26

Field Name : logTypeGtpInvalidVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event invalid GTP version
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.25

Field Name : logTypeGtpHdrInvalidPiggyFlag
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event GTP invalid piggyback flag in header
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.24

Field Name : logTypeGtpHdrInvalidSpareBits
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event GTP invalid spare bits in header
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.23

Field Name : logTypeGtpHdrInvalidProtocolFlag
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event GTP Protocol flag in header
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.22

Field Name : logTypeGtpInvalidMessageLength
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event GTP Invalid message length across layers
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.21

Field Name : logTypeGtpRateLimitPeriodic
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event GTP Rate Limit Periodic
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.20

Field Name : logTypeGtpSeqNumMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event GTP Response Sequence number Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.19

Field Name : logTypeGtpNodeRestart
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event GTP SGW/PGW restarted
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.18

Field Name : logTypeGtpInGtpFiltering
Field Type : CounterBasedGauge64
Field Status : current

Description : Log Event GTP in GTP Filtering
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.17

Field Name : logTypeCountryCodeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event GTP Country Code Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.16

Field Name : logTypeGtpRatTypeFiltering
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event GTP RAT Type Filtering
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.15

Field Name : logTypeGtpApnFiltering
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event Type GTP Apn Filtering
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.14

Field Name : logTypeGtpMessageFiltering
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event Type GTP Message Filtering
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.13

Field Name : logTypeMaxMsgLength
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event GTP Message Length Exceeded Max
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.12

Field Name : logTypeOutOfState
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event GTP Out of State Message
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.11

Field Name : logTypeMessageNotSupported
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event GTP Reserved Message Found
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.10

Field Name : logTypeCrosslayerCorrelation
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event GTP Crosslayer Correlation
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.9

Field Name : logTypeEnduserIpSpoofed
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event Type GTP Enduser IP Spoofed
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.8

Field Name : logTypeGtpOutOfStateIe

Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event Type GTP Out of State IE
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.7

Field Name : logTypeGtpOutOfOrderIe
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event Type GTP Out of Order IE V1
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.6

Field Name : logTypeGtpMsisdnFiltering
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event Type GTP MSISDN Filtering
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.5

Field Name : logTypeGtpMandatoryIeInsideGroupedIeMissing
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event Type GTP Mandatory IE Missing Inside Grouped IE
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.4

Field Name : logTypeGtpMandatoryIeMissing
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event Type GTP Mandatory IE Missing
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.3

Field Name : logGtpTypeReservedIePresent
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event Type GTP Reserved IE Present
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.2

Field Name : logTypeGtpInvalidTeid
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event Type GTP Invalid TEID
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.1

Field Name : fwServiceGroupSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.139.4.1.1

Field Name : fwServiceGroupSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.139.4.1.1.1

Field Name : fwServicePeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Service peak connection
OID : 1.3.6.1.4.1.22610.2.4.10.139.4.1.1.1.4

Field Name : fwServerSelectionFailReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Service selection fail reset
OID : 1.3.6.1.4.1.22610.2.4.10.139.4.1.1.1.3

Field Name : fwServerSelectionFailDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Service selection fail drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.4.1.1.1.2

Field Name : fwServiceGroupName
Field Type : String
Field Status : current
Description : FW Service Name
OID : 1.3.6.1.4.1.22610.2.4.10.139.4.1.1.1.1

Field Name : fwServerSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.139.3.1.1

Field Name : fwServerSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.139.3.1.1.1

Field Name : peakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Peak connections
OID : 1.3.6.1.4.1.22610.2.4.10.139.3.1.1.1.6

Field Name : revPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.3.1.1.1.5

Field Name : fwdPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.3.1.1.1.4

Field Name : totalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total connections
OID : 1.3.6.1.4.1.22610.2.4.10.139.3.1.1.1.3

Field Name : fwServerCurrConn
Field Type : CounterBasedGauge64
Field Status : current

Description : Current connections
OID : 1.3.6.1.4.1.22610.2.4.10.139.3.1.1.1.2

Field Name : fwName
Field Type : String
Field Status : current
Description : Server Name
OID : 1.3.6.1.4.1.22610.2.4.10.139.3.1.1.1.1

Field Name : dummy
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry for a10countergen
OID : 1.3.6.1.4.1.22610.2.4.10.139.23.1.1

Field Name : gtpExtHdrIncorrectLength
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Extension header incorrect length
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.133

Field Name : gtpUInnerIpNotPresent
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U inner IP not present
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.132

Field Name : gtpUMonitorForward
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U messages forwarded via monitor mode
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.284

Field Name : gtpMonitorForward
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP messages forwarded via monitor mode
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.126

Field Name : gtpL5ConnCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP L5 conn created
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.124

Field Name : gtpL3ConnDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP L3 conn deleted
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.121

Field Name : gtpStatelessForward
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Stateless Forward
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.120

Field Name : dropGtpBearerNotFoundInResp

Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Bearer not found in response
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.119

Field Name : dropGtpMissingCondIeBearerCtx
Field Type : CounterBasedGauge64
Field Status : current
Description : Missing conditional IE in bearer context Drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.118

Field Name : gtpPathMessageLengthMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-Path Message Length Mismatch Across Layers
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.117

Field Name : gtpUMessageLengthMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Message Length Mismatch Across Layers
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.116

Field Name : dropGtpIpVersionMismatchHoFteid
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP IP version mismatch in Handover SGW FTEID
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.115

Field Name : dropGtpIpVersionMismatchFteid
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP IP version mismatch for req & response FTEIDs
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.114

Field Name : gtpIpVersionV4V6
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP IP versions of V4&V6 in FTEID
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.113

Field Name : gtpNotEnabledOnStandby
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Not Enabled on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.125

Field Name : gtpSmpPathDelSyncRx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP path delete Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.112

Field Name : gtpSmpPathDelSynced
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP path delete Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.111

Field Name : gtpCL5SyncedBeforeL3
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C L5 conn synced before corresponding L3 GTP-C conn
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.110

Field Name : gtpUSyncedBeforeControl
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Tunnel synced before corresponding GTP-C
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.109

Field Name : dropGtpConnCreationStandby
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Conn creation on Standby Drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.108

Field Name : gtpV2CEchoDelSyncRx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C-Echo Delete Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.107

Field Name : gtpV1CEchoDelSyncRx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C-Echo Delete Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.106

Field Name : gtpV0CEchoDelSyncRx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C-Echo Delete Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.105

Field Name : gtpV2CEchoDelSynced
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Echo Delete Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.104

Field Name : gtpV1CEchoDelSynced
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Echo Delete Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.103

Field Name : gtpV0CEchoDelSynced
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Echo Delete Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.102

Field Name : gtpV2CEchoCreateSyncRx
Field Type : CounterBasedGauge64
Field Status : current

Description : GTPv2-C-Echo Create Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.101

Field Name : gtpV1CEchoCreateSyncRx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C-Echo Create Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.100

Field Name : gtpV0CEchoCreateSyncRx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C-Echo Create Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.99

Field Name : gtpV2CEchoCreateSynced
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Echo Create Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.98

Field Name : gtpV1CEchoCreateSynced
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Echo Create Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.97

Field Name : gtpV0CEchoCreateSynced
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Echo Create Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.96

Field Name : gtpDeleteBearerSyncWithPeriodicUpdateOnStandby
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Bearer Deleted on Standy with Periodic Sync
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.95

Field Name : gtpAddBearerSyncWithPeriodicUpdateOnStandby
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Bearer Added on Standby with Periodic Sync
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.94

Field Name : gtpAddBearerSyncNotRxOnStandby
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Add Bearer Sync Not Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.93

Field Name : gtpSmpAdditionalBearerSyncRx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP Additional Bearer Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.123

Field Name : gtpSmpDelBearerSyncRx

Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP Del Bearer Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.92

Field Name : gtpSmpAddBearerSyncRx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP Add Bearer Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.91

Field Name : gtpSmpAdditionalBearerSynced
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP Additional Bearer Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.122

Field Name : gtpSmpDelBearerSynced
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP Del Bearer Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.90

Field Name : gtpSmpAddBearerSynced
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP Add Bearer Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.89

Field Name : gtpHandoverSyncRx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Handover Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.88

Field Name : gtpHandoverSynced
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Handover Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.87

Field Name : gtpV2CDeleteSyncRx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Tunnel Delete Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.86

Field Name : gtpV1CDeleteSyncRx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Tunnel Delete Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.85

Field Name : gtpV0CDeleteSyncRx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Tunnel Delete Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.84

Field Name : gtpV2CCreateSyncRx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Tunnel Create Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.83

Field Name : gtpV1CCreateSyncRx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Tunnel Create Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.82

Field Name : gtpV0CCreateSyncRx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Tunnel Create Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.81

Field Name : gtpV2CDeleteSynced
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Tunnel Delete Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.80

Field Name : gtpV1CDeleteSynced
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Tunnel Delete Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.79

Field Name : gtpV0CDeleteSynced
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Tunnel Delete Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.78

Field Name : gtpV2CCreateSynced
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Tunnel Create Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.77

Field Name : gtpV1CCreateSynced
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Tunnel Create Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.76

Field Name : gtpV0CCreateSynced
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Tunnel Create Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.75

Field Name : gtpUDownlinkEgressBytes
Field Type : CounterBasedGauge64
Field Status : current

Description : GTP-U Downlink Egress Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.74

Field Name : gtpUDownlinkIngressBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Downlink Ingress Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.73

Field Name : gtpUUplinkEgressBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Uplink Egress Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.72

Field Name : gtpUUplinkIngressBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Uplink Ingress Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.71

Field Name : gtpUDownlinkEgressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Downlink Egress Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.70

Field Name : gtpUDownlinkIngressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Downlink Ingress Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.69

Field Name : gtpUUplinkEgressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Uplink Egress Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.68

Field Name : gtpUUplinkIngressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Uplink Ingress Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.67

Field Name : gtpV2CDownlinkEgressBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Downlink Egress Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.66

Field Name : gtpV2CDownlinkIngressBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Downlink Ingress Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.65

Field Name : gtpV2CUplinkEgressBytes

Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Uplink Egress Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.64

Field Name : gtpV2CUplinkIngressBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Uplink Ingress Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.63

Field Name : gtpV2CDownlinkEgressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Downlink Egress Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.62

Field Name : gtpV2CDownlinkIngressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Downlink Ingress Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.61

Field Name : gtpV2CUplinkEgressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Uplink Egress Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.60

Field Name : gtpV2CUplinkIngressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Uplink Ingress Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.59

Field Name : gtpV1CDownlinkEgressBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Downlink Egress Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.58

Field Name : gtpV1CDownlinkIngressBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Downlink Ingress Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.57

Field Name : gtpV1CUplinkEgressBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Uplink Egress Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.56

Field Name : gtpV1CUplinkIngressBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Uplink Ingress Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.55

Field Name : gtpV1CDownlinkEgressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Downlink Egress Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.54

Field Name : gtpV1CDownlinkIngressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Downlink Ingress Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.53

Field Name : gtpV1CUplinkEgressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Uplink Egress Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.52

Field Name : gtpV1CUplinkIngressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Uplink Ingress Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.51

Field Name : gtpV0CDownlinkEgressBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Downlink Egress Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.50

Field Name : gtpV0CDownlinkIngressBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Downlink Ingress Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.49

Field Name : gtpV0CUplinkEgressBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Uplink Egress Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.48

Field Name : gtpV0CUplinkIngressBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Uplink Ingress Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.47

Field Name : gtpV0CDownlinkEgressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Downlink Egress Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.46

Field Name : gtpV0CDownlinkIngressPackets
Field Type : CounterBasedGauge64
Field Status : current

Description : GTPv0-C Downlink Ingress Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.45

Field Name : gtpV0CUplinkEgressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Uplink Egress Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.44

Field Name : gtpV0CUplinkIngressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Uplink Ingress Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.43

Field Name : gtpPathmFailConnCreateSlow
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP path packet failed while creating L4-session in slowpath
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.361

Field Name : gtpUFailConnCreateSlow
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U packet failed while creating L4-session in slowpath
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.360

Field Name : gtpCFailConnCreateSlow
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C packet failed creating L4-session in slowpath
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.359

Field Name : bladeGtpSmpSigCheckFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP signature check Failed on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.358

Field Name : gtpSmpSigCheckFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP signature check Failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.357

Field Name : bladeGtpUSmpSigCheckFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U SMP signature check Failed on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.356

Field Name : gtpUSmpSigCheckFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP signature check Failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.355

Field Name : bladeGtpCSmpSigCheckFailed

Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SMP signature check Failed on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.354

Field Name : gtpCSmpSigCheckFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SMP signature check Failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.353

Field Name : gtpCMatchCSmpWithHoFlag
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C match C-smp with HO flag
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.352

Field Name : gtpCMatchCSmpWithDelFlag
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C match C-smp with deletion flag
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.351

Field Name : gtpSyncRxDelNoSuchEchoSession
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Del ECHO-Conn not Found
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.350

Field Name : gtpSyncRxDelNoSuchUSession
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Del U-Conn not Found
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.349

Field Name : gtpSyncRxDelNoSuchCSession
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Del C-Conn not Found
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.348

Field Name : gtpSyncTxDeleteEchoCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync delete Session ECHO sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.347

Field Name : gtpSyncTxDeleteUCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync delete Session GTP-U sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.346

Field Name : gtpSyncTxDeleteCCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync delete Session GTP-C sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.345

Field Name : gtpSyncTxCreateEchoCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync create Session ECHO sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.344

Field Name : gtpSyncTxCreateUCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync create Session GTP-U sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.343

Field Name : gtpSyncTxCreateCCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync create Session GTP-C sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.342

Field Name : gtpSyncRxCreateEchoCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync create Session ECHO Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.341

Field Name : gtpSyncRxCreateUCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync create Session GTP-U Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.340

Field Name : gtpSyncRxCreateCCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync create Session GTP-C Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.339

Field Name : gtpSyncRxDelEchoCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Del Session ECHO Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.338

Field Name : gtpSyncRxDelUCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Del Session GTP-U Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.337

Field Name : gtpSyncRxDelCCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Del Session GTP-C Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.336

Field Name : gtpQueryPktRxCounterGtpEcho
Field Type : CounterBasedGauge64
Field Status : current

Description : Conn Query GTP-ECHO recv counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.335

Field Name : gtpQueryPktRxCounterGtpU
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Query GTP-U recv counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.334

Field Name : gtpQueryPktRxCounterGtpC
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Query GTP-C recv counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.333

Field Name : gtpSyncTxFwDropSessionCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync FW gtp Create Session Sent dropped
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.332

Field Name : gtpSyncTxInterPuNoDataError
Field Type : CounterBasedGauge64
Field Status : current
Description : send of inter-pu msg failed with no data to pack
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.331

Field Name : gtpSyncTxInterPuNoMsgHdrError
Field Type : CounterBasedGauge64
Field Status : current
Description : send of inter-pu msg failed as msg header ext failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.330

Field Name : gtpSyncTxInterPuNoUgError
Field Type : CounterBasedGauge64
Field Status : current
Description : send of inter-pu msg failed with no user group error
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.329

Field Name : gtpSyncTxInterPuNoGtpUExt
Field Type : CounterBasedGauge64
Field Status : current
Description : send of inter-pu msg failed with no GTP-U ext
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.328

Field Name : gtpSyncTxInterPuNoVnpError
Field Type : CounterBasedGauge64
Field Status : current
Description : send of inter-pu msg failed with no vnp error
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.327

Field Name : gtpQueryPktTxCounterGtpEcho
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Query GTP-ECHO sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.326

Field Name : gtpQueryPktTxCounterGtpU

Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Query GTP-U sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.325

Field Name : gtpQueryPktTxCounterGtpC
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Query GTP-C sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.324

Field Name : gtpSyncRxCreateExtBitCounterInterPu
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Create with Ext Received with inter-pu comm counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.323

Field Name : gtpCConnWithNoDst
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C created on active with no dst
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.322

Field Name : gtpRevTupleDstUpdated
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP REV tuple updated with dst
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.321

Field Name : gtpFwdTupleDstUpdated
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP FWD tuple updated with dst
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.320

Field Name : bladeGtpInterPuNoRspToQuery
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu No response to query on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.319

Field Name : gtpInterPuNoRspToQuery
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu No response to query
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.318

Field Name : bladeGtpInterPuUDeleteError
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-delete rx drop with error PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.317

Field Name : gtpInterPuUDeleteError
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-delete rx drop with error
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.316

Field Name : bladeGtpInterPuUCreateError
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-create rx drop with error PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.315

Field Name : gtpInterPuUCreateError
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-create rx drop with error
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.314

Field Name : bladeGtpInterPuUDeleteDropNoSmp
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-delete rx drop no smp PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.313

Field Name : gtpInterPuUDeleteDropNoSmp
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-delete rx drop no smp
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.312

Field Name : bladeGtpInterPuUCreateDropNoSmp
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-create rx drop no smp PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.311

Field Name : gtpInterPuUCreateDropNoSmp
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-create rx drop no smp
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.310

Field Name : bladeGtpInterPuCQueryRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu C-mesg recv on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.309

Field Name : bladeGtpInterPuUDeleteRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-deletion recv on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.308

Field Name : bladeGtpInterPuUCreateRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-creation recv on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.307

Field Name : gtpInterPuCQueryRecv
Field Type : CounterBasedGauge64
Field Status : current

Description : GTP inter-pu C-mesg recv
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.306

Field Name : gtpInterPuUDeleteRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-deletion recv
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.305

Field Name : gtpInterPuUCreateRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-creation recv
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.304

Field Name : bladeGtpInterPuCQueryTxFail
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu C-query tx fail on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.303

Field Name : bladeGtpInterPuUDeleteTxFail
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-deletion tx fail on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.302

Field Name : bladeGtpInterPuUCreateTxFail
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-creation tx fail on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.301

Field Name : gtpInterPuCQueryTxFail
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu C-query tx fail
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.300

Field Name : gtpInterPuUDeleteTxFail
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-deletion tx fail
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.299

Field Name : gtpInterPuUCreateTxFail
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-creation tx fail
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.298

Field Name : bladeGtpInterPuCQuerySent
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu C-query sync sent on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.297

Field Name : bladeGtpInterPuUDeleteSent

Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-deletion sync sent on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.296

Field Name : bladeGtpInterPuUCreateSent
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-creation sync sent on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.295

Field Name : gtpInterPuCQuerySent
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu C-query sync sent
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.294

Field Name : gtpInterPuUDeleteSent
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-deletion sync sent
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.293

Field Name : gtpInterPuUCreateSent
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-creation sync sent
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.292

Field Name : bladeGtpSmpNotFoundInterPu
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP smp not found during inter-pu comm on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.291

Field Name : gtpSmpNotFoundInterPu
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP smp not found during inter-pu comm
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.290

Field Name : gtpSyncNewConnCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C sync new conn create
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.289

Field Name : gtpInfoExtNotPacked
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C info not packed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.288

Field Name : bladeGtpSmpNoActionWithUCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SMP no action with u-create at inter-pu sync on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.287

Field Name : gtpSmpNoActionWithUCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SMP no action with u-create at inter-pu sync
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.286

Field Name : bladeGtpSmpSessionCountCheckFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U session count is not in range of 0-11 in GTP-C SMP on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.285

Field Name : bladeGtpCSmpClearedByL3WithL5
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C smp cleared by l3-conn with l5 on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.283

Field Name : bladeGtpCSmpClearedByStandalone
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C smp cleared by standalone conn on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.282

Field Name : bladeGtpUSmpAccessAfterReuse
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U smp access after reuse on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.281

Field Name : bladeGtpCSmpAccessAfterReuse
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C smp access after reuse on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.280

Field Name : bladeGtpCAttemptForDoubleFree
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C smp double free attempted on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.279

Field Name : bladeGtpUAttemptForDoubleFree
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U smp double free attempted on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.278

Field Name : gtpCSmpClearedByL3WithL5
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C smp cleared by l3-conn with l5
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.223

Field Name : gtpCSmpClearedByStandalone
Field Type : CounterBasedGauge64
Field Status : current

Description : GTP-C smp cleared by standalone conn
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.222

Field Name : gtpUSmpAccessAfterReuse
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U smp access after reuse
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.221

Field Name : gtpCSmpAccessAfterReuse
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C smp access after reuse
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.220

Field Name : gtpCAttemptForDoubleFree
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C smp double free attempted
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.219

Field Name : gtpUAttemptForDoubleFree
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U smp double free attempted
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.218

Field Name : gtpUTunnelFragOrJumboPktProcessed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Tunnel Fragmented or Jumbo packet processed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.366

Field Name : gtpEchoFragOrJumboPktProcessed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-Echo Fragmented or Jumbo packet processed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.365

Field Name : gtpCFragOrJumboPktProcessed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Fragmented or Jumbo packet processed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.364

Field Name : gtpUFragPktReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Fragmented packet received
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.217

Field Name : gtpCFragPktReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Fragmented packet received
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.216

Field Name : gtpUFragPktProcessed

Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Fragmented packet processed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.215

Field Name : bladeGtpUPktUSmpValidationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : gtp-u smp ip validation failed on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.277

Field Name : gtpUPktUSmpValidationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : gtp-u smp ip validation failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.214

Field Name : gtpUSmpNotFoundCProcessing
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to extract GTP-U smp not found in C-processing
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.213

Field Name : gtpEchoStatelessForward
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-echo Stateless Forward
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.212

Field Name : bladeGtpUMatchCSmpInRml
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U match C-smp in rml on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.276

Field Name : bladeGtpUInfoExtractFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to extract GTP-U extension during pkt processing on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.275

Field Name : bladeGtpCSmpExtractFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to extract GTP-C smp during pkt processing on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.274

Field Name : bladeGtpCInfoExtractFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to extract GTP-C extension during pkt processing on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.273

Field Name : gtpUMatchCSmpInRml
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U match C-smp in rml
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.211

Field Name : gtpUInfoExtractFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to extract GTP-U extension during pkt processing
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.210

Field Name : gtpCSmpExtractFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to extract GTP-C smp during pkt processing
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.209

Field Name : gtpCInfoExtractFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to extract GTP-C extension during pkt processing
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.208

Field Name : gtpUMatchDbrUSmpConnCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U match U-smp with dbr during conn creation
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.207

Field Name : gtpUMatchCSmpWithHoFlag
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U match C-smp with HO flag
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.206

Field Name : gtpUMatchCSmpWithDelFlag
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U match C-smp with deletion flag
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.205

Field Name : gtpUSmpNotFoundConnCreation
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U smp not found during conn creation
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.204

Field Name : gtpUStatelessForward
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Stateless Forward
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.203

Field Name : bladeGtpUSmpUnlinkedUConnCreation
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U smp unlinked from HT while creating U-conn on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.272

Field Name : bladeGtpCSmpDelMaxRefCount
Field Type : CounterBasedGauge64
Field Status : current

Description : GTP-C SMP with del flag and max ref count during ageout on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.271

Field Name : bladeGtpCRefCountMaxSmpSetForAgeout
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SMP set for deletion during age out with refcount max on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.270

Field Name : bladeGtpCSmpInRmlCConnAgeUpd
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SMP in RML during C-conn age update on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.269

Field Name : bladeGtpSmpAlreadyInDLHash
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP already linked in downlink hash on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.268

Field Name : bladeGtpSmpAlreadyInULHash
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP already linked in uplink hash on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.267

Field Name : bladeGtpUSmpNotFoundInHash
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U SMP not found in hash table to unlink on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.266

Field Name : bladeGtpCSmpNotFoundInHash
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SMP not found in hash table to unlink on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.265

Field Name : bladeGtpSmpPathDoubleFree
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP path added twice to del queue on PU2, cannot be added again
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.264

Field Name : bladeGtpSmpDoubleFree
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP added twice to del queue on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.263

Field Name : gtpUSmpUnlinkedUConnCreation
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U smp unlinked from HT while creating U-conn
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.202

Field Name : gtpCSmpDelMaxRefCount

Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SMP with del flag and max ref count during ageout
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.201

Field Name : gtpCRefCountMaxSmpSetForAgeout
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SMP set for deletion during age out with refcount max
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.200

Field Name : gtpCSmpInRmlCConnAgeUpd
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SMP in RML during C-conn age update
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.199

Field Name : gtpSmpAlreadyInDLHash
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP already linked in downlink hash
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.198

Field Name : gtpSmpAlreadyInULHash
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP already linked in uplink hash
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.197

Field Name : gtpUSmpNotFoundInHash
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U SMP not found in hash table to unlink
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.196

Field Name : gtpCSmpNotFoundInHash
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SMP not found in hash table to unlink
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.195

Field Name : gtpSmpPathDoubleFree
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP path added twice to del queue, cannot be added again
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.194

Field Name : gtpSmpDoubleFree
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP added twice to del queue
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.193

Field Name : bladeGtpSmpPathAlreadyInDelQueue
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP-PATH already in del queue, cannot be added again on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.262

Field Name : bladeGtpSmpAlreadyInDelQueue
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP already in del queue, cannot be added again on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.261

Field Name : bladeGtpCConnPtrNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C conn ptr not found on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.260

Field Name : bladeGtpSmpLinkToHashInRml
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP smp linked to hash table when in rml on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.259

Field Name : bladeGtpUSmpUnlinkFromHashFail
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U smp unlink from hash table failed on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.258

Field Name : bladeGtpCSmpUnlinkFromHashFail
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C smp unlink from hash table failed on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.257

Field Name : bladeGtpInfoExtNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-Info ext not found while freeing C-smp on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.256

Field Name : bladeGtpUSmpAlreadyInRml
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U smp already in rml on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.255

Field Name : bladeGtpCSmpAlreadyInRml
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C smp already in rml on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.254

Field Name : bladeGtpUSmpCheckFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP U-SMP check Failed on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.253

Field Name : bladeGtpCConnNotInRmlWhenFreed
Field Type : CounterBasedGauge64
Field Status : current

Description : GTP-C conn not in rml when tuple is freed on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.252

Field Name : bladeGtpCFreedConnCheck
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C freed conn accessed on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.251

Field Name : bladeGtpSmpDecSessCountCheckFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U session count is 0 in GTP-C SMP on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.250

Field Name : bladeGtpCSmpReferStaleIdx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SMP referring stale C-conn idx on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.249

Field Name : gtpSmpPathAlreadyInDelQueue
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP-PATH already in del queue, cannot be added again
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.192

Field Name : gtpSmpAlreadyInDelQueue
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP already in del queue, cannot be added again
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.191

Field Name : gtpCConnPtrNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C conn ptr not found
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.190

Field Name : gtpSmpLinkToHashInRml
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP smp linked to hash table when in rml
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.189

Field Name : gtpUSmpUnlinkFromHashFail
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U smp unlink from hash table failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.188

Field Name : gtpCSmpUnlinkFromHashFail
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C smp unlink from hash table failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.187

Field Name : gtpInfoExtNotFound

Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-Info ext not found while freeing C-smp
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.186

Field Name : gtpUSmpAlreadyInRml
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U smp already in rml
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.185

Field Name : gtpCSmpAlreadyInRml
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C smp already in rml
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.184

Field Name : gtpUSmpCheckFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP U-SMP check Failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.183

Field Name : gtpCConnNotInRmlWhenFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C conn not in rml when tuple is freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.182

Field Name : gtpCFreedConnCheck
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C freed conn accessed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.181

Field Name : gtpSmpDecSessCountCheckFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U session count is 0 in GTP-C SMP
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.180

Field Name : gtpCSmpReferStaleIdx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SMP referring stale C-conn idx
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.179

Field Name : gtpBldToMstrQueryRespFail
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-PU dcmsg of query response failed from Blade to Master
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.178

Field Name : gtpMstrToBldQueryRespFail
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-PU dcmsg of query response failed from Master to Blade
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.177

Field Name : gtpInterPuBldToMstrQueryRespSent
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-PU GTP-C query response sent from Blade to Master
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.176

Field Name : gtpInterPuBldToMstrQueryRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-PU GTP-C mesg received on Master
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.175

Field Name : gtpInterPuBldToMstrQuerySent
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-PU query sent from Blade to Master
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.174

Field Name : gtpInterPuBldToMstrDcmsgRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-PU dcmsg received on Master
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.173

Field Name : gtpInterPuBldToMstrDcmsgSent
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-PU Blade to Master dcmsg sent
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.172

Field Name : gtpInterPuBldToMstrDcmsgFail
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-PU dcmsg failed from Blade to Master
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.171

Field Name : gtpInterPuMstrToBldQueryRespSent
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-PU GTP-C query response sent from Master to Blade
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.170

Field Name : gtpInterPuMstrToBldQueryRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-PU GTP-C mesg received on Blade
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.169

Field Name : gtpInterPuMstrToBldQuerySent
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-PU query sent from Master to Blade
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.168

Field Name : gtpInterPuMstrToBldDcmsgRecv
Field Type : CounterBasedGauge64
Field Status : current

Description : GTP inter-PU dcmsg received on blade
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.167

Field Name : gtpInterPuMstrToBldDcmsgSent
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-PU Master to Blade dcmsg sent
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.166

Field Name : gtpInterPuMstrToBldDcmsgFail
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-PU dcmsg failed from Master to Blade
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.165

Field Name : gtpCPktFwdConnCreateNoFteid
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C pkt fwded while creating conn when no FTEID
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.164

Field Name : gtpCConnCreatePktDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C conn creation drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.163

Field Name : gtpCGoingThruFwLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C mesg going thru fw lookup can be resp or l5 mesg not matching smp
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.162

Field Name : gtpCRevV2Other
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C rev v2 other messages
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.161

Field Name : gtpCRevV1Other
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C rev v1 other messages
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.160

Field Name : gtpCFwdV2Other
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C fwd v2 other messages
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.159

Field Name : gtpCFwdV1Other
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C fwd v1 other messages
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.158

Field Name : gtpCRevPktDrop

Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C rev pkt drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.157

Field Name : gtpCFwdPktDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C fwd pkt drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.156

Field Name : gtpCProcessPktDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C process pkt drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.155

Field Name : gtpRefreshConnSetHoFlagLatest
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SGW refresh old conn and set ho flag on latest smp
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.154

Field Name : gtpWrongConnHandoverRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C ho mesg matching wrong conn(new teid) with no HO flag
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.153

Field Name : gtpRematchSmpMatchingConn
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C rematch smp with packet matching conn
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.152

Field Name : gtpRefreshCConnReuseTeid
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SGW reuse teid with ho and refresh old conn
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.151

Field Name : gtpUnsetHoFlagReuseTeid
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SGW reuse teid with ho and unset ho flag
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.150

Field Name : gtpHoInProgressCMesg
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C other than ho mesg matching conn with HO In Progress
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.149

Field Name : gtpHoInProgressHandoverResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C ho response matching a conn with HO In Progress
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.148

Field Name : gtpWrongConnHoInProgressHandoverRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C ho mesg matching wrong conn(new teid) with HO In Progress
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.147

Field Name : gtpCorrectConnHoInProgressHandoverRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C ho mesg matching correct conn(reuse teid) with HO In Progress
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.146

Field Name : gtpHoInProgressHandoverRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C ho mesg matching conn with HO In Progress
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.145

Field Name : gtpCHandoverInProgressWithConn
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C mesg matching conn with HO In Progress
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.144

Field Name : gtpUErrorInd
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Error Indication
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.42

Field Name : gtpV1ExtnHdtNotif
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPV1 Supported Extension header notification
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.41

Field Name : gtpV2CVerNotSupp
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Version not supported indication
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.40

Field Name : gtpV1CVerNotSupp
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Version not supported indication
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.39

Field Name : gtpV0CVerNotSupp
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Version not supported indication
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.38

Field Name : gtpCMessageForwardedWithoutConn
Field Type : CounterBasedGauge64
Field Status : current

Description : GTP-C Message Forwarded without Conn
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.37

Field Name : responseWithRejectCauseForwarded
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Response with Reject Cause Forwarded
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.36

Field Name : dropGtpFragOrJumboPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Fragmented or JUMBO packet Drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.35

Field Name : gtpRrCMessageDcmsg
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Message Sent to home CPU in RR Mode
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.34

Field Name : gtpRrEchoMessageDcmsg
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Echo Message Sent to home CPU in RR Mode
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.33

Field Name : gtpURrMessageDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Message Dropped in RR Mode
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.248

Field Name : gtpRrMessageDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Message Dropped in RR Mode
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.32

Field Name : gtpMultipleHandoverRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Multiple Handover Request
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.31

Field Name : gtpV2CBearerNotFoundInDeleteResp
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Bearer Not Found in GTP Response
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.30

Field Name : gtpV2CBearerNotFoundInDeleteReq
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Bearer Not Found in GTP Request
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.29

Field Name : gtpV1CNsapiNotFoundInDeleteReq

Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C NSAPI Not Found in GTP Request
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.28

Field Name : gtpCHandoverRequestOutOfStateDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Handover Request Out of state Drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.27

Field Name : gtpUOutOfStateDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Out of state Drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.26

Field Name : gtpCreateSessionRequestRetxDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Retransmitted Create Session Request dropped
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.134

Field Name : gtpAddBearerResponseRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Retransmitted Add Bearer Response
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.25

Field Name : gtpDelBearerRequestRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Retransmitted Delete Bearer Request
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.24

Field Name : gtpHandoverRequestRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Handover Request Retransmit
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.23

Field Name : gtpDeleteSessionRequestRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Retransmitted Delete Session Request
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.22

Field Name : gtpAddBearerRequestRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Retransmitted Add Bearer Request
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.21

Field Name : gtpCreateSessionRequestRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Retransmitted Create Session Request
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.20

Field Name : dropVldGtpUEchoOutOfState
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Echo Out of State Drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.247

Field Name : dropVldGtpEchoIeLenExceedMsgLen
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Echo IE Length Exceeds Message Length
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.135

Field Name : dropVldGtpEchoOutOfState
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Echo Out of State Drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.19

Field Name : gtpCEchoPathFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Path Failure due to Echo
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.18

Field Name : gtpNodeRestartEcho
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Node Restoration due to Recovery IE in Echo
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.17

Field Name : gtpEchoConnDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Echo Request conn Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.16

Field Name : gtpEchoConnCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Echo Request Conn Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.15

Field Name : bladeGtpRateLimitEntryCreateFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Rate Limit Entry Create Failure on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.246

Field Name : bladeGtpRateLimitT3CtrCreateFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Rate Limit Dynamic Counters Create Failure on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.245

Field Name : bladeGtpRateLimitSmpCreateFailure
Field Type : CounterBasedGauge64
Field Status : current

Description : GTP Rate Limit SMP Create Failure on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.244

Field Name : bladeGtpRateLimitSmpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Rate Limit SMP Freed on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.243

Field Name : bladeGtpRateLimitSmpCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Rate Limit SMP Created on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.242

Field Name : gtpRateLimitEntryCreateFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Rate Limit Entry Create Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.131

Field Name : gtpRateLimitT3CtrCreateFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Rate Limit Dynamic Counters Create Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.130

Field Name : gtpRateLimitSmpCreateFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Rate Limit SMP Create Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.129

Field Name : gtpRateLimitSmpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Rate Limit SMP Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.128

Field Name : gtpRateLimitSmpCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Rate Limit SMP Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.127

Field Name : gtpUTunnelRateLimitEntryDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Tunnel Level Rate Limit Entry Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.241

Field Name : gtpUTunnelRateLimitEntryCreateFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Tunnel Level Rate Limit Entry Create Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.240

Field Name : gtpUTunnelRateLimitEntryIncRefCount

Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Tunnel Level Rate Limit Entry Inc ref count
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.363

Field Name : gtpUTunnelRateLimitEntryCreateSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Tunnel Level Rate Limit Entry Create Success
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.239

Field Name : gtpTunnelRateLimitEntryDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Tunnel Level Rate Limit Entry Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.14

Field Name : gtpTunnelRateLimitEntryCreateFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Tunnel Level Rate Limit Entry Create Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.13

Field Name : gtpTunnelRateLimitEntryIncRefCount
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Tunnel Level Rate Limit Entry Inc ref count
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.362

Field Name : gtpTunnelRateLimitEntryCreateSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Tunnel Level Rate Limit Entry Create Success
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.12

Field Name : gtpEchoPktFwdConnCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-ECHO pkt fwded while creating conn with gtp toggling
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.143

Field Name : gtpCPktFwdConnCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C pkt fwded while creating conn with gtp toggling
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.142

Field Name : gtpUPktFwdConnCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U pkt fwded while creating conn with gtp toggling
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.141

Field Name : bladeGtpUSmpInRmlWithSess
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U smp is linked when C-smp is in rml on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.238

Field Name : gtpUSmpInRmlWithSess
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U smp is linked when C-smp is in rml
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.140

Field Name : bladeGtpCRefCountSmpExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C session count on C-smp exceeded 2 on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.237

Field Name : gtpCRefCountSmpExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C session count on C-smp exceeded 2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.139

Field Name : gtpSmpSessionCountCheckFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U session count is not in range of 0-11 in GTP-C SMP
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.138

Field Name : bladeGtpSmpCCheckFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SMP check Failed on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.236

Field Name : bladeGtpSmpPathCheckFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP PATH check Failed on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.235

Field Name : bladeGtpSmpPathCreationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP PATH creation Failed on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.234

Field Name : bladeGtpSmpPathAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP PATH MEM allocated on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.233

Field Name : bladeGtpSmpPathFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP PATH MEM freed on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.232

Field Name : bladeGtpSmpPathCreated
Field Type : CounterBasedGauge64
Field Status : current

Description : GTP SMP PATH Created on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.231

Field Name : bladeSmpCreationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP Helper Session Creation Failed on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.230

Field Name : bladeGtpSmpDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP Deleted on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.229

Field Name : bladeGtpSmpMarkedDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP Marked Deleted on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.228

Field Name : bladeGtpSmpCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP Created on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.227

Field Name : gtpSmpCCheckFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SMP check Failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.137

Field Name : gtpSmpPathCheckFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP PATH check Failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.136

Field Name : gtpSmpPathCreationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP PATH creation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.11

Field Name : gtpSmpPathAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP PATH MEM allocated
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.10

Field Name : gtpSmpPathFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP PATH MEM freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.9

Field Name : gtpSmpPathCreated

Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP PATH Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.8

Field Name : smpCreationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP Helper Session Creation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.7

Field Name : gtpSmpDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.6

Field Name : gtpSmpMarkedDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP Marked Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.5

Field Name : gtpSmpCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.4

Field Name : gtpNoRevRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : No Reverse Route on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.226

Field Name : gtpNoFwdRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : No Forward Route on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.225

Field Name : bladeOutOfSessionMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of Tunnel Memory on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.224

Field Name : gtpNoRevRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : No Reverse Route for GTP-C
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.3

Field Name : gtpNoFwdRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : No Forward Route for GTP-C
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.2

Field Name : outOfSessionMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of Tunnel Memory for GTP-C
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.1

Field Name : pktAsconfParamLenErrDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid Parameter Length Drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.66

Field Name : pktChunkLenErrDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid Chunk Length Drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.65

Field Name : pktLenErrDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid Packet Length Drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.64

Field Name : sctpInitVtagZeroDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP INIT VTAG ZERO drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.63

Field Name : sctpAsconfProcessDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP ASCONF process drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.62

Field Name : sctpRetxInit
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Retransmitted INIT
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.61

Field Name : sctpRetxInitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Retransmitted INIT drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.60

Field Name : sctpRetxInitAck
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type INIT_ACK retransmitted
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.59

Field Name : sctpNoExtMatch
Field Type : CounterBasedGauge64
Field Status : current

Description : SCTP no extended match found
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.58

Field Name : sctpRouteErrDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP ROUTE lookup failed for chunks other than HEARTBEAT drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.57

Field Name : sctpRerouteFailover
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP REROUTE lookup for chunks other than HEARTBEAT
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.56

Field Name : sctpRouteErrHeartbeatDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP HEARTBEAT ROUTE lookup failed drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.55

Field Name : sctpRetxInitAckDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type INIT_ACK with retx mismatched vtag drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.54

Field Name : sctpChunkHeartBeatClubbed
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP HEARTBEAT chunk with other chunk
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.53

Field Name : sctpChunkTypeAbortDataDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type with ABORT and DATA drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.52

Field Name : sctpChunkTypeShutdownCompleteDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type SHUTDOWN-COMPLETE drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.51

Field Name : sctpChunkTypeInitAckDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type INIT-ACK drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.50

Field Name : sctpChunkTypeInitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type INIT drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.49

Field Name : sctpDataNoExtMatch

Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP DATA no extended match found
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.48

Field Name : sctpDataNoTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP DATA chunk no tuple found
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.47

Field Name : sctpHeartbeatNoTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP HEARTBEAT/ACK no tuple found
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.46

Field Name : sctpChunkTypeOther
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type OTHER
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.45

Field Name : sctpChunkTypeHeartbeatAck
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type HEARTBEAT-ACK
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.44

Field Name : sctpChunkTypeHeartbeat
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type HEARTBEAT
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.43

Field Name : sctpChunkTypeErrorOp
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type ERROR-OP
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.42

Field Name : sctpChunkTypeShutdownComplete
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type SHUTDOWN-COMPLETE
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.41

Field Name : sctpChunkTypeShutdownAck
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type SHUTDOWN-ACK
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.40

Field Name : sctpChunkTypeShutdown
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type SHUTDOWN
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.39

Field Name : sctpChunkTypeAbort
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type ABORT
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.38

Field Name : sctpChunkTypeData
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type DATA
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.37

Field Name : sctpChunkTypeAsconfAck
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type ASCONF-ACK
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.36

Field Name : sctpChunkTypeAsconf
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type ASCONF
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.35

Field Name : sctpChunkTypeSack
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type SACK
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.34

Field Name : sctpChunkTypeCookieAck
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type COOKIE-ACK
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.33

Field Name : sctpChunkTypeCookieEcho
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type COOKIE-ECHO
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.32

Field Name : sctpChunkTypeInitAck
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type INIT-ACK
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.31

Field Name : sctpChunkTypeInit
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type INIT
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.30

Field Name : badAlignmentDropShadow
Field Type : CounterBasedGauge64
Field Status : current

Description : Bad Packet Alignment Drop Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.29

Field Name : badPayloadDropShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Packet Payload Drop Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.28

Field Name : badCsumShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Checksum Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.27

Field Name : connExtSizeMax
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Conn Extension Size
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.26

Field Name : sctpOutOfSystemMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of System Memory
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.25

Field Name : sbyStaticNatCfgNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Static NAT Config Not Found on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.24

Field Name : sbySessionUpdateFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Standby Session Update Failed
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.23

Field Name : sbySessionUpdated
Field Type : CounterBasedGauge64
Field Status : current
Description : Standby Session Updated
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.22

Field Name : sbySessionCreateFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Standby Session Create Failed
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.21

Field Name : sbySessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Standby Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.20

Field Name : rateLimitDrop

Field Type : CounterBasedGauge64
Field Status : current
Description : Rate-limit Drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.19

Field Name : disallowedPktDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Disallowed Packet Drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.18

Field Name : disallowedChunkFiltered
Field Type : CounterBasedGauge64
Field Status : current
Description : Disallowed Chunk Filtered
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.17

Field Name : invalidFragChunkDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid Fragmented Chunks Drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.16

Field Name : vrrpStandbyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT Resource VRRP-A Standby Drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.15

Field Name : cfgErrDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Configuration Error Drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.14

Field Name : staticNatCfgNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Static NAT Config Not Found Drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.13

Field Name : multiHomeAddrNotFoundDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Multi-homing IP Address Not Found Drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.12

Field Name : multiHomeRemoveIpSkip
Field Type : CounterBasedGauge64
Field Status : current
Description : Multi-homing Remove IP Parameter Skip
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.11

Field Name : maxMultiHomeDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Maximum Multi-homing IP Addresses Drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.10

Field Name : oosPktDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Out-of-state Packet Drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.9

Field Name : badAlignmentDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Alignment Drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.8

Field Name : badPayloadDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Payload Drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.7

Field Name : badCsum
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Checksum
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.6

Field Name : pktErrDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet Error Drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.5

Field Name : sctpFwSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Firewall Session Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.4

Field Name : sctpFirewallSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Firewall Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.3

Field Name : sctpStaticNatSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Static NAT Session Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.2

Field Name : sctpStaticNatSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Static NAT Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.1

Field Name : soHairpinConnSuccess
Field Type : CounterBasedGauge64
Field Status : current

Description : Scaleout hairpin connection success
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.56

Field Name : soHairpinIntfWrongTag
Field Type : CounterBasedGauge64
Field Status : current
Description : Scaleout hairpin wrong hairpin interface tag
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.55

Field Name : soHairpinNoHairpinIntf
Field Type : CounterBasedGauge64
Field Status : current
Description : Scaleout hairpin no hairpin interface
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.54

Field Name : soHairpinConnExtFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Scaleout hairpin connection extension failed
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.53

Field Name : soHairpinNoFwdDev
Field Type : CounterBasedGauge64
Field Status : current
Description : Scaleout hairpin no fwd device
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.52

Field Name : soHairpinMissingPktHash
Field Type : CounterBasedGauge64
Field Status : current
Description : Scaleout hairpin missing pkt hash
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.51

Field Name : soHairpinInboundNoDstChange
Field Type : CounterBasedGauge64
Field Status : current
Description : Scaleout hairpin inbound conn no dest change
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.50

Field Name : soHairpinIncorrectIntfTag
Field Type : CounterBasedGauge64
Field Status : current
Description : Scaleout hairpin incorrect interface tag
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.49

Field Name : soHairpinInboundCheckNoRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : Scaleout hairpin inbound check no route
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.48

Field Name : soPktsL2redirectTxFragVlanAddFail
Field Type : CounterBasedGauge64
Field Status : current
Description : L2 redirect tx pkt failed to add vlan
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.47

Field Name : soPktsL2redirectFragVlanRetrievalError

Field Type : CounterBasedGauge64
Field Status : current
Description : L2 redirect pkt frag vlan not retrieved
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.46

Field Name : soPktsRedirectionLoopDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets redirection loop drop
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.45

Field Name : soPktsCgnTrafficMapMismatchDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : CGN packets traffic map mismatch drop
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.44

Field Name : soSyncSlbShadowSessionDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : Sent Sync message for SLB Shadow session deletion
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.43

Field Name : soSyncSlbShadowSessionCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : Sent Sync message for SLB Shadow session creation
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.42

Field Name : soSlbShadowSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : SLB Shadow Session created
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.41

Field Name : soPktsL2redirectSamePktMultipleTimes
Field Type : CounterBasedGauge64
Field Status : current
Description : L2 redirect same pkt multiple times
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.40

Field Name : soPktsL2redirectLoopDetectDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : L2 redirect pkt loop detected and dropped
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.39

Field Name : soPktsL2redirectPortRetrievalError
Field Type : CounterBasedGauge64
Field Status : current
Description : L2 redirect pkt port not retrieved
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.38

Field Name : soPktsL2redirectVlanRetrievalError
Field Type : CounterBasedGauge64
Field Status : current
Description : L2 redirect pkt vlan not retrieved
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.37

Field Name : soHcDeregistrationDone
Field Type : CounterBasedGauge64
Field Status : current
Description : Scaleout stats block de-registered with HC
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.36

Field Name : soHcRegistrationDone
Field Type : CounterBasedGauge64
Field Status : current
Description : Scaleout stats block registered with HC
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.35

Field Name : soFwInternalRuleCount
Field Type : CounterBasedGauge64
Field Status : current
Description : FW internal rule count
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.34

Field Name : soSyncShadowStatsToActive
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Shadow session stats from shadow to active
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.33

Field Name : soSyncFwShadowExt
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync FW Shadow extension creation/updation
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.32

Field Name : soSyncFwShadowSessionDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : Sent Sync message for FW Shadow session deletion
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.31

Field Name : soSyncFwShadowSessionCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : Sent Sync message for FW Shadow session creation
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.30

Field Name : soPktsL3RedirectEncapMtuErrorDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Received L3 Redirected MTU not enough to add encap
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.29

Field Name : soPktsL3RedirectTooLargePktsInDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Received L3 Redirected fragmented packets too large
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.28

Field Name : soPktsL3RedirectEncapIpv6JumboFragDrop
Field Type : CounterBasedGauge64
Field Status : current

Description : L3 Redirect tx ipv6 packet after encap more than max jumbo size
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.27

Field Name : soPktsL3RedirectEncapIpv4JumboFragDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 Redirect ipv4 packet after encap more than max jumbo size
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.26

Field Name : soPktsL3RedirectChassisDestMacError
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 Redirect RX multi-slot Destination MAC Error
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.25

Field Name : soPktsL3RedirectInvalidDevDir
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 Redirect Invalid Device direction during transmission
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.24

Field Name : soPktsL3RedirectTableNoEntryFound
Field Type : TABLE
Field Status : current
Description : L3 redirect Table no redirect entry found error
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.23

Field Name : soPktsL3RedirectFragmentationError
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 redirect encap Fragmentation error
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.22

Field Name : soPktsL3RedirectRcvdInL2ModeDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Recevied l3 redirect packets in L2 mode Drop
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.21

Field Name : soPktsL3RedirectTableError
Field Type : TABLE
Field Status : current
Description : L3 Redirect Table error Drop
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.20

Field Name : soPktsL3RedirectDecapRxEncapParamsDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 Redirect decap Rx encap params error Drop
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.19

Field Name : soPktsL3RedirectDecapNonIpv4VxlanDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 Redirect received non ipv4 VXLAN packet
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.18

Field Name : soPktsL3RedirectDecapVlanSanityDrop

Field Type : CounterBasedGauge64
Field Status : current
Description : L3 Redirect Decap VLAN Sanity Drop during receipt
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.17

Field Name : soPktsL3RedirectInnerMacZeroDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 Redirect inner mac zero drop during transmission
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.16

Field Name : soPktsL3RedirectEncapErrorDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 Redirect encap error drop during transmission
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.15

Field Name : soPktsL2redirectInvalidRedirectInfoError
Field Type : CounterBasedGauge64
Field Status : current
Description : Redirect Table Error due to invalid redirect info
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.14

Field Name : soPktsL2redirectInterfaceNotUp
Field Type : CounterBasedGauge64
Field Status : current
Description : L2redirect Intf is not UP
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.13

Field Name : soPktsL2redirectDestMacZeroDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Destination MAC Address zero Drop
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.12

Field Name : soPktsDestMacMismatchDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Destination MAC Mistmatch Drop
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.11

Field Name : soPktsSlbNatReleaseFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SLB NAT release failures
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.10

Field Name : soPktsSlbNatReserveFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SLB NAT reserve failures
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.9

Field Name : soPktsScaleoutNotActiveDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Scaleout Not Active Drop
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.8

Field Name : soSlbPktsRedirectConnAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SLB redirect conns aged out
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.7

Field Name : soPktsTrafficMapNotFoundDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Traffic MAP Not Found Drop
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.6

Field Name : soFwShadowSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : FW Shadow Session created
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.5

Field Name : soRedirectedPktsRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Total redirected packets received on node
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.4

Field Name : soPktsDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Total packets dropped
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.3

Field Name : soRedirectPktsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total packets redirected out of node
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.2

Field Name : soPktsRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Total data packets received
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.1

Field Name : vcsVbladesStatSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1

Field Name : vcsVbladesStatSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1.1

Field Name : vcsVbladesSlaveCfgUpdResultErr
Field Type : CounterBasedGauge64
Field Status : current

Description : vBlade Configuration Update Result Errors counter of aVCS election
OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1.1.15

Field Name : vcsVbladesSlaveCfgUpdNotifErr
Field Type : CounterBasedGauge64
Field Status : current
Description : vBlade Configuration Update Notif Errors counter of aVCS election
OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1.1.14

Field Name : vcsVbladesSlaveCfgUpdL2Fail
Field Type : CounterBasedGauge64
Field Status : current
Description : vBlade Local Configuration Update Errors (2) counter of aVCS election
OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1.1.13

Field Name : vcsVbladesSlaveCfgUpdRFail
Field Type : CounterBasedGauge64
Field Status : current
Description : vBlade Remote Configuration Update Errors counter of aVCS election
OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1.1.12

Field Name : vcsVbladesSlaveCfgUpdL1Fail
Field Type : CounterBasedGauge64
Field Status : current
Description : vBlade Local Configuration Update Errors (1) counter of aVCS election
OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1.1.11

Field Name : vcsVbladesSlaveCfgUpd
Field Type : CounterBasedGauge64
Field Status : current
Description : vBlade Received Configuration Updates counter of aVCS election
OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1.1.10

Field Name : vcsVbladesSlaveKeepAlive
Field Type : CounterBasedGauge64
Field Status : current
Description : vBlade Received Keepalives counter of aVCS election
OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1.1.9

Field Name : vcsVbladesSlaveMsgInval
Field Type : CounterBasedGauge64
Field Status : current
Description : vBlade Invalid Messages counter of aVCS election
OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1.1.8

Field Name : vcsVbladesSlaveNSent
Field Type : CounterBasedGauge64
Field Status : current
Description : vBlade Sent Messages counter of aVCS election
OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1.1.7

Field Name : vcsVbladesSlaveNRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : vBlade Received Messages counter of aVCS election
OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1.1.6

Field Name : vcsVbladesSlaveSentBytes

Field Type : CounterBasedGauge64
Field Status : current
Description : vBlade Sent Bytes counter of aVCS election
OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1.1.5

Field Name : vcsVbladesSlaveRecvBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : vBlade Received Bytes counter of aVCS election
OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1.1.4

Field Name : vcsVbladesSlaveSendErr
Field Type : CounterBasedGauge64
Field Status : current
Description : vBlade Send Errors counter of aVCS election
OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1.1.3

Field Name : vcsVbladesSlaveRecvErr
Field Type : CounterBasedGauge64
Field Status : current
Description : vBlade Receive Errors counter of aVCS election
OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1.1.2

Field Name : vbladeId
Field Type : INTEGER
Field Status : current
Description : vBlade-id
OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1.1.1

Field Name : trafficControlRuleSetSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.197.2.1.1

Field Name : trafficControlRuleSetSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.197.2.1.1.1

Field Name : hitCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Hit counts
OID : 1.3.6.1.4.1.22610.2.4.10.197.2.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Rule set name
OID : 1.3.6.1.4.1.22610.2.4.10.197.2.1.1.1.1

Field Name : Total
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.39.22.1

Field Name : memory
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.39.32.7

Field Name : storage
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.39.32.6

Field Name : cpuStepping
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.39.32.5

Field Name : cpuCores
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.39.32.4

Field Name : cpu
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.39.32.3

Field Name : serial
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.39.32.2

Field Name : platformDescription
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.39.32.1

Field Name : systemCpuCtrlCpuCpuUsageTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.2.1

Field Name : systemCpuCtrlCpuCpuUsageEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.2.1.1

Field Name : crtlSixtySec
Field Type : CounterBasedGauge64
Field Status : current

Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.2.1.1.6

Field Name : crtlThirtySec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.2.1.1.5

Field Name : crtlTenSec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.2.1.1.4

Field Name : crtlFiveSec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.2.1.1.3

Field Name : crtlOneSec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.2.1.1.2

Field Name : crtlCpuId
Field Type : INTEGER
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.2.1.1.1

Field Name : systemCpuDataCpuCpuUsageTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.1.1

Field Name : systemCpuDataCpuCpuUsageEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.1.1.1

Field Name : dcpuStr
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.1.1.1.7

Field Name : sixtySec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.1.1.1.6

Field Name : thirtySec

Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.1.1.1.5

Field Name : tenSec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.1.1.1.4

Field Name : fiveSec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.1.1.1.3

Field Name : oneSec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.1.1.1.2

Field Name : cpuId
Field Type : INTEGER
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.1.1.1.1

Field Name : systemCpuVportDataCpuVportCpuUsageTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.5.1

Field Name : systemCpuVportDataCpuVportCpuUsageEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.5.1.1

Field Name : sixtySec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.5.1.1.11

Field Name : thirtySec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.5.1.1.10

Field Name : tenSec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.5.1.1.9

Field Name : fiveSec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.5.1.1.8

Field Name : oneSec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.5.1.1.7

Field Name : dcpuStr
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.5.1.1.6

Field Name : vportType
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.5.1.1.5

Field Name : cpuId
Field Type : INTEGER
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.5.1.1.4

Field Name : protocol
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.5.1.1.3

Field Name : portNumber
Field Type : INTEGER
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.5.1.1.2

Field Name : vserverName
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.5.1.1.1

Field Name : systemCpuVserverDataCpuVserverCpuUsageTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.4.1

Field Name : systemCpuVserverDataCpuVserverCpuUsageEntry
Field Type : CounterBasedGauge64
Field Status : current

Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.4.1.1

Field Name : sixtySec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.4.1.1.8

Field Name : thirtySec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.4.1.1.7

Field Name : tenSec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.4.1.1.6

Field Name : fiveSec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.4.1.1.5

Field Name : oneSec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.4.1.1.4

Field Name : dcpuStr
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.4.1.1.3

Field Name : cpuId
Field Type : INTEGER
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.4.1.1.2

Field Name : vserverName
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.4.1.1.1

Field Name : systemCpuDataCpuOverallCpuUsageTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.3.1

Field Name : systemCpuDataCpuOverallCpuUsageEntry

Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.3.1.1

Field Name : allDcpuStr
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.3.1.1.7

Field Name : allSixtySec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.3.1.1.6

Field Name : allThirtySec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.3.1.1.5

Field Name : allTenSec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.3.1.1.4

Field Name : allFiveSec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.3.1.1.3

Field Name : allOneSec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.3.1.1.2

Field Name : allCpuId
Field Type : INTEGER
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.3.1.1.1

Field Name : utilEnableStatus
Field Type : String
Field Status : current
Description : current module percentage enable Status
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.67

Field Name : fpFailAflex
Field Type : CounterBasedGauge64
Field Status : current
Description : aFleX fail
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.66

Field Name : fpFailVerifyCert
Field Type : CounterBasedGauge64
Field Status : current
Description : Cert fetch, validation error
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.65

Field Name : fpFailTcpError
Field Type : CounterBasedGauge64
Field Status : current
Description : Cert fetch, TCP FIN/RST
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.64

Field Name : fpFailHandshake
Field Type : CounterBasedGauge64
Field Status : current
Description : Cert fetch, Fatal alert
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.63

Field Name : serverSslUnknownError
Field Type : CounterBasedGauge64
Field Status : current
Description : Server SSL Unknown Error
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.62

Field Name : serverSslInternalError
Field Type : CounterBasedGauge64
Field Status : current
Description : Server SSL Internal Error
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.61

Field Name : clientSslUnknownError
Field Type : CounterBasedGauge64
Field Status : current
Description : Client SSL Unknown Error
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.60

Field Name : clientSslInternalError
Field Type : CounterBasedGauge64
Field Status : current
Description : Client SSL Internal Error
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.59

Field Name : serverSslFinReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Server SSL, TCP FIN/RST
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.58

Field Name : serverSslFatalAlert
Field Type : CounterBasedGauge64
Field Status : current
Description : Server SSL, SSL Fatal alert
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.57

Field Name : sslSessionFinReset
Field Type : CounterBasedGauge64
Field Status : current

Description : SSL Session, TCP FIN/RST
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.56

Field Name : clientSslFinReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Cert Fetch, TCP FIN/RST
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.55

Field Name : clientSslFatalAlert
Field Type : CounterBasedGauge64
Field Status : current
Description : Cert Fetch, SSL Fatal Alert
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.54

Field Name : unsupportedSslVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : Unsupported SSL Version
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.53

Field Name : revokedOcspResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Revoked OCSP Response
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.52

Field Name : invalidOcspStaplingResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid OCSP Stapling Response
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.51

Field Name : certificateSigningFailures
Field Type : CounterBasedGauge64
Field Status : current
Description : Failed in Certificate Signing
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.50

Field Name : certificateVerificationFailures
Field Type : CounterBasedGauge64
Field Status : current
Description : Failed in Certificate Verification
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.49

Field Name : tcpFailures
Field Type : CounterBasedGauge64
Field Status : current
Description : Failed in TCP
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.48

Field Name : cryptioOperations
Field Type : CounterBasedGauge64
Field Status : current
Description : Crypto operations
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.47

Field Name : sslHandshakeFailure

Field Type : CounterBasedGauge64
Field Status : current
Description : Failed in SSL handshakes
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.46

Field Name : bypassClientAuthSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass Client Auth sessions
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.45

Field Name : dropEsniSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Drop ESNI sessions
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.44

Field Name : bypassEsniSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass ESNI sessions
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.43

Field Name : resetNoSniSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Reset NO SNI sessions
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.42

Field Name : bypassNoSniSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass No SNI sessions
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.41

Field Name : bypassCertSanSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass Cert SAN sessions
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.40

Field Name : bypassCertIssuerSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass Cert Issuer sessions
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.39

Field Name : bypassCertSubjectSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass Cert Subject sessions
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.38

Field Name : bypassSniSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass SNI sessions
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.37

Field Name : bypassAdGroupSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass AD-Group sessions
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.36

Field Name : bypassUsenameSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass Username sessions
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.35

Field Name : bypassFailsafeSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass failsafe SSL sessions
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.34

Field Name : dynamicSslContexts
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Dynamic SSL contexts
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.33

Field Name : staticSslContexts
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Static SSL contexts
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.32

Field Name : currSslContexts
Field Type : CounterBasedGauge64
Field Status : current
Description : Current SSL contexts in use
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.31

Field Name : maxSslContexts
Field Type : CounterBasedGauge64
Field Status : current
Description : Maximum SSL contexts
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.30

Field Name : clientsslContextMallocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Total client ssl context malloc failures
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.29

Field Name : recordTooBig
Field Type : CounterBasedGauge64
Field Status : current
Description : Record too big
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.28

Field Name : hwRingFull
Field Type : CounterBasedGauge64
Field Status : current

Description : HW ring full
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.27

Field Name : hwContextAllocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Context Memory alloc failed
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.26

Field Name : hwContextUsage
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Context Memory In Use
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.25

Field Name : hwContextTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Context Memory Total Count
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.24

Field Name : caVerificationFailures
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL fail CA verification
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.23

Field Name : clientCertAuthFail
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL client certificate authorization failed
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.22

Field Name : serverCertErrors
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL server certificate errors
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.21

Field Name : sslMemoryUsage
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL memory usage
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.20

Field Name : failedCrypto
Field Type : CounterBasedGauge64
Field Status : current
Description : Failed crypto operations
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.19

Field Name : failedHandshakes
Field Type : CounterBasedGauge64
Field Status : current
Description : Failed SSL handshakes
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.18

Field Name : totalServersideFailedEarlyDataConnections

Field Type : CounterBasedGauge64
Field Status : current
Description : Total serverside failed early data connections
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.17

Field Name : totalClientsideFailedEarlyDataConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : Total clientside failed early data connections
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.16

Field Name : totalServersideEarlyDataConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : Total serverside early data connections
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.15

Field Name : totalClientsideEarlyDataConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : Total clientside early data connections
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.14

Field Name : totalReuseSessionTicketServerSsl
Field Type : CounterBasedGauge64
Field Status : current
Description : Total times of stateless session reuse in server ssl
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.13

Field Name : totalReuseSessionTicketClientSsl
Field Type : CounterBasedGauge64
Field Status : current
Description : Total times of stateless session reuse in client ssl
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.12

Field Name : totalReuseServerSsl
Field Type : CounterBasedGauge64
Field Status : current
Description : Total times of stateful session reuse in server ssl
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.11

Field Name : totalReuseClientSsl
Field Type : CounterBasedGauge64
Field Status : current
Description : Total times of stateful session reuse in client ssl
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.10

Field Name : nonSslBypassConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : NON SSL bypass connections
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.9

Field Name : totalServersideConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : Total serverside SSL connections
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.8

Field Name : currentServersideConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : Current serverside SSL connections
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.7

Field Name : totalClientsideConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : Total clientside SSL connections
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.6

Field Name : currentClientsideConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : Current clientside SSL connections
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.5

Field Name : sslModulesCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of SSL modules
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.4

Field Name : thalesHsmStatus
Field Type : String
Field Status : current
Description : Thales HSM Status
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.3

Field Name : configModuleType
Field Type : String
Field Status : current
Description : Config module
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.2

Field Name : sslModuleType
Field Type : String
Field Status : current
Description : SSL module
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.1

Field Name : badHandshakeLength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad handshake length
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.245

Field Name : unsupportedDigestType
Field Type : CounterBasedGauge64
Field Status : current
Description : unsupported digest type
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.244

Field Name : noRequiredDigest
Field Type : CounterBasedGauge64
Field Status : current

Description : no required digest
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.243

Field Name : unsupportedEllipticCurve
Field Type : CounterBasedGauge64
Field Status : current
Description : unsupported elliptic curve
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.242

Field Name : cookieMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : cookie mismatch
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.241

Field Name : badEcpoint
Field Type : CounterBasedGauge64
Field Status : current
Description : bad ecpoint
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.240

Field Name : badEcdsaSig
Field Type : CounterBasedGauge64
Field Status : current
Description : bad ecdsa sig
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.239

Field Name : badEccCert
Field Type : CounterBasedGauge64
Field Status : current
Description : bad ecc cert
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.238

Field Name : tlsInvalidEcpointformatList
Field Type : CounterBasedGauge64
Field Status : current
Description : tls invalid ecpointformat list
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.237

Field Name : multipleSgcRestarts
Field Type : CounterBasedGauge64
Field Status : current
Description : multiple sgc restarts
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.236

Field Name : ssl3ExtInvalidServernameType
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl3 ext invalid servername type
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.235

Field Name : ssl3ExtInvalidServername
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl3 ext invalid servername
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.234

Field Name : serverhelloTlsext

Field Type : CounterBasedGauge64
Field Status : current
Description : serverhello tlsext
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.233

Field Name : parseTlsext
Field Type : CounterBasedGauge64
Field Status : current
Description : parse tlsext
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.232

Field Name : clienthelloTlsext
Field Type : CounterBasedGauge64
Field Status : current
Description : clienthello tlsext
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.231

Field Name : x509VerificationSetupProblems
Field Type : CounterBasedGauge64
Field Status : current
Description : x509 verification setup problems
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.230

Field Name : x509Lib
Field Type : CounterBasedGauge64
Field Status : current
Description : x509 lib
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.229

Field Name : wrongVersionNumber
Field Type : CounterBasedGauge64
Field Status : current
Description : wrong version number
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.228

Field Name : wrongSslVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : wrong ssl version
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.227

Field Name : wrongSignatureSize
Field Type : CounterBasedGauge64
Field Status : current
Description : wrong signature size
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.226

Field Name : wrongSignatureLength
Field Type : CounterBasedGauge64
Field Status : current
Description : wrong signature length
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.225

Field Name : wrongNumberOfKeyBits
Field Type : CounterBasedGauge64
Field Status : current
Description : wrong number of key bits
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.224

Field Name : wrongMessageType
Field Type : CounterBasedGauge64
Field Status : current
Description : wrong message type
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.223

Field Name : wrongCipherReturned
Field Type : CounterBasedGauge64
Field Status : current
Description : wrong cipher returned
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.222

Field Name : writeBioNotSet
Field Type : CounterBasedGauge64
Field Status : current
Description : write bio not set
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.221

Field Name : unsupportedStatusType
Field Type : CounterBasedGauge64
Field Status : current
Description : unsupported status type
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.220

Field Name : unsupportedSslVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : unsupported ssl version
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.219

Field Name : unsupportedProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : unsupported protocol
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.218

Field Name : unsupportedOption
Field Type : CounterBasedGauge64
Field Status : current
Description : unsupported option
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.217

Field Name : unsupportedCompressionAlgorithm
Field Type : CounterBasedGauge64
Field Status : current
Description : unsupported compression algorithm
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.216

Field Name : unsupportedCipher
Field Type : CounterBasedGauge64
Field Status : current
Description : unsupported cipher
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.215

Field Name : unknownState
Field Type : CounterBasedGauge64
Field Status : current

Description : unknown state
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.214

Field Name : unknownSslVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown ssl version
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.213

Field Name : unknownRemoteErrorType
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown remote error type
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.212

Field Name : unknownProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown protocol
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.211

Field Name : unknownPkeyType
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown pkey type
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.210

Field Name : unknownKeyExchangeType
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown key exchange type
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.209

Field Name : unknownCipherType
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown cipher type
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.208

Field Name : unknownCipherReturned
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown cipher returned
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.207

Field Name : unknownCertificateType
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown certificate type
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.206

Field Name : unknownAlertType
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown alert type
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.205

Field Name : uninitialized

Field Type : CounterBasedGauge64
Field Status : current
Description : uninitialized
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.204

Field Name : unexpectedRecord
Field Type : CounterBasedGauge64
Field Status : current
Description : unexpected record
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.203

Field Name : unexpectedMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : unexpected message
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.202

Field Name : unableToLoadSsl3Sha1Routines
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to load ssl3 sha1 routines
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.201

Field Name : unableToLoadSsl3Md5Routines
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to load ssl3 md5 routines
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.200

Field Name : unableToLoadSsl2Md5Routines
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to load ssl2 md5 routines
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.199

Field Name : unableToFindSslMethod
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to find ssl method
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.198

Field Name : unableToFindPublicKeyParameters
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to find public key parameters
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.197

Field Name : unableToFindDhParameters
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to find dh parameters
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.196

Field Name : unableToExtractPublicKey
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to extract public key
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.195

Field Name : unableToDecodeDhCerts
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to decode dh certs
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.194

Field Name : triedToUseUnsupportedCipher
Field Type : CounterBasedGauge64
Field Status : current
Description : tried to use unsupported cipher
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.193

Field Name : tlsRsaEncryptedValueLengthIsWrong
Field Type : CounterBasedGauge64
Field Status : current
Description : tls rsa encrypted value length is wrong
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.192

Field Name : tlsPeerDidNotRespondWithCertList
Field Type : CounterBasedGauge64
Field Status : current
Description : tls peer did not respond with cert list
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.191

Field Name : tlsClientCertReqWithAnonCipher
Field Type : CounterBasedGauge64
Field Status : current
Description : tls client cert req with anon cipher
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.190

Field Name : tlsv1AlertUserCancelled
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert user cancelled
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.189

Field Name : tlsv1AlertUnknownCa
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert unknown ca
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.188

Field Name : tlsv1AlertRecordOverflow
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert record overflow
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.187

Field Name : tlsv1AlertProtocolVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert protocol version
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.186

Field Name : tlsv1AlertNoRenegotiation
Field Type : CounterBasedGauge64
Field Status : current

Description : tlsv1 alert no renegotiation
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.185

Field Name : tlsv1AlertInternalError
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert internal error
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.184

Field Name : tlsv1AlertInsufficientSecurity
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert insufficient security
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.183

Field Name : tlsv1AlertExportRestriction
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert export restriction
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.182

Field Name : tlsv1AlertDecryptError
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert decrypt error
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.181

Field Name : tlsv1AlertDecryptionFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert decryption failed
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.180

Field Name : tlsv1AlertDecodeError
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert decode error
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.179

Field Name : tlsv1AlertAccessDenied
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert access denied
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.178

Field Name : sslSessionIdIsDifferent
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl session id is different
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.177

Field Name : sslSessionIdHasBadLength
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl session id has bad length
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.176

Field Name : sslSessionIdContextTooLong

Field Type : CounterBasedGauge64
Field Status : current
Description : ssl session id context too long
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.175

Field Name : sslSessionIdConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl session id conflict
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.174

Field Name : sslSessionIdCallbackFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl session id callback failed
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.173

Field Name : sslLibraryHasNoCiphers
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl library has no ciphers
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.172

Field Name : sslHandshakeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl handshake failure
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.171

Field Name : sslCtxHasNoDefaultSslVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl ctx has no default ssl version
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.170

Field Name : sslv3AlertUnspportedCert
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert unspported cert
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.169

Field Name : sslv3AlertUnknownRemoteErrType
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert unknown remote err type
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.168

Field Name : sslv3AlertUnexpectedMsg
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert unexpected msg
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.167

Field Name : sslv3AlertPeerErrorUnsuppCertType
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert peer error unsupp cert type
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.166

Field Name : sslv3AlertPeerErrorNoCipher
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert peer error no cipher
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.165

Field Name : sslv3AlertPeerErrorNoCert
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert peer error no cert
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.164

Field Name : sslv3AlertPeerErrorCert
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert peer error cert
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.163

Field Name : sslv3AlertNoCertificate
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert no certificate
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.162

Field Name : sslv3AlertIllegalParameter
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert illegal parameter
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.161

Field Name : sslv3AlertHandshakeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert handshake failure
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.160

Field Name : sslv3AlertDecompressionFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert decompression failure
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.159

Field Name : sslv3AlertCertificateUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert certificate unknown
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.158

Field Name : sslv3AlertCertificateRevoked
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert certificate revoked
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.157

Field Name : sslv3AlertCertificateExpired
Field Type : CounterBasedGauge64
Field Status : current

Description : sslv3 alert certificate expired
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.156

Field Name : sslv3AlertBadRecordMac
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert bad record mac
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.155

Field Name : sslv3AlertBadCertificate
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert bad certificate
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.154

Field Name : ssl3SessionIdTooShort
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl3 session id too short
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.153

Field Name : ssl3SessionIdTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl3 session id too long
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.152

Field Name : ssl2ConnectionIdTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl2 connection id too long
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.151

Field Name : ssl23DoingSessionIdReuse
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl23 doing session id reuse
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.150

Field Name : signatureForNonSigningCertificate
Field Type : CounterBasedGauge64
Field Status : current
Description : signature for non signing certificate
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.149

Field Name : shortRead
Field Type : CounterBasedGauge64
Field Status : current
Description : short read
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.148

Field Name : sessionIdContextUninitialized
Field Type : CounterBasedGauge64
Field Status : current
Description : session id context uninitialized
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.147

Field Name : scsvReceivedWhenRenegotiating

Field Type : CounterBasedGauge64
Field Status : current
Description : scsv received when renegotiating
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.146

Field Name : reuseCipherListNotZero
Field Type : CounterBasedGauge64
Field Status : current
Description : reuse cipher list not zero
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.145

Field Name : reuseCertTypeNotZero
Field Type : CounterBasedGauge64
Field Status : current
Description : reuse cert type not zero
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.144

Field Name : reuseCertLengthNotZero
Field Type : CounterBasedGauge64
Field Status : current
Description : reuse cert length not zero
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.143

Field Name : requiredCipherMissing
Field Type : CounterBasedGauge64
Field Status : current
Description : required cipher missing
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.142

Field Name : recordTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : record too small
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.141

Field Name : recordTooLarge
Field Type : CounterBasedGauge64
Field Status : current
Description : record too large
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.140

Field Name : recordLengthMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : record length mismatch
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.139

Field Name : readWrongPacketType
Field Type : CounterBasedGauge64
Field Status : current
Description : read wrong packet type
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.138

Field Name : readBioNotSet
Field Type : CounterBasedGauge64
Field Status : current
Description : read bio not set
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.137

Field Name : publicKeyNotRsa
Field Type : CounterBasedGauge64
Field Status : current
Description : public key not rsa
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.136

Field Name : publicKeyIsNotRsa
Field Type : CounterBasedGauge64
Field Status : current
Description : public key is not rsa
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.135

Field Name : publicKeyEncryptError
Field Type : CounterBasedGauge64
Field Status : current
Description : public key encrypt error
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.134

Field Name : protocolIsShutdown
Field Type : CounterBasedGauge64
Field Status : current
Description : protocol is shutdown
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.133

Field Name : problemsMappingCipherFunctions
Field Type : CounterBasedGauge64
Field Status : current
Description : problems mapping cipher functions
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.132

Field Name : preMacLengthTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : pre mac length too long
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.131

Field Name : peerErrorUnsupportedCertificateType
Field Type : CounterBasedGauge64
Field Status : current
Description : peer error unsupported certificate type
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.130

Field Name : peerErrorNoCipher
Field Type : CounterBasedGauge64
Field Status : current
Description : peer error no cipher
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.129

Field Name : peerErrorNoCertificate
Field Type : CounterBasedGauge64
Field Status : current
Description : peer error no certificate
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.128

Field Name : peerErrorCertificate
Field Type : CounterBasedGauge64
Field Status : current

Description : peer error certificate
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.127

Field Name : peerError
Field Type : CounterBasedGauge64
Field Status : current
Description : peer error
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.126

Field Name : peerDidNotReturnACertificate
Field Type : CounterBasedGauge64
Field Status : current
Description : peer did not return a certificate
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.125

Field Name : pathTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : path too long
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.124

Field Name : packetLengthTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : packet length too long
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.123

Field Name : oldSessionCipherNotReturned
Field Type : CounterBasedGauge64
Field Status : current
Description : old session cipher not returned
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.122

Field Name : nullSslMethodPassed
Field Type : CounterBasedGauge64
Field Status : current
Description : null ssl method passed
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.121

Field Name : nullSslCtx
Field Type : CounterBasedGauge64
Field Status : current
Description : null ssl ctx
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.120

Field Name : noVerifyCallback
Field Type : CounterBasedGauge64
Field Status : current
Description : no verify callback
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.119

Field Name : noSharedCipher
Field Type : CounterBasedGauge64
Field Status : current
Description : no shared cipher
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.118

Field Name : noPublickey

Field Type : CounterBasedGauge64
Field Status : current
Description : no publickey
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.117

Field Name : noProtocolsAvailable
Field Type : CounterBasedGauge64
Field Status : current
Description : no protocols available
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.116

Field Name : noPrivateKeyAssigned
Field Type : CounterBasedGauge64
Field Status : current
Description : no private key assigned
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.115

Field Name : noPrivatekey
Field Type : CounterBasedGauge64
Field Status : current
Description : no privatekey
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.114

Field Name : noMethodSpecified
Field Type : CounterBasedGauge64
Field Status : current
Description : no method specified
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.113

Field Name : noCompressionSpecified
Field Type : CounterBasedGauge64
Field Status : current
Description : no compression specified
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.112

Field Name : noClientCertReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : no client cert received
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.111

Field Name : noCipherMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : no cipher match
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.110

Field Name : noCipherList
Field Type : CounterBasedGauge64
Field Status : current
Description : no cipher list
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.109

Field Name : noCiphersSpecified
Field Type : CounterBasedGauge64
Field Status : current
Description : no ciphers specified
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.108

Field Name : noCiphersPassed
Field Type : CounterBasedGauge64
Field Status : current
Description : no ciphers passed
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.107

Field Name : noCiphersAvailable
Field Type : CounterBasedGauge64
Field Status : current
Description : no ciphers available
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.106

Field Name : noCertificateSpecified
Field Type : CounterBasedGauge64
Field Status : current
Description : no certificate specified
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.105

Field Name : noCertificateSet
Field Type : CounterBasedGauge64
Field Status : current
Description : no certificate set
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.104

Field Name : noCertificateReturned
Field Type : CounterBasedGauge64
Field Status : current
Description : no certificate returned
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.103

Field Name : noCertificateAssigned
Field Type : CounterBasedGauge64
Field Status : current
Description : no certificate assigned
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.102

Field Name : noCertificatesReturned
Field Type : CounterBasedGauge64
Field Status : current
Description : no certificates returned
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.101

Field Name : nonSslv2InitialPacket
Field Type : CounterBasedGauge64
Field Status : current
Description : non sslv2 initial packet
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.100

Field Name : missingVerifyMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : missing verify message
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.99

Field Name : missingTmpRsaPkey
Field Type : CounterBasedGauge64
Field Status : current

Description : missing tmp rsa pkey
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.98

Field Name : missingTmpRsaKey
Field Type : CounterBasedGauge64
Field Status : current
Description : missing tmp rsa key
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.97

Field Name : missingTmpDhKey
Field Type : CounterBasedGauge64
Field Status : current
Description : missing tmp dh key
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.96

Field Name : missingRsaSigningCert
Field Type : CounterBasedGauge64
Field Status : current
Description : missing rsa signing cert
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.95

Field Name : missingRsaEncryptingCert
Field Type : CounterBasedGauge64
Field Status : current
Description : missing rsa encrypting cert
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.94

Field Name : missingRsaCertificate
Field Type : CounterBasedGauge64
Field Status : current
Description : missing rsa certificate
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.93

Field Name : missingExportTmpRsaKey
Field Type : CounterBasedGauge64
Field Status : current
Description : missing export tmp rsa key
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.92

Field Name : missingExportTmpDhKey
Field Type : CounterBasedGauge64
Field Status : current
Description : missing export tmp dh key
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.91

Field Name : missingDsaSigningCert
Field Type : CounterBasedGauge64
Field Status : current
Description : missing dsa signing cert
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.90

Field Name : missingDhRsaCert
Field Type : CounterBasedGauge64
Field Status : current
Description : missing dh rsa cert
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.89

Field Name : missingDhKey

Field Type : CounterBasedGauge64
Field Status : current
Description : missing dh key
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.88

Field Name : missingDhDsaCert
Field Type : CounterBasedGauge64
Field Status : current
Description : missing dh dsa cert
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.87

Field Name : messageTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : message too long
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.86

Field Name : mastKeyTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : mast key too long
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.85

Field Name : libraryHasNoCiphers
Field Type : CounterBasedGauge64
Field Status : current
Description : library has no ciphers
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.84

Field Name : libraryBug
Field Type : CounterBasedGauge64
Field Status : current
Description : library bug
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.83

Field Name : lengthTooShort
Field Type : CounterBasedGauge64
Field Status : current
Description : length too short
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.82

Field Name : lengthMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : length mismatch
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.81

Field Name : krb5ServerTktSkew
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 server tkt skew
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.80

Field Name : krb5ServerTktNotYetValid
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 server tkt not yet valid
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.79

Field Name : krb5ServerTktExpired
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 server tkt expired
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.78

Field Name : krb5ServerRdReq
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 server rd_req
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.77

Field Name : krb5ServerInit
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 server init
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.76

Field Name : krb5ServerBadTicket
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 server bad ticket
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.75

Field Name : krb5ClientMkReq
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 client mk_req
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.74

Field Name : krb5ClientInit
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 client init
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.73

Field Name : krb5ClientGetCred
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 client get cred
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.72

Field Name : krb5ClientCcPrincipal
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 client cc principal
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.71

Field Name : krb5
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.70

Field Name : keyArgTooLong
Field Type : CounterBasedGauge64
Field Status : current

Description : key arg too long
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.69

Field Name : invalidTrust
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid trust
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.68

Field Name : invalidStatusResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid status response
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.67

Field Name : invalidPurpose
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid purpose
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.66

Field Name : invalidCommand
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid command
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.65

Field Name : invalidChallengeLength
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid challenge length
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.64

Field Name : inappropriateFallback
Field Type : CounterBasedGauge64
Field Status : current
Description : inappropriate fallback
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.63

Field Name : illegalPadding
Field Type : CounterBasedGauge64
Field Status : current
Description : illegal padding
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.62

Field Name : httpRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : http request
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.61

Field Name : httpsProxyRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : https proxy request
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.60

Field Name : gotAFinBeforeACcs

Field Type : CounterBasedGauge64
Field Status : current
Description : got a fin before a ccs
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.59

Field Name : extraDataInMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : extra data in message
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.58

Field Name : excessiveMessageSize
Field Type : CounterBasedGauge64
Field Status : current
Description : excessive message size
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.57

Field Name : errorInReceivedCipherList
Field Type : CounterBasedGauge64
Field Status : current
Description : error in received cipher list
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.56

Field Name : errorGeneratingTmpRsaKey
Field Type : CounterBasedGauge64
Field Status : current
Description : error generating tmp rsa key
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.55

Field Name : encryptedLengthTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : encrypted length too long
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.54

Field Name : digestCheckFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : digest check failed
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.53

Field Name : dhPublicValueLengthIsWrong
Field Type : CounterBasedGauge64
Field Status : current
Description : dh public value length is wrong
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.52

Field Name : decryptionFailedOrBadRecordMac
Field Type : CounterBasedGauge64
Field Status : current
Description : decryption failed or bad record mac
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.51

Field Name : decryptionFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : decryption failed
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.50

Field Name : dataLengthTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : data length too long
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.49

Field Name : dataBetweenCcsAndFinished
Field Type : CounterBasedGauge64
Field Status : current
Description : data between ccs and finished
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.48

Field Name : connectionTypeNotSet
Field Type : CounterBasedGauge64
Field Status : current
Description : connection type not set
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.47

Field Name : connectionIdIsDifferent
Field Type : CounterBasedGauge64
Field Status : current
Description : connection id is different
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.46

Field Name : compressionLibraryError
Field Type : CounterBasedGauge64
Field Status : current
Description : compression library error
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.45

Field Name : compressionFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : compression failure
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.44

Field Name : compressedLengthTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : compressed length too long
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.43

Field Name : cipherTableSrcError
Field Type : TABLE
Field Status : current
Description : cipher table src error
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.42

Field Name : cipherOrHashUnavailable
Field Type : CounterBasedGauge64
Field Status : current
Description : cipher or hash unavailable
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.41

Field Name : cipherCodeWrongLength
Field Type : CounterBasedGauge64
Field Status : current

Description : cipher code wrong length
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.40

Field Name : challengeIsDifferent
Field Type : CounterBasedGauge64
Field Status : current
Description : challenge is different
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.39

Field Name : certLengthMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : cert length mismatch
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.38

Field Name : certificateVerifyFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : certificate verify failed
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.37

Field Name : ccsReceivedEarly
Field Type : CounterBasedGauge64
Field Status : current
Description : ccs received early
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.36

Field Name : caDnTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : ca dn too long
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.35

Field Name : caDnLengthMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : ca dn length mismatch
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.34

Field Name : bnLib
Field Type : CounterBasedGauge64
Field Status : current
Description : bn lib
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.33

Field Name : blockCipherPadIsWrong
Field Type : CounterBasedGauge64
Field Status : current
Description : block cipher pad is wrong
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.32

Field Name : bioNotSet
Field Type : CounterBasedGauge64
Field Status : current
Description : bio not set
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.31

Field Name : badWriteRetry

Field Type : CounterBasedGauge64
Field Status : current
Description : bad write retry
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.30

Field Name : badState
Field Type : CounterBasedGauge64
Field Status : current
Description : bad state
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.29

Field Name : badSslSessionIdLength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad ssl session id length
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.28

Field Name : badSslFiletype
Field Type : CounterBasedGauge64
Field Status : current
Description : bad ssl filetype
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.27

Field Name : badSignature
Field Type : CounterBasedGauge64
Field Status : current
Description : bad signature
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.26

Field Name : badRsaSignature
Field Type : CounterBasedGauge64
Field Status : current
Description : bad rsa signature
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.25

Field Name : badRsaModulusLength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad rsa modulus length
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.24

Field Name : badRsaELength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad rsa e length
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.23

Field Name : badRsaEncrypt
Field Type : CounterBasedGauge64
Field Status : current
Description : bad rsa encrypt
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.22

Field Name : badRsaDecrypt
Field Type : CounterBasedGauge64
Field Status : current
Description : bad rsa decrypt
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.21

Field Name : badResponseArgument
Field Type : CounterBasedGauge64
Field Status : current
Description : bad response argument
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.20

Field Name : badProtocolVersionNumber
Field Type : CounterBasedGauge64
Field Status : current
Description : bad protocol version number
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.19

Field Name : badPacketLength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad packet length
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.18

Field Name : badMessageType
Field Type : CounterBasedGauge64
Field Status : current
Description : bad message type
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.17

Field Name : badMacDecode
Field Type : CounterBasedGauge64
Field Status : current
Description : bad mac decode
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.16

Field Name : badLength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad length
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.15

Field Name : badHelloRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : bad hello request
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.14

Field Name : badDsaSignature
Field Type : CounterBasedGauge64
Field Status : current
Description : bad dsa signature
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.13

Field Name : badDigestLength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad digest length
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.12

Field Name : badDhPLength
Field Type : CounterBasedGauge64
Field Status : current

Description : bad dh p length
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.11

Field Name : badDhPubKeyLength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad dh pub key length
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.10

Field Name : badDhGLength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad dh g length
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.9

Field Name : badDecompression
Field Type : CounterBasedGauge64
Field Status : current
Description : bad decompression
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.8

Field Name : badDataReturnedByCallback
Field Type : CounterBasedGauge64
Field Status : current
Description : bad data returned by callback
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.7

Field Name : badChecksum
Field Type : CounterBasedGauge64
Field Status : current
Description : bad checksum
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.6

Field Name : badChangeCipherSpec
Field Type : CounterBasedGauge64
Field Status : current
Description : bad change cipher spec
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.5

Field Name : badAuthenticationType
Field Type : CounterBasedGauge64
Field Status : current
Description : bad authentication type
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.4

Field Name : badAlertRecord
Field Type : CounterBasedGauge64
Field Status : current
Description : bad alert record
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.3

Field Name : attemptToReuseSessInDiffContext
Field Type : CounterBasedGauge64
Field Status : current
Description : attempt to reuse sess in diff context
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.2

Field Name : appDataInHandshake

Field Type : CounterBasedGauge64
Field Status : current
Description : app data in handshake
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.1

Field Name : fwFullConeSessionSessionTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.16.1

Field Name : fwFullConeSessionSessionEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.16.1.1

Field Name : age
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.16.1.1.7

Field Name : cpu
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.16.1.1.6

Field Name : inbound
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.16.1.1.5

Field Name : outbound
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.16.1.1.4

Field Name : insidePort
Field Type : INTEGER
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.16.1.1.3

Field Name : insideAddress
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.16.1.1.2

Field Name : protocol
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.16.1.1.1

Field Name : fwRateLimitRateLimitTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1

Field Name : totalEntriesScopeParentRadiusUserid
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.16

Field Name : totalEntriesScopeParentRadiusUsergroup
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.15

Field Name : totalEntriesScopeParentSubscriberPrefix
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.14

Field Name : totalEntriesScopeParentSubscriberIp
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.13

Field Name : totalEntriesScopeParent
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.12

Field Name : totalEntriesScopeRadiusUserid
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.11

Field Name : totalEntriesScopeRadiusUsergroup
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.10

Field Name : totalEntriesScopeSubscriberPrefix
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.9

Field Name : totalEntriesScopeSubscriberIp
Field Type : CounterBasedGauge64
Field Status : current

Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.8

Field Name : totalEntriesScopeAggregate
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.7

Field Name : totalNumEntriesFreed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.6

Field Name : totalNumEntriesAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.5

Field Name : totalNumEntries
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.4

Field Name : allocFailures
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.3

Field Name : memUsed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.2

Field Name : fwRateLimitRateLimitEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1

Field Name : memReserved
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1

Field Name : dropCount
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1.15

Field Name : totalTrafficAllowed

Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1.14

Field Name : totalTrafficReceived
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1.13

Field Name : downlinkTrafficAllowed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1.12

Field Name : downlinkTrafficReceived
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1.11

Field Name : uplinkTrafficAllowed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1.10

Field Name : uplinkTrafficReceived
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1.9

Field Name : cpsAllowed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1.8

Field Name : cpsReceived
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1.7

Field Name : type
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1.6

Field Name : templateId
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1.5

Field Name : ruleName
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1.4

Field Name : prefixLen
Field Type : INTEGER
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1.3

Field Name : address
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1.2

Field Name : stringValue
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1.1

Field Name : fwLimitEntryLimitEntryTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.20.1

Field Name : fwLimitEntryLimitEntryEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.20.1.1

Field Name : type
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.20.1.1.7

Field Name : maxCount
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.20.1.1.6

Field Name : currCount
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.20.1.1.5

Field Name : ruleName
Field Type : String
Field Status : current

Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.20.1.1.4

Field Name : stringValue
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.20.1.1.3

Field Name : prefixLen
Field Type : INTEGER
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.20.1.1.2

Field Name : address
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.20.1.1.1

Field Name : radiusEntriesFree
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.18.6

Field Name : radiusEntriesUsed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.18.5

Field Name : smpSessionsFree
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.18.4

Field Name : smpSessionsUsed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.18.3

Field Name : dataSessionsFree
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.18.2

Field Name : dataSessionsUsed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.18.1

Field Name : axGslbGroupMemberLeaveGroup

Field Type : Trap
Field Status : none
Description : The GSLB group member is leaving a group.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.26

Field Name : axGslbGroupMemberJoinGroup
Field Type : Trap
Field Status : none
Description : The GSLB group member is joining a group.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.25

Field Name : axGslbGroupRemovedMaster
Field Type : Trap
Field Status : none
Description : The GSLB group is removed from the Master.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.24

Field Name : axGslbGroupBecomeMaster
Field Type : Trap
Field Status : none
Description : The GSLB group becomes the Master.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.23

Field Name : axGslbZoneServiceOperationalStateDown
Field Type : Trap
Field Status : none
Description : The GSLB zone service is operational down.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.22

Field Name : axGslbZoneServiceOperationalStateUp
Field Type : Trap
Field Status : none
Description : The GSLB zone service is operational up.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.21

Field Name : axGslbZoneServiceAdminDisabled
Field Type : Trap
Field Status : none
Description : The GSLB zone service is administratively disabled.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.20

Field Name : axGslbZoneServiceAdminEnabled
Field Type : Trap
Field Status : none
Description : The GSLB zone service is administratively enabled.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.19

Field Name : axGslbZoneOperationalStateDown
Field Type : Trap
Field Status : none
Description : The GSLB zone is operational down.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.18

Field Name : axGslbZoneOperationalStateUp
Field Type : Trap
Field Status : none
Description : The GSLB zone is operational up.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.17

Field Name : axGslbZoneAdminDisabled
Field Type : Trap
Field Status : none
Description : The GSLB zone status is administratively disabled.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.16

Field Name : axGslbZoneAdminEnabled
Field Type : Trap
Field Status : none
Description : The GSLB zone status is administratively enabled.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.15

Field Name : axGslbServiceIpPortStateDown
Field Type : Trap
Field Status : none
Description : The GSLB service IP port status is changed to down.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.14

Field Name : axGslbServiceIpPortStateUp
Field Type : Trap
Field Status : none
Description : The GSLB service IP port status is changed to up.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.13

Field Name : axGslbServiceIpOperationalStateDown
Field Type : Trap
Field Status : none
Description : The GSLB service IP is operational down.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.12

Field Name : axGslbServiceIpOperationalStateUp
Field Type : Trap
Field Status : none
Description : The GSLB service IP is operational up.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.11

Field Name : axGslbServiceIpAdminDisabled
Field Type : Trap
Field Status : none
Description : The GSLB service IP is administratively disabled.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.10

Field Name : axGslbServiceIpAdminEnabled
Field Type : Trap
Field Status : none
Description : The GSLB service IP is administratively enabled.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.9

Field Name : axGslbSiteSlbDeviceStateDown
Field Type : Trap
Field Status : none
Description : The GSLB site SLB device status is changed to down.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.6

Field Name : axGslbSiteSlbDeviceStateUp
Field Type : Trap
Field Status : none

Description : The GSLB site SLB device status is changed to up.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.5

Field Name : axGslbSiteOperationalStateDown
Field Type : Trap
Field Status : none
Description : The GSLB site is operational down.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.4

Field Name : axGslbSiteOperationalStateUp
Field Type : Trap
Field Status : none
Description : The GSLB site is operational up.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.3

Field Name : axGslbSiteAdminDisabled
Field Type : Trap
Field Status : none
Description : The GSLB site is administratively disabled.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.2

Field Name : axGslbSiteAdminEnabled
Field Type : Trap
Field Status : none
Description : The GSLB site is administratively enabled.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.1

Field Name : axNetworkTrunkPortsThreshold
Field Type : Trap
Field Status : none
Description : The trunk ports threshold trap.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.3.1

Field Name : axServiceBwRateResume
Field Type : Trap
Field Status : none
Description : A SLB service has reached the configured bandwidth rate resuming value.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.40

Field Name : axServiceBwRateLimit
Field Type : Trap
Field Status : none
Description : A SLB service has reached the configured bandwidth rate limit.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.39

Field Name : axServerBwRateResume
Field Type : Trap
Field Status : none
Description : A SLB server has reached the configured bandwidth rate resuming value.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.38

Field Name : axServerBwRateLimit
Field Type : Trap
Field Status : none
Description : A SLB server has reached the configured bandwidth rate limit.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.37

Field Name : axGatewayDown

Field Type : Trap
Field Status : none
Description : A gateway server is down.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.36

Field Name : axGatewayUp
Field Type : Trap
Field Status : none
Description : A gateway server is up.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.35

Field Name : axVcsStateChange
Field Type : Trap
Field Status : none
Description : A VCS state change notification.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.34

Field Name : axServiceGroupMemberDown
Field Type : Trap
Field Status : none
Description : A SLB service group member is down.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.33

Field Name : axServiceGroupMemberUp
Field Type : Trap
Field Status : none
Description : A SLB service group member is up.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.32

Field Name : axServiceGroupDown
Field Type : Trap
Field Status : none
Description : A SLB service group is down.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.31

Field Name : axServiceGroupUp
Field Type : Trap
Field Status : none
Description : A SLB service group is Up.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.30

Field Name : axServerDisabled
Field Type : Trap
Field Status : none
Description : A SLB server is disabled.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.29

Field Name : axVirtualServerDown
Field Type : Trap
Field Status : none
Description : Slb virtual server is down.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.28

Field Name : axVirtualServerUp
Field Type : Trap
Field Status : none
Description : Slb virtual server is up.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.27

Field Name : axServerSelectionFailure
Field Type : Trap
Field Status : none
Description : A SLB server has got a server selection failure.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.26

Field Name : axSslServerCertificateErr
Field Type : Trap
Field Status : none
Description : The SSL server certificate error is detected.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.25

Field Name : axVrrpStandby
Field Type : Trap
Field Status : none
Description : The vrid, axNotificationVrid, in the specific partition becomes the Standby state.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.24

Field Name : axVrrpActive
Field Type : Trap
Field Status : none
Description : The vrid, axNotificationVrid, in the specific partition becomes the Active state.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.23

Field Name : axServiceGroupMemberDisabledForNewConn
Field Type : Trap
Field Status : none
Description : A SLB service group member is disabled, when the current connections of group members are reduced to the conn-resume.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.22

Field Name : axServiceGroupMemberEnabledForNewConn
Field Type : Trap
Field Status : none
Description : A SLB service group member is enabled to accept the new connection, when the current connections of group members exceed the conn-limit.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.21

Field Name : axServiceConnRateLimit
Field Type : Trap
Field Status : none
Description : A SLB service group member has reached the configured conn-rate-limits.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.20

Field Name : axServerConnRateLimit
Field Type : Trap
Field Status : none
Description : A SLB server has reached the configured conn-rate-limits.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.19

Field Name : axVirtualServerReachConnRateLimit
Field Type : Trap
Field Status : none
Description : A virtual server has reached the configured connection rate-limits.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.18

Field Name : axVirtualServerReachConnLimit
Field Type : Trap
Field Status : none
Description : A virtual server has reached the configured connection limits.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.17

Field Name : axVirtualServerPortReachConnRateLimit
Field Type : Trap
Field Status : none
Description : A virtual service port has reached the configured connection rate-limits.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.16

Field Name : axVirtualServerPortReachConnLimit
Field Type : Trap
Field Status : none
Description : A virtual service port has reached the configured connection limits.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.15

Field Name : axApplicationBufferReachLimit
Field Type : Trap
Field Status : none
Description : The AX SLB application buffer usage exceeeded the configured threshold.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.14

Field Name : axVirtualServerPortUp
Field Type : Trap
Field Status : none
Description : A SLB virtual server port is up.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.13

Field Name : axVirtualServerPortDown
Field Type : Trap
Field Status : none
Description : A SLB virtual server port is down.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.12

Field Name : axServiceConnResume
Field Type : Trap
Field Status : none
Description : A SLB service has reached the configured connection-resume value.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.11

Field Name : axServiceConnLimit
Field Type : Trap
Field Status : none
Description : A SLB service has reached the configured connection limits.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.10

Field Name : axServerConnResume
Field Type : Trap
Field Status : none
Description : A SLB server has reached the configured connection-resume value.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.9

Field Name : axServerConnLimit
Field Type : Trap
Field Status : none

Description : A SLB server has reached the configured connection limits.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.8

Field Name : axServerUp
Field Type : Trap
Field Status : none
Description : A SLB server is up.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.7

Field Name : axServerDown
Field Type : Trap
Field Status : none
Description : A SLB server is down.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.6

Field Name : axServiceUp
Field Type : Trap
Field Status : none
Description : A SLB service is up.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.5

Field Name : axServiceDown
Field Type : Trap
Field Status : none
Description : A service is detected DOWN.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.4

Field Name : axHAActiveActive
Field Type : Trap
Field Status : none
Description : The system is going into active-active mode.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.3

Field Name : axHAActive
Field Type : Trap
Field Status : none
Description : The system is going into active mode.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.2

Field Name : axHAStandby
Field Type : Trap
Field Status : none
Description : The system is going into standby mode.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.1

Field Name : axSystemBandwidthThresholdAlert
Field Type : Trap
Field Status : none
Description : The system bandwidth has crossed the threshold.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.45

Field Name : axAppsGlobalCpsThreshold
Field Type : Trap
Field Status : none
Description : The Connections Per Second (CPS) has crossed the threshold.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.44

Field Name : axAppsGlobalSessionsThreshold

Field Type : Trap
Field Status : none
Description : The number of Sessions has crossed the threshold.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.43

Field Name : axSystemLicenseModuleDisabled
Field Type : Trap
Field Status : none
Description : The license module is disabled.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.42

Field Name : axHighPrioritySyslog
Field Type : Trap
Field Status : none
Description : The high severity issue such as hardware failure.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.41

Field Name : axTacacsMonitorServerUpDown
Field Type : Trap
Field Status : none
Description : The AX Tacacs Monitor Server is up/down.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.39

Field Name : axSystemSmpResourceBecomeNormal
Field Type : Trap
Field Status : none
Description : The SMP is back to normal.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.38

Field Name : axSystemSmpResourceHigh
Field Type : Trap
Field Status : none
Description : The system SMP is high.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.37

Field Name : axSystemConnectionResourceBecomeNormal
Field Type : Trap
Field Status : none
Description : The system connection is back to normal.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.36

Field Name : axSystemConnectionResourceHigh
Field Type : Trap
Field Status : none
Description : The system connection is high.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.35

Field Name : axSystemPowerSupplyRecover
Field Type : Trap
Field Status : none
Description : The system power supply is recover.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.34

Field Name : axSystemFanRecover
Field Type : Trap
Field Status : none
Description : The system fan is recover.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.33

Field Name : axMemoryUsageBecomeNormal
Field Type : Trap
Field Status : none
Description : The memory usage is back to normal.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.32

Field Name : axHardDiskUsageBecomeNormal
Field Type : Trap
Field Status : none
Description : The hard disk usage is back to normal.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.31

Field Name : axSystemTempBecomeNormal
Field Type : Trap
Field Status : none
Description : The system tempature is back to normal, axNotificationMsg will contain the system temperature index if it not default system temperature.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.30

Field Name : axSystemDataCpuBecomeNormal
Field Type : Trap
Field Status : none
Description : The AX data CPU usage is back to normal.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.29

Field Name : axSystemControlCpuBecomeNormal
Field Type : Trap
Field Status : none
Description : The AX control CPU usage is back to normal.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.28

Field Name : axSystemLicensedModuleDisabledForDuration
Field Type : Trap
Field Status : none
Description : The system disables the specific licensed module for the past duration seconds.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.27

Field Name : axFileSystemBecomeReadOnly
Field Type : Trap
Field Status : none
Description : The file system is becoming the read-only.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.26

Field Name : axSystemShutdownForReason
Field Type : Trap
Field Status : none
Description : The AX system is mandatorily shut down.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.25

Field Name : axSystemLicenseExpiring
Field Type : Trap
Field Status : none
Description : The license is expiring or will expire at the given time.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.24

Field Name : axSystemLicenseLoadSuccessful

Field Type : Trap
Field Status : none
Description : The system loads the license for specific module successfully.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.23

Field Name : axSystemLicenseRequired
Field Type : Trap
Field Status : none
Description : The system requires the valid license for specific module.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.22

Field Name : axSystemPowerSupplyFailure
Field Type : Trap
Field Status : none
Description : The system power supply is failed.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.21

Field Name : axSystemFanFailure
Field Type : Trap
Field Status : none
Description : The system fan is failed.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.20

Field Name : axSystemDataCpuHigh
Field Type : Trap
Field Status : none
Description : The AX data CPU usage is high.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.19

Field Name : axSystemControlCpuHigh
Field Type : Trap
Field Status : none
Description : The AX control CPU usage is high.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.18

Field Name : axSystemRelieveDropPacketEvent
Field Type : Trap
Field Status : none
Description : The AX recovers from the packet dropped before.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.17

Field Name : axSystemDropPacketEvent
Field Type : Trap
Field Status : none
Description : The AX experiences the packet dropped of axNotificationDroppedPackets.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.16

Field Name : axSystemRestart
Field Type : Trap
Field Status : none
Description : Notify that the agent has been restarted.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.15

Field Name : axMemoryUsageHigh
Field Type : Trap
Field Status : none
Description : The memory usage is high.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.14

Field Name : axHardDiskUsageHigh
Field Type : Trap
Field Status : none
Description : The hard disk usage is high.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.13

Field Name : axSecondaryHardDiskFailure
Field Type : Trap
Field Status : none
Description : The secondary hard disk is failed.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.12

Field Name : axPrimaryHardDiskFailure
Field Type : Trap
Field Status : none
Description : The primary hard disk is failed.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.11

Field Name : axLowerPowerSupplyFailure
Field Type : Trap
Field Status : none
Description : The system lower power supply is failed.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.10

Field Name : axUpperPowerSupplyFailure
Field Type : Trap
Field Status : none
Description : The system upper power supply is failed.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.9

Field Name : axSystemTempLow
Field Type : Trap
Field Status : none
Description : The system temperature is low, axNotificationMsg will contain system temperature index if it is not default system temperature.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.7

Field Name : axFan3Failure
Field Type : Trap
Field Status : none
Description : The system fan3 is failed.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.6

Field Name : axFan2Failure
Field Type : Trap
Field Status : none
Description : The system fan2 is failed.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.5

Field Name : axFan1Failure
Field Type : Trap
Field Status : none
Description : The system fan1 is failed.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.4

Field Name : axSystemTempHigh
Field Type : Trap

Field Status : none
Description : The system temperature is high, axNotificationMsg will contain system temperature index if it is not default system temperature.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.3

Field Name : axSystemShutdown
Field Type : Trap
Field Status : none
Description : Notify that the system is in the process of being shut down.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.2

Field Name : axSystemStart
Field Type : Trap
Field Status : none
Description : Notify that the system has started running.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.1

Field Name : axSlbQpsLowToNormal
Field Type : Trap
Field Status : none
Description : The QPS is changed from low to normal.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.6.16

Field Name : axSlbQpsLow
Field Type : Trap
Field Status : none
Description : The QPS is changed from normal to low.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.6.15

Field Name : axSlbQpsHighToNormal
Field Type : Trap
Field Status : none
Description : The QPS is changed from high to normal.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.6.14

Field Name : axSlbQpsHigh
Field Type : Trap
Field Status : none
Description : The QPS is changed from normal to high.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.6.13

Field Name : axSlbSystemThresholdLowBecomeNormal
Field Type : Trap
Field Status : none
Description : The slb system level resource indicated by
: axNotificationSlbThresholdResourceId is changed from low to normal.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.6.12

Field Name : axSlbSystemThresholdLow
Field Type : Trap
Field Status : none
Description : The slb system level resource indicated by
: axNotificationSlbThresholdResourceId is lower than the configured
: threshold.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.6.11

Field Name : axSlbSystemThresholdHighBecomeNormal
Field Type : Trap

Field Status : none
Description : The slb system level resource indicated by
: axNotificationSlbThresholdResourceId is changed from high to normal.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.6.10

Field Name : axSlbSystemThresholdHigh
Field Type : Trap
Field Status : none
Description : The slb system level resource indicated by
: axNotificationSlbThresholdResourceId is higher than the configured
: threshold.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.6.9

Field Name : axPartitionResourceUsageWarning
Field Type : Trap
Field Status : none
Description : The partition resource usage becomes above/below the configured limitation.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.6.7

Field Name : axSslCertificateExpiring
Field Type : Trap
Field Status : none
Description : The certification is going to be expired.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.6.6

Field Name : axSslCertificateCreateDelete
Field Type : Trap
Field Status : none
Description : Ssl certification is create or delete.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.6.5

Field Name : axServerPortCreateDelete
Field Type : Trap
Field Status : none
Description : Slb server port is added or delete.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.6.4

Field Name : axServerCreateDelete
Field Type : Trap
Field Status : none
Description : Slb server is added or deleted.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.6.3

Field Name : axVirtualServerPortCreateDelete
Field Type : Trap
Field Status : none
Description : Slb virtual server port is addeded or deleted.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.6.2

Field Name : axVirtualServerCreateDelete
Field Type : Trap
Field Status : none
Description : Slb virtual server is added or deleted.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.6.1

Field Name : axLsnFixedNatPortMappingFileChange
Field Type : Trap
Field Status : none

Description : LSN: Fixed nat porting mapping file change.Fixed nat porting mapping file change.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.4.14

Field Name : axLsnSessionUserQuotasExceed
Field Type : Trap
Field Status : none
Description : LSN: Session user-quota exceeded on a specific pool.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.4.13

Field Name : axLsnFullconeCreationFailed
Field Type : Trap
Field Status : none
Description : LSN: Full-cone session creation failed (out-of-memory) for a specific pool.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.4.12

Field Name : axLsnTrafficNewUserQuotasCreationFailed
Field Type : Trap
Field Status : none
Description : LSN: User-quota creation failed (out of memory) for a specific pool.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.4.11

Field Name : axLsnTrafficTcpExtendedUserQuotasExceed
Field Type : Trap
Field Status : none
Description : LSN: TCP extended user-quota exceeded on a specific pool.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.4.10

Field Name : axLsnTrafficUdpExtendedUserQuotasExceed
Field Type : Trap
Field Status : none
Description : LSN: UDP extended user-quota exceeded on a specific pool.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.4.9

Field Name : axLsnTrafficNewUserResourceUnavailable
Field Type : Trap
Field Status : none
Description : LSN: New user could not get a NAT IP on a specific pool.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.4.8

Field Name : axLsnTrafficNatPortUnavailable
Field Type : Trap
Field Status : none
Description : LSN: NAT port usage exceeded on a specific pool.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.4.7

Field Name : axLsnTrafficEspUserQuotasExceed
Field Type : Trap
Field Status : none
Description : LSN: ESP user-quota exceeded on a specific pool.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.4.6

Field Name : axLsnTrafficTcpUserQuotasExceed
Field Type : Trap
Field Status : none
Description : LSN: TCP user-quota exceeded on a specific pool.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.4.5

Field Name : axLsnTrafficUdpUserQuotasExceed
Field Type : Trap
Field Status : none
Description : LSN: UDP user-quota exceeded on a specific pool.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.4.4

Field Name : axLsnTrafficIcmpUserQuotasExceed
Field Type : Trap
Field Status : none
Description : LSN: ICMP user-quota exceeded on a specific pool.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.4.3

Field Name : axLsnIpAllPortExhausted
Field Type : Trap
Field Status : none
Description : LSN any IP port usage reaches the maximum threshold.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.4.2

Field Name : axLsnNatAllPortUsageReachThreshold
Field Type : Trap
Field Status : none
Description : LSN NAT total port usage reaches the maximum threshold.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.4.1

Field Name : axScaleoutTrafficMapDistribution
Field Type : Trap
Field Status : none
Description : Scale out traffic map distribution
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.7.9

Field Name : axScaleoutTrafficMapUpdate
Field Type : Trap
Field Status : none
Description : Scale out traffic map change.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.7.8

Field Name : axScaleoutNodeStatus
Field Type : Trap
Field Status : none
Description : Scale out node status change.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.7.7

Field Name : axScaleoutMasterNodeCallingReelection
Field Type : Trap
Field Status : none
Description : Scale out master node calling reelection.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.7.6

Field Name : axScaleoutElection
Field Type : Trap
Field Status : none
Description : Number of devices on Scale out election.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.7.5

Field Name : axScaleoutSingleNodeStatus
Field Type : Trap
Field Status : none
Description : Scale out sigle node status change.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.7.4

Field Name : axScaleoutServiceMaster
Field Type : Trap
Field Status : none
Description : Scale out service master change.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.7.3

Field Name : axScaleoutLocalNodeDisabled
Field Type : Trap
Field Status : none
Description : Scale out local node disabled.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.7.2

Field Name : axScaleoutVserverTrafficMap
Field Type : Trap
Field Status : none
Description : Scale out Vserver Traffic Map change.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.7.1

Field Name : stateStatsTable
Field Type : TABLE
Field Status : current
Description : HA VRRP-A Global Commands from object 'vrrp-a.state'
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1

Field Name : stateStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The stateStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1

Field Name : stateStatsQueryPktRxError
Field Type : CounterBasedGauge64
Field Status : current
Description : query_pkt_rx_error
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.180

Field Name : stateStatsSyncTxUpdateMiscCounterAct
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_update_misc_counter_act
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.179

Field Name : stateStatsSyncTxUpdateAgeCounterAct
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_update_age_counter_act
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.178

Field Name : stateStatsSyncTxDelCounterAct
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_del_counter_act
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.177

Field Name : stateStatsSyncTxCreateCounterAct
Field Type : CounterBasedGauge64

Field Status : current
Description : sync_tx_create_counter_act
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.176

Field Name : stateStatsSyncTxUpdateMiscBearer
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_update_misc_bearer
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.175

Field Name : stateStatsSyncPktRcvDcMsgDir
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_pkt_rcv_dc_msg_dir
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.174

Field Name : stateStatsSyncRxDropSyncPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_drop_sync_packets
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.173

Field Name : stateStatsSyncRxDcmsgCounterInterPu
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_dcmsg_counter_inter_pu
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.172

Field Name : stateStatsDnsCacheSyncRxErrorCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_cache_sync_rx_error_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.171

Field Name : stateStatsDnsCacheSyncTxErrorCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_cache_sync_tx_error_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.170

Field Name : stateStatsDnsCacheSyncRxFragCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_cache_sync_rx_frag_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.169

Field Name : stateStatsDnsCacheSyncTxFragCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_cache_sync_tx_frag_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.168

Field Name : stateStatsDnsCacheSyncRxDelCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_cache_sync_rx_del_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.167

Field Name : stateStatsDnsCacheSyncTxDelCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_cache_sync_tx_del_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.166

Field Name : stateStatsDnsCacheSyncRxCreateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_cache_sync_rx_create_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.165

Field Name : stateStatsDnsCacheSyncTxCreateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_cache_sync_tx_create_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.164

Field Name : stateStatsSyncRxFwSetDscpCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_fw_set_dscp_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.163

Field Name : stateStatsSyncTxFwSetDscpCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_fw_set_dscp_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.162

Field Name : stateStatsSyncRxExtFwLimitEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_fw_limit_entry
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.161

Field Name : stateStatsSyncTxAflexTableEntryNotEligibleCounter
Field Type : TABLE
Field Status : current
Description : sync_tx_aflex_table_entry_not_eligible_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.160

Field Name : stateStatsSyncTxAflexTableEntryErrorCounter
Field Type : TABLE
Field Status : current
Description : sync_tx_aflex_table_entry_error_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.159

Field Name : stateStatsSyncRxAflexTableEntryFastsyncCounter
Field Type : TABLE
Field Status : current
Description : sync_rx_aflex_table_entry_fastsync_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.158

Field Name : stateStatsSyncTxAflexTableEntryFastsyncCounter
Field Type : TABLE
Field Status : current
Description : sync_tx_aflex_table_entry_fastsync_counter

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.157

Field Name : stateStatsSyncRxAflexTableEntryTimeoutCounter
Field Type : TABLE
Field Status : current
Description : sync_rx_aflex_table_entry_timeout_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.156

Field Name : stateStatsSyncTxAflexTableEntryTimeoutCounter
Field Type : TABLE
Field Status : current
Description : sync_tx_aflex_table_entry_timeout_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.155

Field Name : stateStatsSyncRxAflexTableEntrySetCounter
Field Type : TABLE
Field Status : current
Description : sync_rx_aflex_table_entry_set_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.154

Field Name : stateStatsSyncTxAflexTableEntrySetCounter
Field Type : TABLE
Field Status : current
Description : sync_tx_aflex_table_entry_set_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.153

Field Name : stateStatsSyncRxAflexTableEntryReplaceCounter
Field Type : TABLE
Field Status : current
Description : sync_rx_aflex_table_entry_replace_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.152

Field Name : stateStatsSyncTxAflexTableEntryReplaceCounter
Field Type : TABLE
Field Status : current
Description : sync_tx_aflex_table_entry_replace_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.151

Field Name : stateStatsSyncRxAflexTableEntryLifetimeCounter
Field Type : TABLE
Field Status : current
Description : sync_rx_aflex_table_entry_lifetime_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.150

Field Name : stateStatsSyncTxAflexTableEntryLifetimeCounter
Field Type : TABLE
Field Status : current
Description : sync_tx_aflex_table_entry_lifetime_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.149

Field Name : stateStatsSyncRxAflexTableEntryLookupCounter
Field Type : TABLE
Field Status : current
Description : sync_rx_aflex_table_entry_lookup_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.148

Field Name : stateStatsSyncTxAflexTableEntryLookupCounter
Field Type : TABLE

Field Status : current
Description : sync_tx_aflex_table_entry_lookup_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.147

Field Name : stateStatsSyncRxAflexTableEntryIncrCounter
Field Type : TABLE
Field Status : current
Description : sync_rx_aflex_table_entry_incr_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.146

Field Name : stateStatsSyncTxAflexTableEntryIncrCounter
Field Type : TABLE
Field Status : current
Description : sync_tx_aflex_table_entry_incr_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.145

Field Name : stateStatsSyncRxAflexTableEntryDeleteCounter
Field Type : TABLE
Field Status : current
Description : sync_rx_aflex_table_entry_delete_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.144

Field Name : stateStatsSyncTxAflexTableEntryDeleteCounter
Field Type : TABLE
Field Status : current
Description : sync_tx_aflex_table_entry_delete_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.143

Field Name : stateStatsSyncRxAflexTableEntryAppendCounter
Field Type : TABLE
Field Status : current
Description : sync_rx_aflex_table_entry_append_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.142

Field Name : stateStatsSyncTxAflexTableEntryAppendCounter
Field Type : TABLE
Field Status : current
Description : sync_tx_aflex_table_entry_append_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.141

Field Name : stateStatsSyncRxAflexTableEntryAddCounter
Field Type : TABLE
Field Status : current
Description : sync_rx_aflex_table_entry_add_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.140

Field Name : stateStatsSyncTxAflexTableEntryAddCounter
Field Type : TABLE
Field Status : current
Description : sync_tx_aflex_table_entry_add_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.139

Field Name : stateStatsSyncRxExtFwSoShadowExtInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_fw_so_shadow_ext_info
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.138

Field Name : stateStatsSyncTxSmpClearCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_smp_clear_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.137

Field Name : stateStatsSyncRxSmpClearCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_smp_clear_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.136

Field Name : stateStatsSyncTxSmpUpdateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_smp_update_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.135

Field Name : stateStatsSyncTxSmpDeleteCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_smp_delete_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.134

Field Name : stateStatsSyncTxSmpCreateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_smp_create_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.133

Field Name : stateStatsSyncRxSmpUpdateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_smp_update_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.132

Field Name : stateStatsSyncRxSmpDeleteCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_smp_delete_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.131

Field Name : stateStatsSyncRxSmpCreateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_smp_create_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.130

Field Name : stateStatsSyncRxExtFwGtpEchoExtInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_fw_gtp_echo_ext_info
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.129

Field Name : stateStatsSyncRxUnreachedPktCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_unreached_pkt_counter

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.128

Field Name : stateStatsSyncRxOutOfOrderPktCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_out_of_order_pkt_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.127

Field Name : stateStatsQueryRxInvalidMsgDirCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : query_rx_invalid_msg_dir_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.126

Field Name : stateStatsQueryRxInvalidSyncVersionCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : query_rx_invalid_sync_version_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.125

Field Name : stateStatsQueryRxInvalidHaGroupCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : query_rx_invalid_ha_group_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.124

Field Name : stateStatsQueryRxInvalidPartitionCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : query_rx_invalid_partition_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.123

Field Name : stateStatsSyncRxAflexFragCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_aflex_frag_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.122

Field Name : stateStatsSyncRxAflexDelCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_aflex_del_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.121

Field Name : stateStatsSyncRxAflexCreateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_aflex_create_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.120

Field Name : stateStatsSyncRxAflexUpdateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_aflex_update_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.119

Field Name : stateStatsSyncRxTableEntryDelCounter
Field Type : TABLE

Field Status : current
Description : sync_rx_table_entry_del_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.118

Field Name : stateStatsSyncRxTableEntryCreateCounter
Field Type : TABLE
Field Status : current
Description : sync_rx_table_entry_create_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.117

Field Name : stateStatsSyncRxTableEntryUpdateCounter
Field Type : TABLE
Field Status : current
Description : sync_rx_table_entry_update_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.116

Field Name : stateStatsSyncRxByInactivePeerCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_by_inactive_peer_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.115

Field Name : stateStatsSyncRxNoVgrpCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_no_vgrp_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.114

Field Name : stateStatsSyncRxBadProtocolCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_bad_protocol_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.113

Field Name : stateStatsSyncPktFailedBuffCopyCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_pkt_failed_buff_copy_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.112

Field Name : stateStatsQueryPktNoReceivingIpCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : query_pkt_no_receiving_ip_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.111

Field Name : stateStatsSyncPktNoReceivingVgrpCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_pkt_no_receiving_vgrp_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.110

Field Name : stateStatsSyncPktNoSendingVgrpCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_pkt_no_sending_vgrp_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.109

Field Name : stateStatsSyncPktEmptyBuffCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_pkt_empty_buff_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.108

Field Name : stateStatsSyncRxInvalidSyncPacketCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_invalid_sync_packet_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.107

Field Name : stateStatsSyncRxDdosDropCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ddos_drop_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.106

Field Name : stateStatsSyncRxExtFwGtpLogExtInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_fw_gtp_log_ext_info
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.105

Field Name : stateStatsSyncRxExtFwGtpExtInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_fw_gtp_ext_info
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.104

Field Name : stateStatsSyncRxExtFwGtpUInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_fw_gtp_u_info
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.103

Field Name : stateStatsSyncRxExtFwGtpLogInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_fw_gtp_log_info
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.102

Field Name : stateStatsSyncRxMonEntity
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_mon_entity
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.101

Field Name : stateStatsSyncTxMonEntity
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_mon_entity
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.100

Field Name : stateStatsSyncRxExtFwApps
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_fw_apps

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.99

Field Name : stateStatsSyncRxNotExpectSyncPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_not_expect_sync_pkt
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.98

Field Name : stateStatsSyncRxExtFwGtpInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_fw_gtp_info
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.97

Field Name : stateStatsSyncRxExtDcfwRuleIdleTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_dcfw_rule_idle_timeout
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.96

Field Name : stateStatsSyncRxExtFwHttpLogging
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_fw_http_logging
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.95

Field Name : stateStatsSyncRxZoneFailureCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_zone_failure_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.94

Field Name : stateStatsSyncTxEstabCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_estab_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.93

Field Name : stateStatsSyncRxEstabCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_estab_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.92

Field Name : stateStatsSyncRxExtDcfwLog
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_dcfw_log
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.91

Field Name : stateStatsSyncRxExtDcfwRuleId
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_dcfw_rule_id
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.90

Field Name : stateStatsSyncRxExtNatAlgTcpInfo
Field Type : CounterBasedGauge64

Field Status : current
Description : sync_rx_ext_nat_alg_tcp_info
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.89

Field Name : stateStatsSyncRxUpdateSctpConnAddr
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_update_sctp_conn_addr
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.88

Field Name : stateStatsSyncTxUpdateSctpConnAddr
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_update_sctp_conn_addr
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.87

Field Name : stateStatsSyncErrLsnFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_err_lsn_fullcone
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.86

Field Name : stateStatsSyncRxLsnFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_lsn_fullcone
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.85

Field Name : stateStatsSyncTxLsnFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_lsn_fullcone
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.84

Field Name : stateStatsSyncRxExtNatMac
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_nat_mac
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.83

Field Name : stateStatsSyncRxExtH323Alg
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_h323_alg
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.82

Field Name : stateStatsSyncRxExtSipAlg
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_sip_alg
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.81

Field Name : stateStatsSyncRxExtLsnAcIdleTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_lsn_ac_idle_timeout
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.80

Field Name : stateStatsSyncRxExtLsnAcl
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_lsn_acl
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.79

Field Name : stateStatsSyncRxFtpControl
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ftp_control
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.78

Field Name : stateStatsSyncRxSeqDeltas
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_seq_deltas
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.77

Field Name : stateStatsSyncRxReserveHa
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_reserve_ha
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.76

Field Name : stateStatsSyncRxExtRtsp
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_rtsp
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.75

Field Name : stateStatsSyncRxExtPptp
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_pptp
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.74

Field Name : stateStatsSyncRxCreateStaticSby
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_create_static_sby
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.73

Field Name : stateStatsSyncRxSfw
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_sfw
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.72

Field Name : stateStatsSyncRxInsertTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_insert_tuple
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.71

Field Name : stateStatsSyncRxNatAllocSby
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_nat_alloc_sby

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.70

Field Name : stateStatsSyncRxNatCreateSby
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_nat_create_sby
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.69

Field Name : stateStatsSyncRxLsnCreateSby
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_lsn_create_sby
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.68

Field Name : stateStatsSyncGetBuffFailedPort
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_get_buff_failed_port
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.67

Field Name : stateStatsSyncGetBuffFailedRt
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_get_buff_failed_rt
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.66

Field Name : stateStatsSyncQueryDcmsgCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_query_dcmsg_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.65

Field Name : stateStatsSyncRxApptypeNotSupported
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_apptype_not_supported
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.64

Field Name : stateStatsSyncRxUnkCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_unk_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.63

Field Name : stateStatsSyncRxUpdateSeqnosCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_update_seqnos_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.62

Field Name : stateStatsSyncRxTotalInfoCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_total_info_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.61

Field Name : stateStatsSyncRxDcmsgCounter
Field Type : CounterBasedGauge64

Field Status : current
Description : sync_rx_dcmsg_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.60

Field Name : stateStatsSyncRxZeroInfoCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_zero_info_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.59

Field Name : stateStatsSyncRxTypeInvalid
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_type_invalid
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.58

Field Name : stateStatsSyncRxDelNoSuchSession
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_del_no_such_session
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.57

Field Name : stateStatsSyncRxNoSuchSgNode
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_no_such_sg_node
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.56

Field Name : stateStatsSyncRxNoSuchNatPool
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_no_such_nat_pool
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.55

Field Name : stateStatsSyncRxNoDstForVportInline
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_no_dst_for_vport_inline
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.54

Field Name : stateStatsSyncRxProtoNotSupported
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_proto_not_supported
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.53

Field Name : stateStatsSyncRxConnGetFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_conn_get_failed
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.52

Field Name : stateStatsSyncRxConnExists
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_conn_exists
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.51

Field Name : stateStatsSyncRxCreateExtBitCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_create_ext_bit_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.50

Field Name : stateStatsSyncRxExtBitProcessError
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_bit_process_error
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.49

Field Name : stateStatsSyncRxCannotProcessMandatory
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_cannot_process_mandatory
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.48

Field Name : stateStatsSyncRxNoSuchRport
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_no_such_rport
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.47

Field Name : stateStatsSyncRxNoSuchVport
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_no_such_vport
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.46

Field Name : stateStatsSyncPersistRxConnGetFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_persist_rx_conn_get_failed
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.45

Field Name : stateStatsSyncPersistRxNoSgGroupInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_persist_rx_no_sg_group_info
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.44

Field Name : stateStatsSyncPersistRxNoSuchSgGroup
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_persist_rx_no_such_sg_group
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.43

Field Name : stateStatsSyncPersistRxNoSuchRport
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_persist_rx_no_such_rport
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.42

Field Name : stateStatsSyncPersistRxVporttypeNotSupported
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_persist_rx_vporttype_not_supported

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.41

Field Name : stateStatsSyncPersistRxNoSuchVport
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_persist_rx_no_such_vport
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.40

Field Name : stateStatsSyncPersistRxExtBitProcessError
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_persist_rx_ext_bit_process_error
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.39

Field Name : stateStatsSyncPersistRxCannotProcessMandatory
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_persist_rx_cannot_process_mandatory
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.38

Field Name : stateStatsSyncPersistRxTypeInvalid
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_persist_rx_type_invalid
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.37

Field Name : stateStatsSyncPersistRxProtoNotSupported
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_persist_rx_proto_not_supported
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.36

Field Name : stateStatsSyncPersistRxLenInvalid
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_persist_rx_len_invalid
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.35

Field Name : stateStatsSyncRxLenInvalid
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_len_invalid
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.34

Field Name : stateStatsSyncTxMaxPacked
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_max_packed
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.33

Field Name : stateStatsSyncTxMinPacked
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_min_packed
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.32

Field Name : stateStatsSyncTxUpdateSeqnosCounter
Field Type : CounterBasedGauge64

Field Status : current
Description : sync_tx_update_seqnos_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.31

Field Name : stateStatsSyncTxCreateExtBitCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_create_ext_bit_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.30

Field Name : stateStatsSyncTxTotalInfoCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_total_info_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.29

Field Name : stateStatsSyncTxGetBuffFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_get_buff_failed
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.28

Field Name : stateStatsSyncPktInvalidIdxCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_pkt_invalid_idx_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.27

Field Name : stateStatsQueryRxUnkCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : query_rx_unk_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.26

Field Name : stateStatsQueryRxFullInfoCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : query_rx_full_info_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.25

Field Name : stateStatsQueryRxZeroInfoCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : query_rx_zero_info_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.24

Field Name : stateStatsQueryTxGetBuffFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : query_tx_get_buff_failed
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.23

Field Name : stateStatsQueryPktInvalidIdxCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : query_pkt_invalid_idx_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.22

Field Name : stateStatsQueryTxMinPacked
Field Type : CounterBasedGauge64
Field Status : current
Description : query_tx_min_packed
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.21

Field Name : stateStatsQueryTxMaxPacked
Field Type : CounterBasedGauge64
Field Status : current
Description : query_tx_max_packed
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.20

Field Name : stateStatsSyncRxSmpRadiusTableCounter
Field Type : TABLE
Field Status : current
Description : sync_rx_smp_radius_table_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.19

Field Name : stateStatsSyncTxSmpRadiusTableCounter
Field Type : TABLE
Field Status : current
Description : sync_tx_smp_radius_table_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.18

Field Name : stateStatsQueryPktRcvCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : query_pkt_rcv_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.17

Field Name : stateStatsQueryPktTxCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : query_pkt_tx_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.16

Field Name : stateStatsSyncTxPersistUpdateAgeCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_persist_update_age_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.15

Field Name : stateStatsSyncTxPersistDelCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_persist_del_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.14

Field Name : stateStatsSyncTxPersistCreateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_persist_create_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.13

Field Name : stateStatsSyncRxPersistUpdateAgeCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_persist_update_age_counter

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.12

Field Name : stateStatsSyncRxPersistDelCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_persist_del_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.11

Field Name : stateStatsSyncRxPersistCreateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_persist_create_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.10

Field Name : stateStatsSyncTxUpdateAgeCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_update_age_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.9

Field Name : stateStatsSyncTxDelCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_del_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.8

Field Name : stateStatsSyncTxCreateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_create_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.7

Field Name : stateStatsSyncRxUpdateAgeCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_update_age_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.6

Field Name : stateStatsSyncRxDelCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_del_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.5

Field Name : stateStatsSyncRxCreateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_create_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.4

Field Name : stateStatsSyncPktRcvCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_pkt_rcv_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.3

Field Name : stateStatsSyncPktTxCounter
Field Type : CounterBasedGauge64

Field Status : current
Description : sync_pkt_tx_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.2

Field Name : stateStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.1

Field Name : stateCpuOperCpuUsageTable
Field Type : TABLE
Field Status : current
Description : HA VRRP-A Global Commands from object 'vrrp-a.state-cpu'
OID : 1.3.6.1.4.1.22610.2.4.8.5.1.2

Field Name : stateCpuOperCpuUsageEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The stateCpuOperCpuUsage entry:cpu-usage
OID : 1.3.6.1.4.1.22610.2.4.8.5.1.2.1

Field Name : stateCpuOperCpuUsageMinQueryMsgPerPacket
Field Type : CounterBasedGauge64
Field Status : current
Description : Min-Query-Msg-Per-Packet
OID : 1.3.6.1.4.1.22610.2.4.8.5.1.2.1.7

Field Name : stateCpuOperCpuUsageMaxQueryMsgPerPacket
Field Type : CounterBasedGauge64
Field Status : current
Description : Max-Query-Msg-Per-Packet
OID : 1.3.6.1.4.1.22610.2.4.8.5.1.2.1.6

Field Name : stateCpuOperCpuUsageMinSyncMsgPerPacket
Field Type : CounterBasedGauge64
Field Status : current
Description : Min-Sync-Msg-Per-Packet
OID : 1.3.6.1.4.1.22610.2.4.8.5.1.2.1.5

Field Name : stateCpuOperCpuUsageMaxSyncMsgPerPacket
Field Type : CounterBasedGauge64
Field Status : current
Description : Max-Sync-Msg-Per-Packet
OID : 1.3.6.1.4.1.22610.2.4.8.5.1.2.1.4

Field Name : stateCpuOperCpuUsageCpuId
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-id
OID : 1.3.6.1.4.1.22610.2.4.8.5.1.2.1.3

Field Name : stateCpuOperCpuUsageCpuUsageListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.5.1.2.1.2

Field Name : stateCpuOperCpuUsageSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.5.1.2.1.1

Field Name : commonStatsTable
Field Type : TABLE
Field Status : current
Description : HA VRRP-A Global Commands from object 'vrrp-a.common'
OID : 1.3.6.1.4.1.22610.2.4.8.6.1.1

Field Name : commonStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The commonStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.6.1.1.1

Field Name : commonStatsVrrpCommonDummy
Field Type : CounterBasedGauge64
Field Status : current
Description : vrrp_common_dummy
OID : 1.3.6.1.4.1.22610.2.4.8.6.1.1.1.2

Field Name : commonStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.6.1.1.1.1

Field Name : partitionVridStatusOperAllPartitionListTable
Field Type : TABLE
Field Status : current
Description : display vrrp-a status for all partitions from object 'vrrp-a.partition-vrid-status'
OID : 1.3.6.1.4.1.22610.2.4.8.8.1.2

Field Name : partitionVridStatusOperAllPartitionListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The partitionVridStatusOperAllPartitionList entry:all-partition-list
OID : 1.3.6.1.4.1.22610.2.4.8.8.1.2.1

Field Name : partitionVridStatusOperAllPartitionListActiveWeight
Field Type : CounterBasedGauge64
Field Status : current
Description : active_weight
OID : 1.3.6.1.4.1.22610.2.4.8.8.1.2.1.8

Field Name : partitionVridStatusOperAllPartitionListActivePriority
Field Type : CounterBasedGauge64
Field Status : current
Description : active_priority
OID : 1.3.6.1.4.1.22610.2.4.8.8.1.2.1.7

Field Name : partitionVridStatusOperAllPartitionListActiveDeviceId
Field Type : CounterBasedGauge64
Field Status : current
Description : active_device_id

OID : 1.3.6.1.4.1.22610.2.4.8.8.1.2.1.6

Field Name : partitionVridStatusOperAllPartitionListVrid
Field Type : CounterBasedGauge64
Field Status : current
Description : vrid
OID : 1.3.6.1.4.1.22610.2.4.8.8.1.2.1.5

Field Name : partitionVridStatusOperAllPartitionListPartitionName
Field Type : String
Field Status : current
Description : partition-name
OID : 1.3.6.1.4.1.22610.2.4.8.8.1.2.1.4

Field Name : partitionVridStatusOperAllPartitionListLocalDeviceID
Field Type : CounterBasedGauge64
Field Status : current
Description : local_device_ID
OID : 1.3.6.1.4.1.22610.2.4.8.8.1.2.1.3

Field Name : partitionVridStatusOperAllPartitionListAllPartitionListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.8.1.2.1.2

Field Name : partitionVridStatusOperAllPartitionListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.8.1.2.1.1

Field Name : partitionVridAllStatusOperAllPartitionListTable
Field Type : TABLE
Field Status : current
Description : display vrid all status for all partitions from object 'vrrp-a.partition-vrid-all-status'
OID : 1.3.6.1.4.1.22610.2.4.8.9.1.2

Field Name : partitionVridAllStatusOperAllPartitionListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The partitionVridAllStatusOperAllPartitionList entry:all-partition-list
OID : 1.3.6.1.4.1.22610.2.4.8.9.1.2.1

Field Name : partitionVridAllStatusOperAllPartitionListStandbyWeight
Field Type : CounterBasedGauge64
Field Status : current
Description : standby_weight
OID : 1.3.6.1.4.1.22610.2.4.8.9.1.2.1.11

Field Name : partitionVridAllStatusOperAllPartitionListStandbyPriority
Field Type : CounterBasedGauge64
Field Status : current
Description : standby_priority
OID : 1.3.6.1.4.1.22610.2.4.8.9.1.2.1.10

Field Name : partitionVridAllStatusOperAllPartitionListStandbyDeviceId
Field Type : CounterBasedGauge64

Field Status : current
Description : standby_device_id
OID : 1.3.6.1.4.1.22610.2.4.8.9.1.2.1.9

Field Name : partitionVridAllStatusOperAllPartitionListActiveWeight
Field Type : CounterBasedGauge64
Field Status : current
Description : active_weight
OID : 1.3.6.1.4.1.22610.2.4.8.9.1.2.1.8

Field Name : partitionVridAllStatusOperAllPartitionListActivePriority
Field Type : CounterBasedGauge64
Field Status : current
Description : active_priority
OID : 1.3.6.1.4.1.22610.2.4.8.9.1.2.1.7

Field Name : partitionVridAllStatusOperAllPartitionListActiveDeviceId
Field Type : CounterBasedGauge64
Field Status : current
Description : active_device_id
OID : 1.3.6.1.4.1.22610.2.4.8.9.1.2.1.6

Field Name : partitionVridAllStatusOperAllPartitionListVrid
Field Type : CounterBasedGauge64
Field Status : current
Description : vrid
OID : 1.3.6.1.4.1.22610.2.4.8.9.1.2.1.5

Field Name : partitionVridAllStatusOperAllPartitionListPartitionName
Field Type : String
Field Status : current
Description : partition-name
OID : 1.3.6.1.4.1.22610.2.4.8.9.1.2.1.4

Field Name : partitionVridAllStatusOperAllPartitionListLocalDeviceID
Field Type : CounterBasedGauge64
Field Status : current
Description : local_device_ID
OID : 1.3.6.1.4.1.22610.2.4.8.9.1.2.1.3

Field Name : partitionVridAllStatusOperAllPartitionListAllPartitionListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.9.1.2.1.2

Field Name : partitionVridAllStatusOperAllPartitionListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.9.1.2.1.1

Field Name : hostidOperHostidListTable
Field Type : TABLE
Field Status : current
Description : vrrp-a device serial number or softax UUID from object 'vrrp-a.hostid'
OID : 1.3.6.1.4.1.22610.2.4.8.10.1.3

Field Name : hostidOperTable
Field Type : TABLE
Field Status : current
Description : vrrp-a device serial number or softax UUID from object 'vrrp-a.hostid'
OID : 1.3.6.1.4.1.22610.2.4.8.10.1.2

Field Name : hostidOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The hostidOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.10.1.2.1

Field Name : hostidOperSetID
Field Type : CounterBasedGauge64
Field Status : current
Description : set_ID
OID : 1.3.6.1.4.1.22610.2.4.8.10.1.2.1.2

Field Name : hostidOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.10.1.2.1.1

Field Name : hostidOperHostidListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The hostidOperHostidList entry:hostid-list
OID : 1.3.6.1.4.1.22610.2.4.8.10.1.3.1

Field Name : hostidOperHostidListSN
Field Type : String
Field Status : current
Description : SN
OID : 1.3.6.1.4.1.22610.2.4.8.10.1.3.1.4

Field Name : hostidOperHostidListDeviceID
Field Type : CounterBasedGauge64
Field Status : current
Description : device_ID
OID : 1.3.6.1.4.1.22610.2.4.8.10.1.3.1.3

Field Name : hostidOperHostidListHostidListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.10.1.3.1.2

Field Name : hostidOperHostidListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.10.1.3.1.1

Field Name : macOperVridMacListTable
Field Type : TABLE
Field Status : current
Description : corresponding virtual mac from object 'vrrp-a.mac'

OID : 1.3.6.1.4.1.22610.2.4.8.11.1.2

Field Name : macOperVridMacListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The macOperVridMacList entry:vrid-mac-list
OID : 1.3.6.1.4.1.22610.2.4.8.11.1.2.1

Field Name : macOperVridMacListMacWithSynCookie
Field Type : String
Field Status : current
Description : mac_with_syn_cookie
OID : 1.3.6.1.4.1.22610.2.4.8.11.1.2.1.5

Field Name : macOperVridMacListMacAddress
Field Type : String
Field Status : current
Description : mac_address
OID : 1.3.6.1.4.1.22610.2.4.8.11.1.2.1.4

Field Name : macOperVridMacListVrid
Field Type : CounterBasedGauge64
Field Status : current
Description : vrid
OID : 1.3.6.1.4.1.22610.2.4.8.11.1.2.1.3

Field Name : macOperVridMacListVridMacListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.11.1.2.1.2

Field Name : macOperVridMacListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.11.1.2.1.1

Field Name : setidMonitorOperSetidListIpListTable
Field Type : TABLE
Field Status : current
Description : monitor set id that has been used from object 'vrrp-a.setid-monitor'
OID : 1.3.6.1.4.1.22610.2.4.8.13.1.4

Field Name : setidMonitorOperSetidListTable
Field Type : TABLE
Field Status : current
Description : monitor set id that has been used from object 'vrrp-a.setid-monitor'
OID : 1.3.6.1.4.1.22610.2.4.8.13.1.3

Field Name : setidMonitorOperSetidListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The setidMonitorOperSetidList entry:setid-list
OID : 1.3.6.1.4.1.22610.2.4.8.13.1.3.1

Field Name : setidMonitorOperSetidListLif
Field Type : CounterBasedGauge64

Field Status : current
Description : lif
OID : 1.3.6.1.4.1.22610.2.4.8.13.1.3.1.4

Field Name : setidMonitorOperSetidListInterfaceType
Field Type : String
Field Status : current
Description : interface_type
OID : 1.3.6.1.4.1.22610.2.4.8.13.1.3.1.3

Field Name : setidMonitorOperSetidListSetidListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.13.1.3.1.2

Field Name : setidMonitorOperSetidListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.13.1.3.1.1

Field Name : setidMonitorOperTable
Field Type : TABLE
Field Status : current
Description : monitor set id that has been used from object 'vrrp-a.setid-monitor'
OID : 1.3.6.1.4.1.22610.2.4.8.13.1.2

Field Name : setidMonitorOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The setidMonitorOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.13.1.2.1

Field Name : setidMonitorOperSetId
Field Type : CounterBasedGauge64
Field Status : current
Description : set-id
OID : 1.3.6.1.4.1.22610.2.4.8.13.1.2.1.2

Field Name : setidMonitorOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.13.1.2.1.1

Field Name : setidMonitorOperSetidListIpListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The setidMonitorOperSetidListIpList entry:ip-list
OID : 1.3.6.1.4.1.22610.2.4.8.13.1.4.1

Field Name : setidMonitorOperSetidListIpListLastObserved
Field Type : CounterBasedGauge64
Field Status : current
Description : last_observed
OID : 1.3.6.1.4.1.22610.2.4.8.13.1.4.1.9

Field Name : setidMonitorOperSetidListIpListVlan
Field Type : CounterBasedGauge64
Field Status : current
Description : vlan
OID : 1.3.6.1.4.1.22610.2.4.8.13.1.4.1.8

Field Name : setidMonitorOperSetidListIpListMac
Field Type : String
Field Status : current
Description : mac
OID : 1.3.6.1.4.1.22610.2.4.8.13.1.4.1.7

Field Name : setidMonitorOperSetidListIpListIpv6
Field Type : String
Field Status : current
Description : ipv6
OID : 1.3.6.1.4.1.22610.2.4.8.13.1.4.1.6

Field Name : setidMonitorOperSetidListIpListIpaddress
Field Type : String
Field Status : current
Description : ipaddress
OID : 1.3.6.1.4.1.22610.2.4.8.13.1.4.1.5

Field Name : setidMonitorOperSetidListIpListDeviceId
Field Type : CounterBasedGauge64
Field Status : current
Description : device-id
OID : 1.3.6.1.4.1.22610.2.4.8.13.1.4.1.4

Field Name : setidMonitorOperSetidListIpListIpListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.13.1.4.1.3

Field Name : setidMonitorOperSetidListIpListSetidListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.13.1.4.1.2

Field Name : setidMonitorOperSetidListIpListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.13.1.4.1.1

Field Name : detailOperLocalInfoListLocalEthSendListTable
Field Type : TABLE
Field Status : current
Description : display vrrp-a peer detail status from object 'vrrp-a.detail'
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.7

Field Name : detailOperLocalInfoListTable
Field Type : TABLE
Field Status : current
Description : display vrrp-a peer detail status from object 'vrrp-a.detail'

OID : 1.3.6.1.4.1.22610.2.4.8.14.1.6

Field Name : detailOperLocalInfoListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The detailOperLocalInfoList entry:local_info_list
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.6.1

Field Name : detailOperLocalInfoListVrrpPktSend
Field Type : CounterBasedGauge64
Field Status : current
Description : vrrp_pkt_send
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.6.1.6

Field Name : detailOperLocalInfoListVrid
Field Type : CounterBasedGauge64
Field Status : current
Description : vrid
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.6.1.5

Field Name : detailOperLocalInfoListSwitchToStandby
Field Type : CounterBasedGauge64
Field Status : current
Description : switch_to_standby
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.6.1.4

Field Name : detailOperLocalInfoListSwitchToActive
Field Type : CounterBasedGauge64
Field Status : current
Description : switch_to_active
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.6.1.3

Field Name : detailOperLocalInfoListLocalInfoListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.6.1.2

Field Name : detailOperLocalInfoListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.6.1.1

Field Name : detailOperPeerInfoListPeerListPeerPortListTable
Field Type : TABLE
Field Status : current
Description : display vrrp-a peer detail status from object 'vrrp-a.detail'
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.5

Field Name : detailOperPeerInfoListPeerListPeerPortListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The detailOperPeerInfoListPeerListPeerPortList entry:peer_port_list
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.5.1

Field Name : detailOperPeerInfoListPeerListPeerPortListEthMiss
Field Type : CounterBasedGauge64

Field Status : current
Description : eth_miss
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.5.1.7

Field Name : detailOperPeerInfoListPeerListPeerPortListVrrpPktRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : vrrp_pkt_recv
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.5.1.6

Field Name : detailOperPeerInfoListPeerListPeerPortListEth
Field Type : CounterBasedGauge64
Field Status : current
Description : eth
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.5.1.5

Field Name : detailOperPeerInfoListPeerListPeerPortListPeerPortListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.5.1.4

Field Name : detailOperPeerInfoListPeerListPeerPortListPeerListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.5.1.3

Field Name : detailOperPeerInfoListPeerListPeerPortListPeerInfoListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.5.1.2

Field Name : detailOperPeerInfoListPeerListPeerPortListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.5.1.1

Field Name : detailOperPeerInfoListPeerListTable
Field Type : TABLE
Field Status : current
Description : display vrrp-a peer detail status from object 'vrrp-a.detail'
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.4

Field Name : detailOperPeerInfoListPeerListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The detailOperPeerInfoListPeerList entry:peer_list
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.4.1

Field Name : detailOperPeerInfoListPeerListMissingHeartbeat
Field Type : CounterBasedGauge64
Field Status : current
Description : missing_heartbeat
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.4.1.6

Field Name : detailOperPeerInfoListPeerListVrid
Field Type : CounterBasedGauge64
Field Status : current
Description : vrid
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.4.1.5

Field Name : detailOperPeerInfoListPeerListPeerId
Field Type : CounterBasedGauge64
Field Status : current
Description : peer_id
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.4.1.4

Field Name : detailOperPeerInfoListPeerListPeerListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.4.1.3

Field Name : detailOperPeerInfoListPeerListPeerInfoListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.4.1.2

Field Name : detailOperPeerInfoListPeerListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.4.1.1

Field Name : detailOperPeerInfoListTable
Field Type : TABLE
Field Status : current
Description : display vrrp-a peer detail status from object 'vrrp-a.detail'
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.3

Field Name : detailOperPeerInfoListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The detailOperPeerInfoList entry:peer_info_list
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.3.1

Field Name : detailOperPeerInfoListPeerPktRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : peer_pkt_recv
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.3.1.4

Field Name : detailOperPeerInfoListPeerIp
Field Type : String
Field Status : current
Description : peer_ip
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.3.1.3

Field Name : detailOperPeerInfoListPeerInfoListListId
Field Type : Integer32
Field Status : current
Description :

OID : 1.3.6.1.4.1.22610.2.4.8.14.1.3.1.2

Field Name : detailOperPeerInfoListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.3.1.1

Field Name : detailOperTable
Field Type : TABLE
Field Status : current
Description : display vrrp-a peer detail status from object 'vrrp-a.detail'
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.2

Field Name : detailOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The detailOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.2.1

Field Name : detailOperL2NoRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : l2_no_route
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.2.1.13

Field Name : detailOperLockTry
Field Type : CounterBasedGauge64
Field Status : current
Description : lock_try
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.2.1.12

Field Name : detailOperErrParid
Field Type : CounterBasedGauge64
Field Status : current
Description : err_parid
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.2.1.11

Field Name : detailOperErrDevid
Field Type : CounterBasedGauge64
Field Status : current
Description : err_devid
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.2.1.10

Field Name : detailOperErrPort
Field Type : CounterBasedGauge64
Field Status : current
Description : err_port
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.2.1.9

Field Name : detailOperIp6PoolsExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : ip6_pools_exceeded
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.2.1.8

Field Name : detailOperIpPoolsExceeded
Field Type : CounterBasedGauge64

Field Status : current
Description : ip_pools_exceeded
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.2.1.7

Field Name : detailOperTimeInaccurateCount
Field Type : CounterBasedGauge64
Field Status : current
Description : time_inaccurate_count
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.2.1.6

Field Name : detailOperVrrpVersionMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : vrrp_version_mismatch
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.2.1.5

Field Name : detailOperSetIdMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : set_id_mismatch
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.2.1.4

Field Name : detailOperBadGroupRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : bad_group_rcv
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.2.1.3

Field Name : detailOperDupIdRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : dup_id_rcv
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.2.1.2

Field Name : detailOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.2.1.1

Field Name : detailOperLocalInfoListLocalEthSendListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The detailOperLocalInfoListLocalEthSendList entry:local_eth_send_list
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.7.1

Field Name : detailOperLocalInfoListLocalEthSendListEthPktSend
Field Type : CounterBasedGauge64
Field Status : current
Description : eth_pkt_send
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.7.1.5

Field Name : detailOperLocalInfoListLocalEthSendListEthPort
Field Type : CounterBasedGauge64
Field Status : current
Description : eth_port
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.7.1.4

Field Name : detailOperLocalInfoListLocalEthSendListLocalEthSendListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.7.1.3

Field Name : detailOperLocalInfoListLocalEthSendListLocalInfoListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.7.1.2

Field Name : detailOperLocalInfoListLocalEthSendListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.7.1.1

Field Name : vcsSummaryOperMemberListIpListTable
Field Type : TABLE
Field Status : current
Description : VCS Summary Information from object 'vcs.vcs-summary'
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.7

Field Name : vcsSummaryOperMemberListTable
Field Type : TABLE
Field Status : current
Description : VCS Summary Information from object 'vcs.vcs-summary'
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.6

Field Name : vcsSummaryOperMemberListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The vcsSummaryOperMemberList entry:member-list
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.6.1

Field Name : vcsSummaryOperMemberListLocation
Field Type : String
Field Status : current
Description : location
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.6.1.7

Field Name : vcsSummaryOperMemberListPort
Field Type : CounterBasedGauge64
Field Status : current
Description : port
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.6.1.6

Field Name : vcsSummaryOperMemberListPriority
Field Type : CounterBasedGauge64
Field Status : current
Description : priority
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.6.1.5

Field Name : vcsSummaryOperMemberListState
Field Type : String
Field Status : current
Description : state

OID : 1.3.6.1.4.1.22610.2.4.8.15.1.6.1.4

Field Name : vcsSummaryOperMemberListId
Field Type : CounterBasedGauge64
Field Status : current
Description : id
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.6.1.3

Field Name : vcsSummaryOperMemberListMemberListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.6.1.2

Field Name : vcsSummaryOperMemberListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.6.1.1

Field Name : vcsSummaryOperFloatingIpv6ListTable
Field Type : TABLE
Field Status : current
Description : VCS Summary Information from object 'vcs.vcs-summary'
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.5

Field Name : vcsSummaryOperFloatingIpv6ListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The vcsSummaryOperFloatingIpv6List entry:floating-ipv6-list
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.5.1

Field Name : vcsSummaryOperFloatingIpv6ListFloatingIpv6Prefix
Field Type : CounterBasedGauge64
Field Status : current
Description : floating-ipv6-prefix
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.5.1.4

Field Name : vcsSummaryOperFloatingIpv6ListFloatingIpv6
Field Type : String
Field Status : current
Description : floating-ipv6
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.5.1.3

Field Name : vcsSummaryOperFloatingIpv6ListFloatingIpv6ListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.5.1.2

Field Name : vcsSummaryOperFloatingIpv6ListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.5.1.1

Field Name : vcsSummaryOperFloatingIpv4ListTable
Field Type : TABLE

Field Status : current
Description : VCS Summary Information from object 'vcs.vcs-summary'
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.4

Field Name : vcsSummaryOperFloatingIpv4ListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The vcsSummaryOperFloatingIpv4List entry:floating-ipv4-list
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.4.1

Field Name : vcsSummaryOperFloatingIpv4ListFloatingIpv4Mask
Field Type : String
Field Status : current
Description : floating-ipv4-mask
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.4.1.4

Field Name : vcsSummaryOperFloatingIpv4ListFloatingIpv4
Field Type : String
Field Status : current
Description : floating-ipv4
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.4.1.3

Field Name : vcsSummaryOperFloatingIpv4ListFloatingIpv4ListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.4.1.2

Field Name : vcsSummaryOperFloatingIpv4ListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.4.1.1

Field Name : vcsSummaryOperVcsHandshakeCompletedListTable
Field Type : TABLE
Field Status : current
Description : VCS Summary Information from object 'vcs.vcs-summary'
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.3

Field Name : vcsSummaryOperVcsHandshakeCompletedListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The vcsSummaryOperVcsHandshakeCompletedList entry:vcs-handshake-completed-list
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.3.1

Field Name : vcsSummaryOperVcsHandshakeCompletedListVcsHandshakeCompleted
Field Type : CounterBasedGauge64
Field Status : current
Description : vcs-handshake-completed
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.3.1.4

Field Name : vcsSummaryOperVcsHandshakeCompletedListVcsHandshakeCompletedId
Field Type : CounterBasedGauge64
Field Status : current
Description : vcs-handshake-completed-id
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.3.1.3

Field Name : vcsSummaryOperVcsHandshakeCompletedListVcsHandshakeCompletedListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.3.1.2

Field Name : vcsSummaryOperVcsHandshakeCompletedListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.3.1.1

Field Name : vcsSummaryOperTable
Field Type : TABLE
Field Status : current
Description : VCS Summary Information from object 'vcs.vcs-summary'
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.2

Field Name : vcsSummaryOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The vcsSummaryOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.2.1

Field Name : vcsSummaryOperVmasterMaintenanceLeft
Field Type : CounterBasedGauge64
Field Status : current
Description : vmaster-maintenance-left
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.2.1.8

Field Name : vcsSummaryOperVmasterMaintenanceInterval
Field Type : CounterBasedGauge64
Field Status : current
Description : vmaster-maintenance-interval
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.2.1.7

Field Name : vcsSummaryOperVersion
Field Type : String
Field Status : current
Description : version
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.2.1.6

Field Name : vcsSummaryOperMulticastPort
Field Type : CounterBasedGauge64
Field Status : current
Description : multicast-port
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.2.1.5

Field Name : vcsSummaryOperMulticastAddr
Field Type : String
Field Status : current
Description : multicast-addr
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.2.1.4

Field Name : vcsSummaryOperChassisId
Field Type : CounterBasedGauge64
Field Status : current
Description : chassis-id

OID : 1.3.6.1.4.1.22610.2.4.8.15.1.2.1.3

Field Name : vcsSummaryOperVcsEnabled
Field Type : String
Field Status : current
Description : vcs-enabled
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.2.1.2

Field Name : vcsSummaryOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.2.1.1

Field Name : vcsSummaryOperMemberListIpListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The vcsSummaryOperMemberListIpList entry:ip-list
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.7.1

Field Name : vcsSummaryOperMemberListIpListIp
Field Type : String
Field Status : current
Description : ip
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.7.1.4

Field Name : vcsSummaryOperMemberListIpListIpListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.7.1.3

Field Name : vcsSummaryOperMemberListIpListMemberListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.7.1.2

Field Name : vcsSummaryOperMemberListIpListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.7.1.1

Field Name : imagesOperImagesListTable
Field Type : TABLE
Field Status : current
Description : VCS Images Information from object 'vcs.images'
OID : 1.3.6.1.4.1.22610.2.4.8.16.1.2

Field Name : imagesOperImagesListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The imagesOperImagesList entry:images-list
OID : 1.3.6.1.4.1.22610.2.4.8.16.1.2.1

Field Name : imagesOperImagesListImagesName
Field Type : String

Field Status : current
Description : images-name
OID : 1.3.6.1.4.1.22610.2.4.8.16.1.2.1.4

Field Name : imagesOperImagesListType
Field Type : String
Field Status : current
Description : type
OID : 1.3.6.1.4.1.22610.2.4.8.16.1.2.1.3

Field Name : imagesOperImagesListImagesListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.16.1.2.1.2

Field Name : imagesOperImagesListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.16.1.2.1.1

Field Name : statStatsTable
Field Type : TABLE
Field Status : current
Description : Show aVCS statistics information from object 'vcs.stat'
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1

Field Name : statStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The statStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1

Field Name : statStatsDaemonMsgHandleFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : daemon_msg_handle_failure
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.74

Field Name : statStatsDaemonMsgInval
Field Type : CounterBasedGauge64
Field Status : current
Description : daemon_msg_inval
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.73

Field Name : statStatsDaemonNSent
Field Type : CounterBasedGauge64
Field Status : current
Description : daemon_n_sent
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.72

Field Name : statStatsDaemonNRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : daemon_n_recv
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.71

Field Name : statStatsDaemonSentBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : daemon_sent_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.70

Field Name : statStatsDaemonRecvBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : daemon_recv_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.69

Field Name : statStatsDaemonSendErr
Field Type : CounterBasedGauge64
Field Status : current
Description : daemon_send_err
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.68

Field Name : statStatsDaemonRecvErr
Field Type : CounterBasedGauge64
Field Status : current
Description : daemon_recv_err
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.67

Field Name : statStatsDaemonNElecStop
Field Type : CounterBasedGauge64
Field Status : current
Description : daemon_n_elec_stop
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.66

Field Name : statStatsDaemonNElecStart
Field Type : CounterBasedGauge64
Field Status : current
Description : daemon_n_elec_start
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.65

Field Name : statStatsSlaveCfgUpdFail
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_cfg_upd_fail
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.64

Field Name : statStatsSlaveCfgUpd
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_cfg_upd
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.63

Field Name : statStatsSlaveKeepalive
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_keepalive
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.62

Field Name : statStatsSlaveMsgInval
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_msg_inval

OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.61

Field Name : statStatsSlaveNSent
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_n_sent
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.60

Field Name : statStatsSlaveNRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_n_recv
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.59

Field Name : statStatsSlaveSentBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_sent_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.58

Field Name : statStatsSlaveRecvBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_recv_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.57

Field Name : statStatsSlaveSendErr
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_send_err
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.56

Field Name : statStatsSlaveRecvErr
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_recv_err
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.55

Field Name : statStatsMasterCfgUpdResultErr
Field Type : CounterBasedGauge64
Field Status : current
Description : master_cfg_upd_result_err
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.54

Field Name : statStatsMasterCfgUpdNotifErr
Field Type : CounterBasedGauge64
Field Status : current
Description : master_cfg_upd_notif_err
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.53

Field Name : statStatsMasterCfgUpdRFail
Field Type : CounterBasedGauge64
Field Status : current
Description : master_cfg_upd_r_fail
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.52

Field Name : statStatsMasterCfgUpdLFail
Field Type : CounterBasedGauge64

Field Status : current
Description : master_cfg_upd_l_fail
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.51

Field Name : statStatsMasterCfgUpd
Field Type : CounterBasedGauge64
Field Status : current
Description : master_cfg_upd
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.50

Field Name : statStatsMasterSlaveStop
Field Type : CounterBasedGauge64
Field Status : current
Description : master_slave_stop
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.49

Field Name : statStatsMasterSlaveStart
Field Type : CounterBasedGauge64
Field Status : current
Description : master_slave_start
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.48

Field Name : statStatsMasterSlaveStartErr
Field Type : CounterBasedGauge64
Field Status : current
Description : master_slave_start_err
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.47

Field Name : statStatsElectLeaveMasterTakeOver
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_leave_master_take_over
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.46

Field Name : statStatsElectLeaveMaster
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_leave_master
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.45

Field Name : statStatsElectLeaveSlave
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_leave_slave
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.44

Field Name : statStatsElectLeaveMasterCand
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_leave_master_cand
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.43

Field Name : statStatsElectEnterMasterTakeOver
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_enter_master_take_over
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.42

Field Name : statStatsElectEnterMaster
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_enter_master
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.41

Field Name : statStatsElectEnterSlave
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_enter_slave
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.40

Field Name : statStatsElectEnterMasterCandStat
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_enter_master_cand_stat
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.39

Field Name : statStatsElectMasterDupNeighbour
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_master_dup_neighbour
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.38

Field Name : statStatsElectMasterTooManyNeighbour
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_master_too_many_neighbour
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.37

Field Name : statStatsElectMasterDiscardNeighbour
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_master_discard_neighbour
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.36

Field Name : statStatsElectMasterDupChallenger
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_master_dup_challenger
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.35

Field Name : statStatsElectMasterReplaceChallenger
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_master_replace_challenger
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.34

Field Name : statStatsElectMasterNewChallenger
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_master_new_challenger
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.33

Field Name : statStatsElectMasterDiscardChallenger
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_master_discard_challenger

OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.32

Field Name : statStatsElectSlaveDupNeighbour
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_slave_dup_neighbour
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.31

Field Name : statStatsElectSlaveTooManyNeighbour
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_slave_too_many_neighbour
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.30

Field Name : statStatsElectSlaveDiscardNeighbour
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_slave_discard_neighbour
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.29

Field Name : statStatsElectSlaveDupChallenger
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_slave_dup_challenger
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.28

Field Name : statStatsElectSlaveReplaceChallenger
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_slave_replace_challenger
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.27

Field Name : statStatsElectSlaveDiscardChallenger
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_slave_discard_challenger
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.26

Field Name : statStatsElectSlaveDupMaster
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_slave_dup_master
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.25

Field Name : statStatsElectMcResetTimerByMto
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_mc_reset_timer_by_mto
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.24

Field Name : statStatsElectMcResetTimerByMc
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_mc_reset_timer_by_mc
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.23

Field Name : statStatsElectMcDupMasterr
Field Type : CounterBasedGauge64

Field Status : current
Description : elect_mc_dup_masterr
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.22

Field Name : statStatsElectMcReplaceMaster
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_mc_replace_master
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.21

Field Name : statStatsElectMcDiscardMaster
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_mc_discard_master
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.20

Field Name : statStatsElectPduDevIdCollision
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_pdu_dev_id_collision
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.19

Field Name : statStatsElectPduClusterMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_pdu_cluster_mismatch
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.18

Field Name : statStatsElectPduHwMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_pdu_hw_mismatch
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.17

Field Name : statStatsElectPduInval
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_pdu_inval
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.16

Field Name : statStatsElectPduUnknownSent
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_pdu_unknown_sent
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.15

Field Name : statStatsElectPduMasterTakeOverSent
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_pdu_master_take_over_sent
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.14

Field Name : statStatsElectPduSlaveSent
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_pdu_slave_sent
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.13

Field Name : statStatsElectPduMasterCandSent
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_pdu_master_cand_sent
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.12

Field Name : statStatsElectPduMasterSent
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_pdu_master_sent
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.11

Field Name : statStatsElectPduUnknownRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_pdu_unknown_recv
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.10

Field Name : statStatsElectPduMasterTakeOverRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_pdu_master_take_over_recv
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.9

Field Name : statStatsElectPduSlaveRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_pdu_slave_recv
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.8

Field Name : statStatsElectPduMasterCandRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_pdu_master_cand_recv
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.7

Field Name : statStatsElectPduMasterRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_pdu_master_recv
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.6

Field Name : statStatsElectSendByte
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_send_byte
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.5

Field Name : statStatsElectRecvByte
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_recv_byte
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.4

Field Name : statStatsElectSendErr
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_send_err

OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.3

Field Name : statStatsElectRecvErr
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_recv_err
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.2

Field Name : statStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.1

Field Name : slotSummaryOperMemberListIpListTable
Field Type : TABLE
Field Status : current
Description : Chassis Summary Information from object 'vcs-chassis.slot-summary'
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.7

Field Name : slotSummaryOperMemberListTable
Field Type : TABLE
Field Status : current
Description : Chassis Summary Information from object 'vcs-chassis.slot-summary'
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.6

Field Name : slotSummaryOperMemberListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The slotSummaryOperMemberList entry:member-list
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.6.1

Field Name : slotSummaryOperMemberListLocation
Field Type : String
Field Status : current
Description : location
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.6.1.7

Field Name : slotSummaryOperMemberListPort
Field Type : CounterBasedGauge64
Field Status : current
Description : port
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.6.1.6

Field Name : slotSummaryOperMemberListPriority
Field Type : CounterBasedGauge64
Field Status : current
Description : priority
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.6.1.5

Field Name : slotSummaryOperMemberListState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.6.1.4

Field Name : slotSummaryOperMemberListId
Field Type : CounterBasedGauge64

Field Status : current
Description : id
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.6.1.3

Field Name : slotSummaryOperMemberListMemberListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.6.1.2

Field Name : slotSummaryOperMemberListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.6.1.1

Field Name : slotSummaryOperFloatingIpv6ListTable
Field Type : TABLE
Field Status : current
Description : Chassis Summary Information from object 'vcs-chassis.slot-summary'
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.5

Field Name : slotSummaryOperFloatingIpv6ListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The slotSummaryOperFloatingIpv6List entry:floating-ipv6-list
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.5.1

Field Name : slotSummaryOperFloatingIpv6ListFloatingIpv6Prefix
Field Type : CounterBasedGauge64
Field Status : current
Description : floating-ipv6-prefix
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.5.1.4

Field Name : slotSummaryOperFloatingIpv6ListFloatingIpv6
Field Type : String
Field Status : current
Description : floating-ipv6
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.5.1.3

Field Name : slotSummaryOperFloatingIpv6ListFloatingIpv6ListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.5.1.2

Field Name : slotSummaryOperFloatingIpv6ListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.5.1.1

Field Name : slotSummaryOperFloatingIpv4ListTable
Field Type : TABLE
Field Status : current
Description : Chassis Summary Information from object 'vcs-chassis.slot-summary'
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.4

Field Name : slotSummaryOperFloatingIpv4ListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The slotSummaryOperFloatingIpv4List entry:floating-ipv4-list
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.4.1

Field Name : slotSummaryOperFloatingIpv4ListFloatingIpv4Mask
Field Type : String
Field Status : current
Description : floating-ipv4-mask
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.4.1.4

Field Name : slotSummaryOperFloatingIpv4ListFloatingIpv4
Field Type : String
Field Status : current
Description : floating-ipv4
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.4.1.3

Field Name : slotSummaryOperFloatingIpv4ListFloatingIpv4ListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.4.1.2

Field Name : slotSummaryOperFloatingIpv4ListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.4.1.1

Field Name : slotSummaryOperVcsHandshakeCompletedListTable
Field Type : TABLE
Field Status : current
Description : Chassis Summary Information from object 'vcs-chassis.slot-summary'
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.3

Field Name : slotSummaryOperVcsHandshakeCompletedListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The slotSummaryOperVcsHandshakeCompletedList entry:vcs-handshake-completed-list
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.3.1

Field Name : slotSummaryOperVcsHandshakeCompletedListVcsHandshakeCompleted
Field Type : CounterBasedGauge64
Field Status : current
Description : vcs-handshake-completed
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.3.1.4

Field Name : slotSummaryOperVcsHandshakeCompletedListVcsHandshakeCompletedId
Field Type : CounterBasedGauge64
Field Status : current
Description : vcs-handshake-completed-id
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.3.1.3

Field Name : slotSummaryOperVcsHandshakeCompletedListVcsHandshakeCompletedListListId
Field Type : Integer32
Field Status : current
Description :

OID : 1.3.6.1.4.1.22610.2.4.8.19.1.3.1.2

Field Name : slotSummaryOperVcsHandshakeCompletedListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.3.1.1

Field Name : slotSummaryOperTable
Field Type : TABLE
Field Status : current
Description : Chassis Summary Information from object 'vcs-chassis.slot-summary'
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.2

Field Name : slotSummaryOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The slotSummaryOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.2.1

Field Name : slotSummaryOperVmasterMaintenanceLeft
Field Type : CounterBasedGauge64
Field Status : current
Description : vmaster-maintenance-left
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.2.1.8

Field Name : slotSummaryOperVmasterMaintenanceInterval
Field Type : CounterBasedGauge64
Field Status : current
Description : vmaster-maintenance-interval
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.2.1.7

Field Name : slotSummaryOperVersion
Field Type : String
Field Status : current
Description : version
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.2.1.6

Field Name : slotSummaryOperMulticastPort
Field Type : CounterBasedGauge64
Field Status : current
Description : multicast-port
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.2.1.5

Field Name : slotSummaryOperMulticastAddr
Field Type : String
Field Status : current
Description : multicast-addr
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.2.1.4

Field Name : slotSummaryOperChassisId
Field Type : CounterBasedGauge64
Field Status : current
Description : chassis-id
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.2.1.3

Field Name : slotSummaryOperVcsEnabled
Field Type : String

Field Status : current
Description : vcs-enabled
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.2.1.2

Field Name : slotSummaryOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.2.1.1

Field Name : slotSummaryOperMemberListIpListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The slotSummaryOperMemberListIpList entry:ip-list
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.7.1

Field Name : slotSummaryOperMemberListIpListIp
Field Type : String
Field Status : current
Description : ip
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.7.1.4

Field Name : slotSummaryOperMemberListIpListIpListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.7.1.3

Field Name : slotSummaryOperMemberListIpListMemberListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.7.1.2

Field Name : slotSummaryOperMemberListIpListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.7.1.1

Field Name : controlCpuStatsTable
Field Type : TABLE
Field Status : current
Description : System control cpu information from object 'system.control-cpu'
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1

Field Name : controlCpuStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The controlCpuStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1

Field Name : controlCpuStatsCpu64
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-64
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.66

Field Name : controlCpuStatsCpu63
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-63
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.65

Field Name : controlCpuStatsCpu62
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-62
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.64

Field Name : controlCpuStatsCpu61
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-61
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.63

Field Name : controlCpuStatsCpu60
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-60
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.62

Field Name : controlCpuStatsCpu59
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-59
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.61

Field Name : controlCpuStatsCpu58
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-58
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.60

Field Name : controlCpuStatsCpu57
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-57
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.59

Field Name : controlCpuStatsCpu56
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-56
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.58

Field Name : controlCpuStatsCpu55
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-55
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.57

Field Name : controlCpuStatsCpu54
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-54

OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.56

Field Name : controlCpuStatsCpu53
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-53
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.55

Field Name : controlCpuStatsCpu52
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-52
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.54

Field Name : controlCpuStatsCpu51
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-51
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.53

Field Name : controlCpuStatsCpu50
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-50
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.52

Field Name : controlCpuStatsCpu49
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-49
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.51

Field Name : controlCpuStatsCpu48
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-48
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.50

Field Name : controlCpuStatsCpu47
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-47
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.49

Field Name : controlCpuStatsCpu46
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-46
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.48

Field Name : controlCpuStatsCpu45
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-45
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.47

Field Name : controlCpuStatsCpu44
Field Type : CounterBasedGauge64

Field Status : current
Description : cpu-44
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.46

Field Name : controlCpuStatsCpu43
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-43
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.45

Field Name : controlCpuStatsCpu42
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-42
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.44

Field Name : controlCpuStatsCpu41
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-41
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.43

Field Name : controlCpuStatsCpu40
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-40
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.42

Field Name : controlCpuStatsCpu39
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-39
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.41

Field Name : controlCpuStatsCpu38
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-38
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.40

Field Name : controlCpuStatsCpu37
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-37
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.39

Field Name : controlCpuStatsCpu36
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-36
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.38

Field Name : controlCpuStatsCpu35
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-35
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.37

Field Name : controlCpuStatsCpu34
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-34
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.36

Field Name : controlCpuStatsCpu33
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-33
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.35

Field Name : controlCpuStatsCpu32
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-32
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.34

Field Name : controlCpuStatsCpu31
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-31
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.33

Field Name : controlCpuStatsCpu30
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-30
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.32

Field Name : controlCpuStatsCpu29
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-29
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.31

Field Name : controlCpuStatsCpu28
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-28
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.30

Field Name : controlCpuStatsCpu27
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-27
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.29

Field Name : controlCpuStatsCpu26
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-26
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.28

Field Name : controlCpuStatsCpu25
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-25

OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.27

Field Name : controlCpuStatsCpu24
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-24
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.26

Field Name : controlCpuStatsCpu23
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-23
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.25

Field Name : controlCpuStatsCpu22
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-22
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.24

Field Name : controlCpuStatsCpu21
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-21
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.23

Field Name : controlCpuStatsCpu20
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-20
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.22

Field Name : controlCpuStatsCpu19
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-19
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.21

Field Name : controlCpuStatsCpu18
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-18
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.20

Field Name : controlCpuStatsCpu17
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-17
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.19

Field Name : controlCpuStatsCpu16
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-16
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.18

Field Name : controlCpuStatsCpu15
Field Type : CounterBasedGauge64

Field Status : current
Description : cpu-15
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.17

Field Name : controlCpuStatsCpu14
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-14
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.16

Field Name : controlCpuStatsCpu13
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-13
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.15

Field Name : controlCpuStatsCpu12
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-12
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.14

Field Name : controlCpuStatsCpu11
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-11
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.13

Field Name : controlCpuStatsCpu10
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-10
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.12

Field Name : controlCpuStatsCpu9
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-9
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.11

Field Name : controlCpuStatsCpu8
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-8
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.10

Field Name : controlCpuStatsCpu7
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-7
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.9

Field Name : controlCpuStatsCpu6
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-6
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.8

Field Name : controlCpuStatsCpu5
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-5
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.7

Field Name : controlCpuStatsCpu4
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-4
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.6

Field Name : controlCpuStatsCpu3
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-3
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.5

Field Name : controlCpuStatsCpu2
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-2
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.4

Field Name : controlCpuStatsCpu1
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-1
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.3

Field Name : controlCpuStatsCtrlCpuNumber
Field Type : CounterBasedGauge64
Field Status : current
Description : ctrl-cpu-number
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.2

Field Name : controlCpuStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.1

Field Name : dataCpuStatsTable
Field Type : TABLE
Field Status : current
Description : System data cpu information from object 'system.data-cpu'
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1

Field Name : dataCpuStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dataCpuStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1

Field Name : dataCpuStatsCpu100
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-100

OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.102

Field Name : dataCpuStatsCpu99
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-99
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.101

Field Name : dataCpuStatsCpu98
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-98
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.100

Field Name : dataCpuStatsCpu97
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-97
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.99

Field Name : dataCpuStatsCpu96
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-96
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.98

Field Name : dataCpuStatsCpu95
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-95
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.97

Field Name : dataCpuStatsCpu94
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-94
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.96

Field Name : dataCpuStatsCpu93
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-93
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.95

Field Name : dataCpuStatsCpu92
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-92
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.94

Field Name : dataCpuStatsCpu91
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-91
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.93

Field Name : dataCpuStatsCpu90
Field Type : CounterBasedGauge64

Field Status : current
Description : cpu-90
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.92

Field Name : dataCpuStatsCpu89
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-89
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.91

Field Name : dataCpuStatsCpu88
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-88
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.90

Field Name : dataCpuStatsCpu87
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-87
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.89

Field Name : dataCpuStatsCpu86
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-86
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.88

Field Name : dataCpuStatsCpu85
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-85
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.87

Field Name : dataCpuStatsCpu84
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-84
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.86

Field Name : dataCpuStatsCpu83
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-83
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.85

Field Name : dataCpuStatsCpu82
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-82
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.84

Field Name : dataCpuStatsCpu81
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-81
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.83

Field Name : dataCpuStatsCpu80
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-80
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.82

Field Name : dataCpuStatsCpu79
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-79
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.81

Field Name : dataCpuStatsCpu78
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-78
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.80

Field Name : dataCpuStatsCpu77
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-77
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.79

Field Name : dataCpuStatsCpu76
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-76
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.78

Field Name : dataCpuStatsCpu75
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-75
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.77

Field Name : dataCpuStatsCpu74
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-74
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.76

Field Name : dataCpuStatsCpu73
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-73
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.75

Field Name : dataCpuStatsCpu72
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-72
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.74

Field Name : dataCpuStatsCpu71
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-71

OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.73

Field Name : dataCpuStatsCpu70
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-70
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.72

Field Name : dataCpuStatsCpu69
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-69
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.71

Field Name : dataCpuStatsCpu68
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-68
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.70

Field Name : dataCpuStatsCpu67
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-67
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.69

Field Name : dataCpuStatsCpu66
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-66
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.68

Field Name : dataCpuStatsCpu65
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-65
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.67

Field Name : dataCpuStatsCpu64
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-64
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.66

Field Name : dataCpuStatsCpu63
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-63
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.65

Field Name : dataCpuStatsCpu62
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-62
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.64

Field Name : dataCpuStatsCpu61
Field Type : CounterBasedGauge64

Field Status : current
Description : cpu-61
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.63

Field Name : dataCpuStatsCpu60
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-60
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.62

Field Name : dataCpuStatsCpu59
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-59
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.61

Field Name : dataCpuStatsCpu58
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-58
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.60

Field Name : dataCpuStatsCpu57
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-57
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.59

Field Name : dataCpuStatsCpu56
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-56
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.58

Field Name : dataCpuStatsCpu55
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-55
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.57

Field Name : dataCpuStatsCpu54
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-54
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.56

Field Name : dataCpuStatsCpu53
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-53
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.55

Field Name : dataCpuStatsCpu52
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-52
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.54

Field Name : dataCpuStatsCpu51
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-51
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.53

Field Name : dataCpuStatsCpu50
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-50
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.52

Field Name : dataCpuStatsCpu49
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-49
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.51

Field Name : dataCpuStatsCpu48
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-48
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.50

Field Name : dataCpuStatsCpu47
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-47
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.49

Field Name : dataCpuStatsCpu46
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-46
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.48

Field Name : dataCpuStatsCpu45
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-45
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.47

Field Name : dataCpuStatsCpu44
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-44
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.46

Field Name : dataCpuStatsCpu43
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-43
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.45

Field Name : dataCpuStatsCpu42
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-42

OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.44

Field Name : dataCpuStatsCpu41
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-41
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.43

Field Name : dataCpuStatsCpu40
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-40
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.42

Field Name : dataCpuStatsCpu39
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-39
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.41

Field Name : dataCpuStatsCpu38
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-38
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.40

Field Name : dataCpuStatsCpu37
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-37
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.39

Field Name : dataCpuStatsCpu36
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-36
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.38

Field Name : dataCpuStatsCpu35
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-35
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.37

Field Name : dataCpuStatsCpu34
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-34
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.36

Field Name : dataCpuStatsCpu33
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-33
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.35

Field Name : dataCpuStatsCpu32
Field Type : CounterBasedGauge64

Field Status : current
Description : cpu-32
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.34

Field Name : dataCpuStatsCpu31
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-31
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.33

Field Name : dataCpuStatsCpu30
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-30
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.32

Field Name : dataCpuStatsCpu29
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-29
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.31

Field Name : dataCpuStatsCpu28
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-28
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.30

Field Name : dataCpuStatsCpu27
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-27
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.29

Field Name : dataCpuStatsCpu26
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-26
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.28

Field Name : dataCpuStatsCpu25
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-25
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.27

Field Name : dataCpuStatsCpu24
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-24
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.26

Field Name : dataCpuStatsCpu23
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-23
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.25

Field Name : dataCpuStatsCpu22
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-22
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.24

Field Name : dataCpuStatsCpu21
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-21
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.23

Field Name : dataCpuStatsCpu20
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-20
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.22

Field Name : dataCpuStatsCpu19
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-19
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.21

Field Name : dataCpuStatsCpu18
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-18
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.20

Field Name : dataCpuStatsCpu17
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-17
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.19

Field Name : dataCpuStatsCpu16
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-16
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.18

Field Name : dataCpuStatsCpu15
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-15
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.17

Field Name : dataCpuStatsCpu14
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-14
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.16

Field Name : dataCpuStatsCpu13
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-13

OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.15

Field Name : dataCpuStatsCpu12
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-12
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.14

Field Name : dataCpuStatsCpu11
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-11
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.13

Field Name : dataCpuStatsCpu10
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-10
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.12

Field Name : dataCpuStatsCpu9
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-9
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.11

Field Name : dataCpuStatsCpu8
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-8
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.10

Field Name : dataCpuStatsCpu7
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-7
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.9

Field Name : dataCpuStatsCpu6
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-6
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.8

Field Name : dataCpuStatsCpu5
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-5
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.7

Field Name : dataCpuStatsCpu4
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-4
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.6

Field Name : dataCpuStatsCpu3
Field Type : CounterBasedGauge64

Field Status : current
Description : cpu-3
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.5

Field Name : dataCpuStatsCpu2
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-2
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.4

Field Name : dataCpuStatsCpu1
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-1
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.3

Field Name : dataCpuStatsDataCpuNumber
Field Type : CounterBasedGauge64
Field Status : current
Description : data-cpu-number
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.2

Field Name : dataCpuStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.1

Field Name : dataCpuOperCpuUsageTable
Field Type : TABLE
Field Status : current
Description : Data CPU usage from object 'system-cpu.data-cpu'
OID : 1.3.6.1.4.1.22610.2.4.8.111.1.3

Field Name : dataCpuOperTable
Field Type : TABLE
Field Status : current
Description : Data CPU usage from object 'system-cpu.data-cpu'
OID : 1.3.6.1.4.1.22610.2.4.8.111.1.2

Field Name : dataCpuOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dataCpuOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.111.1.2.1

Field Name : dataCpuOperNumberOfDataCpu
Field Type : CounterBasedGauge64
Field Status : current
Description : number-of-data-cpu
OID : 1.3.6.1.4.1.22610.2.4.8.111.1.2.1.3

Field Name : dataCpuOperNumberOfCpu
Field Type : CounterBasedGauge64
Field Status : current
Description : number-of-cpu
OID : 1.3.6.1.4.1.22610.2.4.8.111.1.2.1.2

Field Name : dataCpuOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.111.1.2.1.1

Field Name : dataCpuOperCpuUsageEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dataCpuOperCpuUsage entry:cpu-usage
OID : 1.3.6.1.4.1.22610.2.4.8.111.1.3.1

Field Name : dataCpuOperCpuUsageDcpuStr
Field Type : String
Field Status : current
Description : dcpu-str
OID : 1.3.6.1.4.1.22610.2.4.8.111.1.3.1.9

Field Name : dataCpuOperCpuUsage60Sec
Field Type : CounterBasedGauge64
Field Status : current
Description : 60-sec
OID : 1.3.6.1.4.1.22610.2.4.8.111.1.3.1.8

Field Name : dataCpuOperCpuUsage30Sec
Field Type : CounterBasedGauge64
Field Status : current
Description : 30-sec
OID : 1.3.6.1.4.1.22610.2.4.8.111.1.3.1.7

Field Name : dataCpuOperCpuUsage10Sec
Field Type : CounterBasedGauge64
Field Status : current
Description : 10-sec
OID : 1.3.6.1.4.1.22610.2.4.8.111.1.3.1.6

Field Name : dataCpuOperCpuUsage5Sec
Field Type : CounterBasedGauge64
Field Status : current
Description : 5-sec
OID : 1.3.6.1.4.1.22610.2.4.8.111.1.3.1.5

Field Name : dataCpuOperCpuUsage1Sec
Field Type : CounterBasedGauge64
Field Status : current
Description : 1-sec
OID : 1.3.6.1.4.1.22610.2.4.8.111.1.3.1.4

Field Name : dataCpuOperCpuUsageCpuId
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-id
OID : 1.3.6.1.4.1.22610.2.4.8.111.1.3.1.3

Field Name : dataCpuOperCpuUsageCpuUsageListId
Field Type : Integer32
Field Status : current
Description :

OID : 1.3.6.1.4.1.22610.2.4.8.111.1.3.1.2

Field Name : dataCpuOperCpuUsageSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.111.1.3.1.1

Field Name : ctrlCpuOperCpuUsageTable
Field Type : TABLE
Field Status : current
Description : Control CPU usage from object 'system-cpu.ctrl-cpu'
OID : 1.3.6.1.4.1.22610.2.4.8.112.1.3

Field Name : ctrlCpuOperTable
Field Type : TABLE
Field Status : current
Description : Control CPU usage from object 'system-cpu.ctrl-cpu'
OID : 1.3.6.1.4.1.22610.2.4.8.112.1.2

Field Name : ctrlCpuOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The ctrlCpuOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.112.1.2.1

Field Name : ctrlCpuOperNumberOfCpu
Field Type : CounterBasedGauge64
Field Status : current
Description : number-of-cpu
OID : 1.3.6.1.4.1.22610.2.4.8.112.1.2.1.3

Field Name : ctrlCpuOperCurrentTime
Field Type : String
Field Status : current
Description : current-time
OID : 1.3.6.1.4.1.22610.2.4.8.112.1.2.1.2

Field Name : ctrlCpuOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.112.1.2.1.1

Field Name : ctrlCpuOperCpuUsageEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The ctrlCpuOperCpuUsage entry:cpu-usage
OID : 1.3.6.1.4.1.22610.2.4.8.112.1.3.1

Field Name : ctrlCpuOperCpuUsage60Sec
Field Type : CounterBasedGauge64
Field Status : current
Description : 60-sec
OID : 1.3.6.1.4.1.22610.2.4.8.112.1.3.1.8

Field Name : ctrlCpuOperCpuUsage30Sec
Field Type : CounterBasedGauge64

Field Status : current
Description : 30-sec
OID : 1.3.6.1.4.1.22610.2.4.8.112.1.3.1.7

Field Name : ctrlCpuOperCpuUsage10Sec
Field Type : CounterBasedGauge64
Field Status : current
Description : 10-sec
OID : 1.3.6.1.4.1.22610.2.4.8.112.1.3.1.6

Field Name : ctrlCpuOperCpuUsage5Sec
Field Type : CounterBasedGauge64
Field Status : current
Description : 5-sec
OID : 1.3.6.1.4.1.22610.2.4.8.112.1.3.1.5

Field Name : ctrlCpuOperCpuUsage1Sec
Field Type : CounterBasedGauge64
Field Status : current
Description : 1-sec
OID : 1.3.6.1.4.1.22610.2.4.8.112.1.3.1.4

Field Name : ctrlCpuOperCpuUsageCpuId
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-id
OID : 1.3.6.1.4.1.22610.2.4.8.112.1.3.1.3

Field Name : ctrlCpuOperCpuUsageCpuUsageListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.112.1.3.1.2

Field Name : ctrlCpuOperCpuUsageSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.112.1.3.1.1

Field Name : classListOperGeoLocationEntriesTable
Field Type : TABLE
Field Status : current
Description : Configure classification list from object 'class-list'
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.8

Field Name : classListOperAcEntriesTable
Field Type : TABLE
Field Status : current
Description : Configure classification list from object 'class-list'
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.7

Field Name : classListOperAcEntriesEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The classListOperAcEntries entry:ac-entries
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.7.1

Field Name : classListOperAcEntriesAcGtpPolicy
Field Type : String
Field Status : current
Description : ac-gtp-policy
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.7.1.8

Field Name : classListOperAcEntriesAcHitCount
Field Type : CounterBasedGauge64
Field Status : current
Description : ac-hit-count
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.7.1.7

Field Name : classListOperAcEntriesAcMatchValue
Field Type : String
Field Status : current
Description : ac-match-value
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.7.1.6

Field Name : classListOperAcEntriesAcMatchString
Field Type : String
Field Status : current
Description : ac-match-string
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.7.1.5

Field Name : classListOperAcEntriesAcMatchType
Field Type : String
Field Status : current
Description : ac-match-type
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.7.1.4

Field Name : classListOperAcEntriesAcEntriesListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.7.1.3

Field Name : classListOperAcEntriesName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.7.1.2

Field Name : classListOperAcEntriesSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.7.1.1

Field Name : classListOperStringEntriesTable
Field Type : TABLE
Field Status : current
Description : Configure classification list from object 'class-list'
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.6

Field Name : classListOperStringEntriesEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The classListOperStringEntries entry:string-entries

OID : 1.3.6.1.4.1.22610.2.4.8.137.1.6.1

Field Name : classListOperStringEntriesStringHitCount
Field Type : CounterBasedGauge64
Field Status : current
Description : string-hit-count
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.6.1.8

Field Name : classListOperStringEntriesStringGlid
Field Type : CounterBasedGauge64
Field Status : current
Description : string-glid
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.6.1.7

Field Name : classListOperStringEntriesStringLid
Field Type : CounterBasedGauge64
Field Status : current
Description : string-lid
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.6.1.6

Field Name : classListOperStringEntriesStringValue
Field Type : String
Field Status : current
Description : string-value
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.6.1.5

Field Name : classListOperStringEntriesStringKey
Field Type : String
Field Status : current
Description : string-key
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.6.1.4

Field Name : classListOperStringEntriesStringEntriesListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.6.1.3

Field Name : classListOperStringEntriesName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.6.1.2

Field Name : classListOperStringEntriesSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.6.1.1

Field Name : classListOperDnsEntriesTable
Field Type : TABLE
Field Status : current
Description : Configure classification list from object 'class-list'
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.5

Field Name : classListOperDnsEntriesEntry
Field Type : CounterBasedGauge64

Field Status : current
Description : The classListOperDnsEntries entry:dns-entries
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.5.1

Field Name : classListOperDnsEntriesDnsRpzType
Field Type : CounterBasedGauge64
Field Status : current
Description : dns-rpz-type
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.5.1.9

Field Name : classListOperDnsEntriesDnsHitCount
Field Type : CounterBasedGauge64
Field Status : current
Description : dns-hit-count
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.5.1.8

Field Name : classListOperDnsEntriesDnsGlid
Field Type : CounterBasedGauge64
Field Status : current
Description : dns-glid
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.5.1.7

Field Name : classListOperDnsEntriesDnsLid
Field Type : CounterBasedGauge64
Field Status : current
Description : dns-lid
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.5.1.6

Field Name : classListOperDnsEntriesDnsMatchString
Field Type : String
Field Status : current
Description : dns-match-string
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.5.1.5

Field Name : classListOperDnsEntriesDnsMatchType
Field Type : String
Field Status : current
Description : dns-match-type
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.5.1.4

Field Name : classListOperDnsEntriesDnsEntriesListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.5.1.3

Field Name : classListOperDnsEntriesName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.5.1.2

Field Name : classListOperDnsEntriesSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.5.1.1

Field Name : classListOperIpv6EntriesTable
Field Type : TABLE
Field Status : current
Description : Configure classification list from object 'class-list'
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.4

Field Name : classListOperIpv6EntriesEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The classListOperIpv6Entries entry:ipv6-entries
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.4.1

Field Name : classListOperIpv6EntriesIpv6RpzType
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-rpz-type
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.4.1.12

Field Name : classListOperIpv6EntriesIpv6Age
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-age
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.4.1.11

Field Name : classListOperIpv6EntriesIpv6HitCount
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-hit-count
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.4.1.10

Field Name : classListOperIpv6EntriesIpv6Category
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-category
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.4.1.13

Field Name : classListOperIpv6EntriesIpv6GtpPolicy
Field Type : String
Field Status : current
Description : ipv6-gtp-policy
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.4.1.9

Field Name : classListOperIpv6EntriesIpv6LsnRadiusProfile
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-lsn-radius-profile
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.4.1.8

Field Name : classListOperIpv6EntriesIpv6LsnLid
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-lsn-lid
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.4.1.7

Field Name : classListOperIpv6EntriesIpv6Glid
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-glid

OID : 1.3.6.1.4.1.22610.2.4.8.137.1.4.1.6

Field Name : classListOperIpv6EntriesIpv6Lid
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-lid
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.4.1.5

Field Name : classListOperIpv6EntriesIpv6addr
Field Type : String
Field Status : current
Description : ipv6addr
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.4.1.4

Field Name : classListOperIpv6EntriesIpv6EntriesListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.4.1.3

Field Name : classListOperIpv6EntriesName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.4.1.2

Field Name : classListOperIpv6EntriesSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.4.1.1

Field Name : classListOperIpv4EntriesTable
Field Type : TABLE
Field Status : current
Description : Configure classification list from object 'class-list'
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.3

Field Name : classListOperIpv4EntriesEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The classListOperIpv4Entries entry:ipv4-entries
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.3.1

Field Name : classListOperIpv4EntriesIpv4RpzType
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-rpz-type
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.3.1.12

Field Name : classListOperIpv4EntriesIpv4Age
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-age
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.3.1.11

Field Name : classListOperIpv4EntriesIpv4HitCount
Field Type : CounterBasedGauge64

Field Status : current
Description : ipv4-hit-count
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.3.1.10

Field Name : classListOperIpv4EntriesIpv4Category
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-category
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.3.1.13

Field Name : classListOperIpv4EntriesIpv4GtpPolicy
Field Type : String
Field Status : current
Description : ipv4-gtp-policy
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.3.1.9

Field Name : classListOperIpv4EntriesIpv4LsnRadiusProfile
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-lsn-radius-profile
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.3.1.8

Field Name : classListOperIpv4EntriesIpv4LsnLid
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-lsn-lid
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.3.1.7

Field Name : classListOperIpv4EntriesIpv4Glid
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-glid
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.3.1.6

Field Name : classListOperIpv4EntriesIpv4Lid
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-lid
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.3.1.5

Field Name : classListOperIpv4EntriesIpv4Addr
Field Type : String
Field Status : current
Description : ipv4-addr
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.3.1.4

Field Name : classListOperIpv4EntriesIpv4EntriesListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.3.1.3

Field Name : classListOperIpv4EntriesName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.3.1.2

Field Name : classListOperIpv4EntriesSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.3.1.1

Field Name : classListOperTable
Field Type : TABLE
Field Status : current
Description : Configure classification list from object 'class-list'
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.2

Field Name : classListOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The classListOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.2.1

Field Name : classListOperGeoLocationTotalEntries
Field Type : CounterBasedGauge64
Field Status : current
Description : geo-location-total-entries
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.2.1.13

Field Name : classListOperAcTotalEntries
Field Type : CounterBasedGauge64
Field Status : current
Description : ac-total-entries
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.2.1.12

Field Name : classListOperStringTotalEntries
Field Type : CounterBasedGauge64
Field Status : current
Description : string-total-entries
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.2.1.11

Field Name : classListOperDnsTotalEntries
Field Type : CounterBasedGauge64
Field Status : current
Description : dns-total-entries
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.2.1.10

Field Name : classListOperIpv6TotalSubnet
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-total-subnet
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.2.1.9

Field Name : classListOperIpv6TotalSingleIp
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-total-single-ip
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.2.1.8

Field Name : classListOperIpv4TotalSubnet
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-total-subnet

OID : 1.3.6.1.4.1.22610.2.4.8.137.1.2.1.7

Field Name : classListOperIpv4TotalSingleIp
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-total-single-ip
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.2.1.6

Field Name : classListOperUserTag
Field Type : String
Field Status : current
Description : user-tag
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.2.1.5

Field Name : classListOperFileOrString
Field Type : String
Field Status : current
Description : file-or-string
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.2.1.4

Field Name : classListOperType
Field Type : String
Field Status : current
Description : type
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.2.1.3

Field Name : classListOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.2.1.2

Field Name : classListOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.2.1.1

Field Name : classListOperGeoLocationEntriesEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The classListOperGeoLocationEntries entry:geo-location-entries
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.8.1

Field Name : classListOperGeoLocationEntriesGeoLocationStatus
Field Type : String
Field Status : current
Description : geo-location-status
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.8.1.5

Field Name : classListOperGeoLocationEntriesGeoLocation
Field Type : String
Field Status : current
Description : geo-location
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.8.1.4

Field Name : classListOperGeoLocationEntriesGeoLocationEntriesListId
Field Type : Integer32

Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.8.1.3

Field Name : classListOperGeoLocationEntriesName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.8.1.2

Field Name : classListOperGeoLocationEntriesSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.8.1.1

Field Name : anomalyDropStatsTable
Field Type : TABLE
Field Status : current
Description : Set IP anomaly drop policy from object 'ip.anomaly-drop'
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1

Field Name : anomalyDropStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The anomalyDropStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1

Field Name : anomalyDropStatsIpv6EhMalformed
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6_eh_malformed
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.49

Field Name : anomalyDropStatsIpv6EhOther
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6_eh_other
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.48

Field Name : anomalyDropStatsIpv6EhNone
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6_eh_none
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.47

Field Name : anomalyDropStatsIpv6EhMobility
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6_eh_mobility
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.46

Field Name : anomalyDropStatsIpv6EhEsp
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6_eh_esp
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.45

Field Name : anomalyDropStatsIpv6EhAh
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6_eh_ah
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.44

Field Name : anomalyDropStatsIpv6EhFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6_eh_frag
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.43

Field Name : anomalyDropStatsIpv6EhRouting
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6_eh_routing
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.42

Field Name : anomalyDropStatsIpv6EhDest
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6_eh_dest
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.41

Field Name : anomalyDropStatsIpv6EhHbh
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6_eh_hbh
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.40

Field Name : anomalyDropStatsGrePptpErr
Field Type : CounterBasedGauge64
Field Status : current
Description : gre_pptp_err
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.39

Field Name : anomalyDropStatsNvgreErr
Field Type : CounterBasedGauge64
Field Status : current
Description : nvgre_err
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.38

Field Name : anomalyDropStatsVxlanErr
Field Type : CounterBasedGauge64
Field Status : current
Description : vxlan_err
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.37

Field Name : anomalyDropStatsIpipTnlErr
Field Type : CounterBasedGauge64
Field Status : current
Description : ipip_tnl_err
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.36

Field Name : anomalyDropStatsTcpOptErr
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_opt_err

OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.35

Field Name : anomalyDropStatsIpipTnlMsmtch
Field Type : CounterBasedGauge64
Field Status : current
Description : ipip_tnl_msmtch
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.34

Field Name : anomalyDropStatsRuntTcpUdpHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : runt_tcp_udp_hdr
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.33

Field Name : anomalyDropStatsRuntIpHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : runt_ip_hdr
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.32

Field Name : anomalyDropStatsUdpBadCsum
Field Type : CounterBasedGauge64
Field Status : current
Description : udp_bad_csum
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.31

Field Name : anomalyDropStatsUdpPortLb
Field Type : CounterBasedGauge64
Field Status : current
Description : udp_port_lb
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.30

Field Name : anomalyDropStatsUdpKerbFrg
Field Type : CounterBasedGauge64
Field Status : current
Description : udp_kerb_frg
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.29

Field Name : anomalyDropStatsUdpBadLen
Field Type : CounterBasedGauge64
Field Status : current
Description : udp_bad_len
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.28

Field Name : anomalyDropStatsUdpSrtHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : udp_srt_hdr
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.27

Field Name : anomalyDropStatsTcpBadCsum
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_bad_csum
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.26

Field Name : anomalyDropStatsTcpFrgHdr
Field Type : CounterBasedGauge64

Field Status : current
Description : tcp_frg_hdr
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.25

Field Name : anomalyDropStatsTcpSynFrg
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_syn_frg
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.24

Field Name : anomalyDropStatsTcpXmasScan
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_xmas_scan
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.23

Field Name : anomalyDropStatsTcpXmas
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_xmas
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.22

Field Name : anomalyDropStatsTcpSynFin
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_syn_fin
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.21

Field Name : anomalyDropStatsTcpNullScan
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_null_scan
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.20

Field Name : anomalyDropStatsTcpNullFrg
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_null_frg
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.19

Field Name : anomalyDropStatsTcpBadIplen
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_bad_iplen
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.18

Field Name : anomalyDropStatsTcpShtHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_sht_hdr
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.17

Field Name : anomalyDropStatsBadTcpUrgOffset
Field Type : CounterBasedGauge64
Field Status : current
Description : bad_tcp_urg_offset
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.16

Field Name : anomalyDropStatsPod
Field Type : CounterBasedGauge64
Field Status : current
Description : pod
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.15

Field Name : anomalyDropStatsCsum
Field Type : CounterBasedGauge64
Field Status : current
Description : csum
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.14

Field Name : anomalyDropStatsBadIpFrgOffset
Field Type : CounterBasedGauge64
Field Status : current
Description : bad_ip_frg_offset
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.13

Field Name : anomalyDropStatsBadIpPayloadLen
Field Type : CounterBasedGauge64
Field Status : current
Description : bad_ip_payload_len
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.12

Field Name : anomalyDropStatsOverIpPayload
Field Type : CounterBasedGauge64
Field Status : current
Description : over_ip_payload
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.11

Field Name : anomalyDropStatsNoIpPayload
Field Type : CounterBasedGauge64
Field Status : current
Description : no_ip_payload
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.10

Field Name : anomalyDropStatsBadIpTtl
Field Type : CounterBasedGauge64
Field Status : current
Description : bad_ip_ttl
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.9

Field Name : anomalyDropStatsBadIpFlg
Field Type : CounterBasedGauge64
Field Status : current
Description : bad_ip_flg
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.8

Field Name : anomalyDropStatsBadIpHdrlen
Field Type : CounterBasedGauge64
Field Status : current
Description : bad_ip_hdrlen
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.7

Field Name : anomalyDropStatsFrg
Field Type : CounterBasedGauge64
Field Status : current
Description : frg

OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.6

Field Name : anomalyDropStatsOpt
Field Type : CounterBasedGauge64
Field Status : current
Description : opt
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.5

Field Name : anomalyDropStatsEmpMicFrg
Field Type : CounterBasedGauge64
Field Status : current
Description : emp_mic_frg
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.4

Field Name : anomalyDropStatsEmpFrg
Field Type : CounterBasedGauge64
Field Status : current
Description : emp_frg
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.3

Field Name : anomalyDropStatsLand
Field Type : CounterBasedGauge64
Field Status : current
Description : land
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.2

Field Name : anomalyDropStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.1

Field Name : configSyncStatusOperConfigSyncListTable
Field Type : TABLE
Field Status : current
Description : Display config sync status for all partitions from object 'config-sync-status'
OID : 1.3.6.1.4.1.22610.2.4.8.170.1.2

Field Name : configSyncStatusOperConfigSyncListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The configSyncStatusOperConfigSyncList entry:config-sync-list
OID : 1.3.6.1.4.1.22610.2.4.8.170.1.2.1

Field Name : configSyncStatusOperConfigSyncListStartupSyncStatus
Field Type : String
Field Status : current
Description : startup-sync-status
OID : 1.3.6.1.4.1.22610.2.4.8.170.1.2.1.5

Field Name : configSyncStatusOperConfigSyncListRunSyncStatus
Field Type : String
Field Status : current
Description : run-sync-status
OID : 1.3.6.1.4.1.22610.2.4.8.170.1.2.1.4

Field Name : configSyncStatusOperConfigSyncListPartitionName
Field Type : String

Field Status : current
Description : partition-name
OID : 1.3.6.1.4.1.22610.2.4.8.170.1.2.1.3

Field Name : configSyncStatusOperConfigSyncListConfigSyncListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.170.1.2.1.2

Field Name : configSyncStatusOperConfigSyncListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.170.1.2.1.1

Field Name : managementOperTable
Field Type : TABLE
Field Status : current
Description : Management interface from object 'interface.management'
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2

Field Name : managementOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The managementOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1

Field Name : managementOperDhcpEnabled
Field Type : CounterBasedGauge64
Field Status : current
Description : dhcp_enabled
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.21

Field Name : managementOperIpv6Acl
Field Type : String
Field Status : current
Description : ipv6_acl
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.20

Field Name : managementOperIpv4Acl
Field Type : String
Field Status : current
Description : ipv4_acl
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.19

Field Name : managementOperFlowControl
Field Type : CounterBasedGauge64
Field Status : current
Description : flow_control
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.18

Field Name : managementOperMtu
Field Type : CounterBasedGauge64
Field Status : current
Description : mtu
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.17

Field Name : managementOperDuplexity
Field Type : String
Field Status : current
Description : duplexity
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.16

Field Name : managementOperSpeed
Field Type : String
Field Status : current
Description : speed
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.15

Field Name : managementOperIpv6DefaultGateway
Field Type : String
Field Status : current
Description : ipv6-default-gateway
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.14

Field Name : managementOperIpv6LinkLocalPrefix
Field Type : String
Field Status : current
Description : ipv6-link-local-prefix
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.13

Field Name : managementOperIpv6LinkLocal
Field Type : String
Field Status : current
Description : ipv6-link-local
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.12

Field Name : managementOperIpv6Prefix
Field Type : String
Field Status : current
Description : ipv6-prefix
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.11

Field Name : managementOperIpv6Addr
Field Type : String
Field Status : current
Description : ipv6-addr
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.10

Field Name : managementOperIpv4DefaultGateway
Field Type : String
Field Status : current
Description : ipv4-default-gateway
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.9

Field Name : managementOperIpv4Mask
Field Type : String
Field Status : current
Description : ipv4-mask
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.8

Field Name : managementOperIpv4Addr
Field Type : String
Field Status : current
Description : ipv4-addr

OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.7

Field Name : managementOperMac
Field Type : String
Field Status : current
Description : mac
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.6

Field Name : managementOperLinkType
Field Type : String
Field Status : current
Description : link_type
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.5

Field Name : managementOperLineProtocol
Field Type : String
Field Status : current
Description : line_protocol
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.4

Field Name : managementOperState
Field Type : CounterBasedGauge64
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.3

Field Name : managementOperInterface
Field Type : String
Field Status : current
Description : interface
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.2

Field Name : managementOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.1

Field Name : managementStatsTable
Field Type : TABLE
Field Status : current
Description : Management interface from object 'interface.management'
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1

Field Name : managementStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The managementStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1

Field Name : managementStatsCollisions
Field Type : CounterBasedGauge64
Field Status : current
Description : collisions
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.18

Field Name : managementStatsOutputErrors
Field Type : CounterBasedGauge64

Field Status : current
Description : output_errors
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.17

Field Name : managementStatsTransmittedUnicasts
Field Type : CounterBasedGauge64
Field Status : current
Description : transmitted_unicasts
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.16

Field Name : managementStatsTransmittedMulticasts
Field Type : CounterBasedGauge64
Field Status : current
Description : transmitted_multicasts
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.15

Field Name : managementStatsTransmittedBroadcasts
Field Type : CounterBasedGauge64
Field Status : current
Description : transmitted_broadcasts
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.14

Field Name : managementStatsBytesOutput
Field Type : CounterBasedGauge64
Field Status : current
Description : bytes_output
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.13

Field Name : managementStatsPacketsOutput
Field Type : CounterBasedGauge64
Field Status : current
Description : packets_output
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.12

Field Name : managementStatsInputErrLong
Field Type : CounterBasedGauge64
Field Status : current
Description : input_err_long
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.11

Field Name : managementStatsInputErrShort
Field Type : CounterBasedGauge64
Field Status : current
Description : input_err_short
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.10

Field Name : managementStatsFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : frame
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.9

Field Name : managementStatsCrc
Field Type : CounterBasedGauge64
Field Status : current
Description : crc
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.8

Field Name : managementStatsInputErrors
Field Type : CounterBasedGauge64
Field Status : current
Description : input_errors
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.7

Field Name : managementStatsReceivedUnicasts
Field Type : CounterBasedGauge64
Field Status : current
Description : received_unicasts
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.6

Field Name : managementStatsReceivedMulticasts
Field Type : CounterBasedGauge64
Field Status : current
Description : received_multicasts
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.5

Field Name : managementStatsReceivedBroadcasts
Field Type : CounterBasedGauge64
Field Status : current
Description : received_broadcasts
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.4

Field Name : managementStatsBytesInput
Field Type : CounterBasedGauge64
Field Status : current
Description : bytes_input
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.3

Field Name : managementStatsPacketsInput
Field Type : CounterBasedGauge64
Field Status : current
Description : packets_input
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.2

Field Name : managementStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.1

Field Name : ethernetOperIpv6ListTable
Field Type : TABLE
Field Status : current
Description : Ethernet interface from object 'interface.ethernet'
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.4

Field Name : ethernetOperIpv6ListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The ethernetOperIpv6List entry:ipv6_list
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.4.1

Field Name : ethernetOperIpv6ListIsAnycast
Field Type : CounterBasedGauge64
Field Status : current
Description : is_anycast

OID : 1.3.6.1.4.1.22610.2.4.8.189.1.4.1.6

Field Name : ethernetOperIpv6ListPrefix
Field Type : String
Field Status : current
Description : prefix
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.4.1.5

Field Name : ethernetOperIpv6ListAddr
Field Type : String
Field Status : current
Description : addr
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.4.1.4

Field Name : ethernetOperIpv6ListIpv6ListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.4.1.3

Field Name : ethernetOperIpv6ListIfnum
Field Type : Integer32
Field Status : current
Description : ifnum
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.4.1.2

Field Name : ethernetOperIpv6ListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.4.1.1

Field Name : ethernetOperIpv4ListTable
Field Type : TABLE
Field Status : current
Description : Ethernet interface from object 'interface.ethernet'
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.3

Field Name : ethernetOperIpv4ListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The ethernetOperIpv4List entry:ipv4_list
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.3.1

Field Name : ethernetOperIpv4ListMask
Field Type : String
Field Status : current
Description : mask
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.3.1.5

Field Name : ethernetOperIpv4ListAddr
Field Type : String
Field Status : current
Description : addr
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.3.1.4

Field Name : ethernetOperIpv4ListIpv4ListListId
Field Type : Integer32

Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.3.1.3

Field Name : ethernetOperIpv4ListIfnum
Field Type : Integer32
Field Status : current
Description : ifnum
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.3.1.2

Field Name : ethernetOperIpv4ListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.3.1.1

Field Name : ethernetOperTable
Field Type : TABLE
Field Status : current
Description : Ethernet interface from object 'interface.ethernet'
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2

Field Name : ethernetOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The ethernetOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1

Field Name : ethernetOperLastDownEventAt
Field Type : String
Field Status : current
Description : last_down_event_at
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.52

Field Name : ethernetOperLastUpEventAt
Field Type : String
Field Status : current
Description : last_up_event_at
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.51

Field Name : ethernetOperLastCountClearAt
Field Type : String
Field Status : current
Description : last_count_clear_at
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.50

Field Name : ethernetOperIpUnnumberedPeerLla
Field Type : String
Field Status : current
Description : ip_unnumbered_peer_lla
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.49

Field Name : ethernetOperIpUnnumberedMacLearned
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_unnumbered_mac_learned
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.48

Field Name : ethernetOperIpUnnumberedEnabled
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_unnumbered_enabled
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.47

Field Name : ethernetOperIpUnnumberedOper
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_unnumbered_oper
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.46

Field Name : ethernetOperOutgoingPktsMonitored
Field Type : CounterBasedGauge64
Field Status : current
Description : outgoing_pkts_monitored
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.45

Field Name : ethernetOperIncomingPktsMonitored
Field Type : CounterBasedGauge64
Field Status : current
Description : incoming_pkts_monitored
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.44

Field Name : ethernetOperOutgoingPktsMirrored
Field Type : CounterBasedGauge64
Field Status : current
Description : outgoing_pkts_mirrored
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.43

Field Name : ethernetOperIncomingPktsMirrored
Field Type : CounterBasedGauge64
Field Status : current
Description : incoming_pkts_mirrored
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.42

Field Name : ethernetOperIsDeviceTransparent
Field Type : CounterBasedGauge64
Field Status : current
Description : is_device_transparent
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.41

Field Name : ethernetOperOutputUtilization
Field Type : CounterBasedGauge64
Field Status : current
Description : output_utilization
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.40

Field Name : ethernetOperInputUtilization
Field Type : CounterBasedGauge64
Field Status : current
Description : input_utilization
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.39

Field Name : ethernetOperRatePktSent
Field Type : CounterBasedGauge64
Field Status : current
Description : rate_pkt_sent

OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.38

Field Name : ethernetOperRatePktRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : rate_pkt_rcvd
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.37

Field Name : ethernetOperRateByteSent
Field Type : CounterBasedGauge64
Field Status : current
Description : rate_byte_sent
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.36

Field Name : ethernetOperRateByteRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : rate_byte_rcvd
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.35

Field Name : ethernetOperIsPristine
Field Type : CounterBasedGauge64
Field Status : current
Description : is_pristine
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.34

Field Name : ethernetOperPortVnpId
Field Type : CounterBasedGauge64
Field Status : current
Description : port_vnp_id
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.33

Field Name : ethernetOperCurrentVnpId
Field Type : CounterBasedGauge64
Field Status : current
Description : current_vnp_id
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.32

Field Name : ethernetOperIsBlocked
Field Type : CounterBasedGauge64
Field Status : current
Description : is_blocked
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.31

Field Name : ethernetOperIsLeadMember
Field Type : CounterBasedGauge64
Field Status : current
Description : is_lead_member
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.30

Field Name : ethernetOperSpanPortState
Field Type : String
Field Status : current
Description : span_port_state
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.29

Field Name : ethernetOperSpanMode
Field Type : String

Field Status : current
Description : span_mode
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.28

Field Name : ethernetOperTaggedVlanList
Field Type : String
Field Status : current
Description : tagged-vlan-list
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.27

Field Name : ethernetOperVlanId
Field Type : CounterBasedGauge64
Field Status : current
Description : vlan-id
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.26

Field Name : ethernetOperIsTagged
Field Type : CounterBasedGauge64
Field Status : current
Description : is-tagged
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.25

Field Name : ethernetOperIcmp6RateOverLimitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp6-rate-over-limit-drop
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.24

Field Name : ethernetOperIcmp6RateLimitCurrent
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp6-rate-limit-current
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.23

Field Name : ethernetOperIcmpRateOverLimitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-rate-over-limit-drop
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.22

Field Name : ethernetOperIcmpRateLimitCurrent
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-rate-limit-current
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.21

Field Name : ethernetOperIgmpQuerySent
Field Type : CounterBasedGauge64
Field Status : current
Description : igmp-query-sent
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.20

Field Name : ethernetOperIpv6LinkLocalScope
Field Type : String
Field Status : current
Description : ipv6-link-local-scope
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.19

Field Name : ethernetOperIpv6LinkLocalType
Field Type : String
Field Status : current
Description : ipv6-link-local-type
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.18

Field Name : ethernetOperIpv6LinkLocalPrefix
Field Type : String
Field Status : current
Description : ipv6-link-local-prefix
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.17

Field Name : ethernetOperIpv6LinkLocal
Field Type : String
Field Status : current
Description : ipv6-link-local
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.16

Field Name : ethernetOperIpv6AddrCount
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6_addr_count
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.15

Field Name : ethernetOperIpv4AddrCount
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4_addr_count
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.14

Field Name : ethernetOperIpv4Netmask
Field Type : String
Field Status : current
Description : ipv4-netmask
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.13

Field Name : ethernetOperIpv4Address
Field Type : String
Field Status : current
Description : ipv4-address
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.12

Field Name : ethernetOperMediaType
Field Type : String
Field Status : current
Description : media_type
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.11

Field Name : ethernetOperActualDuplexity
Field Type : String
Field Status : current
Description : actual_duplexity
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.10

Field Name : ethernetOperConfigDuplexity
Field Type : String
Field Status : current
Description : config_duplexity

OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.9

Field Name : ethernetOperActualSpeed
Field Type : String
Field Status : current
Description : actual_speed
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.8

Field Name : ethernetOperConfigSpeed
Field Type : String
Field Status : current
Description : config_speed
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.7

Field Name : ethernetOperMac
Field Type : String
Field Status : current
Description : mac
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.6

Field Name : ethernetOperLinkType
Field Type : String
Field Status : current
Description : link_type
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.5

Field Name : ethernetOperLineProtocol
Field Type : String
Field Status : current
Description : line_protocol
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.4

Field Name : ethernetOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.3

Field Name : ethernetOperIfnum
Field Type : Integer32
Field Status : current
Description : ifnum
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.2

Field Name : ethernetOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.1

Field Name : ethernetStatsTable
Field Type : TABLE
Field Status : current
Description : Ethernet interface from object 'interface.ethernet'
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1

Field Name : ethernetStatsEntry
Field Type : CounterBasedGauge64

Field Status : current
Description : The ethernetStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1

Field Name : ethernetStatsOutputUtilization
Field Type : CounterBasedGauge64
Field Status : current
Description : output_utilization
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.29

Field Name : ethernetStatsInputUtilization
Field Type : CounterBasedGauge64
Field Status : current
Description : input_utilization
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.28

Field Name : ethernetStatsReceiveDrops
Field Type : CounterBasedGauge64
Field Status : current
Description : receive_drops
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.27

Field Name : ethernetStatsTransmitDrops
Field Type : CounterBasedGauge64
Field Status : current
Description : transmit_drops
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.26

Field Name : ethernetStatsLoadInterval
Field Type : CounterBasedGauge64
Field Status : current
Description : load_interval
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.25

Field Name : ethernetStatsRateByteRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : rate_byte_rcvd
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.24

Field Name : ethernetStatsRatePktRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : rate_pkt_rcvd
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.23

Field Name : ethernetStatsRateByteSent
Field Type : CounterBasedGauge64
Field Status : current
Description : rate_byte_sent
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.22

Field Name : ethernetStatsRatePktSent
Field Type : CounterBasedGauge64
Field Status : current
Description : rate_pkt_sent
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.21

Field Name : ethernetStatsGiantsOutput
Field Type : CounterBasedGauge64
Field Status : current
Description : giants_output
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.20

Field Name : ethernetStatsCollisions
Field Type : CounterBasedGauge64
Field Status : current
Description : collisions
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.19

Field Name : ethernetStatsOutputErrors
Field Type : CounterBasedGauge64
Field Status : current
Description : output_errors
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.18

Field Name : ethernetStatsTransmittedUnicasts
Field Type : CounterBasedGauge64
Field Status : current
Description : transmitted_unicasts
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.17

Field Name : ethernetStatsTransmittedMulticasts
Field Type : CounterBasedGauge64
Field Status : current
Description : transmitted_multicasts
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.16

Field Name : ethernetStatsTransmittedBroadcasts
Field Type : CounterBasedGauge64
Field Status : current
Description : transmitted_broadcasts
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.15

Field Name : ethernetStatsBytesOutput
Field Type : CounterBasedGauge64
Field Status : current
Description : bytes_output
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.14

Field Name : ethernetStatsPacketsOutput
Field Type : CounterBasedGauge64
Field Status : current
Description : packets_output
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.13

Field Name : ethernetStatsGiants
Field Type : CounterBasedGauge64
Field Status : current
Description : giants
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.12

Field Name : ethernetStatsRunts
Field Type : CounterBasedGauge64
Field Status : current
Description : runts

OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.11

Field Name : ethernetStatsFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : frame
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.10

Field Name : ethernetStatsCrc
Field Type : CounterBasedGauge64
Field Status : current
Description : crc
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.9

Field Name : ethernetStatsInputErrors
Field Type : CounterBasedGauge64
Field Status : current
Description : input_errors
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.8

Field Name : ethernetStatsReceivedUnicasts
Field Type : CounterBasedGauge64
Field Status : current
Description : received_unicasts
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.7

Field Name : ethernetStatsReceivedMulticasts
Field Type : CounterBasedGauge64
Field Status : current
Description : received_multicasts
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.6

Field Name : ethernetStatsReceivedBroadcasts
Field Type : CounterBasedGauge64
Field Status : current
Description : received_broadcasts
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.5

Field Name : ethernetStatsBytesInput
Field Type : CounterBasedGauge64
Field Status : current
Description : bytes_input
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.4

Field Name : ethernetStatsPacketsInput
Field Type : CounterBasedGauge64
Field Status : current
Description : packets_input
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.3

Field Name : ethernetStatsIfnum
Field Type : Integer32
Field Status : current
Description : ifnum
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.2

Field Name : ethernetStatsSlotId
Field Type : Integer32

Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.1

Field Name : availableEthListOperIfListTable
Field Type : TABLE
Field Status : current
Description : List of ethernet interfaces available in a partition from object 'interface.available-eth-list'
OID : 1.3.6.1.4.1.22610.2.4.8.190.1.3

Field Name : availableEthListOperTable
Field Type : TABLE
Field Status : current
Description : List of ethernet interfaces available in a partition from object 'interface.available-eth-list'
OID : 1.3.6.1.4.1.22610.2.4.8.190.1.2

Field Name : availableEthListOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The availableEthListOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.190.1.2.1

Field Name : availableEthListOperTotNumOfPorts
Field Type : CounterBasedGauge64
Field Status : current
Description : tot_num_of_ports
OID : 1.3.6.1.4.1.22610.2.4.8.190.1.2.1.2

Field Name : availableEthListOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.190.1.2.1.1

Field Name : availableEthListOperIfListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The availableEthListOperIfList entry:if-list
OID : 1.3.6.1.4.1.22610.2.4.8.190.1.3.1

Field Name : availableEthListOperIfListState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.190.1.3.1.6

Field Name : availableEthListOperIfListIFStatus
Field Type : String
Field Status : current
Description : IF-Status
OID : 1.3.6.1.4.1.22610.2.4.8.190.1.3.1.5

Field Name : availableEthListOperIfListIFNum
Field Type : CounterBasedGauge64
Field Status : current
Description : IF-Num
OID : 1.3.6.1.4.1.22610.2.4.8.190.1.3.1.4

Field Name : availableEthListOperIfListIFType
Field Type : String
Field Status : current
Description : IF-Type
OID : 1.3.6.1.4.1.22610.2.4.8.190.1.3.1.3

Field Name : availableEthListOperIfListIfListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.190.1.3.1.2

Field Name : availableEthListOperIfListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.190.1.3.1.1

Field Name : briefOperInterfacesTable
Field Type : TABLE
Field Status : current
Description : Interface statistics information from object 'interface.brief'
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2

Field Name : briefOperInterfacesEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The briefOperInterfaces entry:interfaces
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1

Field Name : briefOperInterfacesUnnumberedOper
Field Type : String
Field Status : current
Description : unnumbered_oper
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.18

Field Name : briefOperInterfacesIntfName
Field Type : String
Field Status : current
Description : intf_name
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.17

Field Name : briefOperInterfacesIpv6Prefix
Field Type : String
Field Status : current
Description : ipv6_prefix
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.16

Field Name : briefOperInterfacesIpv6Addr
Field Type : String
Field Status : current
Description : ipv6_addr
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.15

Field Name : briefOperInterfacesIpv6AddrCount
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6_addr_count

OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.14

Field Name : briefOperInterfacesIpv4Mask
Field Type : String
Field Status : current
Description : ipv4_mask
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.13

Field Name : briefOperInterfacesIpv4Addr
Field Type : String
Field Status : current
Description : ipv4_addr
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.12

Field Name : briefOperInterfacesIpv4AddrCount
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4_addr_count
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.11

Field Name : briefOperInterfacesMac
Field Type : String
Field Status : current
Description : mac
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.10

Field Name : briefOperInterfacesState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.9

Field Name : briefOperInterfacesEncapInfo
Field Type : String
Field Status : current
Description : encap_info
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.8

Field Name : briefOperInterfacesVlanInfo
Field Type : String
Field Status : current
Description : vlan_info
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.7

Field Name : briefOperInterfacesTrunkGroup
Field Type : String
Field Status : current
Description : trunk_group
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.6

Field Name : briefOperInterfacesDuplexity
Field Type : String
Field Status : current
Description : duplexity
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.5

Field Name : briefOperInterfacesSpeed
Field Type : String

Field Status : current
Description : speed
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.4

Field Name : briefOperInterfacesPortNum
Field Type : String
Field Status : current
Description : port_num
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.3

Field Name : briefOperInterfacesInterfacesListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.2

Field Name : briefOperInterfacesSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.1

Field Name : certStatsOperTable
Field Type : TABLE
Field Status : current
Description : from object 'pki.cert-stats'
OID : 1.3.6.1.4.1.22610.2.4.8.273.1.2

Field Name : certStatsOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The certStatsOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.273.1.2.1

Field Name : certStatsOperPartition
Field Type : String
Field Status : current
Description : partition
OID : 1.3.6.1.4.1.22610.2.4.8.273.1.2.1.5

Field Name : certStatsOperCaCertCount
Field Type : CounterBasedGauge64
Field Status : current
Description : ca-cert-count
OID : 1.3.6.1.4.1.22610.2.4.8.273.1.2.1.4

Field Name : certStatsOperKeyCount
Field Type : CounterBasedGauge64
Field Status : current
Description : key-count
OID : 1.3.6.1.4.1.22610.2.4.8.273.1.2.1.3

Field Name : certStatsOperCertCount
Field Type : CounterBasedGauge64
Field Status : current
Description : cert-count
OID : 1.3.6.1.4.1.22610.2.4.8.273.1.2.1.2

Field Name : certStatsOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.273.1.2.1.1

Field Name : webCategoryOperTable
Field Type : TABLE
Field Status : current
Description : Web-Category Commands from object 'web-category'
OID : 1.3.6.1.4.1.22610.2.4.8.274.1.2

Field Name : webCategoryOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The webCategoryOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.274.1.2.1

Field Name : webCategoryOperWebCatLastSuccessfulConnection
Field Type : String
Field Status : current
Description : web-cat-last-successful-connection
OID : 1.3.6.1.4.1.22610.2.4.8.274.1.2.1.11

Field Name : webCategoryOperWebCatFailureReason
Field Type : String
Field Status : current
Description : web-cat-failure-reason
OID : 1.3.6.1.4.1.22610.2.4.8.274.1.2.1.10

Field Name : webCategoryOperWebCatConnectionStatus
Field Type : String
Field Status : current
Description : web-cat-connection-status
OID : 1.3.6.1.4.1.22610.2.4.8.274.1.2.1.9

Field Name : webCategoryOperWebCatNextUpdateTime
Field Type : String
Field Status : current
Description : web-cat-next-update-time
OID : 1.3.6.1.4.1.22610.2.4.8.274.1.2.1.8

Field Name : webCategoryOperWebCatLastUpdateTime
Field Type : String
Field Status : current
Description : web-cat-last-update-time
OID : 1.3.6.1.4.1.22610.2.4.8.274.1.2.1.7

Field Name : webCategoryOperWebCatDatabaseVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : web-cat-database-version
OID : 1.3.6.1.4.1.22610.2.4.8.274.1.2.1.6

Field Name : webCategoryOperWebCatDatabaseSize
Field Type : String
Field Status : current
Description : web-cat-database-size

OID : 1.3.6.1.4.1.22610.2.4.8.274.1.2.1.5

Field Name : webCategoryOperWebCatDatabaseStatus
Field Type : String
Field Status : current
Description : web-cat-database-status
OID : 1.3.6.1.4.1.22610.2.4.8.274.1.2.1.4

Field Name : webCategoryOperWebCatDatabaseName
Field Type : String
Field Status : current
Description : web-cat-database-name
OID : 1.3.6.1.4.1.22610.2.4.8.274.1.2.1.3

Field Name : webCategoryOperWebCatVersion
Field Type : String
Field Status : current
Description : web-cat-version
OID : 1.3.6.1.4.1.22610.2.4.8.274.1.2.1.2

Field Name : webCategoryOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.274.1.2.1.1

Field Name : licenseOperTable
Field Type : TABLE
Field Status : current
Description : License information from object 'web-category.license'
OID : 1.3.6.1.4.1.22610.2.4.8.278.1.2

Field Name : licenseOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The licenseOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.278.1.2.1

Field Name : licenseOperSerialNumber
Field Type : String
Field Status : current
Description : serial-number
OID : 1.3.6.1.4.1.22610.2.4.8.278.1.2.1.9

Field Name : licenseOperGracePeriod
Field Type : String
Field Status : current
Description : grace-period
OID : 1.3.6.1.4.1.22610.2.4.8.278.1.2.1.8

Field Name : licenseOperIsGrace
Field Type : String
Field Status : current
Description : is-grace
OID : 1.3.6.1.4.1.22610.2.4.8.278.1.2.1.7

Field Name : licenseOperRemainingPeriod
Field Type : String

Field Status : current
Description : remaining-period
OID : 1.3.6.1.4.1.22610.2.4.8.278.1.2.1.6

Field Name : licenseOperLicenseExpiry
Field Type : String
Field Status : current
Description : license-expiry
OID : 1.3.6.1.4.1.22610.2.4.8.278.1.2.1.5

Field Name : licenseOperLicenseType
Field Type : String
Field Status : current
Description : license-type
OID : 1.3.6.1.4.1.22610.2.4.8.278.1.2.1.4

Field Name : licenseOperLicenseStatus
Field Type : String
Field Status : current
Description : license-status
OID : 1.3.6.1.4.1.22610.2.4.8.278.1.2.1.3

Field Name : licenseOperModuleStatus
Field Type : String
Field Status : current
Description : module-status
OID : 1.3.6.1.4.1.22610.2.4.8.278.1.2.1.2

Field Name : licenseOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.278.1.2.1.1

Field Name : statisticsOperPerCpuListTable
Field Type : TABLE
Field Status : current
Description : Statistics from object 'web-category.statistics'
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.3

Field Name : statisticsOperTable
Field Type : TABLE
Field Status : current
Description : Statistics from object 'web-category.statistics'
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.2

Field Name : statisticsOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The statisticsOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.2.1

Field Name : statisticsOperClearCache
Field Type : String
Field Status : current
Description : clear-cache
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.2.1.8

Field Name : statisticsOperTotalReqLookupProcessed
Field Type : CounterBasedGauge64
Field Status : current
Description : total-req-lookup-processed
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.2.1.7

Field Name : statisticsOperTotalReqProcessed
Field Type : CounterBasedGauge64
Field Status : current
Description : total-req-processed
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.2.1.6

Field Name : statisticsOperTotalReqDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : total-req-dropped
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.2.1.5

Field Name : statisticsOperTotalReqQueue
Field Type : CounterBasedGauge64
Field Status : current
Description : total-req-queue
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.2.1.4

Field Name : statisticsOperNumLookupThreads
Field Type : CounterBasedGauge64
Field Status : current
Description : num-lookup-threads
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.2.1.3

Field Name : statisticsOperNumDplaneThreads
Field Type : CounterBasedGauge64
Field Status : current
Description : num-dplane-threads
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.2.1.2

Field Name : statisticsOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.2.1.1

Field Name : statisticsStatsTable
Field Type : TABLE
Field Status : current
Description : Statistics from object 'web-category.statistics'
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.1

Field Name : statisticsStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The statisticsStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.1.1

Field Name : statisticsStatsLookupCacheMem
Field Type : CounterBasedGauge64
Field Status : current
Description : lookup-cache-mem

OID : 1.3.6.1.4.1.22610.2.4.8.280.1.1.1.9

Field Name : statisticsStatsRtuCacheMem
Field Type : CounterBasedGauge64
Field Status : current
Description : rtu-cache-mem
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.1.1.8

Field Name : statisticsStatsDbMem
Field Type : CounterBasedGauge64
Field Status : current
Description : db-mem
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.1.1.7

Field Name : statisticsStatsLookupLatency
Field Type : CounterBasedGauge64
Field Status : current
Description : lookup-latency
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.1.1.6

Field Name : statisticsStatsRtuLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : rtu-lookup
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.1.1.5

Field Name : statisticsStatsCloudLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : cloud-lookup
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.1.1.4

Field Name : statisticsStatsCloudCacheLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : cloud-cache-lookup
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.1.1.3

Field Name : statisticsStatsDbLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : db-lookup
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.1.1.2

Field Name : statisticsStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.1.1.1

Field Name : statisticsOperPerCpuListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The statisticsOperPerCpuList entry:per-cpu-list
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.3.1

Field Name : statisticsOperPerCpuListReqLookupProcessed
Field Type : CounterBasedGauge64

Field Status : current
Description : req-lookup-processed
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.3.1.6

Field Name : statisticsOperPerCpuListReqProcessed
Field Type : CounterBasedGauge64
Field Status : current
Description : req-processed
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.3.1.5

Field Name : statisticsOperPerCpuListReqDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : req-dropped
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.3.1.4

Field Name : statisticsOperPerCpuListReqQueue
Field Type : CounterBasedGauge64
Field Status : current
Description : req-queue
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.3.1.3

Field Name : statisticsOperPerCpuListPerCpuListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.3.1.2

Field Name : statisticsOperPerCpuListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.3.1.1

Field Name : sslAcmeCertStatusOperAcmeCertsTable
Field Type : TABLE
Field Status : current
Description : from object 'slb.ssl-acme-cert-status'
OID : 1.3.6.1.4.1.22610.2.4.8.297.1.2

Field Name : sslAcmeCertStatusOperAcmeCertsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The sslAcmeCertStatusOperAcmeCerts entry:acme-certs
OID : 1.3.6.1.4.1.22610.2.4.8.297.1.2.1

Field Name : sslAcmeCertStatusOperAcmeCertsLastEnrollRenewStatus
Field Type : String
Field Status : current
Description : last-enroll-renew-status
OID : 1.3.6.1.4.1.22610.2.4.8.297.1.2.1.7

Field Name : sslAcmeCertStatusOperAcmeCertsRotated
Field Type : CounterBasedGauge64
Field Status : current
Description : rotated
OID : 1.3.6.1.4.1.22610.2.4.8.297.1.2.1.6

Field Name : sslAcmeCertStatusOperAcmeCertsRenew
Field Type : String
Field Status : current
Description : renew
OID : 1.3.6.1.4.1.22610.2.4.8.297.1.2.1.5

Field Name : sslAcmeCertStatusOperAcmeCertsStatus
Field Type : String
Field Status : current
Description : status
OID : 1.3.6.1.4.1.22610.2.4.8.297.1.2.1.4

Field Name : sslAcmeCertStatusOperAcmeCertsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.297.1.2.1.3

Field Name : sslAcmeCertStatusOperAcmeCertsAcmeCertsListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.297.1.2.1.2

Field Name : sslAcmeCertStatusOperAcmeCertsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.297.1.2.1.1

Field Name : sslStatsOperSslModuleStatsTable
Field Type : TABLE
Field Status : current
Description : SSL Statistics from object 'slb.ssl-stats'
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.3

Field Name : sslStatsOperTable
Field Type : TABLE
Field Status : current
Description : SSL Statistics from object 'slb.ssl-stats'
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2

Field Name : sslStatsOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The sslStatsOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1

Field Name : sslStatsOperUtilEnableStatus
Field Type : String
Field Status : current
Description : util-enable-status
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.68

Field Name : sslStatsOperFpFailAflex
Field Type : CounterBasedGauge64
Field Status : current
Description : fp-fail-aflex

OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.67

Field Name : sslStatsOperFpFailVerifyCert
Field Type : CounterBasedGauge64
Field Status : current
Description : fp-fail-verify-cert
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.66

Field Name : sslStatsOperFpFailTcpError
Field Type : CounterBasedGauge64
Field Status : current
Description : fp-fail-tcp-error
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.65

Field Name : sslStatsOperFpFailHandshake
Field Type : CounterBasedGauge64
Field Status : current
Description : fp-fail-handshake
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.64

Field Name : sslStatsOperServerSslUnknownError
Field Type : CounterBasedGauge64
Field Status : current
Description : server-ssl-unknown-error
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.63

Field Name : sslStatsOperServerSslInternalError
Field Type : CounterBasedGauge64
Field Status : current
Description : server-ssl-internal-error
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.62

Field Name : sslStatsOperClientSslUnknownError
Field Type : CounterBasedGauge64
Field Status : current
Description : client-ssl-unknown-error
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.61

Field Name : sslStatsOperClientSslInternalError
Field Type : CounterBasedGauge64
Field Status : current
Description : client-ssl-internal-error
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.60

Field Name : sslStatsOperServerSslFinReset
Field Type : CounterBasedGauge64
Field Status : current
Description : server-ssl-fin-reset
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.59

Field Name : sslStatsOperServerSslFatalAlert
Field Type : CounterBasedGauge64
Field Status : current
Description : server-ssl-fatal-alert
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.58

Field Name : sslStatsOperSslSessionFinReset
Field Type : CounterBasedGauge64

Field Status : current
Description : ssl-session-fin-reset
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.57

Field Name : sslStatsOperClientSslFinReset
Field Type : CounterBasedGauge64
Field Status : current
Description : client-ssl-fin-reset
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.56

Field Name : sslStatsOperClientSslFatalAlert
Field Type : CounterBasedGauge64
Field Status : current
Description : client-ssl-fatal-alert
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.55

Field Name : sslStatsOperUnsupportedSslVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : unsupported-ssl-version
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.54

Field Name : sslStatsOperRevokedOcspResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : revoked-ocsp-response
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.53

Field Name : sslStatsOperInvalidOcspStaplingResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid-ocsp-stapling-response
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.52

Field Name : sslStatsOperCertificateSigningFailures
Field Type : CounterBasedGauge64
Field Status : current
Description : certificate-signing-failures
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.51

Field Name : sslStatsOperCertificateVerificationFailures
Field Type : CounterBasedGauge64
Field Status : current
Description : certificate-verification-failures
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.50

Field Name : sslStatsOperTcpFailures
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-failures
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.49

Field Name : sslStatsOperCryptioOperations
Field Type : CounterBasedGauge64
Field Status : current
Description : cryptio-operations
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.48

Field Name : sslStatsOperSslHandshakeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl-handshake-failure
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.47

Field Name : sslStatsOperBypassClientAuthSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : bypass-client-auth-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.46

Field Name : sslStatsOperDropEsniSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : drop-esni-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.45

Field Name : sslStatsOperBypassEsniSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : bypass-esni-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.44

Field Name : sslStatsOperResetNoSniSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : reset-no-sni-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.43

Field Name : sslStatsOperBypassNoSniSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : bypass-no-sni-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.42

Field Name : sslStatsOperBypassCertSanSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : bypass-cert-san-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.41

Field Name : sslStatsOperBypassCertIssuerSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : bypass-cert-issuer-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.40

Field Name : sslStatsOperBypassCertSubjectSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : bypass-cert-subject-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.39

Field Name : sslStatsOperBypassSniSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : bypass-sni-sessions

OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.38

Field Name : sslStatsOperBypassAdGroupSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : bypass-ad-group-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.37

Field Name : sslStatsOperBypassUsenameSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : bypass-username-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.36

Field Name : sslStatsOperBypassFailsafeSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : bypass-failsafe-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.35

Field Name : sslStatsOperDynamicSslContexts
Field Type : CounterBasedGauge64
Field Status : current
Description : dynamic-ssl-contexts
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.34

Field Name : sslStatsOperStaticSslContexts
Field Type : CounterBasedGauge64
Field Status : current
Description : static-ssl-contexts
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.33

Field Name : sslStatsOperCurrSslContexts
Field Type : CounterBasedGauge64
Field Status : current
Description : curr-ssl-contexts
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.32

Field Name : sslStatsOperMaxSslContexts
Field Type : CounterBasedGauge64
Field Status : current
Description : max-ssl-contexts
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.31

Field Name : sslStatsOperClientsslContextMallocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : clientssl-context-malloc-fail
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.30

Field Name : sslStatsOperRecordTooBig
Field Type : CounterBasedGauge64
Field Status : current
Description : record-too-big
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.29

Field Name : sslStatsOperHwRingFull
Field Type : CounterBasedGauge64

Field Status : current
Description : hw-ring-full
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.28

Field Name : sslStatsOperHwContextAllocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : hw-context-alloc-fail
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.27

Field Name : sslStatsOperHwContextUsage
Field Type : CounterBasedGauge64
Field Status : current
Description : hw-context-usage
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.26

Field Name : sslStatsOperHwContextTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : hw-context-total
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.25

Field Name : sslStatsOperCaVerificationFailures
Field Type : CounterBasedGauge64
Field Status : current
Description : ca-verification-failures
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.24

Field Name : sslStatsOperClientCertAuthFail
Field Type : CounterBasedGauge64
Field Status : current
Description : client-cert-auth-fail
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.23

Field Name : sslStatsOperServerCertErrors
Field Type : CounterBasedGauge64
Field Status : current
Description : server-cert-errors
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.22

Field Name : sslStatsOperSslMemoryUsage
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl-memory-usage
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.21

Field Name : sslStatsOperFailedCrypto
Field Type : CounterBasedGauge64
Field Status : current
Description : failed-crypto
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.20

Field Name : sslStatsOperFailedHandshakes
Field Type : CounterBasedGauge64
Field Status : current
Description : failed-handshakes
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.19

Field Name : sslStatsOperTotalServersideFailedEarlyDataConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : total-serverside-failed-early-data-connections
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.18

Field Name : sslStatsOperTotalClientsideFailedEarlyDataConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : total-clientside-failed-early-data-connections
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.17

Field Name : sslStatsOperTotalServersideEarlyDataConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : total-serverside-early-data-connections
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.16

Field Name : sslStatsOperTotalClientsideEarlyDataConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : total-clientside-early-data-connections
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.15

Field Name : sslStatsOperTotalReuseSessionTicketServerSsl
Field Type : CounterBasedGauge64
Field Status : current
Description : total-reuse-session-ticket-server-ssl
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.14

Field Name : sslStatsOperTotalReuseSessionTicketClientSsl
Field Type : CounterBasedGauge64
Field Status : current
Description : total-reuse-session-ticket-client-ssl
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.13

Field Name : sslStatsOperTotalReuseServerSsl
Field Type : CounterBasedGauge64
Field Status : current
Description : total-reuse-server-ssl
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.12

Field Name : sslStatsOperTotalReuseClientSsl
Field Type : CounterBasedGauge64
Field Status : current
Description : total-reuse-client-ssl
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.11

Field Name : sslStatsOperNonSslBypassConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : non-ssl-bypass-connections
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.10

Field Name : sslStatsOperTotalServersideConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : total-serverside-connections

OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.9

Field Name : sslStatsOperCurrentServersideConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : current-serverside-connections
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.8

Field Name : sslStatsOperTotalClientsideConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : total-clientside-connections
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.7

Field Name : sslStatsOperCurrentClientsideConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : current-clientside-connections
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.6

Field Name : sslStatsOperSslModulesCount
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl-modules-count
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.5

Field Name : sslStatsOperThalesHsmStatus
Field Type : String
Field Status : current
Description : thales-hsm-status
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.4

Field Name : sslStatsOperConfigModuleType
Field Type : String
Field Status : current
Description : config-module-type
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.3

Field Name : sslStatsOperSslModuleType
Field Type : String
Field Status : current
Description : ssl-module-type
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.2

Field Name : sslStatsOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.1

Field Name : sslStatsOperSslModuleStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The sslStatsOperSslModuleStats entry:ssl-module-stats
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.3.1

Field Name : sslStatsOperSslModuleStats60secRate
Field Type : CounterBasedGauge64

Field Status : current
Description : 60sec-rate
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.3.1.12

Field Name : sslStatsOperSslModuleStats30secRate
Field Type : CounterBasedGauge64
Field Status : current
Description : 30sec-rate
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.3.1.11

Field Name : sslStatsOperSslModuleStats10secRate
Field Type : CounterBasedGauge64
Field Status : current
Description : 10sec-rate
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.3.1.10

Field Name : sslStatsOperSslModuleStats5secRate
Field Type : CounterBasedGauge64
Field Status : current
Description : 5sec-rate
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.3.1.9

Field Name : sslStatsOperSslModuleStats1secRate
Field Type : CounterBasedGauge64
Field Status : current
Description : 1sec-rate
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.3.1.8

Field Name : sslStatsOperSslModuleStatsUtilPercentage
Field Type : CounterBasedGauge64
Field Status : current
Description : util-percentage
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.3.1.7

Field Name : sslStatsOperSslModuleStatsRequestsHandled
Field Type : CounterBasedGauge64
Field Status : current
Description : requests-handled
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.3.1.6

Field Name : sslStatsOperSslModuleStatsTotalAvailableCryptoEngines
Field Type : CounterBasedGauge64
Field Status : current
Description : total-available-crypto-engines
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.3.1.5

Field Name : sslStatsOperSslModuleStatsTotalEnabledCryptoEngines
Field Type : CounterBasedGauge64
Field Status : current
Description : total-enabled-crypto-engines
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.3.1.4

Field Name : sslStatsOperSslModuleStatsSslModulesIndex
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl-modules-index
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.3.1.3

Field Name : sslStatsOperSslModuleStatsSslModuleStatsListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.3.1.2

Field Name : sslStatsOperSslModuleStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.3.1.1

Field Name : sslForwardProxyStatsTable
Field Type : TABLE
Field Status : current
Description : SSL forward proxy stats info from object 'slb.ssl-forward-proxy'
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1

Field Name : sslForwardProxyStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The sslForwardProxyStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1

Field Name : sslForwardProxyStatsBypassServerIpSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : bypass-server-ip-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.37

Field Name : sslForwardProxyStatsBypassClientIpSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : bypass-client-ip-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.36

Field Name : sslForwardProxyStatsCertInCache
Field Type : CounterBasedGauge64
Field Status : current
Description : cert_in_cache
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.35

Field Name : sslForwardProxyStatsAsyncConnLimitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : async_conn_limit_drop
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.34

Field Name : sslForwardProxyStatsAsyncConnTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : async_conn_timeout
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.33

Field Name : sslForwardProxyStatsCurrConnInBuff
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_conn_in_buff

OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.32

Field Name : sslForwardProxyStatsTotConnInBuff
Field Type : CounterBasedGauge64
Field Status : current
Description : tot_conn_in_buff
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.31

Field Name : sslForwardProxyStatsBypassAdGroupSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : bypass-ad-group-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.30

Field Name : sslForwardProxyStatsBypassUsernameSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : bypass-username-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.29

Field Name : sslForwardProxyStatsDropEsniSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : drop-esni-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.28

Field Name : sslForwardProxyStatsBypassEsniSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : bypass-esni-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.27

Field Name : sslForwardProxyStatsResetNoSniSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : reset-no-sni-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.26

Field Name : sslForwardProxyStatsBypassNoSniSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : bypass-no-sni-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.25

Field Name : sslForwardProxyStatsBypassCertSanSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : bypass-cert-san-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.24

Field Name : sslForwardProxyStatsBypassCertIssuerSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : bypass-cert-issuer-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.23

Field Name : sslForwardProxyStatsBypassCertSubjectSessions
Field Type : CounterBasedGauge64

Field Status : current
Description : bypass-cert-subject-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.22

Field Name : sslForwardProxyStatsAflexBypass
Field Type : CounterBasedGauge64
Field Status : current
Description : aflex-bypass
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.21

Field Name : sslForwardProxyStatsConnectionsFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : connections-failed
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.20

Field Name : sslForwardProxyStatsCertificatesInCache
Field Type : CounterBasedGauge64
Field Status : current
Description : certificates-in-cache
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.19

Field Name : sslForwardProxyStatsUnsupportedSslVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : unsupported-ssl-version
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.18

Field Name : sslForwardProxyStatsRevokedOcspResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : revoked-ocsp-response
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.17

Field Name : sslForwardProxyStatsInvalidOcspStaplingResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid-ocsp-stapling-response
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.16

Field Name : sslForwardProxyStatsFailedInCertificateSigning
Field Type : CounterBasedGauge64
Field Status : current
Description : failed-in-certificate-signing
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.15

Field Name : sslForwardProxyStatsFailedInCertificateVerification
Field Type : CounterBasedGauge64
Field Status : current
Description : failed-in-certificate-verification
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.14

Field Name : sslForwardProxyStatsFailedInTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : failed-in-tcp
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.13

Field Name : sslForwardProxyStatsFailedInCryptoOperations
Field Type : CounterBasedGauge64
Field Status : current
Description : failed-in-crypto-operations
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.12

Field Name : sslForwardProxyStatsFailedInSslHandshakes
Field Type : CounterBasedGauge64
Field Status : current
Description : failed-in-ssl-handshakes
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.11

Field Name : sslForwardProxyStatsBypassClientAuthSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : bypass-client-auth-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.10

Field Name : sslForwardProxyStatsBypassSniSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : bypass-sni-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.9

Field Name : sslForwardProxyStatsBypassFailsafeSslSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : bypass-failsafe-ssl-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.8

Field Name : sslForwardProxyStatsConnInspect
Field Type : CounterBasedGauge64
Field Status : current
Description : conn_inspect
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.7

Field Name : sslForwardProxyStatsConnBypass
Field Type : CounterBasedGauge64
Field Status : current
Description : conn_bypass
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.6

Field Name : sslForwardProxyStatsCertMiss
Field Type : CounterBasedGauge64
Field Status : current
Description : cert_miss
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.5

Field Name : sslForwardProxyStatsCertHit
Field Type : CounterBasedGauge64
Field Status : current
Description : cert_hit
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.4

Field Name : sslForwardProxyStatsCertExpr
Field Type : CounterBasedGauge64
Field Status : current
Description : cert_expr

OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.3

Field Name : sslForwardProxyStatsCertCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : cert_create
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.2

Field Name : sslForwardProxyStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.1

Field Name : sslJa3OperRecordTable
Field Type : TABLE
Field Status : current
Description : Show SSL JA3 from object 'slb.ssl-ja3'
OID : 1.3.6.1.4.1.22610.2.4.8.314.1.2

Field Name : sslJa3OperRecordEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The sslJa3OperRecord entry:record
OID : 1.3.6.1.4.1.22610.2.4.8.314.1.2.1

Field Name : sslJa3OperRecordAmount
Field Type : CounterBasedGauge64
Field Status : current
Description : amount
OID : 1.3.6.1.4.1.22610.2.4.8.314.1.2.1.5

Field Name : sslJa3OperRecordAddrV6
Field Type : String
Field Status : current
Description : addr-v6
OID : 1.3.6.1.4.1.22610.2.4.8.314.1.2.1.4

Field Name : sslJa3OperRecordAddrV4
Field Type : String
Field Status : current
Description : addr-v4
OID : 1.3.6.1.4.1.22610.2.4.8.314.1.2.1.3

Field Name : sslJa3OperRecordRecordListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.314.1.2.1.2

Field Name : sslJa3OperRecordSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.314.1.2.1.1

Field Name : sslJa4OperRecordTable
Field Type : TABLE

Field Status : current
Description : Show SSL JA4 from object 'slb.ssl-ja4'
OID : 1.3.6.1.4.1.22610.2.4.8.315.1.2

Field Name : sslJa4OperRecordEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The sslJa4OperRecord entry:record
OID : 1.3.6.1.4.1.22610.2.4.8.315.1.2.1

Field Name : sslJa4OperRecordAmount
Field Type : CounterBasedGauge64
Field Status : current
Description : amount
OID : 1.3.6.1.4.1.22610.2.4.8.315.1.2.1.5

Field Name : sslJa4OperRecordAddrV6
Field Type : String
Field Status : current
Description : addr-v6
OID : 1.3.6.1.4.1.22610.2.4.8.315.1.2.1.4

Field Name : sslJa4OperRecordAddrV4
Field Type : String
Field Status : current
Description : addr-v4
OID : 1.3.6.1.4.1.22610.2.4.8.315.1.2.1.3

Field Name : sslJa4OperRecordRecordListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.315.1.2.1.2

Field Name : sslJa4OperRecordSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.315.1.2.1.1

Field Name : portOperDrsIpNatListNatPoolAddrListTable
Field Type : TABLE
Field Status : current
Description : Real Server Port from object 'slb.server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.8

Field Name : portOperDrsIpNatListTable
Field Type : TABLE
Field Status : current
Description : Real Server Port from object 'slb.server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.7

Field Name : portOperDrsIpNatListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portOperDrsIpNatList entry:drs-ip-nat-list
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.7.1

Field Name : portOperDrsIpNatListPoolName
Field Type : String
Field Status : current
Description : pool_name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.7.1.8

Field Name : portOperDrsIpNatListDrsPort
Field Type : CounterBasedGauge64
Field Status : current
Description : drs_port
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.7.1.7

Field Name : portOperDrsIpNatListDrsName
Field Type : String
Field Status : current
Description : drs_name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.7.1.6

Field Name : portOperDrsIpNatListDrsIpNatListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.7.1.5

Field Name : portOperDrsIpNatListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.7.1.4

Field Name : portOperDrsIpNatListPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.7.1.3

Field Name : portOperDrsIpNatListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.7.1.2

Field Name : portOperDrsIpNatListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.7.1.1

Field Name : portOperNatPoolAddrListTable
Field Type : TABLE
Field Status : current
Description : Real Server Port from object 'slb.server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.6

Field Name : portOperNatPoolAddrListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portOperNatPoolAddrList entry:nat-pool-addr-list

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.6.1

Field Name : portOperNatPoolAddrListAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : alloc_failed
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.6.1.10

Field Name : portOperNatPoolAddrListPortsFreedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_freed_total
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.6.1.9

Field Name : portOperNatPoolAddrListPortsConsumedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed_total
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.6.1.8

Field Name : portOperNatPoolAddrListPortsConsumed
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.6.1.7

Field Name : portOperNatPoolAddrListNatIp
Field Type : String
Field Status : current
Description : nat_ip
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.6.1.6

Field Name : portOperNatPoolAddrListNatPoolAddrListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.6.1.5

Field Name : portOperNatPoolAddrListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.6.1.4

Field Name : portOperNatPoolAddrListPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.6.1.3

Field Name : portOperNatPoolAddrListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.6.1.2

Field Name : portOperNatPoolAddrListSlotId
Field Type : Integer32

Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.6.1.1

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListTable
Field Type : TABLE
Field Status : current
Description : Real Server Port from object 'slb.server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.5

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portOperDrsAutoNatListDrsAutoNatAddressList entry:drs-auto-nat-address-list
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.5.1

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : alloc_failed
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.5.1.14

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListPortsFreedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_freed_total
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.5.1.13

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListPortsConsumedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed_total
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.5.1.12

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListPortsConsumed
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.5.1.11

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListIpRr
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_rr
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.5.1.10

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListHaGroupId
Field Type : CounterBasedGauge64
Field Status : current
Description : ha_group_id
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.5.1.9

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListVrid
Field Type : CounterBasedGauge64
Field Status : current
Description : vrid
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.5.1.8

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListAutoNatIp
Field Type : String
Field Status : current
Description : auto_nat_ip
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.5.1.7

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListDrsAutoNatAddressListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.5.1.6

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListDrsAutoNatListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.5.1.5

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.5.1.4

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.5.1.3

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.5.1.2

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.5.1.1

Field Name : portOperDrsAutoNatListTable
Field Type : TABLE
Field Status : current
Description : Real Server Port from object 'slb.server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.4

Field Name : portOperDrsAutoNatListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portOperDrsAutoNatList entry:drs-auto-nat-list
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.4.1

Field Name : portOperDrsAutoNatListDrsPort
Field Type : CounterBasedGauge64
Field Status : current
Description : drs_port

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.4.1.7

Field Name : portOperDrsAutoNatListDrsName
Field Type : String
Field Status : current
Description : drs_name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.4.1.6

Field Name : portOperDrsAutoNatListDrsAutoNatListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.4.1.5

Field Name : portOperDrsAutoNatListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.4.1.4

Field Name : portOperDrsAutoNatListPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.4.1.3

Field Name : portOperDrsAutoNatListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.4.1.2

Field Name : portOperDrsAutoNatListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.4.1.1

Field Name : portOperAutoNatAddrListTable
Field Type : TABLE
Field Status : current
Description : Real Server Port from object 'slb.server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.3

Field Name : portOperAutoNatAddrListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portOperAutoNatAddrList entry:auto-nat-addr-list
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.3.1

Field Name : portOperAutoNatAddrListAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : alloc_failed
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.3.1.13

Field Name : portOperAutoNatAddrListPortsFreedTotal
Field Type : CounterBasedGauge64

Field Status : current
Description : ports_freed_total
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.3.1.12

Field Name : portOperAutoNatAddrListPortsConsumedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed_total
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.3.1.11

Field Name : portOperAutoNatAddrListPortsConsumed
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.3.1.10

Field Name : portOperAutoNatAddrListIpRr
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_rr
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.3.1.9

Field Name : portOperAutoNatAddrListHaGroupId
Field Type : CounterBasedGauge64
Field Status : current
Description : ha_group_id
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.3.1.8

Field Name : portOperAutoNatAddrListVrid
Field Type : CounterBasedGauge64
Field Status : current
Description : vrid
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.3.1.7

Field Name : portOperAutoNatAddrListAutoNatIp
Field Type : String
Field Status : current
Description : auto_nat_ip
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.3.1.6

Field Name : portOperAutoNatAddrListAutoNatAddrListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.3.1.5

Field Name : portOperAutoNatAddrListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.3.1.4

Field Name : portOperAutoNatAddrListPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.3.1.3

Field Name : portOperAutoNatAddrListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.3.1.2

Field Name : portOperAutoNatAddrListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.3.1.1

Field Name : portOperTable
Field Type : TABLE
Field Status : current
Description : Real Server Port from object 'slb.server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2

Field Name : portOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1

Field Name : portOperPoolName
Field Type : String
Field Status : current
Description : pool_name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.23

Field Name : portOperResvConn
Field Type : CounterBasedGauge64
Field Status : current
Description : resv_conn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.22

Field Name : portOperAflowQueueSize
Field Type : CounterBasedGauge64
Field Status : current
Description : aflow_queue_size
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.21

Field Name : portOperAflowConnLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : aflow_conn_limit
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.20

Field Name : portOperSoftDownTime
Field Type : CounterBasedGauge64
Field Status : current
Description : soft_down_time
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.19

Field Name : portOperHmIndex
Field Type : CounterBasedGauge64
Field Status : current
Description : hm-index

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.18

Field Name : portOperHmKey
Field Type : CounterBasedGauge64
Field Status : current
Description : hm-key
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.17

Field Name : portOperDisable
Field Type : CounterBasedGauge64
Field Status : current
Description : disable
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.16

Field Name : portOperInbandHmReassignNum
Field Type : CounterBasedGauge64
Field Status : current
Description : inband_hm_reassign_num
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.15

Field Name : portOperEsRespTime
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_time
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.14

Field Name : portOperDiameterEnabled
Field Type : CounterBasedGauge64
Field Status : current
Description : diameter_enabled
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.13

Field Name : portOperDownTimeGracePeriod
Field Type : CounterBasedGauge64
Field Status : current
Description : down_time_grace_period
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.12

Field Name : portOperCurrentTime
Field Type : CounterBasedGauge64
Field Status : current
Description : current_time
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.11

Field Name : portOperDownGracePeriodAllowed
Field Type : CounterBasedGauge64
Field Status : current
Description : down_grace_period_allowed
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.10

Field Name : portOperCurrObserveRate
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_observe_rate
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.9

Field Name : portOperSlowStartConnLimit
Field Type : CounterBasedGauge64

Field Status : current
Description : slow_start_conn_limit
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.8

Field Name : portOperConnRateUnit
Field Type : String
Field Status : current
Description : conn_rate_unit
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.7

Field Name : portOperCurrConnRate
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_conn_rate
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.6

Field Name : portOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.5

Field Name : portOperProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.4

Field Name : portOperPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.3

Field Name : portOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.2

Field Name : portOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.1

Field Name : portStatsTable
Field Type : TABLE
Field Status : current
Description : Real Server Port from object 'slb.server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1

Field Name : portStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1

Field Name : portStatsCurrPconn
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_pconn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.39

Field Name : portStatsRespLatency
Field Type : CounterBasedGauge64
Field Status : current
Description : resp-latency
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.38

Field Name : portStatsRespOther
Field Type : CounterBasedGauge64
Field Status : current
Description : resp-other
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.37

Field Name : portStatsResp5xx
Field Type : CounterBasedGauge64
Field Status : current
Description : resp-5xx
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.36

Field Name : portStatsResp4xx
Field Type : CounterBasedGauge64
Field Status : current
Description : resp-4xx
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.35

Field Name : portStatsResp3xx
Field Type : CounterBasedGauge64
Field Status : current
Description : resp-3xx
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.34

Field Name : portStatsResp2xx
Field Type : CounterBasedGauge64
Field Status : current
Description : resp-2xx
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.33

Field Name : portStatsResp1xx
Field Type : CounterBasedGauge64
Field Status : current
Description : resp-1xx
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.32

Field Name : portStatsRespCount
Field Type : CounterBasedGauge64
Field Status : current
Description : resp-count
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.31

Field Name : portStatsTotalSslConn
Field Type : CounterBasedGauge64
Field Status : current
Description : total_ssl_conn

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.30

Field Name : portStatsCurrSslConn
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_ssl_conn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.29

Field Name : portStatsSlowestRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : slowest_rsp_time
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.28

Field Name : portStatsFastestRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : fastest_rsp_time
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.27

Field Name : portStatsResponseTime
Field Type : CounterBasedGauge64
Field Status : current
Description : response_time
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.26

Field Name : portStatsTotalRevPktsInspectedGoodStatusCode
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts_inspected_good_status_code
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.25

Field Name : portStatsTotalRevPktsInspected
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts_inspected
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.24

Field Name : portStatsEsRespInvalidHttp
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_invalid_http
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.23

Field Name : portStatsEsRespCount
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_count
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.22

Field Name : portStatsEsReqCount
Field Type : CounterBasedGauge64
Field Status : current
Description : es_req_count
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.21

Field Name : portStatsEsRespOther
Field Type : CounterBasedGauge64

Field Status : current
Description : es_resp_other
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.20

Field Name : portStatsEsResp500
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_500
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.19

Field Name : portStatsEsResp400
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_400
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.18

Field Name : portStatsEsResp300
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_300
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.17

Field Name : portStatsEsResp200
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_200
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.16

Field Name : portStatsPeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : peak_conn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.15

Field Name : portStatsLastTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : last_total_conn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.14

Field Name : portStatsTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : total_conn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.13

Field Name : portStatsTotalRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.12

Field Name : portStatsTotalRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.11

Field Name : portStatsTotalFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : total_fwd_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.10

Field Name : portStatsTotalFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total_fwd_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.9

Field Name : portStatsTotalReqSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : total_req_succ
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.8

Field Name : portStatsTotalReq
Field Type : CounterBasedGauge64
Field Status : current
Description : total_req
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.7

Field Name : portStatsCurrReq
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_req
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.6

Field Name : portStatsCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_conn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.5

Field Name : portStatsProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.4

Field Name : portStatsPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.3

Field Name : portStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.2

Field Name : portStatsSlotId
Field Type : Integer32
Field Status : current
Description :

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.1

Field Name : portOperDrsIpNatListNatPoolAddrListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portOperDrsIpNatListNatPoolAddrList entry:nat-pool-addr-list
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.8.1

Field Name : portOperDrsIpNatListNatPoolAddrListAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : alloc_failed
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.8.1.11

Field Name : portOperDrsIpNatListNatPoolAddrListPortsFreedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_freed_total
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.8.1.10

Field Name : portOperDrsIpNatListNatPoolAddrListPortsConsumedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed_total
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.8.1.9

Field Name : portOperDrsIpNatListNatPoolAddrListPortsConsumed
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.8.1.8

Field Name : portOperDrsIpNatListNatPoolAddrListNatIp
Field Type : String
Field Status : current
Description : nat_ip
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.8.1.7

Field Name : portOperDrsIpNatListNatPoolAddrListNatPoolAddrListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.8.1.6

Field Name : portOperDrsIpNatListNatPoolAddrListDrsIpNatListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.8.1.5

Field Name : portOperDrsIpNatListNatPoolAddrListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.8.1.4

Field Name : portOperDrsIpNatListNatPoolAddrListPort
Field Type : Integer32

Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.8.1.3

Field Name : portOperDrsIpNatListNatPoolAddrListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.8.1.2

Field Name : portOperDrsIpNatListNatPoolAddrListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.8.1.1

Field Name : serverOperDrsListTable
Field Type : TABLE
Field Status : current
Description : Server from object 'slb.server'
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3

Field Name : serverOperDrsListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serverOperDrsList entry:drs-list
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1

Field Name : serverOperDrsListDrsWeight
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-weight
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.28

Field Name : serverOperDrsListDrsPeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-peak-conn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.27

Field Name : serverOperDrsListDrsTotRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-tot-rev-pkts
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.26

Field Name : serverOperDrsListDrsTotRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-tot-rev-bytes
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.25

Field Name : serverOperDrsListDrsTotFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-tot-fwd-pkts
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.24

Field Name : serverOperDrsListDrsTotFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-tot-fwd-bytes
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.23

Field Name : serverOperDrsListDrsTotReqSuc
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-tot-req-suc
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.22

Field Name : serverOperDrsListDrsTotReq
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-tot-req
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.21

Field Name : serverOperDrsListDrsTotConn
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-tot-conn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.20

Field Name : serverOperDrsListDrsCurrReq
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-curr-req
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.19

Field Name : serverOperDrsListDrsCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-curr-conn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.18

Field Name : serverOperDrsListDrsDisable
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-disable
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.17

Field Name : serverOperDrsListDrsCurrObserveRate
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-curr_observe_rate
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.16

Field Name : serverOperDrsListDrsConnRateUnit
Field Type : String
Field Status : current
Description : drs-conn_rate_unit
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.15

Field Name : serverOperDrsListDrsCurrConnRate
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-curr_conn_rate

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.14

Field Name : serverOperDrsListDrsSlowStartConnLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-slow_start_conn_limit
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.13

Field Name : serverOperDrsListDrsIsAutocreate
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-is_autocreate
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.12

Field Name : serverOperDrsListDrsSrvGatewayArp
Field Type : String
Field Status : current
Description : drs-srv_gateway_arp
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.11

Field Name : serverOperDrsListDrsServerTtl
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-server_ttl
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.10

Field Name : serverOperDrsListDrsDnsUpdateTime
Field Type : String
Field Status : current
Description : drs-dns_update_time
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.9

Field Name : serverOperDrsListDrsCreationType
Field Type : String
Field Status : current
Description : drs-creation_type
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.8

Field Name : serverOperDrsListDrsState
Field Type : String
Field Status : current
Description : drs-state
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.7

Field Name : serverOperDrsListDrsServerIpv6Addr
Field Type : String
Field Status : current
Description : drs-server-ipv6-addr
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.6

Field Name : serverOperDrsListDrsHost
Field Type : String
Field Status : current
Description : drs-host
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.5

Field Name : serverOperDrsListDrsName
Field Type : String

Field Status : current
Description : drs-name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.4

Field Name : serverOperDrsListDrsListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.3

Field Name : serverOperDrsListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.2

Field Name : serverOperDrsListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.1

Field Name : serverOperTable
Field Type : TABLE
Field Status : current
Description : Server from object 'slb.server'
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.2

Field Name : serverOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serverOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.2.1

Field Name : serverOperWeight
Field Type : CounterBasedGauge64
Field Status : current
Description : weight
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.2.1.14

Field Name : serverOperDisable
Field Type : CounterBasedGauge64
Field Status : current
Description : disable
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.2.1.13

Field Name : serverOperCurrObserveRate
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_observe_rate
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.2.1.12

Field Name : serverOperConnRateUnit
Field Type : String
Field Status : current
Description : conn_rate_unit
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.2.1.11

Field Name : serverOperCurrConnRate
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_conn_rate
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.2.1.10

Field Name : serverOperSlowStartConnLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : slow_start_conn_limit
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.2.1.9

Field Name : serverOperIsAutocreate
Field Type : CounterBasedGauge64
Field Status : current
Description : is_autocreate
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.2.1.8

Field Name : serverOperSrvGatewayArp
Field Type : String
Field Status : current
Description : srv_gateway_arp
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.2.1.7

Field Name : serverOperServerTtl
Field Type : CounterBasedGauge64
Field Status : current
Description : server_ttl
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.2.1.6

Field Name : serverOperDnsUpdateTime
Field Type : String
Field Status : current
Description : dns_update_time
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.2.1.5

Field Name : serverOperCreationType
Field Type : String
Field Status : current
Description : creation_type
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.2.1.4

Field Name : serverOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.2.1.3

Field Name : serverOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.2.1.2

Field Name : serverOperSlotId
Field Type : Integer32
Field Status : current
Description :

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.2.1.1

Field Name : serverStatsTable
Field Type : TABLE
Field Status : current
Description : Server from object 'slb.server'
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1

Field Name : serverStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serverStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1

Field Name : serverStatsIpOnlyLbRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_only_lb_rev_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.19

Field Name : serverStatsIpOnlyLbFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_only_lb_fwd_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.18

Field Name : serverStatsIpOnlyLbRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_only_lb_rev_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.17

Field Name : serverStatsIpOnlyLbFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_only_lb_fwd_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.16

Field Name : serverStatsTotalRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.15

Field Name : serverStatsTotalFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : total_fwd_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.14

Field Name : serverStatsTotalRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.13

Field Name : serverStatsTotalFwdBytes
Field Type : CounterBasedGauge64

Field Status : current
Description : total_fwd_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.12

Field Name : serverStatsTotalSslConn
Field Type : CounterBasedGauge64
Field Status : current
Description : total_ssl_conn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.11

Field Name : serverStatsCurrSslConn
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_ssl_conn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.10

Field Name : serverStatsTotalReqSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : total_req_succ
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.9

Field Name : serverStatsTotalReq
Field Type : CounterBasedGauge64
Field Status : current
Description : total_req
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.8

Field Name : serverStatsPeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : peak-conn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.7

Field Name : serverStatsRevPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : rev-pkt
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.6

Field Name : serverStatsFwdPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : fwd-pkt
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.5

Field Name : serverStatsTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : total-conn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.4

Field Name : serverStatsCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : curr-conn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.3

Field Name : serverStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.2

Field Name : serverStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.1

Field Name : serviceOperDrsIpNatListNatPoolAddrListTable
Field Type : TABLE
Field Status : current
Description : Real Server Service from object 'slb.server.service'
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.8

Field Name : serviceOperDrsIpNatListTable
Field Type : TABLE
Field Status : current
Description : Real Server Service from object 'slb.server.service'
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.7

Field Name : serviceOperDrsIpNatListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceOperDrsIpNatList entry:drs-ip-nat-list
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.7.1

Field Name : serviceOperDrsIpNatListPoolName
Field Type : String
Field Status : current
Description : pool_name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.7.1.9

Field Name : serviceOperDrsIpNatListDrsPort
Field Type : CounterBasedGauge64
Field Status : current
Description : drs_port
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.7.1.8

Field Name : serviceOperDrsIpNatListDrsName
Field Type : String
Field Status : current
Description : drs_name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.7.1.7

Field Name : serviceOperDrsIpNatListDrsIpNatListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.7.1.6

Field Name : serviceOperDrsIpNatListLabel
Field Type : String
Field Status : current
Description : label

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.7.1.5

Field Name : serviceOperDrsIpNatListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.7.1.4

Field Name : serviceOperDrsIpNatListPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.7.1.3

Field Name : serviceOperDrsIpNatListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.7.1.2

Field Name : serviceOperDrsIpNatListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.7.1.1

Field Name : serviceOperNatPoolAddrListTable
Field Type : TABLE
Field Status : current
Description : Real Server Service from object 'slb.server.service'
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.6

Field Name : serviceOperNatPoolAddrListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceOperNatPoolAddrList entry:nat-pool-addr-list
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.6.1

Field Name : serviceOperNatPoolAddrListAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : alloc_failed
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.6.1.11

Field Name : serviceOperNatPoolAddrListPortsFreedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_freed_total
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.6.1.10

Field Name : serviceOperNatPoolAddrListPortsConsumedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed_total
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.6.1.9

Field Name : serviceOperNatPoolAddrListPortsConsumed
Field Type : CounterBasedGauge64

Field Status : current
Description : ports_consumed
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.6.1.8

Field Name : serviceOperNatPoolAddrListNatIp
Field Type : String
Field Status : current
Description : nat_ip
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.6.1.7

Field Name : serviceOperNatPoolAddrListNatPoolAddrListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.6.1.6

Field Name : serviceOperNatPoolAddrListLabel
Field Type : String
Field Status : current
Description : label
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.6.1.5

Field Name : serviceOperNatPoolAddrListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.6.1.4

Field Name : serviceOperNatPoolAddrListPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.6.1.3

Field Name : serviceOperNatPoolAddrListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.6.1.2

Field Name : serviceOperNatPoolAddrListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.6.1.1

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListTable
Field Type : TABLE
Field Status : current
Description : Real Server Service from object 'slb.server.service'
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.5

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceOperDrsAutoNatListDrsAutoNatAddressList entry:drs-auto-nat-address-list
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.5.1

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : alloc_failed
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.5.1.15

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListPortsFreedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_freed_total
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.5.1.14

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListPortsConsumedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed_total
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.5.1.13

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListPortsConsumed
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.5.1.12

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListIpRr
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_rr
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.5.1.11

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListHaGroupId
Field Type : CounterBasedGauge64
Field Status : current
Description : ha_group_id
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.5.1.10

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListVrid
Field Type : CounterBasedGauge64
Field Status : current
Description : vrid
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.5.1.9

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListAutoNatIp
Field Type : String
Field Status : current
Description : auto_nat_ip
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.5.1.8

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListDrsAutoNatAddressListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.5.1.7

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListDrsAutoNatListListId
Field Type : Integer32
Field Status : current
Description :

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.5.1.6

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListLabel
Field Type : String
Field Status : current
Description : label
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.5.1.5

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.5.1.4

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.5.1.3

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.5.1.2

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.5.1.1

Field Name : serviceOperDrsAutoNatListTable
Field Type : TABLE
Field Status : current
Description : Real Server Service from object 'slb.server.service'
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.4

Field Name : serviceOperDrsAutoNatListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceOperDrsAutoNatList entry:drs-auto-nat-list
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.4.1

Field Name : serviceOperDrsAutoNatListDrsPort
Field Type : CounterBasedGauge64
Field Status : current
Description : drs_port
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.4.1.8

Field Name : serviceOperDrsAutoNatListDrsName
Field Type : String
Field Status : current
Description : drs_name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.4.1.7

Field Name : serviceOperDrsAutoNatListDrsAutoNatListListId
Field Type : Integer32

Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.4.1.6

Field Name : serviceOperDrsAutoNatListLabel
Field Type : String
Field Status : current
Description : label
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.4.1.5

Field Name : serviceOperDrsAutoNatListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.4.1.4

Field Name : serviceOperDrsAutoNatListPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.4.1.3

Field Name : serviceOperDrsAutoNatListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.4.1.2

Field Name : serviceOperDrsAutoNatListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.4.1.1

Field Name : serviceOperAutoNatAddrListTable
Field Type : TABLE
Field Status : current
Description : Real Server Service from object 'slb.server.service'
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.3

Field Name : serviceOperAutoNatAddrListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceOperAutoNatAddrList entry:auto-nat-addr-list
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.3.1

Field Name : serviceOperAutoNatAddrListAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : alloc_failed
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.3.1.14

Field Name : serviceOperAutoNatAddrListPortsFreedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_freed_total
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.3.1.13

Field Name : serviceOperAutoNatAddrListPortsConsumedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed_total
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.3.1.12

Field Name : serviceOperAutoNatAddrListPortsConsumed
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.3.1.11

Field Name : serviceOperAutoNatAddrListIpRr
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_rr
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.3.1.10

Field Name : serviceOperAutoNatAddrListHaGroupId
Field Type : CounterBasedGauge64
Field Status : current
Description : ha_group_id
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.3.1.9

Field Name : serviceOperAutoNatAddrListVrid
Field Type : CounterBasedGauge64
Field Status : current
Description : vrid
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.3.1.8

Field Name : serviceOperAutoNatAddrListAutoNatIp
Field Type : String
Field Status : current
Description : auto_nat_ip
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.3.1.7

Field Name : serviceOperAutoNatAddrListAutoNatAddrListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.3.1.6

Field Name : serviceOperAutoNatAddrListLabel
Field Type : String
Field Status : current
Description : label
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.3.1.5

Field Name : serviceOperAutoNatAddrListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.3.1.4

Field Name : serviceOperAutoNatAddrListPort
Field Type : Integer32
Field Status : current
Description : port-number

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.3.1.3

Field Name : serviceOperAutoNatAddrListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.3.1.2

Field Name : serviceOperAutoNatAddrListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.3.1.1

Field Name : serviceOperTable
Field Type : TABLE
Field Status : current
Description : Real Server Service from object 'slb.server.service'
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.2

Field Name : serviceOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.2.1

Field Name : serviceOperPoolName
Field Type : String
Field Status : current
Description : pool_name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.2.1.24

Field Name : serviceOperResvConn
Field Type : CounterBasedGauge64
Field Status : current
Description : resv_conn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.2.1.23

Field Name : serviceOperAflowQueueSize
Field Type : CounterBasedGauge64
Field Status : current
Description : aflow_queue_size
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.2.1.22

Field Name : serviceOperAflowConnLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : aflow_conn_limit
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.2.1.21

Field Name : serviceOperSoftDownTime
Field Type : CounterBasedGauge64
Field Status : current
Description : soft_down_time
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.2.1.20

Field Name : serviceOperHmIndex
Field Type : CounterBasedGauge64

Field Status : current
Description : hm-index
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.2.1.19

Field Name : serviceOperHmKey
Field Type : CounterBasedGauge64
Field Status : current
Description : hm-key
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.2.1.18

Field Name : serviceOperDisable
Field Type : CounterBasedGauge64
Field Status : current
Description : disable
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.2.1.17

Field Name : serviceOperInbandHmReassignNum
Field Type : CounterBasedGauge64
Field Status : current
Description : inband_hm_reassign_num
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.2.1.16

Field Name : serviceOperEsRespTime
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_time
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.2.1.15

Field Name : serviceOperDiameterEnabled
Field Type : CounterBasedGauge64
Field Status : current
Description : diameter_enabled
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.2.1.14

Field Name : serviceOperDownTimeGracePeriod
Field Type : CounterBasedGauge64
Field Status : current
Description : down_time_grace_period
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.2.1.13

Field Name : serviceOperCurrentTime
Field Type : CounterBasedGauge64
Field Status : current
Description : current_time
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.2.1.12

Field Name : serviceOperDownGracePeriodAllowed
Field Type : CounterBasedGauge64
Field Status : current
Description : down_grace_period_allowed
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.2.1.11

Field Name : serviceOperCurrObserveRate
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_observe_rate
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.2.1.10

Field Name : serviceOperSlowStartConnLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : slow_start_conn_limit
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.2.1.9

Field Name : serviceOperConnRateUnit
Field Type : String
Field Status : current
Description : conn_rate_unit
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.2.1.8

Field Name : serviceOperCurrConnRate
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_conn_rate
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.2.1.7

Field Name : serviceOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.2.1.6

Field Name : serviceOperLabel
Field Type : String
Field Status : current
Description : label
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.2.1.5

Field Name : serviceOperProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.2.1.4

Field Name : serviceOperPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.2.1.3

Field Name : serviceOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.2.1.2

Field Name : serviceOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.2.1.1

Field Name : serviceStatsTable
Field Type : TABLE
Field Status : current
Description : Real Server Service from object 'slb.server.service'

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1

Field Name : serviceStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1

Field Name : serviceStatsCurrPconn
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_pconn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.40

Field Name : serviceStatsRespLatency
Field Type : CounterBasedGauge64
Field Status : current
Description : resp-latency
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.39

Field Name : serviceStatsRespOther
Field Type : CounterBasedGauge64
Field Status : current
Description : resp-other
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.38

Field Name : serviceStatsResp5xx
Field Type : CounterBasedGauge64
Field Status : current
Description : resp-5xx
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.37

Field Name : serviceStatsResp4xx
Field Type : CounterBasedGauge64
Field Status : current
Description : resp-4xx
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.36

Field Name : serviceStatsResp3xx
Field Type : CounterBasedGauge64
Field Status : current
Description : resp-3xx
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.35

Field Name : serviceStatsResp2xx
Field Type : CounterBasedGauge64
Field Status : current
Description : resp-2xx
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.34

Field Name : serviceStatsResp1xx
Field Type : CounterBasedGauge64
Field Status : current
Description : resp-1xx
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.33

Field Name : serviceStatsRespCount
Field Type : CounterBasedGauge64

Field Status : current
Description : resp-count
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.32

Field Name : serviceStatsTotalSslConn
Field Type : CounterBasedGauge64
Field Status : current
Description : total_ssl_conn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.31

Field Name : serviceStatsCurrSslConn
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_ssl_conn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.30

Field Name : serviceStatsSlowestRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : slowest_rsp_time
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.29

Field Name : serviceStatsFastestRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : fastest_rsp_time
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.28

Field Name : serviceStatsResponseTime
Field Type : CounterBasedGauge64
Field Status : current
Description : response_time
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.27

Field Name : serviceStatsTotalRevPktsInspectedGoodStatusCode
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts_inspected_good_status_code
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.26

Field Name : serviceStatsTotalRevPktsInspected
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts_inspected
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.25

Field Name : serviceStatsEsRespInvalidHttp
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_invalid_http
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.24

Field Name : serviceStatsEsRespCount
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_count
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.23

Field Name : serviceStatsEsReqCount
Field Type : CounterBasedGauge64
Field Status : current
Description : es_req_count
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.22

Field Name : serviceStatsEsRespOther
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_other
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.21

Field Name : serviceStatsEsResp500
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_500
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.20

Field Name : serviceStatsEsResp400
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_400
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.19

Field Name : serviceStatsEsResp300
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_300
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.18

Field Name : serviceStatsEsResp200
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_200
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.17

Field Name : serviceStatsPeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : peak_conn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.16

Field Name : serviceStatsLastTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : last_total_conn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.15

Field Name : serviceStatsTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : total_conn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.14

Field Name : serviceStatsTotalRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.13

Field Name : serviceStatsTotalRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.12

Field Name : serviceStatsTotalFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : total_fwd_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.11

Field Name : serviceStatsTotalFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total_fwd_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.10

Field Name : serviceStatsTotalReqSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : total_req_succ
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.9

Field Name : serviceStatsTotalReq
Field Type : CounterBasedGauge64
Field Status : current
Description : total_req
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.8

Field Name : serviceStatsCurrReq
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_req
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.7

Field Name : serviceStatsCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_conn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.6

Field Name : serviceStatsLabel
Field Type : String
Field Status : current
Description : label
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.5

Field Name : serviceStatsProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.4

Field Name : serviceStatsPort
Field Type : Integer32

Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.3

Field Name : serviceStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.2

Field Name : serviceStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.1.1.1

Field Name : serviceOperDrsIpNatListNatPoolAddrListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceOperDrsIpNatListNatPoolAddrList entry:nat-pool-addr-list
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.8.1

Field Name : serviceOperDrsIpNatListNatPoolAddrListAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : alloc_failed
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.8.1.12

Field Name : serviceOperDrsIpNatListNatPoolAddrListPortsFreedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_freed_total
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.8.1.11

Field Name : serviceOperDrsIpNatListNatPoolAddrListPortsConsumedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed_total
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.8.1.10

Field Name : serviceOperDrsIpNatListNatPoolAddrListPortsConsumed
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.8.1.9

Field Name : serviceOperDrsIpNatListNatPoolAddrListNatIp
Field Type : String
Field Status : current
Description : nat_ip
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.8.1.8

Field Name : serviceOperDrsIpNatListNatPoolAddrListNatPoolAddrListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.8.1.7

Field Name : serviceOperDrsIpNatListNatPoolAddrListDrsIpNatListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.8.1.6

Field Name : serviceOperDrsIpNatListNatPoolAddrListLabel
Field Type : String
Field Status : current
Description : label
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.8.1.5

Field Name : serviceOperDrsIpNatListNatPoolAddrListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.8.1.4

Field Name : serviceOperDrsIpNatListNatPoolAddrListPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.8.1.3

Field Name : serviceOperDrsIpNatListNatPoolAddrListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.8.1.2

Field Name : serviceOperDrsIpNatListNatPoolAddrListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.12.8.1.1

Field Name : serviceGroupOperSgmListTable
Field Type : TABLE
Field Status : current
Description : Service Group from object 'slb.service-group'
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.3

Field Name : serviceGroupOperSgmListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceGroupOperSgmList entry:sgm-list
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.3.1

Field Name : serviceGroupOperSgmListSgmPort
Field Type : CounterBasedGauge64
Field Status : current
Description : sgm-port
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.3.1.5

Field Name : serviceGroupOperSgmListSgmName
Field Type : String
Field Status : current
Description : sgm-name

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.3.1.4

Field Name : serviceGroupOperSgmListSgmListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.3.1.3

Field Name : serviceGroupOperSgmListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.3.1.2

Field Name : serviceGroupOperSgmListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.3.1.1

Field Name : serviceGroupOperTable
Field Type : TABLE
Field Status : current
Description : Service Group from object 'slb.service-group'
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.2

Field Name : serviceGroupOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceGroupOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.2.1

Field Name : serviceGroupOperFilter
Field Type : String
Field Status : current
Description : filter
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.2.1.14

Field Name : serviceGroupOperPriAffinityPriority
Field Type : CounterBasedGauge64
Field Status : current
Description : pri_affinity_priority
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.2.1.13

Field Name : serviceGroupOperHmDsrEnableAllVip
Field Type : CounterBasedGauge64
Field Status : current
Description : hm_dsr_enable_all_vip
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.2.1.12

Field Name : serviceGroupOperStatelessType
Field Type : CounterBasedGauge64
Field Status : current
Description : stateless_type
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.2.1.11

Field Name : serviceGroupOperStatelessState
Field Type : CounterBasedGauge64

Field Status : current
Description : stateless_state
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.2.1.10

Field Name : serviceGroupOperStatelessCurrentUsage
Field Type : CounterBasedGauge64
Field Status : current
Description : stateless_current_usage
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.2.1.9

Field Name : serviceGroupOperStatelessCurrentRate
Field Type : CounterBasedGauge64
Field Status : current
Description : stateless_current_rate
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.2.1.8

Field Name : serviceGroupOperServersTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : servers_total
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.2.1.7

Field Name : serviceGroupOperServersDisable
Field Type : CounterBasedGauge64
Field Status : current
Description : servers_disable
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.2.1.6

Field Name : serviceGroupOperServersDown
Field Type : CounterBasedGauge64
Field Status : current
Description : servers_down
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.2.1.5

Field Name : serviceGroupOperServersUp
Field Type : CounterBasedGauge64
Field Status : current
Description : servers_up
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.2.1.4

Field Name : serviceGroupOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.2.1.3

Field Name : serviceGroupOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.2.1.2

Field Name : serviceGroupOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.2.1.1

Field Name : serviceGroupStatsTable
Field Type : TABLE
Field Status : current
Description : Service Group from object 'slb.service-group'
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.1

Field Name : serviceGroupStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceGroupStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.1.1

Field Name : serviceGroupStatsServiceCurrConnOverflow
Field Type : CounterBasedGauge64
Field Status : current
Description : service_curr_conn_overflow
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.1.1.14

Field Name : serviceGroupStatsServiceResp5xx
Field Type : CounterBasedGauge64
Field Status : current
Description : service_resp_5xx
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.1.1.13

Field Name : serviceGroupStatsServiceResp4xx
Field Type : CounterBasedGauge64
Field Status : current
Description : service_resp_4xx
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.1.1.12

Field Name : serviceGroupStatsServiceResp3xx
Field Type : CounterBasedGauge64
Field Status : current
Description : service_resp_3xx
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.1.1.11

Field Name : serviceGroupStatsServiceResp2xx
Field Type : CounterBasedGauge64
Field Status : current
Description : service_resp_2xx
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.1.1.10

Field Name : serviceGroupStatsServiceRespCount
Field Type : CounterBasedGauge64
Field Status : current
Description : service_resp_count
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.1.1.9

Field Name : serviceGroupStatsServiceReqCount
Field Type : CounterBasedGauge64
Field Status : current
Description : service_req_count
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.1.1.8

Field Name : serviceGroupStatsServiceUnhealthyHost
Field Type : CounterBasedGauge64
Field Status : current
Description : service_unhealthy_host

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.1.1.7

Field Name : serviceGroupStatsServiceHealthyHost
Field Type : CounterBasedGauge64
Field Status : current
Description : service_healthy_host
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.1.1.6

Field Name : serviceGroupStatsServicePeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : service_peak_conn
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.1.1.5

Field Name : serviceGroupStatsServerSelectionFailReset
Field Type : CounterBasedGauge64
Field Status : current
Description : server_selection_fail_reset
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.1.1.4

Field Name : serviceGroupStatsServerSelectionFailDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : server_selection_fail_drop
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.1.1.3

Field Name : serviceGroupStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.1.1.2

Field Name : serviceGroupStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.1.1.1

Field Name : memberOperAltListTable
Field Type : TABLE
Field Status : current
Description : Service Group Member from object 'slb.service-group.member'
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.4

Field Name : memberOperDrsListTable
Field Type : TABLE
Field Status : current
Description : Service Group Member from object 'slb.service-group.member'
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3

Field Name : memberOperDrsListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The memberOperDrsList entry:drs-list
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1

Field Name : memberOperDrsListDrsSrspTime
Field Type : CounterBasedGauge64

Field Status : current
Description : drs-srsp-time
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.25

Field Name : memberOperDrsListDrsFrspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-frsp-time
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.24

Field Name : memberOperDrsListDrsRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-rsp-time
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.23

Field Name : memberOperDrsListDrsPeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-peak-conn
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.22

Field Name : memberOperDrsListDrsFwdBts
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-fwd-bts
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.21

Field Name : memberOperDrsListDrsRevBts
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-rev-bts
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.20

Field Name : memberOperDrsListDrsFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-fwd-pkts
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.19

Field Name : memberOperDrsListDrsRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-rev-pkts
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.18

Field Name : memberOperDrsListDrsTotalReqSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-total-req-succ
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.17

Field Name : memberOperDrsListDrsTotalReq
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-total-req
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.16

Field Name : memberOperDrsListDrsCurrReq
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-curr-req
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.15

Field Name : memberOperDrsListDrsTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-total-conn
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.14

Field Name : memberOperDrsListDrsPersConn
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-pers-conn
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.13

Field Name : memberOperDrsListDrsCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-curr-conn
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.12

Field Name : memberOperDrsListDrsPriority
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-priority
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.11

Field Name : memberOperDrsListDrsPort
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-port
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.10

Field Name : memberOperDrsListDrsHmIndex
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-hm-index
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.9

Field Name : memberOperDrsListDrsHmKey
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-hm-key
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.8

Field Name : memberOperDrsListDrsState
Field Type : String
Field Status : current
Description : drs-state
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.7

Field Name : memberOperDrsListDrsName
Field Type : String
Field Status : current
Description : drs-name

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.6

Field Name : memberOperDrsListDrsListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.5

Field Name : memberOperDrsListPort
Field Type : Integer32
Field Status : current
Description : port
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.4

Field Name : memberOperDrsListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.3

Field Name : memberOperDrsListServiceGroupName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.2

Field Name : memberOperDrsListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.1

Field Name : memberOperTable
Field Type : TABLE
Field Status : current
Description : Service Group Member from object 'slb.service-group.member'
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.2

Field Name : memberOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The memberOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.2.1

Field Name : memberOperHmIndex
Field Type : CounterBasedGauge64
Field Status : current
Description : hm-index
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.2.1.7

Field Name : memberOperHmKey
Field Type : CounterBasedGauge64
Field Status : current
Description : hm-key
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.2.1.6

Field Name : memberOperState
Field Type : String

Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.2.1.5

Field Name : memberOperPort
Field Type : Integer32
Field Status : current
Description : port
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.2.1.4

Field Name : memberOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.2.1.3

Field Name : memberOperServiceGroupName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.2.1.2

Field Name : memberOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.2.1.1

Field Name : memberStatsTable
Field Type : TABLE
Field Status : current
Description : Service Group Member from object 'slb.service-group.member'
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1

Field Name : memberStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The memberStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1

Field Name : memberStatsStateFlaps
Field Type : CounterBasedGauge64
Field Status : current
Description : state_flaps
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.24

Field Name : memberStatsCurrConnOverflow
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_conn_overflow
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.23

Field Name : memberStatsTotalSslConn
Field Type : CounterBasedGauge64
Field Status : current
Description : total_ssl_conn
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.22

Field Name : memberStatsCurrSslConn
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_ssl_conn
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.21

Field Name : memberStatsSlowestRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : slowest_rsp_time
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.20

Field Name : memberStatsFastestRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : fastest_rsp_time
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.19

Field Name : memberStatsResponseTime
Field Type : CounterBasedGauge64
Field Status : current
Description : response_time
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.18

Field Name : memberStatsPeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : peak_conn
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.17

Field Name : memberStatsTotalReqSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : total_req_succ
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.16

Field Name : memberStatsTotalReq
Field Type : CounterBasedGauge64
Field Status : current
Description : total_req
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.15

Field Name : memberStatsCurrReq
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_req
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.14

Field Name : memberStatsTotalRevPktsInspectedStatusCodeNon5xx
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts_inspected_status_code_non_5xx
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.13

Field Name : memberStatsTotalRevPktsInspectedStatusCode2xx
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts_inspected_status_code_2xx

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.12

Field Name : memberStatsTotalRevPktsInspected
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts_inspected
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.11

Field Name : memberStatsTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : total_conn
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.10

Field Name : memberStatsTotalRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.9

Field Name : memberStatsTotalRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.8

Field Name : memberStatsTotalFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : total_fwd_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.7

Field Name : memberStatsTotalFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total_fwd_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.6

Field Name : memberStatsCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_conn
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.5

Field Name : memberStatsPort
Field Type : Integer32
Field Status : current
Description : port
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.4

Field Name : memberStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.3

Field Name : memberStatsServiceGroupName
Field Type : String

Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.2

Field Name : memberStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.1

Field Name : memberOperAltListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The memberOperAltList entry:alt-list
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.4.1

Field Name : memberOperAltListAltPeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : alt-peak-conn
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.4.1.13

Field Name : memberOperAltListAltFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : alt-fwd-pkts
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.4.1.12

Field Name : memberOperAltListAltRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : alt-rev-pkts
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.4.1.11

Field Name : memberOperAltListAltTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : alt-total-conn
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.4.1.10

Field Name : memberOperAltListAltCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : alt-curr-conn
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.4.1.9

Field Name : memberOperAltListAltState
Field Type : String
Field Status : current
Description : alt-state
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.4.1.8

Field Name : memberOperAltListAltPort
Field Type : CounterBasedGauge64
Field Status : current
Description : alt-port
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.4.1.7

Field Name : memberOperAltListAltName
Field Type : String
Field Status : current
Description : alt-name
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.4.1.6

Field Name : memberOperAltListAltListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.4.1.5

Field Name : memberOperAltListPort
Field Type : Integer32
Field Status : current
Description : port
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.4.1.4

Field Name : memberOperAltListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.4.1.3

Field Name : memberOperAltListServiceGroupName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.4.1.2

Field Name : memberOperAltListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.4.1.1

Field Name : migrateVipOperTable
Field Type : TABLE
Field Status : current
Description : Migrate this virtual server from object 'slb.virtual-server.migrate-vip'
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.3.2

Field Name : migrateVipOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The migrateVipOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.3.2.1

Field Name : migrateVipOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.3.2.1.3

Field Name : migrateVipOperName
Field Type : String
Field Status : current
Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.3.2.1.2

Field Name : migrateVipOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.3.2.1.1

Field Name : virtualServerOperTable
Field Type : TABLE
Field Status : current
Description : Create a Virtual Server from object 'slb.virtual-server'
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2

Field Name : virtualServerOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The virtualServerOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1

Field Name : virtualServerOperIpOnlyLbRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_only_lb_rev_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.21

Field Name : virtualServerOperIpOnlyLbFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_only_lb_fwd_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.20

Field Name : virtualServerOperIpOnlyLbRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_only_lb_rev_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.19

Field Name : virtualServerOperIpOnlyLbFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_only_lb_fwd_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.18

Field Name : virtualServerOperCurrConnOverflow
Field Type : CounterBasedGauge64
Field Status : current
Description : curr-conn-overflow
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.17

Field Name : virtualServerOperIpv6Address
Field Type : String
Field Status : current
Description : ipv6-address
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.16

Field Name : virtualServerOperIpAddress
Field Type : String

Field Status : current
Description : ip-address
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.15

Field Name : virtualServerOperPeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : peak-conn
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.14

Field Name : virtualServerOperMigrationStatus
Field Type : String
Field Status : current
Description : migration-status
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.13

Field Name : virtualServerOperIcmpv6RateOverLimitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : icmpv6-rate-over-limit-drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.12

Field Name : virtualServerOperIcmpv6LockupTimeLeft
Field Type : CounterBasedGauge64
Field Status : current
Description : icmpv6-lockup-time-left
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.11

Field Name : virtualServerOperCurrIcmpv6Rate
Field Type : CounterBasedGauge64
Field Status : current
Description : curr-icmpv6-rate
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.10

Field Name : virtualServerOperIcmpRateOverLimitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-rate-over-limit-drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.9

Field Name : virtualServerOperIcmpLockupTimeLeft
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-lockup-time-left
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.8

Field Name : virtualServerOperCurrIcmpRate
Field Type : CounterBasedGauge64
Field Status : current
Description : curr-icmp-rate
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.7

Field Name : virtualServerOperConnRateUnit
Field Type : String
Field Status : current
Description : conn-rate-unit
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.6

Field Name : virtualServerOperCurrConnRate
Field Type : CounterBasedGauge64
Field Status : current
Description : curr-conn-rate
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.5

Field Name : virtualServerOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.4

Field Name : virtualServerOperMac
Field Type : String
Field Status : current
Description : mac
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.3

Field Name : virtualServerOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.2

Field Name : virtualServerOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.1

Field Name : portOperHttpVportCpuListTable
Field Type : TABLE
Field Status : current
Description : Virtual Port from object 'slb.virtual-server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4

Field Name : portOperHttpHitsListTable
Field Type : TABLE
Field Status : current
Description : Virtual Port from object 'slb.virtual-server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.3

Field Name : portOperHttpHitsListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portOperHttpHitsList entry:http-hits-list
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.3.1

Field Name : portOperHttpHitsListHitsCount
Field Type : CounterBasedGauge64
Field Status : current
Description : hits-count
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.3.1.7

Field Name : portOperHttpHitsListName1
Field Type : String
Field Status : current
Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.3.1.6

Field Name : portOperHttpHitsListHttpHitsListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.3.1.5

Field Name : portOperHttpHitsListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.3.1.4

Field Name : portOperHttpHitsListPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.3.1.3

Field Name : portOperHttpHitsListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.3.1.2

Field Name : portOperHttpHitsListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.3.1.1

Field Name : portOperTable
Field Type : TABLE
Field Status : current
Description : Virtual Port from object 'slb.virtual-server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2

Field Name : portOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1

Field Name : portOperClearCurrConn
Field Type : Integer32
Field Status : current
Description : clear_curr_conn
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.23

Field Name : portOperHttpVport
Field Type : Integer32
Field Status : current
Description : http_vport
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.22

Field Name : portOperHttpUrlHits
Field Type : Integer32

Field Status : current
Description : http_url_hits
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.21

Field Name : portOperHttpHostHits
Field Type : Integer32
Field Status : current
Description : http_host_hits
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.20

Field Name : portOperCpuCount
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-count
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.19

Field Name : portOperLocLast
Field Type : String
Field Status : current
Description : loc_last
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.18

Field Name : portOperLocOverride
Field Type : CounterBasedGauge64
Field Status : current
Description : loc_override
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.17

Field Name : portOperLocError
Field Type : CounterBasedGauge64
Field Status : current
Description : loc_error
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.16

Field Name : portOperLocSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : loc_success
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.15

Field Name : portOperLocMaxDepth
Field Type : CounterBasedGauge64
Field Status : current
Description : loc_max_depth
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.14

Field Name : portOperGroupId
Field Type : CounterBasedGauge64
Field Status : current
Description : group_id
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.13

Field Name : portOperLevelStr
Field Type : String
Field Status : current
Description : level_str
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.12

Field Name : portOperGeoLocation
Field Type : String
Field Status : current
Description : geo_location
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.11

Field Name : portOperLocList
Field Type : String
Field Status : current
Description : loc_list
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.10

Field Name : portOperPrintExtendedStats
Field Type : CounterBasedGauge64
Field Status : current
Description : print_extended_stats
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.9

Field Name : portOperCurrConnOverflow
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_conn_overflow
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.8

Field Name : portOperIntCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : int_curr_conn
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.7

Field Name : portOperRealCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : real_curr_conn
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.6

Field Name : portOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.5

Field Name : portOperProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.4

Field Name : portOperPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.3

Field Name : portOperName
Field Type : String
Field Status : current
Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.2

Field Name : portOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.1

Field Name : portStatsTable
Field Type : TABLE
Field Status : current
Description : Virtual Port from object 'slb.virtual-server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1

Field Name : portStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1

Field Name : portStatsDnsrrlNxExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : dnsrrl_nx_exceed
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.102

Field Name : portStatsHttp2ClientIdleTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : http2_client_idle_timeout
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.101

Field Name : portStatsHttp1ClientIdleTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : http1_client_idle_timeout
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.100

Field Name : portStatsDnsrrlTotalTc
Field Type : CounterBasedGauge64
Field Status : current
Description : dnsrrl_total_tc
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.99

Field Name : portStatsCompressionMissTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_miss_total
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.98

Field Name : portStatsCompressionHitTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_hit_total
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.97

Field Name : portStatsCompressionMissBr
Field Type : CounterBasedGauge64

Field Status : current
Description : compression_miss_br
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.96

Field Name : portStatsCompressionHitBr
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_hit_br
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.95

Field Name : portStatsCompressionBytesAfterTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_bytes_after_total
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.94

Field Name : portStatsCompressionBytesBeforeTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_bytes_before_total
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.93

Field Name : portStatsCompressionBytesAfterBr
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_bytes_after_br
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.92

Field Name : portStatsCompressionBytesBeforeBr
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_bytes_before_br
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.91

Field Name : portStatsDnsRpzTriggerNsName
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_rpz_trigger_ns_name
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.90

Field Name : portStatsDnsRpzTriggerQname
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_rpz_trigger_qname
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.89

Field Name : portStatsDnsRpzTriggerNsIp
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_rpz_trigger_ns_ip
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.88

Field Name : portStatsDnsRpzTriggerRespIp
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_rpz_trigger_resp_ip
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.87

Field Name : portStatsDnsRpzTriggerClientIp
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_rpz_trigger_client_ip
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.86

Field Name : portStatsDnsRpzActionLocalData
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_rpz_action_local_data
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.85

Field Name : portStatsDnsRpzActionNodata
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_rpz_action_nodata
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.84

Field Name : portStatsDnsRpzActionNxdomain
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_rpz_action_nxdomain
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.83

Field Name : portStatsDnsRpzActionTcpOnly
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_rpz_action_tcp_only
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.82

Field Name : portStatsDnsRpzActionPassThru
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_rpz_action_pass_thru
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.81

Field Name : portStatsDnsRpzActionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_rpz_action_drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.80

Field Name : portStatsDnsFilterClassOthersDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_filter_class_others_drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.79

Field Name : portStatsDnsFilterClassAnyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_filter_class_any_drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.78

Field Name : portStatsDnsFilterClassNoneDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_filter_class_none_drop

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.77

Field Name : portStatsDnsFilterClassHesiodDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_filter_class_hesiod_drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.76

Field Name : portStatsDnsFilterClassChaosDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_filter_class_chaos_drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.75

Field Name : portStatsDnsFilterClassInternetDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_filter_class_internet_drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.74

Field Name : portStatsDnsFilterTypeOthersDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_filter_type_others_drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.73

Field Name : portStatsDnsFilterTypeAnyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_filter_type_any_drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.72

Field Name : portStatsDnsFilterTypeTxtDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_filter_type_txt_drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.71

Field Name : portStatsDnsFilterTypeSoaDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_filter_type_soa_drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.70

Field Name : portStatsDnsFilterTypePtrDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_filter_type_ptr_drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.69

Field Name : portStatsDnsFilterTypeSrvDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_filter_type_srv_drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.68

Field Name : portStatsDnsFilterTypeNsDrop
Field Type : CounterBasedGauge64

Field Status : current
Description : dns_filter_type_ns_drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.67

Field Name : portStatsDnsFilterTypeMxDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_filter_type_mx_drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.66

Field Name : portStatsDnsFilterTypeCnameDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_filter_type_cname_drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.65

Field Name : portStatsDnsFilterTypeAaaaDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_filter_type_aaaa_drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.64

Field Name : portStatsDnsFilterTypeADrop
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_filter_type_a_drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.63

Field Name : portStatsTotalDnsFilterClassDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : total_dns_filter_class_drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.62

Field Name : portStatsTotalDnsFilterTypeDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : total_dns_filter_type_drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.61

Field Name : portStatsIpOnlyLbRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_only_lb_rev_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.60

Field Name : portStatsIpOnlyLbFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_only_lb_fwd_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.59

Field Name : portStatsIpOnlyLbRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_only_lb_rev_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.58

Field Name : portStatsIpOnlyLbFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_only_lb_fwd_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.57

Field Name : portStatsDynamicMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : dynamic-memory
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.56

Field Name : portStatsDynamicMemoryFree
Field Type : CounterBasedGauge64
Field Status : current
Description : dynamic-memory-free
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.55

Field Name : portStatsDynamicMemoryAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : dynamic-memory-alloc
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.54

Field Name : portStatsThroughputBitsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : throughput-bits-per-sec
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.53

Field Name : portStatsDnsrrlBadFqdn
Field Type : CounterBasedGauge64
Field Status : current
Description : dnsrrl_bad_fqdn
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.52

Field Name : portStatsDnsrrlTotalSlipped
Field Type : CounterBasedGauge64
Field Status : current
Description : dnsrrl_total_slipped
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.51

Field Name : portStatsDnsrrlTotalDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : dnsrrl_total_dropped
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.50

Field Name : portStatsDnsrrlTotalAllowed
Field Type : CounterBasedGauge64
Field Status : current
Description : dnsrrl_total_allowed
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.49

Field Name : portStatsCurrRespRate
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_resp_rate

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.48

Field Name : portStatsTotalRespSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : total_resp_succ
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.47

Field Name : portStatsTotalResp
Field Type : CounterBasedGauge64
Field Status : current
Description : total_resp
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.46

Field Name : portStatsCurrResp
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_resp
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.45

Field Name : portStatsCurrReqRate
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_req_rate
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.44

Field Name : portStatsTotalRevPktsOut
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts_out
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.43

Field Name : portStatsTotalRevBytesOut
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_bytes_out
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.42

Field Name : portStatsTotalFwdPktsOut
Field Type : CounterBasedGauge64
Field Status : current
Description : total_fwd_pkts_out
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.41

Field Name : portStatsTotalFwdBytesOut
Field Type : CounterBasedGauge64
Field Status : current
Description : total_fwd_bytes_out
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.40

Field Name : portStatsOutLatency
Field Type : CounterBasedGauge64
Field Status : current
Description : out-latency
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.39

Field Name : portStatsInLatency
Field Type : CounterBasedGauge64

Field Status : current
Description : in-latency
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.38

Field Name : portStatsBackendTimeToLastByte
Field Type : CounterBasedGauge64
Field Status : current
Description : backend-time-to-last-byte
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.37

Field Name : portStatsBackendTimeToFirstByte
Field Type : CounterBasedGauge64
Field Status : current
Description : backend-time-to-first-byte
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.36

Field Name : portStatsTotalSslConn
Field Type : CounterBasedGauge64
Field Status : current
Description : total_ssl_conn
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.35

Field Name : portStatsCurrSslConn
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_ssl_conn
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.34

Field Name : portStatsLocConn
Field Type : CounterBasedGauge64
Field Status : current
Description : loc_conn
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.33

Field Name : portStatsLocDeny
Field Type : CounterBasedGauge64
Field Status : current
Description : loc_deny
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.32

Field Name : portStatsLocPermit
Field Type : CounterBasedGauge64
Field Status : current
Description : loc_permit
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.31

Field Name : portStatsSlowestRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : slowest_rsp_time
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.30

Field Name : portStatsFastestRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : fastest_rsp_time
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.29

Field Name : portStatsLastRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : last_rsp_time
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.28

Field Name : portStatsCurrConnRate
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_conn_rate
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.27

Field Name : portStatsPeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : peak_conn
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.26

Field Name : portStatsTotalReqSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : total_req_succ
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.25

Field Name : portStatsTotalReq
Field Type : CounterBasedGauge64
Field Status : current
Description : total_req
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.24

Field Name : portStatsCurrReq
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_req
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.23

Field Name : portStatsCompressionMissTemplateExclusion
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_miss_template_exclusion
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.22

Field Name : portStatsCompressionMissNoClient
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_miss_no_client
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.21

Field Name : portStatsCompressionMiss
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_miss
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.20

Field Name : portStatsCompressionHit
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_hit

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.19

Field Name : portStatsCompressionBytesAfter
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_bytes_after
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.18

Field Name : portStatsCompressionBytesBefore
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_bytes_before
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.17

Field Name : portStatsEsTotalFailureActions
Field Type : CounterBasedGauge64
Field Status : current
Description : es_total_failure_actions
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.16

Field Name : portStatsTotalMfDnsPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : total_mf_dns_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.15

Field Name : portStatsTotalDnsPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : total_dns_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.14

Field Name : portStatsTotalRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.13

Field Name : portStatsTotalRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.12

Field Name : portStatsTotalFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : total_fwd_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.11

Field Name : portStatsTotalFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total_fwd_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.10

Field Name : portStatsTotalConn
Field Type : CounterBasedGauge64

Field Status : current
Description : total_conn
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.9

Field Name : portStatsTotalTcpConn
Field Type : CounterBasedGauge64
Field Status : current
Description : total_tcp_conn
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.8

Field Name : portStatsTotalL7Conn
Field Type : CounterBasedGauge64
Field Status : current
Description : total_l7_conn
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.7

Field Name : portStatsTotalL4Conn
Field Type : CounterBasedGauge64
Field Status : current
Description : total_l4_conn
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.6

Field Name : portStatsCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_conn
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.5

Field Name : portStatsProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.4

Field Name : portStatsPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.3

Field Name : portStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.2

Field Name : portStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.1

Field Name : portOperHttpVportCpuListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portOperHttpVportCpuList entry:http-vport-cpu-list
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1

Field Name : portOperHttpVportCpuListDohDnsRespRcodeOther
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_other
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.213

Field Name : portOperHttpVportCpuListDohDnsRespRcodeNotzone
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_notzone
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.212

Field Name : portOperHttpVportCpuListDohDnsRespRcodeNotauth
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_notauth
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.211

Field Name : portOperHttpVportCpuListDohDnsRespRcodeNxrrset
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_nxrrset
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.210

Field Name : portOperHttpVportCpuListDohDnsRespRcodeYxrrset
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_yxrrset
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.209

Field Name : portOperHttpVportCpuListDohDnsRespRcodeYxdomain
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_yxdomain
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.208

Field Name : portOperHttpVportCpuListDohDnsRespRcodeRefuse
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_refuse
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.207

Field Name : portOperHttpVportCpuListDohDnsRespRcodeErrType
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_err_type
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.206

Field Name : portOperHttpVportCpuListDohDnsRespRcodeErrName
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_err_name
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.205

Field Name : portOperHttpVportCpuListDohDnsRespRcodeErrServer
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_err_server

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.204

Field Name : portOperHttpVportCpuListDohDnsRespRcodeErrFormat
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_err_format
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.203

Field Name : portOperHttpVportCpuListDohDnsMalformedQuery
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_malformed_query
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.202

Field Name : portOperHttpVportCpuListDohPostPayloadTooLarge
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_post_payload_too_large
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.201

Field Name : portOperHttpVportCpuListDohGetUriTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_get_uri_too_long
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.200

Field Name : portOperHttpVportCpuListDohRetryWTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_retry_w_tcp
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.199

Field Name : portOperHttpVportCpuListDohServSelFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_serv_sel_failed
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.198

Field Name : portOperHttpVportCpuListDohRespTcpFrags
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_resp_tcp_frags
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.197

Field Name : portOperHttpVportCpuListDohRespUdpFrags
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_resp_udp_frags
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.196

Field Name : portOperHttpVportCpuListDohRespQueFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_resp_que_failed
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.195

Field Name : portOperHttpVportCpuListDohRespHeaderAllocFailed
Field Type : CounterBasedGauge64

Field Status : current
Description : doh_resp_header_alloc_failed
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.194

Field Name : portOperHttpVportCpuListDohRespSetupFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_resp_setup_failed
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.193

Field Name : portOperHttpVportCpuListDohDnsQueryTypeOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_others
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.192

Field Name : portOperHttpVportCpuListDohDnsQueryTypeSoa
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_soa
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.191

Field Name : portOperHttpVportCpuListDohDnsQueryTypeMx
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_mx
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.190

Field Name : portOperHttpVportCpuListDohDnsQueryTypeSrv
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_srv
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.189

Field Name : portOperHttpVportCpuListDohDnsQueryTypeAny
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_any
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.188

Field Name : portOperHttpVportCpuListDohDnsQueryTypeCname
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_cname
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.187

Field Name : portOperHttpVportCpuListDohDnsQueryTypeNs
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_ns
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.186

Field Name : portOperHttpVportCpuListDohDnsQueryTypeAaaa
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_aaaa
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.185

Field Name : portOperHttpVportCpuListDohDnsQueryTypeA
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_a
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.184

Field Name : portOperHttpVportCpuListDohQueryTimeOut
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_query_time_out
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.183

Field Name : portOperHttpVportCpuListDohUdpSendFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_udp_send_failed
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.182

Field Name : portOperHttpVportCpuListDohTcpSendFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_tcp_send_failed
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.181

Field Name : portOperHttpVportCpuListDohNonDohMethod
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_non_doh_method
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.180

Field Name : portOperHttpVportCpuListDohPostPayloadExtractFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_post_payload_extract_failed
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.179

Field Name : portOperHttpVportCpuListDohPostPayloadNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_post_payload_not_found
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.178

Field Name : portOperHttpVportCpuListDohPostContentTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_post_content_type_mismatch
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.177

Field Name : portOperHttpVportCpuListDohGetBase64DecodeFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_get_base64_decode_failed
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.176

Field Name : portOperHttpVportCpuListDohGetDnsArgFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_get_dns_arg_failed

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.175

Field Name : portOperHttpVportCpuListDohPathNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_path_not_found
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.174

Field Name : portOperHttpVportCpuListDohSnatFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_snat_failed
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.173

Field Name : portOperHttpVportCpuListDohReqTcpRetryFail
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_tcp_retry_fail
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.172

Field Name : portOperHttpVportCpuListDohReqTcpRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_tcp_retry
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.171

Field Name : portOperHttpVportCpuListDohReqUdpRetryFail
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_udp_retry_fail
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.170

Field Name : portOperHttpVportCpuListDohReqUdpRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_udp_retry
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.169

Field Name : portOperHttpVportCpuListDohMallocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_malloc_fail
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.168

Field Name : portOperHttpVportCpuListDohRespSendFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_resp_send_failed
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.167

Field Name : portOperHttpVportCpuListDohReqSendFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_send_failed
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.166

Field Name : portOperHttpVportCpuListDohTcpDnsResp
Field Type : CounterBasedGauge64

Field Status : current
Description : doh_tcp_dns_resp
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.165

Field Name : portOperHttpVportCpuListDohTcpDnsReq
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_tcp_dns_req
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.164

Field Name : portOperHttpVportCpuListDohUdpDnsResp
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_udp_dns_resp
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.163

Field Name : portOperHttpVportCpuListDohUdpDnsReq
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_udp_dns_req
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.162

Field Name : portOperHttpVportCpuListDohTcResp
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_tc_resp
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.161

Field Name : portOperHttpVportCpuListDohResp
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_resp
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.160

Field Name : portOperHttpVportCpuListDohNonDohReqPost
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_non_doh_req_post
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.159

Field Name : portOperHttpVportCpuListDohNonDohReqGet
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_non_doh_req_get
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.158

Field Name : portOperHttpVportCpuListDohNonDohReq
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_non_doh_req
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.157

Field Name : portOperHttpVportCpuListDohReqPost
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_post
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.156

Field Name : portOperHttpVportCpuListDohReqGet
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_get
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.155

Field Name : portOperHttpVportCpuListDohReq
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.154

Field Name : portOperHttpVportCpuListRspChunk
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_chunk
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.153

Field Name : portOperHttpVportCpuListReqContentLen
Field Type : CounterBasedGauge64
Field Status : current
Description : req_content_len
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.152

Field Name : portOperHttpVportCpuListReqSzGt256k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_gt_256k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.151

Field Name : portOperHttpVportCpuListReqSz256k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_256k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.150

Field Name : portOperHttpVportCpuListReqSz64k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_64k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.149

Field Name : portOperHttpVportCpuListReqSz32k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_32k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.148

Field Name : portOperHttpVportCpuListReqSz16k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_16k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.147

Field Name : portOperHttpVportCpuListReqSz8k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_8k

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.146

Field Name : portOperHttpVportCpuListReqSz4k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_4k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.145

Field Name : portOperHttpVportCpuListReqSz2k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_2k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.144

Field Name : portOperHttpVportCpuListReqSz1k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_1k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.143

Field Name : portOperHttpVportCpuListChunkSzGt4k
Field Type : CounterBasedGauge64
Field Status : current
Description : chunk_sz_gt_4k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.142

Field Name : portOperHttpVportCpuListChunkSz4k
Field Type : CounterBasedGauge64
Field Status : current
Description : chunk_sz_4k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.141

Field Name : portOperHttpVportCpuListChunkSz2k
Field Type : CounterBasedGauge64
Field Status : current
Description : chunk_sz_2k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.140

Field Name : portOperHttpVportCpuListChunkSz1k
Field Type : CounterBasedGauge64
Field Status : current
Description : chunk_sz_1k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.139

Field Name : portOperHttpVportCpuListChunkSz512
Field Type : CounterBasedGauge64
Field Status : current
Description : chunk_sz_512
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.138

Field Name : portOperHttpVportCpuListRspSzGt256k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_gt_256k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.137

Field Name : portOperHttpVportCpuListRspSz256k
Field Type : CounterBasedGauge64

Field Status : current
Description : rsp_sz_256k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.136

Field Name : portOperHttpVportCpuListRspSz64k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_64k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.135

Field Name : portOperHttpVportCpuListRspSz32k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_32k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.134

Field Name : portOperHttpVportCpuListRspSz16k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_16k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.133

Field Name : portOperHttpVportCpuListRspSz8k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_8k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.132

Field Name : portOperHttpVportCpuListRspSz4k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_4k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.131

Field Name : portOperHttpVportCpuListRspSz2k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_2k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.130

Field Name : portOperHttpVportCpuListRspSz1k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_1k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.129

Field Name : portOperHttpVportCpuListReqTrack
Field Type : CounterBasedGauge64
Field Status : current
Description : req_track
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.128

Field Name : portOperHttpVportCpuListReqUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : req_unknown
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.127

Field Name : portOperHttpVportCpuListReqDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : req_delete
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.126

Field Name : portOperHttpVportCpuListReqConnect
Field Type : CounterBasedGauge64
Field Status : current
Description : req_connect
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.125

Field Name : portOperHttpVportCpuListReqOptions
Field Type : CounterBasedGauge64
Field Status : current
Description : req_options
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.124

Field Name : portOperHttpVportCpuListReqTrace
Field Type : CounterBasedGauge64
Field Status : current
Description : req_trace
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.123

Field Name : portOperHttpVportCpuListReqPost
Field Type : CounterBasedGauge64
Field Status : current
Description : req_post
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.122

Field Name : portOperHttpVportCpuListReqPut
Field Type : CounterBasedGauge64
Field Status : current
Description : req_put
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.121

Field Name : portOperHttpVportCpuListReqHead
Field Type : CounterBasedGauge64
Field Status : current
Description : req_head
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.120

Field Name : portOperHttpVportCpuListReqGet
Field Type : CounterBasedGauge64
Field Status : current
Description : req_get
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.119

Field Name : portOperHttpVportCpuListHeaderLengthLong
Field Type : CounterBasedGauge64
Field Status : current
Description : header_length_long
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.118

Field Name : portOperHttpVportCpuListJsiHashLookupFails
Field Type : CounterBasedGauge64
Field Status : current
Description : jsi_hash_lookup_fails

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.117

Field Name : portOperHttpVportCpuListJsiHashAddFails
Field Type : CounterBasedGauge64
Field Status : current
Description : jsi_hash_add_fails
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.116

Field Name : portOperHttpVportCpuListJsiSkipNotBrowser
Field Type : CounterBasedGauge64
Field Status : current
Description : jsi_skip_not_browser
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.115

Field Name : portOperHttpVportCpuListJsiSkipNoUa
Field Type : CounterBasedGauge64
Field Status : current
Description : jsi_skip_no_ua
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.114

Field Name : portOperHttpVportCpuListJsiSkipNoFi
Field Type : CounterBasedGauge64
Field Status : current
Description : jsi_skip_no_fi
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.113

Field Name : portOperHttpVportCpuListJsiApiNoToken
Field Type : CounterBasedGauge64
Field Status : current
Description : jsi_api_no_token
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.112

Field Name : portOperHttpVportCpuListJsiApiNoAuthHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : jsi_api_no_auth_hdr
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.111

Field Name : portOperHttpVportCpuListJsiApiResponses
Field Type : CounterBasedGauge64
Field Status : current
Description : jsi_api_responses
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.110

Field Name : portOperHttpVportCpuListJsiApiRequests
Field Type : CounterBasedGauge64
Field Status : current
Description : jsi_api_requests
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.109

Field Name : portOperHttpVportCpuListJsiPriRequests
Field Type : CounterBasedGauge64
Field Status : current
Description : jsi_pri_requests
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.108

Field Name : portOperHttpVportCpuListJsiResponses
Field Type : CounterBasedGauge64

Field Status : current
Description : jsi_responses
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.107

Field Name : portOperHttpVportCpuListJsiRequests
Field Type : CounterBasedGauge64
Field Status : current
Description : jsi_requests
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.106

Field Name : portOperHttpVportCpuListTransactionLimited
Field Type : CounterBasedGauge64
Field Status : current
Description : transaction_limited
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.105

Field Name : portOperHttpVportCpuListStreamClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : stream_closed
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.104

Field Name : portOperHttpVportCpuListHttp2GoawaySent
Field Type : CounterBasedGauge64
Field Status : current
Description : http2_goaway_sent
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.103

Field Name : portOperHttpVportCpuListHttp2GoawayReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : http2_goaway_received
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.102

Field Name : portOperHttpVportCpuListHttp2ResetSent
Field Type : CounterBasedGauge64
Field Status : current
Description : http2_reset_sent
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.101

Field Name : portOperHttpVportCpuListHttp2ResetReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : http2_reset_received
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.100

Field Name : portOperHttpVportCpuListHttp2DataBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : http2_data_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.99

Field Name : portOperHttpVportCpuListHttp2HeaderBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : http2_header_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.98

Field Name : portOperHttpVportCpuListHttp2ControlBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : http2_control_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.97

Field Name : portOperHttpVportCpuListTotalHttp2Bytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total_http2_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.96

Field Name : portOperHttpVportCpuListPeakHttp2Conn
Field Type : CounterBasedGauge64
Field Status : current
Description : peak_http2_conn
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.95

Field Name : portOperHttpVportCpuListTotalHttp2Conn
Field Type : CounterBasedGauge64
Field Status : current
Description : total_http2_conn
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.94

Field Name : portOperHttpVportCpuListCurrHttp2Conn
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_http2_conn
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.93

Field Name : portOperHttpVportCpuListTotalRequests
Field Type : CounterBasedGauge64
Field Status : current
Description : total_requests
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.215

Field Name : portOperHttpVportCpuListREQOVER5s
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_OVER_5s
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.92

Field Name : portOperHttpVportCpuListREQ5s
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_5s
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.91

Field Name : portOperHttpVportCpuListREQ2s
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_2s
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.90

Field Name : portOperHttpVportCpuListREQ1s
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_1s

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.89

Field Name : portOperHttpVportCpuListREQ500m
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_500m
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.88

Field Name : portOperHttpVportCpuListREQ200m
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_200m
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.87

Field Name : portOperHttpVportCpuListREQ100m
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_100m
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.86

Field Name : portOperHttpVportCpuListREQ50m
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_50m
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.85

Field Name : portOperHttpVportCpuListREQ20m
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_20m
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.84

Field Name : portOperHttpVportCpuListREQ10m
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_10m
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.83

Field Name : portOperHttpVportCpuListREQ5m
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_5m
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.82

Field Name : portOperHttpVportCpuListREQ2m
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_2m
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.81

Field Name : portOperHttpVportCpuListREQ1m
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_1m
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.80

Field Name : portOperHttpVportCpuListREQ500u
Field Type : CounterBasedGauge64

Field Status : current
Description : REQ_500u
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.79

Field Name : portOperHttpVportCpuListREQ200u
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_200u
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.78

Field Name : portOperHttpVportCpuListREQ100u
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_100u
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.77

Field Name : portOperHttpVportCpuListREQ50u
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_50u
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.76

Field Name : portOperHttpVportCpuListREQ20u
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_20u
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.75

Field Name : portOperHttpVportCpuListREQ10u
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_10u
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.74

Field Name : portOperHttpVportCpuListWsServerSwitch
Field Type : CounterBasedGauge64
Field Status : current
Description : ws_server_switch
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.73

Field Name : portOperHttpVportCpuListWsClientSwitch
Field Type : CounterBasedGauge64
Field Status : current
Description : ws_client_switch
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.72

Field Name : portOperHttpVportCpuListWsHandshakeSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : ws_handshake_success
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.71

Field Name : portOperHttpVportCpuListWsHandshakeRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : ws_handshake_request
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.70

Field Name : portOperHttpVportCpuListStatusUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : status_unknown
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.69

Field Name : portOperHttpVportCpuListStatus6xx
Field Type : CounterBasedGauge64
Field Status : current
Description : status_6xx
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.68

Field Name : portOperHttpVportCpuListStatus5xx
Field Type : CounterBasedGauge64
Field Status : current
Description : status_5xx
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.67

Field Name : portOperHttpVportCpuListStatus4xx
Field Type : CounterBasedGauge64
Field Status : current
Description : status_4xx
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.66

Field Name : portOperHttpVportCpuListStatus3xx
Field Type : CounterBasedGauge64
Field Status : current
Description : status_3xx
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.65

Field Name : portOperHttpVportCpuListStatus2xx
Field Type : CounterBasedGauge64
Field Status : current
Description : status_2xx
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.64

Field Name : portOperHttpVportCpuListStatus1xx
Field Type : CounterBasedGauge64
Field Status : current
Description : status_1xx
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.63

Field Name : portOperHttpVportCpuListStatus510
Field Type : CounterBasedGauge64
Field Status : current
Description : status_510
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.62

Field Name : portOperHttpVportCpuListStatus509
Field Type : CounterBasedGauge64
Field Status : current
Description : status_509
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.61

Field Name : portOperHttpVportCpuListStatus508
Field Type : CounterBasedGauge64
Field Status : current
Description : status_508

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.60

Field Name : portOperHttpVportCpuListStatus507
Field Type : CounterBasedGauge64
Field Status : current
Description : status_507
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.59

Field Name : portOperHttpVportCpuListStatus506
Field Type : CounterBasedGauge64
Field Status : current
Description : status_506
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.58

Field Name : portOperHttpVportCpuListStatus505
Field Type : CounterBasedGauge64
Field Status : current
Description : status_505
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.57

Field Name : portOperHttpVportCpuListStatus504Ax
Field Type : CounterBasedGauge64
Field Status : current
Description : status_504_ax
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.56

Field Name : portOperHttpVportCpuListStatus504
Field Type : CounterBasedGauge64
Field Status : current
Description : status_504
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.55

Field Name : portOperHttpVportCpuListStatus503
Field Type : CounterBasedGauge64
Field Status : current
Description : status_503
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.54

Field Name : portOperHttpVportCpuListStatus502
Field Type : CounterBasedGauge64
Field Status : current
Description : status_502
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.53

Field Name : portOperHttpVportCpuListStatus501
Field Type : CounterBasedGauge64
Field Status : current
Description : status_501
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.52

Field Name : portOperHttpVportCpuListStatus500
Field Type : CounterBasedGauge64
Field Status : current
Description : status_500
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.51

Field Name : portOperHttpVportCpuListStatus450
Field Type : CounterBasedGauge64

Field Status : current
Description : status_450
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.50

Field Name : portOperHttpVportCpuListStatus449
Field Type : CounterBasedGauge64
Field Status : current
Description : status_449
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.49

Field Name : portOperHttpVportCpuListStatus426
Field Type : CounterBasedGauge64
Field Status : current
Description : status_426
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.48

Field Name : portOperHttpVportCpuListStatus425
Field Type : CounterBasedGauge64
Field Status : current
Description : status_425
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.47

Field Name : portOperHttpVportCpuListStatus424
Field Type : CounterBasedGauge64
Field Status : current
Description : status_424
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.46

Field Name : portOperHttpVportCpuListStatus423
Field Type : CounterBasedGauge64
Field Status : current
Description : status_423
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.45

Field Name : portOperHttpVportCpuListStatus422
Field Type : CounterBasedGauge64
Field Status : current
Description : status_422
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.44

Field Name : portOperHttpVportCpuListStatus418
Field Type : CounterBasedGauge64
Field Status : current
Description : status_418
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.43

Field Name : portOperHttpVportCpuListStatus417
Field Type : CounterBasedGauge64
Field Status : current
Description : status_417
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.42

Field Name : portOperHttpVportCpuListStatus416
Field Type : CounterBasedGauge64
Field Status : current
Description : status_416
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.41

Field Name : portOperHttpVportCpuListStatus415
Field Type : CounterBasedGauge64
Field Status : current
Description : status_415
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.40

Field Name : portOperHttpVportCpuListStatus414
Field Type : CounterBasedGauge64
Field Status : current
Description : status_414
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.39

Field Name : portOperHttpVportCpuListStatus413
Field Type : CounterBasedGauge64
Field Status : current
Description : status_413
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.38

Field Name : portOperHttpVportCpuListStatus412
Field Type : CounterBasedGauge64
Field Status : current
Description : status_412
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.37

Field Name : portOperHttpVportCpuListStatus411
Field Type : CounterBasedGauge64
Field Status : current
Description : status_411
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.36

Field Name : portOperHttpVportCpuListStatus410
Field Type : CounterBasedGauge64
Field Status : current
Description : status_410
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.35

Field Name : portOperHttpVportCpuListStatus409
Field Type : CounterBasedGauge64
Field Status : current
Description : status_409
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.34

Field Name : portOperHttpVportCpuListStatus408
Field Type : CounterBasedGauge64
Field Status : current
Description : status_408
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.33

Field Name : portOperHttpVportCpuListStatus407
Field Type : CounterBasedGauge64
Field Status : current
Description : status_407
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.32

Field Name : portOperHttpVportCpuListStatus406
Field Type : CounterBasedGauge64
Field Status : current
Description : status_406

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.31

Field Name : portOperHttpVportCpuListStatus405
Field Type : CounterBasedGauge64
Field Status : current
Description : status_405
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.30

Field Name : portOperHttpVportCpuListStatus404
Field Type : CounterBasedGauge64
Field Status : current
Description : status_404
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.29

Field Name : portOperHttpVportCpuListStatus403
Field Type : CounterBasedGauge64
Field Status : current
Description : status_403
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.28

Field Name : portOperHttpVportCpuListStatus402
Field Type : CounterBasedGauge64
Field Status : current
Description : status_402
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.27

Field Name : portOperHttpVportCpuListStatus401
Field Type : CounterBasedGauge64
Field Status : current
Description : status_401
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.26

Field Name : portOperHttpVportCpuListStatus400
Field Type : CounterBasedGauge64
Field Status : current
Description : status_400
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.25

Field Name : portOperHttpVportCpuListStatus307
Field Type : CounterBasedGauge64
Field Status : current
Description : status_307
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.24

Field Name : portOperHttpVportCpuListStatus306
Field Type : CounterBasedGauge64
Field Status : current
Description : status_306
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.23

Field Name : portOperHttpVportCpuListStatus305
Field Type : CounterBasedGauge64
Field Status : current
Description : status_305
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.22

Field Name : portOperHttpVportCpuListStatus304
Field Type : CounterBasedGauge64

Field Status : current
Description : status_304
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.21

Field Name : portOperHttpVportCpuListStatus303
Field Type : CounterBasedGauge64
Field Status : current
Description : status_303
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.20

Field Name : portOperHttpVportCpuListStatus302
Field Type : CounterBasedGauge64
Field Status : current
Description : status_302
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.19

Field Name : portOperHttpVportCpuListStatus301
Field Type : CounterBasedGauge64
Field Status : current
Description : status_301
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.18

Field Name : portOperHttpVportCpuListStatus300
Field Type : CounterBasedGauge64
Field Status : current
Description : status_300
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.17

Field Name : portOperHttpVportCpuListStatus103
Field Type : CounterBasedGauge64
Field Status : current
Description : status_103
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.214

Field Name : portOperHttpVportCpuListStatus102
Field Type : CounterBasedGauge64
Field Status : current
Description : status_102
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.16

Field Name : portOperHttpVportCpuListStatus101
Field Type : CounterBasedGauge64
Field Status : current
Description : status_101
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.15

Field Name : portOperHttpVportCpuListStatus100
Field Type : CounterBasedGauge64
Field Status : current
Description : status_100
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.14

Field Name : portOperHttpVportCpuListStatus207
Field Type : CounterBasedGauge64
Field Status : current
Description : status_207
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.13

Field Name : portOperHttpVportCpuListStatus206
Field Type : CounterBasedGauge64
Field Status : current
Description : status_206
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.12

Field Name : portOperHttpVportCpuListStatus205
Field Type : CounterBasedGauge64
Field Status : current
Description : status_205
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.11

Field Name : portOperHttpVportCpuListStatus204
Field Type : CounterBasedGauge64
Field Status : current
Description : status_204
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.10

Field Name : portOperHttpVportCpuListStatus203
Field Type : CounterBasedGauge64
Field Status : current
Description : status_203
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.9

Field Name : portOperHttpVportCpuListStatus202
Field Type : CounterBasedGauge64
Field Status : current
Description : status_202
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.8

Field Name : portOperHttpVportCpuListStatus201
Field Type : CounterBasedGauge64
Field Status : current
Description : status_201
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.7

Field Name : portOperHttpVportCpuListStatus200
Field Type : CounterBasedGauge64
Field Status : current
Description : status_200
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.6

Field Name : portOperHttpVportCpuListHttpVportCpuListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.5

Field Name : portOperHttpVportCpuListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.4

Field Name : portOperHttpVportCpuListPort
Field Type : Integer32
Field Status : current
Description : port-number

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.3

Field Name : portOperHttpVportCpuListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.2

Field Name : portOperHttpVportCpuListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.1

Field Name : l7sessionStatsTable
Field Type : TABLE
Field Status : current
Description : Configure l7session from object 'slb.l7session'
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1

Field Name : l7sessionStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The l7sessionStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1

Field Name : l7sessionStatsInvalidServer
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid_server
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.48

Field Name : l7sessionStatsClientNotCleaned
Field Type : CounterBasedGauge64
Field Status : current
Description : client_not_cleaned
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.47

Field Name : l7sessionStatsServerNotCleaned
Field Type : CounterBasedGauge64
Field Status : current
Description : server_not_cleaned
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.46

Field Name : l7sessionStatsOldServerCleaned
Field Type : CounterBasedGauge64
Field Status : current
Description : old_server_cleaned
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.45

Field Name : l7sessionStatsTransactionCleaned
Field Type : CounterBasedGauge64
Field Status : current
Description : transaction_cleaned
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.44

Field Name : l7sessionStatsUdpDataEvent
Field Type : CounterBasedGauge64

Field Status : current
Description : udp_data_event
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.43

Field Name : l7sessionStatsHpsFwdreqFailTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : hps_fwdreq_fail_tuple
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.42

Field Name : l7sessionStatsHpsFwdreqFailServer
Field Type : CounterBasedGauge64
Field Status : current
Description : hps_fwdreq_fail_server
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.41

Field Name : l7sessionStatsHpsFwdreqFailPersist
Field Type : CounterBasedGauge64
Field Status : current
Description : hps_fwdreq_fail_persist
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.40

Field Name : l7sessionStatsHpsFwdreqFailRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : hps_fwdreq_fail_route
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.39

Field Name : l7sessionStatsHpsFwdreqFailRport
Field Type : CounterBasedGauge64
Field Status : current
Description : hps_fwdreq_fail_rport
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.38

Field Name : l7sessionStatsHpsFwdreqFailBuff
Field Type : CounterBasedGauge64
Field Status : current
Description : hps_fwdreq_fail_buff
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.37

Field Name : l7sessionStatsHpsFwdreqFail
Field Type : CounterBasedGauge64
Field Status : current
Description : hps_fwdreq_fail
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.36

Field Name : l7sessionStatsDataCbFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : data_cb_failed
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.35

Field Name : l7sessionStatsEstCbFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : est_cb_failed
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.34

Field Name : l7sessionStatsEstEvent
Field Type : CounterBasedGauge64
Field Status : current
Description : est_event
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.33

Field Name : l7sessionStatsServerSelectFail
Field Type : CounterBasedGauge64
Field Status : current
Description : server_select_fail
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.32

Field Name : l7sessionStatsTotalProxyEs
Field Type : CounterBasedGauge64
Field Status : current
Description : total_proxy_es
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.31

Field Name : l7sessionStatsTotalProxyServer
Field Type : CounterBasedGauge64
Field Status : current
Description : total_proxy_server
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.30

Field Name : l7sessionStatsTotalProxyClient
Field Type : CounterBasedGauge64
Field Status : current
Description : total_proxy_client
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.29

Field Name : l7sessionStatsTotalProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : total_proxy
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.28

Field Name : l7sessionStatsCurrProxyEs
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_proxy_es
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.27

Field Name : l7sessionStatsCurrProxyServer
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_proxy_server
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.26

Field Name : l7sessionStatsCurrProxyClient
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_proxy_client
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.25

Field Name : l7sessionStatsCurrProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_proxy

OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.24

Field Name : l7sessionStatsProxyV2Connection
Field Type : CounterBasedGauge64
Field Status : current
Description : proxy_v2_connection
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.23

Field Name : l7sessionStatsProxyV1Connection
Field Type : CounterBasedGauge64
Field Status : current
Description : proxy_v1_connection
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.22

Field Name : l7sessionStatsServerRstRsp
Field Type : CounterBasedGauge64
Field Status : current
Description : server_rst_rsp
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.21

Field Name : l7sessionStatsServerRstConnected
Field Type : CounterBasedGauge64
Field Status : current
Description : server_rst_connected
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.20

Field Name : l7sessionStatsServerRstConnecting
Field Type : CounterBasedGauge64
Field Status : current
Description : server_rst_connecting
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.19

Field Name : l7sessionStatsServerRstReq
Field Type : CounterBasedGauge64
Field Status : current
Description : server_rst_req
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.18

Field Name : l7sessionStatsClientRstRsp
Field Type : CounterBasedGauge64
Field Status : current
Description : client_rst_rsp
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.17

Field Name : l7sessionStatsClientRstConnected
Field Type : CounterBasedGauge64
Field Status : current
Description : client_rst_connected
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.16

Field Name : l7sessionStatsClientRstConnecting
Field Type : CounterBasedGauge64
Field Status : current
Description : client_rst_connecting
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.15

Field Name : l7sessionStatsClientRstReq
Field Type : CounterBasedGauge64

Field Status : current
Description : client_rst_req
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.14

Field Name : l7sessionStatsServerRst
Field Type : CounterBasedGauge64
Field Status : current
Description : server_rst
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.13

Field Name : l7sessionStatsClientRst
Field Type : CounterBasedGauge64
Field Status : current
Description : client_rst
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.12

Field Name : l7sessionStatsServerConnFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : server_conn_failed
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.11

Field Name : l7sessionStatsErrCbFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : err_cb_failed
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.10

Field Name : l7sessionStatsErrEvent
Field Type : CounterBasedGauge64
Field Status : current
Description : err_event
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.9

Field Name : l7sessionStatsWbufCbFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : wbuf_cb_failed
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.8

Field Name : l7sessionStatsWbufEvent
Field Type : CounterBasedGauge64
Field Status : current
Description : wbuf_event
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.7

Field Name : l7sessionStatsServerFin
Field Type : CounterBasedGauge64
Field Status : current
Description : server_fin
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.6

Field Name : l7sessionStatsClientFin
Field Type : CounterBasedGauge64
Field Status : current
Description : client_fin
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.5

Field Name : l7sessionStatsDataEvent
Field Type : CounterBasedGauge64
Field Status : current
Description : data_event
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.4

Field Name : l7sessionStatsConnNotExist
Field Type : CounterBasedGauge64
Field Status : current
Description : conn_not_exist
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.3

Field Name : l7sessionStatsStartServerConnSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : start_server_conn_succ
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.2

Field Name : l7sessionStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.1

Field Name : dnsStatsTable
Field Type : TABLE
Field Status : current
Description : DNS Packet Statistics from object 'slb.dns'
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1

Field Name : dnsStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1

Field Name : dnsStatsSlbDnsEdnsEcsInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_dns_edns_ecs_inserted
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.37

Field Name : dnsStatsSlbDnsEdnsEcsReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_dns_edns_ecs_received
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.36

Field Name : dnsStatsInvalidQLenToUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid_q_len_to_udp
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.35

Field Name : dnsStatsNatSlbDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : nat_slb_drop

OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.34

Field Name : dnsStatsSlbDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_drop
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.33

Field Name : dnsStatsRpzActionLocalData
Field Type : CounterBasedGauge64
Field Status : current
Description : rpz_action_local_data
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.32

Field Name : dnsStatsRpzActionNodata
Field Type : CounterBasedGauge64
Field Status : current
Description : rpz_action_nodata
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.31

Field Name : dnsStatsRpzActionNxdomain
Field Type : CounterBasedGauge64
Field Status : current
Description : rpz_action_nxdomain
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.30

Field Name : dnsStatsRpzActionTcpOnly
Field Type : CounterBasedGauge64
Field Status : current
Description : rpz_action_tcp_only
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.29

Field Name : dnsStatsRpzActionPassThru
Field Type : CounterBasedGauge64
Field Status : current
Description : rpz_action_pass_thru
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.28

Field Name : dnsStatsRpzActionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : rpz_action_drop
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.27

Field Name : dnsStatsSlbDnsUdpRetransmitFail
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_dns_udp_retransmit_fail
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.26

Field Name : dnsStatsSlbDnsUdpRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_dns_udp_retransmit
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.25

Field Name : dnsStatsSlbDnsEdnsSubnetToServerRemoved
Field Type : CounterBasedGauge64

Field Status : current
Description : slb_dns_edns_subnet_to_server_removed
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.24

Field Name : dnsStatsSlbDnsPaddingToClientAdded
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_dns_padding_to_client_added
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.23

Field Name : dnsStatsSlbDnsPaddingToServerRemoved
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_dns_padding_to_server_removed
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.22

Field Name : dnsStatsSlbDnsUdpConnSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_dns_udp_conn_succ
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.21

Field Name : dnsStatsSlbDnsUdpConn
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_dns_udp_conn
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.20

Field Name : dnsStatsSlbDnsServerSslSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_dns_server_ssl_succ
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.19

Field Name : dnsStatsSlbDnsClientSslSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_dns_client_ssl_succ
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.18

Field Name : dnsStatsFilterTypeAnyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : filter_type_any_drop
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.17

Field Name : dnsStatsFilterClassDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : filter_class_drop
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.16

Field Name : dnsStatsFilterTypeDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : filter_type_drop
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.15

Field Name : dnsStatsNatXidReused
Field Type : CounterBasedGauge64
Field Status : current
Description : nat_xid_reused
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.14

Field Name : dnsStatsNatNoResource
Field Type : CounterBasedGauge64
Field Status : current
Description : nat_no_resource
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.13

Field Name : dnsStatsNatRespNoMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : nat_resp_no_match
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.12

Field Name : dnsStatsNatReqRexmit
Field Type : CounterBasedGauge64
Field Status : current
Description : nat_req_rexmit
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.11

Field Name : dnsStatsNatNoResp
Field Type : CounterBasedGauge64
Field Status : current
Description : nat_no_resp
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.10

Field Name : dnsStatsNatResp
Field Type : CounterBasedGauge64
Field Status : current
Description : nat_resp
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.9

Field Name : dnsStatsNatReq
Field Type : CounterBasedGauge64
Field Status : current
Description : nat_req
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.8

Field Name : dnsStatsSlbNoResource
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_no_resource
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.7

Field Name : dnsStatsSlbRespNoMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_resp_no_match
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.6

Field Name : dnsStatsSlbReqRexmit
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_req_rexmit

OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.5

Field Name : dnsStatsSlbNoResp
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_no_resp
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.4

Field Name : dnsStatsSlbResp
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_resp
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.3

Field Name : dnsStatsSlbReq
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_req
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.2

Field Name : dnsStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.1

Field Name : dnsCacheOperCacheEntryEntryRecordTable
Field Type : TABLE
Field Status : current
Description : DNS Cache Statistics from object 'slb.dns-cache'
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.5

Field Name : dnsCacheOperCacheEntryTable
Field Type : TABLE
Field Status : current
Description : DNS Cache Statistics from object 'slb.dns-cache'
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4

Field Name : dnsCacheOperCacheEntryEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsCacheOperCacheEntry entry:cache-entry
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1

Field Name : dnsCacheOperCacheEntryArCount
Field Type : CounterBasedGauge64
Field Status : current
Description : ar_count
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.17

Field Name : dnsCacheOperCacheEntryNsCount
Field Type : CounterBasedGauge64
Field Status : current
Description : ns_count
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.16

Field Name : dnsCacheOperCacheEntryAnCount
Field Type : CounterBasedGauge64

Field Status : current
Description : an_count
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.15

Field Name : dnsCacheOperCacheEntryHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.14

Field Name : dnsCacheOperCacheEntryWeight
Field Type : CounterBasedGauge64
Field Status : current
Description : weight
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.13

Field Name : dnsCacheOperCacheEntryAge
Field Type : CounterBasedGauge64
Field Status : current
Description : age
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.12

Field Name : dnsCacheOperCacheEntryTtl
Field Type : CounterBasedGauge64
Field Status : current
Description : ttl
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.11

Field Name : dnsCacheOperCacheEntryRLength
Field Type : CounterBasedGauge64
Field Status : current
Description : r_length
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.10

Field Name : dnsCacheOperCacheEntryQLength
Field Type : CounterBasedGauge64
Field Status : current
Description : q_length
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.9

Field Name : dnsCacheOperCacheEntryCacheClass
Field Type : CounterBasedGauge64
Field Status : current
Description : cache_class
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.8

Field Name : dnsCacheOperCacheEntryCacheType
Field Type : CounterBasedGauge64
Field Status : current
Description : cache_type
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.7

Field Name : dnsCacheOperCacheEntryCacheNegative
Field Type : CounterBasedGauge64
Field Status : current
Description : cache_negative
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.6

Field Name : dnsCacheOperCacheEntryDnssec
Field Type : CounterBasedGauge64
Field Status : current
Description : dnssec
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.5

Field Name : dnsCacheOperCacheEntryDomain
Field Type : String
Field Status : current
Description : domain
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.4

Field Name : dnsCacheOperCacheEntryName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.3

Field Name : dnsCacheOperCacheEntryCacheEntryListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.2

Field Name : dnsCacheOperCacheEntrySlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.1

Field Name : dnsCacheOperCacheClientTable
Field Type : TABLE
Field Status : current
Description : DNS Cache Statistics from object 'slb.dns-cache'
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.3

Field Name : dnsCacheOperCacheClientEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsCacheOperCacheClient entry:cache-client
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.3.1

Field Name : dnsCacheOperCacheClientLockupTime
Field Type : CounterBasedGauge64
Field Status : current
Description : lockup_time
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.3.1.9

Field Name : dnsCacheOperCacheClientLockup
Field Type : CounterBasedGauge64
Field Status : current
Description : lockup
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.3.1.8

Field Name : dnsCacheOperCacheClientOverRateLimitTimes
Field Type : CounterBasedGauge64
Field Status : current
Description : over_rate_limit_times

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.3.1.7

Field Name : dnsCacheOperCacheClientCurrRate
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_rate
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.3.1.6

Field Name : dnsCacheOperCacheClientUnitType
Field Type : String
Field Status : current
Description : unit_type
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.3.1.5

Field Name : dnsCacheOperCacheClientAddress
Field Type : String
Field Status : current
Description : address
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.3.1.4

Field Name : dnsCacheOperCacheClientDomain
Field Type : String
Field Status : current
Description : domain
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.3.1.3

Field Name : dnsCacheOperCacheClientCacheClientListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.3.1.2

Field Name : dnsCacheOperCacheClientSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.3.1.1

Field Name : dnsCacheOperTable
Field Type : TABLE
Field Status : current
Description : DNS Cache Statistics from object 'slb.dns-cache'
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2

Field Name : dnsCacheOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsCacheOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1

Field Name : dnsCacheOperRecordAll
Field Type : Integer32
Field Status : current
Description : record-all
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.23

Field Name : dnsCacheOperRecordNumValue
Field Type : CounterBasedGauge64

Field Status : current
Description : record-num-value
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.22

Field Name : dnsCacheOperRdataAll
Field Type : Integer32
Field Status : current
Description : rdata-all
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.21

Field Name : dnsCacheOperRdataSizeValue
Field Type : CounterBasedGauge64
Field Status : current
Description : rdata-size-value
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.20

Field Name : dnsCacheOperContentMode
Field Type : String
Field Status : current
Description : content-mode
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.19

Field Name : dnsCacheOperDomainName
Field Type : String
Field Status : current
Description : domain-name
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.18

Field Name : dnsCacheOperTypeString
Field Type : String
Field Status : current
Description : type-string
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.17

Field Name : dnsCacheOperClassValue
Field Type : CounterBasedGauge64
Field Status : current
Description : class-value
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.16

Field Name : dnsCacheOperClassString
Field Type : String
Field Status : current
Description : class-string
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.15

Field Name : dnsCacheOperFqdnDomain
Field Type : String
Field Status : current
Description : fqdn-domain
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.14

Field Name : dnsCacheOperTypeValue
Field Type : CounterBasedGauge64
Field Status : current
Description : type-value
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.13

Field Name : dnsCacheOperPortNum
Field Type : CounterBasedGauge64
Field Status : current
Description : port-num
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.12

Field Name : dnsCacheOperPortType
Field Type : String
Field Status : current
Description : port-type
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.11

Field Name : dnsCacheOperVsName
Field Type : String
Field Status : current
Description : vs-name
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.10

Field Name : dnsCacheOperVport
Field Type : Integer32
Field Status : current
Description : vport
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.9

Field Name : dnsCacheOperCacheContent
Field Type : Integer32
Field Status : current
Description : cache-content
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.8

Field Name : dnsCacheOperGlobal
Field Type : Integer32
Field Status : current
Description : global
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.7

Field Name : dnsCacheOperEntry1
Field Type : Integer32
Field Status : current
Description : entry
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.6

Field Name : dnsCacheOperClient
Field Type : Integer32
Field Status : current
Description : client
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.5

Field Name : dnsCacheOperHitRatioPercentagePerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : hit_ratio_percentage_per_sec
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.24

Field Name : dnsCacheOperCacheHitRatio
Field Type : String
Field Status : current
Description : cache_hit_ratio

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.4

Field Name : dnsCacheOperCacheUsage
Field Type : String
Field Status : current
Description : cache_usage
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.3

Field Name : dnsCacheOperTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : total
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.2

Field Name : dnsCacheOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.1

Field Name : dnsCacheStatsTable
Field Type : TABLE
Field Status : current
Description : DNS Cache Statistics from object 'slb.dns-cache'
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1

Field Name : dnsCacheStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsCacheStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1

Field Name : dnsCacheStatsHitRatePerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : hit_rate_per_sec
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.26

Field Name : dnsCacheStatsQps
Field Type : CounterBasedGauge64
Field Status : current
Description : qps
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.25

Field Name : dnsCacheStatsTruncatedR
Field Type : CounterBasedGauge64
Field Status : current
Description : truncated_r
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.24

Field Name : dnsCacheStatsResolverQueueFull
Field Type : CounterBasedGauge64
Field Status : current
Description : resolver_queue_full
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.23

Field Name : dnsCacheStatsCurrentDataAllocate
Field Type : CounterBasedGauge64

Field Status : current
Description : current_data_allocate
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.22

Field Name : dnsCacheStatsCurrentAllocate
Field Type : CounterBasedGauge64
Field Status : current
Description : current_allocate
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.21

Field Name : dnsCacheStatsTotalFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : total_freed
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.20

Field Name : dnsCacheStatsTotalAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : total_alloc
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.19

Field Name : dnsCacheStatsTotalLog
Field Type : CounterBasedGauge64
Field Status : current
Description : total_log
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.18

Field Name : dnsCacheStatsAgeoutWeight
Field Type : CounterBasedGauge64
Field Status : current
Description : ageout_weight
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.17

Field Name : dnsCacheStatsBadAnswer
Field Type : CounterBasedGauge64
Field Status : current
Description : bad_answer
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.16

Field Name : dnsCacheStatsAgeout
Field Type : CounterBasedGauge64
Field Status : current
Description : ageout
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.15

Field Name : dnsCacheStatsTtlR
Field Type : CounterBasedGauge64
Field Status : current
Description : ttl_r
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.14

Field Name : dnsCacheStatsAnswerR
Field Type : CounterBasedGauge64
Field Status : current
Description : answer_r
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.13

Field Name : dnsCacheStatsMultipleR
Field Type : CounterBasedGauge64
Field Status : current
Description : multiple_r
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.12

Field Name : dnsCacheStatsEncodeR
Field Type : CounterBasedGauge64
Field Status : current
Description : encode_r
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.11

Field Name : dnsCacheStatsOversizeR
Field Type : CounterBasedGauge64
Field Status : current
Description : oversize_r
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.10

Field Name : dnsCacheStatsBadR
Field Type : CounterBasedGauge64
Field Status : current
Description : bad_r
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.9

Field Name : dnsCacheStatsOversizeQ
Field Type : CounterBasedGauge64
Field Status : current
Description : oversize_q
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.8

Field Name : dnsCacheStatsMultipleQ
Field Type : CounterBasedGauge64
Field Status : current
Description : multiple_q
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.7

Field Name : dnsCacheStatsEncodeQ
Field Type : CounterBasedGauge64
Field Status : current
Description : encode_q
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.6

Field Name : dnsCacheStatsBadQ
Field Type : CounterBasedGauge64
Field Status : current
Description : bad_q
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.5

Field Name : dnsCacheStatsHit
Field Type : CounterBasedGauge64
Field Status : current
Description : hit
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.4

Field Name : dnsCacheStatsTotalR
Field Type : CounterBasedGauge64
Field Status : current
Description : total_r

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.3

Field Name : dnsCacheStatsTotalQ
Field Type : CounterBasedGauge64
Field Status : current
Description : total_q
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.2

Field Name : dnsCacheStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.1

Field Name : dnsCacheOperCacheEntryEntryRecordEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsCacheOperCacheEntryEntryRecord entry:entry-record
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.5.1

Field Name : dnsCacheOperCacheEntryEntryRecordRecordRdataTc
Field Type : CounterBasedGauge64
Field Status : current
Description : record_rdata_tc
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.5.1.9

Field Name : dnsCacheOperCacheEntryEntryRecordRecordRdata
Field Type : String
Field Status : current
Description : record_rdata
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.5.1.8

Field Name : dnsCacheOperCacheEntryEntryRecordRecordRdlen
Field Type : CounterBasedGauge64
Field Status : current
Description : record_rdlen
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.5.1.7

Field Name : dnsCacheOperCacheEntryEntryRecordRecordTtl
Field Type : CounterBasedGauge64
Field Status : current
Description : record_ttl
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.5.1.6

Field Name : dnsCacheOperCacheEntryEntryRecordRecordClass
Field Type : CounterBasedGauge64
Field Status : current
Description : record_class
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.5.1.5

Field Name : dnsCacheOperCacheEntryEntryRecordRecordType
Field Type : CounterBasedGauge64
Field Status : current
Description : record_type
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.5.1.4

Field Name : dnsCacheOperCacheEntryEntryRecordEntryRecordListId
Field Type : Integer32

Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.5.1.3

Field Name : dnsCacheOperCacheEntryEntryRecordCacheEntryListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.5.1.2

Field Name : dnsCacheOperCacheEntryEntryRecordSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.5.1.1

Field Name : httpProxyOperHttpProxyCpuListTable
Field Type : TABLE
Field Status : current
Description : Configure HTTP Proxy global from object 'slb.http-proxy'
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3

Field Name : httpProxyOperTable
Field Type : TABLE
Field Status : current
Description : Configure HTTP Proxy global from object 'slb.http-proxy'
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.2

Field Name : httpProxyOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The httpProxyOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.2.1

Field Name : httpProxyOperDebugFields
Field Type : Integer32
Field Status : current
Description : debug_fields
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.2.1.3

Field Name : httpProxyOperCpuCount
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-count
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.2.1.2

Field Name : httpProxyOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.2.1.1

Field Name : httpProxyStatsTable
Field Type : TABLE
Field Status : current
Description : Configure HTTP Proxy global from object 'slb.http-proxy'
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1

Field Name : httpProxyStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The httpProxyStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1

Field Name : httpProxyStatsTransactionLimited
Field Type : CounterBasedGauge64
Field Status : current
Description : transaction_limited
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.342

Field Name : httpProxyStatsReqHttp11NewProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : req_http11_new_proxy
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.341

Field Name : httpProxyStatsDelH2cHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : del_h2c_header
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.340

Field Name : httpProxyStatsUpgradeToNewProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : upgrade_to_new_proxy
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.339

Field Name : httpProxyStatsHttpAllowedMethods
Field Type : CounterBasedGauge64
Field Status : current
Description : http_allowed_methods
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.338

Field Name : httpProxyStatsHttpDisallowedMethods
Field Type : CounterBasedGauge64
Field Status : current
Description : http_disallowed_methods
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.337

Field Name : httpProxyStatsHttp2ClientIdleTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : http2_client_idle_timeout
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.336

Field Name : httpProxyStatsHttp1ClientIdleTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : http1_client_idle_timeout
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.335

Field Name : httpProxyStatsHeaderFilterRuleHit
Field Type : CounterBasedGauge64
Field Status : current
Description : header_filter_rule_hit

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.334

Field Name : httpProxyStatsResponseHttp3
Field Type : CounterBasedGauge64
Field Status : current
Description : response_http3
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.333

Field Name : httpProxyStatsReqHttp3
Field Type : CounterBasedGauge64
Field Status : current
Description : req_http3
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.332

Field Name : httpProxyStatsH2upWithHostAndAuth
Field Type : CounterBasedGauge64
Field Status : current
Description : h2up_with_host_and_auth
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.331

Field Name : httpProxyStatsGetAndPayload
Field Type : CounterBasedGauge64
Field Status : current
Description : get_and_payload
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.330

Field Name : httpProxyStatsTransferEncodingAndContentLength
Field Type : CounterBasedGauge64
Field Status : current
Description : transfer_encoding_and_content_length
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.329

Field Name : httpProxyStatsMultipleTransferEncoding
Field Type : CounterBasedGauge64
Field Status : current
Description : multiple_transfer_encoding
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.328

Field Name : httpProxyStatsMultipleContentLength
Field Type : CounterBasedGauge64
Field Status : current
Description : multiple_content_length
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.327

Field Name : httpProxyStatsH2upWithTransferEncoding
Field Type : CounterBasedGauge64
Field Status : current
Description : h2up_with_transfer_encoding
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.326

Field Name : httpProxyStatsMalformedH2upSchemeValue
Field Type : CounterBasedGauge64
Field Status : current
Description : malformed_h2up_scheme_value
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.325

Field Name : httpProxyStatsMalformedH2upHeaderValue
Field Type : CounterBasedGauge64

Field Status : current
Description : malformed_h2up_header_value
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.324

Field Name : httpProxyStatsH2upContentLengthAlias
Field Type : CounterBasedGauge64
Field Status : current
Description : h2up_content_length_alias
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.323

Field Name : httpProxyStatsCompressRspTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : compress_rsp_total
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.322

Field Name : httpProxyStatsCompressRspBr
Field Type : CounterBasedGauge64
Field Status : current
Description : compress_rsp_br
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.321

Field Name : httpProxyStatsDecompressionAfterTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : decompression_after_total
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.320

Field Name : httpProxyStatsDecompressionBeforeTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : decompression_before_total
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.319

Field Name : httpProxyStatsDecompressionAfterBr
Field Type : CounterBasedGauge64
Field Status : current
Description : decompression_after_br
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.318

Field Name : httpProxyStatsDecompressionBeforeBr
Field Type : CounterBasedGauge64
Field Status : current
Description : decompression_before_br
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.317

Field Name : httpProxyStatsCompressionAfterTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_after_total
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.316

Field Name : httpProxyStatsCompressionBeforeTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_before_total
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.315

Field Name : httpProxyStatsCompressionAfterBr
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_after_br
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.314

Field Name : httpProxyStatsCompressionBeforeBr
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_before_br
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.313

Field Name : httpProxyStatsDohDnsRespRcodeOther
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_other
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.312

Field Name : httpProxyStatsDohDnsRespRcodeNotzone
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_notzone
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.311

Field Name : httpProxyStatsDohDnsRespRcodeNotauth
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_notauth
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.310

Field Name : httpProxyStatsDohDnsRespRcodeNxrrset
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_nxrrset
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.309

Field Name : httpProxyStatsDohDnsRespRcodeYxrrset
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_yxrrset
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.308

Field Name : httpProxyStatsDohDnsRespRcodeYxdomain
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_yxdomain
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.307

Field Name : httpProxyStatsDohDnsRespRcodeRefuse
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_refuse
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.306

Field Name : httpProxyStatsDohDnsRespRcodeErrType
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_err_type

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.305

Field Name : httpProxyStatsDohDnsRespRcodeErrName
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_err_name
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.304

Field Name : httpProxyStatsDohDnsRespRcodeErrServer
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_err_server
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.303

Field Name : httpProxyStatsDohDnsRespRcodeErrFormat
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_err_format
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.302

Field Name : httpProxyStatsDohDnsMalformedQuery
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_malformed_query
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.301

Field Name : httpProxyStatsDohPostPayloadTooLarge
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_post_payload_too_large
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.300

Field Name : httpProxyStatsDohGetUriTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_get_uri_too_long
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.299

Field Name : httpProxyStatsDohRetryWTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_retry_w_tcp
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.298

Field Name : httpProxyStatsDohServSelFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_serv_sel_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.297

Field Name : httpProxyStatsDohRespTcpFrags
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_resp_tcp_frags
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.296

Field Name : httpProxyStatsDohRespUdpFrags
Field Type : CounterBasedGauge64

Field Status : current
Description : doh_resp_udp_frags
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.295

Field Name : httpProxyStatsDohRespQueFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_resp_que_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.294

Field Name : httpProxyStatsDohRespHeaderAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_resp_header_alloc_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.293

Field Name : httpProxyStatsDohRespSetupFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_resp_setup_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.292

Field Name : httpProxyStatsDohDnsQueryTypeOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_others
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.291

Field Name : httpProxyStatsDohDnsQueryTypeSoa
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_soa
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.290

Field Name : httpProxyStatsDohDnsQueryTypeMx
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_mx
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.289

Field Name : httpProxyStatsDohDnsQueryTypeSrv
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_srv
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.288

Field Name : httpProxyStatsDohDnsQueryTypeAny
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_any
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.287

Field Name : httpProxyStatsDohDnsQueryTypeCname
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_cname
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.286

Field Name : httpProxyStatsDohDnsQueryTypeNs
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_ns
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.285

Field Name : httpProxyStatsDohDnsQueryTypeAaaa
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_aaaa
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.284

Field Name : httpProxyStatsDohDnsQueryTypeA
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_a
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.283

Field Name : httpProxyStatsDohQueryTimeOut
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_query_time_out
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.282

Field Name : httpProxyStatsDohUdpSendFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_udp_send_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.281

Field Name : httpProxyStatsDohTcpSendFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_tcp_send_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.280

Field Name : httpProxyStatsDohNonDohMethod
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_non_doh_method
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.279

Field Name : httpProxyStatsDohPostPayloadExtractFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_post_payload_extract_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.278

Field Name : httpProxyStatsDohPostPayloadNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_post_payload_not_found
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.277

Field Name : httpProxyStatsDohPostContentTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_post_content_type_mismatch

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.276

Field Name : httpProxyStatsDohGetBase64DecodeFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_get_base64_decode_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.275

Field Name : httpProxyStatsDohGetDnsArgFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_get_dns_arg_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.274

Field Name : httpProxyStatsDohPathNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_path_not_found
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.273

Field Name : httpProxyStatsDohSnatFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_snat_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.272

Field Name : httpProxyStatsDohReqTcpRetryFail
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_tcp_retry_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.271

Field Name : httpProxyStatsDohReqTcpRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_tcp_retry
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.270

Field Name : httpProxyStatsDohReqUdpRetryFail
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_udp_retry_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.269

Field Name : httpProxyStatsDohReqUdpRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_udp_retry
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.268

Field Name : httpProxyStatsDohMallocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_malloc_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.267

Field Name : httpProxyStatsDohRespSendFailed
Field Type : CounterBasedGauge64

Field Status : current
Description : doh_resp_send_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.266

Field Name : httpProxyStatsDohReqSendFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_send_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.265

Field Name : httpProxyStatsDohTcpDnsResp
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_tcp_dns_resp
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.264

Field Name : httpProxyStatsDohTcpDnsReq
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_tcp_dns_req
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.263

Field Name : httpProxyStatsDohUdpDnsResp
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_udp_dns_resp
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.262

Field Name : httpProxyStatsDohUdpDnsReq
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_udp_dns_req
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.261

Field Name : httpProxyStatsDohTcResp
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_tc_resp
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.260

Field Name : httpProxyStatsDohResp
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_resp
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.259

Field Name : httpProxyStatsDohNonDohReqPost
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_non_doh_req_post
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.258

Field Name : httpProxyStatsDohNonDohReqGet
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_non_doh_req_get
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.257

Field Name : httpProxyStatsDohNonDohReq
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_non_doh_req
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.256

Field Name : httpProxyStatsDohReqPost
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_post
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.255

Field Name : httpProxyStatsDohReqGet
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_get
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.254

Field Name : httpProxyStatsDohReq
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.253

Field Name : httpProxyStatsReqTimeoutClose
Field Type : CounterBasedGauge64
Field Status : current
Description : req_timeout_close
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.252

Field Name : httpProxyStatsReqTimeoutRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : req_timeout_retry
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.251

Field Name : httpProxyStatsResponseHttp2
Field Type : CounterBasedGauge64
Field Status : current
Description : response_http2
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.250

Field Name : httpProxyStatsReqHttp2
Field Type : CounterBasedGauge64
Field Status : current
Description : req_http2
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.249

Field Name : httpProxyStatsDecompressionAfter
Field Type : CounterBasedGauge64
Field Status : current
Description : decompression_after
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.248

Field Name : httpProxyStatsDecompressionBefore
Field Type : CounterBasedGauge64
Field Status : current
Description : decompression_before

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.247

Field Name : httpProxyStatsNonHttpBypass
Field Type : CounterBasedGauge64
Field Status : current
Description : non_http_bypass
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.246

Field Name : httpProxyStatsReqEnterSsli
Field Type : CounterBasedGauge64
Field Status : current
Description : req_enter_ssli
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.245

Field Name : httpProxyStatsConnectReq
Field Type : CounterBasedGauge64
Field Status : current
Description : connect_req
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.244

Field Name : httpProxyStatsReqTrack
Field Type : CounterBasedGauge64
Field Status : current
Description : req_track
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.243

Field Name : httpProxyStatsInsertClientPort
Field Type : CounterBasedGauge64
Field Status : current
Description : insert_client_port
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.242

Field Name : httpProxyStatsReqOver5s
Field Type : CounterBasedGauge64
Field Status : current
Description : req_over_5s
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.241

Field Name : httpProxyStatsReq5s
Field Type : CounterBasedGauge64
Field Status : current
Description : req_5s
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.240

Field Name : httpProxyStatsReq2s
Field Type : CounterBasedGauge64
Field Status : current
Description : req_2s
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.239

Field Name : httpProxyStatsReq1s
Field Type : CounterBasedGauge64
Field Status : current
Description : req_1s
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.238

Field Name : httpProxyStatsReq500m
Field Type : CounterBasedGauge64

Field Status : current
Description : req_500m
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.237

Field Name : httpProxyStatsReq200m
Field Type : CounterBasedGauge64
Field Status : current
Description : req_200m
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.236

Field Name : httpProxyStatsReq100m
Field Type : CounterBasedGauge64
Field Status : current
Description : req_100m
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.235

Field Name : httpProxyStatsReq50m
Field Type : CounterBasedGauge64
Field Status : current
Description : req_50m
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.234

Field Name : httpProxyStatsReq20m
Field Type : CounterBasedGauge64
Field Status : current
Description : req_20m
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.233

Field Name : httpProxyStatsReq10m
Field Type : CounterBasedGauge64
Field Status : current
Description : req_10m
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.232

Field Name : httpProxyStatsReq5m
Field Type : CounterBasedGauge64
Field Status : current
Description : req_5m
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.231

Field Name : httpProxyStatsReq2m
Field Type : CounterBasedGauge64
Field Status : current
Description : req_2m
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.230

Field Name : httpProxyStatsReq1m
Field Type : CounterBasedGauge64
Field Status : current
Description : req_1m
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.229

Field Name : httpProxyStatsReq500u
Field Type : CounterBasedGauge64
Field Status : current
Description : req_500u
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.228

Field Name : httpProxyStatsReq200u
Field Type : CounterBasedGauge64
Field Status : current
Description : req_200u
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.227

Field Name : httpProxyStatsReq100u
Field Type : CounterBasedGauge64
Field Status : current
Description : req_100u
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.226

Field Name : httpProxyStatsReq50u
Field Type : CounterBasedGauge64
Field Status : current
Description : req_50u
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.225

Field Name : httpProxyStatsReq20u
Field Type : CounterBasedGauge64
Field Status : current
Description : req_20u
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.224

Field Name : httpProxyStatsReq10u
Field Type : CounterBasedGauge64
Field Status : current
Description : req_10u
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.223

Field Name : httpProxyStatsChunkBad
Field Type : CounterBasedGauge64
Field Status : current
Description : chunk_bad
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.222

Field Name : httpProxyStatsPconnConnectingFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : pconn_connecting_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.221

Field Name : httpProxyStatsPconnConnected
Field Type : CounterBasedGauge64
Field Status : current
Description : pconn_connected
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.220

Field Name : httpProxyStatsPconnConnecting
Field Type : CounterBasedGauge64
Field Status : current
Description : pconn_connecting
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.219

Field Name : httpProxyStatsChunkSzGt4k
Field Type : CounterBasedGauge64
Field Status : current
Description : chunk_sz_gt_4k

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.218

Field Name : httpProxyStatsChunkSz4k
Field Type : CounterBasedGauge64
Field Status : current
Description : chunk_sz_4k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.217

Field Name : httpProxyStatsChunkSz2k
Field Type : CounterBasedGauge64
Field Status : current
Description : chunk_sz_2k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.216

Field Name : httpProxyStatsChunkSz1k
Field Type : CounterBasedGauge64
Field Status : current
Description : chunk_sz_1k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.215

Field Name : httpProxyStatsChunkSz512
Field Type : CounterBasedGauge64
Field Status : current
Description : chunk_sz_512
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.214

Field Name : httpProxyStatsRspSzGt256k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_gt_256k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.213

Field Name : httpProxyStatsRspSz256k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_256k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.212

Field Name : httpProxyStatsRspSz64k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_64k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.211

Field Name : httpProxyStatsRspSz32k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_32k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.210

Field Name : httpProxyStatsRspSz16k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_16k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.209

Field Name : httpProxyStatsRspSz8k
Field Type : CounterBasedGauge64

Field Status : current
Description : rsp_sz_8k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.208

Field Name : httpProxyStatsRspSz4k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_4k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.207

Field Name : httpProxyStatsRspSz2k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_2k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.206

Field Name : httpProxyStatsRspSz1k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_1k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.205

Field Name : httpProxyStatsReqSzGt256k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_gt_256k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.204

Field Name : httpProxyStatsReqSz256k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_256k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.203

Field Name : httpProxyStatsReqSz64k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_64k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.202

Field Name : httpProxyStatsReqSz32k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_32k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.201

Field Name : httpProxyStatsReqSz16k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_16k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.200

Field Name : httpProxyStatsReqSz8k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_8k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.199

Field Name : httpProxyStatsReqSz4k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_4k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.198

Field Name : httpProxyStatsReqSz2k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_2k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.197

Field Name : httpProxyStatsReqSz1k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_1k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.196

Field Name : httpProxyStatsReqHttp10Keepalive
Field Type : CounterBasedGauge64
Field Status : current
Description : req_http10_keepalive
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.195

Field Name : httpProxyStatsCloseOnDdos
Field Type : CounterBasedGauge64
Field Status : current
Description : close_on_ddos
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.194

Field Name : httpProxyStatsCacheRsp
Field Type : CounterBasedGauge64
Field Status : current
Description : cache_rsp
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.193

Field Name : httpProxyStatsCompressRatioTooHigh
Field Type : CounterBasedGauge64
Field Status : current
Description : compress_ratio_too_high
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.192

Field Name : httpProxyStatsCompressRespNoClOrCe
Field Type : CounterBasedGauge64
Field Status : current
Description : compress_resp_no_cl_or_ce
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.191

Field Name : httpProxyStatsCompressRespLtMin
Field Type : CounterBasedGauge64
Field Status : current
Description : compress_resp_lt_min
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.190

Field Name : httpProxyStatsCompressNoContentType
Field Type : CounterBasedGauge64
Field Status : current
Description : compress_no_content_type

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.189

Field Name : httpProxyStatsCompressContentTypeExcluded
Field Type : CounterBasedGauge64
Field Status : current
Description : compress_content_type_excluded
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.188

Field Name : httpProxyStatsCompressRespAlreadyCompressed
Field Type : CounterBasedGauge64
Field Status : current
Description : compress_resp_already_compressed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.187

Field Name : httpProxyStatsCompressDelAcceptEnc
Field Type : CounterBasedGauge64
Field Status : current
Description : compress_del_accept_enc
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.186

Field Name : httpProxyStatsCompressRsp
Field Type : CounterBasedGauge64
Field Status : current
Description : compress_rsp
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.185

Field Name : httpProxyStatsReqChunk
Field Type : CounterBasedGauge64
Field Status : current
Description : req_chunk
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.184

Field Name : httpProxyStatsRspChunk
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_chunk
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.183

Field Name : httpProxyStatsRspContentLen
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_content_len
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.182

Field Name : httpProxyStatsReqContentLen
Field Type : CounterBasedGauge64
Field Status : current
Description : req_content_len
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.181

Field Name : httpProxyStatsReqUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : req_unknown
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.180

Field Name : httpProxyStatsReqDelete
Field Type : CounterBasedGauge64

Field Status : current
Description : req_delete
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.179

Field Name : httpProxyStatsReqConnect
Field Type : CounterBasedGauge64
Field Status : current
Description : req_connect
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.178

Field Name : httpProxyStatsReqOptions
Field Type : CounterBasedGauge64
Field Status : current
Description : req_options
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.177

Field Name : httpProxyStatsReqTrace
Field Type : CounterBasedGauge64
Field Status : current
Description : req_trace
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.176

Field Name : httpProxyStatsReqPost
Field Type : CounterBasedGauge64
Field Status : current
Description : req_post
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.175

Field Name : httpProxyStatsReqPut
Field Type : CounterBasedGauge64
Field Status : current
Description : req_put
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.174

Field Name : httpProxyStatsReqHead
Field Type : CounterBasedGauge64
Field Status : current
Description : req_head
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.173

Field Name : httpProxyStatsReqGet
Field Type : CounterBasedGauge64
Field Status : current
Description : req_get
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.172

Field Name : httpProxyStatsResponseHttp11
Field Type : CounterBasedGauge64
Field Status : current
Description : response_http11
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.171

Field Name : httpProxyStatsResponseHttp10
Field Type : CounterBasedGauge64
Field Status : current
Description : response_http10
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.170

Field Name : httpProxyStatsReqHttp11
Field Type : CounterBasedGauge64
Field Status : current
Description : req_http11
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.169

Field Name : httpProxyStatsReqHttp10
Field Type : CounterBasedGauge64
Field Status : current
Description : req_http10
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.168

Field Name : httpProxyStatsResponseUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : response_unknown
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.167

Field Name : httpProxyStatsResponse6xx
Field Type : CounterBasedGauge64
Field Status : current
Description : response_6xx
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.166

Field Name : httpProxyStatsResponse510
Field Type : CounterBasedGauge64
Field Status : current
Description : response_510
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.165

Field Name : httpProxyStatsResponse509
Field Type : CounterBasedGauge64
Field Status : current
Description : response_509
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.164

Field Name : httpProxyStatsResponse508
Field Type : CounterBasedGauge64
Field Status : current
Description : response_508
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.163

Field Name : httpProxyStatsResponse507
Field Type : CounterBasedGauge64
Field Status : current
Description : response_507
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.162

Field Name : httpProxyStatsResponse506
Field Type : CounterBasedGauge64
Field Status : current
Description : response_506
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.161

Field Name : httpProxyStatsResponse505
Field Type : CounterBasedGauge64
Field Status : current
Description : response_505

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.160

Field Name : httpProxyStatsResponse504
Field Type : CounterBasedGauge64
Field Status : current
Description : response_504
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.159

Field Name : httpProxyStatsResponse503
Field Type : CounterBasedGauge64
Field Status : current
Description : response_503
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.158

Field Name : httpProxyStatsResponse502
Field Type : CounterBasedGauge64
Field Status : current
Description : response_502
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.157

Field Name : httpProxyStatsResponse501
Field Type : CounterBasedGauge64
Field Status : current
Description : response_501
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.156

Field Name : httpProxyStatsResponse500
Field Type : CounterBasedGauge64
Field Status : current
Description : response_500
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.155

Field Name : httpProxyStatsResponse5xx
Field Type : CounterBasedGauge64
Field Status : current
Description : response_5xx
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.154

Field Name : httpProxyStatsResponse450
Field Type : CounterBasedGauge64
Field Status : current
Description : response_450
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.153

Field Name : httpProxyStatsResponse449
Field Type : CounterBasedGauge64
Field Status : current
Description : response_449
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.152

Field Name : httpProxyStatsResponse426
Field Type : CounterBasedGauge64
Field Status : current
Description : response_426
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.151

Field Name : httpProxyStatsResponse425
Field Type : CounterBasedGauge64

Field Status : current
Description : response_425
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.150

Field Name : httpProxyStatsResponse424
Field Type : CounterBasedGauge64
Field Status : current
Description : response_424
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.149

Field Name : httpProxyStatsResponse423
Field Type : CounterBasedGauge64
Field Status : current
Description : response_423
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.148

Field Name : httpProxyStatsResponse422
Field Type : CounterBasedGauge64
Field Status : current
Description : response_422
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.147

Field Name : httpProxyStatsResponse418
Field Type : CounterBasedGauge64
Field Status : current
Description : response_418
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.146

Field Name : httpProxyStatsResponse417
Field Type : CounterBasedGauge64
Field Status : current
Description : response_417
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.145

Field Name : httpProxyStatsResponse416
Field Type : CounterBasedGauge64
Field Status : current
Description : response_416
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.144

Field Name : httpProxyStatsResponse415
Field Type : CounterBasedGauge64
Field Status : current
Description : response_415
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.143

Field Name : httpProxyStatsResponse414
Field Type : CounterBasedGauge64
Field Status : current
Description : response_414
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.142

Field Name : httpProxyStatsResponse413
Field Type : CounterBasedGauge64
Field Status : current
Description : response_413
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.141

Field Name : httpProxyStatsResponse412
Field Type : CounterBasedGauge64
Field Status : current
Description : response_412
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.140

Field Name : httpProxyStatsResponse411
Field Type : CounterBasedGauge64
Field Status : current
Description : response_411
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.139

Field Name : httpProxyStatsResponse410
Field Type : CounterBasedGauge64
Field Status : current
Description : response_410
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.138

Field Name : httpProxyStatsResponse409
Field Type : CounterBasedGauge64
Field Status : current
Description : response_409
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.137

Field Name : httpProxyStatsResponse408
Field Type : CounterBasedGauge64
Field Status : current
Description : response_408
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.136

Field Name : httpProxyStatsResponse407
Field Type : CounterBasedGauge64
Field Status : current
Description : response_407
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.135

Field Name : httpProxyStatsResponse406
Field Type : CounterBasedGauge64
Field Status : current
Description : response_406
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.134

Field Name : httpProxyStatsResponse405
Field Type : CounterBasedGauge64
Field Status : current
Description : response_405
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.133

Field Name : httpProxyStatsResponse404
Field Type : CounterBasedGauge64
Field Status : current
Description : response_404
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.132

Field Name : httpProxyStatsResponse403
Field Type : CounterBasedGauge64
Field Status : current
Description : response_403

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.131

Field Name : httpProxyStatsResponse402
Field Type : CounterBasedGauge64
Field Status : current
Description : response_402
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.130

Field Name : httpProxyStatsResponse401
Field Type : CounterBasedGauge64
Field Status : current
Description : response_401
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.129

Field Name : httpProxyStatsResponse400
Field Type : CounterBasedGauge64
Field Status : current
Description : response_400
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.128

Field Name : httpProxyStatsResponse4xx
Field Type : CounterBasedGauge64
Field Status : current
Description : response_4xx
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.127

Field Name : httpProxyStatsResponse307
Field Type : CounterBasedGauge64
Field Status : current
Description : response_307
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.126

Field Name : httpProxyStatsResponse306
Field Type : CounterBasedGauge64
Field Status : current
Description : response_306
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.125

Field Name : httpProxyStatsResponse305
Field Type : CounterBasedGauge64
Field Status : current
Description : response_305
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.124

Field Name : httpProxyStatsResponse304
Field Type : CounterBasedGauge64
Field Status : current
Description : response_304
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.123

Field Name : httpProxyStatsResponse303
Field Type : CounterBasedGauge64
Field Status : current
Description : response_303
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.122

Field Name : httpProxyStatsResponse302
Field Type : CounterBasedGauge64

Field Status : current
Description : response_302
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.121

Field Name : httpProxyStatsResponse301
Field Type : CounterBasedGauge64
Field Status : current
Description : response_301
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.120

Field Name : httpProxyStatsResponse300
Field Type : CounterBasedGauge64
Field Status : current
Description : response_300
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.119

Field Name : httpProxyStatsResponse3xx
Field Type : CounterBasedGauge64
Field Status : current
Description : response_3xx
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.118

Field Name : httpProxyStatsResponse207
Field Type : CounterBasedGauge64
Field Status : current
Description : response_207
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.117

Field Name : httpProxyStatsResponse206
Field Type : CounterBasedGauge64
Field Status : current
Description : response_206
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.116

Field Name : httpProxyStatsResponse205
Field Type : CounterBasedGauge64
Field Status : current
Description : response_205
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.115

Field Name : httpProxyStatsResponse204
Field Type : CounterBasedGauge64
Field Status : current
Description : response_204
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.114

Field Name : httpProxyStatsResponse203
Field Type : CounterBasedGauge64
Field Status : current
Description : response_203
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.113

Field Name : httpProxyStatsResponse202
Field Type : CounterBasedGauge64
Field Status : current
Description : response_202
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.112

Field Name : httpProxyStatsResponse201
Field Type : CounterBasedGauge64
Field Status : current
Description : response_201
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.111

Field Name : httpProxyStatsResponse200
Field Type : CounterBasedGauge64
Field Status : current
Description : response_200
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.110

Field Name : httpProxyStatsResponse2xx
Field Type : CounterBasedGauge64
Field Status : current
Description : response_2xx
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.109

Field Name : httpProxyStatsResponse102
Field Type : CounterBasedGauge64
Field Status : current
Description : response_102
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.108

Field Name : httpProxyStatsResponse101
Field Type : CounterBasedGauge64
Field Status : current
Description : response_101
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.107

Field Name : httpProxyStatsResponse100
Field Type : CounterBasedGauge64
Field Status : current
Description : response_100
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.106

Field Name : httpProxyStatsResponse1xx
Field Type : CounterBasedGauge64
Field Status : current
Description : response_1xx
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.105

Field Name : httpProxyStatsCompressionAfter
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_after
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.104

Field Name : httpProxyStatsCompressionBefore
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_before
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.103

Field Name : httpProxyStatsServerReselFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : server_resel_failed

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.102

Field Name : httpProxyStatsStaleSess
Field Type : CounterBasedGauge64
Field Status : current
Description : stale_sess
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.101

Field Name : httpProxyStatsPktsRetransPush
Field Type : CounterBasedGauge64
Field Status : current
Description : pkts_retrans_push
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.100

Field Name : httpProxyStatsPktsRetransRst
Field Type : CounterBasedGauge64
Field Status : current
Description : pkts_retrans_rst
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.99

Field Name : httpProxyStatsPktsRetransFin
Field Type : CounterBasedGauge64
Field Status : current
Description : pkts_retrans_fin
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.98

Field Name : httpProxyStatsPktsRetransAckFinwait
Field Type : CounterBasedGauge64
Field Status : current
Description : pkts_retrans_ack_finwait
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.97

Field Name : httpProxyStatsPktsRetrans
Field Type : CounterBasedGauge64
Field Status : current
Description : pkts_retrans
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.96

Field Name : httpProxyStatsPktsOfo
Field Type : CounterBasedGauge64
Field Status : current
Description : pkts_ofo
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.95

Field Name : httpProxyStatsConnectingAck
Field Type : CounterBasedGauge64
Field Status : current
Description : connecting_ack
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.94

Field Name : httpProxyStatsConnectingRstOfo
Field Type : CounterBasedGauge64
Field Status : current
Description : connecting_rst_ofo
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.93

Field Name : httpProxyStatsConnectingRstRetrans
Field Type : CounterBasedGauge64

Field Status : current
Description : connecting_rst_retrans
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.92

Field Name : httpProxyStatsConnectingRst
Field Type : CounterBasedGauge64
Field Status : current
Description : connecting_rst
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.91

Field Name : httpProxyStatsConnectingFinOfo
Field Type : CounterBasedGauge64
Field Status : current
Description : connecting_fin_ofo
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.90

Field Name : httpProxyStatsConnectingFinRetrans
Field Type : CounterBasedGauge64
Field Status : current
Description : connecting_fin_retrans
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.89

Field Name : httpProxyStatsConnectingFin
Field Type : CounterBasedGauge64
Field Status : current
Description : connecting_fin
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.88

Field Name : httpProxyStatsClientReqUnexpFlag
Field Type : CounterBasedGauge64
Field Status : current
Description : client_req_unexp_flag
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.87

Field Name : httpProxyStatsAsmSetcookieHeaderFail
Field Type : CounterBasedGauge64
Field Status : current
Description : asm_setcookie_header_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.86

Field Name : httpProxyStatsAsmSetcookieFail
Field Type : CounterBasedGauge64
Field Status : current
Description : asm_setcookie_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.85

Field Name : httpProxyStatsAsmCookieHeaderFail
Field Type : CounterBasedGauge64
Field Status : current
Description : asm_cookie_header_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.84

Field Name : httpProxyStatsAsmCookieFail
Field Type : CounterBasedGauge64
Field Status : current
Description : asm_cookie_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.83

Field Name : httpProxyStatsParseSetcookieFail
Field Type : CounterBasedGauge64
Field Status : current
Description : parse_setcookie_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.82

Field Name : httpProxyStatsParseCookieFail
Field Type : CounterBasedGauge64
Field Status : current
Description : parse_cookie_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.81

Field Name : httpProxyStatsHugeCookieHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : huge_cookie_header
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.80

Field Name : httpProxyStatsHugeCookie
Field Type : CounterBasedGauge64
Field Status : current
Description : huge_cookie
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.79

Field Name : httpProxyStatsLargeCookieHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : large_cookie_header
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.78

Field Name : httpProxyStatsLargeCookie
Field Type : CounterBasedGauge64
Field Status : current
Description : large_cookie
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.77

Field Name : httpProxyStatsNegativeRespRemain
Field Type : CounterBasedGauge64
Field Status : current
Description : negative_resp_remain
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.76

Field Name : httpProxyStatsNegativeReqRemain
Field Type : CounterBasedGauge64
Field Status : current
Description : negative_req_remain
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.75

Field Name : httpProxyStatsInsertClientIp
Field Type : CounterBasedGauge64
Field Status : current
Description : insert_client_ip
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.74

Field Name : httpProxyStatsHeaderDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : header_delete

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.73

Field Name : httpProxyStatsHeaderInsert
Field Type : CounterBasedGauge64
Field Status : current
Description : header_insert
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.72

Field Name : httpProxyStatsWrongRespHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : wrong_resp_header
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.71

Field Name : httpProxyStatsHeaderNameTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : header_name_too_long
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.70

Field Name : httpProxyStatsLineTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : line_too_long
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.69

Field Name : httpProxyStatsTooManyHeaders
Field Type : CounterBasedGauge64
Field Status : current
Description : too_many_headers
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.68

Field Name : httpProxyStatsInvalidHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid_header
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.67

Field Name : httpProxyStatsServerRstResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : server_rst_response
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.66

Field Name : httpProxyStatsServerRstConnected
Field Type : CounterBasedGauge64
Field Status : current
Description : server_rst_connected
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.65

Field Name : httpProxyStatsServerRstConnecting
Field Type : CounterBasedGauge64
Field Status : current
Description : server_rst_connecting
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.64

Field Name : httpProxyStatsServerRstRequest
Field Type : CounterBasedGauge64

Field Status : current
Description : server_rst_request
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.63

Field Name : httpProxyStatsClientRstResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : client_rst_response
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.62

Field Name : httpProxyStatsClientRstConnected
Field Type : CounterBasedGauge64
Field Status : current
Description : client_rst_connected
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.61

Field Name : httpProxyStatsClientRstConnecting
Field Type : CounterBasedGauge64
Field Status : current
Description : client_rst_connecting
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.60

Field Name : httpProxyStatsClientRstRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : client_rst_request
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.59

Field Name : httpProxyStatsAflexLbReselectOk
Field Type : CounterBasedGauge64
Field Status : current
Description : aflex_lb_reselect_ok
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.58

Field Name : httpProxyStatsAflexLbReselect
Field Type : CounterBasedGauge64
Field Status : current
Description : aflex_lb_reselect
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.57

Field Name : httpProxyStatsAflexRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : aflex_retry
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.56

Field Name : httpProxyStatsRetry503
Field Type : CounterBasedGauge64
Field Status : current
Description : retry_503
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.55

Field Name : httpProxyStatsLbSwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : lb_switching_enqueue
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.54

Field Name : httpProxyStatsHostSwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : host_switching_enqueue
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.53

Field Name : httpProxyStatsUrlSwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : url_switching_enqueue
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.52

Field Name : httpProxyStatsHttpPolicySwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : http_policy_switching_enqueue
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.51

Field Name : httpProxyStatsAflexSwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : aflex_switching_enqueue
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.50

Field Name : httpProxyStatsCookieSwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : cookie_switching_enqueue
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.49

Field Name : httpProxyStatsL4SwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : l4_switching_enqueue
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.48

Field Name : httpProxyStatsLbSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : lb_switching_ok
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.47

Field Name : httpProxyStatsHostSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : host_switching_ok
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.46

Field Name : httpProxyStatsUrlSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : url_switching_ok
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.45

Field Name : httpProxyStatsHttpPolicySwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : http_policy_switching_ok

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.44

Field Name : httpProxyStatsAflexSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : aflex_switching_ok
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.43

Field Name : httpProxyStatsCookieSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : cookie_switching_ok
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.42

Field Name : httpProxyStatsL4SwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : l4_switching_ok
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.41

Field Name : httpProxyStatsLbSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : lb_switching
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.40

Field Name : httpProxyStatsHostSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : host_switching
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.39

Field Name : httpProxyStatsUrlSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : url_switching
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.38

Field Name : httpProxyStatsHttpPolicySwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : http_policy_switching
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.37

Field Name : httpProxyStatsAflexSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : aflex_switching
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.36

Field Name : httpProxyStatsCookieSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : cookie_switching
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.35

Field Name : httpProxyStatsL4Switching
Field Type : CounterBasedGauge64

Field Status : current
Description : l4_switching
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.34

Field Name : httpProxyStatsReqRateOverLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : req_rate_over_limit
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.33

Field Name : httpProxyStatsReqOverLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : req_over_limit
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.32

Field Name : httpProxyStatsFullProxyFpgaErr
Field Type : CounterBasedGauge64
Field Status : current
Description : full_proxy_fpga_err
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.31

Field Name : httpProxyStatsFullProxyPipeline
Field Type : CounterBasedGauge64
Field Status : current
Description : full_proxy_pipeline
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.30

Field Name : httpProxyStatsFullProxyPost
Field Type : CounterBasedGauge64
Field Status : current
Description : full_proxy_post
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.29

Field Name : httpProxyStatsFullProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : full_proxy
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.28

Field Name : httpProxyStatsTcpoutrst
Field Type : CounterBasedGauge64
Field Status : current
Description : tcpoutrst
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.27

Field Name : httpProxyStatsSnatFail
Field Type : CounterBasedGauge64
Field Status : current
Description : snat_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.26

Field Name : httpProxyStatsNewSvrconn
Field Type : CounterBasedGauge64
Field Status : current
Description : new_svrconn
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.25

Field Name : httpProxyStatsSvrPremClose
Field Type : CounterBasedGauge64
Field Status : current
Description : svr_prem_close
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.24

Field Name : httpProxyStatsServerResel
Field Type : CounterBasedGauge64
Field Status : current
Description : server_resel
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.23

Field Name : httpProxyStatsReqOfo
Field Type : CounterBasedGauge64
Field Status : current
Description : req_ofo
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.22

Field Name : httpProxyStatsReqRetran
Field Type : CounterBasedGauge64
Field Status : current
Description : req_retran
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.21

Field Name : httpProxyStatsFwdreqdataFail
Field Type : CounterBasedGauge64
Field Status : current
Description : fwdreqdata_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.20

Field Name : httpProxyStatsFwdreqFailTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : fwdreq_fail_tuple
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.19

Field Name : httpProxyStatsFwdreqFailServer
Field Type : CounterBasedGauge64
Field Status : current
Description : fwdreq_fail_server
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.18

Field Name : httpProxyStatsFwdreqFailPersist
Field Type : CounterBasedGauge64
Field Status : current
Description : fwdreq_fail_persist
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.17

Field Name : httpProxyStatsFwdreqFailRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : fwdreq_fail_route
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.16

Field Name : httpProxyStatsFwdreqFailRport
Field Type : CounterBasedGauge64
Field Status : current
Description : fwdreq_fail_rport

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.15

Field Name : httpProxyStatsFwdreqFailBuff
Field Type : CounterBasedGauge64
Field Status : current
Description : fwdreq_fail_buff
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.14

Field Name : httpProxyStatsFwdreqFail
Field Type : CounterBasedGauge64
Field Status : current
Description : fwdreq_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.13

Field Name : httpProxyStatsSvrselFail
Field Type : CounterBasedGauge64
Field Status : current
Description : svrsel_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.12

Field Name : httpProxyStatsParsereqFail
Field Type : CounterBasedGauge64
Field Status : current
Description : parsereq_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.11

Field Name : httpProxyStatsNotuple
Field Type : CounterBasedGauge64
Field Status : current
Description : notuple
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.10

Field Name : httpProxyStatsServerRst
Field Type : CounterBasedGauge64
Field Status : current
Description : server_rst
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.9

Field Name : httpProxyStatsClientRst
Field Type : CounterBasedGauge64
Field Status : current
Description : client_rst
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.8

Field Name : httpProxyStatsNoproxy
Field Type : CounterBasedGauge64
Field Status : current
Description : noproxy
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.7

Field Name : httpProxyStatsReqSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : req_succ
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.6

Field Name : httpProxyStatsReq
Field Type : CounterBasedGauge64

Field Status : current
Description : req
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.5

Field Name : httpProxyStatsTotalProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : total_proxy
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.4

Field Name : httpProxyStatsCurrProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_proxy
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.3

Field Name : httpProxyStatsNum
Field Type : CounterBasedGauge64
Field Status : current
Description : num
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.2

Field Name : httpProxyStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.1

Field Name : httpProxyOperHttpProxyCpuListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The httpProxyOperHttpProxyCpuList entry:http-proxy-cpu-list
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1

Field Name : httpProxyOperHttpProxyCpuListTransactionLimited
Field Type : CounterBasedGauge64
Field Status : current
Description : transaction_limited
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.340

Field Name : httpProxyOperHttpProxyCpuListDelH2cHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : del_h2c_header
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.339

Field Name : httpProxyOperHttpProxyCpuListUpgradeToNewProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : upgrade_to_new_proxy
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.338

Field Name : httpProxyOperHttpProxyCpuListHttpAllowedMethods
Field Type : CounterBasedGauge64
Field Status : current
Description : http_allowed_methods
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.337

Field Name : httpProxyOperHttpProxyCpuListHttpDisallowedMethods
Field Type : CounterBasedGauge64
Field Status : current
Description : http_disallowed_methods
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.336

Field Name : httpProxyOperHttpProxyCpuListHttp2ClientIdleTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : http2_client_idle_timeout
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.335

Field Name : httpProxyOperHttpProxyCpuListHttp1ClientIdleTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : http1_client_idle_timeout
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.334

Field Name : httpProxyOperHttpProxyCpuListHeaderFilterRuleHit
Field Type : CounterBasedGauge64
Field Status : current
Description : header_filter_rule_hit
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.333

Field Name : httpProxyOperHttpProxyCpuListH2upWithHostAndAuth
Field Type : CounterBasedGauge64
Field Status : current
Description : h2up_with_host_and_auth
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.332

Field Name : httpProxyOperHttpProxyCpuListGetAndPayload
Field Type : CounterBasedGauge64
Field Status : current
Description : get_and_payload
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.331

Field Name : httpProxyOperHttpProxyCpuListTransferEncodingAndContentLength
Field Type : CounterBasedGauge64
Field Status : current
Description : transfer_encoding_and_content_length
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.330

Field Name : httpProxyOperHttpProxyCpuListMultipleTransferEncoding
Field Type : CounterBasedGauge64
Field Status : current
Description : multiple_transfer_encoding
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.329

Field Name : httpProxyOperHttpProxyCpuListMultipleContentLength
Field Type : CounterBasedGauge64
Field Status : current
Description : multiple_content_length
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.328

Field Name : httpProxyOperHttpProxyCpuListH2upWithTransferEncoding
Field Type : CounterBasedGauge64
Field Status : current
Description : h2up_with_transfer_encoding

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.327

Field Name : httpProxyOperHttpProxyCpuListMalformedH2upSchemeValue
Field Type : CounterBasedGauge64
Field Status : current
Description : malformed_h2up_scheme_value
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.326

Field Name : httpProxyOperHttpProxyCpuListMalformedH2upHeaderValue
Field Type : CounterBasedGauge64
Field Status : current
Description : malformed_h2up_header_value
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.325

Field Name : httpProxyOperHttpProxyCpuListH2upContentLengthAlias
Field Type : CounterBasedGauge64
Field Status : current
Description : h2up_content_length_alias
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.324

Field Name : httpProxyOperHttpProxyCpuListCompressRspTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : compress_rsp_total
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.323

Field Name : httpProxyOperHttpProxyCpuListCompressRspBr
Field Type : CounterBasedGauge64
Field Status : current
Description : compress_rsp_br
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.322

Field Name : httpProxyOperHttpProxyCpuListDecompressionAfterTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : decompression_after_total
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.321

Field Name : httpProxyOperHttpProxyCpuListDecompressionBeforeTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : decompression_before_total
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.320

Field Name : httpProxyOperHttpProxyCpuListDecompressionAfterBr
Field Type : CounterBasedGauge64
Field Status : current
Description : decompression_after_br
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.319

Field Name : httpProxyOperHttpProxyCpuListDecompressionBeforeBr
Field Type : CounterBasedGauge64
Field Status : current
Description : decompression_before_br
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.318

Field Name : httpProxyOperHttpProxyCpuListCompressionAfterTotal
Field Type : CounterBasedGauge64

Field Status : current
Description : compression_after_total
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.317

Field Name : httpProxyOperHttpProxyCpuListCompressionBeforeTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_before_total
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.316

Field Name : httpProxyOperHttpProxyCpuListCompressionAfterBr
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_after_br
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.315

Field Name : httpProxyOperHttpProxyCpuListCompressionBeforeBr
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_before_br
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.314

Field Name : httpProxyOperHttpProxyCpuListDohDnsRespRcodeOther
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_other
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.313

Field Name : httpProxyOperHttpProxyCpuListDohDnsRespRcodeNotzone
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_notzone
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.312

Field Name : httpProxyOperHttpProxyCpuListDohDnsRespRcodeNotauth
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_notauth
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.311

Field Name : httpProxyOperHttpProxyCpuListDohDnsRespRcodeNxrrset
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_nxrrset
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.310

Field Name : httpProxyOperHttpProxyCpuListDohDnsRespRcodeYxrrset
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_yxrrset
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.309

Field Name : httpProxyOperHttpProxyCpuListDohDnsRespRcodeYxdomain
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_yxdomain
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.308

Field Name : httpProxyOperHttpProxyCpuListDohDnsRespRcodeRefuse
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_refuse
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.307

Field Name : httpProxyOperHttpProxyCpuListDohDnsRespRcodeErrType
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_err_type
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.306

Field Name : httpProxyOperHttpProxyCpuListDohDnsRespRcodeErrName
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_err_name
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.305

Field Name : httpProxyOperHttpProxyCpuListDohDnsRespRcodeErrServer
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_err_server
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.304

Field Name : httpProxyOperHttpProxyCpuListDohDnsRespRcodeErrFormat
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_err_format
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.303

Field Name : httpProxyOperHttpProxyCpuListDohDnsMalformedQuery
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_malformed_query
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.302

Field Name : httpProxyOperHttpProxyCpuListDohPostPayloadTooLarge
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_post_payload_too_large
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.301

Field Name : httpProxyOperHttpProxyCpuListDohGetUriTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_get_uri_too_long
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.300

Field Name : httpProxyOperHttpProxyCpuListDohRetryWTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_retry_w_tcp
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.299

Field Name : httpProxyOperHttpProxyCpuListDohServSelFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_serv_sel_failed

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.298

Field Name : httpProxyOperHttpProxyCpuListDohRespTcpFrags
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_resp_tcp_frags
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.297

Field Name : httpProxyOperHttpProxyCpuListDohRespUdpFrags
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_resp_udp_frags
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.296

Field Name : httpProxyOperHttpProxyCpuListDohRespQueFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_resp_que_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.295

Field Name : httpProxyOperHttpProxyCpuListDohRespHeaderAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_resp_header_alloc_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.294

Field Name : httpProxyOperHttpProxyCpuListDohRespSetupFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_resp_setup_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.293

Field Name : httpProxyOperHttpProxyCpuListDohDnsQueryTypeOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_others
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.292

Field Name : httpProxyOperHttpProxyCpuListDohDnsQueryTypeSoa
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_soa
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.291

Field Name : httpProxyOperHttpProxyCpuListDohDnsQueryTypeMx
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_mx
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.290

Field Name : httpProxyOperHttpProxyCpuListDohDnsQueryTypeSrv
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_srv
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.289

Field Name : httpProxyOperHttpProxyCpuListDohDnsQueryTypeAny
Field Type : CounterBasedGauge64

Field Status : current
Description : doh_dns_query_type_any
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.288

Field Name : httpProxyOperHttpProxyCpuListDohDnsQueryTypeCname
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_cname
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.287

Field Name : httpProxyOperHttpProxyCpuListDohDnsQueryTypeNs
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_ns
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.286

Field Name : httpProxyOperHttpProxyCpuListDohDnsQueryTypeAaaa
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_aaaa
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.285

Field Name : httpProxyOperHttpProxyCpuListDohDnsQueryTypeA
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_a
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.284

Field Name : httpProxyOperHttpProxyCpuListDohQueryTimeOut
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_query_time_out
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.283

Field Name : httpProxyOperHttpProxyCpuListDohUdpSendFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_udp_send_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.282

Field Name : httpProxyOperHttpProxyCpuListDohTcpSendFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_tcp_send_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.281

Field Name : httpProxyOperHttpProxyCpuListDohNonDohMethod
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_non_doh_method
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.280

Field Name : httpProxyOperHttpProxyCpuListDohPostPayloadExtractFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_post_payload_extract_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.279

Field Name : httpProxyOperHttpProxyCpuListDohPostPayloadNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_post_payload_not_found
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.278

Field Name : httpProxyOperHttpProxyCpuListDohPostContentTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_post_content_type_mismatch
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.277

Field Name : httpProxyOperHttpProxyCpuListDohGetBase64DecodeFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_get_base64_decode_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.276

Field Name : httpProxyOperHttpProxyCpuListDohGetDnsArgFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_get_dns_arg_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.275

Field Name : httpProxyOperHttpProxyCpuListDohPathNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_path_not_found
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.274

Field Name : httpProxyOperHttpProxyCpuListDohSnatFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_snat_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.273

Field Name : httpProxyOperHttpProxyCpuListDohReqTcpRetryFail
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_tcp_retry_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.272

Field Name : httpProxyOperHttpProxyCpuListDohReqTcpRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_tcp_retry
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.271

Field Name : httpProxyOperHttpProxyCpuListDohReqUdpRetryFail
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_udp_retry_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.270

Field Name : httpProxyOperHttpProxyCpuListDohReqUdpRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_udp_retry

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.269

Field Name : httpProxyOperHttpProxyCpuListDohMallocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_malloc_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.268

Field Name : httpProxyOperHttpProxyCpuListDohRespSendFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_resp_send_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.267

Field Name : httpProxyOperHttpProxyCpuListDohReqSendFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_send_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.266

Field Name : httpProxyOperHttpProxyCpuListDohTcpDnsResp
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_tcp_dns_resp
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.265

Field Name : httpProxyOperHttpProxyCpuListDohTcpDnsReq
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_tcp_dns_req
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.264

Field Name : httpProxyOperHttpProxyCpuListDohUdpDnsResp
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_udp_dns_resp
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.263

Field Name : httpProxyOperHttpProxyCpuListDohUdpDnsReq
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_udp_dns_req
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.262

Field Name : httpProxyOperHttpProxyCpuListDohTcResp
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_tc_resp
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.261

Field Name : httpProxyOperHttpProxyCpuListDohResp
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_resp
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.260

Field Name : httpProxyOperHttpProxyCpuListDohNonDohReqPost
Field Type : CounterBasedGauge64

Field Status : current
Description : doh_non_doh_req_post
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.259

Field Name : httpProxyOperHttpProxyCpuListDohNonDohReqGet
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_non_doh_req_get
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.258

Field Name : httpProxyOperHttpProxyCpuListDohNonDohReq
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_non_doh_req
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.257

Field Name : httpProxyOperHttpProxyCpuListDohReqPost
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_post
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.256

Field Name : httpProxyOperHttpProxyCpuListDohReqGet
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_get
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.255

Field Name : httpProxyOperHttpProxyCpuListDohReq
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.254

Field Name : httpProxyOperHttpProxyCpuListReqTimeoutClose
Field Type : CounterBasedGauge64
Field Status : current
Description : req_timeout_close
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.253

Field Name : httpProxyOperHttpProxyCpuListReqTimeoutRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : req_timeout_retry
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.252

Field Name : httpProxyOperHttpProxyCpuListWsServerPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : ws_server_packets
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.251

Field Name : httpProxyOperHttpProxyCpuListWsClientPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : ws_client_packets
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.250

Field Name : httpProxyOperHttpProxyCpuListWsHandshakeResp
Field Type : CounterBasedGauge64
Field Status : current
Description : ws_handshake_resp
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.249

Field Name : httpProxyOperHttpProxyCpuListWsHandshakeReq
Field Type : CounterBasedGauge64
Field Status : current
Description : ws_handshake_req
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.248

Field Name : httpProxyOperHttpProxyCpuListChunkBad
Field Type : CounterBasedGauge64
Field Status : current
Description : chunk_bad
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.247

Field Name : httpProxyOperHttpProxyCpuListReqHttp10Keepalive
Field Type : CounterBasedGauge64
Field Status : current
Description : req_http10_keepalive
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.246

Field Name : httpProxyOperHttpProxyCpuListRspChunk
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_chunk
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.245

Field Name : httpProxyOperHttpProxyCpuListReqContentLen
Field Type : CounterBasedGauge64
Field Status : current
Description : req_content_len
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.244

Field Name : httpProxyOperHttpProxyCpuListRspContentLen
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_content_len
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.243

Field Name : httpProxyOperHttpProxyCpuListCompressRatioTooHigh
Field Type : CounterBasedGauge64
Field Status : current
Description : compress_ratio_too_high
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.242

Field Name : httpProxyOperHttpProxyCpuListCompressRespNoClOrCe
Field Type : CounterBasedGauge64
Field Status : current
Description : compress_resp_no_cl_or_ce
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.241

Field Name : httpProxyOperHttpProxyCpuListCompressRespLtMin
Field Type : CounterBasedGauge64
Field Status : current
Description : compress_resp_lt_min

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.240

Field Name : httpProxyOperHttpProxyCpuListCompressNoContentType
Field Type : CounterBasedGauge64
Field Status : current
Description : compress_no_content_type
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.239

Field Name : httpProxyOperHttpProxyCpuListCompressContentTypeExcluded
Field Type : CounterBasedGauge64
Field Status : current
Description : compress_content_type_excluded
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.238

Field Name : httpProxyOperHttpProxyCpuListCompressRespAlreadyCompressed
Field Type : CounterBasedGauge64
Field Status : current
Description : compress_resp_already_compressed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.237

Field Name : httpProxyOperHttpProxyCpuListCompressDelAcceptEnc
Field Type : CounterBasedGauge64
Field Status : current
Description : compress_del_accept_enc
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.236

Field Name : httpProxyOperHttpProxyCpuListCompressRsp
Field Type : CounterBasedGauge64
Field Status : current
Description : compress_rsp
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.235

Field Name : httpProxyOperHttpProxyCpuListPconnConnectingFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : pconn_connecting_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.234

Field Name : httpProxyOperHttpProxyCpuListPconnConnected
Field Type : CounterBasedGauge64
Field Status : current
Description : pconn_connected
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.233

Field Name : httpProxyOperHttpProxyCpuListPconnConnecting
Field Type : CounterBasedGauge64
Field Status : current
Description : pconn_connecting
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.232

Field Name : httpProxyOperHttpProxyCpuListPktsRetransPush
Field Type : CounterBasedGauge64
Field Status : current
Description : pkts_retrans_push
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.231

Field Name : httpProxyOperHttpProxyCpuListPktsRetransRst
Field Type : CounterBasedGauge64

Field Status : current
Description : pkts_retrans_rst
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.230

Field Name : httpProxyOperHttpProxyCpuListPktsRetransFin
Field Type : CounterBasedGauge64
Field Status : current
Description : pkts_retrans_fin
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.229

Field Name : httpProxyOperHttpProxyCpuListPktsRetransAckFinwait
Field Type : CounterBasedGauge64
Field Status : current
Description : pkts_retrans_ack_finwait
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.228

Field Name : httpProxyOperHttpProxyCpuListChunkSzGt4k
Field Type : CounterBasedGauge64
Field Status : current
Description : chunk_sz_gt_4k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.227

Field Name : httpProxyOperHttpProxyCpuListChunkSz4k
Field Type : CounterBasedGauge64
Field Status : current
Description : chunk_sz_4k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.226

Field Name : httpProxyOperHttpProxyCpuListChunkSz2k
Field Type : CounterBasedGauge64
Field Status : current
Description : chunk_sz_2k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.225

Field Name : httpProxyOperHttpProxyCpuListChunkSz1k
Field Type : CounterBasedGauge64
Field Status : current
Description : chunk_sz_1k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.224

Field Name : httpProxyOperHttpProxyCpuListChunkSz512
Field Type : CounterBasedGauge64
Field Status : current
Description : chunk_sz_512
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.223

Field Name : httpProxyOperHttpProxyCpuListRspSzGt256k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_gt_256k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.222

Field Name : httpProxyOperHttpProxyCpuListRspSz256k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_256k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.221

Field Name : httpProxyOperHttpProxyCpuListRspSz64k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_64k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.220

Field Name : httpProxyOperHttpProxyCpuListRspSz32k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_32k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.219

Field Name : httpProxyOperHttpProxyCpuListRspSz16k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_16k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.218

Field Name : httpProxyOperHttpProxyCpuListRspSz8k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_8k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.217

Field Name : httpProxyOperHttpProxyCpuListRspSz4k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_4k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.216

Field Name : httpProxyOperHttpProxyCpuListRspSz2k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_2k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.215

Field Name : httpProxyOperHttpProxyCpuListRspSz1k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_1k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.214

Field Name : httpProxyOperHttpProxyCpuListReqSzGt256k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_gt_256k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.213

Field Name : httpProxyOperHttpProxyCpuListReqSz256k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_256k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.212

Field Name : httpProxyOperHttpProxyCpuListReqSz64k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_64k

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.211

Field Name : httpProxyOperHttpProxyCpuListReqSz32k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_32k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.210

Field Name : httpProxyOperHttpProxyCpuListReqSz16k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_16k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.209

Field Name : httpProxyOperHttpProxyCpuListReqSz8k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_8k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.208

Field Name : httpProxyOperHttpProxyCpuListReqSz4k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_4k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.207

Field Name : httpProxyOperHttpProxyCpuListReqSz2k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_2k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.206

Field Name : httpProxyOperHttpProxyCpuListReqSz1k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_1k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.205

Field Name : httpProxyOperHttpProxyCpuListReqOver5s
Field Type : CounterBasedGauge64
Field Status : current
Description : req_over_5s
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.204

Field Name : httpProxyOperHttpProxyCpuListReq5s
Field Type : CounterBasedGauge64
Field Status : current
Description : req_5s
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.203

Field Name : httpProxyOperHttpProxyCpuListReq2s
Field Type : CounterBasedGauge64
Field Status : current
Description : req_2s
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.202

Field Name : httpProxyOperHttpProxyCpuListReq1s
Field Type : CounterBasedGauge64

Field Status : current
Description : req_1s
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.201

Field Name : httpProxyOperHttpProxyCpuListReq500m
Field Type : CounterBasedGauge64
Field Status : current
Description : req_500m
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.200

Field Name : httpProxyOperHttpProxyCpuListReq200m
Field Type : CounterBasedGauge64
Field Status : current
Description : req_200m
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.199

Field Name : httpProxyOperHttpProxyCpuListReq100m
Field Type : CounterBasedGauge64
Field Status : current
Description : req_100m
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.198

Field Name : httpProxyOperHttpProxyCpuListReq50m
Field Type : CounterBasedGauge64
Field Status : current
Description : req_50m
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.197

Field Name : httpProxyOperHttpProxyCpuListReq20m
Field Type : CounterBasedGauge64
Field Status : current
Description : req_20m
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.196

Field Name : httpProxyOperHttpProxyCpuListReq10m
Field Type : CounterBasedGauge64
Field Status : current
Description : req_10m
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.195

Field Name : httpProxyOperHttpProxyCpuListReq5m
Field Type : CounterBasedGauge64
Field Status : current
Description : req_5m
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.194

Field Name : httpProxyOperHttpProxyCpuListReq2m
Field Type : CounterBasedGauge64
Field Status : current
Description : req_2m
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.193

Field Name : httpProxyOperHttpProxyCpuListReq1m
Field Type : CounterBasedGauge64
Field Status : current
Description : req_1m
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.192

Field Name : httpProxyOperHttpProxyCpuListReq500u
Field Type : CounterBasedGauge64
Field Status : current
Description : req_500u
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.191

Field Name : httpProxyOperHttpProxyCpuListReq200u
Field Type : CounterBasedGauge64
Field Status : current
Description : req_200u
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.190

Field Name : httpProxyOperHttpProxyCpuListReq100u
Field Type : CounterBasedGauge64
Field Status : current
Description : req_100u
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.189

Field Name : httpProxyOperHttpProxyCpuListReq50u
Field Type : CounterBasedGauge64
Field Status : current
Description : req_50u
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.188

Field Name : httpProxyOperHttpProxyCpuListReq20u
Field Type : CounterBasedGauge64
Field Status : current
Description : req_20u
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.187

Field Name : httpProxyOperHttpProxyCpuListReq10u
Field Type : CounterBasedGauge64
Field Status : current
Description : req_10u
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.186

Field Name : httpProxyOperHttpProxyCpuListResponseUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : response_unknown
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.185

Field Name : httpProxyOperHttpProxyCpuListResponse6xx
Field Type : CounterBasedGauge64
Field Status : current
Description : response_6xx
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.184

Field Name : httpProxyOperHttpProxyCpuListResponse510
Field Type : CounterBasedGauge64
Field Status : current
Description : response_510
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.183

Field Name : httpProxyOperHttpProxyCpuListResponse509
Field Type : CounterBasedGauge64
Field Status : current
Description : response_509

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.182

Field Name : httpProxyOperHttpProxyCpuListResponse508
Field Type : CounterBasedGauge64
Field Status : current
Description : response_508
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.181

Field Name : httpProxyOperHttpProxyCpuListResponse507
Field Type : CounterBasedGauge64
Field Status : current
Description : response_507
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.180

Field Name : httpProxyOperHttpProxyCpuListResponse506
Field Type : CounterBasedGauge64
Field Status : current
Description : response_506
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.179

Field Name : httpProxyOperHttpProxyCpuListResponse505
Field Type : CounterBasedGauge64
Field Status : current
Description : response_505
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.178

Field Name : httpProxyOperHttpProxyCpuListResponse504Ax
Field Type : CounterBasedGauge64
Field Status : current
Description : response_504_ax
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.177

Field Name : httpProxyOperHttpProxyCpuListResponse504
Field Type : CounterBasedGauge64
Field Status : current
Description : response_504
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.176

Field Name : httpProxyOperHttpProxyCpuListResponse503
Field Type : CounterBasedGauge64
Field Status : current
Description : response_503
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.175

Field Name : httpProxyOperHttpProxyCpuListResponse502
Field Type : CounterBasedGauge64
Field Status : current
Description : response_502
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.174

Field Name : httpProxyOperHttpProxyCpuListResponse501
Field Type : CounterBasedGauge64
Field Status : current
Description : response_501
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.173

Field Name : httpProxyOperHttpProxyCpuListResponse500
Field Type : CounterBasedGauge64

Field Status : current
Description : response_500
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.172

Field Name : httpProxyOperHttpProxyCpuListResponse5xx
Field Type : CounterBasedGauge64
Field Status : current
Description : response_5xx
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.171

Field Name : httpProxyOperHttpProxyCpuListResponse450
Field Type : CounterBasedGauge64
Field Status : current
Description : response_450
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.170

Field Name : httpProxyOperHttpProxyCpuListResponse449
Field Type : CounterBasedGauge64
Field Status : current
Description : response_449
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.169

Field Name : httpProxyOperHttpProxyCpuListResponse426
Field Type : CounterBasedGauge64
Field Status : current
Description : response_426
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.168

Field Name : httpProxyOperHttpProxyCpuListResponse425
Field Type : CounterBasedGauge64
Field Status : current
Description : response_425
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.167

Field Name : httpProxyOperHttpProxyCpuListResponse424
Field Type : CounterBasedGauge64
Field Status : current
Description : response_424
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.166

Field Name : httpProxyOperHttpProxyCpuListResponse423
Field Type : CounterBasedGauge64
Field Status : current
Description : response_423
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.165

Field Name : httpProxyOperHttpProxyCpuListResponse422
Field Type : CounterBasedGauge64
Field Status : current
Description : response_422
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.164

Field Name : httpProxyOperHttpProxyCpuListResponse418
Field Type : CounterBasedGauge64
Field Status : current
Description : response_418
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.163

Field Name : httpProxyOperHttpProxyCpuListResponse417
Field Type : CounterBasedGauge64
Field Status : current
Description : response_417
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.162

Field Name : httpProxyOperHttpProxyCpuListResponse416
Field Type : CounterBasedGauge64
Field Status : current
Description : response_416
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.161

Field Name : httpProxyOperHttpProxyCpuListResponse415
Field Type : CounterBasedGauge64
Field Status : current
Description : response_415
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.160

Field Name : httpProxyOperHttpProxyCpuListResponse414
Field Type : CounterBasedGauge64
Field Status : current
Description : response_414
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.159

Field Name : httpProxyOperHttpProxyCpuListResponse413
Field Type : CounterBasedGauge64
Field Status : current
Description : response_413
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.158

Field Name : httpProxyOperHttpProxyCpuListResponse412
Field Type : CounterBasedGauge64
Field Status : current
Description : response_412
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.157

Field Name : httpProxyOperHttpProxyCpuListResponse411
Field Type : CounterBasedGauge64
Field Status : current
Description : response_411
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.156

Field Name : httpProxyOperHttpProxyCpuListResponse410
Field Type : CounterBasedGauge64
Field Status : current
Description : response_410
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.155

Field Name : httpProxyOperHttpProxyCpuListResponse409
Field Type : CounterBasedGauge64
Field Status : current
Description : response_409
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.154

Field Name : httpProxyOperHttpProxyCpuListResponse408
Field Type : CounterBasedGauge64
Field Status : current
Description : response_408

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.153

Field Name : httpProxyOperHttpProxyCpuListResponse407
Field Type : CounterBasedGauge64
Field Status : current
Description : response_407
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.152

Field Name : httpProxyOperHttpProxyCpuListResponse406
Field Type : CounterBasedGauge64
Field Status : current
Description : response_406
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.151

Field Name : httpProxyOperHttpProxyCpuListResponse405
Field Type : CounterBasedGauge64
Field Status : current
Description : response_405
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.150

Field Name : httpProxyOperHttpProxyCpuListResponse404
Field Type : CounterBasedGauge64
Field Status : current
Description : response_404
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.149

Field Name : httpProxyOperHttpProxyCpuListResponse403
Field Type : CounterBasedGauge64
Field Status : current
Description : response_403
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.148

Field Name : httpProxyOperHttpProxyCpuListResponse402
Field Type : CounterBasedGauge64
Field Status : current
Description : response_402
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.147

Field Name : httpProxyOperHttpProxyCpuListResponse401
Field Type : CounterBasedGauge64
Field Status : current
Description : response_401
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.146

Field Name : httpProxyOperHttpProxyCpuListResponse400
Field Type : CounterBasedGauge64
Field Status : current
Description : response_400
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.145

Field Name : httpProxyOperHttpProxyCpuListResponse4xx
Field Type : CounterBasedGauge64
Field Status : current
Description : response_4xx
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.144

Field Name : httpProxyOperHttpProxyCpuListResponse307
Field Type : CounterBasedGauge64

Field Status : current
Description : response_307
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.143

Field Name : httpProxyOperHttpProxyCpuListResponse306
Field Type : CounterBasedGauge64
Field Status : current
Description : response_306
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.142

Field Name : httpProxyOperHttpProxyCpuListResponse305
Field Type : CounterBasedGauge64
Field Status : current
Description : response_305
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.141

Field Name : httpProxyOperHttpProxyCpuListResponse304
Field Type : CounterBasedGauge64
Field Status : current
Description : response_304
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.140

Field Name : httpProxyOperHttpProxyCpuListResponse303
Field Type : CounterBasedGauge64
Field Status : current
Description : response_303
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.139

Field Name : httpProxyOperHttpProxyCpuListResponse302
Field Type : CounterBasedGauge64
Field Status : current
Description : response_302
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.138

Field Name : httpProxyOperHttpProxyCpuListResponse301
Field Type : CounterBasedGauge64
Field Status : current
Description : response_301
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.137

Field Name : httpProxyOperHttpProxyCpuListResponse300
Field Type : CounterBasedGauge64
Field Status : current
Description : response_300
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.136

Field Name : httpProxyOperHttpProxyCpuListResponse3xx
Field Type : CounterBasedGauge64
Field Status : current
Description : response_3xx
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.135

Field Name : httpProxyOperHttpProxyCpuListResponse207
Field Type : CounterBasedGauge64
Field Status : current
Description : response_207
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.134

Field Name : httpProxyOperHttpProxyCpuListResponse206
Field Type : CounterBasedGauge64
Field Status : current
Description : response_206
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.133

Field Name : httpProxyOperHttpProxyCpuListResponse205
Field Type : CounterBasedGauge64
Field Status : current
Description : response_205
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.132

Field Name : httpProxyOperHttpProxyCpuListResponse204
Field Type : CounterBasedGauge64
Field Status : current
Description : response_204
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.131

Field Name : httpProxyOperHttpProxyCpuListResponse203
Field Type : CounterBasedGauge64
Field Status : current
Description : response_203
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.130

Field Name : httpProxyOperHttpProxyCpuListResponse202
Field Type : CounterBasedGauge64
Field Status : current
Description : response_202
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.129

Field Name : httpProxyOperHttpProxyCpuListResponse201
Field Type : CounterBasedGauge64
Field Status : current
Description : response_201
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.128

Field Name : httpProxyOperHttpProxyCpuListResponse200
Field Type : CounterBasedGauge64
Field Status : current
Description : response_200
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.127

Field Name : httpProxyOperHttpProxyCpuListResponse2xx
Field Type : CounterBasedGauge64
Field Status : current
Description : response_2xx
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.126

Field Name : httpProxyOperHttpProxyCpuListResponse102
Field Type : CounterBasedGauge64
Field Status : current
Description : response_102
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.125

Field Name : httpProxyOperHttpProxyCpuListResponse101
Field Type : CounterBasedGauge64
Field Status : current
Description : response_101

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.124

Field Name : httpProxyOperHttpProxyCpuListResponse100
Field Type : CounterBasedGauge64
Field Status : current
Description : response_100
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.123

Field Name : httpProxyOperHttpProxyCpuListResponse1xx
Field Type : CounterBasedGauge64
Field Status : current
Description : response_1xx
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.122

Field Name : httpProxyOperHttpProxyCpuListResponseHttp11
Field Type : CounterBasedGauge64
Field Status : current
Description : response_http11
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.121

Field Name : httpProxyOperHttpProxyCpuListResponseHttp10
Field Type : CounterBasedGauge64
Field Status : current
Description : response_http10
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.120

Field Name : httpProxyOperHttpProxyCpuListReqUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : req_unknown
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.119

Field Name : httpProxyOperHttpProxyCpuListReqDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : req_delete
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.118

Field Name : httpProxyOperHttpProxyCpuListReqConnect
Field Type : CounterBasedGauge64
Field Status : current
Description : req_connect
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.117

Field Name : httpProxyOperHttpProxyCpuListReqOptions
Field Type : CounterBasedGauge64
Field Status : current
Description : req_options
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.116

Field Name : httpProxyOperHttpProxyCpuListReqTrack
Field Type : CounterBasedGauge64
Field Status : current
Description : req_track
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.115

Field Name : httpProxyOperHttpProxyCpuListReqTrace
Field Type : CounterBasedGauge64

Field Status : current
Description : req_trace
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.114

Field Name : httpProxyOperHttpProxyCpuListReqPost
Field Type : CounterBasedGauge64
Field Status : current
Description : req_post
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.113

Field Name : httpProxyOperHttpProxyCpuListReqPut
Field Type : CounterBasedGauge64
Field Status : current
Description : req_put
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.112

Field Name : httpProxyOperHttpProxyCpuListReqHead
Field Type : CounterBasedGauge64
Field Status : current
Description : req_head
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.111

Field Name : httpProxyOperHttpProxyCpuListReqGet
Field Type : CounterBasedGauge64
Field Status : current
Description : req_get
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.110

Field Name : httpProxyOperHttpProxyCpuListResponseHttp3
Field Type : CounterBasedGauge64
Field Status : current
Description : response_http3
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.109

Field Name : httpProxyOperHttpProxyCpuListReqHttp3
Field Type : CounterBasedGauge64
Field Status : current
Description : req_http3
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.108

Field Name : httpProxyOperHttpProxyCpuListResponseHttp2
Field Type : CounterBasedGauge64
Field Status : current
Description : response_http2
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.107

Field Name : httpProxyOperHttpProxyCpuListReqHttp2
Field Type : CounterBasedGauge64
Field Status : current
Description : req_http2
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.106

Field Name : httpProxyOperHttpProxyCpuListReqHttp11NewProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : req_http11_new_proxy
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.105

Field Name : httpProxyOperHttpProxyCpuListReqHttp11
Field Type : CounterBasedGauge64
Field Status : current
Description : req_http11
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.104

Field Name : httpProxyOperHttpProxyCpuListReqHttp10
Field Type : CounterBasedGauge64
Field Status : current
Description : req_http10
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.103

Field Name : httpProxyOperHttpProxyCpuListAflexLbReselectOk
Field Type : CounterBasedGauge64
Field Status : current
Description : aflex_lb_reselect_ok
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.102

Field Name : httpProxyOperHttpProxyCpuListAflexLbReselect
Field Type : CounterBasedGauge64
Field Status : current
Description : aflex_lb_reselect
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.101

Field Name : httpProxyOperHttpProxyCpuListAflexRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : aflex_retry
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.100

Field Name : httpProxyOperHttpProxyCpuListRetry503
Field Type : CounterBasedGauge64
Field Status : current
Description : retry_503
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.99

Field Name : httpProxyOperHttpProxyCpuListNegativeRespRemain
Field Type : CounterBasedGauge64
Field Status : current
Description : negative_resp_remain
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.98

Field Name : httpProxyOperHttpProxyCpuListNegativeReqRemain
Field Type : CounterBasedGauge64
Field Status : current
Description : negative_req_remain
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.97

Field Name : httpProxyOperHttpProxyCpuListSkipInsertClientPort
Field Type : CounterBasedGauge64
Field Status : current
Description : skip_insert_client_port
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.96

Field Name : httpProxyOperHttpProxyCpuListSkipInsertClientIp
Field Type : CounterBasedGauge64
Field Status : current
Description : skip_insert_client_ip

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.95

Field Name : httpProxyOperHttpProxyCpuListInsertClientPort
Field Type : CounterBasedGauge64
Field Status : current
Description : insert_client_port
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.94

Field Name : httpProxyOperHttpProxyCpuListInsertClientIp
Field Type : CounterBasedGauge64
Field Status : current
Description : insert_client_ip
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.93

Field Name : httpProxyOperHttpProxyCpuListHeaderDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : header_delete
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.92

Field Name : httpProxyOperHttpProxyCpuListHeaderInsert
Field Type : CounterBasedGauge64
Field Status : current
Description : header_insert
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.91

Field Name : httpProxyOperHttpProxyCpuListWrongRespHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : wrong_resp_header
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.90

Field Name : httpProxyOperHttpProxyCpuListHeaderNameTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : header_name_too_long
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.89

Field Name : httpProxyOperHttpProxyCpuListLineTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : line_too_long
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.88

Field Name : httpProxyOperHttpProxyCpuListTooManyHeaders
Field Type : CounterBasedGauge64
Field Status : current
Description : too_many_headers
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.87

Field Name : httpProxyOperHttpProxyCpuListInvalidHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid_header
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.86

Field Name : httpProxyOperHttpProxyCpuListAsmSetcookieHeaderFail
Field Type : CounterBasedGauge64

Field Status : current
Description : asm_setcookie_header_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.85

Field Name : httpProxyOperHttpProxyCpuListAsmSetcookieFail
Field Type : CounterBasedGauge64
Field Status : current
Description : asm_setcookie_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.84

Field Name : httpProxyOperHttpProxyCpuListAsmCookieHeaderFail
Field Type : CounterBasedGauge64
Field Status : current
Description : asm_cookie_header_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.83

Field Name : httpProxyOperHttpProxyCpuListAsmCookieFail
Field Type : CounterBasedGauge64
Field Status : current
Description : asm_cookie_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.82

Field Name : httpProxyOperHttpProxyCpuListParseSetcookieFail
Field Type : CounterBasedGauge64
Field Status : current
Description : parse_setcookie_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.81

Field Name : httpProxyOperHttpProxyCpuListParseCookieFail
Field Type : CounterBasedGauge64
Field Status : current
Description : parse_cookie_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.80

Field Name : httpProxyOperHttpProxyCpuListHugeCookieHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : huge_cookie_header
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.79

Field Name : httpProxyOperHttpProxyCpuListHugeCookie
Field Type : CounterBasedGauge64
Field Status : current
Description : huge_cookie
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.78

Field Name : httpProxyOperHttpProxyCpuListLargeCookieHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : large_cookie_header
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.77

Field Name : httpProxyOperHttpProxyCpuListLargeCookie
Field Type : CounterBasedGauge64
Field Status : current
Description : large_cookie
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.76

Field Name : httpProxyOperHttpProxyCpuListServerReselFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : server_resel_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.75

Field Name : httpProxyOperHttpProxyCpuListStaleSess
Field Type : CounterBasedGauge64
Field Status : current
Description : stale_sess
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.74

Field Name : httpProxyOperHttpProxyCpuListPktsRetrans
Field Type : CounterBasedGauge64
Field Status : current
Description : pkts_retrans
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.73

Field Name : httpProxyOperHttpProxyCpuListPktsOfo
Field Type : CounterBasedGauge64
Field Status : current
Description : pkts_ofo
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.72

Field Name : httpProxyOperHttpProxyCpuListConnectingAck
Field Type : CounterBasedGauge64
Field Status : current
Description : connecting_ack
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.71

Field Name : httpProxyOperHttpProxyCpuListConnectingRstOfo
Field Type : CounterBasedGauge64
Field Status : current
Description : connecting_rst_ofo
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.70

Field Name : httpProxyOperHttpProxyCpuListConnectingRstRetrans
Field Type : CounterBasedGauge64
Field Status : current
Description : connecting_rst_retrans
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.69

Field Name : httpProxyOperHttpProxyCpuListConnectingRst
Field Type : CounterBasedGauge64
Field Status : current
Description : connecting_rst
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.68

Field Name : httpProxyOperHttpProxyCpuListConnectingFinOfo
Field Type : CounterBasedGauge64
Field Status : current
Description : connecting_fin_ofo
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.67

Field Name : httpProxyOperHttpProxyCpuListConnectingFinRetrans
Field Type : CounterBasedGauge64
Field Status : current
Description : connecting_fin_retrans

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.66

Field Name : httpProxyOperHttpProxyCpuListConnectingFin
Field Type : CounterBasedGauge64
Field Status : current
Description : connecting_fin
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.65

Field Name : httpProxyOperHttpProxyCpuListClientReqUnexpFlag
Field Type : CounterBasedGauge64
Field Status : current
Description : client_req_unexp_flag
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.64

Field Name : httpProxyOperHttpProxyCpuListServerRstResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : server_rst_response
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.63

Field Name : httpProxyOperHttpProxyCpuListServerRstConnected
Field Type : CounterBasedGauge64
Field Status : current
Description : server_rst_connected
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.62

Field Name : httpProxyOperHttpProxyCpuListServerRstConnecting
Field Type : CounterBasedGauge64
Field Status : current
Description : server_rst_connecting
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.61

Field Name : httpProxyOperHttpProxyCpuListServerRstRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : server_rst_request
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.60

Field Name : httpProxyOperHttpProxyCpuListClientRstResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : client_rst_response
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.59

Field Name : httpProxyOperHttpProxyCpuListClientRstConnected
Field Type : CounterBasedGauge64
Field Status : current
Description : client_rst_connected
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.58

Field Name : httpProxyOperHttpProxyCpuListClientRstConnecting
Field Type : CounterBasedGauge64
Field Status : current
Description : client_rst_connecting
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.57

Field Name : httpProxyOperHttpProxyCpuListClientRstRequest
Field Type : CounterBasedGauge64

Field Status : current
Description : client_rst_request
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.56

Field Name : httpProxyOperHttpProxyCpuListNonHttpBypass
Field Type : CounterBasedGauge64
Field Status : current
Description : non_http_bypass
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.55

Field Name : httpProxyOperHttpProxyCpuListHttpPolicySwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : http_policy_switching_enqueue
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.343

Field Name : httpProxyOperHttpProxyCpuListLbSwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : lb_switching_enqueue
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.54

Field Name : httpProxyOperHttpProxyCpuListHostSwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : host_switching_enqueue
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.53

Field Name : httpProxyOperHttpProxyCpuListUrlSwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : url_switching_enqueue
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.52

Field Name : httpProxyOperHttpProxyCpuListAflexSwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : aflex_switching_enqueue
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.51

Field Name : httpProxyOperHttpProxyCpuListCookieSwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : cookie_switching_enqueue
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.50

Field Name : httpProxyOperHttpProxyCpuListL4SwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : l4_switching_enqueue
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.49

Field Name : httpProxyOperHttpProxyCpuListHttpPolicySwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : http_policy_switching_ok
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.342

Field Name : httpProxyOperHttpProxyCpuListLbSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : lb_switching_ok
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.48

Field Name : httpProxyOperHttpProxyCpuListHostSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : host_switching_ok
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.47

Field Name : httpProxyOperHttpProxyCpuListUrlSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : url_switching_ok
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.46

Field Name : httpProxyOperHttpProxyCpuListAflexSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : aflex_switching_ok
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.45

Field Name : httpProxyOperHttpProxyCpuListCookieSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : cookie_switching_ok
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.44

Field Name : httpProxyOperHttpProxyCpuListL4SwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : l4_switching_ok
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.43

Field Name : httpProxyOperHttpProxyCpuListHttpPolicySwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : http_policy_switching
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.341

Field Name : httpProxyOperHttpProxyCpuListLbSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : lb_switching
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.42

Field Name : httpProxyOperHttpProxyCpuListHostSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : host_switching
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.41

Field Name : httpProxyOperHttpProxyCpuListUrlSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : url_switching

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.40

Field Name : httpProxyOperHttpProxyCpuListAflexSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : aflex_switching
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.39

Field Name : httpProxyOperHttpProxyCpuListCookieSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : cookie_switching
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.38

Field Name : httpProxyOperHttpProxyCpuListL4Switching
Field Type : CounterBasedGauge64
Field Status : current
Description : l4_switching
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.37

Field Name : httpProxyOperHttpProxyCpuListFwdreqFailTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : fwdreq_fail_tuple
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.36

Field Name : httpProxyOperHttpProxyCpuListFwdreqFailServer
Field Type : CounterBasedGauge64
Field Status : current
Description : fwdreq_fail_server
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.35

Field Name : httpProxyOperHttpProxyCpuListFwdreqFailPersist
Field Type : CounterBasedGauge64
Field Status : current
Description : fwdreq_fail_persist
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.34

Field Name : httpProxyOperHttpProxyCpuListFwdreqFailRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : fwdreq_fail_route
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.33

Field Name : httpProxyOperHttpProxyCpuListFwdreqFailRport
Field Type : CounterBasedGauge64
Field Status : current
Description : fwdreq_fail_rport
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.32

Field Name : httpProxyOperHttpProxyCpuListFwdreqFailBuff
Field Type : CounterBasedGauge64
Field Status : current
Description : fwdreq_fail_buff
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.31

Field Name : httpProxyOperHttpProxyCpuListFwdreqFail
Field Type : CounterBasedGauge64

Field Status : current
Description : fwdreq_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.30

Field Name : httpProxyOperHttpProxyCpuListServerRst
Field Type : CounterBasedGauge64
Field Status : current
Description : server_rst
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.29

Field Name : httpProxyOperHttpProxyCpuListClientRst
Field Type : CounterBasedGauge64
Field Status : current
Description : client_rst
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.28

Field Name : httpProxyOperHttpProxyCpuListDecompressionAfter
Field Type : CounterBasedGauge64
Field Status : current
Description : decompression_after
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.27

Field Name : httpProxyOperHttpProxyCpuListDecompressionBefore
Field Type : CounterBasedGauge64
Field Status : current
Description : decompression_before
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.26

Field Name : httpProxyOperHttpProxyCpuListCloseOnDdos
Field Type : CounterBasedGauge64
Field Status : current
Description : close_on_ddos
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.25

Field Name : httpProxyOperHttpProxyCpuListReqRateOverLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : req_rate_over_limit
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.24

Field Name : httpProxyOperHttpProxyCpuListReqOverLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : req_over_limit
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.23

Field Name : httpProxyOperHttpProxyCpuListCompressionAfter
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_after
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.22

Field Name : httpProxyOperHttpProxyCpuListCompressionBefore
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_before
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.21

Field Name : httpProxyOperHttpProxyCpuListSnatFail
Field Type : CounterBasedGauge64
Field Status : current
Description : snat_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.20

Field Name : httpProxyOperHttpProxyCpuListNewSvrconn
Field Type : CounterBasedGauge64
Field Status : current
Description : new_svrconn
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.19

Field Name : httpProxyOperHttpProxyCpuListSvrPremClose
Field Type : CounterBasedGauge64
Field Status : current
Description : svr_prem_close
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.18

Field Name : httpProxyOperHttpProxyCpuListServerResel
Field Type : CounterBasedGauge64
Field Status : current
Description : server_resel
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.17

Field Name : httpProxyOperHttpProxyCpuListReqOfo
Field Type : CounterBasedGauge64
Field Status : current
Description : req_ofo
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.16

Field Name : httpProxyOperHttpProxyCpuListReqRetran
Field Type : CounterBasedGauge64
Field Status : current
Description : req_retran
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.15

Field Name : httpProxyOperHttpProxyCpuListFwdreqdataFail
Field Type : CounterBasedGauge64
Field Status : current
Description : fwdreqdata_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.14

Field Name : httpProxyOperHttpProxyCpuListSvrselFail
Field Type : CounterBasedGauge64
Field Status : current
Description : svrsel_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.13

Field Name : httpProxyOperHttpProxyCpuListParsereqFail
Field Type : CounterBasedGauge64
Field Status : current
Description : parsereq_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.12

Field Name : httpProxyOperHttpProxyCpuListNotuple
Field Type : CounterBasedGauge64
Field Status : current
Description : notuple

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.11

Field Name : httpProxyOperHttpProxyCpuListNoproxy
Field Type : CounterBasedGauge64
Field Status : current
Description : noproxy
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.10

Field Name : httpProxyOperHttpProxyCpuListCacheRsp
Field Type : CounterBasedGauge64
Field Status : current
Description : cache_rsp
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.9

Field Name : httpProxyOperHttpProxyCpuListReqSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : req_succ
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.8

Field Name : httpProxyOperHttpProxyCpuListReqEnterSsli
Field Type : CounterBasedGauge64
Field Status : current
Description : req_enter_ssli
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.7

Field Name : httpProxyOperHttpProxyCpuListConnectReq
Field Type : CounterBasedGauge64
Field Status : current
Description : connect_req
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.6

Field Name : httpProxyOperHttpProxyCpuListReq
Field Type : CounterBasedGauge64
Field Status : current
Description : req
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.5

Field Name : httpProxyOperHttpProxyCpuListTotalProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : total_proxy
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.4

Field Name : httpProxyOperHttpProxyCpuListCurrProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_proxy
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.3

Field Name : httpProxyOperHttpProxyCpuListHttpProxyCpuListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.2

Field Name : httpProxyOperHttpProxyCpuListSlotId
Field Type : Integer32

Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.1

Field Name : l4OperL4CpuListTable
Field Type : TABLE
Field Status : current
Description : Configure L4 from object 'slb.l4'
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3

Field Name : l4OperTable
Field Type : TABLE
Field Status : current
Description : Configure L4 from object 'slb.l4'
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.2

Field Name : l4OperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The l4Oper entry
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.2.1

Field Name : l4OperCpuCount
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-count
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.2.1.2

Field Name : l4OperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.2.1.1

Field Name : l4StatsTable
Field Type : TABLE
Field Status : current
Description : Configure L4 from object 'slb.l4'
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1

Field Name : l4StatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The l4Stats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1

Field Name : l4StatsFastPathL2Reroute
Field Type : CounterBasedGauge64
Field Status : current
Description : fast_path_l2_reroute
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.139

Field Name : l4StatsFastPathReroute
Field Type : CounterBasedGauge64
Field Status : current
Description : fast_path_reroute
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.138

Field Name : l4StatsPbslbEntryLimitExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : pbslb_entry_limit_exceed
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.137

Field Name : l4StatsSlbGtpProxyRetxRequests
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_retx_requests
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.136

Field Name : l4StatsSlbGtpProxySmpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_smp_freed
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.135

Field Name : l4StatsSlbGtpProxySmpFreeNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_smp_free_not_found
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.134

Field Name : l4StatsSlbGtpProxySmpCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_smp_created
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.133

Field Name : l4StatsSlbGtpProxySmpCreationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_smp_creation_failed
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.132

Field Name : l4StatsSlbGtpProxyCProcessLocalRr
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_c_process_local_rr
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.131

Field Name : l4StatsSlbGtpProxySmpNoMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_smp_no_match
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.130

Field Name : l4StatsSlbGtpProxySmpMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_smp_match
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.129

Field Name : l4StatsSlbGtpProxyPktRcvRr
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_pkt_rcv_rr

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.128

Field Name : l4StatsProxyProtDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : proxy_prot_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.127

Field Name : l4StatsProxyProtError
Field Type : CounterBasedGauge64
Field Status : current
Description : proxy_prot_error
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.126

Field Name : l4StatsProxyHeaderRexmit
Field Type : CounterBasedGauge64
Field Status : current
Description : proxy_header_rexmit
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.125

Field Name : l4StatsProxyHeaderInsert
Field Type : CounterBasedGauge64
Field Status : current
Description : proxy_header_insert
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.124

Field Name : l4StatsSnatForcePreserveFree
Field Type : CounterBasedGauge64
Field Status : current
Description : snat_force_preserve_free
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.123

Field Name : l4StatsSnatForcePreserveAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : snat_force_preserve_alloc
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.122

Field Name : l4StatsSnatPortOverloadFail
Field Type : CounterBasedGauge64
Field Status : current
Description : snat_port_overload_fail
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.121

Field Name : l4StatsReselectSvrselfail
Field Type : CounterBasedGauge64
Field Status : current
Description : reselect_svrselfail
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.120

Field Name : l4StatsGtpCInvalidMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : gtp_c_invalid_message
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.119

Field Name : l4StatsGtpCInvalidHeader
Field Type : CounterBasedGauge64

Field Status : current
Description : gtp_c_invalid_header
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.118

Field Name : l4StatsGtpCInvalidPort
Field Type : CounterBasedGauge64
Field Status : current
Description : gtp_c_invalid_port
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.117

Field Name : l4StatsTcpConnectionsClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_connections_closed
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.116

Field Name : l4StatsRateDropResetUnkn
Field Type : CounterBasedGauge64
Field Status : current
Description : rate_drop_reset_unkn
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.115

Field Name : l4StatsDnssecSwitch
Field Type : CounterBasedGauge64
Field Status : current
Description : dnssec_switch
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.114

Field Name : l4StatsServerDownDel
Field Type : CounterBasedGauge64
Field Status : current
Description : server_down_del
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.113

Field Name : l4StatsDnsIdSwitch
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_id_switch
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.112

Field Name : l4StatsSynreceivedHw
Field Type : CounterBasedGauge64
Field Status : current
Description : synreceived_hw
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.111

Field Name : l4StatsSkipInsertClientIp
Field Type : CounterBasedGauge64
Field Status : current
Description : skip_insert_client_ip
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.110

Field Name : l4StatsSyncookieBuffQueue
Field Type : CounterBasedGauge64
Field Status : current
Description : syncookie_buff_queue
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.109

Field Name : l4StatsSyncookieBuffDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : syncookie_buff_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.108

Field Name : l4StatsSynRate
Field Type : CounterBasedGauge64
Field Status : current
Description : syn_rate
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.107

Field Name : l4StatsSynattack
Field Type : CounterBasedGauge64
Field Status : current
Description : synattack
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.106

Field Name : l4StatsTcpEst
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_est
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.105

Field Name : l4StatsOutSeqAckDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : out_seq_ack_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.104

Field Name : l4StatsUdpRespOneplus
Field Type : CounterBasedGauge64
Field Status : current
Description : udp_resp_oneplus
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.103

Field Name : l4StatsUdpReqOneplus
Field Type : CounterBasedGauge64
Field Status : current
Description : udp_req_oneplus
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.102

Field Name : l4StatsUdpRespMoreReq
Field Type : CounterBasedGauge64
Field Status : current
Description : udp_resp_more_req
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.101

Field Name : l4StatsUdpReqMoreResp
Field Type : CounterBasedGauge64
Field Status : current
Description : udp_req_more_resp
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.100

Field Name : l4StatsUdpReqRespNotmatch
Field Type : CounterBasedGauge64
Field Status : current
Description : udp_req_resp_notmatch

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.99

Field Name : l4StatsUdpReqOneOneplusResp
Field Type : CounterBasedGauge64
Field Status : current
Description : udp_req_one_oneplus_resp
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.98

Field Name : l4StatsUdpReqOneplusNoResp
Field Type : CounterBasedGauge64
Field Status : current
Description : udp_req_oneplus_no_resp
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.97

Field Name : l4StatsTcpRevRst
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_rev_rst
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.96

Field Name : l4StatsTcpFwdRst
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_fwd_rst
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.95

Field Name : l4StatsTcpRevAckfin
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_rev_ackfin
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.94

Field Name : l4StatsTcpRevFinDup
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_rev_fin_dup
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.93

Field Name : l4StatsTcpFwdFinDup
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_fwd_fin_dup
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.92

Field Name : l4StatsTcpRexmitSynackDelq
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_rexmit_synack_delq
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.91

Field Name : l4StatsTcpRexmitSynack
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_rexmit_synack
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.90

Field Name : l4StatsTcpRexmitSynDelq
Field Type : CounterBasedGauge64

Field Status : current
Description : tcp_rexmit_syn_delq
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.89

Field Name : l4StatsTcpRexmitSyn
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_rexmit_syn
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.88

Field Name : l4StatsTcpSessNoestSsynXmitAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_sess_noest_ssyn_xmit_aged_out
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.87

Field Name : l4StatsTcpSessNoestCsynRcvAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_sess_noest_csyn_rcv_aged_out
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.86

Field Name : l4StatsTcpSessNoestAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_sess_noest_aged_out
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.85

Field Name : l4StatsTcpSynRcvRst
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_syn_rcv_rst
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.84

Field Name : l4StatsTcpSynRcvAck
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_syn_rcv_ack
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.83

Field Name : l4StatsTcpAxRexmitSyn
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_ax_rexmit_syn
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.82

Field Name : l4StatsStatelessConnTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : stateless_conn_timeout
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.81

Field Name : l4StatsSvrSynHandshakeFail
Field Type : CounterBasedGauge64
Field Status : current
Description : svr_syn_handshake_fail
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.80

Field Name : l4StatsConcurrentConnExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : concurrent_conn_exceed
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.79

Field Name : l4StatsSslWatermarkDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl_watermark_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.78

Field Name : l4StatsSslTptExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl_tpt_exceed
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.77

Field Name : l4StatsSslCpsExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl_cps_exceed
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.76

Field Name : l4StatsL7CpsExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : l7_cps_exceed
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.75

Field Name : l4StatsNatCpsExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : nat_cps_exceed
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.74

Field Name : l4StatsL4CpsExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : l4_cps_exceed
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.73

Field Name : l4StatsBwWatermarkDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : bw_watermark_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.72

Field Name : l4StatsBwRateLimitExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : bw_rate_limit_exceed
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.71

Field Name : l4StatsTcpotherflagsDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : tcpotherflags_drop

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.70

Field Name : l4StatsTcpsyndataDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : tcpsyndata_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.69

Field Name : l4StatsPortPreserveSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : port_preserve_succ
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.68

Field Name : l4StatsPortPreserveAttempt
Field Type : CounterBasedGauge64
Field Status : current
Description : port_preserve_attempt
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.67

Field Name : l4StatsL3Dsr
Field Type : CounterBasedGauge64
Field Status : current
Description : l3_dsr
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.66

Field Name : l4StatsL2Dsr
Field Type : CounterBasedGauge64
Field Status : current
Description : l2_dsr
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.65

Field Name : l4StatsIgnoreMsl
Field Type : CounterBasedGauge64
Field Status : current
Description : ignore_msl
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.64

Field Name : l4StatsResetL7OnFailover
Field Type : CounterBasedGauge64
Field Status : current
Description : reset_l7_on_failover
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.63

Field Name : l4StatsResetUnknownConn
Field Type : CounterBasedGauge64
Field Status : current
Description : reset_unknown_conn
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.62

Field Name : l4StatsNoResourseDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : no_resourse_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.61

Field Name : l4StatsAnomalyPbslbDrop
Field Type : CounterBasedGauge64

Field Status : current
Description : anomaly_pbslb_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.60

Field Name : l4StatsAnomalyBadContent
Field Type : CounterBasedGauge64
Field Status : current
Description : anomaly_bad_content
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.59

Field Name : l4StatsAnomalyZeroWin
Field Type : CounterBasedGauge64
Field Status : current
Description : anomaly_zero_win
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.58

Field Name : l4StatsAnomalyOutSeq
Field Type : CounterBasedGauge64
Field Status : current
Description : anomaly_out_seq
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.57

Field Name : l4StatsTcpInvalidDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_invalid_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.56

Field Name : l4StatsDnsPolicyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_policy_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.55

Field Name : l4StatsFastAgingReset
Field Type : CounterBasedGauge64
Field Status : current
Description : fast_aging_reset
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.54

Field Name : l4StatsFastAgingSet
Field Type : CounterBasedGauge64
Field Status : current
Description : fast_aging_set
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.53

Field Name : l4StatsAutoReassign
Field Type : CounterBasedGauge64
Field Status : current
Description : auto_reassign
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.52

Field Name : l4StatsInbandHmReassign
Field Type : CounterBasedGauge64
Field Status : current
Description : inband_hm_reassign
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.51

Field Name : l4StatsInbandHmRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : inband_hm_retry
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.50

Field Name : l4StatsDropGslb
Field Type : CounterBasedGauge64
Field Status : current
Description : drop_gslb
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.49

Field Name : l4StatsThrottleSyn
Field Type : CounterBasedGauge64
Field Status : current
Description : throttle_syn
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.48

Field Name : l4StatsUdpNoSlb
Field Type : CounterBasedGauge64
Field Status : current
Description : udp_no_slb
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.47

Field Name : l4StatsTcpNoSlb
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_no_slb
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.46

Field Name : l4StatsOtherSessAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : other_sess_aged_out
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.45

Field Name : l4StatsUdpSessAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : udp_sess_aged_out
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.44

Field Name : l4StatsTcpSessAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_sess_aged_out
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.43

Field Name : l4StatsSessAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : sess_aged_out
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.42

Field Name : l4StatsDropAflex
Field Type : CounterBasedGauge64
Field Status : current
Description : drop_aflex

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.41

Field Name : l4StatsProxyNosockDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : proxy_nosock_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.40

Field Name : l4StatsConnRateLimitReset
Field Type : CounterBasedGauge64
Field Status : current
Description : conn_rate_limit_reset
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.39

Field Name : l4StatsConnRateLimitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : conn_rate_limit_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.38

Field Name : l4StatsConnlimitReset
Field Type : CounterBasedGauge64
Field Status : current
Description : connlimit_reset
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.37

Field Name : l4StatsConnlimitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : connlimit_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.36

Field Name : l4StatsNosynDropAck
Field Type : CounterBasedGauge64
Field Status : current
Description : nosyn_drop_ack
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.35

Field Name : l4StatsNosynDropRst
Field Type : CounterBasedGauge64
Field Status : current
Description : nosyn_drop_rst
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.34

Field Name : l4StatsNosynDropFin
Field Type : CounterBasedGauge64
Field Status : current
Description : nosyn_drop_fin
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.33

Field Name : l4StatsNosynDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : nosyn_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.32

Field Name : l4StatsNoVportDrop
Field Type : CounterBasedGauge64

Field Status : current
Description : no_vport_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.31

Field Name : l4StatsNovportDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : novport_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.30

Field Name : l4StatsSyncookiescheckfailed
Field Type : CounterBasedGauge64
Field Status : current
Description : syncookiescheckfailed
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.29

Field Name : l4StatsSmartNatIdMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : smart_nat_id_mismatch
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.28

Field Name : l4StatsSnatIcmpNoMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : snat_icmp_no_match
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.27

Field Name : l4StatsSnatIcmpErrorProcess
Field Type : CounterBasedGauge64
Field Status : current
Description : snat_icmp_error_process
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.26

Field Name : l4StatsSnatNoRevRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : snat_no_rev_route
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.25

Field Name : l4StatsSnatNoFwdRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : snat_no_fwd_route
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.24

Field Name : l4StatsSnatFail
Field Type : CounterBasedGauge64
Field Status : current
Description : snat_fail
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.23

Field Name : l4StatsNoroute
Field Type : CounterBasedGauge64
Field Status : current
Description : noroute
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.22

Field Name : l4StatsSvrselfail
Field Type : CounterBasedGauge64
Field Status : current
Description : svrselfail
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.21

Field Name : l4StatsOutrstTcpproxy
Field Type : CounterBasedGauge64
Field Status : current
Description : outrst_tcpproxy
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.20

Field Name : l4StatsSynStaleSess
Field Type : CounterBasedGauge64
Field Status : current
Description : syn_stale_sess
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.19

Field Name : l4StatsOutrstStaleSess
Field Type : CounterBasedGauge64
Field Status : current
Description : outrst_stale_sess
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.18

Field Name : l4StatsOutrstAflex
Field Type : CounterBasedGauge64
Field Status : current
Description : outrst_aflex
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.17

Field Name : l4StatsOutrstAckAttack
Field Type : CounterBasedGauge64
Field Status : current
Description : outrst_ack_attack
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.16

Field Name : l4StatsOutrstBroker
Field Type : CounterBasedGauge64
Field Status : current
Description : outrst_broker
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.15

Field Name : l4StatsOutrstNosyn
Field Type : CounterBasedGauge64
Field Status : current
Description : outrst_nosyn
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.14

Field Name : l4StatsOutrst
Field Type : CounterBasedGauge64
Field Status : current
Description : outrst
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.13

Field Name : l4StatsSyncookiessentfailed
Field Type : CounterBasedGauge64
Field Status : current
Description : syncookiessentfailed

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.12

Field Name : l4StatsSyncookiessentTs
Field Type : CounterBasedGauge64
Field Status : current
Description : syncookiessent_ts
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.11

Field Name : l4StatsSyncookiessent
Field Type : CounterBasedGauge64
Field Status : current
Description : syncookiessent
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.10

Field Name : l4StatsInudp
Field Type : CounterBasedGauge64
Field Status : current
Description : inudp
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.9

Field Name : l4StatsTcpFwdAckfin
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_fwd_ackfin
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.8

Field Name : l4StatsTcpFwdFin
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_fwd_fin
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.7

Field Name : l4StatsTcpRevFin
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_rev_fin
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.6

Field Name : l4StatsTcpRevLastAck
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_rev_last_ack
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.5

Field Name : l4StatsTcpFwdLastAck
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_fwd_last_ack
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.4

Field Name : l4StatsSynreceived
Field Type : CounterBasedGauge64
Field Status : current
Description : synreceived
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.3

Field Name : l4StatsIntcp
Field Type : CounterBasedGauge64

Field Status : current
Description : intcp
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.2

Field Name : l4StatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.1

Field Name : l4OperL4CpuListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The l4OperL4CpuList entry:l4-cpu-list
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1

Field Name : l4OperL4CpuListFastPathL2Reroute
Field Type : CounterBasedGauge64
Field Status : current
Description : fast_path_l2_reroute
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.137

Field Name : l4OperL4CpuListFastPathReroute
Field Type : CounterBasedGauge64
Field Status : current
Description : fast_path_reroute
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.136

Field Name : l4OperL4CpuListPbslbEntryLimitExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : pbslb_entry_limit_exceed
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.135

Field Name : l4OperL4CpuListSlbGtpProxyRetxRequests
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_retx_requests
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.134

Field Name : l4OperL4CpuListSlbGtpProxySmpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_smp_freed
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.133

Field Name : l4OperL4CpuListSlbGtpProxySmpFreeNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_smp_free_not_found
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.132

Field Name : l4OperL4CpuListSlbGtpProxySmpCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_smp_created
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.131

Field Name : l4OperL4CpuListSlbGtpProxySmpCreationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_smp_creation_failed
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.130

Field Name : l4OperL4CpuListSlbGtpProxyCProcessLocalRr
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_c_process_local_rr
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.129

Field Name : l4OperL4CpuListSlbGtpProxySmpNoMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_smp_no_match
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.128

Field Name : l4OperL4CpuListSlbGtpProxySmpMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_smp_match
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.127

Field Name : l4OperL4CpuListSlbGtpProxyPktRcvRr
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_pkt_rcv_rr
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.126

Field Name : l4OperL4CpuListProxyProtDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : proxy_prot_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.125

Field Name : l4OperL4CpuListProxyProtError
Field Type : CounterBasedGauge64
Field Status : current
Description : proxy_prot_error
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.124

Field Name : l4OperL4CpuListProxyHeaderRexmit
Field Type : CounterBasedGauge64
Field Status : current
Description : proxy_header_rexmit
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.123

Field Name : l4OperL4CpuListProxyHeaderInsert
Field Type : CounterBasedGauge64
Field Status : current
Description : proxy_header_insert
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.122

Field Name : l4OperL4CpuListSnatForcePreserveFree
Field Type : CounterBasedGauge64
Field Status : current
Description : snat_force_preserve_free

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.121

Field Name : l4OperL4CpuListSnatForcePreserveAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : snat_force_preserve_alloc
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.120

Field Name : l4OperL4CpuListSnatPortOverloadFail
Field Type : CounterBasedGauge64
Field Status : current
Description : snat_port_overload_fail
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.119

Field Name : l4OperL4CpuListReselectSvrselfail
Field Type : CounterBasedGauge64
Field Status : current
Description : reselect_svrselfail
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.118

Field Name : l4OperL4CpuListGtpCInvalidMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : gtp_c_invalid_message
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.117

Field Name : l4OperL4CpuListGtpCInvalidHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : gtp_c_invalid_header
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.116

Field Name : l4OperL4CpuListGtpCInvalidPort
Field Type : CounterBasedGauge64
Field Status : current
Description : gtp_c_invalid_port
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.115

Field Name : l4OperL4CpuListTcpConnectionsClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_connections_closed
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.114

Field Name : l4OperL4CpuListServerDownDel
Field Type : CounterBasedGauge64
Field Status : current
Description : server_down_del
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.113

Field Name : l4OperL4CpuListSyncookiesBuffDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : syncookies_buff_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.112

Field Name : l4OperL4CpuListSyncookiesBuffQueue
Field Type : CounterBasedGauge64

Field Status : current
Description : syncookies_buff_queue
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.111

Field Name : l4OperL4CpuListDnssecSwitch
Field Type : CounterBasedGauge64
Field Status : current
Description : dnssec_switch
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.110

Field Name : l4OperL4CpuListDnsIdSwitch
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_id_switch
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.109

Field Name : l4OperL4CpuListSkipInsertClientIp
Field Type : CounterBasedGauge64
Field Status : current
Description : skip_insert_client_ip
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.108

Field Name : l4OperL4CpuListSynattack
Field Type : CounterBasedGauge64
Field Status : current
Description : synattack
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.107

Field Name : l4OperL4CpuListTcpEst
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_est
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.106

Field Name : l4OperL4CpuListRcvUdpRsps
Field Type : CounterBasedGauge64
Field Status : current
Description : rcv_udp_rsps
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.105

Field Name : l4OperL4CpuListRcvUdpReqs
Field Type : CounterBasedGauge64
Field Status : current
Description : rcv_udp_reqs
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.104

Field Name : l4OperL4CpuListRcvRspsMorethanReqs
Field Type : CounterBasedGauge64
Field Status : current
Description : rcv_rsps_morethan_reqs
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.103

Field Name : l4OperL4CpuListRcvReqMorethanRsps
Field Type : CounterBasedGauge64
Field Status : current
Description : rcv_req_morethan_rsps
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.102

Field Name : l4OperL4CpuListRcvReqNotMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : rcv_req_not_match
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.101

Field Name : l4OperL4CpuListRcvReqRsps
Field Type : CounterBasedGauge64
Field Status : current
Description : rcv_req_rsps
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.100

Field Name : l4OperL4CpuListRcvReqsNoRsp
Field Type : CounterBasedGauge64
Field Status : current
Description : rcv_reqs_no_rsp
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.99

Field Name : l4OperL4CpuListRcvRevRst
Field Type : CounterBasedGauge64
Field Status : current
Description : rcv_rev_rst
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.98

Field Name : l4OperL4CpuListRcvFwdRst
Field Type : CounterBasedGauge64
Field Status : current
Description : rcv_fwd_rst
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.97

Field Name : l4OperL4CpuListRcvRevFinack
Field Type : CounterBasedGauge64
Field Status : current
Description : rcv_rev_finack
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.96

Field Name : l4OperL4CpuListRcvRevFinDup
Field Type : CounterBasedGauge64
Field Status : current
Description : rcv_rev_fin_dup
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.95

Field Name : l4OperL4CpuListRcvRevFin
Field Type : CounterBasedGauge64
Field Status : current
Description : rcv_rev_fin
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.94

Field Name : l4OperL4CpuListRcvFwdFinack
Field Type : CounterBasedGauge64
Field Status : current
Description : rcv_fwd_finack
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.93

Field Name : l4OperL4CpuListRcvFwdFinDup
Field Type : CounterBasedGauge64
Field Status : current
Description : rcv_fwd_fin_dup

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.92

Field Name : l4OperL4CpuListRcvFwdFin
Field Type : CounterBasedGauge64
Field Status : current
Description : rcv_fwd_fin
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.91

Field Name : l4OperL4CpuListRcvRevLastAck
Field Type : CounterBasedGauge64
Field Status : current
Description : rcv_rev_last_ack
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.90

Field Name : l4OperL4CpuListRcvFwdLastAck
Field Type : CounterBasedGauge64
Field Status : current
Description : rcv_fwd_last_ack
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.89

Field Name : l4OperL4CpuListRcvRexmitSynackDelq
Field Type : CounterBasedGauge64
Field Status : current
Description : rcv_rexmit_synack_delq
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.88

Field Name : l4OperL4CpuListRcvRexmitSynack
Field Type : CounterBasedGauge64
Field Status : current
Description : rcv_rexmit_synack
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.87

Field Name : l4OperL4CpuListRcvRexmitSynDelq
Field Type : CounterBasedGauge64
Field Status : current
Description : rcv_rexmit_syn_delq
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.86

Field Name : l4OperL4CpuListRcvRexmitSyn
Field Type : CounterBasedGauge64
Field Status : current
Description : rcv_rexmit_syn
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.85

Field Name : l4OperL4CpuListNoestServerSynXmitAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : noest_server_syn_xmit_aged_out
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.84

Field Name : l4OperL4CpuListNoestClientSynAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : noest_client_syn_aged_out
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.83

Field Name : l4OperL4CpuListTcpNoestAgedOut
Field Type : CounterBasedGauge64

Field Status : current
Description : tcp_noest_aged_out
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.82

Field Name : l4OperL4CpuListRcvRstOnSyn
Field Type : CounterBasedGauge64
Field Status : current
Description : rcv_rst_on_syn
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.81

Field Name : l4OperL4CpuListRcvAckOnSyn
Field Type : CounterBasedGauge64
Field Status : current
Description : rcv_ack_on_syn
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.80

Field Name : l4OperL4CpuListAxRexmitSyn
Field Type : CounterBasedGauge64
Field Status : current
Description : ax_rexmit_syn
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.79

Field Name : l4OperL4CpuListStatelessConnTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : stateless_conn_timeout
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.78

Field Name : l4OperL4CpuListL4SvrHandshakeFail
Field Type : CounterBasedGauge64
Field Status : current
Description : l4_svr_handshake_fail
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.77

Field Name : l4OperL4CpuListConnLimitExceedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : conn_limit_exceed_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.76

Field Name : l4OperL4CpuListSslWatermarkDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl_watermark_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.75

Field Name : l4OperL4CpuListSslTptExceedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl_tpt_exceed_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.74

Field Name : l4OperL4CpuListSslCpsExceedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl_cps_exceed_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.73

Field Name : l4OperL4CpuListL7CpsExceedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : l7_cps_exceed_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.72

Field Name : l4OperL4CpuListNatCpsExceedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : nat_cps_exceed_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.71

Field Name : l4OperL4CpuListL4CpsExceedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : l4_cps_exceed_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.70

Field Name : l4OperL4CpuListBwWatermarkDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : bw_watermark_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.69

Field Name : l4OperL4CpuListBwRateLimitExceedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : bw_rate_limit_exceed_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.68

Field Name : l4OperL4CpuListPortPreserveSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : port_preserve_succ
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.67

Field Name : l4OperL4CpuListPortPreserveAttempt
Field Type : CounterBasedGauge64
Field Status : current
Description : port_preserve_attempt
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.66

Field Name : l4OperL4CpuListL3Dsr
Field Type : CounterBasedGauge64
Field Status : current
Description : l3_dsr
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.65

Field Name : l4OperL4CpuListL2Dsr
Field Type : CounterBasedGauge64
Field Status : current
Description : l2_dsr
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.64

Field Name : l4OperL4CpuListIgnoreMsl
Field Type : CounterBasedGauge64
Field Status : current
Description : ignore_msl

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.63

Field Name : l4OperL4CpuListTcpSynWithdata
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_syn_withdata
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.62

Field Name : l4OperL4CpuListTcpSynOtherflags
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_syn_otherflags
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.61

Field Name : l4OperL4CpuListResetL7OnFailover
Field Type : CounterBasedGauge64
Field Status : current
Description : reset_l7_on_failover
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.60

Field Name : l4OperL4CpuListResetUnknownConn
Field Type : CounterBasedGauge64
Field Status : current
Description : reset_unknown_conn
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.59

Field Name : l4OperL4CpuListNoResourceDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : no_resource_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.58

Field Name : l4OperL4CpuListAnomalyPbslbDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : anomaly_pbslb_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.57

Field Name : l4OperL4CpuListAnomalyBadContent
Field Type : CounterBasedGauge64
Field Status : current
Description : anomaly_bad_content
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.56

Field Name : l4OperL4CpuListAnomalyZeroWin
Field Type : CounterBasedGauge64
Field Status : current
Description : anomaly_zero_win
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.55

Field Name : l4OperL4CpuListAnomalyOutSeq
Field Type : CounterBasedGauge64
Field Status : current
Description : anomaly_out_seq
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.54

Field Name : l4OperL4CpuListOutSeqAckDrop
Field Type : CounterBasedGauge64

Field Status : current
Description : out_seq_ack_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.53

Field Name : l4OperL4CpuListTcpInvalidDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_invalid_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.52

Field Name : l4OperL4CpuListFastAgingReset
Field Type : CounterBasedGauge64
Field Status : current
Description : fast_aging_reset
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.51

Field Name : l4OperL4CpuListFastAgingSet
Field Type : CounterBasedGauge64
Field Status : current
Description : fast_aging_set
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.50

Field Name : l4OperL4CpuListAutoReassign
Field Type : CounterBasedGauge64
Field Status : current
Description : auto_reassign
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.49

Field Name : l4OperL4CpuListInbandHmReassign
Field Type : CounterBasedGauge64
Field Status : current
Description : inband_hm_reassign
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.48

Field Name : l4OperL4CpuListInbandHmRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : inband_hm_retry
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.47

Field Name : l4OperL4CpuListThrottleSyn
Field Type : CounterBasedGauge64
Field Status : current
Description : throttle_syn
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.46

Field Name : l4OperL4CpuListUdpNoSlb
Field Type : CounterBasedGauge64
Field Status : current
Description : udp_no_slb
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.45

Field Name : l4OperL4CpuListTcpNoSlb
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_no_slb
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.44

Field Name : l4OperL4CpuListOtherSessAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : other_sess_aged_out
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.43

Field Name : l4OperL4CpuListUdpSessAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : udp_sess_aged_out
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.42

Field Name : l4OperL4CpuListTcpSessAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_sess_aged_out
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.41

Field Name : l4OperL4CpuListSessAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : sess_aged_out
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.40

Field Name : l4OperL4CpuListAflexDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : aflex_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.39

Field Name : l4OperL4CpuListProxyNosockDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : proxy_nosock_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.38

Field Name : l4OperL4CpuListConnRateLimitReset
Field Type : CounterBasedGauge64
Field Status : current
Description : conn_rate_limit_reset
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.37

Field Name : l4OperL4CpuListConnRateLimitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : conn_rate_limit_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.36

Field Name : l4OperL4CpuListConnlimitReset
Field Type : CounterBasedGauge64
Field Status : current
Description : connlimit_reset
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.35

Field Name : l4OperL4CpuListConnlimitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : connlimit_drop

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.34

Field Name : l4OperL4CpuListNosynDropAck
Field Type : CounterBasedGauge64
Field Status : current
Description : nosyn_drop_ack
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.33

Field Name : l4OperL4CpuListNosynDropRst
Field Type : CounterBasedGauge64
Field Status : current
Description : nosyn_drop_rst
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.32

Field Name : l4OperL4CpuListNosynDropFin
Field Type : CounterBasedGauge64
Field Status : current
Description : nosyn_drop_fin
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.31

Field Name : l4OperL4CpuListNosynDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : nosyn_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.30

Field Name : l4OperL4CpuListNoVportDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : no_vport_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.29

Field Name : l4OperL4CpuListNovportDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : novport_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.28

Field Name : l4OperL4CpuListTcpSyncookiescheckfailed
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_syncookiescheckfailed
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.27

Field Name : l4OperL4CpuListSmartNatIdMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : smart_nat_id_mismatch
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.26

Field Name : l4OperL4CpuListSnatIcmpNoMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : snat_icmp_no_match
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.25

Field Name : l4OperL4CpuListSnatIcmpErrorProcess
Field Type : CounterBasedGauge64

Field Status : current
Description : snat_icmp_error_process
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.24

Field Name : l4OperL4CpuListSnatNoRevRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : snat_no_rev_route
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.23

Field Name : l4OperL4CpuListSnatNoFwdRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : snat_no_fwd_route
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.22

Field Name : l4OperL4CpuListSnatFail
Field Type : CounterBasedGauge64
Field Status : current
Description : snat_fail
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.21

Field Name : l4OperL4CpuListSvrSelFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : svr_sel_failed
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.20

Field Name : l4OperL4CpuListInudp
Field Type : CounterBasedGauge64
Field Status : current
Description : inudp
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.19

Field Name : l4OperL4CpuListIntcp
Field Type : CounterBasedGauge64
Field Status : current
Description : intcp
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.18

Field Name : l4OperL4CpuListTcpSyncookiessentfailed
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_syncookiessentfailed
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.17

Field Name : l4OperL4CpuListTcpSyncookiessentTs
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_syncookiessent_ts
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.16

Field Name : l4OperL4CpuListTcpSyncookiessent
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_syncookiessent
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.15

Field Name : l4OperL4CpuListTcpSynRate
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_syn_rate
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.14

Field Name : l4OperL4CpuListTcpSynreceivedHw
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_synreceived_hw
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.13

Field Name : l4OperL4CpuListTcpSynreceived
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_synreceived
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.12

Field Name : l4OperL4CpuListTcpOutrstTcpproxy
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_outrst_tcpproxy
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.11

Field Name : l4OperL4CpuListTcpSynStaleSess
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_syn_stale_sess
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.10

Field Name : l4OperL4CpuListTcpOutrstStaleSess
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_outrst_stale_sess
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.9

Field Name : l4OperL4CpuListTcpOutrstAflex
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_outrst_aflex
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.8

Field Name : l4OperL4CpuListTcpOutrstAckAttack
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_outrst_ack_attack
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.7

Field Name : l4OperL4CpuListTcpOutrstBroker
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_outrst_broker
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.6

Field Name : l4OperL4CpuListTcpOutrstNosyn
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_outrst_nosyn

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.5

Field Name : l4OperL4CpuListTcpOutrst
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_outrst
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.4

Field Name : l4OperL4CpuListIpOutnoroute
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_outnoroute
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.3

Field Name : l4OperL4CpuListL4CpuListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.2

Field Name : l4OperL4CpuListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.1

Field Name : statusOperPartitionListTable
Field Type : TABLE
Field Status : current
Description : NGWAF status from object 'ng-waf.status'
OID : 1.3.6.1.4.1.22610.2.4.8.386.1.3

Field Name : statusOperTable
Field Type : TABLE
Field Status : current
Description : NGWAF status from object 'ng-waf.status'
OID : 1.3.6.1.4.1.22610.2.4.8.386.1.2

Field Name : statusOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The statusOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.386.1.2.1

Field Name : statusOperNgwafVersion
Field Type : String
Field Status : current
Description : ngwaf-version
OID : 1.3.6.1.4.1.22610.2.4.8.386.1.2.1.2

Field Name : statusOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.386.1.2.1.1

Field Name : statusOperPartitionListEntry
Field Type : CounterBasedGauge64

Field Status : current
Description : The statusOperPartitionList entry:partition-list
OID : 1.3.6.1.4.1.22610.2.4.8.386.1.3.1

Field Name : statusOperPartitionListTrackedCustomSignal
Field Type : CounterBasedGauge64
Field Status : current
Description : tracked-custom-signal
OID : 1.3.6.1.4.1.22610.2.4.8.386.1.3.1.9

Field Name : statusOperPartitionListCacheEntries
Field Type : CounterBasedGauge64
Field Status : current
Description : cache-entries
OID : 1.3.6.1.4.1.22610.2.4.8.386.1.3.1.8

Field Name : statusOperPartitionListCpu
Field Type : String
Field Status : current
Description : cpu
OID : 1.3.6.1.4.1.22610.2.4.8.386.1.3.1.10

Field Name : statusOperPartitionListSecretAccessKey
Field Type : String
Field Status : current
Description : secret-access-key
OID : 1.3.6.1.4.1.22610.2.4.8.386.1.3.1.7

Field Name : statusOperPartitionListAccessKeyId
Field Type : String
Field Status : current
Description : access-key-id
OID : 1.3.6.1.4.1.22610.2.4.8.386.1.3.1.6

Field Name : statusOperPartitionListAgentName
Field Type : String
Field Status : current
Description : agent-name
OID : 1.3.6.1.4.1.22610.2.4.8.386.1.3.1.5

Field Name : statusOperPartitionListStatus
Field Type : String
Field Status : current
Description : status
OID : 1.3.6.1.4.1.22610.2.4.8.386.1.3.1.4

Field Name : statusOperPartitionListPartitionName
Field Type : String
Field Status : current
Description : partition-name
OID : 1.3.6.1.4.1.22610.2.4.8.386.1.3.1.3

Field Name : statusOperPartitionListPartitionListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.386.1.3.1.2

Field Name : statusOperPartitionListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.386.1.3.1.1

Field Name : serverOperDrsListTable
Field Type : TABLE
Field Status : current
Description : CGNV6 logging Server from object 'cgnv6.server'
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3

Field Name : serverOperDrsListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serverOperDrsList entry:drs-list
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1

Field Name : serverOperDrsListDrsWeight
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-weight
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.28

Field Name : serverOperDrsListDrsPeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-peak-conn
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.27

Field Name : serverOperDrsListDrsTotRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-tot-rev-pkts
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.26

Field Name : serverOperDrsListDrsTotRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-tot-rev-bytes
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.25

Field Name : serverOperDrsListDrsTotFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-tot-fwd-pkts
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.24

Field Name : serverOperDrsListDrsTotFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-tot-fwd-bytes
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.23

Field Name : serverOperDrsListDrsTotReqSuc
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-tot-req-suc

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.22

Field Name : serverOperDrsListDrsTotReq
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-tot-req
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.21

Field Name : serverOperDrsListDrsTotConn
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-tot-conn
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.20

Field Name : serverOperDrsListDrsCurrReq
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-curr-req
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.19

Field Name : serverOperDrsListDrsCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-curr-conn
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.18

Field Name : serverOperDrsListDrsDisable
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-disable
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.17

Field Name : serverOperDrsListDrsCurrObserveRate
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-curr_observe_rate
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.16

Field Name : serverOperDrsListDrsConnRateUnit
Field Type : String
Field Status : current
Description : drs-conn_rate_unit
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.15

Field Name : serverOperDrsListDrsCurrConnRate
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-curr_conn_rate
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.14

Field Name : serverOperDrsListDrsSlowStartConnLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-slow_start_conn_limit
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.13

Field Name : serverOperDrsListDrsIsAutocreate
Field Type : CounterBasedGauge64

Field Status : current
Description : drs-is_autocreate
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.12

Field Name : serverOperDrsListDrsSrvGatewayArp
Field Type : String
Field Status : current
Description : drs-srv_gateway_arp
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.11

Field Name : serverOperDrsListDrsServerTtl
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-server_ttl
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.10

Field Name : serverOperDrsListDrsDnsUpdateTime
Field Type : String
Field Status : current
Description : drs-dns_update_time
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.9

Field Name : serverOperDrsListDrsCreationType
Field Type : String
Field Status : current
Description : drs-creation_type
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.8

Field Name : serverOperDrsListDrsState
Field Type : String
Field Status : current
Description : drs-state
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.7

Field Name : serverOperDrsListDrsServerIpv6Addr
Field Type : String
Field Status : current
Description : drs-server-ipv6-addr
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.6

Field Name : serverOperDrsListDrsHost
Field Type : String
Field Status : current
Description : drs-host
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.5

Field Name : serverOperDrsListDrsName
Field Type : String
Field Status : current
Description : drs-name
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.4

Field Name : serverOperDrsListDrsListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.3

Field Name : serverOperDrsListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.2

Field Name : serverOperDrsListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.1

Field Name : serverOperTable
Field Type : TABLE
Field Status : current
Description : CGNV6 logging Server from object 'cgnv6.server'
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.2

Field Name : serverOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serverOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.2.1

Field Name : serverOperWeight
Field Type : CounterBasedGauge64
Field Status : current
Description : weight
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.2.1.14

Field Name : serverOperDisable
Field Type : CounterBasedGauge64
Field Status : current
Description : disable
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.2.1.13

Field Name : serverOperCurrObserveRate
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_observe_rate
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.2.1.12

Field Name : serverOperConnRateUnit
Field Type : String
Field Status : current
Description : conn_rate_unit
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.2.1.11

Field Name : serverOperCurrConnRate
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_conn_rate
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.2.1.10

Field Name : serverOperSlowStartConnLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : slow_start_conn_limit

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.2.1.9

Field Name : serverOperIsAutocreate
Field Type : CounterBasedGauge64
Field Status : current
Description : is_autocreate
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.2.1.8

Field Name : serverOperSrvGatewayArp
Field Type : String
Field Status : current
Description : srv_gateway_arp
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.2.1.7

Field Name : serverOperServerTtl
Field Type : CounterBasedGauge64
Field Status : current
Description : server_ttl
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.2.1.6

Field Name : serverOperDnsUpdateTime
Field Type : String
Field Status : current
Description : dns_update_time
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.2.1.5

Field Name : serverOperCreationType
Field Type : String
Field Status : current
Description : creation_type
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.2.1.4

Field Name : serverOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.2.1.3

Field Name : serverOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.2.1.2

Field Name : serverOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.2.1.1

Field Name : serverStatsTable
Field Type : TABLE
Field Status : current
Description : CGNV6 logging Server from object 'cgnv6.server'
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.1

Field Name : serverStatsEntry
Field Type : CounterBasedGauge64

Field Status : current
Description : The serverStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.1.1

Field Name : serverStatsPeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : peak-conn
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.1.1.7

Field Name : serverStatsRevPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : rev-pkt
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.1.1.6

Field Name : serverStatsFwdPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : fwd-pkt
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.1.1.5

Field Name : serverStatsTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : total-conn
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.1.1.4

Field Name : serverStatsCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : curr-conn
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.1.1.3

Field Name : serverStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.1.1.2

Field Name : serverStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.1.1.1

Field Name : portOperDrsIpNatListNatPoolAddrListTable
Field Type : TABLE
Field Status : current
Description : Real Server Port from object 'cgnv6.server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.8

Field Name : portOperDrsIpNatListTable
Field Type : TABLE
Field Status : current
Description : Real Server Port from object 'cgnv6.server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.7

Field Name : portOperDrsIpNatListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portOperDrsIpNatList entry:drs-ip-nat-list
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.7.1

Field Name : portOperDrsIpNatListPoolName
Field Type : String
Field Status : current
Description : pool_name
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.7.1.8

Field Name : portOperDrsIpNatListDrsPort
Field Type : CounterBasedGauge64
Field Status : current
Description : drs_port
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.7.1.7

Field Name : portOperDrsIpNatListDrsName
Field Type : String
Field Status : current
Description : drs_name
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.7.1.6

Field Name : portOperDrsIpNatListDrsIpNatListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.7.1.5

Field Name : portOperDrsIpNatListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.7.1.4

Field Name : portOperDrsIpNatListPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.7.1.3

Field Name : portOperDrsIpNatListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.7.1.2

Field Name : portOperDrsIpNatListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.7.1.1

Field Name : portOperNatPoolAddrListTable
Field Type : TABLE
Field Status : current
Description : Real Server Port from object 'cgnv6.server.port'

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.6

Field Name : portOperNatPoolAddrListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portOperNatPoolAddrList entry:nat-pool-addr-list
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.6.1

Field Name : portOperNatPoolAddrListAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : alloc_failed
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.6.1.10

Field Name : portOperNatPoolAddrListPortsFreedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_freed_total
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.6.1.9

Field Name : portOperNatPoolAddrListPortsConsumedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed_total
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.6.1.8

Field Name : portOperNatPoolAddrListPortsConsumed
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.6.1.7

Field Name : portOperNatPoolAddrListNatIp
Field Type : String
Field Status : current
Description : nat_ip
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.6.1.6

Field Name : portOperNatPoolAddrListNatPoolAddrListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.6.1.5

Field Name : portOperNatPoolAddrListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.6.1.4

Field Name : portOperNatPoolAddrListPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.6.1.3

Field Name : portOperNatPoolAddrListName
Field Type : String

Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.6.1.2

Field Name : portOperNatPoolAddrListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.6.1.1

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListTable
Field Type : TABLE
Field Status : current
Description : Real Server Port from object 'cgnv6.server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.5

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portOperDrsAutoNatListDrsAutoNatAddressList entry:drs-auto-nat-address-list
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.5.1

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : alloc_failed
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.5.1.14

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListPortsFreedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_freed_total
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.5.1.13

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListPortsConsumedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed_total
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.5.1.12

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListPortsConsumed
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.5.1.11

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListIpRr
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_rr
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.5.1.10

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListHaGroupId
Field Type : CounterBasedGauge64
Field Status : current
Description : ha_group_id
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.5.1.9

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListVrid
Field Type : CounterBasedGauge64
Field Status : current
Description : vrid
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.5.1.8

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListAutoNatIp
Field Type : String
Field Status : current
Description : auto_nat_ip
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.5.1.7

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListDrsAutoNatAddressListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.5.1.6

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListDrsAutoNatListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.5.1.5

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.5.1.4

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.5.1.3

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.5.1.2

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.5.1.1

Field Name : portOperDrsAutoNatListTable
Field Type : TABLE
Field Status : current
Description : Real Server Port from object 'cgnv6.server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.4

Field Name : portOperDrsAutoNatListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portOperDrsAutoNatList entry:drs-auto-nat-list

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.4.1

Field Name : portOperDrsAutoNatListDrsPort
Field Type : CounterBasedGauge64
Field Status : current
Description : drs_port
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.4.1.7

Field Name : portOperDrsAutoNatListDrsName
Field Type : String
Field Status : current
Description : drs_name
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.4.1.6

Field Name : portOperDrsAutoNatListDrsAutoNatListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.4.1.5

Field Name : portOperDrsAutoNatListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.4.1.4

Field Name : portOperDrsAutoNatListPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.4.1.3

Field Name : portOperDrsAutoNatListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.4.1.2

Field Name : portOperDrsAutoNatListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.4.1.1

Field Name : portOperAutoNatAddrListTable
Field Type : TABLE
Field Status : current
Description : Real Server Port from object 'cgnv6.server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.3

Field Name : portOperAutoNatAddrListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portOperAutoNatAddrList entry:auto-nat-addr-list
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.3.1

Field Name : portOperAutoNatAddrListAllocFailed
Field Type : CounterBasedGauge64

Field Status : current
Description : alloc_failed
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.3.1.13

Field Name : portOperAutoNatAddrListPortsFreedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_freed_total
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.3.1.12

Field Name : portOperAutoNatAddrListPortsConsumedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed_total
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.3.1.11

Field Name : portOperAutoNatAddrListPortsConsumed
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.3.1.10

Field Name : portOperAutoNatAddrListIpRr
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_rr
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.3.1.9

Field Name : portOperAutoNatAddrListHaGroupId
Field Type : CounterBasedGauge64
Field Status : current
Description : ha_group_id
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.3.1.8

Field Name : portOperAutoNatAddrListVrid
Field Type : CounterBasedGauge64
Field Status : current
Description : vrid
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.3.1.7

Field Name : portOperAutoNatAddrListAutoNatIp
Field Type : String
Field Status : current
Description : auto_nat_ip
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.3.1.6

Field Name : portOperAutoNatAddrListAutoNatAddrListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.3.1.5

Field Name : portOperAutoNatAddrListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.3.1.4

Field Name : portOperAutoNatAddrListPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.3.1.3

Field Name : portOperAutoNatAddrListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.3.1.2

Field Name : portOperAutoNatAddrListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.3.1.1

Field Name : portOperTable
Field Type : TABLE
Field Status : current
Description : Real Server Port from object 'cgnv6.server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2

Field Name : portOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1

Field Name : portOperPoolName
Field Type : String
Field Status : current
Description : pool_name
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.23

Field Name : portOperResvConn
Field Type : CounterBasedGauge64
Field Status : current
Description : resv_conn
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.22

Field Name : portOperAflowQueueSize
Field Type : CounterBasedGauge64
Field Status : current
Description : aflow_queue_size
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.21

Field Name : portOperAflowConnLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : aflow_conn_limit
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.20

Field Name : portOperSoftDownTime
Field Type : CounterBasedGauge64
Field Status : current
Description : soft_down_time

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.19

Field Name : portOperHmIndex
Field Type : CounterBasedGauge64
Field Status : current
Description : hm-index
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.18

Field Name : portOperHmKey
Field Type : CounterBasedGauge64
Field Status : current
Description : hm-key
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.17

Field Name : portOperDisable
Field Type : CounterBasedGauge64
Field Status : current
Description : disable
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.16

Field Name : portOperInbandHmReassignNum
Field Type : CounterBasedGauge64
Field Status : current
Description : inband_hm_reassign_num
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.15

Field Name : portOperEsRespTime
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_time
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.14

Field Name : portOperDiameterEnabled
Field Type : CounterBasedGauge64
Field Status : current
Description : diameter_enabled
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.13

Field Name : portOperDownTimeGracePeriod
Field Type : CounterBasedGauge64
Field Status : current
Description : down_time_grace_period
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.12

Field Name : portOperCurrentTime
Field Type : CounterBasedGauge64
Field Status : current
Description : current_time
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.11

Field Name : portOperDownGracePeriodAllowed
Field Type : CounterBasedGauge64
Field Status : current
Description : down_grace_period_allowed
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.10

Field Name : portOperCurrObserveRate
Field Type : CounterBasedGauge64

Field Status : current
Description : curr_observe_rate
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.9

Field Name : portOperSlowStartConnLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : slow_start_conn_limit
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.8

Field Name : portOperConnRateUnit
Field Type : String
Field Status : current
Description : conn_rate_unit
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.7

Field Name : portOperCurrConnRate
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_conn_rate
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.6

Field Name : portOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.5

Field Name : portOperProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.4

Field Name : portOperPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.3

Field Name : portOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.2

Field Name : portOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.1

Field Name : portStatsTable
Field Type : TABLE
Field Status : current
Description : Real Server Port from object 'cgnv6.server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1

Field Name : portStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1

Field Name : portStatsSlowestRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : slowest_rsp_time
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.28

Field Name : portStatsFastestRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : fastest_rsp_time
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.27

Field Name : portStatsResponseTime
Field Type : CounterBasedGauge64
Field Status : current
Description : response_time
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.26

Field Name : portStatsTotalRevPktsInspectedGoodStatusCode
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts_inspected_good_status_code
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.25

Field Name : portStatsTotalRevPktsInspected
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts_inspected
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.24

Field Name : portStatsEsRespInvalidHttp
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_invalid_http
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.23

Field Name : portStatsEsRespCount
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_count
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.22

Field Name : portStatsEsReqCount
Field Type : CounterBasedGauge64
Field Status : current
Description : es_req_count
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.21

Field Name : portStatsEsRespOther
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_other

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.20

Field Name : portStatsEsResp500
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_500
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.19

Field Name : portStatsEsResp400
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_400
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.18

Field Name : portStatsEsResp300
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_300
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.17

Field Name : portStatsEsResp200
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_200
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.16

Field Name : portStatsPeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : peak_conn
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.15

Field Name : portStatsLastTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : last_total_conn
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.14

Field Name : portStatsTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : total_conn
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.13

Field Name : portStatsTotalRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.12

Field Name : portStatsTotalRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.11

Field Name : portStatsTotalFwdPkts
Field Type : CounterBasedGauge64

Field Status : current
Description : total_fwd_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.10

Field Name : portStatsTotalFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total_fwd_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.9

Field Name : portStatsTotalReqSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : total_req_succ
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.8

Field Name : portStatsTotalReq
Field Type : CounterBasedGauge64
Field Status : current
Description : total_req
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.7

Field Name : portStatsCurrReq
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_req
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.6

Field Name : portStatsCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_conn
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.5

Field Name : portStatsProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.4

Field Name : portStatsPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.3

Field Name : portStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.2

Field Name : portStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.1

Field Name : portOperDrsIpNatListNatPoolAddrListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portOperDrsIpNatListNatPoolAddrList entry:nat-pool-addr-list
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.8.1

Field Name : portOperDrsIpNatListNatPoolAddrListAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : alloc_failed
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.8.1.11

Field Name : portOperDrsIpNatListNatPoolAddrListPortsFreedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_freed_total
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.8.1.10

Field Name : portOperDrsIpNatListNatPoolAddrListPortsConsumedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed_total
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.8.1.9

Field Name : portOperDrsIpNatListNatPoolAddrListPortsConsumed
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.8.1.8

Field Name : portOperDrsIpNatListNatPoolAddrListNatIp
Field Type : String
Field Status : current
Description : nat_ip
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.8.1.7

Field Name : portOperDrsIpNatListNatPoolAddrListNatPoolAddrListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.8.1.6

Field Name : portOperDrsIpNatListNatPoolAddrListDrsIpNatListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.8.1.5

Field Name : portOperDrsIpNatListNatPoolAddrListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.8.1.4

Field Name : portOperDrsIpNatListNatPoolAddrListPort
Field Type : Integer32
Field Status : current
Description : port-number

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.8.1.3

Field Name : portOperDrsIpNatListNatPoolAddrListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.8.1.2

Field Name : portOperDrsIpNatListNatPoolAddrListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.8.1.1

Field Name : serviceGroupOperSgmListTable
Field Type : TABLE
Field Status : current
Description : Service Group from object 'cgnv6.service-group'
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.3

Field Name : serviceGroupOperSgmListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceGroupOperSgmList entry:sgm-list
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.3.1

Field Name : serviceGroupOperSgmListSgmPort
Field Type : CounterBasedGauge64
Field Status : current
Description : sgm-port
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.3.1.5

Field Name : serviceGroupOperSgmListSgmName
Field Type : String
Field Status : current
Description : sgm-name
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.3.1.4

Field Name : serviceGroupOperSgmListSgmListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.3.1.3

Field Name : serviceGroupOperSgmListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.3.1.2

Field Name : serviceGroupOperSgmListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.3.1.1

Field Name : serviceGroupOperTable
Field Type : TABLE

Field Status : current
Description : Service Group from object 'cgnv6.service-group'
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.2

Field Name : serviceGroupOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceGroupOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.2.1

Field Name : serviceGroupOperFilter
Field Type : String
Field Status : current
Description : filter
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.2.1.14

Field Name : serviceGroupOperPriAffinityPriority
Field Type : CounterBasedGauge64
Field Status : current
Description : pri_affinity_priority
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.2.1.13

Field Name : serviceGroupOperHmDsrEnableAllVip
Field Type : CounterBasedGauge64
Field Status : current
Description : hm_dsr_enable_all_vip
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.2.1.12

Field Name : serviceGroupOperStatelessType
Field Type : CounterBasedGauge64
Field Status : current
Description : stateless_type
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.2.1.11

Field Name : serviceGroupOperStatelessState
Field Type : CounterBasedGauge64
Field Status : current
Description : stateless_state
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.2.1.10

Field Name : serviceGroupOperStatelessCurrentUsage
Field Type : CounterBasedGauge64
Field Status : current
Description : stateless_current_usage
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.2.1.9

Field Name : serviceGroupOperStatelessCurrentRate
Field Type : CounterBasedGauge64
Field Status : current
Description : stateless_current_rate
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.2.1.8

Field Name : serviceGroupOperServersTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : servers_total
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.2.1.7

Field Name : serviceGroupOperServersDisable
Field Type : CounterBasedGauge64
Field Status : current
Description : servers_disable
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.2.1.6

Field Name : serviceGroupOperServersDown
Field Type : CounterBasedGauge64
Field Status : current
Description : servers_down
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.2.1.5

Field Name : serviceGroupOperServersUp
Field Type : CounterBasedGauge64
Field Status : current
Description : servers_up
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.2.1.4

Field Name : serviceGroupOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.2.1.3

Field Name : serviceGroupOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.2.1.2

Field Name : serviceGroupOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.2.1.1

Field Name : serviceGroupStatsTable
Field Type : TABLE
Field Status : current
Description : Service Group from object 'cgnv6.service-group'
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.1

Field Name : serviceGroupStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceGroupStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.1.1

Field Name : serviceGroupStatsServicePeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : service_peak_conn
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.1.1.5

Field Name : serviceGroupStatsServerSelectionFailReset
Field Type : CounterBasedGauge64
Field Status : current
Description : server_selection_fail_reset

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.1.1.4

Field Name : serviceGroupStatsServerSelectionFailDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : server_selection_fail_drop
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.1.1.3

Field Name : serviceGroupStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.1.1.2

Field Name : serviceGroupStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.1.1.1

Field Name : memberOperAltListTable
Field Type : TABLE
Field Status : current
Description : Service Group Member from object 'cgnv6.service-group.member'
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.4

Field Name : memberOperDrsListTable
Field Type : TABLE
Field Status : current
Description : Service Group Member from object 'cgnv6.service-group.member'
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3

Field Name : memberOperDrsListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The memberOperDrsList entry:drs-list
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1

Field Name : memberOperDrsListDrsSrspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-srsp-time
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.25

Field Name : memberOperDrsListDrsFrspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-frsp-time
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.24

Field Name : memberOperDrsListDrsRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-rsp-time
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.23

Field Name : memberOperDrsListDrsPeakConn
Field Type : CounterBasedGauge64

Field Status : current
Description : drs-peak-conn
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.22

Field Name : memberOperDrsListDrsFwdBts
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-fwd-bts
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.21

Field Name : memberOperDrsListDrsRevBts
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-rev-bts
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.20

Field Name : memberOperDrsListDrsFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-fwd-pkts
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.19

Field Name : memberOperDrsListDrsRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-rev-pkts
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.18

Field Name : memberOperDrsListDrsTotalReqSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-total-req-succ
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.17

Field Name : memberOperDrsListDrsTotalReq
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-total-req
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.16

Field Name : memberOperDrsListDrsCurrReq
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-curr-req
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.15

Field Name : memberOperDrsListDrsTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-total-conn
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.14

Field Name : memberOperDrsListDrsPersConn
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-pers-conn
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.13

Field Name : memberOperDrsListDrsCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-curr-conn
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.12

Field Name : memberOperDrsListDrsPriority
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-priority
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.11

Field Name : memberOperDrsListDrsPort
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-port
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.10

Field Name : memberOperDrsListDrsHmIndex
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-hm-index
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.9

Field Name : memberOperDrsListDrsHmKey
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-hm-key
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.8

Field Name : memberOperDrsListDrsState
Field Type : String
Field Status : current
Description : drs-state
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.7

Field Name : memberOperDrsListDrsName
Field Type : String
Field Status : current
Description : drs-name
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.6

Field Name : memberOperDrsListDrsListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.5

Field Name : memberOperDrsListPort
Field Type : Integer32
Field Status : current
Description : port
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.4

Field Name : memberOperDrsListName
Field Type : String
Field Status : current
Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.3

Field Name : memberOperDrsListServiceGroupName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.2

Field Name : memberOperDrsListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.1

Field Name : memberOperTable
Field Type : TABLE
Field Status : current
Description : Service Group Member from object 'cgnv6.service-group.member'
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.2

Field Name : memberOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The memberOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.2.1

Field Name : memberOperHmIndex
Field Type : CounterBasedGauge64
Field Status : current
Description : hm-index
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.2.1.7

Field Name : memberOperHmKey
Field Type : CounterBasedGauge64
Field Status : current
Description : hm-key
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.2.1.6

Field Name : memberOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.2.1.5

Field Name : memberOperPort
Field Type : Integer32
Field Status : current
Description : port
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.2.1.4

Field Name : memberOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.2.1.3

Field Name : memberOperServiceGroupName
Field Type : String

Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.2.1.2

Field Name : memberOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.2.1.1

Field Name : memberStatsTable
Field Type : TABLE
Field Status : current
Description : Service Group Member from object 'cgnv6.service-group.member'
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1

Field Name : memberStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The memberStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1

Field Name : memberStatsStateFlaps
Field Type : CounterBasedGauge64
Field Status : current
Description : state_flaps
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.24

Field Name : memberStatsCurrConnOverflow
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_conn_overflow
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.23

Field Name : memberStatsTotalSslConn
Field Type : CounterBasedGauge64
Field Status : current
Description : total_ssl_conn
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.22

Field Name : memberStatsCurrSslConn
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_ssl_conn
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.21

Field Name : memberStatsSlowestRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : slowest_rsp_time
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.20

Field Name : memberStatsFastestRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : fastest_rsp_time
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.19

Field Name : memberStatsResponseTime
Field Type : CounterBasedGauge64
Field Status : current
Description : response_time
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.18

Field Name : memberStatsPeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : peak_conn
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.17

Field Name : memberStatsTotalReqSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : total_req_succ
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.16

Field Name : memberStatsTotalReq
Field Type : CounterBasedGauge64
Field Status : current
Description : total_req
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.15

Field Name : memberStatsCurrReq
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_req
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.14

Field Name : memberStatsTotalRevPktsInspectedStatusCodeNon5xx
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts_inspected_status_code_non_5xx
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.13

Field Name : memberStatsTotalRevPktsInspectedStatusCode2xx
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts_inspected_status_code_2xx
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.12

Field Name : memberStatsTotalRevPktsInspected
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts_inspected
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.11

Field Name : memberStatsTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : total_conn
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.10

Field Name : memberStatsTotalRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.9

Field Name : memberStatsTotalRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.8

Field Name : memberStatsTotalFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : total_fwd_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.7

Field Name : memberStatsTotalFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total_fwd_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.6

Field Name : memberStatsCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_conn
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.5

Field Name : memberStatsPort
Field Type : Integer32
Field Status : current
Description : port
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.4

Field Name : memberStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.3

Field Name : memberStatsServiceGroupName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.2

Field Name : memberStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.1

Field Name : memberOperAltListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The memberOperAltList entry:alt-list
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.4.1

Field Name : memberOperAltListAltPeakConn
Field Type : CounterBasedGauge64

Field Status : current
Description : alt-peak-conn
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.4.1.13

Field Name : memberOperAltListAltFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : alt-fwd-pkts
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.4.1.12

Field Name : memberOperAltListAltRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : alt-rev-pkts
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.4.1.11

Field Name : memberOperAltListAltTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : alt-total-conn
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.4.1.10

Field Name : memberOperAltListAltCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : alt-curr-conn
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.4.1.9

Field Name : memberOperAltListAltState
Field Type : String
Field Status : current
Description : alt-state
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.4.1.8

Field Name : memberOperAltListAltPort
Field Type : CounterBasedGauge64
Field Status : current
Description : alt-port
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.4.1.7

Field Name : memberOperAltListAltName
Field Type : String
Field Status : current
Description : alt-name
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.4.1.6

Field Name : memberOperAltListAltListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.4.1.5

Field Name : memberOperAltListPort
Field Type : Integer32
Field Status : current
Description : port
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.4.1.4

Field Name : memberOperAltListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.4.1.3

Field Name : memberOperAltListServiceGroupName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.4.1.2

Field Name : memberOperAltListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.4.1.1

Field Name : ipEntriesOperDdosIpEntriesListTable
Field Type : TABLE
Field Status : current
Description : from object 'cgnv6.ddos-protection.ip-entries'
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3

Field Name : ipEntriesOperTable
Field Type : TABLE
Field Status : current
Description : from object 'cgnv6.ddos-protection.ip-entries'
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.2

Field Name : ipEntriesOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The ipEntriesOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.2.1

Field Name : ipEntriesOperV4Netmask
Field Type : String
Field Status : current
Description : v4-netmask
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.2.1.5

Field Name : ipEntriesOperNatPool
Field Type : String
Field Status : current
Description : nat-pool
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.2.1.4

Field Name : ipEntriesOperAll
Field Type : Integer32
Field Status : current
Description : all
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.2.1.3

Field Name : ipEntriesOperTotalEntries
Field Type : CounterBasedGauge64
Field Status : current
Description : total-entries

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.2.1.2

Field Name : ipEntriesOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.2.1.1

Field Name : ipEntriesOperDdosIpEntriesListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The ipEntriesOperDdosIpEntriesList entry:ddos-ip-entries-list
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3.1

Field Name : ipEntriesOperDdosIpEntriesListHardwareIndex
Field Type : CounterBasedGauge64
Field Status : current
Description : hardware-index
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3.1.15

Field Name : ipEntriesOperDdosIpEntriesListInHardware
Field Type : CounterBasedGauge64
Field Status : current
Description : in-hardware
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3.1.14

Field Name : ipEntriesOperDdosIpEntriesListInBlacklist
Field Type : CounterBasedGauge64
Field Status : current
Description : in-blacklist
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3.1.13

Field Name : ipEntriesOperDdosIpEntriesListTotalPps
Field Type : CounterBasedGauge64
Field Status : current
Description : total-pps
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3.1.12

Field Name : ipEntriesOperDdosIpEntriesListHwL3DropPps
Field Type : CounterBasedGauge64
Field Status : current
Description : hw-l3-drop-pps
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3.1.11

Field Name : ipEntriesOperDdosIpEntriesListSwL3DropPps
Field Type : CounterBasedGauge64
Field Status : current
Description : sw-l3-drop-pps
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3.1.10

Field Name : ipEntriesOperDdosIpEntriesListHwL4DropPps
Field Type : CounterBasedGauge64
Field Status : current
Description : hw-l4-drop-pps
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3.1.9

Field Name : ipEntriesOperDdosIpEntriesListSwL4DropPps
Field Type : CounterBasedGauge64

Field Status : current
Description : sw-l4-drop-pps
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3.1.8

Field Name : ipEntriesOperDdosIpEntriesListSwReceivePps
Field Type : CounterBasedGauge64
Field Status : current
Description : sw-receive-pps
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3.1.7

Field Name : ipEntriesOperDdosIpEntriesListL4EntriesCount
Field Type : CounterBasedGauge64
Field Status : current
Description : l4-entries-count
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3.1.6

Field Name : ipEntriesOperDdosIpEntriesListHints
Field Type : String
Field Status : current
Description : hints
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3.1.5

Field Name : ipEntriesOperDdosIpEntriesListExpiration
Field Type : CounterBasedGauge64
Field Status : current
Description : expiration
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3.1.4

Field Name : ipEntriesOperDdosIpEntriesListV4Address
Field Type : String
Field Status : current
Description : v4-address
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3.1.3

Field Name : ipEntriesOperDdosIpEntriesListDdosIpEntriesListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3.1.2

Field Name : ipEntriesOperDdosIpEntriesListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3.1.1

Field Name : l4EntriesOperDdosL4EntriesListTable
Field Type : TABLE
Field Status : current
Description : from object 'cgnv6.ddos-protection.l4-entries'
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.3

Field Name : l4EntriesOperTable
Field Type : TABLE
Field Status : current
Description : from object 'cgnv6.ddos-protection.l4-entries'
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.2

Field Name : l4EntriesOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The l4EntriesOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.2.1

Field Name : l4EntriesOperNotInHardware
Field Type : Integer32
Field Status : current
Description : not-in-hardware
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.2.1.6

Field Name : l4EntriesOperV4Netmask
Field Type : String
Field Status : current
Description : v4-netmask
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.2.1.5

Field Name : l4EntriesOperNatPool
Field Type : String
Field Status : current
Description : nat-pool
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.2.1.4

Field Name : l4EntriesOperAll
Field Type : Integer32
Field Status : current
Description : all
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.2.1.3

Field Name : l4EntriesOperTotalEntries
Field Type : CounterBasedGauge64
Field Status : current
Description : total-entries
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.2.1.2

Field Name : l4EntriesOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.2.1.1

Field Name : l4EntriesOperDdosL4EntriesListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The l4EntriesOperDdosL4EntriesList entry:ddos-l4-entries-list
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.3.1

Field Name : l4EntriesOperDdosL4EntriesListIsDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : is-deleted
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.3.1.10

Field Name : l4EntriesOperDdosL4EntriesListExpiration
Field Type : CounterBasedGauge64
Field Status : current
Description : expiration

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.3.1.9

Field Name : l4EntriesOperDdosL4EntriesListPps
Field Type : CounterBasedGauge64
Field Status : current
Description : pps
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.3.1.8

Field Name : l4EntriesOperDdosL4EntriesListHardwareIndex
Field Type : CounterBasedGauge64
Field Status : current
Description : hardware-index
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.3.1.7

Field Name : l4EntriesOperDdosL4EntriesListInHardware
Field Type : CounterBasedGauge64
Field Status : current
Description : in-hardware
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.3.1.6

Field Name : l4EntriesOperDdosL4EntriesListPort
Field Type : CounterBasedGauge64
Field Status : current
Description : port
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.3.1.5

Field Name : l4EntriesOperDdosL4EntriesListL4Protocol
Field Type : String
Field Status : current
Description : l4-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.3.1.4

Field Name : l4EntriesOperDdosL4EntriesListV4Address
Field Type : String
Field Status : current
Description : v4-address
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.3.1.3

Field Name : l4EntriesOperDdosL4EntriesListDdosL4EntriesListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.3.1.2

Field Name : l4EntriesOperDdosL4EntriesListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.3.1.1

Field Name : ddosProtectionStatsTable
Field Type : TABLE
Field Status : current
Description : Configure CGNV6 DDoS Protection from object 'cgnv6.ddos-protection'
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1

Field Name : ddosProtectionStatsEntry
Field Type : CounterBasedGauge64

Field Status : current
Description : The ddosProtectionStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1

Field Name : ddosProtectionStatsSynCookieConnSetupFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : syn_cookie_conn_setup_failed
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.40

Field Name : ddosProtectionStatsSynCookieVerificationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : syn_cookie_verification_failed
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.39

Field Name : ddosProtectionStatsSynCookieVerificationPassed
Field Type : CounterBasedGauge64
Field Status : current
Description : syn_cookie_verification_passed
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.38

Field Name : ddosProtectionStatsSynCookieSynAckSent
Field Type : CounterBasedGauge64
Field Status : current
Description : syn_cookie_syn_ack_sent
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.37

Field Name : ddosProtectionStatsL3EntryAddToHwFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : l3_entry_add_to_hw_failure
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.36

Field Name : ddosProtectionStatsL3EntryRemoveFromBgpFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : l3_entry_remove_from_bgp_failure
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.35

Field Name : ddosProtectionStatsL3EntryAddToBgpFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : l3_entry_add_to_bgp_failure
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.34

Field Name : ddosProtectionStatsEntryInvalidated
Field Type : CounterBasedGauge64
Field Status : current
Description : entry_invalidated
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.33

Field Name : ddosProtectionStatsEntryAddedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : entry_added_shadow
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.32

Field Name : ddosProtectionStatsIpOtherBlockAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_other_block_alloc_failure
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.31

Field Name : ddosProtectionStatsIpOtherBlockFree
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_other_block_free
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.30

Field Name : ddosProtectionStatsIpOtherBlockAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_other_block_alloc
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.29

Field Name : ddosProtectionStatsIpPortBlockAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_port_block_alloc_failure
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.28

Field Name : ddosProtectionStatsIpPortBlockFree
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_port_block_free
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.27

Field Name : ddosProtectionStatsIpPortBlockAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_port_block_alloc
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.26

Field Name : ddosProtectionStatsIpNodeAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_node_alloc_failure
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.25

Field Name : ddosProtectionStatsIpNodeFree
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_node_free
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.24

Field Name : ddosProtectionStatsIpNodeAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_node_alloc
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.23

Field Name : ddosProtectionStatsL4EntryListAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : l4_entry_list_alloc_failure

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.22

Field Name : ddosProtectionStatsL4EntryListFree
Field Type : CounterBasedGauge64
Field Status : current
Description : l4_entry_list_free
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.21

Field Name : ddosProtectionStatsL4EntryListAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : l4_entry_list_alloc
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.20

Field Name : ddosProtectionStatsL4EntryDropMaxHwExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : l4_entry_drop_max_hw_exceeded
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.19

Field Name : ddosProtectionStatsL4EntryMatchDropHw
Field Type : CounterBasedGauge64
Field Status : current
Description : l4_entry_match_drop_hw
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.18

Field Name : ddosProtectionStatsL4EntryMatchDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : l4_entry_match_drop
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.17

Field Name : ddosProtectionStatsL4HwOutOfEntries
Field Type : CounterBasedGauge64
Field Status : current
Description : l4_hw_out_of_entries
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.16

Field Name : ddosProtectionStatsL4EntryRemovedFromHw
Field Type : CounterBasedGauge64
Field Status : current
Description : l4_entry_removed_from_hw
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.15

Field Name : ddosProtectionStatsL4EntryAddedToHw
Field Type : CounterBasedGauge64
Field Status : current
Description : l4_entry_added_to_hw
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.14

Field Name : ddosProtectionStatsL4EntryDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : l4_entry_deleted
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.13

Field Name : ddosProtectionStatsL4EntryAdded
Field Type : CounterBasedGauge64

Field Status : current
Description : l4_entry_added
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.12

Field Name : ddosProtectionStatsL3EntryDropMaxHwExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : l3_entry_drop_max_hw_exceeded
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.11

Field Name : ddosProtectionStatsL3EntryMatchDropHw
Field Type : CounterBasedGauge64
Field Status : current
Description : l3_entry_match_drop_hw
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.10

Field Name : ddosProtectionStatsL3EntryMatchDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : l3_entry_match_drop
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.9

Field Name : ddosProtectionStatsL3EntryTooMany
Field Type : CounterBasedGauge64
Field Status : current
Description : l3_entry_too_many
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.8

Field Name : ddosProtectionStatsL3EntryRemovedFromHw
Field Type : CounterBasedGauge64
Field Status : current
Description : l3_entry_removed_from_hw
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.7

Field Name : ddosProtectionStatsL3EntryAddedToHw
Field Type : CounterBasedGauge64
Field Status : current
Description : l3_entry_added_to_hw
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.6

Field Name : ddosProtectionStatsL3EntryRemovedFromBgp
Field Type : CounterBasedGauge64
Field Status : current
Description : l3_entry_removed_from_bgp
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.5

Field Name : ddosProtectionStatsL3EntryAddedToBgp
Field Type : CounterBasedGauge64
Field Status : current
Description : l3_entry_added_to_bgp
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.4

Field Name : ddosProtectionStatsL3EntryDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : l3_entry_deleted
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.3

Field Name : ddosProtectionStatsL3EntryAdded
Field Type : CounterBasedGauge64
Field Status : current
Description : l3_entry_added
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.2

Field Name : ddosProtectionStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.1

Field Name : disableNatIpByBgpOperDdosDisabledByBgpEntriesListTable
Field Type : TABLE
Field Status : current
Description : from object 'cgnv6.ddos-protection.disable-nat-ip-by-bgp'
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.4.3

Field Name : disableNatIpByBgpOperTable
Field Type : TABLE
Field Status : current
Description : from object 'cgnv6.ddos-protection.disable-nat-ip-by-bgp'
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.4.2

Field Name : disableNatIpByBgpOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The disableNatIpByBgpOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.4.2.1

Field Name : disableNatIpByBgpOperV4Address
Field Type : String
Field Status : current
Description : v4-address
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.4.2.1.4

Field Name : disableNatIpByBgpOperAll
Field Type : Integer32
Field Status : current
Description : all
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.4.2.1.3

Field Name : disableNatIpByBgpOperTotalEntries
Field Type : CounterBasedGauge64
Field Status : current
Description : total-entries
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.4.2.1.2

Field Name : disableNatIpByBgpOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.4.2.1.1

Field Name : disableNatIpByBgpOperDdosDisabledByBgpEntriesListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The disableNatIpByBgpOperDdosDisabledByBgpEntriesList entry:ddos-disabled-by-bgp-entries-list

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.4.3.1

Field Name : disableNatIpByBgpOperDdosDisabledByBgpEntriesListNatPoolName
Field Type : String
Field Status : current
Description : nat-pool-name
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.4.3.1.4

Field Name : disableNatIpByBgpOperDdosDisabledByBgpEntriesListV4Address
Field Type : String
Field Status : current
Description : v4-address
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.4.3.1.3

Field Name : disableNatIpByBgpOperDdosDisabledByBgpEntriesListDdosDisabledByBgpEntriesListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.4.3.1.2

Field Name : disableNatIpByBgpOperDdosDisabledByBgpEntriesListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.4.3.1.1

Field Name : sharedServiceGroupOperSharedServiceGroupListTable
Field Type : TABLE
Field Status : current
Description : CGNv6 Shared Service Group from object 'cgnv6.shared-service-group'
OID : 1.3.6.1.4.1.22610.2.4.8.412.1.2

Field Name : sharedServiceGroupOperSharedServiceGroupListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The sharedServiceGroupOperSharedServiceGroupList entry:shared-service-group-list
OID : 1.3.6.1.4.1.22610.2.4.8.412.1.2.1

Field Name : sharedServiceGroupOperSharedServiceGroupListServiceGroupName
Field Type : String
Field Status : current
Description : service-group-name
OID : 1.3.6.1.4.1.22610.2.4.8.412.1.2.1.3

Field Name : sharedServiceGroupOperSharedServiceGroupListSharedServiceGroupListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.412.1.2.1.2

Field Name : sharedServiceGroupOperSharedServiceGroupListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.412.1.2.1.1

Field Name : tcpSvrStatusOperTcpSvrListTable
Field Type : TABLE

Field Status : current
Description : from object 'cgnv6.logging.tcp-svr-status'
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.3.2

Field Name : tcpSvrStatusOperTcpSvrListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The tcpSvrStatusOperTcpSvrList entry:tcp-svr-list
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.3.2.1

Field Name : tcpSvrStatusOperTcpSvrListStatus
Field Type : String
Field Status : current
Description : status
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.3.2.1.8

Field Name : tcpSvrStatusOperTcpSvrListNumCpus
Field Type : CounterBasedGauge64
Field Status : current
Description : num-cpus
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.3.2.1.7

Field Name : tcpSvrStatusOperTcpSvrListOverallStatus
Field Type : CounterBasedGauge64
Field Status : current
Description : overall-status
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.3.2.1.6

Field Name : tcpSvrStatusOperTcpSvrListServerPort
Field Type : CounterBasedGauge64
Field Status : current
Description : server-port
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.3.2.1.5

Field Name : tcpSvrStatusOperTcpSvrListServerName
Field Type : String
Field Status : current
Description : server-name
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.3.2.1.4

Field Name : tcpSvrStatusOperTcpSvrListTemplate
Field Type : String
Field Status : current
Description : template
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.3.2.1.3

Field Name : tcpSvrStatusOperTcpSvrListTcpSvrListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.3.2.1.2

Field Name : tcpSvrStatusOperTcpSvrListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.3.2.1.1

Field Name : sourceAddressOperSourceAddressListTable
Field Type : TABLE
Field Status : current
Description : from object 'cgnv6.logging.source-address'
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.2.2

Field Name : sourceAddressOperSourceAddressListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The sourceAddressOperSourceAddressList entry:source-address-list
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.2.2.1

Field Name : sourceAddressOperSourceAddressListUdpFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : udp-failed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.2.2.1.12

Field Name : sourceAddressOperSourceAddressListUdpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : udp-freed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.2.2.1.11

Field Name : sourceAddressOperSourceAddressListUdpAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : udp-allocated
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.2.2.1.10

Field Name : sourceAddressOperSourceAddressListUdpTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : udp-total
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.2.2.1.9

Field Name : sourceAddressOperSourceAddressListTcpFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-failed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.2.2.1.8

Field Name : sourceAddressOperSourceAddressListTcpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-freed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.2.2.1.7

Field Name : sourceAddressOperSourceAddressListTcpAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-allocated
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.2.2.1.6

Field Name : sourceAddressOperSourceAddressListTcpTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-total

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.2.2.1.5

Field Name : sourceAddressOperSourceAddressListRefCount
Field Type : CounterBasedGauge64
Field Status : current
Description : ref-count
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.2.2.1.4

Field Name : sourceAddressOperSourceAddressListSourceAddress
Field Type : String
Field Status : current
Description : source-address
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.2.2.1.3

Field Name : sourceAddressOperSourceAddressListSourceAddressListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.2.2.1.2

Field Name : sourceAddressOperSourceAddressListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.2.2.1.1

Field Name : loggingStatsTable
Field Type : TABLE
Field Status : current
Description : CGNV6 Logging Statistics from object 'cgnv6.logging'
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1

Field Name : loggingStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The loggingStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1

Field Name : loggingStatsIddosL4EntryDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : iddos-l4-entry-delete
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.84

Field Name : loggingStatsIddosL4EntryCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : iddos-l4-entry-create
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.83

Field Name : loggingStatsIddosL3EntryDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : iddos-l3-entry-delete
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.82

Field Name : loggingStatsIddosL3EntryCreate
Field Type : CounterBasedGauge64

Field Status : current
Description : iddos-l3-entry-create
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.81

Field Name : loggingStatsHttpSpmFreeType4
Field Type : CounterBasedGauge64
Field Status : current
Description : http-spm-free-type4
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.80

Field Name : loggingStatsHttpSpmFreeType3
Field Type : CounterBasedGauge64
Field Status : current
Description : http-spm-free-type3
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.79

Field Name : loggingStatsHttpSpmFreeType2
Field Type : CounterBasedGauge64
Field Status : current
Description : http-spm-free-type2
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.78

Field Name : loggingStatsHttpSpmFreeType1
Field Type : CounterBasedGauge64
Field Status : current
Description : http-spm-free-type1
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.77

Field Name : loggingStatsHttpSpmFreeType0
Field Type : CounterBasedGauge64
Field Status : current
Description : http-spm-free-type0
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.76

Field Name : loggingStatsHttpSpmAllocType4
Field Type : CounterBasedGauge64
Field Status : current
Description : http-spm-alloc-type4
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.75

Field Name : loggingStatsHttpSpmAllocType3
Field Type : CounterBasedGauge64
Field Status : current
Description : http-spm-alloc-type3
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.74

Field Name : loggingStatsHttpSpmAllocType2
Field Type : CounterBasedGauge64
Field Status : current
Description : http-spm-alloc-type2
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.73

Field Name : loggingStatsHttpSpmAllocType1
Field Type : CounterBasedGauge64
Field Status : current
Description : http-spm-alloc-type1
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.72

Field Name : loggingStatsHttpSpmAllocType0
Field Type : CounterBasedGauge64
Field Status : current
Description : http-spm-alloc-type0
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.71

Field Name : loggingStatsHttpMfree
Field Type : CounterBasedGauge64
Field Status : current
Description : http-mfree
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.70

Field Name : loggingStatsHttpMalloc
Field Type : CounterBasedGauge64
Field Status : current
Description : http-malloc
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.69

Field Name : loggingStatsHttpFragMergeFailedDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : http-frag-merge-failed-dropped
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.68

Field Name : loggingStatsHttpAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : http-alloc-failed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.67

Field Name : loggingStatsHttpOutOfOrderDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : http-out-of-order-dropped
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.66

Field Name : loggingStatsLogMessageTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : log-message-too-long
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.65

Field Name : loggingStatsPortBlockAccountingAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : port-block-accounting-allocated
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.64

Field Name : loggingStatsPortBlockAccountingFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : port-block-accounting-freed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.63

Field Name : loggingStatsUdpPortBatchInterimUpdated
Field Type : CounterBasedGauge64
Field Status : current
Description : udp-port-batch-interim-updated

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.62

Field Name : loggingStatsTcpPortBatchInterimUpdated
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-port-batch-interim-updated
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.61

Field Name : loggingStatsInterimUpdateNoBuffRetried
Field Type : CounterBasedGauge64
Field Status : current
Description : interim-update-no-buff-retried
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.60

Field Name : loggingStatsInterimUpdateMemoryFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : interim-update-memory-freed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.59

Field Name : loggingStatsInterimUpdateTerminated
Field Type : CounterBasedGauge64
Field Status : current
Description : interim-update-terminated
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.58

Field Name : loggingStatsInterimUpdateScheduleFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : interim-update-schedule-failed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.57

Field Name : loggingStatsInterimUpdateScheduled
Field Type : CounterBasedGauge64
Field Status : current
Description : interim-update-scheduled
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.56

Field Name : loggingStatsIpv6FragFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-frag-failed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.55

Field Name : loggingStatsIpv6FragApplied
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-frag-applied
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.54

Field Name : loggingStatsIpv4FragFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-frag-failed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.53

Field Name : loggingStatsIpv4FragApplied
Field Type : CounterBasedGauge64

Field Status : current
Description : ipv4-frag-applied
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.52

Field Name : loggingStatsConnTcpCreateFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : conn-tcp-create-failed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.51

Field Name : loggingStatsRtspPortFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : rtsp-port-freed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.50

Field Name : loggingStatsRtspPortAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : rtsp-port-allocated
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.49

Field Name : loggingStatsAddMsgFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : add-msg-failed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.48

Field Name : loggingStatsOutOfBuffers
Field Type : CounterBasedGauge64
Field Status : current
Description : out-of-buffers
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.47

Field Name : loggingStatsReducedLogsByDestination
Field Type : CounterBasedGauge64
Field Status : current
Description : reduced-logs-by-destination
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.46

Field Name : loggingStatsHttpRequestLogged
Field Type : CounterBasedGauge64
Field Status : current
Description : http-request-logged
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.45

Field Name : loggingStatsUdpPortOverloadingFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : udp-port-overloading-freed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.44

Field Name : loggingStatsUdpPortOverloadingAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : udp-port-overloading-allocated
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.43

Field Name : loggingStatsTcpPortOverloadingFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-port-overloading-freed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.42

Field Name : loggingStatsTcpPortOverloadingAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-port-overloading-allocated
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.41

Field Name : loggingStatsConnTcpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : conn-tcp-dropped
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.40

Field Name : loggingStatsConnTcpEstablished
Field Type : CounterBasedGauge64
Field Status : current
Description : conn-tcp-established
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.39

Field Name : loggingStatsLogDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : log-dropped
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.38

Field Name : loggingStatsLogSent
Field Type : CounterBasedGauge64
Field Status : current
Description : log-sent
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.37

Field Name : loggingStatsEnhancedUserLog
Field Type : CounterBasedGauge64
Field Status : current
Description : enhanced-user-log
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.36

Field Name : loggingStatsFixedNatInterimUpdated
Field Type : CounterBasedGauge64
Field Status : current
Description : fixed-nat-interim-updated
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.35

Field Name : loggingStatsFixedNatPeriodicConfigLogged
Field Type : CounterBasedGauge64
Field Status : current
Description : fixed-nat-periodic-config-logged
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.34

Field Name : loggingStatsFixedNatPeriodicConfigLogsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : fixed-nat-periodic-config-logs-sent

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.33

Field Name : loggingStatsFixedNatDisableConfigLogsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : fixed-nat-disable-config-logs-sent
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.32

Field Name : loggingStatsFixedNatDisableConfigLogged
Field Type : CounterBasedGauge64
Field Status : current
Description : fixed-nat-disable-config-logged
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.31

Field Name : loggingStatsFixedNatUserPorts
Field Type : CounterBasedGauge64
Field Status : current
Description : fixed-nat-user-ports
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.30

Field Name : loggingStatsEspResourceFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : esp-resource-freed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.29

Field Name : loggingStatsEspResourceAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : esp-resource-allocated
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.28

Field Name : loggingStatsEspSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : esp-session-deleted
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.27

Field Name : loggingStatsEspSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : esp-session-created
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.26

Field Name : loggingStatsGreResourceFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : gre-resource-freed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.25

Field Name : loggingStatsGreResourceAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : gre-resource-allocated
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.24

Field Name : loggingStatsGreSessionDeleted
Field Type : CounterBasedGauge64

Field Status : current
Description : gre-session-deleted
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.23

Field Name : loggingStatsGreSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : gre-session-created
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.22

Field Name : loggingStatsIcmpv6ResourceFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : icmpv6-resource-freed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.21

Field Name : loggingStatsIcmpv6ResourceAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : icmpv6-resource-allocated
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.20

Field Name : loggingStatsIcmpv6SessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : icmpv6-session-deleted
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.19

Field Name : loggingStatsIcmpv6SessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : icmpv6-session-created
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.18

Field Name : loggingStatsIcmpResourceFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-resource-freed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.17

Field Name : loggingStatsIcmpResourceAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-resource-allocated
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.16

Field Name : loggingStatsIcmpSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-session-deleted
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.15

Field Name : loggingStatsIcmpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-session-created
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.14

Field Name : loggingStatsUdpPortBatchFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : udp-port-batch-freed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.13

Field Name : loggingStatsUdpPortBatchAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : udp-port-batch-allocated
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.12

Field Name : loggingStatsUdpPortFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : udp-port-freed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.11

Field Name : loggingStatsUdpPortAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : udp-port-allocated
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.10

Field Name : loggingStatsUdpSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : udp-session-deleted
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.9

Field Name : loggingStatsUdpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : udp-session-created
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.8

Field Name : loggingStatsTcpPortBatchFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-port-batch-freed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.7

Field Name : loggingStatsTcpPortBatchAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-port-batch-allocated
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.6

Field Name : loggingStatsTcpPortFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-port-freed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.5

Field Name : loggingStatsTcpPortAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-port-allocated

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.4

Field Name : loggingStatsTcpSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-session-deleted
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.3

Field Name : loggingStatsTcpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-session-created
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.2

Field Name : loggingStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.1

Field Name : l4StatsTable
Field Type : TABLE
Field Status : current
Description : CGNV6 L4 Statistics from object 'cgnv6.l4'
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1

Field Name : l4StatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The l4Stats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1

Field Name : l4StatsFwNextActionIncorrectDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : fw-next-action-incorrect-drop
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.64

Field Name : l4StatsNatRangeListAclPermit
Field Type : CounterBasedGauge64
Field Status : current
Description : nat-range-list-acl-permit
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.63

Field Name : l4StatsNatRangeListAclDeny
Field Type : CounterBasedGauge64
Field Status : current
Description : nat-range-list-acl-deny
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.62

Field Name : l4StatsFwZoneMismatchReroutingDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : fw-zone-mismatch-rerouting-drop
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.61

Field Name : l4StatsL3Ipv6DstInvalidUnicast
Field Type : CounterBasedGauge64

Field Status : current
Description : l3-ipv6-dst-invalid-unicast
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.60

Field Name : l4StatsL3Ipv6SrcInvalidUnicast
Field Type : CounterBasedGauge64
Field Status : current
Description : l3-ipv6-src-invalid-unicast
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.59

Field Name : l4StatsL3IpDstInvalidUnicast
Field Type : CounterBasedGauge64
Field Status : current
Description : l3-ip-dst-invalid-unicast
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.58

Field Name : l4StatsL3IpSrcInvalidUnicast
Field Type : CounterBasedGauge64
Field Status : current
Description : l3-ip-src-invalid-unicast
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.57

Field Name : l4StatsDstNatPoolNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : dst-nat-pool-not-found
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.56

Field Name : l4StatsSrcNatPoolNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : src-nat-pool-not-found
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.55

Field Name : l4StatsIpUnknownProcess
Field Type : CounterBasedGauge64
Field Status : current
Description : ip-unknown-process
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.54

Field Name : l4StatsFwMatchNoRuleDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : fw-match-no-rule-drop
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.53

Field Name : l4StatsProcessError
Field Type : CounterBasedGauge64
Field Status : current
Description : process-error
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.52

Field Name : l4StatsProcessContinue
Field Type : CounterBasedGauge64
Field Status : current
Description : process-continue
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.51

Field Name : l4StatsProcessSpecial
Field Type : CounterBasedGauge64
Field Status : current
Description : process-special
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.50

Field Name : l4StatsPreprocessError
Field Type : CounterBasedGauge64
Field Status : current
Description : preprocess-error
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.49

Field Name : l4StatsProcessL4
Field Type : CounterBasedGauge64
Field Status : current
Description : process-l4
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.48

Field Name : l4StatsStaticNatFree
Field Type : CounterBasedGauge64
Field Status : current
Description : static-nat-free
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.47

Field Name : l4StatsStaticNatAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : static-nat-alloc
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.46

Field Name : l4StatsTcpRstLoopDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-rst-loop-drop
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.45

Field Name : l4StatsInvalidNat64TranslatedAddr
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid-nat64-translated-addr
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.44

Field Name : l4StatsDstNatNeededDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : dst-nat-needed-drop
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.43

Field Name : l4StatsStaticNatFastSetupErr
Field Type : CounterBasedGauge64
Field Status : current
Description : static-nat-fast-setup-err
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.42

Field Name : l4StatsStaticNatFastSetup
Field Type : CounterBasedGauge64
Field Status : current
Description : static-nat-fast-setup

OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.41

Field Name : l4StatsFixedNatFastSetupMtuTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : fixed-nat-fast-setup-mtu-too-small
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.40

Field Name : l4StatsFixedNatFastSetupDelayedErr
Field Type : CounterBasedGauge64
Field Status : current
Description : fixed-nat-fast-setup-delayed-err
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.39

Field Name : l4StatsFixedNatDsliteFastSetupErr
Field Type : CounterBasedGauge64
Field Status : current
Description : fixed-nat-dslite-fast-setup-err
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.38

Field Name : l4StatsFixedNatDsliteFastSetup
Field Type : CounterBasedGauge64
Field Status : current
Description : fixed-nat-dslite-fast-setup
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.37

Field Name : l4StatsFixedNat64FastSetupErr
Field Type : CounterBasedGauge64
Field Status : current
Description : fixed-nat64-fast-setup-err
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.36

Field Name : l4StatsFixedNat64FastSetup
Field Type : CounterBasedGauge64
Field Status : current
Description : fixed-nat64-fast-setup
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.35

Field Name : l4StatsFixedNat44FastSetupErr
Field Type : CounterBasedGauge64
Field Status : current
Description : fixed-nat44-fast-setup-err
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.34

Field Name : l4StatsFixedNat44FastSetup
Field Type : CounterBasedGauge64
Field Status : current
Description : fixed-nat44-fast-setup
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.33

Field Name : l4StatsFastSetupMtuTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : fast-setup-mtu-too-small
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.32

Field Name : l4StatsFastSetupDelayedErr
Field Type : CounterBasedGauge64

Field Status : current
Description : fast-setup-delayed-err
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.31

Field Name : l4StatsDsliteFastSetupErr
Field Type : CounterBasedGauge64
Field Status : current
Description : dslite-fast-setup-err
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.30

Field Name : l4StatsDsliteFastSetup
Field Type : CounterBasedGauge64
Field Status : current
Description : dslite-fast-setup
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.29

Field Name : l4StatsNat64FastSetupErr
Field Type : CounterBasedGauge64
Field Status : current
Description : nat64-fast-setup-err
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.28

Field Name : l4StatsNat64FastSetup
Field Type : CounterBasedGauge64
Field Status : current
Description : nat64-fast-setup
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.27

Field Name : l4StatsLsnFastSetupErr
Field Type : CounterBasedGauge64
Field Status : current
Description : lsn-fast-setup-err
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.26

Field Name : l4StatsLsnFastSetup
Field Type : CounterBasedGauge64
Field Status : current
Description : lsn-fast-setup
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.25

Field Name : l4StatsCrossCpuAlgGrePreprocessErr
Field Type : CounterBasedGauge64
Field Status : current
Description : cross-cpu-alg-gre-preprocess-err
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.24

Field Name : l4StatsCrossCpuAlgGreNoMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : cross-cpu-alg-gre-no-match
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.23

Field Name : l4StatsTtlExceededSent
Field Type : CounterBasedGauge64
Field Status : current
Description : ttl-exceeded-sent
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.22

Field Name : l4StatsOutOfStateDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : out-of-state-dropped
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.21

Field Name : l4StatsIcmpv6ReplySent
Field Type : CounterBasedGauge64
Field Status : current
Description : icmpv6-reply-sent
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.20

Field Name : l4StatsIcmpReplySent
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-reply-sent
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.19

Field Name : l4StatsSpecialIpv6NoRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : special-ipv6-no-route
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.18

Field Name : l4StatsSpecialIpv4NoRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : special-ipv4-no-route
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.17

Field Name : l4StatsBadL3Protocol
Field Type : CounterBasedGauge64
Field Status : current
Description : bad-l3-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.16

Field Name : l4StatsRateDropResetUnkn
Field Type : CounterBasedGauge64
Field Status : current
Description : rate_drop_reset_unkn
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.15

Field Name : l4StatsIpv6DstInvalidUnicast
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-dst-invalid-unicast
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.14

Field Name : l4StatsIpv6SrcInvalidUnicast
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-src-invalid-unicast
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.13

Field Name : l4StatsIpDstInvalidUnicast
Field Type : CounterBasedGauge64
Field Status : current
Description : ip-dst-invalid-unicast

OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.12

Field Name : l4StatsIpSrcInvalidUnicast
Field Type : CounterBasedGauge64
Field Status : current
Description : ip-src-invalid-unicast
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.11

Field Name : l4StatsIpipTruncated
Field Type : CounterBasedGauge64
Field Status : current
Description : ipip-truncated
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.10

Field Name : l4StatsIcmpReplyNoSessionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-reply-no-session-drop
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.9

Field Name : l4StatsIcmpHostUnreachableSent
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-host-unreachable-sent
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.8

Field Name : l4StatsIcmpFilteredSent
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-filtered-sent
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.7

Field Name : l4StatsIpipIcmpReplySent
Field Type : CounterBasedGauge64
Field Status : current
Description : ipip-icmp-reply-sent
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.6

Field Name : l4StatsTcpRstSent
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-rst-sent
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.5

Field Name : l4StatsOutOfSessionMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : out-of-session-memory
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.4

Field Name : l4StatsNoRevRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : no-rev-route
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.3

Field Name : l4StatsNoFwdRoute
Field Type : CounterBasedGauge64

Field Status : current
Description : no-fwd-route
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.2

Field Name : l4StatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.1

Field Name : icmpStatsTable
Field Type : TABLE
Field Status : current
Description : CGNV6 ICMP Statistics from object 'cgnv6.icmp'
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1

Field Name : icmpStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The icmpStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1

Field Name : icmpStatsErrorIpMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : error-ip-mismatch
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.38

Field Name : icmpStatsErrorToPoolDropV6
Field Type : CounterBasedGauge64
Field Status : current
Description : error-to-pool-drop-v6
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.37

Field Name : icmpStatsEchoToPoolDropV6
Field Type : CounterBasedGauge64
Field Status : current
Description : echo-to-pool-drop-v6
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.36

Field Name : icmpStatsEchoToPoolReplyV6
Field Type : CounterBasedGauge64
Field Status : current
Description : echo-to-pool-reply-v6
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.35

Field Name : icmpStatsErrorToPoolDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : error-to-pool-drop
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.34

Field Name : icmpStatsEchoToPoolDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : echo-to-pool-drop
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.33

Field Name : icmpStatsEchoToPoolReply
Field Type : CounterBasedGauge64
Field Status : current
Description : echo-to-pool-reply
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.32

Field Name : icmpStatsStaticNat
Field Type : CounterBasedGauge64
Field Status : current
Description : static-nat
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.31

Field Name : icmpStatsIcmpv6ToIcmpv6UnknownL4
Field Type : CounterBasedGauge64
Field Status : current
Description : icmpv6-to-icmpv6-unknown-l4
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.30

Field Name : icmpStatsIcmpv6ToIcmpUnknownL4
Field Type : CounterBasedGauge64
Field Status : current
Description : icmpv6-to-icmp-unknown-l4
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.29

Field Name : icmpStatsIcmpToIcmpv6UnknownL4
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-to-icmpv6-unknown-l4
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.28

Field Name : icmpStatsIcmpToIcmpUnknownL4
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-to-icmp-unknown-l4
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.27

Field Name : icmpStatsEncapCrossCpuPreprocessErr
Field Type : CounterBasedGauge64
Field Status : current
Description : encap-cross-cpu-preprocess-err
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.26

Field Name : icmpStatsEncapCrossCpuNoMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : encap-cross-cpu-no-match
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.25

Field Name : icmpStatsIcmpv6ToIcmpv6Err
Field Type : CounterBasedGauge64
Field Status : current
Description : icmpv6-to-icmpv6-err
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.24

Field Name : icmpStatsIcmpv6ToIcmpErr
Field Type : CounterBasedGauge64
Field Status : current
Description : icmpv6-to-icmp-err

OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.23

Field Name : icmpStatsIcmpToIcmpv6Err
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-to-icmpv6-err
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.22

Field Name : icmpStatsIcmpToIcmpErr
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-to-icmp-err
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.21

Field Name : icmpStats46BadEncapIpHeaderLen
Field Type : CounterBasedGauge64
Field Status : current
Description : 46-bad-encap-ip-header-len
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.20

Field Name : icmpStats46NoPrefixForIpv4
Field Type : CounterBasedGauge64
Field Status : current
Description : 46-no-prefix-for-ipv4
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.19

Field Name : icmpStats46UnknownDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : 46-unknown-drop
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.18

Field Name : icmpStats46KnownDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : 46-known-drop
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.17

Field Name : icmpStats64MidpointHop
Field Type : CounterBasedGauge64
Field Status : current
Description : 64-midpoint-hop
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.16

Field Name : icmpStats64UnknownDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : 64-unknown-drop
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.15

Field Name : icmpStats64KnownDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : 64-known-drop
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.14

Field Name : icmpStatsIcmpv6BadType
Field Type : CounterBasedGauge64

Field Status : current
Description : icmpv6-bad-type
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.13

Field Name : icmpStatsIcmpBadType
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-bad-type
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.12

Field Name : icmpStatsIcmpv6ToIcmpv6
Field Type : CounterBasedGauge64
Field Status : current
Description : icmpv6-to-icmpv6
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.11

Field Name : icmpStatsIcmpv6ToIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : icmpv6-to-icmp
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.10

Field Name : icmpStatsIcmpToIcmpv6
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-to-icmpv6
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.9

Field Name : icmpStatsIcmpToIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-to-icmp
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.8

Field Name : icmpStatsIcmpv6NoSessionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : icmpv6-no-session-drop
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.7

Field Name : icmpStatsIcmpv6NoPortInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : icmpv6-no-port-info
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.6

Field Name : icmpStatsIcmpv6UnknownType
Field Type : CounterBasedGauge64
Field Status : current
Description : icmpv6-unknown-type
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.5

Field Name : icmpStatsIcmpNoSessionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-no-session-drop
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.4

Field Name : icmpStatsIcmpNoPortInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-no-port-info
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.3

Field Name : icmpStatsIcmpUnknownType
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-unknown-type
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.2

Field Name : icmpStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.1

Field Name : httpAlgStatsTable
Field Type : TABLE
Field Status : current
Description : HTTP-ALG Statistics from object 'cgnv6.http-alg'
OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1

Field Name : httpAlgStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The httpAlgStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1

Field Name : httpAlgStatsNoQueue
Field Type : CounterBasedGauge64
Field Status : current
Description : no-queue
OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.20

Field Name : httpAlgStatsHeaderRemovalFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : header-removal-failed
OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.19

Field Name : httpAlgStatsHeaderInsertionFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : header-insertion-failed
OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.18

Field Name : httpAlgStatsBuffSpiltFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : buff-spilt-failed
OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.17

Field Name : httpAlgStatsBuffResent
Field Type : CounterBasedGauge64
Field Status : current
Description : buff-resent

OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.16

Field Name : httpAlgStatsOutOfOrderDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : out-of-order-dropped
OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.15

Field Name : httpAlgStatsQueueLenExceedDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : queue-len-exceed-dropped
OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.14

Field Name : httpAlgStatsOutOfMemoryDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : out-of-memory-dropped
OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.13

Field Name : httpAlgStatsRadiusResponseDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : radius-response-dropped
OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.12

Field Name : httpAlgStatsRadiusResponseReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : radius-response-received
OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.11

Field Name : httpAlgStatsRadiusRequstDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : radius-requst-dropped
OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.10

Field Name : httpAlgStatsRadiusRequstSent
Field Type : CounterBasedGauge64
Field Status : current
Description : radius-requst-sent
OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.9

Field Name : httpAlgStatsRadiusQueryFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : radius-query-failed
OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.8

Field Name : httpAlgStatsRadiusQuerySucceed
Field Type : CounterBasedGauge64
Field Status : current
Description : radius-query-succeed
OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.7

Field Name : httpAlgStatsQueuedSessionTooMany
Field Type : CounterBasedGauge64

Field Status : current
Description : queued-session-too-many
OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.6

Field Name : httpAlgStatsRequestInsertMsisdnUnavailable
Field Type : CounterBasedGauge64
Field Status : current
Description : request-insert-msisdn-unavailable
OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.5

Field Name : httpAlgStatsRequestInsertClientIpPerformed
Field Type : CounterBasedGauge64
Field Status : current
Description : request-insert-client-ip-performed
OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.4

Field Name : httpAlgStatsRequestInsertMsisdnPerformed
Field Type : CounterBasedGauge64
Field Status : current
Description : request-insert-msisdn-performed
OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.3

Field Name : httpAlgStatsRequestProcessed
Field Type : CounterBasedGauge64
Field Status : current
Description : request-processed
OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.2

Field Name : httpAlgStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.1

Field Name : dns64StatsTable
Field Type : TABLE
Field Status : current
Description : DNS64 Statistics from object 'cgnv6.dns64'
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1

Field Name : dns64StatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dns64Stats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1

Field Name : dns64StatsDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : drop
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1.16

Field Name : dns64StatsCache
Field Type : CounterBasedGauge64
Field Status : current
Description : cache
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1.15

Field Name : dns64StatsAdjust
Field Type : CounterBasedGauge64
Field Status : current
Description : adjust
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1.14

Field Name : dns64StatsRespLocal
Field Type : CounterBasedGauge64
Field Status : current
Description : resp-local
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1.13

Field Name : dns64StatsRespEmpty
Field Type : CounterBasedGauge64
Field Status : current
Description : resp-empty
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1.12

Field Name : dns64StatsRespErr
Field Type : CounterBasedGauge64
Field Status : current
Description : resp-err
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1.11

Field Name : dns64StatsRespChg
Field Type : CounterBasedGauge64
Field Status : current
Description : resp-chg
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1.10

Field Name : dns64StatsRespBadQr
Field Type : CounterBasedGauge64
Field Status : current
Description : resp-bad-qr
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1.9

Field Name : dns64StatsRespBadPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : resp-bad-pkt
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1.8

Field Name : dns64StatsResp
Field Type : CounterBasedGauge64
Field Status : current
Description : resp
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1.7

Field Name : dns64StatsQueryPassive
Field Type : CounterBasedGauge64
Field Status : current
Description : query-passive
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1.6

Field Name : dns64StatsQueryParallel
Field Type : CounterBasedGauge64
Field Status : current
Description : query-parallel

OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1.5

Field Name : dns64StatsQueryChg
Field Type : CounterBasedGauge64
Field Status : current
Description : query-chg
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1.4

Field Name : dns64StatsQueryBadPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : query-bad-pkt
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1.3

Field Name : dns64StatsQuery
Field Type : CounterBasedGauge64
Field Status : current
Description : query
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1.2

Field Name : dns64StatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1.1

Field Name : statisticsOperTable
Field Type : TABLE
Field Status : current
Description : GSLB Global stats from object 'gslb.statistics'
OID : 1.3.6.1.4.1.22610.2.4.8.422.1.2

Field Name : statisticsOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The statisticsOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.422.1.2.1

Field Name : statisticsOperCurrSslCtx
Field Type : CounterBasedGauge64
Field Status : current
Description : curr-ssl-ctx
OID : 1.3.6.1.4.1.22610.2.4.8.422.1.2.1.2

Field Name : statisticsOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.422.1.2.1.1

Field Name : portOperTable
Field Type : TABLE
Field Status : current
Description : Server Port from object 'gslb.service-ip.port'
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.2

Field Name : portStatsTable
Field Type : TABLE

Field Status : current
Description : Server Port from object 'gslb.service-ip.port'
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.1

Field Name : portStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.1.1

Field Name : portStatsCurrent
Field Type : CounterBasedGauge64
Field Status : current
Description : current
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.1.1.7

Field Name : portStatsActive
Field Type : CounterBasedGauge64
Field Status : current
Description : active
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.1.1.6

Field Name : portStatsPortProto
Field Type : String
Field Status : current
Description : port-proto
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.1.1.4

Field Name : portStatsPortNum
Field Type : Integer32
Field Status : current
Description : port-num
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.1.1.3

Field Name : portStatsNodeName
Field Type : String
Field Status : current
Description : node-name
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.1.1.2

Field Name : portStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.1.1.1

Field Name : portOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.2.1

Field Name : portOperDynamic
Field Type : CounterBasedGauge64
Field Status : current
Description : dynamic
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.2.1.14

Field Name : portOperUseGslbState
Field Type : CounterBasedGauge64
Field Status : current
Description : use_gslb_state
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.2.1.13

Field Name : portOperManuallyHealthCheck
Field Type : CounterBasedGauge64
Field Status : current
Description : manually-health-check
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.2.1.12

Field Name : portOperTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.2.1.11

Field Name : portOperLocalProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : local-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.2.1.10

Field Name : portOperGslbProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : gslb-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.2.1.9

Field Name : portOperDisabled
Field Type : CounterBasedGauge64
Field Status : current
Description : disabled
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.2.1.8

Field Name : portOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.2.1.7

Field Name : portOperServicePort
Field Type : CounterBasedGauge64
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.2.1.6

Field Name : portOperPortProto
Field Type : String
Field Status : current
Description : port-proto
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.2.1.4

Field Name : portOperPortNum
Field Type : Integer32
Field Status : current
Description : port-num

OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.2.1.3

Field Name : portOperNodeName
Field Type : String
Field Status : current
Description : node-name
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.2.1.2

Field Name : portOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.2.1.1

Field Name : serviceIpOperTable
Field Type : TABLE
Field Status : current
Description : Service IP from object 'gslb.service-ip'
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.2

Field Name : serviceIpOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceIpOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.2.1

Field Name : serviceIpOperDynamic
Field Type : CounterBasedGauge64
Field Status : current
Description : dynamic
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.2.1.13

Field Name : serviceIpOperUseGslbState
Field Type : CounterBasedGauge64
Field Status : current
Description : use_gslb_state
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.2.1.12

Field Name : serviceIpOperManuallyHealthCheck
Field Type : CounterBasedGauge64
Field Status : current
Description : manually-health-check
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.2.1.11

Field Name : serviceIpOperLocalProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : local-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.2.1.10

Field Name : serviceIpOperGslbProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : gslb-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.2.1.9

Field Name : serviceIpOperDisabled
Field Type : CounterBasedGauge64

Field Status : current
Description : disabled
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.2.1.8

Field Name : serviceIpOperVirtualServer
Field Type : CounterBasedGauge64
Field Status : current
Description : virtual-server
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.2.1.7

Field Name : serviceIpOperPortCount
Field Type : CounterBasedGauge64
Field Status : current
Description : port-count
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.2.1.6

Field Name : serviceIpOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.2.1.5

Field Name : serviceIpOperIp
Field Type : String
Field Status : current
Description : ip
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.2.1.4

Field Name : serviceIpOperServiceIp
Field Type : String
Field Status : current
Description : service-ip
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.2.1.3

Field Name : serviceIpOperNodeName
Field Type : String
Field Status : current
Description : node-name
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.2.1.2

Field Name : serviceIpOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.2.1.1

Field Name : serviceIpStatsTable
Field Type : TABLE
Field Status : current
Description : Service IP from object 'gslb.service-ip'
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.1

Field Name : serviceIpStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceIpStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.1.1

Field Name : serviceIpStatsRecent
Field Type : CounterBasedGauge64
Field Status : current
Description : recent
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.1.1.4

Field Name : serviceIpStatsHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.1.1.3

Field Name : serviceIpStatsNodeName
Field Type : String
Field Status : current
Description : node-name
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.1.1.2

Field Name : serviceIpStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.1.1.1

Field Name : serviceOperTable
Field Type : TABLE
Field Status : current
Description : Service Port from object 'gslb.service-ip.service'
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.15.2

Field Name : serviceStatsTable
Field Type : TABLE
Field Status : current
Description : Service Port from object 'gslb.service-ip.service'
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.15.1

Field Name : serviceStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.15.1.1

Field Name : serviceStatsCurrent
Field Type : CounterBasedGauge64
Field Status : current
Description : current
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.15.1.1.7

Field Name : serviceStatsActive
Field Type : CounterBasedGauge64
Field Status : current
Description : active
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.15.1.1.6

Field Name : serviceStatsLabel
Field Type : String
Field Status : current
Description : label

OID : 1.3.6.1.4.1.22610.2.4.8.424.1.15.1.1.5

Field Name : serviceStatsPortProto
Field Type : String
Field Status : current
Description : port-proto
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.15.1.1.4

Field Name : serviceStatsPortNum
Field Type : Integer32
Field Status : current
Description : port-num
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.15.1.1.3

Field Name : serviceStatsNodeName
Field Type : String
Field Status : current
Description : node-name
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.15.1.1.2

Field Name : serviceStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.15.1.1.1

Field Name : serviceOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.15.2.1

Field Name : serviceOperDynamic
Field Type : CounterBasedGauge64
Field Status : current
Description : dynamic
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.15.2.1.14

Field Name : serviceOperUseGslbState
Field Type : CounterBasedGauge64
Field Status : current
Description : use_gslb_state
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.15.2.1.13

Field Name : serviceOperManuallyHealthCheck
Field Type : CounterBasedGauge64
Field Status : current
Description : manually-health-check
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.15.2.1.12

Field Name : serviceOperTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.15.2.1.11

Field Name : serviceOperLocalProtocol
Field Type : CounterBasedGauge64

Field Status : current
Description : local-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.15.2.1.10

Field Name : serviceOperGslbProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : gslb-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.15.2.1.9

Field Name : serviceOperDisabled
Field Type : CounterBasedGauge64
Field Status : current
Description : disabled
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.15.2.1.8

Field Name : serviceOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.15.2.1.7

Field Name : serviceOperServicePort
Field Type : CounterBasedGauge64
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.15.2.1.6

Field Name : serviceOperLabel
Field Type : String
Field Status : current
Description : label
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.15.2.1.5

Field Name : serviceOperPortProto
Field Type : String
Field Status : current
Description : port-proto
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.15.2.1.4

Field Name : serviceOperPortNum
Field Type : Integer32
Field Status : current
Description : port-num
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.15.2.1.3

Field Name : serviceOperNodeName
Field Type : String
Field Status : current
Description : node-name
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.15.2.1.2

Field Name : serviceOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.15.2.1.1

Field Name : ipServerOperIpServerPortTable
Field Type : TABLE
Field Status : current
Description : Specify a real server for the GSLB site from object 'gslb.site.ip-server'
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.5

Field Name : ipServerOperDrsListDrsPortTable
Field Type : TABLE
Field Status : current
Description : Specify a real server for the GSLB site from object 'gslb.site.ip-server'
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.4

Field Name : ipServerOperDrsListDrsPortEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The ipServerOperDrsListDrsPort entry:drs-port
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.4.1

Field Name : ipServerOperDrsListDrsPortServiceName
Field Type : String
Field Status : current
Description : service-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.4.1.9

Field Name : ipServerOperDrsListDrsPortVportState
Field Type : String
Field Status : current
Description : vport-state
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.4.1.8

Field Name : ipServerOperDrsListDrsPortVportProtocol
Field Type : String
Field Status : current
Description : vport-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.4.1.7

Field Name : ipServerOperDrsListDrsPortVport
Field Type : CounterBasedGauge64
Field Status : current
Description : vport
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.4.1.6

Field Name : ipServerOperDrsListDrsPortDrsPortListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.4.1.5

Field Name : ipServerOperDrsListDrsPortDrsListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.4.1.4

Field Name : ipServerOperDrsListDrsPortIpServerName
Field Type : String
Field Status : current
Description : ip-server-name

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.4.1.3

Field Name : ipServerOperDrsListDrsPortSiteName
Field Type : String
Field Status : current
Description : site-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.4.1.2

Field Name : ipServerOperDrsListDrsPortSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.4.1.1

Field Name : ipServerOperDrsListTable
Field Type : TABLE
Field Status : current
Description : Specify a real server for the GSLB site from object 'gslb.site.ip-server'
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3

Field Name : ipServerOperDrsListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The ipServerOperDrsList entry:drs-list
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1

Field Name : ipServerOperDrsListDrsRecent
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-recent
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.19

Field Name : ipServerOperDrsListDrsHits
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-hits
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.18

Field Name : ipServerOperDrsListDrsDynamic
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-dynamic
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.17

Field Name : ipServerOperDrsListDrsUseGslbState
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-use_gslb_state
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.16

Field Name : ipServerOperDrsListDrsManuallyHealthCheck
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-manually-health-check
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.15

Field Name : ipServerOperDrsListDrsLocalProtocol
Field Type : CounterBasedGauge64

Field Status : current
Description : drs-local-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.14

Field Name : ipServerOperDrsListDrsGslbProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-gslb-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.13

Field Name : ipServerOperDrsListDrsDisabled
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-disabled
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.12

Field Name : ipServerOperDrsListDrsVirtualServer
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-virtual-server
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.11

Field Name : ipServerOperDrsListDrsPortCount
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-port-count
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.10

Field Name : ipServerOperDrsListDrsServiceIp
Field Type : String
Field Status : current
Description : drs-service-ip
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.9

Field Name : ipServerOperDrsListDrsState
Field Type : String
Field Status : current
Description : drs-state
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.8

Field Name : ipServerOperDrsListDrsFqdnName
Field Type : String
Field Status : current
Description : drs-fqdn-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.7

Field Name : ipServerOperDrsListDrsIpAddress
Field Type : String
Field Status : current
Description : drs-ip-address
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.6

Field Name : ipServerOperDrsListDrsName
Field Type : String
Field Status : current
Description : drs-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.5

Field Name : ipServerOperDrsListDrsListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.4

Field Name : ipServerOperDrsListIpServerName
Field Type : String
Field Status : current
Description : ip-server-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.3

Field Name : ipServerOperDrsListSiteName
Field Type : String
Field Status : current
Description : site-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.2

Field Name : ipServerOperDrsListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.1

Field Name : ipServerOperTable
Field Type : TABLE
Field Status : current
Description : Specify a real server for the GSLB site from object 'gslb.site.ip-server'
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2

Field Name : ipServerOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The ipServerOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1

Field Name : ipServerOperRecent
Field Type : CounterBasedGauge64
Field Status : current
Description : recent
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.18

Field Name : ipServerOperHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.17

Field Name : ipServerOperDynamic
Field Type : CounterBasedGauge64
Field Status : current
Description : dynamic
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.16

Field Name : ipServerOperUseGslbState
Field Type : CounterBasedGauge64
Field Status : current
Description : use_gslb_state

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.15

Field Name : ipServerOperManuallyHealthCheck
Field Type : CounterBasedGauge64
Field Status : current
Description : manually-health-check
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.14

Field Name : ipServerOperLocalProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : local-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.13

Field Name : ipServerOperGslbProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : gslb-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.12

Field Name : ipServerOperDisabled
Field Type : CounterBasedGauge64
Field Status : current
Description : disabled
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.11

Field Name : ipServerOperVirtualServer
Field Type : CounterBasedGauge64
Field Status : current
Description : virtual-server
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.10

Field Name : ipServerOperPortCount
Field Type : CounterBasedGauge64
Field Status : current
Description : port-count
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.9

Field Name : ipServerOperServiceIp
Field Type : String
Field Status : current
Description : service-ip
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.8

Field Name : ipServerOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.7

Field Name : ipServerOperDesc
Field Type : String
Field Status : current
Description : desc
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.6

Field Name : ipServerOperIpAddress
Field Type : String

Field Status : current
Description : ip-address
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.5

Field Name : ipServerOperIpServer
Field Type : String
Field Status : current
Description : ip-server
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.4

Field Name : ipServerOperIpServerName
Field Type : String
Field Status : current
Description : ip-server-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.3

Field Name : ipServerOperSiteName
Field Type : String
Field Status : current
Description : site-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.2

Field Name : ipServerOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.1

Field Name : ipServerStatsTable
Field Type : TABLE
Field Status : current
Description : Specify a real server for the GSLB site from object 'gslb.site.ip-server'
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.1

Field Name : ipServerStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The ipServerStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.1.1

Field Name : ipServerStatsRecent
Field Type : CounterBasedGauge64
Field Status : current
Description : recent
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.1.1.5

Field Name : ipServerStatsHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.1.1.4

Field Name : ipServerStatsIpServerName
Field Type : String
Field Status : current
Description : ip-server-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.1.1.3

Field Name : ipServerStatsSiteName
Field Type : String
Field Status : current
Description : site-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.1.1.2

Field Name : ipServerStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.1.1.1

Field Name : ipServerOperIpServerPortEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The ipServerOperIpServerPort entry:ip-server-port
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.5.1

Field Name : ipServerOperIpServerPortServiceName
Field Type : String
Field Status : current
Description : service-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.5.1.8

Field Name : ipServerOperIpServerPortVportState
Field Type : String
Field Status : current
Description : vport-state
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.5.1.7

Field Name : ipServerOperIpServerPortVportProtocol
Field Type : String
Field Status : current
Description : vport-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.5.1.6

Field Name : ipServerOperIpServerPortVport
Field Type : CounterBasedGauge64
Field Status : current
Description : vport
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.5.1.5

Field Name : ipServerOperIpServerPortIpServerPortListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.5.1.4

Field Name : ipServerOperIpServerPortIpServerName
Field Type : String
Field Status : current
Description : ip-server-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.5.1.3

Field Name : ipServerOperIpServerPortSiteName
Field Type : String
Field Status : current
Description : site-name

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.5.1.2

Field Name : ipServerOperIpServerPortSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.5.1.1

Field Name : siteOperClientLdnsListTable
Field Type : TABLE
Field Status : current
Description : Specify a GSLB site from object 'gslb.site'
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.4

Field Name : siteOperClientLdnsListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The siteOperClientLdnsList entry:client-ldns-list
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.4.1

Field Name : siteOperClientLdnsListRdtSample8
Field Type : CounterBasedGauge64
Field Status : current
Description : rdt-sample8
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.4.1.14

Field Name : siteOperClientLdnsListRdtSample7
Field Type : CounterBasedGauge64
Field Status : current
Description : rdt-sample7
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.4.1.13

Field Name : siteOperClientLdnsListRdtSample6
Field Type : CounterBasedGauge64
Field Status : current
Description : rdt-sample6
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.4.1.12

Field Name : siteOperClientLdnsListRdtSample5
Field Type : CounterBasedGauge64
Field Status : current
Description : rdt-sample5
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.4.1.11

Field Name : siteOperClientLdnsListRdtSample4
Field Type : CounterBasedGauge64
Field Status : current
Description : rdt-sample4
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.4.1.10

Field Name : siteOperClientLdnsListRdtSample3
Field Type : CounterBasedGauge64
Field Status : current
Description : rdt-sample3
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.4.1.9

Field Name : siteOperClientLdnsListRdtSample2
Field Type : CounterBasedGauge64

Field Status : current
Description : rdt-sample2
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.4.1.8

Field Name : siteOperClientLdnsListRdtSample1
Field Type : CounterBasedGauge64
Field Status : current
Description : rdt-sample1
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.4.1.7

Field Name : siteOperClientLdnsListType
Field Type : String
Field Status : current
Description : type
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.4.1.6

Field Name : siteOperClientLdnsListAge
Field Type : CounterBasedGauge64
Field Status : current
Description : age
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.4.1.5

Field Name : siteOperClientLdnsListClientIp
Field Type : String
Field Status : current
Description : client-ip
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.4.1.4

Field Name : siteOperClientLdnsListClientLdnsListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.4.1.3

Field Name : siteOperClientLdnsListSiteName
Field Type : String
Field Status : current
Description : site-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.4.1.2

Field Name : siteOperClientLdnsListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.4.1.1

Field Name : siteOperTypeLastTable
Field Type : TABLE
Field Status : current
Description : Specify a GSLB site from object 'gslb.site'
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.3

Field Name : siteOperTypeLastEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The siteOperTypeLast entry:type-last
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.3.1

Field Name : siteOperTypeLastLast
Field Type : String
Field Status : current
Description : last
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.3.1.5

Field Name : siteOperTypeLastType
Field Type : String
Field Status : current
Description : type
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.3.1.4

Field Name : siteOperTypeLastTypeLastListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.3.1.3

Field Name : siteOperTypeLastSiteName
Field Type : String
Field Status : current
Description : site-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.3.1.2

Field Name : siteOperTypeLastSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.3.1.1

Field Name : siteOperTable
Field Type : TABLE
Field Status : current
Description : Specify a GSLB site from object 'gslb.site'
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.2

Field Name : siteOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The siteOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.2.1

Field Name : siteOperTotalVipCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : total-vip-curr-conn
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.2.1.5

Field Name : siteOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.2.1.4

Field Name : siteOperGslbSite
Field Type : String
Field Status : current
Description : gslb-site

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.2.1.3

Field Name : siteOperSiteName
Field Type : String
Field Status : current
Description : site-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.2.1.2

Field Name : siteOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.2.1.1

Field Name : siteStatsTable
Field Type : TABLE
Field Status : current
Description : Specify a GSLB site from object 'gslb.site'
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.1

Field Name : siteStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The siteStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.1.1

Field Name : siteStatsHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.1.1.3

Field Name : siteStatsSiteName
Field Type : String
Field Status : current
Description : site-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.1.1.2

Field Name : siteStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.1.1.1

Field Name : slbDevOperClientLdnsListTable
Field Type : TABLE
Field Status : current
Description : Specify a SLB device for the GSLB site from object 'gslb.site.slb-dev'
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3

Field Name : slbDevOperClientLdnsListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The slbDevOperClientLdnsList entry:client-ldns-list
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3.1

Field Name : slbDevOperClientLdnsListRdtSample8
Field Type : CounterBasedGauge64

Field Status : current
Description : rdt-sample8
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3.1.15

Field Name : slbDevOperClientLdnsListRdtSample7
Field Type : CounterBasedGauge64
Field Status : current
Description : rdt-sample7
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3.1.14

Field Name : slbDevOperClientLdnsListRdtSample6
Field Type : CounterBasedGauge64
Field Status : current
Description : rdt-sample6
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3.1.13

Field Name : slbDevOperClientLdnsListRdtSample5
Field Type : CounterBasedGauge64
Field Status : current
Description : rdt-sample5
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3.1.12

Field Name : slbDevOperClientLdnsListRdtSample4
Field Type : CounterBasedGauge64
Field Status : current
Description : rdt-sample4
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3.1.11

Field Name : slbDevOperClientLdnsListRdtSample3
Field Type : CounterBasedGauge64
Field Status : current
Description : rdt-sample3
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3.1.10

Field Name : slbDevOperClientLdnsListRdtSample2
Field Type : CounterBasedGauge64
Field Status : current
Description : rdt-sample2
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3.1.9

Field Name : slbDevOperClientLdnsListRdtSample1
Field Type : CounterBasedGauge64
Field Status : current
Description : rdt-sample1
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3.1.8

Field Name : slbDevOperClientLdnsListType
Field Type : String
Field Status : current
Description : type
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3.1.7

Field Name : slbDevOperClientLdnsListAge
Field Type : CounterBasedGauge64
Field Status : current
Description : age
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3.1.6

Field Name : slbDevOperClientLdnsListClientIp
Field Type : String
Field Status : current
Description : client-ip
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3.1.5

Field Name : slbDevOperClientLdnsListClientLdnsListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3.1.4

Field Name : slbDevOperClientLdnsListDeviceName
Field Type : String
Field Status : current
Description : device-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3.1.3

Field Name : slbDevOperClientLdnsListSiteName
Field Type : String
Field Status : current
Description : site-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3.1.2

Field Name : slbDevOperClientLdnsListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3.1.1

Field Name : slbDevOperTable
Field Type : TABLE
Field Status : current
Description : Specify a SLB device for the GSLB site from object 'gslb.site.slb-dev'
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.2

Field Name : slbDevOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The slbDevOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.2.1

Field Name : slbDevOperDevState
Field Type : String
Field Status : current
Description : dev-state
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.2.1.12

Field Name : slbDevOperDevIpCnt
Field Type : CounterBasedGauge64
Field Status : current
Description : dev_ip_cnt
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.2.1.11

Field Name : slbDevOperDevGwState
Field Type : String
Field Status : current
Description : dev_gw_state

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.2.1.10

Field Name : slbDevOperDevSessionUtil
Field Type : CounterBasedGauge64
Field Status : current
Description : dev_session_util
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.2.1.9

Field Name : slbDevOperDevSessionNum
Field Type : CounterBasedGauge64
Field Status : current
Description : dev_session_num
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.2.1.8

Field Name : slbDevOperDevAdminPreference
Field Type : CounterBasedGauge64
Field Status : current
Description : dev_admin_preference
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.2.1.7

Field Name : slbDevOperDevAttr
Field Type : String
Field Status : current
Description : dev_attr
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.2.1.6

Field Name : slbDevOperDevIp
Field Type : String
Field Status : current
Description : dev_ip
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.2.1.5

Field Name : slbDevOperDevName
Field Type : String
Field Status : current
Description : dev_name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.2.1.4

Field Name : slbDevOperDeviceName
Field Type : String
Field Status : current
Description : device-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.2.1.3

Field Name : slbDevOperSiteName
Field Type : String
Field Status : current
Description : site-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.2.1.2

Field Name : slbDevOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.2.1.1

Field Name : vipServerV6OperDevVipPortListTable
Field Type : TABLE

Field Status : current
Description : Specify a VIP for the SLB device from object 'gslb.site.slb-dev.vip-server.vip-server-v6'
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.3

Field Name : vipServerV6OperTable
Field Type : TABLE
Field Status : current
Description : Specify a VIP for the SLB device from object 'gslb.site.slb-dev.vip-server.vip-server-v6'
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2

Field Name : vipServerV6OperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The vipServerV6Oper entry
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1

Field Name : vipServerV6OperRecent
Field Type : CounterBasedGauge64
Field Status : current
Description : recent
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.19

Field Name : vipServerV6OperHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.18

Field Name : vipServerV6OperShared
Field Type : CounterBasedGauge64
Field Status : current
Description : shared
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.17

Field Name : vipServerV6OperDynamic
Field Type : CounterBasedGauge64
Field Status : current
Description : dynamic
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.16

Field Name : vipServerV6OperUseGslbState
Field Type : CounterBasedGauge64
Field Status : current
Description : use_gslb_state
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.15

Field Name : vipServerV6OperManuallyHealthCheck
Field Type : CounterBasedGauge64
Field Status : current
Description : manually-health-check
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.14

Field Name : vipServerV6OperLocalProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : local-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.13

Field Name : vipServerV6OperGslbProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : gslb-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.12

Field Name : vipServerV6OperDisabled
Field Type : CounterBasedGauge64
Field Status : current
Description : disabled
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.11

Field Name : vipServerV6OperVirtualServer
Field Type : CounterBasedGauge64
Field Status : current
Description : virtual-server
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.10

Field Name : vipServerV6OperPortCount
Field Type : CounterBasedGauge64
Field Status : current
Description : port-count
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.9

Field Name : vipServerV6OperServiceIp
Field Type : String
Field Status : current
Description : service-ip
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.8

Field Name : vipServerV6OperNodeName
Field Type : String
Field Status : current
Description : node-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.7

Field Name : vipServerV6OperDevVipState
Field Type : String
Field Status : current
Description : dev_vip_state
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.6

Field Name : vipServerV6OperDevVipAddr
Field Type : String
Field Status : current
Description : dev_vip_addr
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.5

Field Name : vipServerV6OperIpv6
Field Type : String
Field Status : current
Description : ipv6
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.4

Field Name : vipServerV6OperDeviceName
Field Type : String
Field Status : current
Description : device-name

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.3

Field Name : vipServerV6OperSiteName
Field Type : String
Field Status : current
Description : site-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.2

Field Name : vipServerV6OperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.1

Field Name : vipServerV6StatsTable
Field Type : TABLE
Field Status : current
Description : Specify a VIP for the SLB device from object 'gslb.site.slb-dev.vip-server.vip-server-v6'
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.1

Field Name : vipServerV6StatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The vipServerV6Stats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.1.1

Field Name : vipServerV6StatsDevVipRecent
Field Type : CounterBasedGauge64
Field Status : current
Description : dev_vip_recent
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.1.1.6

Field Name : vipServerV6StatsDevVipHits
Field Type : CounterBasedGauge64
Field Status : current
Description : dev_vip_hits
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.1.1.5

Field Name : vipServerV6StatsIpv6
Field Type : String
Field Status : current
Description : ipv6
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.1.1.4

Field Name : vipServerV6StatsDeviceName
Field Type : String
Field Status : current
Description : device-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.1.1.3

Field Name : vipServerV6StatsSiteName
Field Type : String
Field Status : current
Description : site-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.1.1.2

Field Name : vipServerV6StatsSlotId
Field Type : Integer32

Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.1.1.1

Field Name : vipServerV6OperDevVipPortListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The vipServerV6OperDevVipPortList entry:dev-vip-port-list
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.3.1

Field Name : vipServerV6OperDevVipPortListDevVipPortServiceName
Field Type : String
Field Status : current
Description : dev-vip-port-service-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.3.1.10

Field Name : vipServerV6OperDevVipPortListDevVipPortProtocol
Field Type : String
Field Status : current
Description : dev-vip-port-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.3.1.9

Field Name : vipServerV6OperDevVipPortListDevVipPortDevCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : dev-vip-port-dev-curr-conn
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.3.1.8

Field Name : vipServerV6OperDevVipPortListDevVipPortState
Field Type : String
Field Status : current
Description : dev-vip-port-state
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.3.1.7

Field Name : vipServerV6OperDevVipPortListDevVipPortNum
Field Type : CounterBasedGauge64
Field Status : current
Description : dev-vip-port-num
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.3.1.6

Field Name : vipServerV6OperDevVipPortListDevVipPortListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.3.1.5

Field Name : vipServerV6OperDevVipPortListIpv6
Field Type : String
Field Status : current
Description : ipv6
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.3.1.4

Field Name : vipServerV6OperDevVipPortListDeviceName
Field Type : String
Field Status : current
Description : device-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.3.1.3

Field Name : vipServerV6OperDevVipPortListSiteName
Field Type : String
Field Status : current
Description : site-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.3.1.2

Field Name : vipServerV6OperDevVipPortListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.3.1.1

Field Name : vipServerV4OperDevVipPortListTable
Field Type : TABLE
Field Status : current
Description : Specify a VIP for the SLB device from object 'gslb.site.slb-dev.vip-server.vip-server-v4'
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.3

Field Name : vipServerV4OperTable
Field Type : TABLE
Field Status : current
Description : Specify a VIP for the SLB device from object 'gslb.site.slb-dev.vip-server.vip-server-v4'
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2

Field Name : vipServerV4OperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The vipServerV4Oper entry
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1

Field Name : vipServerV4OperRecent
Field Type : CounterBasedGauge64
Field Status : current
Description : recent
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.19

Field Name : vipServerV4OperHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.18

Field Name : vipServerV4OperShared
Field Type : CounterBasedGauge64
Field Status : current
Description : shared
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.17

Field Name : vipServerV4OperDynamic
Field Type : CounterBasedGauge64
Field Status : current
Description : dynamic
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.16

Field Name : vipServerV4OperUseGslbState
Field Type : CounterBasedGauge64
Field Status : current
Description : use_gslb_state

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.15

Field Name : vipServerV4OperManuallyHealthCheck
Field Type : CounterBasedGauge64
Field Status : current
Description : manually-health-check
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.14

Field Name : vipServerV4OperLocalProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : local-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.13

Field Name : vipServerV4OperGslbProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : gslb-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.12

Field Name : vipServerV4OperDisabled
Field Type : CounterBasedGauge64
Field Status : current
Description : disabled
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.11

Field Name : vipServerV4OperVirtualServer
Field Type : CounterBasedGauge64
Field Status : current
Description : virtual-server
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.10

Field Name : vipServerV4OperPortCount
Field Type : CounterBasedGauge64
Field Status : current
Description : port-count
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.9

Field Name : vipServerV4OperServiceIp
Field Type : String
Field Status : current
Description : service-ip
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.8

Field Name : vipServerV4OperNodeName
Field Type : String
Field Status : current
Description : node-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.7

Field Name : vipServerV4OperDevVipState
Field Type : String
Field Status : current
Description : dev_vip_state
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.6

Field Name : vipServerV4OperDevVipAddr
Field Type : String

Field Status : current
Description : dev_vip_addr
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.5

Field Name : vipServerV4OperIpv4
Field Type : String
Field Status : current
Description : ipv4
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.4

Field Name : vipServerV4OperDeviceName
Field Type : String
Field Status : current
Description : device-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.3

Field Name : vipServerV4OperSiteName
Field Type : String
Field Status : current
Description : site-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.2

Field Name : vipServerV4OperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.1

Field Name : vipServerV4StatsTable
Field Type : TABLE
Field Status : current
Description : Specify a VIP for the SLB device from object 'gslb.site.slb-dev.vip-server.vip-server-v4'
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.1

Field Name : vipServerV4StatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The vipServerV4Stats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.1.1

Field Name : vipServerV4StatsDevVipRecent
Field Type : CounterBasedGauge64
Field Status : current
Description : dev_vip_recent
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.1.1.6

Field Name : vipServerV4StatsDevVipHits
Field Type : CounterBasedGauge64
Field Status : current
Description : dev_vip_hits
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.1.1.5

Field Name : vipServerV4StatsIpv4
Field Type : String
Field Status : current
Description : ipv4
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.1.1.4

Field Name : vipServerV4StatsDeviceName
Field Type : String
Field Status : current
Description : device-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.1.1.3

Field Name : vipServerV4StatsSiteName
Field Type : String
Field Status : current
Description : site-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.1.1.2

Field Name : vipServerV4StatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.1.1.1

Field Name : vipServerV4OperDevVipPortListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The vipServerV4OperDevVipPortList entry:dev-vip-port-list
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.3.1

Field Name : vipServerV4OperDevVipPortListDevVipPortServiceName
Field Type : String
Field Status : current
Description : dev-vip-port-service-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.3.1.10

Field Name : vipServerV4OperDevVipPortListDevVipPortProtocol
Field Type : String
Field Status : current
Description : dev-vip-port-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.3.1.9

Field Name : vipServerV4OperDevVipPortListDevVipPortDevCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : dev-vip-port-dev-curr-conn
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.3.1.8

Field Name : vipServerV4OperDevVipPortListDevVipPortState
Field Type : String
Field Status : current
Description : dev-vip-port-state
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.3.1.7

Field Name : vipServerV4OperDevVipPortListDevVipPortNum
Field Type : CounterBasedGauge64
Field Status : current
Description : dev-vip-port-num
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.3.1.6

Field Name : vipServerV4OperDevVipPortListDevVipPortListListId
Field Type : Integer32
Field Status : current
Description :

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.3.1.5

Field Name : vipServerV4OperDevVipPortListIpv4
Field Type : String
Field Status : current
Description : ipv4
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.3.1.4

Field Name : vipServerV4OperDevVipPortListDeviceName
Field Type : String
Field Status : current
Description : device-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.3.1.3

Field Name : vipServerV4OperDevVipPortListSiteName
Field Type : String
Field Status : current
Description : site-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.3.1.2

Field Name : vipServerV4OperDevVipPortListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.3.1.1

Field Name : vipServerNameOperDevVipPortListTable
Field Type : TABLE
Field Status : current
Description : Specify a VIP for the SLB device from object 'gslb.site.slb-dev.vip-server.vip-server-name'
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.3

Field Name : vipServerNameOperTable
Field Type : TABLE
Field Status : current
Description : Specify a VIP for the SLB device from object 'gslb.site.slb-dev.vip-server.vip-server-name'
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2

Field Name : vipServerNameOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The vipServerNameOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1

Field Name : vipServerNameOperRecent
Field Type : CounterBasedGauge64
Field Status : current
Description : recent
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.19

Field Name : vipServerNameOperHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.18

Field Name : vipServerNameOperShared
Field Type : CounterBasedGauge64

Field Status : current
Description : shared
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.17

Field Name : vipServerNameOperDynamic
Field Type : CounterBasedGauge64
Field Status : current
Description : dynamic
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.16

Field Name : vipServerNameOperUseGslbState
Field Type : CounterBasedGauge64
Field Status : current
Description : use_gslb_state
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.15

Field Name : vipServerNameOperManuallyHealthCheck
Field Type : CounterBasedGauge64
Field Status : current
Description : manually-health-check
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.14

Field Name : vipServerNameOperLocalProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : local-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.13

Field Name : vipServerNameOperGslbProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : gslb-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.12

Field Name : vipServerNameOperDisabled
Field Type : CounterBasedGauge64
Field Status : current
Description : disabled
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.11

Field Name : vipServerNameOperVirtualServer
Field Type : CounterBasedGauge64
Field Status : current
Description : virtual-server
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.10

Field Name : vipServerNameOperPortCount
Field Type : CounterBasedGauge64
Field Status : current
Description : port-count
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.9

Field Name : vipServerNameOperServiceIp
Field Type : String
Field Status : current
Description : service-ip
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.8

Field Name : vipServerNameOperNodeName
Field Type : String
Field Status : current
Description : node-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.7

Field Name : vipServerNameOperDevVipState
Field Type : String
Field Status : current
Description : dev_vip_state
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.6

Field Name : vipServerNameOperDevVipAddr
Field Type : String
Field Status : current
Description : dev_vip_addr
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.5

Field Name : vipServerNameOperVipName
Field Type : String
Field Status : current
Description : vip-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.4

Field Name : vipServerNameOperDeviceName
Field Type : String
Field Status : current
Description : device-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.3

Field Name : vipServerNameOperSiteName
Field Type : String
Field Status : current
Description : site-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.2

Field Name : vipServerNameOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.1

Field Name : vipServerNameStatsTable
Field Type : TABLE
Field Status : current
Description : Specify a VIP for the SLB device from object 'gslb.site.slb-dev.vip-server.vip-server-name'
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.1

Field Name : vipServerNameStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The vipServerNameStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.1.1

Field Name : vipServerNameStatsDevVipRecent
Field Type : CounterBasedGauge64
Field Status : current
Description : dev_vip_recent

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.1.1.6

Field Name : vipServerNameStatsDevVipHits
Field Type : CounterBasedGauge64
Field Status : current
Description : dev_vip_hits
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.1.1.5

Field Name : vipServerNameStatsVipName
Field Type : String
Field Status : current
Description : vip-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.1.1.4

Field Name : vipServerNameStatsDeviceName
Field Type : String
Field Status : current
Description : device-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.1.1.3

Field Name : vipServerNameStatsSiteName
Field Type : String
Field Status : current
Description : site-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.1.1.2

Field Name : vipServerNameStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.1.1.1

Field Name : vipServerNameOperDevVipPortListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The vipServerNameOperDevVipPortList entry:dev-vip-port-list
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.3.1

Field Name : vipServerNameOperDevVipPortListDevVipPortServiceName
Field Type : String
Field Status : current
Description : dev-vip-port-service-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.3.1.10

Field Name : vipServerNameOperDevVipPortListDevVipPortProtocol
Field Type : String
Field Status : current
Description : dev-vip-port-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.3.1.9

Field Name : vipServerNameOperDevVipPortListDevVipPortDevCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : dev-vip-port-dev-curr-conn
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.3.1.8

Field Name : vipServerNameOperDevVipPortListDevVipPortState
Field Type : String

Field Status : current
Description : dev-vip-port-state
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.3.1.7

Field Name : vipServerNameOperDevVipPortListDevVipPortNum
Field Type : CounterBasedGauge64
Field Status : current
Description : dev-vip-port-num
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.3.1.6

Field Name : vipServerNameOperDevVipPortListDevVipPortListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.3.1.5

Field Name : vipServerNameOperDevVipPortListVipName
Field Type : String
Field Status : current
Description : vip-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.3.1.4

Field Name : vipServerNameOperDevVipPortListDeviceName
Field Type : String
Field Status : current
Description : device-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.3.1.3

Field Name : vipServerNameOperDevVipPortListSiteName
Field Type : String
Field Status : current
Description : site-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.3.1.2

Field Name : vipServerNameOperDevVipPortListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.3.1.1

Field Name : dnsCaaRecordOperTable
Field Type : TABLE
Field Status : current
Description : Specify DNS CAA Record from object 'gslb.zone.dns-caa-record'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.6.2

Field Name : dnsCaaRecordStatsTable
Field Type : TABLE
Field Status : current
Description : Specify DNS CAA Record from object 'gslb.zone.dns-caa-record'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.6.1

Field Name : dnsCaaRecordStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsCaaRecordStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.6.1.1

Field Name : dnsCaaRecordStatsHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.6.1.1.6

Field Name : dnsCaaRecordStatsRdata
Field Type : String
Field Status : current
Description : rdata
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.6.1.1.5

Field Name : dnsCaaRecordStatsPropertyTag
Field Type : String
Field Status : current
Description : property-tag
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.6.1.1.4

Field Name : dnsCaaRecordStatsCriticalFlag
Field Type : Integer32
Field Status : current
Description : critical-flag
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.6.1.1.3

Field Name : dnsCaaRecordStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.6.1.1.2

Field Name : dnsCaaRecordStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.6.1.1.1

Field Name : dnsCaaRecordOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsCaaRecordOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.6.2.1

Field Name : dnsCaaRecordOperLastServer
Field Type : String
Field Status : current
Description : last-server
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.6.2.1.6

Field Name : dnsCaaRecordOperRdata
Field Type : String
Field Status : current
Description : rdata
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.6.2.1.5

Field Name : dnsCaaRecordOperPropertyTag
Field Type : String
Field Status : current
Description : property-tag

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.6.2.1.4

Field Name : dnsCaaRecordOperCriticalFlag
Field Type : Integer32
Field Status : current
Description : critical-flag
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.6.2.1.3

Field Name : dnsCaaRecordOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.6.2.1.2

Field Name : dnsCaaRecordOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.6.2.1.1

Field Name : dnsNsRecordOperTable
Field Type : TABLE
Field Status : current
Description : Specify DNS NS Record from object 'gslb.zone.dns-ns-record'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.5.2

Field Name : dnsNsRecordStatsTable
Field Type : TABLE
Field Status : current
Description : Specify DNS NS Record from object 'gslb.zone.dns-ns-record'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.5.1

Field Name : dnsNsRecordStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsNsRecordStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.5.1.1

Field Name : dnsNsRecordStatsHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.5.1.1.4

Field Name : dnsNsRecordStatsNsName
Field Type : String
Field Status : current
Description : ns-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.5.1.1.3

Field Name : dnsNsRecordStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.5.1.1.2

Field Name : dnsNsRecordStatsSlotId
Field Type : Integer32

Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.5.1.1.1

Field Name : dnsNsRecordOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsNsRecordOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.5.2.1

Field Name : dnsNsRecordOperHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.5.2.1.5

Field Name : dnsNsRecordOperLastServer
Field Type : String
Field Status : current
Description : last-server
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.5.2.1.4

Field Name : dnsNsRecordOperNsName
Field Type : String
Field Status : current
Description : ns-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.5.2.1.3

Field Name : dnsNsRecordOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.5.2.1.2

Field Name : dnsNsRecordOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.5.2.1.1

Field Name : dnsMxRecordOperTable
Field Type : TABLE
Field Status : current
Description : Specify DNS MX Record from object 'gslb.zone.dns-mx-record'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.4.2

Field Name : dnsMxRecordStatsTable
Field Type : TABLE
Field Status : current
Description : Specify DNS MX Record from object 'gslb.zone.dns-mx-record'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.4.1

Field Name : dnsMxRecordStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsMxRecordStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.4.1.1

Field Name : dnsMxRecordStatsHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.4.1.1.4

Field Name : dnsMxRecordStatsMxName
Field Type : String
Field Status : current
Description : mx-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.4.1.1.3

Field Name : dnsMxRecordStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.4.1.1.2

Field Name : dnsMxRecordStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.4.1.1.1

Field Name : dnsMxRecordOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsMxRecordOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.4.2.1

Field Name : dnsMxRecordOperPriority
Field Type : CounterBasedGauge64
Field Status : current
Description : priority
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.4.2.1.6

Field Name : dnsMxRecordOperHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.4.2.1.5

Field Name : dnsMxRecordOperLastServer
Field Type : String
Field Status : current
Description : last-server
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.4.2.1.4

Field Name : dnsMxRecordOperMxName
Field Type : String
Field Status : current
Description : mx-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.4.2.1.3

Field Name : dnsMxRecordOperName
Field Type : String
Field Status : current
Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.4.2.1.2

Field Name : dnsMxRecordOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.4.2.1.1

Field Name : zoneOperDnsSoaRecordListTable
Field Type : TABLE
Field Status : current
Description : Specify the DNS zone name for which global SLB is provided from object 'gslb.zone'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.3

Field Name : zoneOperDnsSoaRecordListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The zoneOperDnsSoaRecordList entry:dns-soa-record-list
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.3.1

Field Name : zoneOperDnsSoaRecordListMxName
Field Type : String
Field Status : current
Description : mx-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.3.1.11

Field Name : zoneOperDnsSoaRecordListTtl
Field Type : CounterBasedGauge64
Field Status : current
Description : ttl
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.3.1.10

Field Name : zoneOperDnsSoaRecordListRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : retry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.3.1.9

Field Name : zoneOperDnsSoaRecordListSerial
Field Type : CounterBasedGauge64
Field Status : current
Description : serial
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.3.1.8

Field Name : zoneOperDnsSoaRecordListRefresh
Field Type : CounterBasedGauge64
Field Status : current
Description : refresh
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.3.1.7

Field Name : zoneOperDnsSoaRecordListExpire
Field Type : CounterBasedGauge64
Field Status : current
Description : expire
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.3.1.6

Field Name : zoneOperDnsSoaRecordListType

Field Type : String
Field Status : current
Description : type
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.3.1.5

Field Name : zoneOperDnsSoaRecordListName1
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.3.1.4

Field Name : zoneOperDnsSoaRecordListDnsSoaRecordListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.3.1.3

Field Name : zoneOperDnsSoaRecordListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.3.1.2

Field Name : zoneOperDnsSoaRecordListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.3.1.1

Field Name : zoneOperTable
Field Type : TABLE
Field Status : current
Description : Specify the DNS zone name for which global SLB is provided from object
'gslb.zone'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.2

Field Name : zoneOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The zoneOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.2.1

Field Name : zoneOperSmrule
Field Type : Integer32
Field Status : current
Description : smrule
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.2.1.4

Field Name : zoneOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.2.1.3

Field Name : zoneOperName
Field Type : String
Field Status : current
Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.2.1.2

Field Name : zoneOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.2.1.1

Field Name : zoneStatsTable
Field Type : TABLE
Field Status : current
Description : Specify the DNS zone name for which global SLB is provided from object 'gslb.zone'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.1

Field Name : zoneStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The zoneStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.1.1

Field Name : zoneStatsSmruleRedirFromSvcMiss
Field Type : CounterBasedGauge64
Field Status : current
Description : smrule-redir-from-svc-miss
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.1.1.11

Field Name : zoneStatsSmruleRedirFromSvcHit
Field Type : CounterBasedGauge64
Field Status : current
Description : smrule-redir-from-svc-hit
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.1.1.10

Field Name : zoneStatsBackupModeResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : backup-mode-response
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.1.1.9

Field Name : zoneStatsStickyModeResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : sticky-mode-response
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.1.1.8

Field Name : zoneStatsServerModeResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : server-mode-response
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.1.1.7

Field Name : zoneStatsCacheModeResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : cache-mode-response
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.1.1.6

Field Name : zoneStatsProxyModeResponse

Field Type : CounterBasedGauge64
Field Status : current
Description : proxy-mode-response
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.1.1.5

Field Name : zoneStatsSentResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : sent-response
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.1.1.4

Field Name : zoneStatsReceivedQuery
Field Type : CounterBasedGauge64
Field Status : current
Description : received-query
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.1.1.3

Field Name : zoneStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.1.1.2

Field Name : zoneStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.1.1.1

Field Name : dnsCaaRecordServiceStatsTable
Field Type : TABLE
Field Status : current
Description : Specify DNS CAA Record from object 'gslb.zone.service.dns-caa-record'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.14.1

Field Name : dnsCaaRecordServiceStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsCaaRecordServiceStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.14.1.1

Field Name : dnsCaaRecordServiceStatsHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.14.1.1.8

Field Name : dnsCaaRecordServiceStatsRdata
Field Type : String
Field Status : current
Description : rdata
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.14.1.1.7

Field Name : dnsCaaRecordServiceStatsPropertyTag
Field Type : String
Field Status : current
Description : property-tag
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.14.1.1.6

Field Name : dnsCaaRecordServiceStatsCriticalFlag
Field Type : Integer32
Field Status : current
Description : critical-flag
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.14.1.1.5

Field Name : dnsCaaRecordServiceStatsServiceName
Field Type : String
Field Status : current
Description : service-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.14.1.1.4

Field Name : dnsCaaRecordServiceStatsServicePort
Field Type : Integer32
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.14.1.1.3

Field Name : dnsCaaRecordServiceStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.14.1.1.2

Field Name : dnsCaaRecordServiceStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.14.1.1.1

Field Name : dnsTxtRecordStatsTable
Field Type : TABLE
Field Status : current
Description : Specify DNS TXT Record from object 'gslb.zone.service.dns-txt-record'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.13.1

Field Name : dnsTxtRecordStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsTxtRecordStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.13.1.1

Field Name : dnsTxtRecordStatsHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.13.1.1.6

Field Name : dnsTxtRecordStatsRecordName
Field Type : String
Field Status : current
Description : record-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.13.1.1.5

Field Name : dnsTxtRecordStatsServiceName
Field Type : String
Field Status : current

Description : service-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.13.1.1.4

Field Name : dnsTxtRecordStatsServicePort
Field Type : Integer32
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.13.1.1.3

Field Name : dnsTxtRecordStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.13.1.1.2

Field Name : dnsTxtRecordStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.13.1.1.1

Field Name : dnsNaptrRecordStatsTable
Field Type : TABLE
Field Status : current
Description : Specify DNS NAPTR Record from object 'gslb.zone.service.dns-naptr-record'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.12.1

Field Name : dnsNaptrRecordStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsNaptrRecordStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.12.1.1

Field Name : dnsNaptrRecordStatsNaptrHits
Field Type : CounterBasedGauge64
Field Status : current
Description : naptr-hits
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.12.1.1.8

Field Name : dnsNaptrRecordStatsFlag
Field Type : String
Field Status : current
Description : flag
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.12.1.1.7

Field Name : dnsNaptrRecordStatsServiceProto
Field Type : String
Field Status : current
Description : service-proto
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.12.1.1.6

Field Name : dnsNaptrRecordStatsNaptrTarget
Field Type : String
Field Status : current
Description : naptr-target
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.12.1.1.5

Field Name : dnsNaptrRecordStatsServiceName

Field Type : String
Field Status : current
Description : service-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.12.1.1.4

Field Name : dnsNaptrRecordStatsServicePort
Field Type : Integer32
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.12.1.1.3

Field Name : dnsNaptrRecordStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.12.1.1.2

Field Name : dnsNaptrRecordStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.12.1.1.1

Field Name : dnsSrvRecordStatsTable
Field Type : TABLE
Field Status : current
Description : Specify DNS SRV Record from object 'gslb.zone.service.dns-srv-record'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.11.1

Field Name : dnsSrvRecordStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsSrvRecordStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.11.1.1

Field Name : dnsSrvRecordStatsHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.11.1.1.7

Field Name : dnsSrvRecordStatsPort
Field Type : Integer32
Field Status : current
Description : port
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.11.1.1.6

Field Name : dnsSrvRecordStatsSrvName
Field Type : String
Field Status : current
Description : srv-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.11.1.1.5

Field Name : dnsSrvRecordStatsServiceName
Field Type : String
Field Status : current
Description : service-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.11.1.1.4

Field Name : dnsSrvRecordStatsServicePort
Field Type : Integer32
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.11.1.1.3

Field Name : dnsSrvRecordStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.11.1.1.2

Field Name : dnsSrvRecordStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.11.1.1.1

Field Name : dnsPtrRecordStatsTable
Field Type : TABLE
Field Status : current
Description : Specify DNS PTR Record from object 'gslb.zone.service.dns-ptr-record'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.10.1

Field Name : dnsPtrRecordStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsPtrRecordStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.10.1.1

Field Name : dnsPtrRecordStatsHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.10.1.1.6

Field Name : dnsPtrRecordStatsPtrName
Field Type : String
Field Status : current
Description : ptr-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.10.1.1.5

Field Name : dnsPtrRecordStatsServiceName
Field Type : String
Field Status : current
Description : service-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.10.1.1.4

Field Name : dnsPtrRecordStatsServicePort
Field Type : Integer32
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.10.1.1.3

Field Name : dnsPtrRecordStatsName
Field Type : String
Field Status : current

Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.10.1.1.2

Field Name : dnsPtrRecordStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.10.1.1.1

Field Name : dnsNsRecordServiceOperTable
Field Type : TABLE
Field Status : current
Description : Specify DNS NS Record from object 'gslb.zone.service.dns-ns-record'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.2

Field Name : dnsNsRecordServiceStatsTable
Field Type : TABLE
Field Status : current
Description : Specify DNS NS Record from object 'gslb.zone.service.dns-ns-record'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.1

Field Name : dnsNsRecordServiceStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsNsRecordServiceStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.1.1

Field Name : dnsNsRecordServiceStatsHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.1.1.6

Field Name : dnsNsRecordServiceStatsNsName
Field Type : String
Field Status : current
Description : ns-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.1.1.5

Field Name : dnsNsRecordServiceStatsServiceName
Field Type : String
Field Status : current
Description : service-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.1.1.4

Field Name : dnsNsRecordServiceStatsServicePort
Field Type : Integer32
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.1.1.3

Field Name : dnsNsRecordServiceStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.1.1.2

Field Name : dnsNsRecordServiceStatsSlotId

Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.1.1.1

Field Name : dnsNsRecordServiceOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsNsRecordServiceOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.2.1

Field Name : dnsNsRecordServiceOperHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.2.1.7

Field Name : dnsNsRecordServiceOperLastServer
Field Type : String
Field Status : current
Description : last-server
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.2.1.6

Field Name : dnsNsRecordServiceOperNsName
Field Type : String
Field Status : current
Description : ns-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.2.1.5

Field Name : dnsNsRecordServiceOperServiceName
Field Type : String
Field Status : current
Description : service-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.2.1.4

Field Name : dnsNsRecordServiceOperServicePort
Field Type : Integer32
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.2.1.3

Field Name : dnsNsRecordServiceOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.2.1.2

Field Name : dnsNsRecordServiceOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.2.1.1

Field Name : dnsMxRecordServiceOperTable
Field Type : TABLE
Field Status : current
Description : Specify DNS MX Record from object 'gslb.zone.service.dns-mx-record'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.2

Field Name : dnsMxRecordServiceStatsTable
Field Type : TABLE
Field Status : current
Description : Specify DNS MX Record from object 'gslb.zone.service.dns-mx-record'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.1

Field Name : dnsMxRecordServiceStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsMxRecordServiceStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.1.1

Field Name : dnsMxRecordServiceStatsHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.1.1.6

Field Name : dnsMxRecordServiceStatsMxName
Field Type : String
Field Status : current
Description : mx-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.1.1.5

Field Name : dnsMxRecordServiceStatsServiceName
Field Type : String
Field Status : current
Description : service-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.1.1.4

Field Name : dnsMxRecordServiceStatsServicePort
Field Type : Integer32
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.1.1.3

Field Name : dnsMxRecordServiceStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.1.1.2

Field Name : dnsMxRecordServiceStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.1.1.1

Field Name : dnsMxRecordServiceOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsMxRecordServiceOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.2.1

Field Name : dnsMxRecordServiceOperPriority
Field Type : CounterBasedGauge64
Field Status : current

Description : priority
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.2.1.8

Field Name : dnsMxRecordServiceOperHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.2.1.7

Field Name : dnsMxRecordServiceOperLastServer
Field Type : String
Field Status : current
Description : last-server
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.2.1.6

Field Name : dnsMxRecordServiceOperMxName
Field Type : String
Field Status : current
Description : mx-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.2.1.5

Field Name : dnsMxRecordServiceOperServiceName
Field Type : String
Field Status : current
Description : service-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.2.1.4

Field Name : dnsMxRecordServiceOperServicePort
Field Type : Integer32
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.2.1.3

Field Name : dnsMxRecordServiceOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.2.1.2

Field Name : dnsMxRecordServiceOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.2.1.1

Field Name : dnsCnameRecordStatsTable
Field Type : TABLE
Field Status : current
Description : Specify DNS CNAME Record from object 'gslb.zone.service.dns-cname-record'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.7.1

Field Name : dnsCnameRecordStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsCnameRecordStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.7.1.1

Field Name : dnsCnameRecordStatsCnameHits

Field Type : CounterBasedGauge64
Field Status : current
Description : cname-hits
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.7.1.1.6

Field Name : dnsCnameRecordStatsAliasName
Field Type : String
Field Status : current
Description : alias-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.7.1.1.5

Field Name : dnsCnameRecordStatsServiceName
Field Type : String
Field Status : current
Description : service-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.7.1.1.4

Field Name : dnsCnameRecordStatsServicePort
Field Type : Integer32
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.7.1.1.3

Field Name : dnsCnameRecordStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.7.1.1.2

Field Name : dnsCnameRecordStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.7.1.1.1

Field Name : dnsARecordIpv4StatsTable
Field Type : TABLE
Field Status : current
Description : Specify DNS Address Record from object 'gslb.zone.service.dns-a-record.dns-a-record-ipv4'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.3.1

Field Name : dnsARecordIpv4StatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsARecordIpv4Stats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.3.1.1

Field Name : dnsARecordIpv4StatsHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.3.1.1.6

Field Name : dnsARecordIpv4StatsIp
Field Type : String
Field Status : current
Description : dns-a-record-ip
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.3.1.1.5

Field Name : dnsARecordIpv4StatsServiceName
Field Type : String
Field Status : current
Description : service-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.3.1.1.4

Field Name : dnsARecordIpv4StatsServicePort
Field Type : Integer32
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.3.1.1.3

Field Name : dnsARecordIpv4StatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.3.1.1.2

Field Name : dnsARecordIpv4StatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.3.1.1.1

Field Name : dnsARecordSrvStatsTable
Field Type : TABLE
Field Status : current
Description : Specify DNS Address Record from object 'gslb.zone.service.dns-a-record.dns-a-record-srv'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.2.1

Field Name : dnsARecordSrvStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsARecordSrvStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.2.1.1

Field Name : dnsARecordSrvStatsHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.2.1.1.6

Field Name : dnsARecordSrvStatsSvrname
Field Type : String
Field Status : current
Description : svrname
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.2.1.1.5

Field Name : dnsARecordSrvStatsServiceName
Field Type : String
Field Status : current
Description : service-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.2.1.1.4

Field Name : dnsARecordSrvStatsServicePort
Field Type : Integer32
Field Status : current

Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.2.1.1.3

Field Name : dnsARecordSrvStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.2.1.1.2

Field Name : dnsARecordSrvStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.2.1.1.1

Field Name : dnsARecordIpv6StatsTable
Field Type : TABLE
Field Status : current
Description : Specify DNS Address Record from object 'gslb.zone.service.dns-a-record.dns-a-record-ipv6'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.4.1

Field Name : dnsARecordIpv6StatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsARecordIpv6Stats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.4.1.1

Field Name : dnsARecordIpv6StatsHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.4.1.1.6

Field Name : dnsARecordIpv6StatsIpv6
Field Type : String
Field Status : current
Description : dns-a-record-ipv6
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.4.1.1.5

Field Name : dnsARecordIpv6StatsServiceName
Field Type : String
Field Status : current
Description : service-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.4.1.1.4

Field Name : dnsARecordIpv6StatsServicePort
Field Type : Integer32
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.4.1.1.3

Field Name : dnsARecordIpv6StatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.4.1.1.2

Field Name : dnsARecordIpv6StatsSlotId

Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.4.1.1.1

Field Name : serviceOperDnsARecordListTable
Field Type : TABLE
Field Status : current
Description : Service information for the GSLB zone from object 'gslb.zone.service'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.5

Field Name : serviceOperDnsARecordListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceOperDnsARecordList entry:dns-a-record-list
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.5.1

Field Name : serviceOperDnsARecordListRecTtl
Field Type : CounterBasedGauge64
Field Status : current
Description : rec-ttl
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.5.1.7

Field Name : serviceOperDnsARecordListIp
Field Type : String
Field Status : current
Description : ip
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.5.1.6

Field Name : serviceOperDnsARecordListDnsARecordListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.5.1.5

Field Name : serviceOperDnsARecordListServiceName
Field Type : String
Field Status : current
Description : service-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.5.1.4

Field Name : serviceOperDnsARecordListServicePort
Field Type : Integer32
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.5.1.3

Field Name : serviceOperDnsARecordListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.5.1.2

Field Name : serviceOperDnsARecordListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.5.1.1

Field Name : serviceOperSessionListTable
Field Type : TABLE
Field Status : current
Description : Service information for the GSLB zone from object 'gslb.zone.service'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.4

Field Name : serviceOperSessionListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceOperSessionList entry:session-list
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.4.1

Field Name : serviceOperSessionListAging
Field Type : CounterBasedGauge64
Field Status : current
Description : aging
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.4.1.13

Field Name : serviceOperSessionListUpdate
Field Type : CounterBasedGauge64
Field Status : current
Description : update
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.4.1.12

Field Name : serviceOperSessionListTtl
Field Type : String
Field Status : current
Description : ttl
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.4.1.11

Field Name : serviceOperSessionListLastSecondHits
Field Type : CounterBasedGauge64
Field Status : current
Description : last-second-hits
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.4.1.10

Field Name : serviceOperSessionListHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.4.1.9

Field Name : serviceOperSessionListMode
Field Type : String
Field Status : current
Description : mode
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.4.1.8

Field Name : serviceOperSessionListBest
Field Type : String
Field Status : current
Description : best
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.4.1.7

Field Name : serviceOperSessionListClient
Field Type : String
Field Status : current

Description : client
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.4.1.6

Field Name : serviceOperSessionListSessionListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.4.1.5

Field Name : serviceOperSessionListServiceName
Field Type : String
Field Status : current
Description : service-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.4.1.4

Field Name : serviceOperSessionListServicePort
Field Type : Integer32
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.4.1.3

Field Name : serviceOperSessionListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.4.1.2

Field Name : serviceOperSessionListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.4.1.1

Field Name : serviceOperCacheListTable
Field Type : TABLE
Field Status : current
Description : Service information for the GSLB zone from object 'gslb.zone.service'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.3

Field Name : serviceOperCacheListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceOperCacheList entry:cache-list
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.3.1

Field Name : serviceOperCacheListAdditionalRecords
Field Type : CounterBasedGauge64
Field Status : current
Description : additional-records
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.3.1.13

Field Name : serviceOperCacheListAuthorityRecords
Field Type : CounterBasedGauge64
Field Status : current
Description : authority-records
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.3.1.12

Field Name : serviceOperCacheListAnswerRecords

Field Type : CounterBasedGauge64
Field Status : current
Description : answer-records
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.3.1.11

Field Name : serviceOperCacheListQuestionRecords
Field Type : CounterBasedGauge64
Field Status : current
Description : question-records
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.3.1.10

Field Name : serviceOperCacheListCacheDnsFlag
Field Type : String
Field Status : current
Description : cache-dns-flag
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.3.1.9

Field Name : serviceOperCacheListCacheTtl
Field Type : CounterBasedGauge64
Field Status : current
Description : cache-ttl
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.3.1.8

Field Name : serviceOperCacheListCacheLength
Field Type : CounterBasedGauge64
Field Status : current
Description : cache-length
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.3.1.7

Field Name : serviceOperCacheListAlias
Field Type : String
Field Status : current
Description : alias
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.3.1.6

Field Name : serviceOperCacheListCacheListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.3.1.5

Field Name : serviceOperCacheListServiceName
Field Type : String
Field Status : current
Description : service-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.3.1.4

Field Name : serviceOperCacheListServicePort
Field Type : Integer32
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.3.1.3

Field Name : serviceOperCacheListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.3.1.2

Field Name : serviceOperCacheListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.3.1.1

Field Name : serviceOperTable
Field Type : TABLE
Field Status : current
Description : Service information for the GSLB zone from object 'gslb.zone.service'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.2

Field Name : serviceOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.2.1

Field Name : serviceOperTotalSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : total-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.2.1.7

Field Name : serviceOperMatched
Field Type : CounterBasedGauge64
Field Status : current
Description : matched
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.2.1.6

Field Name : serviceOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.2.1.5

Field Name : serviceOperServiceName
Field Type : String
Field Status : current
Description : service-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.2.1.4

Field Name : serviceOperServicePort
Field Type : Integer32
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.2.1.3

Field Name : serviceOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.2.1.2

Field Name : serviceOperSlotId
Field Type : Integer32
Field Status : current

Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.2.1.1

Field Name : serviceStatsTable
Field Type : TABLE
Field Status : current
Description : Service information for the GSLB zone from object 'gslb.zone.service'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.1

Field Name : serviceStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.1.1

Field Name : serviceStatsSmruleRedirFromSvcMiss
Field Type : CounterBasedGauge64
Field Status : current
Description : smrule-redir-from-svc-miss
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.1.1.13

Field Name : serviceStatsSmruleRedirFromSvcHit
Field Type : CounterBasedGauge64
Field Status : current
Description : smrule-redir-from-svc-hit
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.1.1.12

Field Name : serviceStatsBackupModeResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : backup-mode-response
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.1.1.11

Field Name : serviceStatsStickyModeResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : sticky-mode-response
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.1.1.10

Field Name : serviceStatsServerModeResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : server-mode-response
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.1.1.9

Field Name : serviceStatsCacheModeResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : cache-mode-response
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.1.1.8

Field Name : serviceStatsProxyModeResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : proxy-mode-response
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.1.1.7

Field Name : serviceStatsSentResponse

Field Type : CounterBasedGauge64
Field Status : current
Description : sent-response
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.1.1.6

Field Name : serviceStatsReceivedQuery
Field Type : CounterBasedGauge64
Field Status : current
Description : received-query
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.1.1.5

Field Name : serviceStatsServiceName
Field Type : String
Field Status : current
Description : service-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.1.1.4

Field Name : serviceStatsServicePort
Field Type : Integer32
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.1.1.3

Field Name : serviceStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.1.1.2

Field Name : serviceStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.1.1.1

Field Name : servicePortOperTable
Field Type : TABLE
Field Status : current
Description : from object 'gslb.service-port'
OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2

Field Name : servicePortOperServicePortListTable
Field Type : TABLE
Field Status : current
Description : from object 'gslb.service-port'
OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2

Field Name : servicePortOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The servicePortOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2.1

Field Name : servicePortOperServicePortListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The servicePortOperServicePortList entry:service-port-list
OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2.1

Field Name : servicePortOperServicePortListServiceHcode
Field Type : CounterBasedGauge64
Field Status : current
Description : service-hcode
OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2.1.9

Field Name : servicePortOperServicePortListServiceLabel
Field Type : String
Field Status : current
Description : service-label
OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2.1.8

Field Name : servicePortOperServicePortListCurrentConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : current-connections
OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2.1.7

Field Name : servicePortOperServicePortListActiveRealServer
Field Type : CounterBasedGauge64
Field Status : current
Description : active-real-server
OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2.1.6

Field Name : servicePortOperServicePortListState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2.1.5

Field Name : servicePortOperPortCount
Field Type : CounterBasedGauge64
Field Status : current
Description : port-count
OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2.1.4

Field Name : servicePortOperServicePortListAttributes
Field Type : String
Field Status : current
Description : attributes
OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2.1.4

Field Name : servicePortOperLabel
Field Type : String
Field Status : current
Description : label
OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2.1.3

Field Name : servicePortOperServicePortListServicePortName
Field Type : String
Field Status : current
Description : service-port-name
OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2.1.3

Field Name : servicePortOperServiceHash
Field Type : CounterBasedGauge64
Field Status : current

Description : service-hash
OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2.1.2

Field Name : servicePortOperServicePortListServicePortListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2.1.2

Field Name : servicePortOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2.1.1

Field Name : servicePortOperServicePortListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2.1.1

Field Name : monitorOperTable
Field Type : TABLE
Field Status : current
Description : Configure NetFlow Monitor from object 'netflow.monitor'
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.2

Field Name : monitorOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The monitorOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.2.1

Field Name : monitorOperResendTemplateTimeout
Field Type : String
Field Status : current
Description : resend-template-timeout
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.2.1.12

Field Name : monitorOperResendTemplatePerRecords
Field Type : String
Field Status : current
Description : resend-template-per-records
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.2.1.11

Field Name : monitorOperCounterPollingInterval
Field Type : String
Field Status : current
Description : counter-polling-interval
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.2.1.10

Field Name : monitorOperFlowTimeout
Field Type : String
Field Status : current
Description : flow-timeout
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.2.1.9

Field Name : monitorOperSourceIpAddr

Field Type : String
Field Status : current
Description : source-ip-addr
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.2.1.8

Field Name : monitorOperSourceIpUseMgmt
Field Type : String
Field Status : current
Description : source-ip-use-mgmt
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.2.1.7

Field Name : monitorOperDestination
Field Type : String
Field Status : current
Description : destination
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.2.1.6

Field Name : monitorOperFilter
Field Type : String
Field Status : current
Description : filter
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.2.1.5

Field Name : monitorOperStatus
Field Type : String
Field Status : current
Description : status
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.2.1.4

Field Name : monitorOperProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.2.1.3

Field Name : monitorOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.2.1.2

Field Name : monitorOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.2.1.1

Field Name : monitorStatsTable
Field Type : TABLE
Field Status : current
Description : Configure NetFlow Monitor from object 'netflow.monitor'
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1

Field Name : monitorStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The monitorStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1

Field Name : monitorStatsDdosHttpStatRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : ddos-http-stat-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.131

Field Name : monitorStatsDdosHttpStatRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : ddos-http-stat-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.130

Field Name : monitorStatsDdosGeneralStatRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : ddos-general-stat-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.129

Field Name : monitorStatsDdosGeneralStatRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : ddos-general-stat-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.128

Field Name : monitorStatsCustomGtpRateLimitPeriodicRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-gtp-rate-limit-periodic-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.127

Field Name : monitorStatsCustomGtpRateLimitPeriodicRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-gtp-rate-limit-periodic-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.126

Field Name : monitorStatsCustomNatIddosL4EntryDeletedRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-nat-iddos-l4-entry-deleted-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.125

Field Name : monitorStatsCustomNatIddosL4EntryDeletedRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-nat-iddos-l4-entry-deleted-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.124

Field Name : monitorStatsCustomNatIddosL4EntryCreatedRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-nat-iddos-l4-entry-created-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.123

Field Name : monitorStatsCustomNatIddosL4EntryCreatedRecordsSent
Field Type : CounterBasedGauge64
Field Status : current

Description : custom-nat-iddos-l4-entry-created-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.122

Field Name : monitorStatsCustomNatIddosL3EntryDeletedRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-nat-iddos-l3-entry-deleted-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.121

Field Name : monitorStatsCustomNatIddosL3EntryDeletedRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-nat-iddos-l3-entry-deleted-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.120

Field Name : monitorStatsCustomNatIddosL3EntryCreatedRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-nat-iddos-l3-entry-created-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.119

Field Name : monitorStatsCustomNatIddosL3EntryCreatedRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-nat-iddos-l3-entry-created-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.118

Field Name : monitorStatsCustomFwSesnLimitExceededRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-fw-sesn-limit-exceeded-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.117

Field Name : monitorStatsCustomFwSesnLimitExceededRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-fw-sesn-limit-exceeded-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.116

Field Name : monitorStatsCustomFwIddosEntryDeletedRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-fw-iddos-entry-deleted-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.115

Field Name : monitorStatsCustomFwIddosEntryDeletedRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-fw-iddos-entry-deleted-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.114

Field Name : monitorStatsCustomFwIddosEntryCreatedRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-fw-iddos-entry-created-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.113

Field Name : monitorStatsCustomFwIddosEntryCreatedRecordsSent

Field Type : CounterBasedGauge64
Field Status : current
Description : custom-fw-iddos-entry-created-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.112

Field Name : monitorStatsCustomGtpInfoEventRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-gtp-info-event-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.111

Field Name : monitorStatsCustomGtpInfoEventRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-gtp-info-event-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.110

Field Name : monitorStatsCustomGtpDenyEventRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-gtp-deny-event-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.109

Field Name : monitorStatsCustomGtpDenyEventRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-gtp-deny-event-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.108

Field Name : monitorStatsCustomGtpUTunnelEventRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-gtp-u-tunnel-event-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.107

Field Name : monitorStatsCustomGtpUTunnelEventRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-gtp-u-tunnel-event-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.106

Field Name : monitorStatsCustomGtpCTunnelEventRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-gtp-c-tunnel-event-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.105

Field Name : monitorStatsCustomGtpCTunnelEventRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-gtp-c-tunnel-event-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.104

Field Name : monitorStatsReducedLogsByDestination
Field Type : CounterBasedGauge64
Field Status : current
Description : reduced-logs-by-destination
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.103

Field Name : monitorStatsCustomPortBatchingV2DsliteDeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-v2-dslite-deletion-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.102

Field Name : monitorStatsCustomPortBatchingV2DsliteDeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-v2-dslite-deletion-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.101

Field Name : monitorStatsCustomPortBatchingV2Nat64DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-v2-nat64-deletion-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.100

Field Name : monitorStatsCustomPortBatchingV2Nat64DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-v2-nat64-deletion-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.99

Field Name : monitorStatsCustomPortBatchingV2Nat44DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-v2-nat44-deletion-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.98

Field Name : monitorStatsCustomPortBatchingV2Nat44DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-v2-nat44-deletion-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.97

Field Name : monitorStatsCustomPortBatchingV2DsliteCreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-v2-dslite-creation-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.96

Field Name : monitorStatsCustomPortBatchingV2DsliteCreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-v2-dslite-creation-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.95

Field Name : monitorStatsCustomPortBatchingV2Nat64CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-v2-nat64-creation-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.94

Field Name : monitorStatsCustomPortBatchingV2Nat64CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current

Description : custom-port-batching-v2-nat64-creation-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.93

Field Name : monitorStatsCustomPortBatchingV2Nat44CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-v2-nat44-creation-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.92

Field Name : monitorStatsCustomPortBatchingV2Nat44CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-v2-nat44-creation-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.91

Field Name : monitorStatsCustomPortBatchingDsliteDeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-dslite-deletion-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.90

Field Name : monitorStatsCustomPortBatchingDsliteDeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-dslite-deletion-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.89

Field Name : monitorStatsCustomPortBatchingNat64DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-nat64-deletion-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.88

Field Name : monitorStatsCustomPortBatchingNat64DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-nat64-deletion-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.87

Field Name : monitorStatsCustomPortBatchingNat44DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-nat44-deletion-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.86

Field Name : monitorStatsCustomPortBatchingNat44DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-nat44-deletion-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.85

Field Name : monitorStatsCustomPortBatchingDsliteCreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-dslite-creation-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.84

Field Name : monitorStatsCustomPortBatchingDsliteCreationRecordsSent

Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-dslite-creation-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.83

Field Name : monitorStatsCustomPortBatchingNat64CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-nat64-creation-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.82

Field Name : monitorStatsCustomPortBatchingNat64CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-nat64-creation-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.81

Field Name : monitorStatsCustomPortBatchingNat44CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-nat44-creation-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.80

Field Name : monitorStatsCustomPortBatchingNat44CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-nat44-creation-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.79

Field Name : monitorStatsCustomPortMappingDsliteDeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-mapping-dslite-deletion-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.78

Field Name : monitorStatsCustomPortMappingDsliteDeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-mapping-dslite-deletion-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.77

Field Name : monitorStatsCustomPortMappingNat64DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-mapping-nat64-deletion-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.76

Field Name : monitorStatsCustomPortMappingNat64DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-mapping-nat64-deletion-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.75

Field Name : monitorStatsCustomPortMappingNat44DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-mapping-nat44-deletion-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.74

Field Name : monitorStatsCustomPortMappingNat44DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-mapping-nat44-deletion-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.73

Field Name : monitorStatsCustomPortMappingDsliteCreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-mapping-dslite-creation-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.72

Field Name : monitorStatsCustomPortMappingDsliteCreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-mapping-dslite-creation-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.71

Field Name : monitorStatsCustomPortMappingNat64CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-mapping-nat64-creation-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.70

Field Name : monitorStatsCustomPortMappingNat64CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-mapping-nat64-creation-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.69

Field Name : monitorStatsCustomPortMappingNat44CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-mapping-nat44-creation-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.68

Field Name : monitorStatsCustomPortMappingNat44CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-mapping-nat44-creation-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.67

Field Name : monitorStatsCustomDenyResetEventFw6RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-deny-reset-event-fw6-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.66

Field Name : monitorStatsCustomDenyResetEventFw6RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-deny-reset-event-fw6-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.65

Field Name : monitorStatsCustomDenyResetEventFw4RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current

Description : custom-deny-reset-event-fw4-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.64

Field Name : monitorStatsCustomDenyResetEventFw4RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-deny-reset-event-fw4-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.63

Field Name : monitorStatsCustomSessionEventFw6DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-fw6-deletion-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.62

Field Name : monitorStatsCustomSessionEventFw6DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-fw6-deletion-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.61

Field Name : monitorStatsCustomSessionEventFw4DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-fw4-deletion-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.60

Field Name : monitorStatsCustomSessionEventFw4DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-fw4-deletion-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.59

Field Name : monitorStatsCustomSessionEventFw6CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-fw6-creation-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.58

Field Name : monitorStatsCustomSessionEventFw6CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-fw6-creation-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.57

Field Name : monitorStatsCustomSessionEventFw4CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-fw4-creation-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.56

Field Name : monitorStatsCustomSessionEventFw4CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-fw4-creation-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.55

Field Name : monitorStatsCustomSessionEventDsliteDeletionRecordsSentFailure

Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-dslite-deletion-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.54

Field Name : monitorStatsCustomSessionEventDsliteDeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-dslite-deletion-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.53

Field Name : monitorStatsCustomSessionEventNat64DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-nat64-deletion-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.52

Field Name : monitorStatsCustomSessionEventNat64DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-nat64-deletion-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.51

Field Name : monitorStatsCustomSessionEventNat44DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-nat44-deletion-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.50

Field Name : monitorStatsCustomSessionEventNat44DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-nat44-deletion-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.49

Field Name : monitorStatsCustomSessionEventDsliteCreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-dslite-creation-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.48

Field Name : monitorStatsCustomSessionEventDsliteCreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-dslite-creation-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.47

Field Name : monitorStatsCustomSessionEventNat64CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-nat64-creation-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.46

Field Name : monitorStatsCustomSessionEventNat64CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-nat64-creation-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.45

Field Name : monitorStatsCustomSessionEventNat44CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-nat44-creation-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.44

Field Name : monitorStatsCustomSessionEventNat44CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-nat44-creation-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.43

Field Name : monitorStatsPortBatchingV2DsliteRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : port-batching-v2-dslite-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.42

Field Name : monitorStatsPortBatchingV2DsliteRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : port-batching-v2-dslite-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.41

Field Name : monitorStatsPortBatchingV2Nat64RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : port-batching-v2-nat64-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.40

Field Name : monitorStatsPortBatchingV2Nat64RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : port-batching-v2-nat64-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.39

Field Name : monitorStatsPortBatchingV2Nat44RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : port-batching-v2-nat44-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.38

Field Name : monitorStatsPortBatchingV2Nat44RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : port-batching-v2-nat44-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.37

Field Name : monitorStatsPortBatchingDsliteRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : port-batching-dslite-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.36

Field Name : monitorStatsPortBatchingDsliteRecordsSent
Field Type : CounterBasedGauge64
Field Status : current

Description : port-batching-dslite-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.35

Field Name : monitorStatsPortBatchingNat64RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : port-batching-nat64-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.34

Field Name : monitorStatsPortBatchingNat64RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : port-batching-nat64-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.33

Field Name : monitorStatsPortBatchingNat44RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : port-batching-nat44-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.32

Field Name : monitorStatsPortBatchingNat44RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : port-batching-nat44-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.31

Field Name : monitorStatsNetflowV5ExtRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : netflow-v5-ext-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.30

Field Name : monitorStatsNetflowV5ExtRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : netflow-v5-ext-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.29

Field Name : monitorStatsNetflowV5RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : netflow-v5-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.28

Field Name : monitorStatsNetflowV5RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : netflow-v5-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.27

Field Name : monitorStatsPortMappingDsliteRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : port-mapping-dslite-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.26

Field Name : monitorStatsPortMappingDsliteRecordsSent

Field Type : CounterBasedGauge64
Field Status : current
Description : port-mapping-dslite-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.25

Field Name : monitorStatsPortMappingNat64RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : port-mapping-nat64-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.24

Field Name : monitorStatsPortMappingNat64RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : port-mapping-nat64-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.23

Field Name : monitorStatsPortMappingNat44RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : port-mapping-nat44-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.22

Field Name : monitorStatsPortMappingNat44RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : port-mapping-nat44-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.21

Field Name : monitorStatsSessionEventFw6RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : session-event-fw6-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.20

Field Name : monitorStatsSessionEventFw6RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : session-event-fw6-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.19

Field Name : monitorStatsSessionEventFw4RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : session-event-fw4-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.18

Field Name : monitorStatsSessionEventFw4RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : session-event-fw4-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.17

Field Name : monitorStatsSessionEventDsliteRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : session-event-dslite-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.16

Field Name : monitorStatsSessionEventDsliteRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : session-event-dslite-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.15

Field Name : monitorStatsSessionEventNat64RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : session-event-nat64-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.14

Field Name : monitorStatsSessionEventNat64RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : session-event-nat64-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.13

Field Name : monitorStatsSessionEventNat44RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : session-event-nat44-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.12

Field Name : monitorStatsSessionEventNat44RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : session-event-nat44-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.11

Field Name : monitorStatsDsliteRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : dslite-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.10

Field Name : monitorStatsDsliteRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : dslite-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.9

Field Name : monitorStatsNat64RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : nat64-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.8

Field Name : monitorStatsNat64RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : nat64-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.7

Field Name : monitorStatsNat44RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current

Description : nat44-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.6

Field Name : monitorStatsNat44RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : nat44-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.5

Field Name : monitorStatsBytesSent
Field Type : CounterBasedGauge64
Field Status : current
Description : bytes-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.4

Field Name : monitorStatsPacketsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : packets-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.3

Field Name : monitorStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.2

Field Name : monitorStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.1

Field Name : ruleSetOperRuleStatsTable
Field Type : TABLE
Field Status : current
Description : Configure Security policy Rule Set from object 'rule-set'
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.3

Field Name : ruleSetOperTable
Field Type : TABLE
Field Status : current
Description : Configure Security policy Rule Set from object 'rule-set'
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2

Field Name : ruleSetOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The ruleSetOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1

Field Name : ruleSetOperTopnRules
Field Type : String
Field Status : current
Description : topn-rules
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.23

Field Name : ruleSetOperShowTotalStats

Field Type : String
Field Status : current
Description : show-total-stats
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.22

Field Name : ruleSetOperTotalActiveOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : total-active-others
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.21

Field Name : ruleSetOperTotalActiveIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : total-active-icmp
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.20

Field Name : ruleSetOperTotalActiveUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : total-active-udp
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.19

Field Name : ruleSetOperTotalActiveTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : total-active-tcp
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.18

Field Name : ruleSetOperTotalPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : total-packets
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.17

Field Name : ruleSetOperTotalResetPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : total-reset-packets
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.16

Field Name : ruleSetOperTotalDenyPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : total-deny-packets
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.15

Field Name : ruleSetOperTotalPermitPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : total-permit-packets
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.14

Field Name : ruleSetOperTotalBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total-bytes
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.13

Field Name : ruleSetOperTotalResetBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total-reset-bytes
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.12

Field Name : ruleSetOperTotalDenyBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total-deny-bytes
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.11

Field Name : ruleSetOperTotalPermitBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total-permit-bytes
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.10

Field Name : ruleSetOperTotalHit
Field Type : CounterBasedGauge64
Field Status : current
Description : total-hit
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.9

Field Name : ruleSetOperPolicyRuleCount
Field Type : CounterBasedGauge64
Field Status : current
Description : policy-rule-count
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.8

Field Name : ruleSetOperPolicyReset
Field Type : CounterBasedGauge64
Field Status : current
Description : policy-reset
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.7

Field Name : ruleSetOperPolicyDeny
Field Type : CounterBasedGauge64
Field Status : current
Description : policy-deny
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.6

Field Name : ruleSetOperPolicyPermit
Field Type : CounterBasedGauge64
Field Status : current
Description : policy-permit
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.5

Field Name : ruleSetOperPolicyUnmatchedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : policy-unmatched-drop
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.4

Field Name : ruleSetOperPolicyStatus
Field Type : String
Field Status : current

Description : policy-status
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.3

Field Name : ruleSetOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.2

Field Name : ruleSetOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.1

Field Name : ruleSetStatsTable
Field Type : TABLE
Field Status : current
Description : Configure Security policy Rule Set from object 'rule-set'
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.1

Field Name : ruleSetStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The ruleSetStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.1.1

Field Name : ruleSetStatsReset
Field Type : CounterBasedGauge64
Field Status : current
Description : reset
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.1.1.6

Field Name : ruleSetStatsDeny
Field Type : CounterBasedGauge64
Field Status : current
Description : deny
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.1.1.5

Field Name : ruleSetStatsPermit
Field Type : CounterBasedGauge64
Field Status : current
Description : permit
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.1.1.4

Field Name : ruleSetStatsUnmatchedDrops
Field Type : CounterBasedGauge64
Field Status : current
Description : unmatched-drops
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.1.1.3

Field Name : ruleSetStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.1.1.2

Field Name : ruleSetStatsSlotId

Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.1.1.1

Field Name : ruleSetOperRuleStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The ruleSetOperRuleStats entry:rule-stats
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.3.1

Field Name : ruleSetOperRuleStatsRuleStatus
Field Type : String
Field Status : current
Description : rule-status
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.3.1.7

Field Name : ruleSetOperRuleStatsRuleAction
Field Type : String
Field Status : current
Description : rule-action
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.3.1.6

Field Name : ruleSetOperRuleStatsRuleHitcount
Field Type : CounterBasedGauge64
Field Status : current
Description : rule-hitcount
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.3.1.5

Field Name : ruleSetOperRuleStatsRuleName
Field Type : String
Field Status : current
Description : rule-name
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.3.1.4

Field Name : ruleSetOperRuleStatsRuleStatsListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.3.1.3

Field Name : ruleSetOperRuleStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.3.1.2

Field Name : ruleSetOperRuleStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.3.1.1

Field Name : ruleOperTable
Field Type : TABLE
Field Status : current
Description : Configure rule-set rule from object 'rule-set.rule'
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2

Field Name : ruleOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The ruleOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1

Field Name : ruleOperTcphalfopencount
Field Type : CounterBasedGauge64
Field Status : current
Description : tcphalfopencount
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.33

Field Name : ruleOperVerificationfailed
Field Type : CounterBasedGauge64
Field Status : current
Description : verificationfailed
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.32

Field Name : ruleOperVerificationpassed
Field Type : CounterBasedGauge64
Field Status : current
Description : verificationpassed
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.31

Field Name : ruleOperSynacksent
Field Type : CounterBasedGauge64
Field Status : current
Description : synacksent
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.30

Field Name : ruleOperSyncookieon
Field Type : CounterBasedGauge64
Field Status : current
Description : syncookieon
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.29

Field Name : ruleOperRatelimitdrops
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimitdrops
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.28

Field Name : ruleOperSessiontotal
Field Type : CounterBasedGauge64
Field Status : current
Description : sessiontotal
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.27

Field Name : ruleOperSessionother
Field Type : CounterBasedGauge64
Field Status : current
Description : sessionother
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.26

Field Name : ruleOperSessionsctp
Field Type : CounterBasedGauge64
Field Status : current

Description : sessionsctp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.25

Field Name : ruleOperSessionicmp
Field Type : CounterBasedGauge64
Field Status : current
Description : sessionicmp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.24

Field Name : ruleOperSessionudp
Field Type : CounterBasedGauge64
Field Status : current
Description : sessionudp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.23

Field Name : ruleOperSessiontcp
Field Type : CounterBasedGauge64
Field Status : current
Description : sessiontcp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.22

Field Name : ruleOperActivesessiontotal
Field Type : CounterBasedGauge64
Field Status : current
Description : activesessiontotal
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.21

Field Name : ruleOperActivesessionother
Field Type : CounterBasedGauge64
Field Status : current
Description : activesessionother
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.20

Field Name : ruleOperActivesessionsctp
Field Type : CounterBasedGauge64
Field Status : current
Description : activesessionsctp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.19

Field Name : ruleOperActivesessionicmp
Field Type : CounterBasedGauge64
Field Status : current
Description : activesessionicmp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.18

Field Name : ruleOperActivesessionudp
Field Type : CounterBasedGauge64
Field Status : current
Description : activesessionudp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.17

Field Name : ruleOperActivesessiontcp
Field Type : CounterBasedGauge64
Field Status : current
Description : activesessiontcp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.16

Field Name : ruleOperTotalpackets

Field Type : CounterBasedGauge64
Field Status : current
Description : totalpackets
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.15

Field Name : ruleOperResetpackets
Field Type : CounterBasedGauge64
Field Status : current
Description : resetpackets
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.14

Field Name : ruleOperDenypackets
Field Type : CounterBasedGauge64
Field Status : current
Description : denypackets
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.13

Field Name : ruleOperPermitpackets
Field Type : CounterBasedGauge64
Field Status : current
Description : permitpackets
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.12

Field Name : ruleOperTotalbytes
Field Type : CounterBasedGauge64
Field Status : current
Description : totalbytes
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.11

Field Name : ruleOperResetbytes
Field Type : CounterBasedGauge64
Field Status : current
Description : resetbytes
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.10

Field Name : ruleOperDenybytes
Field Type : CounterBasedGauge64
Field Status : current
Description : denybytes
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.9

Field Name : ruleOperPermitbytes
Field Type : CounterBasedGauge64
Field Status : current
Description : permitbytes
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.8

Field Name : ruleOperStatus
Field Type : String
Field Status : current
Description : status
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.7

Field Name : ruleOperAction
Field Type : String
Field Status : current
Description : action
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.6

Field Name : ruleOperLastHitcountTime
Field Type : String
Field Status : current
Description : last-hitcount-time
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.5

Field Name : ruleOperHitcount
Field Type : CounterBasedGauge64
Field Status : current
Description : hitcount
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.4

Field Name : ruleOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.3

Field Name : ruleOperRuleSetName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.2

Field Name : ruleOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.1

Field Name : ruleStatsTable
Field Type : TABLE
Field Status : current
Description : Configure rule-set rule from object 'rule-set.rule'
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1

Field Name : ruleStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The ruleStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1

Field Name : ruleStatsTcpHalfOpenCount
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-half-open-count
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.27

Field Name : ruleStatsSynCookieConnSetupFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : syn-cookie-conn-setup-failed
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.26

Field Name : ruleStatsSynCookieVerificationFailed
Field Type : CounterBasedGauge64
Field Status : current

Description : syn-cookie-verification-failed
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.25

Field Name : ruleStatsSynCookieVerificationPassed
Field Type : CounterBasedGauge64
Field Status : current
Description : syn-cookie-verification-passed
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.24

Field Name : ruleStatsSynCookieSynAckSent
Field Type : CounterBasedGauge64
Field Status : current
Description : syn-cookie-syn-ack-sent
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.23

Field Name : ruleStatsRateLimitDrops
Field Type : CounterBasedGauge64
Field Status : current
Description : rate-limit-drops
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.22

Field Name : ruleStatsHitcountTimestamp
Field Type : CounterBasedGauge64
Field Status : current
Description : hitcount-timestamp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.21

Field Name : ruleStatsSessionSctp
Field Type : CounterBasedGauge64
Field Status : current
Description : session-sctp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.20

Field Name : ruleStatsActiveSessionSctp
Field Type : CounterBasedGauge64
Field Status : current
Description : active-session-sctp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.19

Field Name : ruleStatsSessionOther
Field Type : CounterBasedGauge64
Field Status : current
Description : session-other
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.18

Field Name : ruleStatsSessionIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : session-icmp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.17

Field Name : ruleStatsSessionUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : session-udp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.16

Field Name : ruleStatsSessionTcp

Field Type : CounterBasedGauge64
Field Status : current
Description : session-tcp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.15

Field Name : ruleStatsActiveSessionOther
Field Type : CounterBasedGauge64
Field Status : current
Description : active-session-other
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.14

Field Name : ruleStatsActiveSessionIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : active-session-icmp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.13

Field Name : ruleStatsActiveSessionUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : active-session-udp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.12

Field Name : ruleStatsActiveSessionTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : active-session-tcp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.11

Field Name : ruleStatsResetPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : reset-packets
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.10

Field Name : ruleStatsDenyPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : deny-packets
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.9

Field Name : ruleStatsPermitPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : permit-packets
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.8

Field Name : ruleStatsResetBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : reset-bytes
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.7

Field Name : ruleStatsDenyBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : deny-bytes
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.6

Field Name : ruleStatsPermitBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : permit-bytes
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.5

Field Name : ruleStatsHitCount
Field Type : CounterBasedGauge64
Field Status : current
Description : hit-count
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.4

Field Name : ruleStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.3

Field Name : ruleStatsRuleSetName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.2

Field Name : ruleStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.1

Field Name : rulesByZoneOperGroupListRuleListDscpListTable
Field Type : TABLE
Field Status : current
Description : from object 'rule-set.rules-by-zone'
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.7

Field Name : rulesByZoneOperGroupListRuleListServiceListTable
Field Type : TABLE
Field Status : current
Description : from object 'rule-set.rules-by-zone'
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.6

Field Name : rulesByZoneOperGroupListRuleListServiceListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The rulesByZoneOperGroupListRuleListServiceList entry:service-list
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.6.1

Field Name : rulesByZoneOperGroupListRuleListServiceListService
Field Type : String
Field Status : current
Description : service
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.6.1.6

Field Name : rulesByZoneOperGroupListRuleListServiceListServiceListListId
Field Type : Integer32
Field Status : current

Description :
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.6.1.5

Field Name : rulesByZoneOperGroupListRuleListServiceListRuleListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.6.1.4

Field Name : rulesByZoneOperGroupListRuleListServiceListGroupListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.6.1.3

Field Name : rulesByZoneOperGroupListRuleListServiceListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.6.1.2

Field Name : rulesByZoneOperGroupListRuleListServiceListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.6.1.1

Field Name : rulesByZoneOperGroupListRuleListDestListTable
Field Type : TABLE
Field Status : current
Description : from object 'rule-set.rules-by-zone'
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.5

Field Name : rulesByZoneOperGroupListRuleListDestListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The rulesByZoneOperGroupListRuleListDestList entry:dest-list
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.5.1

Field Name : rulesByZoneOperGroupListRuleListDestListDest
Field Type : String
Field Status : current
Description : dest
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.5.1.6

Field Name : rulesByZoneOperGroupListRuleListDestListDestListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.5.1.5

Field Name : rulesByZoneOperGroupListRuleListDestListRuleListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.5.1.4

Field Name : rulesByZoneOperGroupListRuleListDestListGroupListListId

Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.5.1.3

Field Name : rulesByZoneOperGroupListRuleListDestListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.5.1.2

Field Name : rulesByZoneOperGroupListRuleListDestListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.5.1.1

Field Name : rulesByZoneOperGroupListRuleListSourceListTable
Field Type : TABLE
Field Status : current
Description : from object 'rule-set.rules-by-zone'
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.4

Field Name : rulesByZoneOperGroupListRuleListSourceListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The rulesByZoneOperGroupListRuleListSourceList entry:source-list
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.4.1

Field Name : rulesByZoneOperGroupListRuleListSourceListSource
Field Type : String
Field Status : current
Description : source
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.4.1.6

Field Name : rulesByZoneOperGroupListRuleListSourceListSourceListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.4.1.5

Field Name : rulesByZoneOperGroupListRuleListSourceListRuleListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.4.1.4

Field Name : rulesByZoneOperGroupListRuleListSourceListGroupListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.4.1.3

Field Name : rulesByZoneOperGroupListRuleListSourceListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.4.1.2

Field Name : rulesByZoneOperGroupListRuleListSourceListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.4.1.1

Field Name : rulesByZoneOperGroupListRuleListTable
Field Type : TABLE
Field Status : current
Description : from object 'rule-set.rules-by-zone'
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.3

Field Name : rulesByZoneOperGroupListRuleListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The rulesByZoneOperGroupListRuleList entry:rule-list
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.3.1

Field Name : rulesByZoneOperGroupListRuleListAction
Field Type : String
Field Status : current
Description : action
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.3.1.6

Field Name : rulesByZoneOperGroupListRuleListName1
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.3.1.5

Field Name : rulesByZoneOperGroupListRuleListRuleListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.3.1.4

Field Name : rulesByZoneOperGroupListRuleListGroupListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.3.1.3

Field Name : rulesByZoneOperGroupListRuleListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.3.1.2

Field Name : rulesByZoneOperGroupListRuleListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.3.1.1

Field Name : rulesByZoneOperGroupListTable
Field Type : TABLE
Field Status : current

Description : from object 'rule-set.rules-by-zone'
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.2

Field Name : rulesByZoneOperGroupListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The rulesByZoneOperGroupList entry:group-list
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.2.1

Field Name : rulesByZoneOperGroupListTo
Field Type : String
Field Status : current
Description : to
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.2.1.5

Field Name : rulesByZoneOperGroupListFrom
Field Type : String
Field Status : current
Description : from
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.2.1.4

Field Name : rulesByZoneOperGroupListGroupListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.2.1.3

Field Name : rulesByZoneOperGroupListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.2.1.2

Field Name : rulesByZoneOperGroupListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.2.1.1

Field Name : rulesByZoneStatsTable
Field Type : TABLE
Field Status : current
Description : from object 'rule-set.rules-by-zone'
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.1

Field Name : rulesByZoneStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The rulesByZoneStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.1.1

Field Name : rulesByZoneStatsDummy
Field Type : CounterBasedGauge64
Field Status : current
Description : dummy
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.1.1.3

Field Name : rulesByZoneStatsName

Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.1.1.2

Field Name : rulesByZoneStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.1.1.1

Field Name : rulesByZoneOperGroupListRuleListDscpListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The rulesByZoneOperGroupListRuleListDscpList entry:dscp-list
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.7.1

Field Name : rulesByZoneOperGroupListRuleListDscpListDscp
Field Type : String
Field Status : current
Description : dscp
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.7.1.6

Field Name : rulesByZoneOperGroupListRuleListDscpListDscpListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.7.1.5

Field Name : rulesByZoneOperGroupListRuleListDscpListRuleListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.7.1.4

Field Name : rulesByZoneOperGroupListRuleListDscpListGroupListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.7.1.3

Field Name : rulesByZoneOperGroupListRuleListDscpListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.7.1.2

Field Name : rulesByZoneOperGroupListRuleListDscpListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.7.1.1

Field Name : appOperGroupListTable
Field Type : TABLE
Field Status : current
Description : Show application firewall supported protocols from object 'fw.app'
OID : 1.3.6.1.4.1.22610.2.4.8.477.1.3

Field Name : appOperTable
Field Type : TABLE
Field Status : current
Description : Show application firewall supported protocols from object 'fw.app'
OID : 1.3.6.1.4.1.22610.2.4.8.477.1.2

Field Name : appOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The appOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.477.1.2.1

Field Name : appOperRelated
Field Type : String
Field Status : current
Description : related
OID : 1.3.6.1.4.1.22610.2.4.8.477.1.2.1.4

Field Name : appOperContains
Field Type : String
Field Status : current
Description : contains
OID : 1.3.6.1.4.1.22610.2.4.8.477.1.2.1.3

Field Name : appOperCategory
Field Type : String
Field Status : current
Description : category
OID : 1.3.6.1.4.1.22610.2.4.8.477.1.2.1.2

Field Name : appOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.477.1.2.1.1

Field Name : appStatsTable
Field Type : TABLE
Field Status : current
Description : Show application firewall supported protocols from object 'fw.app'
OID : 1.3.6.1.4.1.22610.2.4.8.477.1.1

Field Name : appStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The appStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.477.1.1.1

Field Name : appStatsDummy
Field Type : CounterBasedGauge64
Field Status : current
Description : dummy
OID : 1.3.6.1.4.1.22610.2.4.8.477.1.1.1.2

Field Name : appStatsSlotId
Field Type : Integer32
Field Status : current

Description :
OID : 1.3.6.1.4.1.22610.2.4.8.477.1.1.1.1

Field Name : appOperGroupListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The appOperGroupList entry:group-list
OID : 1.3.6.1.4.1.22610.2.4.8.477.1.3.1

Field Name : appOperGroupListAppDesc
Field Type : String
Field Status : current
Description : app-desc
OID : 1.3.6.1.4.1.22610.2.4.8.477.1.3.1.5

Field Name : appOperGroupListAppName
Field Type : String
Field Status : current
Description : app-name
OID : 1.3.6.1.4.1.22610.2.4.8.477.1.3.1.4

Field Name : appOperGroupListCategoryName
Field Type : String
Field Status : current
Description : category-name
OID : 1.3.6.1.4.1.22610.2.4.8.477.1.3.1.3

Field Name : appOperGroupListGroupListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.477.1.3.1.2

Field Name : appOperGroupListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.477.1.3.1.1

Field Name : serverOperTable
Field Type : TABLE
Field Status : current
Description : Firewall logging Server from object 'fw.server'
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.2

Field Name : serverOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serverOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.2.1

Field Name : serverOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.2.1.3

Field Name : serverOperName

Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.2.1.2

Field Name : serverOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.2.1.1

Field Name : serverStatsTable
Field Type : TABLE
Field Status : current
Description : Firewall logging Server from object 'fw.server'
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.1

Field Name : serverStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serverStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.1.1

Field Name : serverStatsPeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : peak-conn
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.1.1.7

Field Name : serverStatsRevPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : rev-pkt
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.1.1.6

Field Name : serverStatsFwdPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : fwd-pkt
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.1.1.5

Field Name : serverStatsTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : total-conn
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.1.1.4

Field Name : serverStatsCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : curr-conn
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.1.1.3

Field Name : serverStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.1.1.2

Field Name : serverStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.1.1.1

Field Name : portOperTable
Field Type : TABLE
Field Status : current
Description : Real Server Port from object 'fw.server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.2

Field Name : portStatsTable
Field Type : TABLE
Field Status : current
Description : Real Server Port from object 'fw.server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1

Field Name : portStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1

Field Name : portStatsSlowestRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : slowest_rsp_time
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.28

Field Name : portStatsFastestRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : fastest_rsp_time
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.27

Field Name : portStatsResponseTime
Field Type : CounterBasedGauge64
Field Status : current
Description : response_time
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.26

Field Name : portStatsTotalRevPktsInspectedGoodStatusCode
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts_inspected_good_status_code
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.25

Field Name : portStatsTotalRevPktsInspected
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts_inspected
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.24

Field Name : portStatsEsRespInvalidHttp
Field Type : CounterBasedGauge64
Field Status : current

Description : es_resp_invalid_http
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.23

Field Name : portStatsEsRespCount
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_count
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.22

Field Name : portStatsEsReqCount
Field Type : CounterBasedGauge64
Field Status : current
Description : es_req_count
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.21

Field Name : portStatsEsRespOther
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_other
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.20

Field Name : portStatsEsResp500
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_500
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.19

Field Name : portStatsEsResp400
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_400
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.18

Field Name : portStatsEsResp300
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_300
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.17

Field Name : portStatsEsResp200
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_200
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.16

Field Name : portStatsPeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : peak_conn
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.15

Field Name : portStatsLastTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : last_total_conn
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.14

Field Name : portStatsTotalConn

Field Type : CounterBasedGauge64
Field Status : current
Description : total_conn
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.13

Field Name : portStatsTotalRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.12

Field Name : portStatsTotalRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.11

Field Name : portStatsTotalFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : total_fwd_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.10

Field Name : portStatsTotalFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total_fwd_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.9

Field Name : portStatsTotalReqSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : total_req_succ
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.8

Field Name : portStatsTotalReq
Field Type : CounterBasedGauge64
Field Status : current
Description : total_req
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.7

Field Name : portStatsCurrReq
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_req
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.6

Field Name : portStatsCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_conn
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.5

Field Name : portStatsProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.4

Field Name : portStatsPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.3

Field Name : portStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.2

Field Name : portStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.1

Field Name : portOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.2.1

Field Name : portOperAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : alloc_failed
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.2.1.13

Field Name : portOperPortsFreedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_freed_total
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.2.1.12

Field Name : portOperPortsConsumedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed_total
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.2.1.11

Field Name : portOperPortsConsumed
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.2.1.10

Field Name : portOperHaGroupId
Field Type : CounterBasedGauge64
Field Status : current
Description : ha_group_id
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.2.1.9

Field Name : portOperVrid
Field Type : CounterBasedGauge64
Field Status : current

Description : vrid
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.2.1.8

Field Name : portOperIpv6
Field Type : String
Field Status : current
Description : ipv6
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.2.1.7

Field Name : portOperIp
Field Type : String
Field Status : current
Description : ip
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.2.1.6

Field Name : portOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.2.1.5

Field Name : portOperProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.2.1.4

Field Name : portOperPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.2.1.3

Field Name : portOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.2.1.2

Field Name : portOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.2.1.1

Field Name : loggingStatsTable
Field Type : TABLE
Field Status : current
Description : logging configurations e.g. FW logging template Binding/CEF log options
from object 'fw.logging'
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1

Field Name : loggingStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The loggingStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1

Field Name : loggingStatsSessionLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : session-limit-exceeded
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.44

Field Name : loggingStatsIddosBlackholeEntryDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : iddos-blackhole-entry-delete
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.43

Field Name : loggingStatsIddosBlackholeEntryCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : iddos-blackhole-entry-create
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.42

Field Name : loggingStatsTcpLoggingPortAllocationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-logging-port-allocation-failed
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.41

Field Name : loggingStatsTcpLoggingPortFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-logging-port-freed
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.40

Field Name : loggingStatsTcpLoggingPortAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-logging-port-allocated
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.39

Field Name : loggingStatsLogTypeSctpInnerProtoFilter
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_sctp_inner_proto_filter
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.38

Field Name : loggingStatsSctpSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-session-deleted
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.37

Field Name : loggingStatsSctpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-session-created
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.36

Field Name : loggingStatsHttpAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : http-alloc-failed

OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.35

Field Name : loggingStatsHttpOutOfOrderDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : http-out-of-order-dropped
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.34

Field Name : loggingStatsLogMessageTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : log-message-too-long
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.33

Field Name : loggingStatsTcpLoggingConnDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-logging-conn-dropped
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.32

Field Name : loggingStatsTcpLoggingConnCreateFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-logging-conn-create-failed
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.31

Field Name : loggingStatsTcpLoggingConnEstablished
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-logging-conn-established
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.30

Field Name : loggingStatsAddMsgFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : add-msg-failed
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.29

Field Name : loggingStatsOutOfBuffers
Field Type : CounterBasedGauge64
Field Status : current
Description : out-of-buffers
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.28

Field Name : loggingStatsIpv6FragFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-frag-failed
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.27

Field Name : loggingStatsIpv6FragApplied
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-frag-applied
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.26

Field Name : loggingStatsIpv4FragFailed
Field Type : CounterBasedGauge64

Field Status : current
Description : ipv4-frag-failed
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.25

Field Name : loggingStatsIpv4FragApplied
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-frag-applied
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.24

Field Name : loggingStatsTemplateError
Field Type : CounterBasedGauge64
Field Status : current
Description : template_error
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.23

Field Name : loggingStatsAlgOverridePermit
Field Type : CounterBasedGauge64
Field Status : current
Description : alg_override_permit
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.22

Field Name : loggingStatsDcmsgPermit
Field Type : CounterBasedGauge64
Field Status : current
Description : dcmsg_permit
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.21

Field Name : loggingStatsHttpLoggingInvalidFormat
Field Type : CounterBasedGauge64
Field Status : current
Description : http-logging-invalid-format
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.20

Field Name : loggingStatsHttpRequestLogged
Field Type : CounterBasedGauge64
Field Status : current
Description : http-request-logged
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.19

Field Name : loggingStatsOtherSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : other-session-created
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.18

Field Name : loggingStatsOtherSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : other-session-deleted
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.17

Field Name : loggingStatsIcmpv6SessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : icmpv6-session-created
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.16

Field Name : loggingStatsIcmpv6SessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : icmpv6-session-deleted
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.15

Field Name : loggingStatsIcmpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-session-created
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.14

Field Name : loggingStatsIcmpSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-session-deleted
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.13

Field Name : loggingStatsUdpSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : udp-session-deleted
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.12

Field Name : loggingStatsUdpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : udp-session-created
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.11

Field Name : loggingStatsTcpSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-session-deleted
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.10

Field Name : loggingStatsTcpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-session-created
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.9

Field Name : loggingStatsLogDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : log-dropped
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.8

Field Name : loggingStatsRuleNotLogged
Field Type : CounterBasedGauge64
Field Status : current
Description : rule_not_logged
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.7

Field Name : loggingStatsLogTypeSessionOpened
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_session_opened

OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.6

Field Name : loggingStatsLogTypeSessionClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_session_closed
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.5

Field Name : loggingStatsLogTypeDeny
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_deny
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.4

Field Name : loggingStatsLogTypeReset
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_reset
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.3

Field Name : loggingStatsLogMessageSent
Field Type : CounterBasedGauge64
Field Status : current
Description : log_message_sent
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.2

Field Name : loggingStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.1

Field Name : gtpStatsTable
Field Type : TABLE
Field Status : current
Description : Counters for GTP Logging from object 'fw.logging.gtp'
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1

Field Name : gtpStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The gtpStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1

Field Name : gtpStatsLogTypeGtpInvalidPorts
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_invalid_ports
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.27

Field Name : gtpStatsLogTypeGtpInvalidVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_invalid_version
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.26

Field Name : gtpStatsLogTypeGtpHdrInvalidPiggyFlag
Field Type : CounterBasedGauge64

Field Status : current
Description : log_type_gtp_hdr_invalid_piggy_flag
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.25

Field Name : gtpStatsLogTypeGtpHdrInvalidSpareBits
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_hdr_invalid_spare_bits
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.24

Field Name : gtpStatsLogTypeGtpHdrInvalidProtocolFlag
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_hdr_invalid_protocol_flag
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.23

Field Name : gtpStatsLogTypeGtpInvalidMessageLength
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_invalid_message_length
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.22

Field Name : gtpStatsLogTypeGtpRateLimitPeriodic
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_rate_limit_periodic
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.21

Field Name : gtpStatsLogTypeGtpSeqNumMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_seq_num_mismatch
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.20

Field Name : gtpStatsLogTypeGtpNodeRestart
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_node_restart
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.19

Field Name : gtpStatsLogTypeGtpInGtpFiltering
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_in_gtp_filtering
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.18

Field Name : gtpStatsLogTypeCountryCodeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_country_code_mismatch
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.17

Field Name : gtpStatsLogTypeGtpRatTypeFiltering
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_rat_type_filtering
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.16

Field Name : gtpStatsLogTypeGtpApnFiltering
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_apn_filtering
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.15

Field Name : gtpStatsLogTypeGtpMessageFiltering
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_message_filtering
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.14

Field Name : gtpStatsLogTypeMaxMsgLength
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_max_msg_length
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.13

Field Name : gtpStatsLogTypeOutOfState
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_out_of_state
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.12

Field Name : gtpStatsLogTypeMessageNotSupported
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_message_not_supported
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.11

Field Name : gtpStatsLogTypeCrosslayerCorrelation
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_crosslayer_correlation
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.10

Field Name : gtpStatsLogTypeEnduserIpSpoofed
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_enduser_ip_spoofed
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.9

Field Name : gtpStatsLogTypeGtpOutOfStateIe
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_out_of_state_ie
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.8

Field Name : gtpStatsLogTypeGtpOutOfOrderIe
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_out_of_order_ie
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.7

Field Name : gtpStatsLogTypeGtpMsisdnFiltering
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_msisdn_filtering

OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.6

Field Name : gtpStatsLogTypeGtpMandatoryIeInsideGroupedIeMissing
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_mandatory_ie_inside_grouped_ie_missing
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.5

Field Name : gtpStatsLogTypeGtpMandatoryIeMissing
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_mandatory_ie_missing
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.4

Field Name : gtpStatsLogGtpTypeReservedIePresent
Field Type : CounterBasedGauge64
Field Status : current
Description : log_gtp_type_reserved_ie_present
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.3

Field Name : gtpStatsLogTypeGtpInvalidTeid
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_invalid_teid
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.2

Field Name : gtpStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.1

Field Name : rateLimitOperRateLimitListTable
Field Type : TABLE
Field Status : current
Description : View Rate Limit Entries from object 'fw.rate-limit'
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3

Field Name : rateLimitOperRateLimitListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The rateLimitOperRateLimitList entry:rate-limit-list
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1

Field Name : rateLimitOperRateLimitListDropCount
Field Type : CounterBasedGauge64
Field Status : current
Description : drop-count
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.16

Field Name : rateLimitOperRateLimitListTotalTrafficAllowed
Field Type : CounterBasedGauge64
Field Status : current
Description : total-traffic-allowed
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.15

Field Name : rateLimitOperRateLimitListTotalTrafficReceived
Field Type : CounterBasedGauge64

Field Status : current
Description : total-traffic-received
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.14

Field Name : rateLimitOperRateLimitListDownlinkTrafficAllowed
Field Type : CounterBasedGauge64
Field Status : current
Description : downlink-traffic-allowed
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.13

Field Name : rateLimitOperRateLimitListDownlinkTrafficReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : downlink-traffic-received
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.12

Field Name : rateLimitOperRateLimitListUplinkTrafficAllowed
Field Type : CounterBasedGauge64
Field Status : current
Description : uplink-traffic-allowed
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.11

Field Name : rateLimitOperRateLimitListUplinkTrafficReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : uplink-traffic-received
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.10

Field Name : rateLimitOperRateLimitListCpsAllowed
Field Type : CounterBasedGauge64
Field Status : current
Description : cps-allowed
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.9

Field Name : rateLimitOperRateLimitListCpsReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : cps-received
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.8

Field Name : rateLimitOperRateLimitListType
Field Type : String
Field Status : current
Description : type
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.7

Field Name : rateLimitOperRateLimitListTemplateId
Field Type : CounterBasedGauge64
Field Status : current
Description : template-id
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.6

Field Name : rateLimitOperRateLimitListRuleName
Field Type : String
Field Status : current
Description : rule-name
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.5

Field Name : rateLimitOperRateLimitListPrefixLen
Field Type : CounterBasedGauge64
Field Status : current
Description : prefix-len
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.4

Field Name : rateLimitOperRateLimitListAddress
Field Type : String
Field Status : current
Description : address
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.3

Field Name : rateLimitOperRateLimitListStringValue
Field Type : String
Field Status : current
Description : string-value
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.17

Field Name : rateLimitOperRateLimitListRateLimitListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.2

Field Name : rateLimitOperRateLimitListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.1

Field Name : rateLimitOperTable
Field Type : TABLE
Field Status : current
Description : View Rate Limit Entries from object 'fw.rate-limit'
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.2

Field Name : rateLimitOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The rateLimitOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.2.1

Field Name : rateLimitOperTemplateId
Field Type : CounterBasedGauge64
Field Status : current
Description : template-id
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.2.1.5

Field Name : rateLimitOperStringValue
Field Type : String
Field Status : current
Description : string-value
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.2.1.6

Field Name : rateLimitOperV6Prefix
Field Type : String
Field Status : current
Description : v6-prefix

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.2.1.4

Field Name : rateLimitOperV4Netmask
Field Type : String
Field Status : current
Description : v4-netmask
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.2.1.3

Field Name : rateLimitOperV4Address
Field Type : String
Field Status : current
Description : v4-address
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.2.1.2

Field Name : rateLimitOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.2.1.1

Field Name : rateLimitStatsTable
Field Type : TABLE
Field Status : current
Description : View Rate Limit Entries from object 'fw.rate-limit'
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1

Field Name : rateLimitStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The rateLimitStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1

Field Name : rateLimitStatsRatelimitEntryCountParentRadiusUserid
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_entry_count_parent_radius_userid
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.29

Field Name : rateLimitStatsRatelimitEntryCountRadiusUserid
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_entry_count_radius_userid
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.28

Field Name : rateLimitStatsRatelimitEntryCountParentRadiusUsergroup
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_entry_count_parent_radius_usergroup
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.27

Field Name : rateLimitStatsRatelimitEntryCountRadiusUsergroup
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_entry_count_radius_usergroup
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.26

Field Name : rateLimitStatsRatelimitEntryCountParentIp
Field Type : CounterBasedGauge64

Field Status : current
Description : ratelimit_entry_count_parent_ip
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.25

Field Name : rateLimitStatsRatelimitEntryCountRuleIp
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_entry_count_rule_ip
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.24

Field Name : rateLimitStatsRatelimitEntryCountFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_entry_count_freed
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.23

Field Name : rateLimitStatsRatelimitEntryCountAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_entry_count_allocated
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.22

Field Name : rateLimitStatsRatelimitInfraGenericErrors
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_infra_generic_errors
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.21

Field Name : rateLimitStatsRatelimitEntryCountParentIpv6Prefix
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_entry_count_parent_ipv6_prefix
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.20

Field Name : rateLimitStatsRatelimitEntryCountParentIpv4Prefix
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_entry_count_parent_ipv4_prefix
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.19

Field Name : rateLimitStatsRatelimitEntryCountParentUid
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_entry_count_parent_uid
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.18

Field Name : rateLimitStatsRatelimitEntryCountRuleIpv6Prefix
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_entry_count_rule_ipv6_prefix
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.17

Field Name : rateLimitStatsRatelimitEntryCountRuleIpv4Prefix
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_entry_count_rule_ipv4_prefix
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.16

Field Name : rateLimitStatsRatelimitEntryCountSessionId
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_entry_count_session_id
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.15

Field Name : rateLimitStatsRatelimitEntryCountIp6Addr
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_entry_count_ip6_addr
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.14

Field Name : rateLimitStatsRatelimitEntryCountIpAddr
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_entry_count_ip_addr
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.13

Field Name : rateLimitStatsRatelimitEntryCountFwRuleUid
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_entry_count_fw_rule_uid
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.12

Field Name : rateLimitStatsRatelimitEntryCountT2Key
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_entry_count_t2_key
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.11

Field Name : rateLimitStatsRatelimitEntryAllocFailMetricCountGtSupported
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_entry_alloc_fail_metric_count_gt_supported
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.10

Field Name : rateLimitStatsRatelimitEntryAllocFailRateTooHigh
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_entry_alloc_fail_rate_too_high
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.9

Field Name : rateLimitStatsRatelimitHighPerfEntrySecondaryAllocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_high_perf_entry_secondary_alloc_fail
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.8

Field Name : rateLimitStatsRatelimitHighPerfEntryAllocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_high_perf_entry_alloc_fail
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.7

Field Name : rateLimitStatsRatelimitHighAccurateEntryAllocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_high_accurate_entry_alloc_fail

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.6

Field Name : rateLimitStatsRatelimitEntryAllocFrmSpmMem
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_entry_alloc_frm_spm_mem
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.5

Field Name : rateLimitStatsRatelimitUsedHeapMem
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_used_heap_mem
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.4

Field Name : rateLimitStatsRatelimitUsedSpmMem
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_used_spm_mem
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.3

Field Name : rateLimitStatsRatelimitUsedTotalMem
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_used_total_mem
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.2

Field Name : rateLimitStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.1

Field Name : summaryOperTable
Field Type : TABLE
Field Status : current
Description : View A Summary About Rate Limit Entries from object 'fw.rate-limit.summary'
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2

Field Name : summaryOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The summaryOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1

Field Name : summaryOperTotalEntriesScopeParentRadiusUserid
Field Type : CounterBasedGauge64
Field Status : current
Description : total_entries_scope_parent_radius_userid
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.17

Field Name : summaryOperTotalEntriesScopeParentRadiusUsergroup
Field Type : CounterBasedGauge64
Field Status : current
Description : total_entries_scope_parent_radius_usergroup
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.16

Field Name : summaryOperTotalEntriesScopeParentSubscriberPrefix
Field Type : CounterBasedGauge64

Field Status : current
Description : total_entries_scope_parent_subscriber-prefix
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.13

Field Name : summaryOperTotalEntriesScopeParentSubscriberIp
Field Type : CounterBasedGauge64
Field Status : current
Description : total_entries_scope_parent_subscriber_ip
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.12

Field Name : summaryOperTotalEntriesScopeParent
Field Type : CounterBasedGauge64
Field Status : current
Description : total_entries_scope_parent
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.11

Field Name : summaryOperTotalEntriesScopeRadiusUserid
Field Type : CounterBasedGauge64
Field Status : current
Description : total_entries_scope_radius_userid
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.15

Field Name : summaryOperTotalEntriesScopeRadiusUsergroup
Field Type : CounterBasedGauge64
Field Status : current
Description : total_entries_scope_radius_usergroup
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.14

Field Name : summaryOperTotalEntriesScopeSubscriberPrefix
Field Type : CounterBasedGauge64
Field Status : current
Description : total_entries_scope_subscriber_prefix
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.10

Field Name : summaryOperTotalEntriesScopeSubscriberIp
Field Type : CounterBasedGauge64
Field Status : current
Description : total_entries_scope_subscriber_ip
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.9

Field Name : summaryOperTotalEntriesScopeAggregate
Field Type : CounterBasedGauge64
Field Status : current
Description : total_entries_scope_aggregate
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.8

Field Name : summaryOperTotalNumEntriesFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : total_num_entries_freed
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.7

Field Name : summaryOperTotalNumEntriesAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : total_num_entries_allocated
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.6

Field Name : summaryOperTotalNumEntries
Field Type : CounterBasedGauge64
Field Status : current
Description : total_num_entries
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.5

Field Name : summaryOperAllocFailures
Field Type : CounterBasedGauge64
Field Status : current
Description : alloc_failures
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.4

Field Name : summaryOperMemUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : mem_used
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.3

Field Name : summaryOperMemReserved
Field Type : CounterBasedGauge64
Field Status : current
Description : mem_reserved
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.2

Field Name : summaryOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.1

Field Name : tcpWindowCheckStatsTable
Field Type : TABLE
Field Status : current
Description : Configure TCP window check from object 'fw.tcp-window-check'
OID : 1.3.6.1.4.1.22610.2.4.8.484.1.1

Field Name : tcpWindowCheckStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The tcpWindowCheckStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.484.1.1.1

Field Name : tcpWindowCheckStatsOutsideWindow
Field Type : CounterBasedGauge64
Field Status : current
Description : outside-window
OID : 1.3.6.1.4.1.22610.2.4.8.484.1.1.1.2

Field Name : tcpWindowCheckStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.484.1.1.1.1

Field Name : fullConeSessionOperSessionListTable
Field Type : TABLE
Field Status : current
Description : Full Cone Sessions from object 'fw.full-cone-session'

OID : 1.3.6.1.4.1.22610.2.4.8.485.1.3

Field Name : fullConeSessionOperTable
Field Type : TABLE
Field Status : current
Description : Full Cone Sessions from object 'fw.full-cone-session'
OID : 1.3.6.1.4.1.22610.2.4.8.485.1.2

Field Name : fullConeSessionOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The fullConeSessionOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.485.1.2.1

Field Name : fullConeSessionOperIpv6Addr
Field Type : String
Field Status : current
Description : ipv6-addr
OID : 1.3.6.1.4.1.22610.2.4.8.485.1.2.1.4

Field Name : fullConeSessionOperIpv4Addr
Field Type : String
Field Status : current
Description : ipv4-addr
OID : 1.3.6.1.4.1.22610.2.4.8.485.1.2.1.3

Field Name : fullConeSessionOperTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : total
OID : 1.3.6.1.4.1.22610.2.4.8.485.1.2.1.2

Field Name : fullConeSessionOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.485.1.2.1.1

Field Name : fullConeSessionOperSessionListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The fullConeSessionOperSessionList entry:session-list
OID : 1.3.6.1.4.1.22610.2.4.8.485.1.3.1

Field Name : fullConeSessionOperSessionListAge
Field Type : String
Field Status : current
Description : age
OID : 1.3.6.1.4.1.22610.2.4.8.485.1.3.1.9

Field Name : fullConeSessionOperSessionListCpu
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu
OID : 1.3.6.1.4.1.22610.2.4.8.485.1.3.1.8

Field Name : fullConeSessionOperSessionListInbound
Field Type : CounterBasedGauge64

Field Status : current
Description : inbound
OID : 1.3.6.1.4.1.22610.2.4.8.485.1.3.1.7

Field Name : fullConeSessionOperSessionListOutbound
Field Type : CounterBasedGauge64
Field Status : current
Description : outbound
OID : 1.3.6.1.4.1.22610.2.4.8.485.1.3.1.6

Field Name : fullConeSessionOperSessionListInsidePort
Field Type : CounterBasedGauge64
Field Status : current
Description : inside-port
OID : 1.3.6.1.4.1.22610.2.4.8.485.1.3.1.5

Field Name : fullConeSessionOperSessionListInsideAddress
Field Type : String
Field Status : current
Description : inside-address
OID : 1.3.6.1.4.1.22610.2.4.8.485.1.3.1.4

Field Name : fullConeSessionOperSessionListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.485.1.3.1.3

Field Name : fullConeSessionOperSessionListSessionListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.485.1.3.1.2

Field Name : fullConeSessionOperSessionListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.485.1.3.1.1

Field Name : systemStatusOperTable
Field Type : TABLE
Field Status : current
Description : Firewall system status from object 'fw.system-status'
OID : 1.3.6.1.4.1.22610.2.4.8.486.1.2

Field Name : systemStatusOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The systemStatusOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.486.1.2.1

Field Name : systemStatusOperRadiusEntriesFree
Field Type : CounterBasedGauge64
Field Status : current
Description : radius-entries-free
OID : 1.3.6.1.4.1.22610.2.4.8.486.1.2.1.7

Field Name : systemStatusOperRadiusEntriesUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : radius-entries-used
OID : 1.3.6.1.4.1.22610.2.4.8.486.1.2.1.6

Field Name : systemStatusOperSmpSessionsFree
Field Type : CounterBasedGauge64
Field Status : current
Description : smp-sessions-free
OID : 1.3.6.1.4.1.22610.2.4.8.486.1.2.1.5

Field Name : systemStatusOperSmpSessionsUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : smp-sessions-used
OID : 1.3.6.1.4.1.22610.2.4.8.486.1.2.1.4

Field Name : systemStatusOperDataSessionsFree
Field Type : CounterBasedGauge64
Field Status : current
Description : data-sessions-free
OID : 1.3.6.1.4.1.22610.2.4.8.486.1.2.1.3

Field Name : systemStatusOperDataSessionsUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : data-sessions-used
OID : 1.3.6.1.4.1.22610.2.4.8.486.1.2.1.2

Field Name : systemStatusOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.486.1.2.1.1

Field Name : statusOperTable
Field Type : TABLE
Field Status : current
Description : Firewall status from object 'fw.status'
OID : 1.3.6.1.4.1.22610.2.4.8.487.1.2

Field Name : statusOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The statusOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.487.1.2.1

Field Name : statusOperInternal
Field Type : Integer32
Field Status : current
Description : internal
OID : 1.3.6.1.4.1.22610.2.4.8.487.1.2.1.7

Field Name : statusOperMostRecentCompilationStatus
Field Type : String
Field Status : current
Description : most-recent-compilation-status

OID : 1.3.6.1.4.1.22610.2.4.8.487.1.2.1.6

Field Name : statusOperMostRecentCompilationAttempt
Field Type : String
Field Status : current
Description : most-recent-compilation-attempt
OID : 1.3.6.1.4.1.22610.2.4.8.487.1.2.1.5

Field Name : statusOperPreviousSuccessfulCompilationDuration
Field Type : String
Field Status : current
Description : previous-successful-compilation-duration
OID : 1.3.6.1.4.1.22610.2.4.8.487.1.2.1.4

Field Name : statusOperPreviousSuccessfulCompilationAttempt
Field Type : String
Field Status : current
Description : previous-successful-compilation-attempt
OID : 1.3.6.1.4.1.22610.2.4.8.487.1.2.1.3

Field Name : statusOperCurrentActiveRuleSet
Field Type : String
Field Status : current
Description : current-active-rule-set
OID : 1.3.6.1.4.1.22610.2.4.8.487.1.2.1.2

Field Name : statusOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.487.1.2.1.1

Field Name : resourceUsageOperTable
Field Type : TABLE
Field Status : current
Description : Firewall resource usage from object 'fw.resource-usage'
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2

Field Name : resourceUsageOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The resourceUsageOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1

Field Name : resourceUsageOperClausePerObjGrp
Field Type : Integer32
Field Status : current
Description : clause-per-obj-grp
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.28

Field Name : resourceUsageOperRadiusTableSize
Field Type : TABLE
Field Status : current
Description : radius-table-size
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.27

Field Name : resourceUsageOperHelperSessions
Field Type : Integer32

Field Status : current
Description : helper-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.26

Field Name : resourceUsageOperIpRange
Field Type : Integer32
Field Status : current
Description : ip-range
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.25

Field Name : resourceUsageOperZone
Field Type : Integer32
Field Status : current
Description : zone
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.24

Field Name : resourceUsageOperRule
Field Type : Integer32
Field Status : current
Description : rule
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.23

Field Name : resourceUsageOperRuleSet
Field Type : Integer32
Field Status : current
Description : rule-set
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.22

Field Name : resourceUsageOperObjectGroup
Field Type : Integer32
Field Status : current
Description : object-group
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.21

Field Name : resourceUsageOperObject
Field Type : Integer32
Field Status : current
Description : object
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.20

Field Name : resourceUsageOperClausePerObjGrpTotalCount
Field Type : CounterBasedGauge64
Field Status : current
Description : clause-per-obj-grp-total-count
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.19

Field Name : resourceUsageOperClausePerObjGrpCurrentCount
Field Type : String
Field Status : current
Description : clause-per-obj-grp-current-count
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.18

Field Name : resourceUsageOperRadiusTableTotalCount
Field Type : TABLE
Field Status : current
Description : radius-table-total-count
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.17

Field Name : resourceUsageOperRadiusTableCurrentCount
Field Type : TABLE
Field Status : current
Description : radius-table-current-count
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.16

Field Name : resourceUsageOperFwHelperSessionsTotalCount
Field Type : CounterBasedGauge64
Field Status : current
Description : fw-helper-sessions-total-count
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.15

Field Name : resourceUsageOperFwHelperSessionsCurrentCount
Field Type : CounterBasedGauge64
Field Status : current
Description : fw-helper-sessions-current-count
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.14

Field Name : resourceUsageOperFwIpRangeTotalCount
Field Type : CounterBasedGauge64
Field Status : current
Description : fw-ip-range-total-count
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.13

Field Name : resourceUsageOperFwIpRangeCurrentCount
Field Type : CounterBasedGauge64
Field Status : current
Description : fw-ip-range-current-count
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.12

Field Name : resourceUsageOperFwZoneTotalCount
Field Type : CounterBasedGauge64
Field Status : current
Description : fw-zone-total-count
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.11

Field Name : resourceUsageOperFwZoneCurrentCount
Field Type : CounterBasedGauge64
Field Status : current
Description : fw-zone-current-count
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.10

Field Name : resourceUsageOperFwRuleTotalCount
Field Type : CounterBasedGauge64
Field Status : current
Description : fw-rule-total-count
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.9

Field Name : resourceUsageOperFwRuleCurrentCount
Field Type : CounterBasedGauge64
Field Status : current
Description : fw-rule-current-count
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.8

Field Name : resourceUsageOperFwRuleSetTotalCount
Field Type : CounterBasedGauge64
Field Status : current
Description : fw-rule-set-total-count

OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.7

Field Name : resourceUsageOperFwRuleSetCurrentCount
Field Type : CounterBasedGauge64
Field Status : current
Description : fw-rule-set-current-count
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.6

Field Name : resourceUsageOperFwObjectGroupTotalCount
Field Type : CounterBasedGauge64
Field Status : current
Description : fw-object-group-total-count
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.5

Field Name : resourceUsageOperFwObjectGroupCurrentCount
Field Type : CounterBasedGauge64
Field Status : current
Description : fw-object-group-current-count
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.4

Field Name : resourceUsageOperFwObjectTotalCount
Field Type : CounterBasedGauge64
Field Status : current
Description : fw-object-total-count
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.3

Field Name : resourceUsageOperFwObjectCurrentCount
Field Type : CounterBasedGauge64
Field Status : current
Description : fw-object-current-count
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.2

Field Name : resourceUsageOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.1

Field Name : ddosProtectionOperEntriesListTable
Field Type : TABLE
Field Status : current
Description : Configure FW DDoS Protection from object 'fw.ddos-protection'
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.3

Field Name : ddosProtectionOperTable
Field Type : TABLE
Field Status : current
Description : Configure FW DDoS Protection from object 'fw.ddos-protection'
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.2

Field Name : ddosProtectionOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The ddosProtectionOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.2.1

Field Name : ddosProtectionOperV6Prefix
Field Type : String

Field Status : current
Description : v6-prefix
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.2.1.5

Field Name : ddosProtectionOperV4Netmask
Field Type : String
Field Status : current
Description : v4-netmask
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.2.1.4

Field Name : ddosProtectionOperV4Address
Field Type : String
Field Status : current
Description : v4-address
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.2.1.3

Field Name : ddosProtectionOperDetails
Field Type : Integer32
Field Status : current
Description : details
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.2.1.2

Field Name : ddosProtectionOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.2.1.1

Field Name : ddosProtectionStatsTable
Field Type : TABLE
Field Status : current
Description : Configure FW DDoS Protection from object 'fw.ddos-protection'
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.1

Field Name : ddosProtectionStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The ddosProtectionStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.1.1

Field Name : ddosProtectionStatsDdosPacketDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : ddos_packet_dropped
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.1.1.9

Field Name : ddosProtectionStatsDdosEntryRemoveFromBgpFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : ddos_entry_remove_from_bgp_failure
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.1.1.8

Field Name : ddosProtectionStatsDdosEntryAddToBgpFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : ddos_entry_add_to_bgp_failure
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.1.1.7

Field Name : ddosProtectionStatsDdosEntryRemovedFromBgp
Field Type : CounterBasedGauge64
Field Status : current
Description : ddos_entry_removed_from_bgp
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.1.1.6

Field Name : ddosProtectionStatsDdosEntryAddedToBgp
Field Type : CounterBasedGauge64
Field Status : current
Description : ddos_entry_added_to_bgp
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.1.1.5

Field Name : ddosProtectionStatsDdosEntryRemoved
Field Type : CounterBasedGauge64
Field Status : current
Description : ddos_entry_removed
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.1.1.4

Field Name : ddosProtectionStatsDdosEntryAdded
Field Type : CounterBasedGauge64
Field Status : current
Description : ddos_entry_added
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.1.1.3

Field Name : ddosProtectionStatsDdosEntriesTooMany
Field Type : CounterBasedGauge64
Field Status : current
Description : ddos_entries_too_many
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.1.1.2

Field Name : ddosProtectionStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.1.1.1

Field Name : ddosProtectionOperEntriesListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The ddosProtectionOperEntriesList entry:entries-list
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.3.1

Field Name : ddosProtectionOperEntriesListRate
Field Type : CounterBasedGauge64
Field Status : current
Description : rate
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.3.1.11

Field Name : ddosProtectionOperEntriesListLid
Field Type : CounterBasedGauge64
Field Status : current
Description : lid
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.3.1.10

Field Name : ddosProtectionOperEntriesListHash
Field Type : CounterBasedGauge64
Field Status : current
Description : hash

OID : 1.3.6.1.4.1.22610.2.4.8.491.1.3.1.9

Field Name : ddosProtectionOperEntriesListHints
Field Type : String
Field Status : current
Description : hints
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.3.1.8

Field Name : ddosProtectionOperEntriesListExpiration
Field Type : CounterBasedGauge64
Field Status : current
Description : expiration
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.3.1.7

Field Name : ddosProtectionOperEntriesListPps
Field Type : CounterBasedGauge64
Field Status : current
Description : pps
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.3.1.6

Field Name : ddosProtectionOperEntriesListRuleName
Field Type : String
Field Status : current
Description : rule-name
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.3.1.5

Field Name : ddosProtectionOperEntriesListPrefix
Field Type : CounterBasedGauge64
Field Status : current
Description : prefix
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.3.1.4

Field Name : ddosProtectionOperEntriesListIp
Field Type : String
Field Status : current
Description : ip
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.3.1.3

Field Name : ddosProtectionOperEntriesListEntriesListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.3.1.2

Field Name : ddosProtectionOperEntriesListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.3.1.1

Field Name : globalStatsTable
Field Type : TABLE
Field Status : current
Description : SCTP Statistics from object 'sctp.global'
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1

Field Name : globalStatsEntry
Field Type : CounterBasedGauge64

Field Status : current
Description : The globalStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1

Field Name : globalStatsPktAsconfParamLenErrDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : pkt-asconf-param-len-err-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.67

Field Name : globalStatsPktChunkLenErrDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : pkt-chunk-len-err-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.66

Field Name : globalStatsPktLenErrDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : pkt-len-err-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.65

Field Name : globalStatsSctpInitVtagZeroDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-init-vtag-zero-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.64

Field Name : globalStatsSctpAsconfProcessDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-asconf-process-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.63

Field Name : globalStatsSctpRetxInit
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-retx-init
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.62

Field Name : globalStatsSctpRetxInitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-retx-init-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.61

Field Name : globalStatsSctpRetxInitAck
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-retx-init-ack
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.60

Field Name : globalStatsSctpNoExtMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-no-ext-match
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.59

Field Name : globalStatsSctpRouteErrDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-route-err-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.58

Field Name : globalStatsSctpRerouteFailover
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-reroute-failover
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.57

Field Name : globalStatsSctpRouteErrHeartbeatDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-route-err-heartbeat-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.56

Field Name : globalStatsSctpRetxInitAckDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-retx-init-ack-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.55

Field Name : globalStatsSctpChunkHeartBeatClubbed
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-heart-beat-clubbed
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.54

Field Name : globalStatsSctpChunkTypeAbortDataDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-abort-data-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.53

Field Name : globalStatsSctpChunkTypeShutdownCompleteDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-shutdown-complete-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.52

Field Name : globalStatsSctpChunkTypeInitAckDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-init-ack-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.51

Field Name : globalStatsSctpChunkTypeInitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-init-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.50

Field Name : globalStatsSctpDataNoExtMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-data-no-ext-match

OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.49

Field Name : globalStatsSctpDataNoTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-data-no-tuple
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.48

Field Name : globalStatsSctpHeartbeatNoTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-heartbeat-no-tuple
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.47

Field Name : globalStatsSctpChunkTypeOther
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-other
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.46

Field Name : globalStatsSctpChunkTypeHeartbeatAck
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-heartbeat-ack
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.45

Field Name : globalStatsSctpChunkTypeHeartbeat
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-heartbeat
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.44

Field Name : globalStatsSctpChunkTypeErrorOp
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-error-op
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.43

Field Name : globalStatsSctpChunkTypeShutdownComplete
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-shutdown-complete
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.42

Field Name : globalStatsSctpChunkTypeShutdownAck
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-shutdown-ack
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.41

Field Name : globalStatsSctpChunkTypeShutdown
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-shutdown
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.40

Field Name : globalStatsSctpChunkTypeAbort
Field Type : CounterBasedGauge64

Field Status : current
Description : sctp-chunk-type-abort
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.39

Field Name : globalStatsSctpChunkTypeData
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-data
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.38

Field Name : globalStatsSctpChunkTypeAsconfAck
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-asconf-ack
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.37

Field Name : globalStatsSctpChunkTypeAsconf
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-asconf
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.36

Field Name : globalStatsSctpChunkTypeSack
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-sack
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.35

Field Name : globalStatsSctpChunkTypeCookieAck
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-cookie-ack
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.34

Field Name : globalStatsSctpChunkTypeCookieEcho
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-cookie-echo
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.33

Field Name : globalStatsSctpChunkTypeInitAck
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-init-ack
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.32

Field Name : globalStatsSctpChunkTypeInit
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-init
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.31

Field Name : globalStatsBadAlignmentDropShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : bad-alignment-drop-shadow
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.30

Field Name : globalStatsBadPayloadDropShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : bad-payload-drop-shadow
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.29

Field Name : globalStatsBadCsumShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : bad-csum-shadow
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.28

Field Name : globalStatsConnExtSizeMax
Field Type : CounterBasedGauge64
Field Status : current
Description : conn_ext_size_max
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.27

Field Name : globalStatsSctpOutOfSystemMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-out-of-system-memory
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.26

Field Name : globalStatsSbyStaticNatCfgNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : sby-static-nat-cfg-not-found
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.25

Field Name : globalStatsSbySessionUpdateFail
Field Type : CounterBasedGauge64
Field Status : current
Description : sby-session-update-fail
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.24

Field Name : globalStatsSbySessionUpdated
Field Type : CounterBasedGauge64
Field Status : current
Description : sby-session-updated
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.23

Field Name : globalStatsSbySessionCreateFail
Field Type : CounterBasedGauge64
Field Status : current
Description : sby-session-create-fail
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.22

Field Name : globalStatsSbySessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : sby-session-created
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.21

Field Name : globalStatsRateLimitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : rate-limit-drop

OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.20

Field Name : globalStatsDisallowedPktDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : disallowed-pkt-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.19

Field Name : globalStatsDisallowedChunkFiltered
Field Type : CounterBasedGauge64
Field Status : current
Description : disallowed-chunk-filtered
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.18

Field Name : globalStatsInvalidFragChunkDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid-frag-chunk-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.17

Field Name : globalStatsVrrpStandbyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : vrrp-standby-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.16

Field Name : globalStatsCfgErrDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : cfg-err-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.15

Field Name : globalStatsStaticNatCfgNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : static-nat-cfg-not-found
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.14

Field Name : globalStatsMultiHomeAddrNotFoundDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : multi-home-addr-not-found-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.13

Field Name : globalStatsMultiHomeRemoveIpSkip
Field Type : CounterBasedGauge64
Field Status : current
Description : multi-home-remove-ip-skip
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.12

Field Name : globalStatsMaxMultiHomeDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : max-multi-home-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.11

Field Name : globalStatsOosPktDrop
Field Type : CounterBasedGauge64

Field Status : current
Description : oos-pkt-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.10

Field Name : globalStatsBadAlignmentDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : bad-alignment-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.9

Field Name : globalStatsBadPayloadDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : bad-payload-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.8

Field Name : globalStatsBadCsum
Field Type : CounterBasedGauge64
Field Status : current
Description : bad-csum
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.7

Field Name : globalStatsPktErrDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : pkt-err-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.6

Field Name : globalStatsSctpFwSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-fw-session-deleted
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.5

Field Name : globalStatsSctpFwSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-fw-session-created
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.4

Field Name : globalStatsSctpStaticNatSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-static-nat-session-deleted
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.3

Field Name : globalStatsSctpStaticNatSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-static-nat-session-created
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.2

Field Name : globalStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.1

Field Name : statStatsTable
Field Type : TABLE
Field Status : current
Description : Show aVCS vBlade box statistics information from object 'vcs-vblades.stat'
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1

Field Name : statStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The statStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1

Field Name : statStatsSlaveCfgUpdResultErr
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_cfg_upd_result_err
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1.16

Field Name : statStatsSlaveCfgUpdNotifErr
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_cfg_upd_notif_err
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1.15

Field Name : statStatsSlaveCfgUpdL2Fail
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_cfg_upd_l2_fail
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1.14

Field Name : statStatsSlaveCfgUpdRFail
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_cfg_upd_r_fail
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1.13

Field Name : statStatsSlaveCfgUpdL1Fail
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_cfg_upd_l1_fail
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1.12

Field Name : statStatsSlaveCfgUpd
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_cfg_upd
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1.11

Field Name : statStatsSlaveKeepalive
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_keepalive
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1.10

Field Name : statStatsSlaveMsgInval
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_msg_inval

OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1.9

Field Name : statStatsSlaveNSent
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_n_sent
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1.8

Field Name : statStatsSlaveNRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_n_recv
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1.7

Field Name : statStatsSlaveSentBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_sent_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1.6

Field Name : statStatsSlaveRecvBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_recv_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1.5

Field Name : statStatsSlaveSendErr
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_send_err
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1.4

Field Name : statStatsSlaveRecvErr
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_recv_err
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1.3

Field Name : statStatsVbladeId
Field Type : Integer32
Field Status : current
Description : vblade-id
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1.2

Field Name : statStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1.1

Contact Us

©2025 A10 Networks, Inc. All rights reserved. A10 Networks, the A10 Networks logo, ACOS, A10 Thunder, Thunder TPS, A10 Harmony, SSLi and SSL Insight are trademarks or registered trademarks of A10 Networks, Inc. in the United States and other countries. All other trademarks are property of their respective owners. A10 Networks assumes no responsibility for any inaccuracies in this document. A10 Networks reserves the right to change, modify, transfer, or otherwise revise this publication without notice. For the full list of trademarks, visit: www.a10networks.com/company/legal/trademarks/.